Stellar Cyber 6.6.0s is now live! Discover all the updates in the release notes!

Configuring F5 BIG-IP Firewall Connectors

You can connect Stellar Cyber to firewalls so that you can quickly and easily implement firewall rules on those firewalls from within Stellar Cyber, while you are threat hunting. You can configure firewall actions or manually trigger a firewall action from the event display. For either action you must already have your firewall connected.

Connector Overview: F5 BIG-IP Firewall

Capabilities

- Collect: **No**
- Respond: **Yes**
- Native Alerts Mapped: **No**
- Runs on: **DP** or **Sensor**
- Interval: **N/A**

Collected Data

N/A

Domain

https://<Device IP Address>:<Device Port>

where <Device IP Address> and <Device Port> are variables from the configuration of this connector

Response Actions

Action	Required Fields
Block IP	`srcip` or `dstip`

Third Party Native Alert Integration Details

N/A

Required Credentials and Configurations

- User Name, Password, Device IP Address, Source Address List, Destination Address List, and Device Port

Adding an F5 BIG-IP Firewall Connector

To add a new F5 BIG-IP firewall connector:

1. Create firewall rules
2. Add the connector in Stellar Cyber
3. Test the connector

You can also send F5 BIG-IP telemetry data to a sensor using API calls.

Creating Firewall Rules

To trigger firewall actions you must have rules on your F5 BIG-IP firewall that you can trigger. We suggest two rules, one to block outgoing destinations and one to block incoming.

On your F5 BIG-IP firewall:


1. Create two address lists. You will use these when adding the connector in Stellar Cyber. When a firewall action is triggered, Stellar Cyber adds the IP address to one of these lists. For our examples, we used **dst_group** and **src_group**.
2. Create a deny policy to all destinations with the **src_group** as the source.
3. Create a deny policy with the **dst_group** as the destination and all sources.

The Block IP action adds an IP address to the corresponding address list. The Unblock IP action removes the IP address from the corresponding address list.


Adding the Connector in Stellar Cyber

To add a new F5 BIG-IP firewall connector in Stellar Cyber:

1. Log in to Stellar Cyber.
2. Click **System | INTEGRATIONS | Connectors**. The **Connector Overview** appears.




3. Click **Create** and select **Connector**.



The **General** tab of the **Add Connector** screen appears. The information on this tab cannot be changed after you add the connector.

4. Choose **Firewall** from the **Category** dropdown.
5. Choose **F5 BIG-IP Firewall** from the **Type** dropdown.




The asterisk (*) indicates a required field.

6. For this connector, the supported **Function** is **Respond**, which is enabled already.
7. Enter a **Name**.

Notes:

- This field does not accept multibyte characters.
- It is recommended that you follow a naming convention such as tenantname-connectortype.

8. Choose a **Tenant Name**. The Interflow records created by this connector include this tenant name.
9. Choose the device on which to run the connector.
10. Click **Next**. The **Configuration** tab appears.



The asterisk (*) indicates a required field.


11. Enter the **User Name** to log in to the firewall. This user must have access rights to modify a rule.
12. Enter the **Password** to log in to the firewall.

The password should not include non-ASCII special characters.

13. Enter the **Device IP Address**. This is the management IP address for the firewall.
14. Enter the **Source Address List** to which to add the IP address. This is the source address list you created that is used to include IP addresses that should be blocked as source.
15. Enter the **Destination Address List** to which to add the IP address. This is the destination address list you created that is used to include IP addresses that should be

blocked as destination.

16. Enter the **Device Port**. This is the API port.
17. Click **Next**. The final confirmation tab appears.



18. Click **Submit**.


The new firewall connector is immediately active.

Testing the Connector

When you add (or edit) a connector, we recommend that you run a test to validate the connectivity parameters you entered. The test validates authentication and connectivity.

For connectors running on a sensor, Stellar Cyber recommends that you allow 30-60 seconds for new or modified configuration details to be propagated to the sensor before performing a test.

1. Click **System | INTEGRATIONS | Connectors**. The **Connector Overview** appears.



2. Locate the connector by name that you added, or modified, or that you want to test.
3. Click **Test** at the right side of that row. The test runs immediately.

Note that you may run only one test at a time.

Stellar Cyber conducts a basic connectivity test for the connector and reports a success or failure result. A successful test indicates that you entered all of the connector information correctly.

To aid troubleshooting your connector, the dialog remains open until you explicitly close it by using the **X** button. If the test fails, you can select the button from the same row to review and correct issues.

The connector status is updated every five (5) minutes. A successful test clears the connector status, but if issues persist, the status reverts to failed after a minute.


Repeat the test as needed.

Display sample messages...


Success !



Failure with summary of issue:



Show More example detail:



If the test fails, the common HTTP status error codes are as follows:

HTTP Error Code	HTTP Standard Error Name	Explanation	Recommendation
400	Bad Request	This error occurs when there is an error in the connector configuration.	Did you configure the connector correctly?
401	Unauthorized	This error occurs when an authentication credential is invalid or when a user does not have sufficient privileges to access a specific API.	Did you enter your credentials correctly? Are your credentials expired? Are your credentials entitled or licensed for that specific resource?
403	Forbidden	This error occurs when the permission or scope is not correct in a valid credential.	Did you enter your credentials correctly? Do you have the required role or permissions for that credential?
404	Not Found	This error occurs when a URL path does not resolve to an entity.	Did you enter your API URL correctly?
429	Too Many Requests	This error occurs when the API server receives too much traffic or if a user's license or entitlement quota is exceeded.	The server or user license/quota will eventually recover. The connector will periodically retry the query. If this occurs unexpectedly or too often, work with your API provider to investigate the server limits, user licensing, or quotas.

For a full list of codes, refer to HTTP response status codes.

© 2026 Stellar Cyber . All rights reserved.