Stellar Cyber 6.6.0s is now live! Discover all the updates in the release notes!

Configuring Firewalla Managed Security Portal Connectors 6.5.0

This connector allows Stellar Cyber to ingest logs from the Firewalla Managed Security Portal and add the records to the data lake. It integrates with the Firewalla API to get device and network flow data from Firewalla firewalls.

Stellar Cyber connectors with the Collect function (collectors) may skip collecting some data when the ingestion volume is large, which potentially can lead to data loss. This can happen when the processing capacity of the collector is exceeded.

Connector Overview: Firewalla Managed Security Portal

Capabilities

- Collect: **Yes**
- Respond: **No**
- Native Alerts Mapped: **No**
- Runs on: **DP**
- Interval: **Configurable**

Collected Data

Content Type	Index	Locating Records
Device	Syslog	msg_class: `firewalla_msp_device`
Flow	Assets (for Device)	`firewalla_msp_flow` msg_origin.source: `firewalla_msp` msg_origin.vendor:

Content Type	Index	Locating Records

		`firewalla`
		
		msg_origin.category:
		`firewall`

Domain

<Base URL>

where <Base URL> is a variable from the configuration of this connector

Response Actions

N/A

Third Party Native Alert Integration Details

N/A

Required Credentials and Configurations

- Base URL, Access Token

Adding a Firewalla Managed Security Portal Connector

To add a Firewalla Managed Security Portal connector:

1. Obtain credentials
2. Add the connector in Stellar Cyber
3. Test the connector
4. Verify ingestion

Obtaining Firewalla Managed Security Portal Credentials


Before you configure the connector in Stellar Cyber, you must obtain the following Firewalla Managed Security Portal (MSP) credentials. Refer to the Firewalla documentation for Getting Started with the Firewalla MSP API.

- Base URL—The base URL for API access. The URL is a custom domain specific to your account and has the following format: https://<yourMSP>.firewalla.net
- Access Token—The credentials for authentication. Follow the guidance in the Firewalla documentation to Create your personal access token.
- (Optional) Box ID—The unique identifier of a Firewalla box, which is a physical device. Use a Box ID to limit the amount of data received to a specific box. Use the API to get a list of boxes.


Adding the Connector in Stellar Cyber

To add a Firewalla Managed Security Portal connector in Stellar Cyber:

1. Log in to Stellar Cyber.
2. Click **System | INTEGRATIONS | Connectors**. The **Connector Overview** appears.




3. Click **Create** and select **Connector**.



   The **General** tab of the **Add Connector** screen appears. The information on this tab cannot be changed after you add the connector.

4. Choose **Firewall** from the **Category** dropdown.
5. Choose **Firewalla Managed Security Portal** from the **Type** dropdown.




   The asterisk (*) indicates a required field.

6. For this connector, the supported **Function** is **Collect**, which is enabled already.
7. Enter a **Name**.

   Notes:
   - This field does not accept multibyte characters.
   - It is recommended that you follow a naming convention such as tenantname-connectortype.

8. Choose a **Tenant Name**. The Interflow records created by this connector include this tenant name.
9. Choose the device on which to run the connector.
10. (Optional) When the **Function** is **Collect**, you can apply **Log Filters**. For information, see Managing Log Filters.
11. Click **Next**. The **Configuration** tab appears.



The asterisk (*) indicates a required field.


12. Enter the **Base URL** you noted above in Obtaining Firewalla Managed Security Portal Credentials.
13. Enter the **Access Token** you noted above.
14. (Optional) Enter a specific **Box ID** you noted above.
15. Choose the **Interval (min)**. This is how often the logs are collected.

    The logs for **Device** are queried every 24 hours.

16. (Optional) Click **Disable SSL Certificate Verification** if you want to disable SSL certificate verification. Only disable SSL certificates if you have a necessary reason to, otherwise, it is not a good security practice and may expose the connection to security risks.
17. Choose the **Content Type** you would like to collect. The logs for **Device** and **Flow** are supported.

    The **Device** content type is always selected and cannot be removed from the configuration as it is required for host information.

18. Click **Next**. The final confirmation tab appears.



19. Click **Submit**.


The new connector is immediately active.

Testing the Connector

When you add (or edit) a connector, we recommend that you run a test to validate the connectivity parameters you entered. The test validates authentication and connectivity.

For connectors running on a sensor, Stellar Cyber recommends that you allow 30-60 seconds for new or modified configuration details to be propagated to the sensor before performing a test.

1. Click **System | INTEGRATIONS | Connectors**. The **Connector Overview** appears.



2. Locate the connector by name that you added, or modified, or that you want to test.
3. Click **Test** at the right side of that row. The test runs immediately.

Note that you may run only one test at a time.

Stellar Cyber conducts a basic connectivity test for the connector and reports a success or failure result. A successful test indicates that you entered all of the connector information correctly.

To aid troubleshooting your connector, the dialog remains open until you explicitly close it by using the **X** button. If the test fails, you can select the button from the same row to review and correct issues.

The connector status is updated every five (5) minutes. A successful test clears the connector status, but if issues persist, the status reverts to failed after a minute.


Repeat the test as needed.

Display sample messages...


Success !



Failure with summary of issue:



Show More example detail:



If the test fails, the common HTTP status error codes are as follows:

HTTP Error Code	HTTP Standard Error Name	Explanation	Recommendation
400	Bad Request	This error occurs when there is an error in the connector configuration.	Did you configure the connector correctly?
401	Unauthorized	This error occurs when an authentication credential is invalid or when a user does not have sufficient privileges to access a specific API.	Did you enter your credentials correctly? Are your credentials expired? Are your credentials entitled or licensed for that specific resource?

HTTP Error Code	HTTP Standard Error Name	Explanation	Recommendation
403	Forbidden	This error occurs when the permission or scope is not correct in a valid credential.	Did you enter your credentials correctly? Do you have the required role or permissions for that credential?
404	Not Found	This error occurs when a URL path does not resolve to an entity.	Did you enter your API URL correctly?
429	Too Many Requests	This error occurs when the API server receives too much traffic or if a user's license or entitlement quota is exceeded.	The server or user license/quota will eventually recover. The connector will periodically retry the query. If this occurs unexpectedly or too often, work with your API provider to investigate the server limits, user licensing, or quotas.

For a full list of codes, refer to HTTP response status codes.

Verifying Ingestion

To verify ingestion:

1. Select **Threat Hunting**.

   The **Interflow Search** tab appears.

2. Change the **Indices** for the type of content you collected:

   - For **Device** and **Flow**, change the **Indices** to **Syslog**.
   - For **Device** only, change the **Indices** to **Assets**.

   The table immediately updates to show ingested Interflow records.

© 2026 Stellar Cyber . All rights reserved.