Stellar Cyber 6.6.0s is now live! Discover all the updates in the release notes!

Configuring Verkada Connectors 6.1.0

This connector allows Stellar Cyber to ingest logs from Verkada and add the records to the data lake. It integrates with the Verkada API to query camera devices, access events, and audit logs.

Verkada provides a hybrid-cloud physical security platform integrating security cameras, access control, environmental sensors, alarms, and intercoms.

Stellar Cyber integrates Verkada's physical security and surveillance alerts, enabling users to gain insights from Verkada's camera and sensor data, enhancing overall threat detection and response capabilities.

Note the following rate limit: The Verkada API rate limit is 300 requests/minute across all endpoints per organization. If there are multiple connectors with different keys but under the same organization, this connector may reach the rate limit if data volume is high or there is spike.

Stellar Cyber connectors with the Collect function (collectors) may skip collecting some data when the ingestion volume is large, which potentially can lead to data loss. This can happen when the processing capacity of the collector is exceeded.

Connector Overview: Verkada

Capabilities

- Collect: **Yes**
- Respond: **No**
- Native Alerts Mapped: **No**
- Runs on: **DP**
- Interval: **Configurable**

Collected Data

Content Type	Index	Locating Records
Access Events Audit Logs Camera Devices	Syslog Assets (for Camera Devices)	msg_class: `verkada_access_events`

Content Type	Index	Locating Records

		`verkada_audit_logs`
		`verkada_camera_devices`
		
		msg_origin.source:
		`verkada`
		
		msg_origin.vendor:
		`verkada`
		
		msg_origin.category:
		`iotsec`

Domain

<Base URL>

where <Base URL> is a variable from the configuration of this connector

Response Actions

N/A

Third Party Native Alert Integration Details

N/A

Required Credentials and Configurations

- Base URL and API Key

Adding a Verkada Connector

To add Verkada connector:

1. Obtain credentials
2. Add the connector in Stellar Cyber
3. Test the connector
4. Verify ingestion

For a limitation on filtering APIs, see Filtering APIs on Verkada Connectors.

Obtaining Verkada Credentials

Before you configure the connector in Stellar Cyber, you must obtain the following Verkada credentials:


- Base URL—The base URL for API access. The default (for United States) is https://api.verkada.com/. Locate the Base URL for other regions at Service Regions.
- API Key—The authentication credential. There are Legacy API Keys and new API Keys. Legacy API Keys are valid until their expiry. To get new API Keys, follow the

guidance in the Verkada Quick Start Guide.


Adding the Connector in Stellar Cyber

To add a Verkada connector in Stellar Cyber:

1. Log in to Stellar Cyber.
2. Click **System | INTEGRATIONS | Connectors**. The **Connector Overview** appears.




3. Click **Create** and select **Connector**.



The **General** tab of the **Add Connector** screen appears. The information on this tab cannot be changed after you add the connector.

4. Choose **Internet of Things Security** from the **Category** dropdown.
5. Choose **Verkada** from the **Type** dropdown.



The asterisk (*) indicates a required field.


6. For this connector, the supported **Function** is **Collect**, which is enabled already.
7. Enter a **Name**.

Notes:

- This field does not accept multibyte characters.
- It is recommended that you follow a naming convention such as tenantname-connectortype.

8. Choose a **Tenant Name**. The Interflow records created by this connector include this tenant name.
9. Choose the device on which to run the connector.

10. (Optional) When the **Function** is **Collect**, you can apply **Log Filters**. For information, see Managing Log Filt
11. Click **Next**. The **Configuration** tab appears.




The asterisk (*) indicates a required field.

12. Select the **Base URL** you noted above in Obtaining Verkada Credentials.
13. Enter the **API Key** you noted above. The default is a Legacy API Key.
14. If the **API Key** is not a Legacy Key, remove the checkmark for **Legacy Key** and enter a new **API Key** above.
15. (Optional) Click **Disable SSL Certificate Verification** if you want to disable SSL certificate verification. Only disable SSL certificates if you have a necessary reason to, otherwise, it is not a good security practice and may expose the connection to security risks.
16. Choose the **Interval (min)**. This is how often the logs are collected.
17. Choose the **Content Type** you would like to collect. The logs for **Camera Devices**, **Access Events**, and **Audit Logs** are supported.

> The **Camera Devices** content type is always selected and cannot be removed from the configuration as it is required for host information.

> The **Camera Devices** data is deduplicated, but there still may be some duplicates.

18. Click **Next**. The final confirmation tab appears.



19. Click **Submit**.

The new connector is immediately active.


Testing the Connector

> In addition to testing for connectivity, the **Test** button for the Verkada connector tests that the Base URL and API Key are correct and data requests for the requested content types return successful responses.

When you add (or edit) a connector, we recommend that you run a test to validate the connectivity parameters you entered. The test validates authentication and connectivity.

For connectors running on a sensor, Stellar Cyber recommends that you allow 30-60 seconds for new or modified configuration details to be propagated to the sensor before performing a test.

1. Click **System | INTEGRATIONS | Connectors**. The **Connector Overview** appears.



2. Locate the connector by name that you added, or modified, or that you want to test.
3. Click **Test** at the right side of that row. The test runs immediately.

   Note that you may run only one test at a time.

Stellar Cyber conducts a basic connectivity test for the connector and reports a success or failure result. A successful test indicates that you entered all of the connector information correctly.

To aid troubleshooting your connector, the dialog remains open until you explicitly close it by using the **X** button. If the test fails, you can select the button from the same row to review and correct issues.

The connector status is updated every five (5) minutes. A successful test clears the connector status, but if issues persist, the status reverts to failed after a minute.


Repeat the test as needed.

Display sample messages...


Success !



Failure with summary of issue:



Show More example detail:



If the test fails, the common HTTP status error codes are as follows:

HTTP Error Code	HTTP Standard Error Name	Explanation	Recommendation
400	Bad Request	This error occurs when there is an error in the connector configuration.	Did you configure the connector correctly?
401	Unauthorized	This error occurs when an authentication credential is invalid or when a user does not have sufficient privileges to access a specific API.	Did you enter your credentials correctly? Are your credentials expired? Are your credentials entitled or licensed for that specific resource?
403	Forbidden	This error occurs when the permission or scope is not correct in a valid credential.	Did you enter your credentials correctly? Do you have the required role or permissions for that credential?
404	Not Found	This error occurs when a URL path does not resolve to an entity.	Did you enter your API URL correctly?
429	Too Many Requests	This error occurs when the API server receives too much traffic or if a user's license or entitlement quota is exceeded.	The server or user license/quota will eventually recover. The connector will periodically retry the query. If this occurs unexpectedly or too often, work with your API provider to investigate the server limits, user licensing, or quotas.

For a full list of codes, refer to HTTP response status codes.

Verifying Ingestion

To verify ingestion:

1. Select **Threat Hunting**.

   The **Interflow Search** tab appears.

2. Change the **Indices** for the type of content you collected:
   - For all content types, change the **Indices** to **Syslog**.
   - For **Camera Devices** only, change the **Indices** to **Assets**.

   The table immediately updates to show ingested Interflow records.

Filtering APIs on Verkada Connectors

Some vendor APIs integrated through Stellar Cyber connectors do not support time-bounded querying (for example, using start_time, end_time, or equivalent filters), and may lack time-series metadata on records. As a result, Stellar Cyber is required to pull the entire dataset during each polling cycle, regardless of whether the data has changed.

Potential Impact

- Performance Overhead: The absence of time-based filtering may lead to increased load on the Stellar Cyber ingestion pipeline and degrade collection performance over time.
- Inefficient Polling: The connector must fetch and process all available records each cycle, leading to longer collection durations and higher resource usage.
- Scalability Limitations: For large or growing datasets (for example, alerts, logs, or assets), this limitation may result in delayed data availability or collection timeouts.
- Data Inconsistency: Data may be duplicated or missed due to the quantity of data.

When working with connectors that have this limitation, consider the potential impact on performance and collection efficiency.

Recommendation

Where possible, we recommend working with your vendor to improve or add time range filtering capabilities to their APIs.

Verkada Connector Content Types

The Verkada connector content types impacted by this limitation are as follows:

- Access Events
- Audit Logs
- Camera Devices (assets)

The Camera Devices content type does not support time-bounded querying. This connector can only pull the entire dataset during each polling cycle, regardless of whether the data has changed. The connector will filter the retrieved data and only ingest data with dates within the query period.

© 2026 Stellar Cyber . All rights reserved.