

TECHNISCHE DATEN UND KONSTRUKTION DETAILS

IEC 61355

Vollständige Bezeichnung		Strukturbeschreibung
mounting-location		
+BSF		Grundrahmen
+ENG		Motor
+GEN		Generator inkl. Klemmenkasten
+MIP		Motor-Steuer-Schrank
+MMC		MTU Modul Steuerschrank
+GCB		Generator Leistungsschalter
+MCB		Netz Leistungsschalter
+FAN		Lüfter Steuerschrank
+TNK		Kraftstoff-Tank
+EXT		Nicht im Schaltschrank eingebaute Geräte und Gehäuse die nicht von MTU geliefert werden
+CUS		
+DOK		Dokumente
+TB1		Alternator terminal box

Vollständige Bezeichnung		Strukturbeschreibung
document-type		
&EAA		Deckblatt
&EAB		Inhaltsverzeichnis
&EDB		Beschreibung
&EFS		Schaltplan
&ETL		Layout
&EMA		Klemmenplan
&EMB		Kabelplan
&EPC		Materialstückliste

Vollständige Bezeichnung		Strukturbeschreibung
system		
=EKW		Elektrische Stromversorgung
=CON		Steuerspannung
=EES		Maschinen Not-Halt
=PLC		SPS oder Genset Controller
=COM		Kommunikation
=STR		Motor Start
=MCC		Gemisch Kühl-Kreis
=ECC		Motor/Kühlwasser System
=HWC		Heiz-Wasser-Kreis
=FUL		Kraftstoff Versorgung
=MSC		Sonstiges

TECHNICAL DATA AND CONSTRUCTION DETAILS

line and color definition for potential tracing	
Supply, Line and measure voltage	L1, L2, L3 (120V, 230V, 400V, 690V, ...)
Supply, Line and measure voltage	N (120V, 230V, 400V, 690V, ...)
Protective earth	Ground
Control voltage + 24VDC, 12VDC L+	L+
Control voltage - 0VDC L-	L-
Shield	SH
Starter battery cabling +24V	L+Batt
Starter battery cabling -24V	L-Batt

line and color definition for potential tracing	
Control voltage 24VAC	24VAC-L
Control voltage 24VAC	24VAC-N
External source voltage	ext
Analog signals	analog
Current transformer	L1-k-Geno
Emergency stop	NA
All other connections EPLAN standard	

TECHNICAL DATA AND CONSTRUCTION DETAILS

Wire colors within enclosure

According
IEC EN 60204-1

Rated voltage	Above 48VAC	black
Neutral wire	N	light blue
Protective earth	PE	green/yellow
Control voltage	24-240V AC	red
	0V AC	red/white
	24-110V DC	dark blue
	0V DC	grey
PLC-Controller		white
Measuring technique		grey
wires before Mainswitch		orange

Main power before main switch	L1 - L2 - L3
Main power main switch on	1L1 - 1L2 - 1L3
Neutral wire	N
Protective conductor	PE

Mains power supply	400VAC	-XD00
Power supply Heating GEN	230VAC	-XD01
Power supply heatg. cool. water	400VAC	-XD02
Emergency stop		-XD06
Supply DC	24VDC	-XDL+
Supply DC	0VDC	-XDL-
Harness W010-ECU7 / W011-ECU9 Digital		-1XD01
Harness W010-ECU7 / W011-ECU9 Analog		-1XD02
Harness W020 Engine		-2XD01
Harness W033 Generator signal		-3XD01 /-3XD02 / -3XD03
Option		
Customer interface WD04.1 / WG04.2 / WG04.3 / WD04.4		-4XD01 / -4XD02 / -4XD03 / -4XD04 / -4XD05
Harness W050 Power panel		-5XD01
Control cable WD06.1 Generator circuit breaker		-6XD01
Control cable WD07.1 Mains circuit breaker		-7XD01
Control cable WD08.1 Fan control enclosure		-8XD01
Control cable WD09.1/WD09.2 Fuel control		-9XD01/-9XD02
CAN bus		-XF01

Tightening torque

Power relay	75A	M3,5x5 M5x8	1,1-1,2 Nm 3,2-3,5 Nm
Starter	Prestolite 9KW	M5 M12	2,0-3,0 Nm 27-33 Nm
Starter	Prestolite 15KW	M5 M10	1,5-1,7 Nm 9-10 Nm
Starter	Delco 9KW	Housing 10-32 INCH 1/2-13 INCH	18-23 Nm 1,8-3,4 Nm 27-34 Nm
Battery disconnect switches		M10 M12	15-20 Nm 18-22 Nm
Battery terminals	DIN 72331	Cable M6 M8	5-6 Nm Class 4,6 / 3,5 Nm Class 4,6 / 8,4 Nm
Grounding		M8 M10 M12 M14	Class 8,8 / 28 Nm Class 8,8 / 54 Nm Class 8,8 / 93 Nm Class 8,8 / 148 Nm