Class Test: 2
Time: 30 minutes
ROLL NO:

BSF24 AFT
Instructor: Abdul Khaliq

Question 1: **[10]**

Consider the Data area of a Program given below (where the address of first Variable i.e V1V is 0012) How this data will be stored in the memory (fill the given area with suitable contents in hexadecimal form at given addresses)

```
V1V   DB    0ABh, 0CDh, 0EFh, 40h, 50h, 60h
V2V   DB    -32
V3V   DB    123D,1011B
V4V   DW    1234h, 0ABCDh
V5V   DD    45768923h, 1234ABCDh
V6V   DW    10 Dup(?)
V7V   DB    "AAAAA"
V8V   DW    V2V
```

(Note : ASCII code of character **A** is 41h)

0010	0011	0012	0013	0014	0015	0016	0017	0018	0019	001A	001B	001C	001D	001E	001F
		AB	CD	EF	40	50	60	E0	7B	0B	34	12	CD	AB	23
0020	0021	0022	0023	0024	0025	0026	0027	0028	0029	002A	002B	002C	002D	002E	002F
89	76	45	CD	AB	34	12	00	00	00	00	00	00	00	00	00
0030	0031	0032	0033	0034	0035	0036	0037	0038	0039	003A	003B	003C	003D	003E	003F
00	00	00	00	00	00	00	00	00	00	00	41	41	41	41	41
0040	0041	…	…	…	…	…	…	…	…	…	…	…	…	…	004F
18	00														

Question 2: **[10]**
Consider the same Data area of the Program (discussed earlier),Give the Values of the mentioned operand, after the execution of the given instructions

	INSTRUCTION	OUTPUT
1	MOV AX,V8V	0018
2	MOV BX,V4V +2	ABCD
3	MOV CX,WORD PTR V5V+2	4576
4	MOV DX,OFFSET V7V	003B
5	MOV AL,0AH	0A
6	MOV BL,[0017]	60
7	MOV CL , BYTE PTR V4V	34
8	MOV AH, Type V4V	02
9	MOV BH, LENGTH V6V	10
10	MOV CH, SIZE V6V	20

Question 3: **[5]**
As each of the instruction in the following program is executed, fill in the hexadecimal value of the operand listed on the right hand side:

```
.data
Var1 dw 1234h
Var2 dw  0abcdh

.code
:
        Mov ax,var1

        Xchg var2,ax        ; AX=abcd

        Dec ax

        Sub var2,2          ;VAR2= 1232

        Mov bx,var2

        Add ah,bl           ;AX=ddcc
:
:
```

****