```
enable
configure terminal
hostname Switch-Lyon-2
no ip domain-lookup
enable secret 123Soleil!

banner motd #
*-*-*-*-*-*-*-*-*-*-*-*-*-*-*(SWITCH-LYON-2)*-*-*-*-*-*-*-*-*-*-*-*-*-*-*
#

service password-encryption
line console 0
password 123Soleil!
login
exec-timeout 15 0
logging synchronous
exit

ip domain-name nordtech.local

crypto key generate rsa

## !--Attendre le choix de clé avant de continuer–! 2048




username admin privilege 15 secret 123Soleil!
line vty 0 4
login local
transport input ssh
exec-timeout 15 0
exit
ip ssh version 2


vlan 99
name Management
exit
interface Vlan99
ip address 10.20.99.5 255.255.255.0
no shutdown
exit
ip default-gateway 10.20.99.1


vlan 999
name Native_Unused
exit


vlan 50
```

```
name Commerc
exit
vlan 60
name Prod
exit
vlan 70
name Stagiaires


interface fa0/10
switchport mode access
switchport access vlan 60
switchport port-security
switchport port-security maximum 2
switchport port-security mac-address sticky
switchport port-security violation restrict
spanning-tree portfast
spanning-tree bpduguard enable
no shutdown
exit
interface fa0/11
switchport mode access
switchport access vlan 70
switchport port-security
switchport port-security maximum 2
switchport port-security mac-address sticky
switchport port-security violation restrict
spanning-tree portfast
spanning-tree bpduguard enable
no shutdown
exit

interface range fa0/1-9, fa0/12-24
switchport mode access
switchport access vlan 999
shutdown

interface range gigabitEthernet 0/1 - 2
ip dhcp snooping trust
ip dhcp snooping
ip dhcp snooping vlan 50,60

spanning-tree mode rapid-pvst
interface range gi0/1 - 2
switchport mode trunk
switchport trunk native vlan 999
switchport trunk allowed vlan 50,60,99,999
no shutdown
exit

ip access-list standard MGMT-ONLY
permit 10.20.99.0 0.0.0.255
exit

line vty 0 4
```

```
access-class MGMT-ONLY in
exit
line vty 5 15
login local
transport input ssh
access-class MGMT-ONLY in
exec-timeout 15 0
exit

end
wr
```