Configuration routeurs

Brest 1:

PARTIE 1

```
enable
configure terminal
license boot module c2900 technology-package securityk9
```

PARTIE 2

```
exit
```

PARTIE 3

```
copy running-config startup-config
```

PARTIE 4

```
reload
```

PARTIE 5

```
enable
conf t
hostname Routeur-Brest-1
no ip domain-lookup

enable secret 123Soleil!

banner motd #
—--------ROUTEUR-BREST-1—--------
#

service password-encryption

line console 0
 password 123Soleil!
 login
 exec-timeout 15 0
 logging synchronous
 exit

ip domain-name nordtech.local
crypto key generate rsa
```

PARTIE 6

```
username admin privilege 15 secret 123Soleil!
line vty 0 4
 login local
 transport input ssh
 exec-timeout 15 0
 exit

ip ssh version 2

interface g0/0
 description Vers-Nuage-WAN-Lien-Primaire
 ip address 100.64.0.1 255.255.255.252
 no shutdown
 exit

interface g0/1
 description Vers-Switch-Brest-3-Primaire
 ip address 10.10.253.1 255.255.255.252
 no shutdown
 exit

interface g0/2
 description Vers-Switch-Brest-4-Secours
 ip address 10.10.253.5 255.255.255.252
 no shutdown
 exit

ip route 10.10.0.0 255.255.0.0 10.10.253.2 10
ip route 10.10.0.0 255.255.0.0 10.10.253.6 20
ip route 10.20.0.0 255.255.0.0 100.64.0.2 10

crypto isakmp policy 10
 encryption aes 256
 hash sha
 authentication pre-share
 group 2
 lifetime 86400
 exit

crypto isakmp key NordTechBrest/Lyon1! address 100.64.0.2
crypto ipsec transform-set TS-VPN esp-aes 256 esp-sha-hmac
```

```
ip access-list extended VPN-TRAFFIC
 permit ip 10.10.0.0 0.0.255.255 10.20.0.0 0.0.255.255
 exit

crypto map CMAP-VPN 10 ipsec-isakmp
 set peer 100.64.0.2
 set transform-set TS-VPN
 match address VPN-TRAFFIC
 exit

interface g0/0
 description Vers-Nuage-WAN-Lien-Primaire
 ip address 100.64.0.1 255.255.255.252
 crypto map CMAP-VPN
 no shutdown
 exit

ip access-list standard MGMT-ONLY
 permit 10.10.99.0 0.0.0.255
 exit

line vty 0 4
 access-class MGMT-ONLY in
 exit
```

Brest 2:

PARTIE 1

```
enable
configure terminal
license boot module c2900 technology-package securityk9
```

PARTIE 2

```
exit
```

PARTIE 3

```
copy running-config startup-config
```

PARTIE 4

```
reload
```

PARTIE 5

```
enable
conf t
hostname Routeur-Brest-2
no ip domain-lookup

enable secret 123Soleil!

banner motd #
—--------ROUTEUR-BREST-2—--------
#

service password-encryption

line console 0
 password 123Soleil!
 login
 exec-timeout 15 0
 logging synchronous
 exit

ip domain-name nordtech.local
crypto key generate rsa
```

PARTIE 6

```
username admin privilege 15 secret 123Soleil!
line vty 0 4
 login local
 transport input ssh
 exec-timeout 15 0
 exit

ip ssh version 2

interface g0/0
 description Vers-Nuage-WAN-Lien-Secours
 ip address 100.64.0.5 255.255.255.252
 no shutdown
 exit

interface g0/1
 description Vers-Switch-Brest-4-Primaire
 ip address 10.10.253.9 255.255.255.252
 no shutdown
 exit

interface g0/2
 description Vers-Switch-Brest-3-Secours
 ip address 10.10.253.13 255.255.255.252
 no shutdown
 exit

ip route 10.10.0.0 255.255.0.0 10.10.253.10 10
ip route 10.10.0.0 255.255.0.0 10.10.253.14 20
ip route 10.20.0.0 255.255.0.0 100.64.0.6 10

crypto isakmp policy 10
 encryption aes 256
 hash sha
 authentication pre-share
 group 2
 lifetime 86400
 exit

crypto isakmp key NordTechBrest/Lyon2! address 100.64.0.6
crypto ipsec transform-set TS-VPN esp-aes 256 esp-sha-hmac

ip access-list extended VPN-TRAFFIC
 permit ip 10.10.0.0 0.0.255.255 10.20.0.0 0.0.255.255
 exit
```

```
crypto map CMAP-VPN 10 ipsec-isakmp
 set peer 100.64.0.6
 set transform-set TS-VPN
 match address VPN-TRAFFIC
 exit

interface g0/0
 description Vers-Nuage-WAN-Lien-Secours
 ip address 100.64.0.5 255.255.255.252
 crypto map CMAP-VPN
 no shutdown
 exit

ip access-list standard MGMT-ONLY
 permit 10.10.99.0 0.0.0.255
 exit

line vty 0 4
 access-class MGMT-ONLY in
 exit
```

Lyon 1:

PARTIE 1

```
enable
configure terminal
license boot module c2900 technology-package securityk9
```

PARTIE 2

```
exit
```

PARTIE 3

```
copy running-config startup-config
```

PARTIE 4

```
reload
```

PARTIE 5

```
enable
conf t
hostname Routeur-Lyon-1
no ip domain-lookup

enable secret 123Soleil!

banner motd #
—--------ROUTEUR-LYON-1—--------
#

service password-encryption

line console 0
 password 123Soleil!
 login
 exec-timeout 15 0
 logging synchronous
 exit

ip domain-name nordtech.local
crypto key generate rsa
```

PARTIE 6

```
username admin privilege 15 secret 123Soleil!
line vty 0 4
 login local
 transport input ssh
 exec-timeout 15 0
 exit

ip ssh version 2

interface g0/0
 description Vers-Nuage-WAN-Lien-Primaire
 ip address 100.64.0.2 255.255.255.252
 no shutdown
 exit

interface g0/1
 description Vers-Switch-Lyon-3-Primaire
 ip address 10.20.253.1 255.255.255.252
 no shutdown
 exit

interface g0/2
 description Vers-Switch-Lyon-4-Secours
 ip address 10.20.253.5 255.255.255.252
 no shutdown
 exit

ip route 10.20.0.0 255.255.0.0 10.20.253.2 10
ip route 10.20.0.0 255.255.0.0 10.20.253.6 20
ip route 10.10.0.0 255.255.0.0 100.64.0.1 10

crypto isakmp policy 10
 encryption aes 256
 hash sha
 authentication pre-share
 group 2
 lifetime 86400
 exit

crypto isakmp key NordTechBrest/Lyon1! address 100.64.0.1
crypto ipsec transform-set TS-VPN esp-aes 256 esp-sha-hmac


ip access-list extended VPN-TRAFFIC
 permit ip 10.20.0.0 0.0.255.255 10.10.0.0 0.0.255.255
 exit
```

```
crypto map CMAP-VPN 10 ipsec-isakmp
 set peer 100.64.0.1
 set transform-set TS-VPN
 match address VPN-TRAFFIC
 exit

interface g0/0
 description Vers-Nuage-WAN-Lien-Primaire
 ip address 100.64.0.2 255.255.255.252
 crypto map CMAP-VPN
 no shutdown
 exit

ip access-list standard MGMT-ONLY
 permit 10.20.99.0 0.0.0.255
 exit

line vty 0 4
 access-class MGMT-ONLY in
 exit
exit

wr
```

Lyon 2:

PARTIE 1

```
enable
configure terminal
license boot module c2900 technology-package securityk9
```

PARTIE 2

```
exit
```

PARTIE 3

```
copy running-config startup-config
```

PARTIE 4

```
reload
```

PARTIE 5

```
en
conf t
hostname Routeur-Lyon-2
no ip domain-lookup

enable secret 123Soleil!

banner motd #
—--------ROUTEUR-LYON-2—--------
#

service password-encryption

line console 0
 password 123Soleil!
 login
 exec-timeout 15 0
 logging synchronous
 exit

ip domain-name nordtech.local
crypto key generate rsa
```

PARTIE 6

```
username admin privilege 15 secret 123Soleil!
line vty 0 4
 login local
 transport input ssh
 exec-timeout 15 0
 exit

ip ssh version 2

interface g0/0
 description Vers-Nuage-WAN-Lien-Secours
 ip address 100.64.0.6 255.255.255.252
 no shutdown
 exit

interface g0/1
 description Vers-Switch-Lyon-4-Primaire
 ip address 10.20.253.9 255.255.255.252
 no shutdown
 exit

interface g0/2
 description Vers-Switch-Lyon-3-Secours
 ip address 10.20.253.13 255.255.255.252
 no shutdown
 exit

ip route 10.20.0.0 255.255.0.0 10.20.253.10 10
ip route 10.20.0.0 255.255.0.0 10.20.253.14 20
ip route 10.10.0.0 255.255.0.0 100.64.0.5 10

crypto isakmp policy 10
 encryption aes 256
 hash sha
 authentication pre-share
 group 2
 lifetime 86400
 exit

crypto isakmp key NordTechBrest/Lyon2! address 100.64.0.5
crypto ipsec transform-set TS-VPN esp-aes 256 esp-sha-hmac


ip access-list extended VPN-TRAFFIC
 permit ip 10.20.0.0 0.0.255.255 10.10.0.0 0.0.255.255
```

```
 exit

crypto map CMAP-VPN 10 ipsec-isakmp
 set peer 100.64.0.5
 set transform-set TS-VPN
 match address VPN-TRAFFIC
 exit

interface g0/0
 description Vers-Nuage-WAN-Lien-Secours
 ip address 100.64.0.6 255.255.255.252
 crypto map CMAP-VPN
 no shutdown
 exit

ip access-list standard MGMT-ONLY
 permit 10.20.99.0 0.0.0.255
 exit

line vty 0 4
 access-class MGMT-ONLY in
 exit
exit

wr
```