

ACS server user guide

The ACS itself is a command line application. It has a rich set of configurations. See: [protodoc](#) for details (or [protodoc.html](#)).

The application also has a set of command line arguments. A description of the available commands can be found by starting the ACS with the flag `-h` (for help).

```
./acs -h
Dirac Audio Control Server (ACS)

Tuning and Demo ACS that can connect to a DAP using DAP_DISPATCH.

Version: 0.1.0

Usage: acs [OPTIONS]

Options:
  -h,--help                Print this help message and exit
  -v,--version             Display program version information and exit
  -c,--config TEXT         ACS configuration file. Alternative to using cli
parameters.
  -s,--standalone TEXT     Loads dar/interface files from the supplied folder.
--standalone-startup-dar TEXT
                           DAR to load in standalone mode. Default is to load
the first one.
--standalone-startup-configuration TEXT
                           Configuration to load in standalone mode. Default is
to load the first one.
  --uri TEXT               URI to use when connecting to the DAP. Default is to
use URI from config.json
  --dump-config            Dump configuration to stdout on startup.
  --dump-versions          Read versions from DAP and exit.
  --dump-default-config    Dump default config and exit.
  --disable-rest BOOLEAN   Disable the REST server.
  --rest-address TEXT      Address to bind rest server to. (Https not yet
supported.)
  --rest-serve-folder TEXT Folder to serve by the rest server. Default: don't
serve.
  -l,--log-level TEXT      Log level (verbose, debug, info, warning, fatal,
off).
```

Examples

Starting the ACS server using the example-config.json

The ACS server requires a json-file containing its configuration. The [example-config.json](#) is an example for this file. One thing it specifies is the GRPC port number that the server will use for dirac-io grpc communication. In

the example-config.json this is specified as "grpc_port": 55813. If left empty the grpc port number will be autogenerated at startup of the server.

```
./acs -c example-config.json
```

Starting the ACS server using a standalone folder with dar/interface

When performing measurements using Filterlab the ACS server needs information from the interface.json file to propagate to FilterLab during connection. For this reason the ACS server needs to be started using the standalone flag pointing out a folder containing the dar and interface.json file.

```
./acs -c example-config.json -s folder_with_dar_and_interface_json
```