

SINE TABLE

300	40	58	60	7A
304	7F	7A	60	58
308	40	28	13	05
30c	00	05	13	28

PASS PASSWORD

310 70 60 60 D0 A0 B0 (SUTEKH DEFAULT)

WHITE

ADDR

	KEYC	DIGIT	TONES	FRAC	INT	FRAC	INT
380	0	D	1633 + 941	F6	01	21	01
384	1	#	1477 + 941	C6	01	21	01
388	2	0	1336 + 941	9A	01	21	01
38C	3	*	1209 + 941	73	01	21	01
390	4	C	1633 + 852	F6	01	06	01
394	5	9	1477 + 852	C6	01	06	01
398	6	8	1336 + 852	9A	01	06	01
39C	7	7	1209 + 852	73	01	06	01
3A0	8	B	1633 + 770	F6	01	ED	00
3A4	9	6	1477 + 770	C6	01	ED	00
3A8	A	5	1336 + 770	9A	01	ED	00
3AC	B	4	1209 + 770	73	01	ED	00
3B0	C	A	1633 + 691	F6	01	D4	00
3B4	D	3	1477 + 691	C6	01	D4	00
3B8	E	2	1336 + 691	9A	01	D4	00
3BC	F	1	1209 + 691	73	01	D4	00

BLUE

<u>ADDR</u>	KEYC	DIGIT	TONES	<u>FRAC</u>	<u>INT</u>	<u>FRAC</u>	<u>INT</u>
3C0	0	2600	2600	00	00	00	00
3C4	1	C12	1700 + 900	0A	02	14	01
3C8	2	0	1500 + 1300	CD	01	8F	01
3CC	3	C11	1700 + 700	0A	02	D7	00
3D0	4	ST	1700 + 1500	0A	02	CD	01
3D4	5	9	1500 + 1100	CD	01	52	01
3D8	6	8	1500 + 900	CD	01	14	01
3DC	7	7	1500 + 700	CD	01	D7	00
3E0	8	KP2	1700 + 1300	0A	02	8F	01
3E4	9	6	1300 + 1100	8F	01	52	01
3E8	A	5	1300 + 900	8F	01	14	01
3EC	B	4	1300 + 700	8F	01	D7	00
3F0	C	KP	1700 + 1100	0A	02	52	01
3F4	D	3	1100 + 900	52	01	14	01
3F8	E	2	1100 + 700	52	01	D7	00
3FC	F	1	900 + 700	14	01	D7	00