

MikroTik site visit checklist

EUNISET LOVE · voucher system · work top to bottom · no internet needed on site

Before you start. Open Winbox, connect to the router, choose **New Terminal** (or SSH to the router's IP). Every command below runs on the router itself. To copy output, select it in the terminal and press Ctrl+C. Photograph the screen as a backup — a blurry photo beats a second trip.

Step 0 — write these down first

```
/system resource print
```

Router model

RouterOS version

Router LAN IP

Step 1 — the public IP test (the important one)

This decides whether the online dashboard can ever reach your router.

```
/ip address print
```

WAN address (the interface facing Starlink)

```
/ip cloud set ddns-enabled=yes  
/ip cloud print
```

public-address

dns-name

What you see	What it means
The two addresses match	You have a public IP. Everything can work from the online dashboard.
They differ	Behind CGNAT. Needs a tunnel, or run the system on site.
WAN starts 100.64.–100.127.	CGNAT confirmed — that range is reserved for exactly this.

Write both numbers down either way. Don't try to judge it on site.

Step 2 — turn on the API

The API is already in the router. It only needs enabling.

```
/ip service print
/ip service enable api
/ip service enable api-ssl
/ip service print
```

Copy the whole table from the last command.

Step 3 — create a dedicated API user

Do not reuse your admin login. **Choose a long password and write it here — it cannot be recovered later.**

API password

```
/user group add name=voucher-api policy=api,read,write,test
/user add name=voucher-api group=voucher-api password=PUT-PASSWORD-HERE
/user print
```

Confirm voucher-api appears in the list.

Step 4 — capture the hotspot setup

The dashboard's packages must match these profile names exactly.

```
/ip hotspot print
/ip hotspot profile print
/ip hotspot user profile print
```

Profile names

Check whether accounting is on — without it, usage figures are impossible:

```
/ip hotspot user profile print detail
```

Look for accounting= on each profile. Note any that say no.

Step 5 — export your vouchers (bring this file back)

```
/ip hotspot user print count-only
```

Voucher count

```
/ip hotspot user export file=vouchers
```

This creates **vouchers.rsc** on the router. Get it off via Winbox → **Files** → find `vouchers.rsc` → drag it to your desktop (or right-click → Download). Copy it to a USB stick too.

This file is the point of the trip — it is your entire voucher stock, and the system imports it directly.

If export is unavailable on your version, use this instead and take the file the same way:

```
/ip hotspot user print detail file=vouchers
```

Step 6 — active sessions (optional)

```
/ip hotspot active print
```

Shows whether accounting is producing real numbers.

Step 7 — only if Step 1 showed a PUBLIC IP

```
/ip firewall filter print
```

Copy the output. **Do not open any port yet** — we will add a rule restricted to one source address rather than exposing the API to the whole internet.

Bring back

- ☐ **vouchers.rsc** — the export file (most important)
- ☐ Step 1: both addresses
- ☐ Step 2: the `/ip service print` table
- ☐ Step 3: the API password you chose
- ☐ Step 4: profile names, and which have accounting off
- ☐ Step 5: voucher count
- ☐ Step 6: active sessions output
- ☐ Router model and RouterOS version

If something goes wrong

Problem	What to do
A command errors	Write the exact message down and move on. Nothing here is destructive; a failed command changes nothing.
<code>/ip cloud</code> not available	Older RouterOS. Skip it — the WAN address plus the <code>100.64–100.127</code> rule still answers the question.
Worried about lockout	Adding a user and enabling a service cannot lock you out. Your own login is unchanged.

To undo everything:

```
/ip service disable api
/ip service disable api-ssl
/user remove voucher-api
/user group remove voucher-api
```

Nothing in this checklist touches your hotspot, your existing vouchers, or any connected customer. **Customers stay online throughout.**