

2H MICROSTEP DRIVER

DM860A

Current Table (Peak=RMS*1.4)

Peak RMS	SW1	SW2	SW3
2.8A 2.0A	ON	ON	ON
3.5A 2.5A	OFF	ON	ON
4.2A 3.0A	ON	OFF	ON
4.9A 3.5A	OFF	OFF	ON
5.7A 4.0A	ON	ON	OFF
6.4A 4.5A	OFF	ON	OFF
7.0A 5.0A	ON	OFF	OFF
7.8A 5.6A	OFF	OFF	OFF

SW4:OFF=Half Current;ON=Full Current

Pulse/rev Table

Pulse/rev	SW5	SW6	SW7	SW8
400	ON	ON	ON	ON
800	OFF	ON	ON	ON
1600	ON	OFF	ON	ON
3200	OFF	OFF	ON	ON
6400	ON	ON	OFF	ON
12800	OFF	ON	OFF	ON
25600	ON	OFF	OFF	ON
51200	OFF	OFF	OFF	ON
1000	ON	ON	ON	OFF
2000	OFF	ON	ON	OFF
5000	ON	OFF	ON	OFF
10000	OFF	OFF	ON	OFF
25000	ON	OFF	OFF	OFF
50000	OFF	ON	OFF	OFF

SIGNAL

PWR/ALM
PUL+ (+5V)
PUL- (PUL)
DIR+ (+5V)
DIR- (DIR)
ENBL+ (+5V)
ENBL- (ENB)

SETTING

SW8
SW7
SW6
SW5
SW4
SW3
SW2
SW1

POWER

GND
VDC
A+
A-
B+
B-

