

EPROM ADDRESS DECODING JUMPER SETTINGS

JP1 - ROM2 TO ADDRESS 1000-1FFF
JP2 - ROM3 TO ADDRESS 0000-0FFF
JP3 - ROM2 TO ADDRESS D000-DFFF
JP4 - ROM3 TO ADDRESS C000-CFFF

JP5 - ASSIGN ADDRESS RANGE 0000-3FFF TO THE EXTERNAL BUS
JP8 - ASSIGN ADDRESS RANGE 0000-3FFF TO ROM4 (27128/27256)

JP6 OR
JP7 - BANK SWITCH ENABLE FOR THE LOWER 4K OF A 27256 IN ROM4

EPROM TYPE SELECT JUMPERS

ROM1 TYPE SELECT - ADDRESS F000-FFFF
JP10 & JP12 BRIDGED = 2532 EPROMS
JP9 & JP10 BRIDGED = 27xxx EPROMS

ROM2 TYPE SELECT - ADDRESS D000-DFFF
JP14 & JP16 BRIDGED = 2532 EPROMS
JP13 & JP15 BRIDGED = 27xxx EPROMS

ROM3 TYPE SELECT - ADDRESS C000-CFFF
JP18 & JP20 BRIDGED = 2532 EPROMS
JP17 & JP19 BRIDGED = 27xxx EPROMS

(NOTE: ONLY THE TOP 4K OF 27xxx ACCESSIBLE)