为 NFS 过渡做准备

ONTAP 7-Mode Transition

NetApp
May 19, 2022

This PDF was generated from https://docs.netapp.com/zh-cn/ontap-7mode-transition/copy-free/concept_prerequisites_to_transition_nfs_configurations.html on May 19, 2022. Always check docs.netapp.com for the latest.

目录

为 NFS 过渡做准备 1
过渡 NFS 配置的前提条件 1
NFS 过渡：支持和不支持的配置以及所需的手动步骤 1
NFS 导出的过渡方式 3

为 NFS 过渡做准备

如果 NFS 已获得许可，并且 NFS 服务正在 7- 模式系统上运行，则必须手动准备集群和目标 SVM 以过渡 NFS 配置。此外，您还必须了解要过渡的配置。

ONTAP 不支持某些在 7- 模式下运行的 NFS 配置。某些配置不会通过 7- 模式过渡工具进行过渡，必须手动应用于 SVM 。

过渡 NFS 配置的前提条件

只有在 7- 模式系统和集群满足特定前提条件时， 7- 模式过渡工具才会过渡 NFS 配置。如果不满足任何条件，该工具将不会过渡配置。

7- 模式前提条件

- NFS 必须获得许可。
- 如果 MultiStore 已获得许可，则必须在所有 vFiler 单元上启用 NFS 。
- 过渡期间， 7- 模式系统上必须运行 NFS 服务。

  即使在断开客户端访问并准备开始导出阶段后，该服务也必须在 7- 模式系统上运行。

- 如果要过渡内存导出规则，必须在过渡前将其添加到 ` /etc/exports` 文件中。

  7- 模式过渡工具仅过渡在 ` /etc/exports` 文件中定义的持久导出规则。

集群前提条件

- NFS 必须获得许可。
- 相关信息 *

"NetApp 文档： ONTAP 9"

NFS 过渡：支持和不支持的配置以及所需的手动步骤

某些 NFS 配置不会过渡到 ONTAP ，因为它们在 ONTAP 中不受支持，与 7- 模式存在功能差异，或者必须手动过渡。您应验证所有预检错误和警告消息，以评估此类配置对过渡的影响。

支持过渡的配置

从较高层面来看， 7- 模式过渡工具会过渡以下 NFS 配置：

- NFS 选项：
  - `nfs.udp.xfersize`

    - `nfs.v4.id.domain`
    - `nfs.v4.acl.max.aces`
    - `nfs.tcp.xfersize`
    - `nfs.rpcsec.ctx.high`
    - `nfs.rpcsec.ctx.idle`
    - `nfs.response.trigger`
    - `wafl.default_nt_user`
    - `nfs.mount_rootonly`
    - `nfs.tcp.enable`
    - `nfs.udp.enable`
    - `nfs.response.trace`
    - `nfs.v4.read_delegation`
    - `nfs.v4.write_delegation`
    - `nfs.v4.acl.enable`
    - `nfs.vStorage.enable`
    - `nfs.v3.enable`
    - `nfs.v4.enable`
- NFS 导出规则：

  如果导出规则配置了 -actual 选项，则会忽略导出的路径（别名路径），并使用实际路径配置导出规则。

- 具有 Kerberos 安全 krb5p 的导出规则

有关这些 NFS 配置的详细信息，请参见预检结果。

ONTAP 中不支持的配置

ONTAP 不支持以下 NFS 配置：

- 除 qtree 级 NFS 导出以外的子卷 NFS 导出
- WebNFS
- PC-NFS
- NFSv2
- 从一个或多个文件系统隔离 NFS 客户端 路径
- 一些 NFS 选项

  有关不支持的选项的完整列表，请参见预检警告消息。

必须手动过渡的配置

ONTAP 中支持某些 NFS 配置，但 7- 模式过渡工具不会过渡这些配置。

以下 NFS 配置会在预检操作中生成警告消息，您必须在 SVM 上手动应用这些配置：

- NFS 审核配置
- NFS 选项：
  - `rpc.Nsm.tcp.port`
  - `rpc.Nsm.udp.port`
  - `rpc.mount.tcp.port`
  - `rpc.mount.udp.port`
  - `nfs.export.neg.timeout`
  - `nfs.export.pos.timeout`
  - `nfs.export.harvest.timeout` 使用 `vserver nfs modify` 命令修改启用了 NFS 的 Storage Virtual Machine （ SVM ）的配置。
- Kerberos 配置

在 **ONTAP** 中功能不同的配置

以下 NFS 配置在 ONTAP 中的功能有所不同：

- NFS 导出规则
- NFS 导出访问缓存
- NFS 诊断命令
- 支持 `showmount` 命令
- NFS Kerberos 加密
- NLM 版本支持
- 相关信息 *

自定义 7- 模式配置的过渡

"NFS 管理"

NFS 导出的过渡方式

您必须了解过渡后如何在 SVM 上配置 NFS 导出。如果 ONTAP 不支持 7- 模式导出配置，则可能需要执行一些手动步骤。

您必须了解有关 NFS 导出过渡的以下注意事项：

- 如果未导出 SVM 根卷以允许对所有 NFS 客户端进行只读访问，则 7- 模式过渡工具会创建一个新的导出策略，允许所有 NFS 客户端进行只读访问，并使用新的导出策略导出 SVM 的根卷。

要确保所有过渡后的卷或 qtree 均可挂载，必须允许所有 NFS 客户端对 SVM 的根卷进行只读访问。

- 过渡具有 ONTAP 不支持的导出配置的 7- 模式卷时，这些卷将被导出，以禁止访问所有 NFS 客户端。

  过渡后，必须手动配置这些卷的导出策略，以提供所需的访问权限。

- 过渡具有 ONTAP 不支持的导出配置的 7- 模式 qtree 时，它们将继承父卷的导出策略。

  过渡后，必须手动配置这些 qtree 的导出策略，以提供所需的访问权限。

- 在 ONTAP 中，要使 NFS 客户端能够挂载 qtree ， NFS 客户端必须在所有父接合路径上具有只读权限，直到 SVM 的根卷接合路径（即 / ）为止。

  要使 NFS 客户端能够挂载 qtree ， qtree 必须属于具有只读权限的卷。如果在卷级别没有只读权限， NFS 客户端将无法挂载 qtree 。

- 如果在只读，读写和 root 访问权限列表的组合中指定了同一主机，则必须在过渡后评估过渡后的导出规则，以确定这些主机的适当访问权限。

"NetApp 技术报告 4067 ：《 NFS 最佳实践和实施指南》"

示例：修改卷的导出策略以允许访问 qtree

请考虑在 7- 模式存储系统（ 192.168.26.18 ）中配置的以下导出规则，该规则允许 NFS 客户端 192.168.10.10 对卷 volstd10 和 qtree qtree1 进行读 / 写访问：

```
/vol/volstd10/qtree1 -sec=sys,rw=192.168.10.10,nosuid
/vol/volstd10 -sec=sys,rw=192.168.11.11,nosuid
```

过渡后， ONTAP 中卷 volsdt10 的导出策略如下所示：

```
cluster-01::> export-policy rule show -vserver std_22 -policyname std_2226
-instance
 (vserver export-policy rule show)

                                                 Vserver: std_22
                                             Policy Name: std_2226
                                              Rule Index: 1
                                          Access Protocol: any
Client Match Hostname, IP Address, Netgroup, or Domain: 192.168.11.11
                                           RO Access Rule: sys
                                           RW Access Rule: sys
           User ID To Which Anonymous Users Are Mapped:65534
                                  Superuser Security Types: none
                              Honor SetUID Bits in SETATTR: false
                                 Allow Creation of Devices: true
cluster-01::>
```

过渡后， ONTAP 中 qtree qtree1 的导出策略如下所示：

```
 cluster-01::> export-policy rule show -vserver std_22 -policyname
std_2225 -instance
  (vserver export-policy rule show)

                                     Vserver: std_22
                                Policy Name: std_2225
                                 Rule Index: 1
                            Access Protocol: any
Client Match Hostname, IP Address, Netgroup, or Domain: 192.168.10.10
                             RO Access Rule: sys
                             RW Access Rule: sys
User ID To Which Anonymous Users Are Mapped: 65534
                    Superuser Security Types: none
                Honor SetUID Bits in SETATTR: false
                   Allow Creation of Devices: true
cluster-01::>
```

要使 NFS 客户端 192.168.10.10 能够访问 qtree ， NFS 客户端 192.168.10.10 必须对 qtree 的父卷具有只读访问权限。

以下输出显示 NFS 客户端在挂载 qtree 时被拒绝访问：

```
 [root@192.168.10.10 ]# mount 192.168.35.223:/vol/volstd10/qtree1
transition_volume_qtreemount:192.168.35.223:/vol/volstd10/qtree1 failed,
reason
given by server: Permission denied [root@192.168.10.10 ]#
```

您必须手动修改卷的导出策略，以便为 NFS 客户端 192.168.10.10 提供只读访问权限。

```
cluster-01::> export-policy rule create -vserver std_22 -policyname
std_2226 -clientmatch
192.168.10.10 -rorule sys -rwrule never -allow-suid false -allow-dev true
-superuser none -protocol nfs
  (vserver export-policy rule create)

cluster-01::> export-policy rule show -vserver std_22 -policyname std_2226
-instance
  (vserver export-policy rule show)

                                    Vserver: std_22
                                Policy Name: std_2226
                                 Rule Index: 1
                            Access Protocol: any
Client Match Hostname, IP Address, Netgroup, or Domain: 192.168.11.11
                              RO Access Rule: sys
                              RW Access Rule: sys
User ID To Which Anonymous Users Are Mapped: 65534
                    Superuser Security Types: none
                Honor SetUID Bits in SETATTR: false
                   Allow Creation of Devices: true

**                                    Vserver: std_22
                                Policy Name: std_2226
                                 Rule Index: 2
                            Access Protocol: nfs
Client Match Hostname, IP Address, Netgroup, or Domain: 192.168.10.10
                              RO Access Rule: sys
                              RW Access Rule: never
User ID To Which Anonymous Users Are Mapped: 65534
                    Superuser Security Types: none
                Honor SetUID Bits in SETATTR: false
                   Allow Creation of Devices: true**

cluster-01::>
```

示例： qtree 导出规则在 7- 模式和 ONTAP 中有何不同

在 7- 模式存储系统中，当 NFS 客户端通过 qtree 的父卷的挂载点访问 qtree 时， qtree 导出规则将被忽略，其父卷的导出规则将生效。但是，在 ONTAP 中，无论 NFS 客户端是直接挂载到 qtree ，还是通过 qtree 的父卷的挂载点访问 qtree ， qtree 导出规则始终会强制执行。此示例专门适用于 NFSv4 。

以下是 7- 模式存储系统（ 192.168.26.18 ）上的导出规则示例：

```
/vol/volstd10/qtree1 -sec=sys,ro=192.168.10.10,nosuid
/vol/volstd10   -sec=sys,rw=192.168.10.10,nosuid
```

在 7- 模式存储系统上， NFS 客户端 192.168.10.10 仅对 qtree 具有只读访问权限。但是，当客户端通过其父卷的挂载点访问 qtree 时，客户端可以向 qtree 写入数据，因为客户端对卷具有读 / 写访问权限。

```
[root@192.168.10.10]# mount 192.168.26.18:/vol/volstd10 transition_volume
[root@192.168.10.10]# cd transition_volume/qtree1
[root@192.168.10.10]# ls transition_volume/qtree1
[root@192.168.10.10]# mkdir new_folder
[root@192.168.10.10]# ls
new_folder
[root@192.168.10.10]#
```

在 ONTAP 中，当 NFS 客户端 192.168.10.10 直接访问 qtree qtree1 或通过 qtree 父卷的挂载点访问 qtree 时，该客户端仅对该 qtree 具有只读访问权限。

过渡后，您必须评估强制实施 NFS 导出策略的影响，如果需要，请将这些过程修改为在 ONTAP 中强制实施 NFS 导出策略的新方式。

- 相关信息 *

"NFS 管理"

Copyright Information

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.