新しいコントローラモジュールを設置してケーブル接続します

ONTAP MetroCluster

NetApp
May 03, 2022

This PDF was generated from https://docs.netapp.com/ja-jp/ontap-metrocluster/upgrade/task_install_and_cable_the_new_controller.html on May 03, 2022. Always check docs.netapp.com for the latest.

目次

新しいコントローラモジュールを設置してケーブル接続します 1
新しいコントローラモジュールを設置してケーブル接続 1
新しいコントローラモジュールの FC-VI ポートおよび HBA ポートを FC スイッチにケーブル接続します 2
新しいコントローラモジュールのクラスタピアリングのケーブル接続 2

新しいコントローラモジュールを設置してケーブル接続します

新しいコントローラモジュールを設置してケーブル接続

新しいコントローラモジュールをシャーシに物理的に設置し、ケーブルを接続する必要があります。

手順

1. I/O 拡張モジュール（ IOXM ）が搭載されているシステムでシングルシャーシの HA ペアを作成する場合は、 IOXM をケーブルを外して取り出す必要があります。

   空になったベイを新しいコントローラモジュールに使用できます。ただし、新しい構成では IOXM によって追加の I/O は提供されません。

2. 新しいコントローラモジュールを物理的に設置し、必要に応じて追加のファンを取り付けます。

コントローラモジュールの追加先	実行する手順
空のベイに追加してシングルシャーシの HA ペアを作成する。システムのプラットフォームは次のいずれか： • FAS8200 • 80XX	a. 新しいコントローラモジュールを取り付ける空のベイに対応するシャーシ背面のブランクプレートを取り外します。 b. コントローラモジュールをシャーシの途中までそっと押し込みます。 コントローラモジュールが自動的にブートしないようにするために、この手順の後半までシャーシに完全に挿入しないでください。
既存の構成がコントローラ IOX モジュール構成である場合、 HA パートナーとは別のシャーシにデュアルシャーシの HA ペアを作成します。	新しいシステムをラックまたはシステムキャビネットに設置します。

3. 必要に応じて、クラスタネットワーク接続をケーブル接続します。

   a. コントローラモジュールでクラスタ接続用のポートを特定します。

      "AFF A320 システム：設置とセットアップ"

      "AFF A220 / FAS2700 システムの設置とセットアップの手順"

      "AFF A800 システムの設置とセットアップの手順"

      "AFF A300 システム『 Installation and Setup Instructions 』"

"FAS8200 システム設置とセットアップの手順"

b. スイッチクラスタを設定する場合は、クラスタネットワークスイッチで使用するポートを特定します。

使用するスイッチに応じて、『 clustered Data ONTAP スイッチセットアップガイド』、『 NetApp 10G Cluster-Mode Switch Installation Guide 』、または『 NetApp 1G Cluster-Mode Switch Installation Guide 』を参照してください。

c. クラスタポートにケーブルを接続します。

クラスタの種類	作業
2 ノードスイッチレスクラスタ	既存のコントローラモジュールのクラスタポートを、新しいコントローラモジュールの対応するクラスタポートに直接接続します。
スイッチクラスタ	各コントローラのクラスタポートを、手順 b で特定したクラスタネットワークスイッチのポートに接続します

新しいコントローラモジュールの **FC-VI** ポートおよび **HBA** ポートを **FC** スイッチにケーブル接続します

新しいコントローラモジュールの FC-VI ポートと HBA （ホストバスアダプタ）をサイトの FC スイッチにケーブル接続する必要があります。

手順

1. 構成とスイッチモデルの表を使用して、 FC-VI ポートと HBA ポートをケーブル接続します。
   - "ONTAP 9.1 以降を使用している場合の FC スイッチのポート割り当て"
   - "ONTAP 9.0 を使用している場合の FC スイッチのポート割り当て"
   - "2 つのイニシエータポートを使用するシステムのポート割り当て"

新しいコントローラモジュールのクラスタピアリングのケーブル接続

パートナーサイトのクラスタと接続できるように、新しいコントローラモジュールをクラスタピアリングネットワークにケーブル接続する必要があります。

クラスタピアリングには、各コントローラモジュールの少なくとも 2 つのポートを使用します。

ポートおよびネットワーク接続の推奨される最小帯域幅は 1GbE です。

手順

1. クラスタピアリングに使用する少なくとも 2 つのポートを特定してケーブル接続し、そのポートがパートナークラスタとネットワーク接続されていることを確認します。

Copyright Information

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.