# View NVMe subsystem controllers

ONTAP 9.14.1 REST API reference

NetApp
February 12, 2024

This PDF was generated from https://docs.netapp.com/us-en/ontap-restapi/ontap/protocols_nvme_subsystem-controllers_endpoint_overview.html on February 12, 2024.
Always check docs.netapp.com for the latest.

# Table of Contents

View NVMe subsystem controllers . . . 1
Protocols NVMe subsystem-controllers endpoint overview . . . 1
Retrieve NVMe subsystem controllers . . . 7
Retrieve an NVMe subsystem controller . . . 18

# View NVMe subsystem controllers

## Protocols NVMe subsystem-controllers endpoint overview

### Overview

Non-Volatile Memory Express (NVMe) subsystem controllers represent dynamic connections between hosts and a storage solution.

The NVMe subsystem controllers REST API provides information about connected hosts.

### Examples

#### Retrieving the NVMe subsystem controllers for the entire system

```
# The API:
GET /api/protocols/nvme/subsystem-controllers

# The call:
curl -X GET 'https://<mgmt-ip>/api/protocols/nvme/subsystem-controllers'
-H 'Accept: application/hal+json'

# The response:
{
"records": [
  {
    "svm": {
      "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_fcnvme_vserver_0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
        }
      }
    },
    "subsystem": {
      "uuid": "14875240-2594-11e9-abde-00a098984313",
      "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_0",
      "_links": {
        "self": {
          "href": "/api/protocols/nvme/subsystems/14875240-2594-11e9-abde-
00a098984313"
        }
      }
    },
    "id": "0040h",
```

```
    "_links": {
      "self": {
        "href": "/api/protocols/nvme/subsystem-controllers/14875240-2594-
11e9-abde-00a098984313/0040h"
      }
    }
  },
  {
    "svm": {
      "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_fcnvme_vserver_0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
        }
      }
    },
    "subsystem": {
      "uuid": "14875240-2594-11e9-abde-00a098984313",
      "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_0",
      "_links": {
        "self": {
          "href": "/api/protocols/nvme/subsystems/14875240-2594-11e9-abde-
00a098984313"
        }
      }
    },
    "id": "0041h",
    "_links": {
      "self": {
        "href": "/api/protocols/nvme/subsystem-controllers/14875240-2594-
11e9-abde-00a098984313/0041h"
      }
    }
  },
  {
    "svm": {
      "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_fcnvme_vserver_0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
        }
      }
    },
    "subsystem": {
```

```
      "uuid": "1489d0d5-2594-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_1",
      "_links": {
        "self": {
          "href": "/api/protocols/nvme/subsystems/1489d0d5-2594-11e9-94c4-
00a0989a1c8e"
        }
      }
    },
    "id": "0040h",
    "_links": {
      "self": {
        "href": "/api/protocols/nvme/subsystem-controllers/1489d0d5-2594-
11e9-94c4-00a0989a1c8e/0040h"
      }
    }
  },
  {
    "svm": {
      "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_fcnvme_vserver_0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
        }
      }
    },
    "subsystem": {
      "uuid": "1489d0d5-2594-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_1",
      "_links": {
        "self": {
          "href": "/api/protocols/nvme/subsystems/1489d0d5-2594-11e9-94c4-
00a0989a1c8e"
        }
      }
    },
    "id": "0041h",
    "_links": {
      "self": {
        "href": "/api/protocols/nvme/subsystem-controllers/1489d0d5-2594-
11e9-94c4-00a0989a1c8e/0041h"
      }
    }
  }
],
```

```
"num_records": 4,
"_links": {
  "self": {
    "href": "/api/protocols/nvme/subsystem-controllers"
  }
}
}
```

---

#### Retrieving the NVMe subsystem controllers for a specific subsystem

```
# The API:
GET /api/protocols/nvme/subsystem-controllers

# The call:
curl -X GET 'https://<mgmt-ip>/api/protocols/nvme/subsystem-
controllers?subsystem.uuid=14875240-2594-11e9-abde-00a098984313' -H
'Accept: application/hal+json'

# The response:
{
"records": [
  {
    "svm": {
      "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_fcnvme_vserver_0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
        }
      }
    },
    "subsystem": {
      "uuid": "14875240-2594-11e9-abde-00a098984313",
      "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_0",
      "_links": {
        "self": {
          "href": "/api/protocols/nvme/subsystems/14875240-2594-11e9-abde-
00a098984313"
        }
      }
    },
    "id": "0040h",
    "_links": {
      "self": {
```

```
        "href": "/api/protocols/nvme/subsystem-controllers/14875240-2594-
11e9-abde-00a098984313/0040h"
      }
    }
  },
  {
    "svm": {
      "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
      "name": "symmcon_fcnvme_vserver_0",
      "_links": {
        "self": {
          "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
        }
      }
    },
    "subsystem": {
      "uuid": "14875240-2594-11e9-abde-00a098984313",
      "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_0",
      "_links": {
        "self": {
          "href": "/api/protocols/nvme/subsystems/14875240-2594-11e9-abde-
00a098984313"
        }
      }
    },
    "id": "0041h",
    "_links": {
      "self": {
        "href": "/api/protocols/nvme/subsystem-controllers/14875240-2594-
11e9-abde-00a098984313/0041h"
      }
    }
  }
],
"num_records": 2,
"_links": {
  "self": {
    "href": "/api/protocols/nvme/subsystem-controllers/14875240-2594-11e9-
abde-00a098984313"
  }
}
}
```

#### Retrieving a specific NVMe subsystem controller

```
# The API:
GET /api/protocols/nvme/subsystem-controllers/{subsystem.uuid}/{id}

# The call:
curl -X GET 'https://<mgmt-ip>/api/protocols/nvme/subsystem-
controllers/14875240-2594-11e9-abde-00a098984313/0040h' -H 'Accept:
application/hal+json'

# The response:
{
"svm": {
  "uuid": "f0f5b928-2593-11e9-94c4-00a0989a1c8e",
  "name": "symmcon_fcnvme_vserver_0",
  "_links": {
    "self": {
      "href": "/api/svm/svms/f0f5b928-2593-11e9-94c4-00a0989a1c8e"
    }
  }
},
"subsystem": {
  "uuid": "14875240-2594-11e9-abde-00a098984313",
  "name": "symmcon_symmcon_fcnvme_vserver_0_subsystem_0",
  "_links": {
    "self": {
      "href": "/api/protocols/nvme/subsystems/14875240-2594-11e9-abde-
00a098984313"
    }
  }
},
"id": "0040h",
"interface": {
  "name": "symmcon_lif_fcnvme_symmcon_fcnvme_vserver_0_3a_0",
  "uuid": "fa1c5941-2593-11e9-94c4-00a0989a1c8e",
  "transport_address": "nn-0x200400a0989a1c8d:pn-0x200500a0989a1c8d",
  "_links": {
    "self": {
      "href": "/api/protocols/nvme/interfaces/fa1c5941-2593-11e9-94c4-
00a0989a1c8e"
    }
  }
},
"node": {
  "name": "ssan-8040-94a",
  "uuid": "ebf66f05-2590-11e9-abde-00a098984313",
```

```
    "_links": {
      "self": {
        "href": "/api/cluster/nodes/ebf66f05-2590-11e9-abde-00a098984313"
      }
    }
  },
  "host": {
    "transport_address": "nn-0x20000090fae00806:pn-0x10000090fae00806",
    "nqn": "nqn.2014-08.org.nvmexpress:uuid:c2846cb1-89d2-4020-a3b0-
71ce907b4eef",
    "id": "b8546ca6097349e5b1558dc154fc073b"
  },
  "io_queue": {
    "count": 4,
    "depth": [
      32,
      32,
      32,
      32
    ]
  },
  "admin_queue": {
    "depth": 32
  },
  "keep_alive_timeout": 4000,
  "dh_hmac_chap": {
    "mode": "none"
  },
  "_links": {
    "self": {
      "href": "/api/protocols/nvme/subsystem-controllers/14875240-2594-11e9-
abde-00a098984313/0040h"
    }
  }
}
```


# Retrieve NVMe subsystem controllers

GET `/protocols/nvme/subsystem-controllers`

**Introduced In:** 9.6

Retrieves NVMe subsystem controllers.

## Related ONTAP commands

- `vserver nvme subsystem controller show`

## Learn more

- DOC /protocols/nvme/subsystem-controllers

## Parameters

| Name | Type | In | Required | Description |
|---|---|---|---|---|
| id | string | query | False | Filter by id |
| host.id | string | query | False | Filter by host.id |
| host.nqn | string | query | False | Filter by host.nqn<br>• maxLength: 223<br>• minLength: 1 |
| host.transport_address | string | query | False | Filter by host.transport_address |
| interface.transport_address | string | query | False | Filter by interface.transport_address |
| interface.uuid | string | query | False | Filter by interface.uuid |
| interface.name | string | query | False | Filter by interface.name |
| svm.uuid | string | query | False | Filter by svm.uuid |
| svm.name | string | query | False | Filter by svm.name |
| subsystem.uuid | string | query | False | Filter by subsystem.uuid |
| subsystem.name | string | query | False | Filter by subsystem.name<br>• maxLength: 64<br>• minLength: 1 |

| Name | Type | In | Required | Description |
|---|---|---|---|---|
| node.name | string | query | False | Filter by node.name |
| node.uuid | string | query | False | Filter by node.uuid |
| admin_queue.depth | integer | query | False | Filter by admin_queue.depth |
| dh_hmac_chap.mode | string | query | False | Filter by dh_hmac_chap.mode<br>• Introduced in: 9.12 |
| dh_hmac_chap.group_size | string | query | False | Filter by dh_hmac_chap.group_size<br>• Introduced in: 9.12 |
| dh_hmac_chap.hash_function | string | query | False | Filter by dh_hmac_chap.hash_function<br>• Introduced in: 9.12 |
| io_queue.depth | integer | query | False | Filter by io_queue.depth |
| io_queue.count | integer | query | False | Filter by io_queue.count |
| keep_alive_timeout | integer | query | False | Filter by keep_alive_timeout<br>• Introduced in: 9.14 |
| fields | array[string] | query | False | Specify the fields to return. |
| max_records | integer | query | False | Limit the number of records returned. |

| Name | Type | In | Required | Description |
|---|---|---|---|---|
| return_records | boolean | query | False | The default is true for GET calls. When set to false, only the number of records is returned.<br>• Default value: 1 |
| return_timeout | integer | query | False | The number of seconds to allow the call to execute before returning. When iterating over a collection, the default is 15 seconds. ONTAP returns earlier if either max records or the end of the collection is reached.<br>• Default value: 1<br>• Max value: 120<br>• Min value: 0 |
| order_by | array[string] | query | False | Order results by specified fields and optional [asc |

## Response

```
Status: 200, Ok
```

| Name | Type | Description |
|---|---|---|
| _links | _links | |
| num_records | integer | The number of records in the response. |
| records | array[nvme_subsystem_controller] | |

**Example response**


```
{
  "_links": {
    "next": {
      "href": "/api/resourcelink"
    },
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "num_records": 1,
  "records": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "admin_queue": {
      "depth": 0
    },
    "dh_hmac_chap": {
      "group_size": "none",
      "hash_function": "sha_256",
      "mode": "bidirectional"
    },
    "host": {
      "id": "b8546ca6097349e5b1558dc154fc073b",
      "nqn": "nqn.2014-08.org.nvmexpress:uuid:c2846cb1-89d2-4020-a3b0-
71ce907b4eef",
      "transport_address": "nn-0x20000090fae00806:pn-
0x10000090fae00806"
    },
    "id": "0040h",
    "interface": {
      "name": "lif1",
      "transport_address": "nn-0x200400a0989a1c8d:pn-
0x200500a0989a1c8d",
      "uuid": "fa1c5941-2593-11e9-94c4-00a0989a1c8e"
    },
    "io_queue": {
      "count": 0,
      "depth": {
      }
    },
    "keep_alive_timeout": 1500,
```

```
    "node": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "node1",
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "subsystem": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "subsystem1",
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "svm": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "svm1",
      "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
    }
  }
}
```


## Error

```
Status: Default, Error
```

| Name | Type | Description |
|---|---|---|
| error | returned_error | |

**Example error**

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

**See Definitions**

href

| Name | Type | Description |
|---|---|---|
| href | string | |

_links

| Name | Type | Description |
|---|---|---|
| next | href | |
| self | href | |

_links

| Name | Type | Description |
|---|---|---|
| self | href | |

admin_queue

| Name | Type | Description |
|---|---|---|
| depth | integer | The depth of the admin queue for the controller. |

dh_hmac_chap

A container for properties of the NVMe in-band authentication DH-HMAC-CHAP protocol used by the the host connection to the controller.

| Name | Type | Description |
|---|---|---|
| group_size | string | The Diffie-Hellman group size used for NVMe in-band authentication. |
| hash_function | string | The hash function used for NVMe in-band authentication. |

| Name | Type | Description |
| --- | --- | --- |
| mode | string | The NVMe in-band authentication mode used for the host connection. When set to:<br>• none: Neither the host nor controller was authenticated.<br>• unidirectional: The controller authenticated the host.<br>• bidirectional: The controller authenticated the host and the host authenticated the controller. |

host

Properties of the connected host.

| Name | Type | Description |
| --- | --- | --- |
| id | string | The host identifier registered with the controller. |
| nqn | string | The NVMe qualified name of the host. |
| transport_address | string | The transport address of the host. |

interface

The logical interface through which the host is connected.

| Name | Type | Description |
| --- | --- | --- |
| name | string | The name of the logical interface. |
| transport_address | string | The transport address of the logical interface. |
| uuid | string | The unique identifier of the logical interface. |

io_queue

Properties of the I/O queues available to the controller.

| Name | Type | Description |
| --- | --- | --- |
| count | integer | The number of I/O queues available to the controller. |
| depth | array[integer] | The depths of the I/O queues. |

node

| Name | Type | Description |
| --- | --- | --- |
| _links | _links | |
| name | string | |
| uuid | string | |

subsystem

An NVMe subsystem maintains configuration state and NVMe namespace access control for a set of NVMe-connected hosts.

| Name | Type | Description |
| --- | --- | --- |
| _links | _links | |
| name | string | The name of the NVMe subsystem. |
| uuid | string | The unique identifier of the NVMe subsystem. |

svm

SVM, applies only to SVM-scoped objects.

| Name | Type | Description |
| --- | --- | --- |
| _links | _links | |
| name | string | The name of the SVM. This field cannot be specified in a PATCH method. |
| uuid | string | The unique identifier of the SVM. This field cannot be specified in a PATCH method. |

nvme_subsystem_controller

A Non-Volatile Memory Express (NVMe) subsystem controller represents a connection between a host and a storage solution.

An NVMe subsystem controller is identified by the NVMe subsystem UUID and the controller ID.

| Name | Type | Description |
|---|---|---|
| _links | _links | |
| admin_queue | admin_queue | |
| dh_hmac_chap | dh_hmac_chap | A container for properties of the NVMe in-band authentication DH-HMAC-CHAP protocol used by the the host connection to the controller. |
| host | host | Properties of the connected host. |
| id | string | The identifier of the subsystem controller. This field consists of 4 zero-filled hexadecimal digits followed by an 'h'. |
| interface | interface | The logical interface through which the host is connected. |
| io_queue | io_queue | Properties of the I/O queues available to the controller. |
| keep_alive_timeout | integer | The keep-alive timeout value for the controller and all of its host connections, in milliseconds.<br><br>If the NVMe controller does not receive a keep-alive request or an I/O request within the timeout window, the NVMe controller terminates its admin queue and I/O queue connections leading to NVMe controller teardown. If the NVMe host does not receive a response to a keep-alive request or an I/O request within the timeout window, the NVMe host initiates a connection disconnect. |
| node | node | |
| subsystem | subsystem | An NVMe subsystem maintains configuration state and NVMe namespace access control for a set of NVMe-connected hosts. |

| Name | Type | Description |
|---|---|---|
| svm | svm | SVM, applies only to SVM-scoped objects. |

error_arguments

| Name | Type | Description |
|---|---|---|
| code | string | Argument code |
| message | string | Message argument |

returned_error

| Name | Type | Description |
|---|---|---|
| arguments | array[error_arguments] | Message arguments |
| code | string | Error code |
| message | string | Error message |
| target | string | The target parameter that caused the error. |

# Retrieve an NVMe subsystem controller

GET `/protocols/nvme/subsystem-controllers/{subsystem.uuid}/{id}`

**Introduced In:** 9.6

Retrieves an NVMe subsystem controller.

## Related ONTAP commands

- `vserver nvme subsystem controller show`

## Learn more

- DOC /protocols/nvme/subsystem-controllers

## Parameters

| Name | Type | In | Required | Description |
|---|---|---|---|---|
| subsystem.uuid | string | path | True | The unique identifier of the NVMe subsystem. |
| id | string | path | True | The unique identifier of the NVMe subsystem controller. |
| fields | array[string] | query | False | Specify the fields to return. |

## Response

```
Status: 200, Ok
```

| Name | Type | Description |
|---|---|---|
| _links | _links | |
| admin_queue | admin_queue | |
| dh_hmac_chap | dh_hmac_chap | A container for properties of the NVMe in-band authentication DH-HMAC-CHAP protocol used by the the host connection to the controller. |
| host | host | Properties of the connected host. |
| id | string | The identifier of the subsystem controller. This field consists of 4 zero-filled hexadecimal digits followed by an 'h'. |
| interface | interface | The logical interface through which the host is connected. |
| io_queue | io_queue | Properties of the I/O queues available to the controller. |

| Name | Type | Description |
| --- | --- | --- |
| keep_alive_timeout | integer | The keep-alive timeout value for the controller and all of its host connections, in milliseconds.<br><br>If the NVMe controller does not receive a keep-alive request or an I/O request within the timeout window, the NVMe controller terminates its admin queue and I/O queue connections leading to NVMe controller teardown. If the NVMe host does not receive a response to a keep-alive request or an I/O request within the timeout window, the NVMe host initiates a connection disconnect. |
| node | node | |
| subsystem | subsystem | An NVMe subsystem maintains configuration state and NVMe namespace access control for a set of NVMe-connected hosts. |
| svm | svm | SVM, applies only to SVM-scoped objects. |

**Example response**


```
{
  "_links": {
    "self": {
      "href": "/api/resourcelink"
    }
  },
  "admin_queue": {
    "depth": 0
  },
  "dh_hmac_chap": {
    "group_size": "none",
    "hash_function": "sha_256",
    "mode": "bidirectional"
  },
  "host": {
    "id": "b8546ca6097349e5b1558dc154fc073b",
    "nqn": "nqn.2014-08.org.nvmexpress:uuid:c2846cb1-89d2-4020-a3b0-
71ce907b4eef",
    "transport_address": "nn-0x20000090fae00806:pn-0x10000090fae00806"
  },
  "id": "0040h",
  "interface": {
    "name": "lif1",
    "transport_address": "nn-0x200400a0989a1c8d:pn-0x200500a0989a1c8d",
    "uuid": "fa1c5941-2593-11e9-94c4-00a0989a1c8e"
  },
  "io_queue": {
    "count": 0,
    "depth": {
    }
  },
  "keep_alive_timeout": 1500,
  "node": {
    "_links": {
      "self": {
        "href": "/api/resourcelink"
      }
    },
    "name": "node1",
    "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
  },
  "subsystem": {
    "_links": {
      "self": {
```

```
          "href": "/api/resourcelink"
        }
      },
      "name": "subsystem1",
      "uuid": "1cd8a442-86d1-11e0-ae1c-123478563412"
    },
    "svm": {
      "_links": {
        "self": {
          "href": "/api/resourcelink"
        }
      },
      "name": "svm1",
      "uuid": "02c9e252-41be-11e9-81d5-00a0986138f7"
    }
  }
```


## Error

```
Status: Default
```

ONTAP Error Response Codes

| Error Code | Description |
|---|---|
| 72090001 | The supplied subsystem identifier does not exist. |

Also see the table of common errors in the Response body overview section of this documentation.

| Name | Type | Description |
|---|---|---|
| error | returned_error | |

**Example error**

```
{
  "error": {
    "arguments": {
      "code": "string",
      "message": "string"
    },
    "code": "4",
    "message": "entry doesn't exist",
    "target": "uuid"
  }
}
```

## Definitions

**See Definitions**

href

| Name | Type | Description |
|---|---|---|
| href | string | |

_links

| Name | Type | Description |
|---|---|---|
| self | href | |

admin_queue

| Name | Type | Description |
|---|---|---|
| depth | integer | The depth of the admin queue for the controller. |

dh_hmac_chap

A container for properties of the NVMe in-band authentication DH-HMAC-CHAP protocol used by the the host connection to the controller.

| Name | Type | Description |
|---|---|---|
| group_size | string | The Diffie-Hellman group size used for NVMe in-band authentication. |
| hash_function | string | The hash function used for NVMe in-band authentication. |
| mode | string | The NVMe in-band authentication mode used for the host connection. When set to:<br>• none: Neither the host nor controller was authenticated.<br>• unidirectional: The controller authenticated the host.<br>• bidirectional: The controller authenticated the host and the host authenticated the controller. |

host

Properties of the connected host.

| Name | Type | Description |
| --- | --- | --- |
| id | string | The host identifier registered with the controller. |
| nqn | string | The NVMe qualified name of the host. |
| transport_address | string | The transport address of the host. |

interface

The logical interface through which the host is connected.

| Name | Type | Description |
| --- | --- | --- |
| name | string | The name of the logical interface. |
| transport_address | string | The transport address of the logical interface. |
| uuid | string | The unique identifier of the logical interface. |

io_queue

Properties of the I/O queues available to the controller.

| Name | Type | Description |
| --- | --- | --- |
| count | integer | The number of I/O queues available to the controller. |
| depth | array[integer] | The depths of the I/O queues. |

node

| Name | Type | Description |
| --- | --- | --- |
| _links | _links | |
| name | string | |
| uuid | string | |

subsystem

An NVMe subsystem maintains configuration state and NVMe namespace access control for a set of NVMe-connected hosts.

| Name | Type | Description |
| --- | --- | --- |
| _links | _links | |
| name | string | The name of the NVMe subsystem. |
| uuid | string | The unique identifier of the NVMe subsystem. |

svm

SVM, applies only to SVM-scoped objects.

| Name | Type | Description |
| --- | --- | --- |
| _links | _links | |
| name | string | The name of the SVM. This field cannot be specified in a PATCH method. |
| uuid | string | The unique identifier of the SVM. This field cannot be specified in a PATCH method. |

error_arguments

| Name | Type | Description |
| --- | --- | --- |
| code | string | Argument code |
| message | string | Message argument |

returned_error

| Name | Type | Description |
| --- | --- | --- |
| arguments | array[error_arguments] | Message arguments |
| code | string | Error code |
| message | string | Error message |
| target | string | The target parameter that caused the error. |

**Copyright information**

Copyright © 2024 NetApp, Inc. All Rights Reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means—graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system—without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

LIMITED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (b)(3) of the Rights in Technical Data -Noncommercial Items at DFARS 252.227-7013 (FEB 2014) and FAR 52.227-19 (DEC 2007).

Data contained herein pertains to a commercial product and/or commercial service (as defined in FAR 2.101) and is proprietary to NetApp, Inc. All NetApp technical data and computer software provided under this Agreement is commercial in nature and developed solely at private expense. The U.S. Government has a non-exclusive, non-transferrable, nonsublicensable, worldwide, limited irrevocable license to use the Data only in connection with and in support of the U.S. Government contract under which the Data was delivered. Except as provided herein, the Data may not be used, disclosed, reproduced, modified, performed, or displayed without the prior written approval of NetApp, Inc. United States Government license rights for the Department of Defense are limited to those rights identified in DFARS clause 252.227-7015(b) (FEB 2014).

**Trademark information**

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.