# 管理文件锁定

## ONTAP 9

NetApp
March 01, 2022

This PDF was generated from https://docs.netapp.com/zh-cn/ontap/smb-admin/file-locking-between-protocols-concept.html on March 01, 2022. Always check docs.netapp.com for the latest.

# 目录

管理文件锁定 . . . . . 1
关于协议之间的文件锁定 . . . . . 1
ONTAP 如何处理只读位 . . . . . 1
在处理共享路径组件上的锁定时， ONTAP 与 Windows 有何不同 . . . . . 2
显示有关锁定的信息 . . . . . 2
中断锁定 . . . . . 4

# 管理文件锁定

## 关于协议之间的文件锁定

文件锁定是客户端应用程序用来防止用户访问先前由另一用户打开的文件的方法。ONTAP 锁定文件的方式取决于客户端的协议。

如果客户端是 NFS 客户端，则建议锁定；如果客户端是 SMB 客户端，则必须锁定。

由于 NFS 和 SMB 文件锁定之间的差异， NFS 客户端可能无法访问先前由 SMB 应用程序打开的文件。

当 NFS 客户端尝试访问 SMB 应用程序锁定的文件时，会发生以下情况：

- 在混合卷或 NTFS 卷中，文件操作（例如 `rm` ， `rmdir` 和 `mv` ）可以使 NFS 应用程序发生原因失败。
- SMB 拒绝读取和拒绝写入打开模式分别拒绝 NFS 读取和写入操作。
- 如果文件的写入范围使用独占 SMB 字节锁锁定，则 NFS 写入操作将失败。

在 UNIX 安全模式卷中， NFS 取消链接和重命名操作会忽略 SMB 锁定状态并允许访问文件。UNIX 安全模式卷上的所有其他 NFS 操作均遵循 SMB 锁定状态。

## ONTAP 如何处理只读位

只读位会逐个文件进行设置，以反映文件是可写（已禁用）还是只读（已启用）。

使用 Windows 的 SMB 客户端可以设置每个文件的只读位。NFS 客户端不会设置每个文件只读位，因为 NFS 客户端不会执行任何使用每个文件只读位的协议操作。

当使用 Windows 的 SMB 客户端创建文件时， ONTAP 可以在该文件上设置只读位。在 NFS 客户端和 SMB 客户端之间共享文件时， ONTAP 还可以设置只读位。NFS 客户端和 SMB 客户端使用某些软件时，需要启用只读位。

要使 ONTAP 对 NFS 客户端和 SMB 客户端之间共享的文件保持适当的读写权限，它会根据以下规则处理只读位：

- NFS 会将启用了只读位的任何文件视为未启用写入权限位。
- 如果 NFS 客户端禁用了所有写入权限位，并且先前至少启用了其中一个位，则 ONTAP 会为该文件启用只读位。
- 如果 NFS 客户端启用任何写入权限位，则 ONTAP 会禁用该文件的只读位。
- 如果启用了文件的只读位，而 NFS 客户端尝试发现文件的权限，则不会将文件的权限位发送到 NFS 客户端；而 ONTAP 是将权限位发送到 NFS 客户端，并屏蔽写入权限位。
- 如果启用了文件的只读位，而 SMB 客户端禁用了只读位，则 ONTAP 将为此文件启用所有者的写入权限位。
- 启用了只读位的文件只能由 root 用户写入。

对文件权限的更改会立即在 SMB 客户端上生效，但如果 NFS 客户端启用属性缓存，则可能不会立即在 NFS 客户端上生效。

# 在处理共享路径组件上的锁定时， ONTAP 与 Windows 有何不同

## 与 Windows 不同， ONTAP 不会在打开文件时锁定打开文件的路径的每个组件。此行为也会影响 SMB 共享路径。

由于 ONTAP 不会锁定路径的每个组件，因此可以重命名打开的文件或共享上方的路径组件，这可能会导致某些应用程序出现发生原因问题，也可能发生原因会使 SMB 配置中的共享路径无效。这可能发生原因会使此共享无法访问。

为了避免重命名路径组件导致的问题，您可以应用安全设置来防止用户或应用程序重命名关键目录。

# 显示有关锁定的信息

## 您可以显示有关当前文件锁定的信息，包括锁定的锁定类型以及锁定状态，字节范围锁定，共享锁定模式，委派锁定和机会锁定的详细信息，以及锁定是使用持久句柄还是持久句柄打开的。

对于通过 NFSv4 或 NFSv4.1 建立的锁定，无法显示客户端 IP 地址。

默认情况下，命令会显示有关所有锁定的信息。您可以使用命令参数显示有关特定 Storage Virtual Machine （ SVM ）锁定的信息，或者按其他条件筛选命令的输出。

`vserver locks show` 命令可显示有关四种锁定类型的信息：

- 字节范围锁定，仅锁定文件的一部分。
- 共享锁定，用于锁定打开的文件。
- 机会锁，用于控制 SMB 上的客户端缓存。
- 委派，用于通过 NFSv4.x 控制客户端缓存

通过指定可选参数，您可以确定有关每个锁定类型的重要信息。有关详细信息，请参见命令的手册页。

步骤

1. 使用 `vserver locks show` 命令显示有关锁定的信息。

以下示例显示路径为 ` /vol1/file1` 的文件上 NFSv4 锁定的摘要信息。共享锁定访问模式为 write-deny_none ，而锁定是通过写入委派授予的：

```
cluster1::> vserver locks show

Vserver: vs0
Volume  Object Path                LIF         Protocol  Lock Type   Client
------- ------------------------- ----------- --------- -----------
-------
vol1    /vol1/file1               lif1        nfsv4     share-level -
               Sharelock Mode: write-deny_none
                                                         delegation  -
               Delegation Type: write
```

以下示例显示路径为 ` /data2/data2_2/intro pptx` 的文件上有关 SMB 锁定的详细机会锁和共享锁定信息。对于 IP 地址为 10.3.1.3 的客户端，共享锁定访问模式为 write-deny_none 的文件会授予持久句柄。租用机会锁会授予批量机会锁级别：

```
cluster1::> vserver locks show -instance -path /data2/data2_2/intro.pptx

                    Vserver: vs1
                     Volume: data2_2
         Logical Interface: lif2
               Object Path: /data2/data2_2/intro.pptx
                 Lock UUID: 553cf484-7030-4998-88d3-1125adbba0b7
             Lock Protocol: cifs
                 Lock Type: share-level
   Node Holding Lock State: node3
                Lock State: granted
  Bytelock Starting Offset: -
    Number of Bytes Locked: -
     Bytelock is Mandatory: -
     Bytelock is Exclusive: -
     Bytelock is Superlock: -
          Bytelock is Soft: -
              Oplock Level: -
   Shared Lock Access Mode: write-deny_none
       Shared Lock is Soft: false
           Delegation Type: -
            Client Address: 10.3.1.3
             SMB Open Type: durable
         SMB Connect State: connected
SMB Expiration Time (Secs): -
         SMB Open Group ID:
78a90c59d45ae211998100059a3c7a00a007f70da0f8ffffcd445b0300000000

                    Vserver: vs1
                     Volume: data2_2
```

```
          Logical Interface: lif2
                Object Path: /data2/data2_2/test.pptx
                  Lock UUID: 302fd7b1-f7bf-47ae-9981-f0dcb6a224f9
             Lock Protocol: cifs
                 Lock Type: op-lock
    Node Holding Lock State: node3
                  Lock State: granted
   Bytelock Starting Offset: -
     Number of Bytes Locked: -
      Bytelock is Mandatory: -
      Bytelock is Exclusive: -
      Bytelock is Superlock: -
           Bytelock is Soft: -
               Oplock Level: batch
    Shared Lock Access Mode: -
        Shared Lock is Soft: -
            Delegation Type: -
             Client Address: 10.3.1.3
              SMB Open Type: -
          SMB Connect State: connected
 SMB Expiration Time (Secs): -
          SMB Open Group ID:
78a90c59d45ae211998100059a3c7a00a007f70da0f8ffffcd445b0300000000
```

# 中断锁定

当文件锁定阻止客户端访问文件时，您可以显示有关当前持有的锁定的信息，然后中断特定锁定。可能需要中断锁定的情形示例包括调试应用程序。

`vserver locks break` 命令只能在高级权限级别及更高权限级别下使用。命令的手册页包含详细信息。

步骤

1. 要查找中断锁定所需的信息，请使用 `vserver locks show` 命令。

   命令的手册页包含详细信息。

2. 将权限级别设置为 advanced： `set -privilege advanced`
3. 执行以下操作之一：

| 如果要通过指定 ... 来中断锁定 | 输入命令 ... |
| --- | --- |
| SVM 名称，卷名称， LIF 名称和文件路径 | `vserver locks break -vserver vserver_name -volume volume_name -path path -lif lif` |

| 如果要通过指定 ... 来中断锁定 | 输入命令 ... |
| --- | --- |
| 锁定 ID | `vserver locks break -lockid UUID` |

4. 返回到管理权限级别： `set -privilege admin`

**Copyright Information**

Copyright © 2022 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

**Trademark Information**

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.