Repository error messages

Snap Creator Framework

Aksel Davis, Zachary Wambold
January 19, 2021

This PDF was generated from https://docs.netapp.com/us-en/snap-creator-framework/administration/reference_repository_error_messages.html on August 04, 2021. Always check docs.netapp.com for the latest.

Table of Contents

Repository error messages 1

Repository error messages

The following table lists the Repository error messages.

Error code	Error message	Description/resolution
REPO-01001	Global configuration does not exist	Check if the global.conf file exists in the configs folder.
REPO-01002	Global configuration already exists	The global.conf file already exists in the configs folder. Either delete the global configuration file first or update the existing file.
REPO-01103	Creating global configuration failed with error [%s]	Failed to create the global.conf file in the configs folder. Check the permissions of the user running Snap Creator against directory.
REPO-01203	Updating global configuration failed with error [%s]	Failed to update the global.conf file in the configs folder. Check the permissions of user running Snap Creator against directory.
REPO-01303	Removing global configuration failed with error [%s]	Failed to remove global.conf file in the configs folder. Check if the file is present in configs folder or check permissions of user running Snap Creator against directory
REPO-01403	Exporting global configuration failed with error [%s]	Failed to read global.conf file in the configs folder. Check if your global configuration file is deleted.
REPO-01503	Importing global configuration [%s] failed with error [%s]	Failed to update the global.conf file in the configs folder. Check permissions of user running Snap Creator against directory.
REPO-01603	Retrieving global configuration failed with error [%s]	Failed to read global.conf file in the configs folder. Check if your global configuration file is deleted.
REPO-02002	Profile [%s] already exists, use a different name.	Profile with same name already exists. If the profile is not visible, then the user does not have permission on this profile.

Error code	Error message	Description/resolution
REPO-02003	Profile [%s] does not exist	Check if your profile is renamed or deleted. Also, the user might not have permission on this profile.
REPO-02103	Creating global profile configuration [%s] failed with error [%s]	Failed to create global.conf file in the profile. Check permissions of user running Snap Creator against directory.
REPO-02106	Creating profile configuration [%s] failed with error [%s]	Failed to create profile in the configs folder. Check permissions of user running Snap Creator against directory.
REPO-02203	Updating profile configuration [%s] failed with error [%s]	Failed to update the profile in the configs folder. Check permissions of user running Snap Creator against directory.
REPO-02213	Renaming profile [%s] to [%s] failed with error [%s]	Failed to rename profile in the configs folder. Check permissions of user running Snap Creator against directory or check if your profile is already renamed or deleted.
REPO-02303	Removing profile configuration [%s] failed	
REPO-02403	Exporting profile configuration [%s] failed with error [%s]	
REPO-02503	Importing profile configuration [%s] failed with error [%s]	
REPO-02603	Retrieving global profile failed with error [%s]	
REPO-02606	Retrieving profile [%s] failed with error [%s]	
REPO-02703	Listing profiles failed with error [%s]	Listing profiles failed. Check the configs folder path.
REPO-03002	Configuration [%s] already exists for profile [%s]	Configuration file with same name already exists for the given profile. Choose a different name.

Error code	Error message	Description/resolution
REPO-03103	Creating configuration [%s] for profile [%s] failed with error [%s]	
REPO-03203	Updating configuration [%s] for profile [%s] failed with error [%s]	
REPO-03212	Renaming configuration [%s] for profile [%s] to [%s] failed	Failed to rename the configuration from profile. Check if your configuration is renamed or deleted and also check permissions of user running Snap Creator against directory.
REPO-03303	Removing configuration [%s] from profile [%s] failed	Failed to delete configuration from profile in the configs folder. Check permissions of user running Snap Creator against directory.
REPO-03403	Exporting configuration [%s] for profile [%s] failed with error [%s]	
REPO-03503	Importing configuration [%s] to profile [%s] failed with error [%s]	
REPO-03603	Retrieving configuration [%s] from profile [%s] failed with error [%s]	
REPO-03703	Listing configurations from profile [%s] failed with error [%s]	
REPO-04003	Reading catalog for profile [%s], configuration [%s] and timestamp [%s] failed with error [%s]	
REPO-04103	Writing catalog for profile [%s], configuration [%s] and timestamp [%s] failed with error [%s]	
REPO-04203	Purging catalog for profile [%s], configuration [%s] and timestamp [%s] failed with error [%s]	
REPO-04303	Inventoring catalog for profile [%s] and configuration [%s] failed with error [%s]	
REPO-04304	Configuration [%s] does not exist	

Error code	Error message	Description/resolution
REPO-04309	Adding policy object failed [%s]	Database error; check stack trace for more information.
REPO-04313	Removing policy object failed for policy Id: %s	Database error; check stack trace for more information.
REPO-04315	Updating policy object failed : %s	Database error; check stack trace for more information.
REPO-04316	Failed to list policies	Database error; check stack trace for more information.
REPO-04321	Adding backup type object failed [%s]	Database error; check stack trace for more information.
REPO-04323	Backup type entry does not exist for backup type id: %s	Pass a valid backup type.
REPO-04325	Removing backup type object failed for backup type Id: %s	Database error; check stack trace for more information.
REPO-04327	Updating backup type object failed : %s	Database error; check stack trace for more information.
REPO-04328	Failed to list backup types	Database error; check stack trace for more information.
REPO-04333	Adding scheduler job object failed [%s]	Database error; check stack trace for more information.
REPO-04335	Scheduler job entry does not exist for job id: %s	Pass a valid scheduler job.
REPO-04337	Removing scheduler job object failed for job Id: %s	Database error; check stack trace for more information.
REPO-04339	Updating scheduler job object failed : %s	Database error; check stack trace for more information.
REPO-04340	Failed to list scheduler jobs	Database error; check stack trace for more information.
REPO-04341	Adding policy object failed, policy [%s] with same name already exists	Policy with same name already exists; try with different name.

Error code	Error message	Description/resolution
REPO-04342	Adding backup type object failed, backup type [%s] with same name already exists	Backup type with same name already exists; try with different name.
REPO-04343	Adding scheduler object failed, scheduler [%s] with same task name already exists	
REPO-04344	Failed to update profile [%s]. Profile is empty.	
REPO-04345	Policy Type cannot be null while adding new policy	
REPO-04346	Storage object cannot be null	
REPO-04347	Adding storage object failed, storage [%s] with same name/IP already exists	
REPO-04348	Failed to fetch the storage details. Database Error!	
REPO-04349	Invalid host name. Storage with the host name/IP [%s] does not exist	
REPO-04350	Hostname cannot be null	Invalid host name
REPO-04351	Deleting storage [%s] failed with error [%s]	Failed to delete the storage. Database Error!
REPO-04355	Updating storage [%s] failed with error [%s]	Failed to update the storage. Database Error!
REPO-04356	Cluster object cannot be null	
REPO-04358	Adding storage [%s] failed with error [%s]	
REPO-04359	Updating cluster [%s] failed with error [%s]	
REPO-04360	Adding cluster object failed, cluster [%s] with same name/IP already exists	Cluster with same host name already exists

Copyright Information

Copyright © 2021 NetApp, Inc. All rights reserved. Printed in the U.S. No part of this document covered by copyright may be reproduced in any form or by any means-graphic, electronic, or mechanical, including photocopying, recording, taping, or storage in an electronic retrieval system- without prior written permission of the copyright owner.

Software derived from copyrighted NetApp material is subject to the following license and disclaimer:

THIS SOFTWARE IS PROVIDED BY NETAPP “AS IS” AND WITHOUT ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE, WHICH ARE HEREBY DISCLAIMED. IN NO EVENT SHALL NETAPP BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA, OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

NetApp reserves the right to change any products described herein at any time, and without notice. NetApp assumes no responsibility or liability arising from the use of products described herein, except as expressly agreed to in writing by NetApp. The use or purchase of this product does not convey a license under any patent rights, trademark rights, or any other intellectual property rights of NetApp.

The product described in this manual may be protected by one or more U.S. patents, foreign patents, or pending applications.

RESTRICTED RIGHTS LEGEND: Use, duplication, or disclosure by the government is subject to restrictions as set forth in subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause at DFARS 252.277-7103 (October 1988) and FAR 52-227-19 (June 1987).

Trademark Information

NETAPP, the NETAPP logo, and the marks listed at http://www.netapp.com/TM are trademarks of NetApp, Inc. Other company and product names may be trademarks of their respective owners.