

Day 2 Install Team — Field Guide

Describes Lumina app version 2.5.10+89.

Audience: Install techs running the Day 2 LED installation on a Lumina job.

Log in, read the blueprint, put up the strip, walk the customer through wrap-up, close the job. Day 2 is the last mile — get it right and the customer is live the same day.

What you'll need

- Your 4-digit **Installer PIN** (dealer code + installer code)
 - The Lumina app on your phone
 - All materials from the Day 2 list — LED strip, mounting clips, brackets, connectors
 - Your install tools
 - Phone signal or Wi-Fi at the job site (required for check-offs, photo uploads, account creation)
-

1. Log in

Day 2 happens inside **Installer Mode**, gated by a 4-digit PIN.

PIN format

- Digits 1–2: dealer code (e.g., 42)
- Digits 3–4: installer code (e.g., 07)
- Together: 4207

You got this from your dealer admin at onboarding.

Steps

1. Open the Lumina app
2. Tap the **Lumina logo** 5 times on the login screen — **all five taps within 3 seconds**, or the count resets.
There's no visual feedback until the Staff PIN screen opens on tap 5.
3. Type your 4-digit PIN

Session timeout

- Sessions run **30 minutes** of activity
 - Warning pops **5 minutes before** timeout — tap to extend
 - Your work is always saved. If you get logged out, sign back in.
-

2. Open the Day 2 Queue

From the **Installer Landing** screen, tap **Day 2 Queue**.

What's in it

Every job for your dealer that's had Day 1 completed and is ready for installation:

- **Pre-wire complete** (amber badge) — wiring done, Day 2 not scheduled yet
- **Install scheduled** (green badge) — Day 2 date locked in

Card fields

Element	Meaning
Customer name	Who the job is for
Address	Full street, city, state, zip
Status badge	Amber = Pre-wire complete, green = Install scheduled
Day 2: {date}	Shown only if scheduled
Reschedule	Inline button next to the date
Schedule Day 2	Shown only if not yet scheduled

3. Schedule Day 2

For any **Pre-wire complete** job, tap **Schedule Day 2**.

1. Pick a date. Earliest = the day Day 1 was completed. Latest = 365 days out.
2. Tap **OK**.
3. Snackbar: "**Day 2 scheduled for {date}**".

Job moves from **Pre-wire complete** to **Install scheduled**. Customer gets an SMS confirming the install date. Reminder SMS goes out the night before.

4. The Day 2 Blueprint

Tap any job card to open the **Day 2 Blueprint**.

Different from Day 1

If you've worked Day 1 before, familiar but with key differences:

Element	Day 1	Day 2
Channel cards	Wiring tasks	Install tasks with " Wiring complete ✓ " badge
Run direction	Listed	Front and center as a direction instruction box
Materials	Power + Hardware	Strip + Hardware only — no power supplies, no wire
Tasks	Run wire, cap injections	Install strip, connect injections, power on, capture photos

"Wiring complete" badge

Green **Wiring complete ✓** badge at the top of every channel detail card. The Day 1 electrician has confirmed every wire for that channel is in place and accessible. You should find each wire end exactly where the blueprint says.

Run direction instruction

Each channel has a clear instruction box:

"Feed strip {direction} starting at {start description}. Run is {feet}ft."

Example:

"Feed strip left to right starting at left corner of house, ground level. Run is 120ft. Injection points at 60ft."

Tells you:

- Which physical end to start at
- Which direction to roll the strip
- How long the run is
- Where injection points are (so you plug in as you pass each one)

Materials list

Day 2 materials card shows only:

- **STRIP** — LED strip broken down by channel
- **HARDWARE** — mounting clips, brackets, connectors

Arrive with everything on this list. Short on anything? Call your dealer admin before you arrive.

Task checklist

Same checkbox interface as Day 1, with Day 2 tasks:

- **Per channel:** "Install {label} strip — feed {direction}, {feet}ft"
- **Per injection point:** "Connect injection at {location}"
- **Plug in controller** (or "at {mount location}")
- **Power on and verify all channels respond**
- **Per channel:** "Capture completion photo for {label}"

Tap each box as you complete. Progress bar shows X of N tasks complete.

5. Install sequence

Typical Day 2:

1. **Arrive on-site** and greet the customer. Confirm gate codes and any access notes from the salesperson.
2. **Walk the perimeter** with the blueprint open. Find each channel's start and end. Locate every Day 1 wire (controller wire, injection wires).
3. **Install the strip** for each channel, feeding in the direction the blueprint specifies. Connect at injection points as you pass them.
4. **Plug in the controller.** All channels should illuminate.
5. **Power on and verify** every channel responds — turn each on/off, change colors, confirm no dark spots or color shifts.
6. **Capture a completion photo** for each channel. Wrap-up requires these.
7. **Check off every task** as you go.

When all tasks are checked, the bottom button changes to **Wrap up install** → (green). Tap it to start wrap-up.

6. Wrap-up — the most important part

The 4-step wizard that closes the job, hands the system to the customer, and fires all the final automated communications. A step indicator at the top shows where you are.

Step 1 — Install photos

Required: one completion photo per channel.

Why: proof of work and quality record. Corporate uses them for warranty claims and dealer audits.

Steps:

1. Row per channel (e.g., "Front Roofline", "Garage", "Side Accent")
2. For each row, tap the camera icon and capture a photo showing the installed strip lit up at night or in shadow so the LEDs are visible
3. After capturing, the row shows a thumbnail. Tap the row again to retake.
4. **Continue** → is disabled until every channel has a photo

You can't proceed past Step 1 without a photo for every channel.

Step 2 — Material check-in

What it asks for: how much of each material was actually used vs. how much you brought.

Why it matters: feeds the dealer's **Waste Intelligence** dashboard. Over time, it tells your dealer how accurate estimates are and where waste happens — so the dealer orders smarter and reduces shrinkage.

Steps:

1. Table of materials from the original estimate
2. **Estimated qty** is shown (read-only) for each material
3. In **Quantity Returned**, type how many units you're bringing back unused
4. App auto-calculates **Used = Estimated – Returned** and displays the **waste %**

Example:

- Estimated: 200 ft of 14/2 wire
- Returned: 15 ft
- Used: 185 ft
- Waste: 7.5%

Be honest. Under-reporting returns inflates "used" numbers and corrupts waste data. Over-reporting hides actual waste and doesn't fix underlying problems.

If you're not returning anything for an item, leave the field blank or enter **0**.

Tap **Continue** → when done.

Step 3 — Customer account

What it does: creates the customer's Lumina account so they can control their lights.

Why it's critical: the customer can't use the lights until they have an account. This step creates the account, sends the password-reset email, and prepares the handoff.

Steps:

1. Fields pre-filled from the prospect record:
 - **First Name**
 - **Last Name**
 - **Email**
 - **Phone** (display only)
2. Verify each field with the customer. Confirm the email — this is where their login link goes.
3. Tap **Create account**.

4. The app creates the user, generates a password-reset link, and sends the customer a welcome email titled "**Set up your Nex-Gen LED Lumina account**" with the reset link and app download links.
5. On success, the screen shows "**Account created for {email}**" and the button changes to **Re-send invite** (in case the customer never receives the email).

If creation fails:

- Check the email format and try again.
- If it still fails, complete the rest of the wrap-up — Step 4 still lets you close the job. Note the failure and contact your dealer admin so they can manually provision the account.

Creating the account does NOT link their controllers. A green "Account created" is not a finished handoff — the customer can sign in and see nothing. Controllers are linked in Step 4's Controller Setup. Do not skip Step 4 on the assumption that Step 3 finished the job.

Don't tap Create account twice. If the button seems slow, wait. A double-tap has produced two identical installation records seconds apart, only one of which the customer's account points at — leaving an orphan record carrying a full copy of their personal details. If you think you may have double-tapped, tell your dealer admin so it can be cleaned up.

Tap **Continue** → when done.

Step 4 — Launch setup for the customer (optional, recommended)

What it does: walks the customer through the in-app first-time setup so they can pair with the controller and learn the basics.

Optional but **highly recommended** — cuts support calls in the first 48 hours dramatically.

Steps:

1. After Step 3 succeeds, you'll see **Launch Lumina setup**
2. Tap it. The app pivots into the **Installer Setup Wizard** with customer info pre-loaded.
3. Hand the device to the customer (or sit with them).
4. Walk them through:
 - **Customer Info** confirmation
 - **Controller Setup** — pair the controller with their network
 - **Zone Configuration** — name their zones if needed
 - **Handoff** — final transfer of ownership

Re-using a controller from another install? A controller must belong to exactly one customer, but nothing in the app enforces it — claiming a controller that's still linked to a previous customer silently gives it two owners, and both accounts then disagree about its LED count and IP. If this controller has been installed anywhere before, have your dealer admin unlink it from the old account *before* you claim it here.

5. When done, you're back on the wrap-up screen.

Coach the customer through the basics before you leave:

- How to turn lights on/off from the home screen
- How to pick a color or pattern
- How to set a schedule
- The lights will run automatically at dusk to dawn

Step 5 — Close the job

What it does: marks the job as **Install complete** and triggers the final customer email.

Steps:

1. Summary card lists:
 - X channel photos captured
 - X items checked in
 - Customer account created (checkmark)
 2. Tap **Finish & Close Job** (green)
 3. Confirmation dialog appears with totals
 4. Tap **Confirm**
 5. The app:
 - Moves the job status to **Install complete**
 - Records you as the Day 2 tech
 - Saves the completion timestamp
 - Triggers the customer's "**Your Nex-Gen LED system is live!**" email with app download links
 6. You're back in the Day 2 Queue. Job is closed and gone.
-

7. What the customer gets after Install Complete

1. "**Your Nex-Gen LED system is live!**" email with:
 - Confirmation the system is installed
 - Download buttons for Lumina (iPhone + Android)
 - A pointer to the account setup email from Step 3
 - Welcome message from your dealer
2. **The account setup email** (sent earlier in Step 3) titled "**Set up your Nex-Gen LED Lumina account**":
 - Password reset link
 - Download links for Lumina

Customer should be fully self-sufficient at this point.

8. Recording returns (Step 2)

The app expects the **quantity returned**, not the quantity used. "Used" is computed automatically.

Why it matters

Waste Intelligence uses this data to:

- Identify materials that are consistently overbought
- Spot installers who are wasteful or efficient
- Tune future estimates so the dealer doesn't tie up cash in unnecessary inventory

Tips for accurate check-in

- **Count the actual returns** — don't estimate
 - **Record returns as decimals** when needed (e.g., 12.5 ft of wire)
 - **Don't pad the numbers** — the long-term value depends on every install being honest
 - **If you used more than estimated**, leave returned at 0 and flag it to your dealer admin so they can adjust the estimate template
-

9. Critical Day 2 rules

Rule	Why it matters
Capture a completion photo for every channel.	Required for warranty and audit. Step 1 won't let you proceed without them.
Verify every channel powers on before wrap-up.	A dead channel after the customer is unhappy costs 10× what fixing it now costs.
Be accurate in material check-in.	Bad data corrupts waste tracking and inventory ordering.
Confirm the customer's email before creating their account.	A typo means they won't get the password setup email.
Walk the customer through the basics.	5 minutes of training prevents 30 minutes of support calls.
Always close the job through Step 4.	Skip it and the customer never gets the welcome email and never gets their account.

What success looks like

- Every channel lit, no dark spots, no color shifts
- Completion photo captured for every channel
- Material check-in numbers entered accurately
- Customer account created; "Account created for {email}" confirmation showing
- Customer walked through basics — they've turned lights on, changed a color, saved a favorite
- **Finish & Close Job** tapped; job moved out of your queue
- Customer has received both the account setup email and the "Your system is live!" email

If something isn't working

"A channel is dead after I plug in the controller." Stop. Find the wire feeding that channel and the injection wires. Verify Day 1 ran wire all the way to the strip end. If wires are missing or buried in walls, the job is not Day 2 ready — call your dealer admin.

"Customer account creation fails with 'Email already exists'." The customer has a Lumina account from a previous install. Tap **Re-send invite** to send a fresh password link. If they don't recognize the existing account, contact your dealer admin to investigate.

"I forgot to take a completion photo before leaving." Step 1 requires every photo. Either return to the site or take a photo from a different angle that still shows the lights. Don't skip it.

"The Day 1 wires aren't where the blueprint says." Day 1 issue — electrician didn't leave wires accessible. Document the problem, call your dealer admin, reschedule. Don't cut into walls to install.

"I'm partway through wrap-up and need to leave." Wrap-up doesn't auto-save between steps the way the blueprint does. If you abandon mid-wrap-up, you'll need to redo steps when you return. **Do not** mark the job complete until everything is actually done.

"The customer's email is wrong and they've already left." Complete the rest of wrap-up. Contact your dealer admin to update the email and re-trigger account creation.

"PIN won't work." Confirm all 4 digits. If locked out after 5 failed attempts, wait 30 seconds or dismiss and reopen the Staff PIN screen. Still blocked? Your dealer admin needs to confirm your installer account is active.

Need help? Call your dealer admin or your Nex-Gen LED LLC corporate contact.

Describes Lumina app version 2.5.10+89 — August 2026