Ring and case: every conductor, one line each (from design/wiring/product-wiring.csv, 67 lines)

drawn and routed · specified and landed · drawn, not routed · stated in text only · not drawn

R3 joystick switch lines (FLEX1) (ends also in R1) 10 lines

FLEX1	BTN_REC (via land J_BAND_A:5)	W010 FLEX1 13.302-15.235 mm	SW2.3 BTN_REC	FLEX1
off board SW1, SW3, SW4, SW5	SW1.1 JOY_UP	W006 inside the switch	SW1.3 JOY_UP	off board
	SW3.1 JOY_DOWN	W007 inside the switch	SW3.3 JOY_DOWN	
	SW4.1 JOY_LEFT	W008 inside the switch	SW4.3 JOY_LEFT	
	SW5.1 JOY_RIGHT	W009 inside the switch	SW5.3 JOY_RIGHT	
ring main board J_BAND_A	J_BAND_A.1 JOY_UP	W001 FLEX1 11.577-13.519 mm	SW1.3 JOY_UP	FLEX1 SW1, SW3, SW4, SW5, SW2
	J_BAND_A.2 JOY_DOWN	W002 FLEX1 20.219-22.164 mm	SW3.3 JOY_DOWN	
	J_BAND_A.3 JOY_LEFT	W003 FLEX1 14.569-16.513 mm	SW4.3 JOY_LEFT	
	J_BAND_A.4 JOY_RIGHT	W004 FLEX1 15.815-17.758 mm	SW5.3 JOY_RIGHT	
	J_BAND_A.5 BTN_REC	W005 FLEX1 12.552-14.485 mm	SW2.1 BTN_REC	

R4 joystick switch grounds (FLEX1) (ends also in R1) 10 lines

FLEX1	GND (via land J_BAND_A:6)	W016 FLEX1 18.385-20.328 mm	SW1.4 GND	FLEX1 SW1, SW2, SW3, SW5
	GND (via land J_BAND_A:6)	W017 FLEX1 16.735-18.678 mm	SW2.2 GND	
	GND (via land J_BAND_A:6)	W018 FLEX1 16.735-18.678 mm	SW2.4 GND	
	GND (via land J_BAND_A:6)	W019 FLEX1 17.985-19.928 mm	SW3.4 GND	
	GND (via land J_BAND_A:6)	W020 FLEX1 18.385-20.328 mm	SW5.4 GND	
off board SW1, SW3, SW4, SW5	SW1.2 GND	W012 inside the switch	SW1.4 GND	off board
	SW3.2 GND	W013 inside the switch	SW3.4 GND	
	SW4.2 GND	W014 inside the switch	SW4.4 GND	
	SW5.2 GND	W015 inside the switch	SW5.4 GND	
ring main board	J_BAND_A.8 GND	W011 FLEX1 11.685-13.628 mm	SW4.4 GND	FLEX1

R5 motor M1: FLEX1 lines and motor leads (ends also in R1) 4 lines

motor M1 M1	M1.1 VMOT	W023 red lead wire AWG32 of the motor, cut 1.07-1.44 mm	M1.1 VMOT	FLEX1 M1
	M1.2 GND	W024 blue lead wire AWG32 of the motor, cut 1.07-1.44 mm	M1.2 GND	
ring main board J_BAND_A	J_BAND_A.6 GND	W021 FLEX1 7.786-8.980 mm	M1.2 GND	
	J_BAND_A.7 VMOT	W022 FLEX1 5.737-6.931 mm	M1.1 VMOT	

R6 cell lines on FLEX2 (to the PRT1 tab lands) (ends also in R2) 2 lines

ring main board J_BAND_B	J_BAND_B.1 VBAT	W025 FLEX2 5.995-6.799 mm	PRT1.1 VBAT	FLEX2 PRT1
	J_BAND_B.2 GND	W026 FLEX2 7.233-8.037 mm	PRT1.2 GND	

R7 thermistor line on FLEX2 (ends also in R2) 1 line

ring main board	J_BAND_B.3 NTC	W027 FLEX2 6.505-7.310 mm	PRT1.3 NTC	FLEX2

R8 thermistor ground on the PRT1 board (ends also in R10) 1 line

cell pack BT1 + PRT1 + RT1,	RT1.2 GND	W028 inside the cell pack	BT1.2 GND	inside the pack

R9 charging pads CP1 to CP4 on FLEX2 (ends also in R2) 4 lines

ring main board J_BAND_B	J_BAND_B.4 VBUS	W029 FLEX2 23.182-30.514 mm	CP1.1 VBUS	FLEX2 CP1, CP2, CP3, CP4
	J_BAND_B.5 USB_DN	W030 FLEX2 25.946-33.269 mm	CP2.1 USB_DN	
	J_BAND_B.6 USB_DP	W031 FLEX2 28.704-36.018 mm	CP3.1 USB_DP	
	J_BAND_B.7 GND	W032 FLEX2 32.860-40.165 mm	CP4.1 GND	

R10 cell protection circuit PRT1: output tabs (ends also in R6, R7) 3 lines

cell pack BT1 + PRT1 + RT1, one purchased part BT1, RT1	BT1.1 VBAT	W033 PRT1 tab (nickel strip)	PRT1.1 VBAT	FLEX2 PRT1
	BT1.2 GND	W034 PRT1 tab (nickel strip)	PRT1.2 GND	
	RT1.1 NTC	W035 PRT1 tab (nickel strip)	PRT1.3 NTC	

R11 antenna feed (main board copper) 1 line

ring main board	ANT1.1 RF_FEED	W036 main board copper	RF_FEED (C13:1 L4:2)	ring main board

R12 antenna ground and trim terminals 3 lines

ring main board ANT1	ANT1.2 ANT_TRIM	W037 main board copper	ANT_TRIM (LT1:1)	ring main board
	ANT1.3 ANT_TRIM	W038 main board copper	ANT_TRIM (LT1:1)	
	ANT1.4 GND	W039 main board copper	GND (ground)	

R13 screen cable into J1 14 lines

screen DISP1 DISP1	DISP1.1 ELVSS	W040 screen's own cable, contact 1	J1.1 ELVSS	ring main board J1
	DISP1.10 LCD_SCK	W041 screen's own cable, contact 10	J1.10 LCD_SCK	
	DISP1.11 LCD_DCX	W042 screen's own cable, contact 11	J1.11 LCD_DCX	
	DISP1.12 LCD_MOSI	W043 screen's own cable, contact 12	J1.12 LCD_MOSI	
	DISP1.13 GND	W044 screen's own cable, contact 13	J1.13 GND	
	DISP1.14 GND	W045 screen's own cable, contact 14	J1.14 GND	
	DISP1.15 GND	W046 screen's own cable, contact 15	J1.15 GND	
	DISP1.2 ELVDD	W047 screen's own cable, contact 2	J1.2 ELVDD	
	DISP1.4 VDD_3V0	W048 screen's own cable, contact 4	J1.4 VDD_3V0	
	DISP1.5 VDD_1V8	W049 screen's own cable, contact 5	J1.5 VDD_1V8	
	DISP1.6 SWIRE	W050 screen's own cable, contact 6	J1.6 SWIRE	
	DISP1.7 LCD_TE	W051 screen's own cable, contact 7	J1.7 LCD_TE	
	DISP1.8 LCD_RST	W052 screen's own cable, contact 8	J1.8 LCD_RST	
	DISP1.9 LCD_CS	W053 screen's own cable, contact 9	J1.9 LCD_CS	

R15 ring pads to case spring pins P1 to P4 (ends also in C4, R9) 4 lines

FLEX2 CP1, CP2, CP3, CP4	CP1.1 VBUS	W054 spring pin (pressed)	P1.1 VRING	case pin board PCB2 P1, P2, P3, P4
	CP2.1 USB_DN	W055 spring pin (pressed)	P2.1 USB_D-	
	CP3.1 USB_DP	W056 spring pin (pressed)	P3.1 USB_D+	
	CP4.1 GND	W057 spring pin (pressed)	P4.1 GND	

C1 case cell lead + 1 line

case cell BT1	BT1.1 BAT	W059 cell's own flying lead (red +), cut 13.0 mm	W5.1 BAT	case main board PCB1

C2 case cell lead - 1 line

case cell BT1	BT1.2 GND	W060 cell's own flying lead (black -), cut 15.2 mm	W6.1 GND	case main board PCB1

C3 case thermistor TH1 leads 2 lines

thermistor on the cell face TH1	TH1.1 TS	W061 thermistor's own lead, bare, no polarity, cut 10 mm	TH1.1 TS	case main board PCB1 TH1
	TH1.2 GND	W062 thermistor's own lead, bare, no polarity, cut 10 mm	TH1.2 GND	

C5 case wires pin board to main board 5 lines

case pin board PCB2 WP1, WP2, WP3, WP4, WP7	WP1.1 VRING	W063 wire 30 AWG stranded, red insulation, cut 15.6 mm	W1.1 VRING	case main board PCB1 W1, W2, W3, W4, W7
	WP2.1 USB_D-	W064 wire 30 AWG stranded, white insulation, cut 16.3 mm	W2.1 USB_D-	
	WP3.1 USB_D+	W065 wire 30 AWG stranded, green insulation, cut 16.3 mm	W3.1 USB_D+	
	WP4.1 GND	W066 wire 30 AWG stranded, black insulation, cut 15.6 mm	W4.1 GND	
	WP7.1 RING_TOUCH	W067 wire 30 AWG stranded, yellow insulation, cut 15.9 mm	W7.1 RING_TOUCH	

SENSING GAP, NO CONDUCTOR (counted apart from the conductors): R16 band metal to case touch electrode E1 (no conductor) 1 line

ring band metal, no file holds	band metal (no terminal)	W058 no conductor, gap 2.28-2.42 mm	E1.1 RING_TOUCH	case pin board PCB2

Line style = state of the line in the csv (column state). Copper lengths are the shortest copper path pad to pad in the band boards (smallest to largest over US 7 to 13); cut lengths are the lead or wire cut length (smallest to largest over US 7 to 13). Made by design/wiring/draw_wiring.py.