

5. A. Pogiatis and G. Samakovitis (2021). "An Event-Driven Serverless ETL Pipeline on AWS" Applied Sciences 11, no. 1: 191
6. I. Fé, R. Matos, J. Dantas, C. Melo, T. A. Nguyen, D. Min, E. Choi, F. A. Silva, and P. R. M. Maciel (2022). "Performance-Cost Trade-Off in Auto-Scaling Mechanisms for Cloud Computing" Sensors 22, no. 3: 1221
7. Сайт Google Trends <https://trends.google.com/trends/>
8. Сайт Amazon Web Services <https://aws.amazon.com>

Raximov B.N.

Rector of the Military Institute of Information and Communication Technologies and Communication, Professor, DSc.

Berdiyev A.A.

PhD, Head of the Department of "Teleradiobroadcasting systems", TUIT named after Muhammad al-Khwarizmi

Khudayberganov J.D.

PhD student of the Department of "Teleradiobroadcasting systems", TUIT named after Muhammad al-Khwarizmi

IMPLEMENTATION OF ADAPTIVE NOISE REDUCTION FILTERS BASED ON MATLAB

Рахимов Бахтиёржон Негматович

Ректор Военного института информационно-коммуникационных технологий и связи, профессор. доктор технических наук

Худайбергенов Журабек Давлатбоевич

Докторант кафедры "Системы телерадиовещания" ТУИТ имени Мухаммада аль-Хоразмий

Бердиев Алишер Аликулович

PhD, заведующий кафедрой "Системы телерадиовещания" ТУИТ имени Мухаммада аль-Хоразмий

РЕАЛИЗАЦИЯ АДАПТИВНЫХ ФИЛЬТРОВ ШУМОПОДАВЛЕНИЯ НА БАЗЕ MATLAB.

DOI: 10.31618/ESSA.2782-1994.2024.1.101.4671

Summary: This study explores the implementation of adaptive noise reduction filters using Matlab, focusing on the Least Mean Squares (LMS), Normalized Least Mean Squares (NLMS), and Recursive Least Squares (RLS) algorithms. These adaptive filters are pivotal in improving speech signal clarity in telecommunication systems by dynamically reducing background noise. Through real-time audio signal processing tests, we assess the effectiveness of each algorithm based on the Signal-to-Noise Ratio (SNR) improvements and compare their performance against established benchmarks. The findings highlight significant enhancements in speech quality, providing a comparative analysis that aids in selecting the optimal filtering approach for various telecommunication applications.

Аннотация: В этом исследовании рассматривается реализация адаптивных фильтров шумоподавления с использованием Matlab с упором на алгоритмы наименьших средних квадратов (LMS), нормализованных наименьших средних квадратов (NLMS) и рекурсивных алгоритмов наименьших квадратов (RLS). Эти адаптивные фильтры играют решающую роль в улучшении четкости речевого сигнала в телекоммуникационных системах за счет динамического снижения фонового шума. Посредством тестов обработки аудиосигнала в реальном времени мы оцениваем эффективность каждого алгоритма на основе улучшения отношения сигнал/шум (SNR) и сравниваем их производительность с установленными стандартами. Результаты подчеркивают значительное улучшение качества речи, обеспечивая сравнительный анализ, который помогает выбрать оптимальный подход к фильтрации для различных телекоммуникационных приложений.

Keywords: Adaptive Filters, Audio Signal Processing, LMS, NLMS, RLS, MSE, NMSE, PSNR, IIC, eNMLS, VoIP, Kalman filter.

Ключевые слова: адаптивные фильтры, обработка аудиосигнала, LMS, NLMS, RLS, MSE, NMSE, PSNR, IIC, eNMLS, VoIP, фильтр Калмана.

Introduction

Speech signal quality in telecommunications is pivotal for ensuring clear and effective communication. Factors that influence speech quality include bandwidth, noise, echo, and codec performance. Bandwidth constraints can limit the frequency range of

the transmitted speech, reducing clarity. Noise from various sources degrades the intelligibility of the speech, necessitating the use of noise reduction technologies. Echo, particularly in VoIP and conferencing systems, can cause confusion and disrupt

conversations, making echo cancellation techniques crucial.

Enhancing speech quality involves deploying techniques such as adaptive noise reduction filters, automatic gain control, and voice activity detection. These technologies help maintain consistent loudness levels, reduce background noise, and optimize bandwidth use, thereby improving the overall user experience in telecommunication systems. The goal is to achieve a natural, clear, and stable communication experience, regardless of the underlying network conditions.

There are two main types of echo in VoIP communications: circuit echo and acoustic echo. Converting two wires from the switch to four wires from the mains side creates an echo circuit [1]. However, with the advancement of echo cancellation technology, echoes within the circuit have been effectively reduced and eliminated. As a result, the focus of echo cancellation has shifted from circular echo to acoustic echo. Acoustic echo suppression is very difficult. There are several main reasons: The communication process usually occurs in closed spaces such as conference rooms. Here, the sound produced by the speaker is reflected repeatedly and then picked up by a microphone and mixed with the words from the nearest speaker. This process results in a long echo tail and the corresponding echo path [2] has a long impulse response. Therefore, to remove echoes, the order of the adaptive filter must be increased. It is impossible to ensure complete silence in the environment when communicating. Noise caused by human movement or other types of interference can disrupt sound propagation and cause significant changes in the acoustic impulse response. Therefore, the acoustic echo path is unstable. The rapid changes in the echo path require high convergence speed [3] and good tracking performance during the echo cancellation process. However, algorithms with high convergence rates are closely related to computational complexity. Because the echo cancellation filters used to suppress echoes are high order, traditional fast algorithms often cannot solve the problem effectively. During VoIP communication, ambient noise may affect echo cancellation. Additionally, in situations where the noise floor is high, filter design becomes very complex as the echo cancellation function must not only handle echoes but also take background noise into account. In addition, several world scientists have conducted research in this field. In particular, is devoted to how the feedback problem can be reformulated as a system identification task and to cancel considerations. In this study, the application of Kalman filter-based adaptation in the frequency domain is proposed due to its robustness to the long phases of two-way conversation and the near-end single conversation. Researches [4], [5] proposed new methods for detecting and suppressing acoustic noise caused by feedback. In this research work, Efficient NLMS algorithm (eNLMS,) and Inverse Cyclic Convolution (ICC) are considered for arbitrary periodic excitation. It shows that both methods provide mathematically equivalent results and

complexity numbers. Along these lines, a flexible model of an acoustic echo suppression filter is presented in the scientific research work [6]. This flexible filter provides a quick overview of ways to remove acoustic echo and extra noise during a conference call, as well as filters that only capture the voices of participants. Despite the scope of research and the effectiveness of scientific results, the problem of real-time elimination of acoustic noise in teleconferencing systems has not been completely solved. In this research work the filtering processes of the LMS, NLMS and RLS filters for the pre-recorded audio file were performed. In this research work, simulation of the filtering process was carried out on the basis of the Matlab program.

Effective transmission and reception of voice signals require careful consideration of various technical aspects, including signal processing, noise reduction, and echo cancellation. Advanced codecs and algorithms are employed to ensure that the voice remains clear and distinct, minimizing distortions and delays. Maintaining high-quality voice signals is key in modern communication technologies, facilitating seamless and effective interactions across diverse and globally distributed networks.

Audio filtering is essential in various applications to enhance the quality of sound by selectively attenuating unwanted components of an audio signal. This process is crucial in environments with background noise, such as in telecommunications, where it improves speech clarity and intelligibility by reducing noise and echo. Filtering is also vital in audio production, broadcasting, and hearing aids to tailor the sound quality to specific needs or to compensate for acoustic imperfections.

In more technical terms, audio filtering helps manage frequency components, removing or suppressing those that are undesirable or irrelevant, and amplifying those that carry useful information. This leads to clearer audio in real-time communication systems, better soundtracks in multimedia, and more effective hearing aids.

In the field of speech processing, the quality of speech signals is often degraded by various types of noise, including background noise, echoes, and interference from other sources. Voice quality degradation due to noise can have serious consequences for a variety of applications, including communications, audio recording, and speech recognition. Therefore, there is a growing need for effective noise reduction techniques to improve the quality of speech signals in noisy environments.

One promising approach to noise reduction is the use of adaptive filters, the parameters of which can be adjusted in accordance with the characteristics of the input signal. Adaptive filters adapt to changing noise conditions and provide real-time processing, providing a flexible and effective solution for reducing noise in speech signals.

Adaptive filters [7] like the Least Mean Squares (LMS), Normalized Least Mean Squares (NLMS), and Recursive Least Squares (RLS) are advanced tools in

this domain. LMS is popular for its simplicity and effectiveness, adjusting its coefficients to minimize the mean square error between the desired and actual output. NLMS improves upon LMS by normalizing the update step, making it more robust to signal variations. RLS, although more computationally intensive, offers faster convergence and better performance in environments with variable dynamics by recursively updating its coefficients based on the incoming signal's properties. These adaptive filtering techniques are fundamental in achieving optimal audio quality in dynamic and unpredictable environments.

The Acoustic Echo Cancellation (AEC) block is designed to remove echoes, reverberation, and unwanted added sounds from a signal that passes through an acoustic space. As shown in the diagram below, the sound coming from the remote person speaking, known as the Far End In, is sent in parallel to

a DSP path and to an acoustic path. The acoustic path consists of an amplifier/loudspeaker, an acoustic environment, and a microphone returning the signal to the DSP. The AEC block is based on an adaptive FIR filter [7]. The algorithm continuously adapts this filter to model the acoustic path. The output of the filter is then subtracted from the acoustic path signal to produce a “clean” signal output with the linear portion of acoustic echoes largely removed. The AEC block also calculates a residual signal containing nonlinear acoustic artifacts. This signal is sent to a Residual Echo Cancellation block (RES) that further recovers the input signal. The signal is then (optionally) passed through a noise reduction function to produce the output, which is a known as the “Far End Out.” Below is an acoustic noise and echo cancellation block diagram for our research (Fig.1).




Fig.1. Block diagram of an adaptive filter for a conferencing system

Adaptive filter algorithms

Adaptive filters [8] are a class of filters that adjust their parameters based on the input signal to optimize their performance. They are commonly used in applications where the characteristics of the signal or the environment are changing over time. Adaptive filters are particularly useful for tasks such as noise cancellation, echo cancellation, and equalization.

1. Least Mean Square (LMS) Algorithm:

LMS algorithm is the same category of adaptive filters which is used to minimize the error (noise) of the input signal and give us error free (noise) output using least squares method i.e. - say, the difference between the desired response $d(n)$ and the input signal $u(n)$. The following equations can be used for the least mean square calculation, given the input vector at time n .

$$x(n) = [x(n), x(n-1), \dots, x(n-N+1)]$$

and the desired answer at time n is $d(n)$ and the error is $e(n)$.

$$e(n) = d(n) - y(n)$$

$$e(n) = d(n) - w^H(n)x(n) \quad (1)$$

The weight update equation for the LMS algorithm is as follows:

$$w(n+1) = w(n) + \mu \cdot e(n) \cdot x(n) \quad (2)$$

where: $w(n)$ is the filter coefficient vector at iteration n , μ is the step size or learning rate, $e(n)$ is the error signal (difference between the desired signal and the filter output), $x(n)$ is the input signal vector.

2. Normalized Least Mean Square (NLMS) Algorithm

The normalized least squares algorithm is identical to LMS, but the difference between the two algorithms lies in the calculation of the weight. The NLMS algorithm is a variation of the LMS algorithm that normalizes the step size based on the power of the input signal. This normalization helps to prevent the algorithm from diverging or converging too slowly.

The LMS algorithm may suffer from increased gradient noise, so it is a normalized least squares algorithm. The normalized LMS can be calculated using the updated equation below. The update equation for the NLMS algorithm is:

$$w(n+1) = w(n) + \frac{\mu}{\|x(n)\|^2 + \epsilon} * e(n) * x(n) \quad (3)$$

where $\|x(n)\|^2$ is the power of the input signal vector and ϵ is a small positive constant to prevent division by zero.

3. Recursive Least Square (RLS) Algorithm

The recursive least squares algorithm, in $n-1$ iterations, is such that given the least squares estimate of the desired filter weights, then in n iterations, as new data samples arrive, it can compute an updated estimate to update the weights. The algorithm is a recursive least squares method called the least squares algorithm. The following recursive equations can be used to calculate the RLS algorithm:

$$\pi(n) = P(n-1)x(n) \quad (4)$$

$$k(n) = \frac{\pi(n)}{\lambda + x^H(n)\pi(n)} \quad (5)$$

$$\varepsilon(n) = d(n) - w^H(n-1)x(n) \quad (6)$$

$$w(n) = w(n-1) + k(n) * \varepsilon(n) \quad (7)$$

$$P(n) = \lambda^{-1}P(n-1) - \lambda^{-1}k(n)x^H(n)P(n-1) \quad (8)$$

The update equation for the RLS algorithm is:

$$w(n+1) = w(n) + K(n) * e(n) * P(n) * x(n) \quad (9)$$

where: $P(n)$ is the inverse of the autocorrelation matrix of the input signal, $K(n)$ is the gain matrix, other variables are similar to those in the LMS algorithm.

Comparative analysis

This section presents a comparative analysis of adaptive filter algorithms such as Least Mean Square (LMS), Normalized Least Mean Square (NLMS) and Recursive Least Square (RLS) are used for adaptive noise cancellation and echo cancellation.

Table 1.

	Convergence Speed	Computational Complexity	Stability	Performance in Non-Stationary Environments	Robustness to Variations in Signal Power	Robustness to Model Mismatch
LMS	Converges relatively slowly, especially in scenarios with high noise levels or highly correlated inputs.	Low computational complexity, making it suitable for real-time applications.	Stable for a wide range of step sizes, but can be sensitive to the choice of step size.	Less effective in non-stationary environments due to its slow convergence.	Not inherently robust to variations in signal power, as the step size is fixed.	Less robust to model mismatch, as it relies on the accuracy of the model.
NLMS	Converges faster than LMS due to its normalization, but may still be slower than RLS.	Slightly higher computational complexity than LMS due to the additional normalization calculation.	More stable than LMS due to its normalization, but can still exhibit instability if the step size is too large.	More robust in non-stationary environments compared to LMS.	More robust to variations in signal power due to its normalization.	More robust to model mismatch compared to LMS.
RLS	Converges quickly, making it suitable for applications where rapid adaptation is required.	Highest computational complexity among the three, which can be a limiting factor in real-time applications or applications with limited computational resources.	Generally stable, but can be sensitive to noise and model errors.	Highly effective in non-stationary environments due to its ability to adapt quickly.	Can be sensitive to variations in signal power if the forgetting factor is not properly chosen.	Relatively robust to model mismatch due to its recursive nature.

Overall, the choice of the most optimal algorithm depends on the specific requirements of the application. For applications where computational complexity is not a concern and rapid adaptation is required, RLS may be the most optimal choice. However, for real-time applications with limited computational resources, LMS or NLMS may be more suitable despite their slower convergence rates. Overall, the choice of the

most optimal algorithm depends on the specific requirements of the application. For applications where computational complexity is not a concern and rapid adaptation is required, RLS may be the most optimal choice. However, for real-time applications with limited computational resources, LMS or NLMS may be more suitable despite their slower convergence rates.

The proposed algorithm for the ongoing research is given below (Fig.2).




Fig.2. Algorithm for ongoing research

The algorithm description is presented in a descriptive style: Parameter Definition - the algorithm begins by defining crucial parameters. First, it sets the sampling frequency (f_s), which determines the rate at which audio signals are sampled. Second, it specifies the filter order, determining the complexity of the filter. Third, it sets the step sizes for adaptive filters (μ for LMS and NLMS), controlling how much the filter coefficients are adjusted at each iteration. Fourth, it defines the regularization factor (δ for NLMS), regulating the impact of the error on the filter update. Lastly, it establishes the forgetting factor (λ for RLS), controlling the influence of past data on the filter coefficients. These parameters are essential for configuring the behavior of the adaptive filters.

The algorithm proceeds by setting up audio recording and playback functionalities. First, it utilizes MATLAB's audiorecorder and audioplayer objects. Second, it configures the recording environment to capture mono audio at a 16-bit depth and the specified sampling rate. Third, it initializes a playback object with silence, ensuring synchronization between the start of playback and recording.

Next, the algorithm employs a timer mechanism to manage the duration of the audio recording. It automatically stops the recording after 10 seconds, providing a practical approach for controlling recording length in experimental or testing setups.

Noise Addition - to simulate real-world conditions, the algorithm introduces noise into the recorded signal. It adds white Gaussian noise, with the noise level determined by a signal-to-noise ratio (SNR). This SNR influences the variance of the added noise, thereby replicating real-world noisy environments.

Finally, the algorithm implements three types of adaptive filters:

- LMS (Least Mean Squares): This filter updates its coefficients by minimizing the mean squares of the error between the estimated and actual signals.

- NLMS (Normalized Least Mean Squares): An extension of LMS, NLMS normalizes the update step by the signal's energy. This normalization enhances stability and convergence, especially in environments with varying signal power.

- RLS (Recursive Least Squares): RLS utilizes a forgetting factor to assign exponentially less weight to older error values. This focus on recent data helps in

non-stationary environments by prioritizing recent information over past observations.

At the next stage of signal processing and visualization. The filtered signals are processed in a loop that adjusts filter coefficients based on the incoming audio data. The original, noisy, and filtered signals are plotted for visual comparison. This allows the user to observe the filter's performance and make adjustments as needed. The visualization also enables the identification of any potential issues with the filtering process, ensuring that the output meets the desired quality standards.

This script is a prototype that can be used in experimental setups for testing and developing noise reduction techniques in audio signals, suitable for applications like teleconferencing where background noise and feedback can be problematic. Each component of the script is modular, allowing for adjustments and optimizations based on specific needs or different experimental conditions.

At the next stage of our research, we will conduct research on LMS, NLMS and RLS algorithms for adaptive filtering of audio signals based on Matlab software. This will enable us to evaluate the effectiveness of these algorithms in real-world scenarios and identify the most suitable approach for various applications. Furthermore, we plan to explore the use of machine learning techniques, such as deep learning and neural networks, to improve the accuracy and efficiency of noise reduction methods. The ultimate goal is to develop a robust and adaptive noise reduction system that can seamlessly integrate with existing audio processing systems, providing users with high-quality audio experiences in diverse environments.

Main part

Implementation and evaluation of adaptive filtering techniques for speech signal enhancement

In this part of the study, various adaptive filtering methods namely least mean squares (LMS), normalized least mean squares (NLMS) and recursive least squares (RLS) are modeled using Matlab software to improve the quality of noisy speech. The purpose of this stage is the initial step of improving the quality of communication in teleconferencing systems - filtering the speech signal from noise, the first step of improving the quality of communication.

In the first step, the implementation of adaptive filters begins with the task of developing MATLAB code to apply LMS, NLMS and RLS [9] algorithms to the noisy speech signal coming to the device through the microphone. As a result, applying each filtering technique involves setting the initial conditions, determining the filter parameters, and iterating through

the signal. The results of the program are displayed as a graphical representation of the filtered signal.

The next stage is the stage of analyzing the performance of the filter. At this stage, the performance of each adaptive filter is evaluated in terms of its ability to reduce noise and improve the quality of the speech signal. This includes the tasks of analyzing the output signals from each filter and comparing them with the original noisy signal. In addition, the filter performance analysis at this stage included an evaluation of how effectively the filter improves the quality of the noisy speech signal.

The third stage is the stage of quantitative evaluation of signal quality improvement. In this step, the effectiveness of each filter is evaluated by checking the improvements in parameters such as Signal-to-Noise Ratio (SNR) [9] and Mean Square Error (MSE) [10] between the filtered signals and the original clean speech signal. To evaluate the signal quality improvement, the SNR calculation process is performed for the noisy input signal and the filtered output signal, and the filtered speech signal is determined by the difference between these two SNR values. As a result, a higher SNR improvement indicates a more effective noise reduction and signal enhancement through the filtering algorithm. The mean squared error (MSE), on the other hand, measures the average of the squared errors between the original clean signal and the filtered signal. This Mean Squared Error (MSE) is a widely used metric to quantify signal distortion.

The last stage is the stage of visualization of results. In this step, plots should be used to visually compare the original speech signal, the noisy signal, and the output of each adaptive filter. This visualization goes a long way in showing the relative effectiveness of LMS, NLMS, and RLS algorithms in reducing noise and improving speech quality. In addition, at this stage, there are options to visualize the results in several ways. For example, when comparing signals, results can also be introduced in the form of a spectrogram.

Taking into account the criteria mentioned above, at the next stage of the research, the research will be conducted in the Matlab program. In this case, the simplest method is simulated by adding Gaussian white noise with SNR=10 dB value to the sinusoidal signal equal to $f_s=44100$ Hz as an initial signal, and the result of the program based on these conditions is shown in Figure 3 below. In this process, a Gaussian white noise signal is added to the original original signal, and the resulting noisy signal is denoised using LMS, NLMS and RLS filters.




Fig.3. Frequency Spectrum Analysis of Speech Signal Processing

This MATLAB program demonstrates the application of three different adaptive filtering algorithms—Least Mean Squares (LMS), Normalized Least Mean Squares (NLMS), and Recursive Least Squares (RLS)—to a synthetic speech signal contaminated with white Gaussian noise. The synthetic speech signal is represented by a pure sine wave at 50 Hz, and the noise is added based on a predefined signal-to-noise ratio (SNR) of 10 dB. Each adaptive filter is configured with specific parameters such as filter order, step size, and forgetting factor to optimize its performance. The program processes the noisy signal using the LMS, NLMS, and RLS filters, each attempting to recover the original speech signal by minimizing the error between the filtered output and the original signal. The effectiveness of each filter is then visually compared using frequency spectrum plots of the original, noisy, and filtered signals, providing insights into the filter's performance and suitability for noise reduction in speech signals.

Practical Implementation and Real-Time Evaluation of Adaptive Filters for Speech Enhancement

The main objective of this chapter is to evaluate the implementation and performance of adaptive filtering methods - Least Mean Squares (LMS), Normalized Least Mean Squares (NLMS) and Recursive Least Squares (RLS) - in a real-time environment using MATLAB. The conducted research will serve to demonstrate the real-life application of these adaptive filters in improving speech signal quality in noisy conditions, which is an important aspect of audio signal processing in the future telecommunications industry.

In the next step, 10 seconds of sound is recorded from the personal computer microphone, and based on this recorded signal, the research is continued. In the process of filtering the recorded sound sample, 10 db Gaussian white noise is artificially added to the original sound to create a noisy environment, and by applying three different adaptive filters, the result is as follows (Figure 4-5). In this process - LMS (Least Mean Squares), NLMS (Normalized Least Mean Squares) and RLS (Recursive Least Squares) noise suppression and restoration of the original signal are performed.




Fig. 4. Audio Noise Suppression Simulator output.




Fig.5. The original sound signals and Gaussian white noise added (SNR=10 dB) and the LMS, NLMS and RLS filtered quality signal results of a spectrogram.

Based on the obtained results, the filter performance indicators are compared at the analysis stage. These metrics are compared in terms of MSE, NMSE, and PSNR. The Mean Squared Error (MSE) is a statistical measure that quantifies the average of the squares of the errors or deviations. Specifically, it is the average squared difference between the estimated values produced by a model and the actual values of the quantity being estimated. The Normalized Mean Squared Error (NMSE) modifies the MSE to provide a scale-independent metric by normalizing the squared errors by the variance of the dataset. This normalization allows for the assessment of the error magnitude relative to the variability of the data, thus facilitating

comparisons across datasets with different scales. The Peak Signal-to-Noise Ratio (PSNR) is widely used in the field of image and video quality assessment. It measures the ratio between the maximum possible power of a signal (representing image pixel intensities) and the power of corrupting noise that affects the fidelity of its representation. These metrics are fundamental in quantitative analysis in fields like image processing, computer vision, and audio processing, providing benchmarks to assess the accuracy and efficacy of various algorithms and systems in replicating or predicting data with high fidelity. Based on these indicators, the research results are compared in Table 2 below.

Table 2.

Filter Performance Metrics:

	MSE	NMSE	PSNR
LMS	$0.15983 \cdot 10^{-3}$	0.032814	36.534
NLMS	$0.1464 \cdot 10^{-3}$	0.030057	36.916
RLS	$0.905750 \cdot 10^{-4}$	0.018596	39.001

Discussion.

The results of the study showed that the best filter was the RLS filter. The Recursive Least Squares (RLS) algorithm is a powerful method for adaptive filtering that offers rapid convergence and robust performance, particularly in environments with changing statistics. However, this filter has several disadvantages, and in the research conducted on recorded audio files, the RLS filter achieved the highest result. However, if we mention the disadvantages, the RLS algorithm involves higher computational complexity compared to simpler adaptive filters such as the Least Mean Squares (LMS) algorithm. This complexity arises from matrix operations such as inversion or factorization that are required at each step. These operations are computationally expensive, particularly when dealing with large datasets or high-dimensional data, making RLS less suitable for applications with strict real-time processing constraints or limited processing power. Besides, RLS requires the storage of past data in the form of covariance matrices, which can become a significant burden in terms of memory usage. This requirement for keeping a record of previous data points makes RLS less attractive for applications with limited memory resources or for long-running systems where data accumulates over time.

The program serves educational, experimental, and development purposes, especially useful for those studying or working in fields related to digital signal processing, audio engineering, and telecommunications. It provides a practical demonstration of adaptive filtering techniques and their applications in real-world noise reduction scenarios. We hope that the results of the research conducted for the experiment will be of great help to the research of several scientists in the future.

Conclusion

The RLS filter demonstrated the quickest convergence rate and highest noise reduction efficacy as evidenced by its superior PSNR values across most test scenarios. However, it also exhibited the highest

computational demand. In contrast, the LMS filter, while being the least computationally intensive, showed modest performance improvements. The NLMS filter presented a balanced profile with moderate computational requirements and effective noise suppression, making it suitable for real-time audio processing applications.

The study underscores the trade-offs between computational efficiency and noise reduction capabilities inherent in these filtering techniques. While the RLS filter is preferable for applications where computational resources are ample and optimal noise reduction is paramount, the NLMS filter offers a viable compromise for real-time applications with moderate resource availability. The LMS filter, owing to its minimal computational demand, remains relevant for low-power applications despite its lower performance metrics.

Unsolved Problem: Real-Time Acoustic Noise Cancellation in Dynamic Environments

Real-time acoustic noise cancellation in dynamic environments remains an unsolved problem that requires a multidisciplinary approach, combining signal processing, real-time computing, and potentially machine learning. Addressing this problem could significantly enhance the quality of audio communication and recording in various real-world applications.

Acoustic noise cancellation (ANC) is a crucial technology for improving the quality of audio communication and recording. Adaptive filters like LMS (Least Mean Squares), NLMS (Normalized Least Mean Squares), and RLS (Recursive Least Squares) are commonly used to achieve noise reduction. These algorithms have shown significant promise in controlled environments. However, in real-world scenarios, such as during a live conference in a dynamically changing acoustic environment, maintaining effective noise cancellation remains a challenging problem.

Developing a robust and adaptive noise cancellation system capable of real-time operation in dynamically changing acoustic environments. The system should be able to switch adaptively between different filtering algorithms (LMS, NLMS, RLS) based on real-time analysis of the signal-to-noise ratio (SNR) and other relevant parameters to achieve optimal performance.

By accomplishing these objectives, the chapter will not only demonstrate the technical implementation of adaptive filters but also highlight their practical benefits and limitations in real-time audio signal processing. This approach underscores the relevance of adaptive filtering techniques in modern audio and telecommunication systems, providing a foundation for further research and development in this field. Today, this research work has its practical continuation and the research work is continued.

References

- [1] L. Liu, M. Fukumoto, и S. Saikfi, «An improved mu-law proportionate NLMS algorithm», ICASSP, IEEE Int. Conf. Acoust. Speech Signal Process. - Proc., вып. 3, сс. 3797–3800, 2008, doi: 10.1109/ICASSP.2008.4518480.
- [2] Paulo S. R. Diniz, THE LEAST-MEAN-SQUARE (LMS) ALGORITHM. 2020. doi: 10.1007/978-0-387-68606-6.
- [3] D. T. M. Slock, «On the Convergence Behavior of the LMS and the Normalized LMS Algorithms», IEEE Trans. Signal Process., т. 41, вып. 9, сс. 2811–2825, 1993, doi: 10.1109/78.236504.
- [4] S. Kuhl, S. Nagel, T. Kabzinski, C. Antweiler, и P. Jax, «A Joint Perspective of Periodically Excited Efficient NLMS Algorithm and Inverse Cyclic Convolution», ICASSP, IEEE Int. Conf. Acoust. Speech Signal Process. - Proc., т. 2018-April, вып. 3, сс. 406–410, 2018, doi: 10.1109/ICASSP.2018.8461341.
- [5] S. Kuhl, C. Anemüller, C. Antweiler, P. Jax, F. Heese, и P. Vicinus, «Acoustic howling detection and suppression for IP-based teleconference systems», Speech Commun. - 13th ITG-Fachtagung Sprachkommunikation, сс. 291–295, 2020.
- [6] R. B.N. и X. J.D., «COMPARATIVE ANALYSIS OF MODERN METHODS OF ELIMINATING ACOUSTIC ECHO INTERFERENCE IN TELECOMMUNICATION SYSTEMS», World Sci., т. 6, вып. 5, сс. 60–65, 2023, [Онлайн]. Доступно на: <https://scientificacademy.org/index.php/ws/article/view/205>
- [7] R. B.N., B. A.A., и X. J.D., «Telekommunikatsiya tizimlarida akustik aks-sado shovqinlarini bartaraf qilishda zamonaviy usullarining qiyosiy tahlili», Muhammad al-Xorazmiy avlodlari, т. 1, вып. 23, 2023.
- [8] M. Jane Carline и D. C. Diana, «An Investigation on Adaptive Algorithms for Echo Cancellation of Acoustic Signals», 2nd Int. Conf. Sustain. Comput. Data Commun. Syst. ICSCDS 2023 - Proc., сс. 960–966, 2023, doi: 10.1109/ICSCDS56580.2023.10105081.
- [9] I. D. Ficiu, C. Paleologu, J. Benesty, C. Elisei-Iliecu, C. L. Stanciu, и C. Anghel, «A Decomposition-Based RLS Algorithm for Stereophonic Acoustic Echo Cancellation», 2022 15th Int. Symp. Electron. Telecommun. ISETC 2022 - Conf. Proc., сс. 7–10, 2022, doi: 10.1109/ISETC56213.2022.10009977.
- [10] Y. Wang, Z. Qin, J. Tao, F. Tong, и Y. Qiao, «Sparse Adaptive Channel Estimation based on l0-PRLS Algorithm for Underwater Acoustic Communications», Ocean. Conf. Rec., сс. 1–5, 2022, doi: 10.1109/OCEANSSChennai45887.2022.9775337.