

Parking Mode - Frame Description

In Parking mode, the response frame we will receive is explained below:

<SOF>	"Starting Of Frame" – 1 byte
<FRAME>	"Covering Command code, Flags & Data"
<CRC>	"Cyclic Redundancy Check" – 2 bytes .

Now let me split the <FRAME> for more clarity:

<Len>	"Frame Length" – 1 byte
<0xE2>	"Fixed 1 byte before Flags information" – 1 byte
<Flags>	"1 st byte is for Tag's Status & 2 nd byte is for Device ID, Date-Time & TID" – 2 bytes*
<Device ID>	"Serial No of the Reader/Device" – 4 bytes in REVERSE
<Date-Time>	"Sequence of byte as HH MM SS mm dd yy" – 6 bytes
<TID Len>	"Length of TID" – 1 byte
<TID>	"This is Unique ID" – 12 bytes

* Let's understand the 2 bytes of <Flags> based on our initial Reader/Device configuration...

1. The 1st byte value indicates the Tag's status, i.e., Is it Tag "Active" or "Blocked".

For "Active" Tags, the 1st byte of <Flags> will be "0x02".

For "Blocked" Tags, the 1st byte of <Flags> will be "0x04".

And, for "Unregistered / New" Tags, the 1st byte of <Flags> will be "0x00".

2. The 2nd byte value is all together calculated value based on our configuration we wish to have in our Frame (i.e., Device ID, Date-Time & TID OR only Date-Time & TID).

Device ID	–	0x40
Date-Time	–	0x80
TID	–	0x02

So, if we select/configured to have Device ID in our Response Frame; then the 2nd byte of <Flags> will be "0xC2".

And, as the Date-Time & TID are default in Parking mode; so, if we won't select/configured the Device ID; then the 2nd byte of <Flags> will be "0x82".