

- (2) Take the DRS60L6 series as an example:

-----Setting the parameters for Point-----

SetGlobalPoint(1, "GL_P1", 200, 200, -100, 0, 0, 0, 0, {0,0,0,0,0,0,4})

SetGlobalPoint(2, "GL_P2", 300, 100, -100, 0, 0, 0, 0, {0,0,0,0,0,0,4})

SetGlobalPoint(3, "GL_P3", 200, 0, -100, 0, 0, 0, 0, {0,0,0,0,0,0,4})

SafetyMode(1) --Switch the functional pause mode to 1

for i=1,2 do --Use the for loop. The loop ends when the value of *i* matches the set condition

DO(i, "ON")--Switch DO1 and DO2 to ON

end

MovP(1) --Move to Point number 1 at the default speed

MovP(2) --Move to Point number 2 at the default speed. If the functional pause is triggered while the robot is moving, the program pauses after the motion is complete. DO1 and DO2 statuses remain unchanged. You need to switch the system DI3 to OFF, ON, and then OFF to resume the robot operation.

SafetyMode(5) --Switch the functional pause mode to 5

MovP(3) --Move to Point number 3 at the default speed. If the functional pause is triggered while the robot is moving, the program pauses immediately. DO1 and DO2 are switched to OFF.

