

SVG Capacity	Recommended Protection Device Model
50 kvar	Schneider NSX100H TMD100 3P3D (690V 100A)
100 kvar	Schneider NSX250H TMD200 3P3D (690V 200A)
150 kvar	Schneider NSX400H TMD400 3P3D (690V Adjust to about 300A)

- The short circuit parameters of the SVG are as follows:

SVG Capacity	Conditional Short Circuit Current (Icc)	Prospective Short Circuit Current for the Minimum Demand (Icp,mr)	Short Circuit Protection Device (SCPD)
50 kvar	20 kA	2.5 kA	80A Fuse *2 Type: BUSSMANN 80FE
100 kvar	20 kA	5 kA	160A Fuse *2 Type: HINODE 660GH-160
150 kvar	20 kA	5 kA	280A Fuse Type: Hollyland HEA280

- The three-phase, four-wire SVG is applicable to the power grid system with neutral grounding.
- The CT wire shall be fastened to avoid open circuit, which will lead to high-voltage risk and secondary circuit burning.

1.3 Usage Warnings

- Only qualified service personnel can update SVG hardware and firmware.
- Since the SVG is used for reactive power and imbalance compensation of the power grid, the capacity selection of the SVG shall be subject to reactive power and imbalance content to avoid poor compensation due to insufficient capacity.
- Before installation, wiring and working on the SVG's internal circuits, please completely cut off all power supplying to the SVG.
- Since SVG is used for reactive power mitigation, external CT shall be connected to detect the reactive current.
- To guarantee sound reliability and avoid overheating, do not block or cover the air inlet and outlet.
- The thermal loss of Mixed Fixed type SVG is not bigger than 3% of rated apparent power.