RV1

GND 1

2 POT_DRY

3V3A 3

B10K Dry

RV2

GND 1

2 POT_LOOP

3V3A 3

B10K Loop

RV3

GND 1

2 POT_SUB

3V3A 3

B10K −8

RV4

GND 1

2 POT_FIFTH

3V3A 3

B10K +5

RV5

GND 1

2 POT_OCT

3V3A 3

B10K +8

RV6

GND 1

2 POT_FADE

3V3A 3

B10K Fade

RV7

GND 1

2 POT_TEX

3V3A 3

B10K Texture

J1

FS_FREEZE 1

GND 2

Freeze footswitch

J2

FS_CLEAR 1

GND 2

Clear footswitch

U1 Daisy Seed3

+3V3A	21	3V3A	
POT_DRY	22	A0/D15	
POT_LOOP	23	A1/D16	
POT_SUB	24	A2/D17	
POT_FIFTH	25	A3/D18	
POT_OCT	26	A4/D19	
POT_FADE	27	A5/D20	
POT_TEX	28	A6/D21	
	29	A7/D22	
	30	A8/D23	
	31	A9/D24	
	32	A10/D25	
OUTR_DETECT	33	D26	
	34	D27	
	35	A11/D28	
	36	D29/USB_D−	
	37	D30/USB_D+	
+3V3D	38	3V3D	
GND	39	VIN	
	40	GND	

	20	GND	
	19	OUT_R	
	18	OUT_L	
	17	AUDIO_IN	
	16	AUDIO_IN	
	15		
	14		
	13	LED_GRN_DRV	
	12	LED_RED_DRV	
	11	FS_CLEAR	
	10	FS_FREEZE	
	9	TGL_FIFTH_DIR	
	8	TGL_LAYERS	
	7		
	6		
	5		
	4		
	3		
	2		
	1		

AUDIO_OUT_R

AUDIO_OUT_L

AUDIO_IN_R

AUDIO_IN_L

R1

LED_RED_DRV — 470 — LED_RED

R2

LED_GRN_DRV — 470 — LED_GRN

D1

GND 2

LED_RED 1

LED_GRN 3

Red/Green

J3

GND TN

AUDIO_IN T

RN

R

GND S

In (mono; grounded when empty)

J4

JOUT_L TN

T

RN

R

GND S

Out L / Mono

J5

JOUT_R TN

T

OUTR_DETECT RN

R

GND S

Out R (ring switch = plug detect)

C1

OUT_L — JOUT_L

10u

JOUT_L

GND

100k

C2

OUT_R — JOUT_R

10u

JOUT_R

GND

100k

SW1

TGL_LAYERS

GND 1

2

+3V3D 3

Single / Multi

SW2

TGL_FIFTH_DIR

GND 1

2

+3V3D 3

+5 up / down

H1 H2 H3 H4

M3 M3 M3 M3

Pots: CCW end (1) to GND, CW end (3) to +3V3A, wiper straight to the ADC pin; firmware smooths readings.

Mono in feeds both codec inputs; the In jack's tip switch grounds the input when nothing is plugged in.

Out R plug detect: ring tied to GND, ring−normal contact to D26 (internal pull−up). Empty jack reads low, any plug reads high. Low = firmware sums to Out L. Toggles and footswitches use no resistors.

One carrier ground: Seed AGND (pin 20) and DGND (pin 40) both tie to the GND pour

Bare board, all through−hole. Pots/toggles/LED on top; Seed3 + jacks underneath; footswitches on J

Generated by gen_schematic.py from one netlist definition — edit the script, not the sheet

Sheet: /

File: carrier.kicad_sch

Title: Daisy Freeze Pedal — carrier board

Size: A3	Date: 2026−10−26	**Rev: A**
KiCad E.D.A. kicad−cli 7.0.11+dfsg−1build4		Id: 1/1