

Appendix—List of Cisco IOS commands used in this lab

Purpose	Command
Enter the global configuration mode.	configure terminal Example: Router> enable Router# configure terminal Router(config)#
Specify the name for the Cisco device.	hostname name Example: Router(config)# hostname Router1 Router(config)#
Specify an encrypted password to prevent unauthorized access to the privileged EXEC mode.	enable secret password Example: Router(config)# enable secret cisco Router(config)#
Specify a password to prevent unauthorized access to the console.	password password login Example: Router(config)# line con 0 Router(config-line)# password class Router(config-line)# login Router(config)#
Specify a password to prevent unauthorized Telnet access. Router vty lines: 0 4 Switch vty lines: 0 15	password password login Example: Router(config)# line vty 0 4 Router(config-line)# password class Router(config-line)# login Router(config-line)#
Configure the MOTD banner.	Banner motd % Example: Router(config)# banner motd % Router(config)#
Configure a Router interface. Router interface is OFF by default	Example: Router(config)# interface Fa0/0 Router(config-if)# description description Router(config-if)# ip address address mask Router(config-if)# no shutdown Router(config-if)#
Switch interface is ON by default (VLAN interface is OFF by default)	Example: Switch(config)# interface Fa0/0 Switch(config-if)# description description Switch(config)# interface vlan1 Switch(config-if)# ip address address mask Switch(config-if)# no shutdown Switch(config-if)#
Switch- create a default IP gateway	Switch(config)# ip default-gateway address
Save the configuration to NVRAM.	copy running-config startup-config Example:

	Router# copy running-config startup-config
--	---