

# OVP Guide to Using Processor Models

Model specific information for ARM\_Cortex-A65AEMPx4

---

X-2025.12 December,2025



## Copyright and Proprietary Information Notice

© 2025 Synopsys, Inc. This Synopsys software and all associated documentation are proprietary to Synopsys, Inc. and may only be used pursuant to the terms and conditions of a written license agreement with Synopsys, Inc. All other use, reproduction, modification, or distribution of the Synopsys software or the associated documentation is strictly prohibited.

## Destination Control Statement

All technical data contained in this publication is subject to the export control laws of the United States of America. Disclosure to nationals of other countries contrary to United States law is prohibited. It is the reader's responsibility to determine the applicable regulations and to comply with them.

## Disclaimer

SYNOPSYS, INC., AND ITS LICENSORS MAKE NO WARRANTY OF ANY KIND, EXPRESS OR IMPLIED, WITH REGARD TO THIS MATERIAL, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE.

## Trademarks

Synopsys and certain Synopsys product names are trademarks of Synopsys, as set forth at <https://www.synopsys.com/company/legal/trademarks-brands.html>. All other product or company names may be trademarks of their respective owners.

## Free and Open-Source Licensing Notices

If applicable, Free and Open-Source Software (FOSS) licensing notices are available in the product installation.

## Third-Party Links

Any links to third-party websites included in this document are for your convenience only. Synopsys does not endorse and is not responsible for such websites and their practices, including privacy practices, availability, and content.

[www.synopsys.com](http://www.synopsys.com)

## Document Status

|          |                                                         |
|----------|---------------------------------------------------------|
| Author   | Synopsys Inc                                            |
| Version  | X-2025.12                                               |
| Filename | OVP_Model_Specific_Information_arm_Cortex-A65AEMPx4.pdf |
| Created  | 10 December 2025                                        |
| Status   | OVP Standard Release                                    |

## Model Release Status

This model is included in all general releases.

# Contents

|          |                                                     |           |
|----------|-----------------------------------------------------|-----------|
| <b>1</b> | <b>Overview</b>                                     | <b>1</b>  |
| 1.1      | Description . . . . .                               | 1         |
| 1.2      | Licensing . . . . .                                 | 1         |
| 1.3      | Limitations . . . . .                               | 2         |
| 1.4      | Verification . . . . .                              | 3         |
| 1.5      | Features . . . . .                                  | 3         |
| 1.5.1    | Core Features . . . . .                             | 3         |
| 1.5.2    | Memory System . . . . .                             | 3         |
| 1.5.3    | Advanced SIMD and Floating-Point Features . . . . . | 4         |
| 1.5.4    | Generic Timer . . . . .                             | 4         |
| 1.5.5    | Generic Interrupt Controller . . . . .              | 4         |
| 1.6      | Debug Mask . . . . .                                | 5         |
| 1.7      | Integration Support . . . . .                       | 5         |
| 1.7.1    | Memory Transaction Query . . . . .                  | 5         |
| 1.7.2    | Page Table Walk Query . . . . .                     | 6         |
| 1.7.3    | Artifact Page Table Walks . . . . .                 | 6         |
| 1.7.4    | MMU and Page Table Walk Events . . . . .            | 6         |
| 1.7.5    | Artifact Address Translations . . . . .             | 7         |
| 1.7.6    | TLB Invalidation . . . . .                          | 7         |
| 1.7.7    | Halt Reason Introspection . . . . .                 | 7         |
| 1.7.8    | Automatic WFI Wake Up . . . . .                     | 7         |
| 1.7.9    | System Register Access Monitor . . . . .            | 7         |
| 1.7.10   | System Register Implementation . . . . .            | 8         |
| <b>2</b> | <b>Configuration</b>                                | <b>9</b>  |
| 2.1      | Location . . . . .                                  | 9         |
| 2.2      | GDB Path . . . . .                                  | 9         |
| 2.3      | Semi-Host Library . . . . .                         | 9         |
| 2.4      | Processor Endian-ness . . . . .                     | 9         |
| 2.5      | QuantumLeap Support . . . . .                       | 9         |
| 2.6      | Processor ELF code . . . . .                        | 9         |
| <b>3</b> | <b>All Variants in this model</b>                   | <b>10</b> |
| <b>4</b> | <b>Bus Master Ports</b>                             | <b>14</b> |
| <b>5</b> | <b>Bus Slave Ports</b>                              | <b>15</b> |

|           |                                             |           |
|-----------|---------------------------------------------|-----------|
| <b>6</b>  | <b>Net Ports</b>                            | <b>16</b> |
| <b>7</b>  | <b>FIFO Ports</b>                           | <b>37</b> |
| <b>8</b>  | <b>Formal Parameters</b>                    | <b>38</b> |
| 8.1       | Parameter values and limits . . . . .       | 44        |
| 8.2       | Parameter values and limits . . . . .       | 48        |
| <b>9</b>  | <b>Execution Modes</b>                      | <b>49</b> |
| <b>10</b> | <b>Exceptions</b>                           | <b>50</b> |
| <b>11</b> | <b>Hierarchy of the model</b>               | <b>51</b> |
| 11.1      | Level 1: MPCORE . . . . .                   | 51        |
| 11.2      | Level 2: CORE . . . . .                     | 51        |
| 11.3      | Level 3: THREAD . . . . .                   | 51        |
| <b>12</b> | <b>Model Commands</b>                       | <b>53</b> |
| 12.1      | Level 1: MPCORE . . . . .                   | 53        |
| 12.1.1    | isync . . . . .                             | 53        |
| 12.1.2    | itrace . . . . .                            | 53        |
| 12.2      | Level 2: CORE . . . . .                     | 54        |
| 12.2.1    | isync . . . . .                             | 54        |
| 12.2.2    | itrace . . . . .                            | 54        |
| 12.3      | Level 3: THREAD . . . . .                   | 54        |
| 12.3.1    | debugflags . . . . .                        | 54        |
| 12.3.2    | dumpTLB . . . . .                           | 55        |
| 12.3.3    | isync . . . . .                             | 55        |
| 12.3.4    | itrace . . . . .                            | 55        |
| 12.3.5    | listSysRegsAA64 . . . . .                   | 56        |
| 12.3.5.1  | Argument description . . . . .              | 56        |
| 12.3.6    | validateTLB . . . . .                       | 56        |
| <b>13</b> | <b>Registers</b>                            | <b>57</b> |
| 13.1      | Level 1: MPCORE . . . . .                   | 57        |
| 13.2      | Level 2: CORE . . . . .                     | 57        |
| 13.3      | Level 3: THREAD . . . . .                   | 57        |
| 13.3.1    | Core_AArch64 . . . . .                      | 57        |
| 13.3.2    | SIMD_FP_AArch64 . . . . .                   | 58        |
| 13.3.3    | AArch64_system . . . . .                    | 58        |
| 13.3.4    | AArch64_secure_system . . . . .             | 66        |
| 13.3.5    | AArch64_non_secure_system . . . . .         | 66        |
| 13.3.6    | AArch64_system_artifact . . . . .           | 67        |
| 13.3.7    | AArch64_SYS_instruction_registers . . . . . | 67        |
| 13.3.8    | Integration_support . . . . .               | 68        |
| 13.3.9    | MPCore_distributor . . . . .                | 69        |
| 13.3.10   | MPCore_physical_redistributor . . . . .     | 72        |
| 13.3.11   | MPCore_processor_interface . . . . .        | 73        |
| 13.3.12   | MPCore_virtual_interface_control . . . . .  | 73        |

13.3.13 MPCore\_virtual\_processor\_interface . . . . . 74

13.3.14 MPCore\_ITS . . . . . 74

# Chapter 1

## Overview

This document provides the details of an OVP Fast Processor Model variant.

OVP Fast Processor Models are written in C and provide a C API for use in C based platforms. The models also provide a native interface for use in SystemC TLM2 platforms.

The models are written using the OVP VMI API that provides a Virtual Machine Interface that defines the behavior of the processor. The VMI API makes a clear line between model and simulator allowing very good optimization and world class high speed performance. Most models are provided as a binary shared object and also as source. This allows the download and use of the model binary or the use of the source to explore and modify the model.

The models are run through an extensive QA and regression testing process and most model families are validated using technology provided by the processor IP owners. There is a companion document (OVP Guide to Using Processor Models) which explains the general concepts of OVP Fast Processor Models and their use. It is downloadable from the OVPworld website documentation pages.

### 1.1 Description

ARM Processor Model

### 1.2 Licensing

Usage of binary model under license governing simulator usage.

Note that for models of ARM CPUs the license includes the following terms:

Licensee is granted a non-exclusive, worldwide, non-transferable, revocable licence to:

If no source is being provided to the Licensee: use and copy only (no modifications rights are granted) the model for the sole purpose of designing, developing, analyzing, debugging, testing, verifying, validating and optimizing software which: (a) (i) is for ARM based systems; and (ii) does not incorporate the ARM Models or any part thereof; and (b) such ARM Models may not be used

to emulate an ARM based system to run application software in a production or live environment.

If source code is being provided to the Licensee: use, copy and modify the model for the sole purpose of designing, developing, analyzing, debugging, testing, verifying, validating and optimizing software which: (a) (i) is for ARM based systems; and (ii) does not incorporate the ARM Models or any part thereof; and (b) such ARM Models may not be used to emulate an ARM based system to run application software in a production or live environment.

In the case of any Licensee who is either or both an academic or educational institution the purposes shall be limited to internal use.

Except to the extent that such activity is permitted by applicable law, Licensee shall not reverse engineer, decompile, or disassemble this model. If this model was provided to Licensee in Europe, Licensee shall not reverse engineer, decompile or disassemble the Model for the purposes of error correction.

The License agreement does not entitle Licensee to manufacture in silicon any product based on this model.

The License agreement does not entitle Licensee to use this model for evaluating the validity of any ARM patent.

Source of model available under separate Imperas Software License Agreement.

## 1.3 Limitations

Instruction pipelines are not modeled in any way. All instructions are assumed to complete immediately. This means that instruction barrier instructions (e.g. ISB, CP15ISB) are treated as NOPs, with the exception of any undefined instruction behavior, which is modeled. The model does not implement speculative fetch behavior. The branch cache is not modeled.

Caches and write buffers are not modeled in any way. All loads, fetches and stores complete immediately and in order, and are fully synchronous (as if the memory was of Strongly Ordered or Device-nGnRnE type). Data barrier instructions (e.g. DSB, CP15DSB) are treated as NOPs, with the exception of any undefined instruction behavior, which is modeled. Cache manipulation instructions are implemented as NOPs, with the exception of any undefined instruction behavior, which is modeled.

Real-world timing effects are not modeled: all instructions are assumed to complete in a single cycle.

Performance Monitors are implemented as a register interface only except for the cycle counter, which is implemented assuming one instruction per cycle.

TLBs are architecturally-accurate but not device accurate. This means that all TLB maintenance and address translation operations are fully implemented but the cache is larger than in the real device.

DynamIQ Shared Unit Control registers are implemented as a register interface only - caches and busses are not modeled.

DynamIQ Shared Unit Performance Monitor registers are implemented as a register interface only

- caches and busses are not modeled.

Activity Monitor registers are implemented as a register interface only.

Debug registers are implemented but non-functional (which is sufficient to allow operating systems such as Linux to boot). Debug state is not implemented.

The GICv3 block is implemented without any ITS. Implementation-defined GICR registers for control of LPIs (GICR\_SETLPIR, GICR\_CLRLPIR, GICR\_INVLPIR, GICR\_INVALLR and GICR\_SYNCR) are all implemented.

## 1.4 Verification

Models have been extensively tested by Imperas. ARM Cortex-A models have been successfully used by customers to simulate SMP Linux, Ubuntu Desktop, VxWorks and ThreadX on Xilinx Zynq virtual platforms.

## 1.5 Features

The precise set of implemented features in the model is defined by ID registers. Use overrides to modify these if required (for example `override_PFR0` or `override_AA64PFR0_EL1`).

### 1.5.1 Core Features

AArch64 is implemented at EL3, EL2, EL1 and EL0.

The following ARMv8.0 core features are implemented: FEAT\_CSV2, FEAT\_CSV3, FEAT\_SSBS.

The following ARMv8.0 cryptographic features are implemented: FEAT\_AES, FEAT\_PMULL, FEAT\_SHA1, FEAT\_SHA256.

The following ARMv8.1 core features are implemented: FEAT\_HAFDBS (access flag and dirty state), FEAT\_HPDS, FEAT\_LOR, FEAT\_LSE, FEAT\_PAN, FEAT\_RDM, FEAT\_VHE, FEAT\_VMID16.

The following ARMv8.2 core features are implemented: FEAT\_AA32HPD, FEAT\_DotProd, FEAT\_DPB, FEAT\_FP16, FEAT\_HPDS2, FEAT\_IESB, FEAT\_PAN2, FEAT\_RAS (with no error records), FEAT\_TTCNP, FEAT\_UAO, FEAT\_XNX.

The following ARMv8.3 core features are implemented: FEAT\_LRCPC.

Individual PEs in this cluster are multi-threaded.

### 1.5.2 Memory System

Security extensions are implemented (also known as TrustZone). To make non-secure accesses visible externally, override `ID_AA64MMFR0_EL1.PARange` to specify the required physical bus size (32, 36, 40, 42, 44, 48 or 52 bits) and connect the processor to a bus one bit wider (33, 37,

41, 43, 45, 49 or 53 bits, respectively). The extra most-significant bit is the NS bit, indicating a non-secure access. If non-secure accesses are not required to be made visible externally, connect the processor to a bus of exactly the size implied by ID\_AA64MMFR0\_EL1.PARange.

VMSA EL1, EL2 and EL3 stage 1 address translation is implemented. VMSA stage 2 address translation is implemented.

LPA (large physical address extension) is implemented as standard in ARMv8.

TLB behavior is controlled by parameter ASIDCacheSize. If this parameter is 0, then an unlimited number of TLB entries will be maintained concurrently. If this parameter is non-zero, then only TLB entries for up to ASIDCacheSize different ASIDs will be maintained concurrently initially; as new ASIDs are used, TLB entries for less-recently used ASIDs are deleted, which improves model performance in some cases (especially when 16-bit ASIDs are in use). If the model detects that the TLB entry cache is too small (entry ejections are very frequent), it will increase the cache size automatically. In this variant, ASIDCacheSize is 8

### 1.5.3 Advanced SIMD and Floating-Point Features

SIMD and VFP instructions are implemented.

The model implements trapped exceptions if FPTrap is set to 1 in MVFR0 (for AArch32) or MVFR0\_EL1 (for AArch64). When floating point exception traps are taken, cumulative exception flags are not updated (in other words, cumulative flag state is always the same as prior to instruction execution, even for SIMD instructions). When multiple enabled exceptions are raised by a single floating point operation, the exception reported is the one in least-significant bit position in FPSCR (for AArch32) or FPCR (for AArch64). When multiple enabled exceptions are raised by different SIMD element computations, the exception reported is selected from the lowest-index-number SIMD operation. Contact Imperas if requirements for exception reporting differ from these.

Trapped exceptions not are implemented in this variant (FPTrap=0)

### 1.5.4 Generic Timer

Generic Timer is present. Use parameter “override\_timerScaleFactor” to specify the counter rate as a fraction of the processor MIPS rate (e.g. 10 implies Generic Timer counters increment once every 10 processor instructions).

### 1.5.5 Generic Interrupt Controller

GIC block is implemented (GICv3, including security extensions). Accesses to GIC registers can be viewed externally by connecting to the 32-bit GICRegisters and GICDRegisters bus ports. Secure register accesses are at offset 0x0 on these busses; for example, a secure access to GICD register GICD\_CTLR can be observed by monitoring address 0x00000000 of bus GICDRegisters. Non-secure accesses are at offset 0x80000000 on these busses; for example, a non-secure access to GICD register GICD\_CTLR can be observed by monitoring address 0x80000000 of bus GICDRegisters

GIC Distributor registers are located at address 0x2f000000. Use parameter “override\_GICv3\_DistributorBase” to change this if required.

The internal GIC block can be disabled by raising signal GICCDISABLE, in which case the GIC needs to be modeled using a platform component instead. Input signals `vfiq_CPU<N>` and `virq_CPU<N>` can be used by this component to raise virtual FIQ and IRQ interrupts on cores in the cluster if required.

## 1.6 Debug Mask

It is possible to enable model debug features in various categories. This can be done statically using the “`override_debugMask`” parameter, or dynamically using the “`debugflags`” command. Enabled debug features are specified using a bitmask value, as follows:

Value 0x004: enable debugging of MMU/MPU mappings.

Value 0x020: enable debugging of reads and writes of GIC block registers.

Value 0x040: enable debugging of exception routing via the GIC model component.

Value 0x080: enable debugging of all system register accesses.

Value 0x100: enable debugging of all traps of system register accesses.

Value 0x200: enable verbose debugging of other miscellaneous behavior (for example, the reason why a particular instruction is undefined).

Value 0x400: enable debugging of Performance Monitor timers

Value 0x800: enable dynamic validation of TLB entries against in-memory page table contents (finds some classes of error where page table entries are updated without a subsequent flush of affected TLB entries).

All other bits in the debug bitmask are reserved and must not be set to non-zero values.

## 1.7 Integration Support

This model implements a number of non-architectural pseudo-registers and other features to facilitate integration.

### 1.7.1 Memory Transaction Query

Three registers are intended for use within memory callback functions to provide additional information about the current memory access. Register `transactPL` indicates the processor execution level of the current access (0-3). Note that for load/store translate instructions (e.g. LDRT, STRT) the reported execution level will be 0, indicating an EL0 access. Register `transactAT` indicates the type of memory access: 0 for a normal read or write; and 1 for a physical access resulting from a page table walk. Register `atomicType` indicates whether the current instruction has any special atomic constraints (0 indicates no constraint, 1 indicates atomic, 2 indicates exclusive access).

### 1.7.2 Page Table Walk Query

A banked set of registers provides information about the most recently completed page table walk. There are up to six banks of registers: bank 0 is for stage 1 walks, bank 1 is for stage 2 walks, and banks 2-5 are for stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively. Banks 1-5 are present only for processors with virtualization extensions. The currently active bank can be set using register PTWBankSelect. Register PTWBankValid is a bitmask indicating which banks contain valid data: for example, the value 0xb indicates that banks 0, 1 and 3 contain valid data.

Within each bank, there are registers that record addresses and values read during that page table walk. Register PTWBase records the table base address, register PTWInput contains the input address that starts a walk, register PTWOutput contains the result address and register PTWPgSize contains the page size (PTWOutput and PTWPgSize are valid only if the page table walk completes). Registers PTWAddressL0-PTWAddressL3 record the addresses of level 0 to level 3 entries read, respectively. Register PTWAddressValid is a bitmask indicating which address registers contain valid data: bits 0-3 indicate PTWAddressL0-PTWAddressL3, respectively, bit 4 indicates PTWBase, bit 5 indicates PTWInput, bit 6 indicates both PTWOutput and PTWPgSize. For example, the value 0x73 indicates that PTWBase, PTWInput, PTWOutput, PTWPgSize and PTWAddressL0-L1 are valid but PTWAddressL2-L3 are not. Register PTWAddressNS is a bitmask indicating whether an address is in non-secure memory: bits 0-3 indicate PTWAddressL0-PTWAddressL3, respectively, bit 4 indicates PTWBase, bit 6 indicates PTWOutput (PTWInput is a VA and thus has no secure/non-secure info). Registers PTWValueL0-PTWValueL3 contain page table entry values read at level 0 to level 3. Register PTWValueValid is a bitmask indicating which value registers contain valid data: bits 0-3 indicate PTWValueL0-PTWValueL3, respectively.

### 1.7.3 Artifact Page Table Walks

Registers are also available to enable a simulation environment to initiate an artifact page table walk (for example, to determine the ultimate PA corresponding to a given VA). Register PTWI\_EL1S initiates a secure EL1 table walk for a fetch. Register PTWD\_EL1S initiates a secure EL1 table walk for a load or store (note that current ARM processors have unified TLBs, so these registers are synonymous). Registers PTW[ID]\_EL1NS initiate walks for non-secure EL1 accesses. Registers PTW[ID]\_EL2 initiate EL2 walks. Registers PTW[ID]\_S2 initiate stage 2 walks. Registers PTW[ID]\_EL3 initiate AArch64 EL3 walks. Finally, registers PTW[ID]\_current initiate current-mode walks (useful in a memory callback context). Each walk fills the query registers described above.

### 1.7.4 MMU and Page Table Walk Events

Two events are available that allow a simulation environment to be notified on MMU and page table walk actions. Event mmuEnable triggers when any MMU is enabled or disabled. Event pageTableWalk triggers on completion of any page table walk (including artifact walks).

### 1.7.5 Artifact Address Translations

A simulation environment can trigger an artifact address translation operation by writing to the architectural address translation registers (e.g. ATS1CPR). The results of such translations are written to an integration support register artifactPAR, instead of the architectural PAR register. This means that such artifact writes will not perturb architectural state.

### 1.7.6 TLB Invalidation

A simulation environment can cause TLB state for one or more address translation regimes in the processor to be flushed by writing to the artifact register ResetTLBs. The argument is a bitmask value, in which non-zero bits select the TLBs to be flushed, as follows:

Bit 0: EL0/EL1 stage 1 secure TLB

Bit 1: EL0/EL1 stage 1 non-secure TLB

Bit 2: EL2 stage 1 non-secure TLB

Bit 3: EL0/EL1 stage 2 non-secure TLB

Bit 4: EL3 stage 1 TLB

### 1.7.7 Halt Reason Introspection

An artifact register HaltReason can be read to determine the reason or reasons that a processor is halted. This register is a bitfield, with the following encoding: bit 0 indicates the processor has executed a wait-for-event (WFE) instruction; bit 1 indicates the processor has executed a wait-for-interrupt (WFI) instruction; and bit 2 indicates the processor is held in reset.

### 1.7.8 Automatic WFI Wake Up

A simulation environment can cause a core to wake up from the WFI state by writing to the artifact register WakeWFINow.

### 1.7.9 System Register Access Monitor

If parameter “enableSystemMonitorBus” is True, an artifact 32-bit bus “SystemMonitor” is enabled for each PE. Every system register read or write by that PE is then visible as a read or write on this artifact bus, and can therefore be monitored using callbacks installed in the client environment (use opBusReadMonitorAdd/opBusWriteMonitorAdd or icmAddBusReadCallback/icmAddBusWriteCallback, depending on the client API). The format of the address on the bus is as follows:

bits 31:26 - zero

bit 25 - 1 if AArch64 access, 0 if AArch32 access

bit 24 - 1 if non-secure access, 0 if secure access

bits 23:20 - CRm value

bits 19:16 - CRn value

bits 15:12 - op2 value

bits 11:8 - op1 value

bits 7:4 - op0 value (AArch64) or coprocessor number (AArch32)

bits 3:0 - zero

As an example, to view non-secure writes to writes to CNTFRQ\_EL0 in AArch64 state, install a write monitor on address range 0x020e0330:0x020e0333.

### 1.7.10 System Register Implementation

If parameter “enableSystemBus” is True, an artifact 32-bit bus “System” is enabled for each PE. Slave callbacks installed on this bus can be used to implement modified system register behavior (use opBusSlaveNew or icmMapExternalMemory, depending on the client API). The format of the address on the bus is the same as for the system monitor bus, described above.

## Chapter 2

# Configuration

### 2.1 Location

This model's VLVN is `arm.ovpworld.org/processor/arm/1.0`.

The model source is usually at:

`$IMPERAS_HOME/ImperasLib/source/arm.ovpworld.org/processor/arm/1.0`

The model binary is usually at:

`$IMPERAS_HOME/lib/$IMPERAS_ARCH/ImperasLib/arm.ovpworld.org/processor/arm/1.0`

### 2.2 GDB Path

The default GDB for this model is: `$IMPERAS_HOME/lib/$IMPERAS_ARCH/gdb/aarch64-none-elf-gdb`.

### 2.3 Semi-Host Library

The default semi-host library file is `arm.ovpworld.org/semihosting/armAngel/1.0`

### 2.4 Processor Endian-ness

This is a LITTLE endian model.

### 2.5 QuantumLeap Support

This processor is qualified to run in a QuantumLeap enabled simulator.

### 2.6 Processor ELF code

ELF codes supported by this model are: 0xb7 and 0x28.

## Chapter 3

# All Variants in this model

This model has these variants

| Variant     | Description |
|-------------|-------------|
| ARMv4T      |             |
| ARMv4xM     |             |
| ARMv4       |             |
| ARMv4TxM    |             |
| ARMv5xM     |             |
| ARMv5       |             |
| ARMv5TxM    |             |
| ARMv5T      |             |
| ARMv5TExP   |             |
| ARMv5TE     |             |
| ARMv5TEJ    |             |
| ARMv6       |             |
| ARMv6K      |             |
| ARMv6T2     |             |
| ARMv6KZ     |             |
| ARMv7       |             |
| ARM7TDMI    |             |
| ARM7EJ-S    |             |
| ARM720T     |             |
| ARM920T     |             |
| ARM922T     |             |
| ARM926EJ-S  |             |
| ARM940T     |             |
| ARM946E     |             |
| ARM966E     |             |
| ARM968E-S   |             |
| ARM1020E    |             |
| ARM1022E    |             |
| ARM1026EJ-S |             |
| ARM1136J-S  |             |
| ARM1156T2-S |             |

|                 |  |
|-----------------|--|
| ARM1176JZ-S     |  |
| Cortex-R4       |  |
| Cortex-R4F      |  |
| Cortex-R5MPx1   |  |
| Cortex-R5MPx2   |  |
| Cortex-R8MPx1   |  |
| Cortex-R8MPx2   |  |
| Cortex-R8MPx3   |  |
| Cortex-R8MPx4   |  |
| Cortex-R52MPx1  |  |
| Cortex-R52MPx2  |  |
| Cortex-R52MPx3  |  |
| Cortex-R52MPx4  |  |
| Cortex-R52+MPx1 |  |
| Cortex-R52+MPx2 |  |
| Cortex-R52+MPx3 |  |
| Cortex-R52+MPx4 |  |
| Cortex-R82MPx1  |  |
| Cortex-R82MPx2  |  |
| Cortex-R82MPx3  |  |
| Cortex-R82MPx4  |  |
| Cortex-R82MPx5  |  |
| Cortex-R82MPx6  |  |
| Cortex-R82MPx7  |  |
| Cortex-R82MPx8  |  |
| Cortex-A5UP     |  |
| Cortex-A5MPx1   |  |
| Cortex-A5MPx2   |  |
| Cortex-A5MPx3   |  |
| Cortex-A5MPx4   |  |
| Cortex-A8       |  |
| Cortex-A9UP     |  |
| Cortex-A9MPx1   |  |
| Cortex-A9MPx2   |  |
| Cortex-A9MPx3   |  |
| Cortex-A9MPx4   |  |
| Cortex-A7UP     |  |
| Cortex-A7MPx1   |  |
| Cortex-A7MPx2   |  |
| Cortex-A7MPx3   |  |
| Cortex-A7MPx4   |  |
| Cortex-A15UP    |  |
| Cortex-A15MPx1  |  |
| Cortex-A15MPx2  |  |
| Cortex-A15MPx3  |  |

|                  |                              |
|------------------|------------------------------|
| Cortex-A15MPx4   |                              |
| Cortex-A17MPx1   |                              |
| Cortex-A17MPx2   |                              |
| Cortex-A17MPx3   |                              |
| Cortex-A17MPx4   |                              |
| AArch32          |                              |
| AArch64          |                              |
| Cortex-A32MPx1   |                              |
| Cortex-A32MPx2   |                              |
| Cortex-A32MPx3   |                              |
| Cortex-A32MPx4   |                              |
| Cortex-A35MPx1   |                              |
| Cortex-A35MPx2   |                              |
| Cortex-A35MPx3   |                              |
| Cortex-A35MPx4   |                              |
| Cortex-A53MPx1   |                              |
| Cortex-A53MPx2   |                              |
| Cortex-A53MPx3   |                              |
| Cortex-A53MPx4   |                              |
| Cortex-A55MPx1   |                              |
| Cortex-A55MPx2   |                              |
| Cortex-A55MPx3   |                              |
| Cortex-A55MPx4   |                              |
| Cortex-A57MPx1   |                              |
| Cortex-A57MPx2   |                              |
| Cortex-A57MPx3   |                              |
| Cortex-A57MPx4   |                              |
| Cortex-A65AEMPx1 |                              |
| Cortex-A65AEMPx2 |                              |
| Cortex-A65AEMPx3 |                              |
| Cortex-A65AEMPx4 | (described in this document) |
| Cortex-A72MPx1   |                              |
| Cortex-A72MPx2   |                              |
| Cortex-A72MPx3   |                              |
| Cortex-A72MPx4   |                              |
| Cortex-A73MPx1   |                              |
| Cortex-A73MPx2   |                              |
| Cortex-A73MPx3   |                              |
| Cortex-A73MPx4   |                              |
| Cortex-A75MPx1   |                              |
| Cortex-A75MPx2   |                              |
| Cortex-A75MPx3   |                              |
| Cortex-A75MPx4   |                              |
| Cortex-A76MPx1   |                              |
| Cortex-A76MPx2   |                              |

|                |  |
|----------------|--|
| Cortex-A76MPx3 |  |
| Cortex-A76MPx4 |  |
| Cortex-A78MPx1 |  |
| Cortex-A78MPx2 |  |
| Cortex-A78MPx3 |  |
| Cortex-A78MPx4 |  |
| MultiCluster   |  |

Table 3.1: All Variants in this model

## Chapter 4

# Bus Master Ports

This model has these bus master ports.

| <b>Name</b>   | min | max | Connect?  | Description                       |
|---------------|-----|-----|-----------|-----------------------------------|
| INSTRUCTION   | 32  | 53  | mandatory |                                   |
| DATA          | 32  | 53  | optional  |                                   |
| GICRegisters  | 32  | 32  | optional  | GIC memory-mapped register block  |
| GICDRegisters | 32  | 32  | optional  | GICD memory-mapped register block |

Table 4.1: Bus Master Ports

## Chapter 5

# Bus Slave Ports

This model has no bus slave ports.

## Chapter 6

# Net Ports

This model has these net ports.

| Name  | Type  | Connect? | Description                 |
|-------|-------|----------|-----------------------------|
| SPI32 | input | optional | Shared peripheral interrupt |
| SPI33 | input | optional | Shared peripheral interrupt |
| SPI34 | input | optional | Shared peripheral interrupt |
| SPI35 | input | optional | Shared peripheral interrupt |
| SPI36 | input | optional | Shared peripheral interrupt |
| SPI37 | input | optional | Shared peripheral interrupt |
| SPI38 | input | optional | Shared peripheral interrupt |
| SPI39 | input | optional | Shared peripheral interrupt |
| SPI40 | input | optional | Shared peripheral interrupt |
| SPI41 | input | optional | Shared peripheral interrupt |
| SPI42 | input | optional | Shared peripheral interrupt |
| SPI43 | input | optional | Shared peripheral interrupt |
| SPI44 | input | optional | Shared peripheral interrupt |
| SPI45 | input | optional | Shared peripheral interrupt |
| SPI46 | input | optional | Shared peripheral interrupt |
| SPI47 | input | optional | Shared peripheral interrupt |
| SPI48 | input | optional | Shared peripheral interrupt |
| SPI49 | input | optional | Shared peripheral interrupt |
| SPI50 | input | optional | Shared peripheral interrupt |
| SPI51 | input | optional | Shared peripheral interrupt |
| SPI52 | input | optional | Shared peripheral interrupt |
| SPI53 | input | optional | Shared peripheral interrupt |
| SPI54 | input | optional | Shared peripheral interrupt |
| SPI55 | input | optional | Shared peripheral interrupt |
| SPI56 | input | optional | Shared peripheral interrupt |
| SPI57 | input | optional | Shared peripheral interrupt |
| SPI58 | input | optional | Shared peripheral interrupt |
| SPI59 | input | optional | Shared peripheral interrupt |
| SPI60 | input | optional | Shared peripheral interrupt |
| SPI61 | input | optional | Shared peripheral interrupt |

|               |        |          |                                                                                      |
|---------------|--------|----------|--------------------------------------------------------------------------------------|
| SPI62         | input  | optional | Shared peripheral interrupt                                                          |
| SPI63         | input  | optional | Shared peripheral interrupt                                                          |
| SPI64         | input  | optional | Shared peripheral interrupt                                                          |
| SPI65         | input  | optional | Shared peripheral interrupt                                                          |
| SPI66         | input  | optional | Shared peripheral interrupt                                                          |
| SPI67         | input  | optional | Shared peripheral interrupt                                                          |
| SPI68         | input  | optional | Shared peripheral interrupt                                                          |
| SPI69         | input  | optional | Shared peripheral interrupt                                                          |
| SPI70         | input  | optional | Shared peripheral interrupt                                                          |
| SPI71         | input  | optional | Shared peripheral interrupt                                                          |
| SPI72         | input  | optional | Shared peripheral interrupt                                                          |
| SPI73         | input  | optional | Shared peripheral interrupt                                                          |
| SPI74         | input  | optional | Shared peripheral interrupt                                                          |
| SPI75         | input  | optional | Shared peripheral interrupt                                                          |
| SPI76         | input  | optional | Shared peripheral interrupt                                                          |
| SPI77         | input  | optional | Shared peripheral interrupt                                                          |
| SPI78         | input  | optional | Shared peripheral interrupt                                                          |
| SPI79         | input  | optional | Shared peripheral interrupt                                                          |
| SPI80         | input  | optional | Shared peripheral interrupt                                                          |
| SPI81         | input  | optional | Shared peripheral interrupt                                                          |
| SPI82         | input  | optional | Shared peripheral interrupt                                                          |
| SPI83         | input  | optional | Shared peripheral interrupt                                                          |
| SPI84         | input  | optional | Shared peripheral interrupt                                                          |
| SPI85         | input  | optional | Shared peripheral interrupt                                                          |
| SPI86         | input  | optional | Shared peripheral interrupt                                                          |
| SPI87         | input  | optional | Shared peripheral interrupt                                                          |
| SPI88         | input  | optional | Shared peripheral interrupt                                                          |
| SPI89         | input  | optional | Shared peripheral interrupt                                                          |
| SPI90         | input  | optional | Shared peripheral interrupt                                                          |
| SPI91         | input  | optional | Shared peripheral interrupt                                                          |
| SPI92         | input  | optional | Shared peripheral interrupt                                                          |
| SPI93         | input  | optional | Shared peripheral interrupt                                                          |
| SPI94         | input  | optional | Shared peripheral interrupt                                                          |
| SPI95         | input  | optional | Shared peripheral interrupt                                                          |
| SPIVector     | input  | optional | Shared peripheral interrupt vectorized input                                         |
| periphReset   | input  | optional | Peripheral reset (active high)                                                       |
| GICCDISABLE   | input  | optional | GIC CPU interface logic disable (active high, sampled on rising edge of periphReset) |
| EVENTI        | input  | optional | Event input signal, active on rising edge                                            |
| EVENTO        | output | optional | Event output signal, active on rising edge                                           |
| PPI16_CPU0_T0 | input  | optional | Private peripheral interrupt                                                         |
| PPI17_CPU0_T0 | input  | optional | Private peripheral interrupt                                                         |
| PPI18_CPU0_T0 | input  | optional | Private peripheral interrupt                                                         |

|                    |        |          |                                                                           |
|--------------------|--------|----------|---------------------------------------------------------------------------|
| PPI19_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU0_T0      | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU0_T0    | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU0_T0   | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU0_T0  | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU0_T0  | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU0_T0   | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU0_T0     | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU0_T0     | output | optional | FIQ wakeup                                                                |
| CLUSTERIDAFF1      | input  | optional | Configure MPIDR.Aff1                                                      |
| CLUSTERIDAFF2      | input  | optional | Configure MPIDR.Aff2                                                      |
| CLUSTERIDAFF3      | input  | optional | Configure MPIDR.Aff3                                                      |
| RVBARADDRx_CPU0_T0 | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITHI_CPU0_T0    | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU0_T0     | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU0_T0      | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU0_T0      | input  | optional | Processor reset, active high                                              |
| fiq_CPU0_T0        | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU0_T0        | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU0_T0        | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfq_CPU0_T0        | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU0_T0       | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU0_T0       | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |

|                      |        |          |                                                      |
|----------------------|--------|----------|------------------------------------------------------|
| haltReason_CPU0_T0   | output | optional | Indicates why core is halted                         |
| AXI_SLVERR_CPU0_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)         |
| CP15SDISABLE_CPU0_T0 | input  | optional | CP15SDISABLE (active high)                           |
| PMUIRQ_CPU0_T0       | output | optional | Performance monitor event (active high)              |
| syncCluster_CPU0_T0  | output | optional | Cluster synchronization required                     |
| updateTimer_CPU0_T0  | output | optional | Internal timer update                                |
| PPI16_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI17_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI18_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI19_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI20_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI21_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI22_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI23_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI24_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI25_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI26_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI27_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI28_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI29_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI30_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| PPI31_CPU0_T1        | input  | optional | Private peripheral interrupt                         |
| CNTVIRQ_CPU0_T1      | output | optional | EL1 Virtual timer event (active high)                |
| CNTPSIRQ_CPU0_T1     | output | optional | EL3 Physical timer event (active high)               |
| CNTPNSIRQ_CPU0_T1    | output | optional | EL1 Physical timer event (active high)               |
| CNTPHPIRQ_CPU0_T1    | output | optional | Non-secure EL2 Physical timer event (active high)    |
| CNTHVIRQ_CPU0_T1     | output | optional | Non-secure EL2 Virtual timer event (active high)     |
| IRQOUT_CPU0_T1       | output | optional | IRQ wakeup                                           |
| FIQOUT_CPU0_T1       | output | optional | FIQ wakeup                                           |
| RVBARADDRx_CPU0_T1   | input  | optional | Configure AArch64 Reset Vector Base Address at reset |
| VINITH1_CPU0_T1      | input  | optional | Configure HIVECS mode (SCTLR.V)                      |
| CFGEND_CPU0_T1       | input  | optional | Configure exception endianness (SCTLR.EE)            |
| CFGTE_CPU0_T1        | input  | optional | Configure exception state at reset (SCTLR.TE)        |
| reset_CPU0_T1        | input  | optional | Processor reset, active high                         |
| fiq_CPU0_T1          | input  | optional | FIQ interrupt, active high (negation of nFIQ)        |
| irq_CPU0_T1          | input  | optional | IRQ interrupt, active high (negation of nIRQ)        |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| sei_CPU0_T1          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU0_T1         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU0_T1         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU0_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU0_T1   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU0_T1   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU0_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU0_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU0_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU0_T1  | output | optional | Internal timer update                                                     |
| PPI16_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU1_T0        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU1_T0      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU1_T0     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU1_T0    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU1_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU1_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU1_T0       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU1_T0       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU1_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU1_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU1_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| CFGTE_CPU1_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU1_T0        | input  | optional | Processor reset, active high                                              |
| fiq_CPU1_T0          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU1_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU1_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfq_CPU1_T0          | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU1_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU1_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU1_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU1_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU1_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU1_T0       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU1_T0  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU1_T0  | output | optional | Internal timer update                                                     |
| PPI16_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU1_T1        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU1_T1      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU1_T1     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU1_T1    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU1_T1    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU1_T1     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| IRQOUT_CPU1_T1       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU1_T1       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU1_T1   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITHL_CPU1_T1      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU1_T1       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU1_T1        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU1_T1        | input  | optional | Processor reset, active high                                              |
| fiq_CPU1_T1          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU1_T1          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU1_T1          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfq_CPU1_T1          | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU1_T1         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU1_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU1_T1   | output | optional | Indicates why core is halted                                              |
| AXISLVERR_CPU1_T1    | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU1_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU1_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU1_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU1_T1  | output | optional | Internal timer update                                                     |
| PPI16_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU2_T0        | input  | optional | Private peripheral interrupt                                              |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| CNTVIRQ_CPU2_T0      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU2_T0     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU2_T0    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU2_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU2_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU2_T0       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU2_T0       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU2_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU2_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU2_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU2_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU2_T0        | input  | optional | Processor reset, active high                                              |
| fiq_CPU2_T0          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU2_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU2_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU2_T0         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU2_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU2_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU2_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU2_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU2_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU2_T0       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU2_T0  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU2_T0  | output | optional | Internal timer update                                                     |
| PPI16_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| PPI26_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU2_T1        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU2_T1      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU2_T1     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU2_T1    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU2_T1    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU2_T1     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU2_T1       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU2_T1       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU2_T1   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU2_T1      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU2_T1       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU2_T1        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU2_T1        | input  | optional | Processor reset, active high                                              |
| fiq_CPU2_T1          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU2_T1          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU2_T1          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfq_CPU2_T1          | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU2_T1         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU2_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU2_T1   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU2_T1   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU2_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU2_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU2_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU2_T1  | output | optional | Internal timer update                                                     |
| PPI16_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| PPI20_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU3_T0        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU3_T0      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU3_T0     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU3_T0    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU3_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU3_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU3_T0       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU3_T0       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU3_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU3_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU3_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU3_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU3_T0        | input  | optional | Processor reset, active high                                              |
| firq_CPU3_T0         | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU3_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU3_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfirq_CPU3_T0        | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU3_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU3_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU3_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU3_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU3_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU3_T0       | output | optional | Performance monitor event (active high)                                   |

|                     |        |          |                                                                  |
|---------------------|--------|----------|------------------------------------------------------------------|
| syncCluster_CPU3_T0 | output | optional | Cluster synchronization required                                 |
| updateTimer_CPU3_T0 | output | optional | Internal timer update                                            |
| PPI16_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI17_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI18_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI19_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI20_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI21_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI22_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI23_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI24_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI25_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI26_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI27_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI28_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI29_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI30_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| PPI31_CPU3_T1       | input  | optional | Private peripheral interrupt                                     |
| CNTVIRQ_CPU3_T1     | output | optional | EL1 Virtual timer event (active high)                            |
| CNTPSIRQ_CPU3_T1    | output | optional | EL3 Physical timer event (active high)                           |
| CNTPNSIRQ_CPU3_T1   | output | optional | EL1 Physical timer event (active high)                           |
| CNTPHPIRQ_CPU3_T1   | output | optional | Non-secure EL2 Physical timer event (active high)                |
| CNTHVIRQ_CPU3_T1    | output | optional | Non-secure EL2 Virtual timer event (active high)                 |
| IRQOUT_CPU3_T1      | output | optional | IRQ wakeup                                                       |
| FIQOUT_CPU3_T1      | output | optional | FIQ wakeup                                                       |
| RVBARADDRx_CPU3_T1  | input  | optional | Configure AArch64 Reset Vector Base Address at reset             |
| VINITHL_CPU3_T1     | input  | optional | Configure HIVECS mode (SCTLR.V)                                  |
| CFGEND_CPU3_T1      | input  | optional | Configure exception endianness (SCTLR.EE)                        |
| CFGTE_CPU3_T1       | input  | optional | Configure exception state at reset (SCTLR.TE)                    |
| reset_CPU3_T1       | input  | optional | Processor reset, active high                                     |
| fiq_CPU3_T1         | input  | optional | FIQ interrupt, active high (negation of nFIQ)                    |
| irq_CPU3_T1         | input  | optional | IRQ interrupt, active high (negation of nIRQ)                    |
| sei_CPU3_T1         | input  | optional | System error interrupt, active on rising edge (negation of nSEI) |
| vfq_CPU3_T1         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)           |
| virq_CPU3_T1        | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)           |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| vsei_CPU3_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU3_T1   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU3_T1   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU3_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU3_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU3_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU3_T1  | output | optional | Internal timer update                                                     |
| PPI16_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU4_T0        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU4_T0      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU4_T0     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU4_T0    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU4_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU4_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU4_T0       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU4_T0       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU4_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU4_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU4_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU4_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU4_T0        | input  | optional | Processor reset, active high                                              |
| fiq_CPU4_T0          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| irq_CPU4_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU4_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU4_T0         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU4_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU4_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU4_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU4_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU4_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU4_T0       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU4_T0  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU4_T0  | output | optional | Internal timer update                                                     |
| PPI16_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU4_T1        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU4_T1      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU4_T1     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU4_T1    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU4_T1    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU4_T1     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU4_T1       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU4_T1       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU4_T1   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITIL_CPU4_T1      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| CFGEND_CPU4_T1       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU4_T1        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU4_T1        | input  | optional | Processor reset, active high                                              |
| fiq_CPU4_T1          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU4_T1          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU4_T1          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU4_T1         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU4_T1         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU4_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU4_T1   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU4_T1   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU4_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU4_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU4_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU4_T1  | output | optional | Internal timer update                                                     |
| PPI16_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU5_T0        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU5_T0      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU5_T0     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU5_T0    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU5_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                         |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| CNTHVIRQ_CPU5_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU5_T0       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU5_T0       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU5_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITI1_CPU5_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU5_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU5_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU5_T0        | input  | optional | Processor reset, active high                                              |
| fiq_CPU5_T0          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU5_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU5_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU5_T0         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU5_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU5_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU5_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU5_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU5_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU5_T0       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU5_T0  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU5_T0  | output | optional | Internal timer update                                                     |
| PPI16_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| PPI30_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU5_T1        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU5_T1      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU5_T1     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU5_T1    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU5_T1    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU5_T1     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU5_T1       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU5_T1       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU5_T1   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU5_T1      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU5_T1       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU5_T1        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU5_T1        | input  | optional | Processor reset, active high                                              |
| fiq_CPU5_T1          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU5_T1          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU5_T1          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU5_T1         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU5_T1         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU5_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU5_T1   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU5_T1   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU5_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU5_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU5_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU5_T1  | output | optional | Internal timer update                                                     |
| PPI16_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| PPI24_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU6_T0        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU6_T0      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU6_T0     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU6_T0    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU6_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU6_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU6_T0       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU6_T0       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU6_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU6_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU6_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU6_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU6_T0        | input  | optional | Processor reset, active high                                              |
| fiq_CPU6_T0          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU6_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU6_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfq_CPU6_T0          | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU6_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU6_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU6_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU6_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU6_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU6_T0       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU6_T0  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU6_T0  | output | optional | Internal timer update                                                     |
| PPI16_CPU6_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU6_T1        | input  | optional | Private peripheral interrupt                                              |

|                    |        |          |                                                                           |
|--------------------|--------|----------|---------------------------------------------------------------------------|
| PPI18_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU6_T1      | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU6_T1    | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU6_T1   | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU6_T1  | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHIRQ_CPU6_T1   | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU6_T1   | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU6_T1     | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU6_T1     | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU6_T1 | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU6_T1    | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU6_T1     | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU6_T1      | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU6_T1      | input  | optional | Processor reset, active high                                              |
| fiq_CPU6_T1        | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU6_T1        | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU6_T1        | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfq_CPU6_T1        | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU6_T1       | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU6_T1       | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU6_T1 | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU6_T1 | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |

|                      |        |          |                                                                  |
|----------------------|--------|----------|------------------------------------------------------------------|
| CP15SDISABLE_CPU6_T1 | input  | optional | CP15SDISABLE (active high)                                       |
| PMUIRQ_CPU6_T1       | output | optional | Performance monitor event (active high)                          |
| syncCluster_CPU6_T1  | output | optional | Cluster synchronization required                                 |
| updateTimer_CPU6_T1  | output | optional | Internal timer update                                            |
| PPI16_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI17_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI18_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI19_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI20_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI21_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI22_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI23_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI24_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI25_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI26_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI27_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI28_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI29_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI30_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| PPI31_CPU7_T0        | input  | optional | Private peripheral interrupt                                     |
| CNTVIRQ_CPU7_T0      | output | optional | EL1 Virtual timer event (active high)                            |
| CNTPSIRQ_CPU7_T0     | output | optional | EL3 Physical timer event (active high)                           |
| CNTPNSIRQ_CPU7_T0    | output | optional | EL1 Physical timer event (active high)                           |
| CNTPHPIRQ_CPU7_T0    | output | optional | Non-secure EL2 Physical timer event (active high)                |
| CNTHVIRQ_CPU7_T0     | output | optional | Non-secure EL2 Virtual timer event (active high)                 |
| IRQOUT_CPU7_T0       | output | optional | IRQ wakeup                                                       |
| FIQOUT_CPU7_T0       | output | optional | FIQ wakeup                                                       |
| RVBARADDRx_CPU7_T0   | input  | optional | Configure AArch64 Reset Vector Base Address at reset             |
| VINITH1_CPU7_T0      | input  | optional | Configure HIVECS mode (SCTLR.V)                                  |
| CFGEND_CPU7_T0       | input  | optional | Configure exception endianness (SCTLR.EE)                        |
| CFGTE_CPU7_T0        | input  | optional | Configure exception state at reset (SCTLR.TE)                    |
| reset_CPU7_T0        | input  | optional | Processor reset, active high                                     |
| fiq_CPU7_T0          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                    |
| irq_CPU7_T0          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                    |
| sei_CPU7_T0          | input  | optional | System error interrupt, active on rising edge (negation of nSEI) |
| vfiq_CPU7_T0         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)           |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| virq_CPU7_T0         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU7_T0         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU7_T0   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU7_T0   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU7_T0 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU7_T0       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU7_T0  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU7_T0  | output | optional | Internal timer update                                                     |
| PPI16_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI17_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI18_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI19_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI20_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI21_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI22_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI23_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI24_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI25_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI26_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI27_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI28_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI29_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI30_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| PPI31_CPU7_T1        | input  | optional | Private peripheral interrupt                                              |
| CNTVIRQ_CPU7_T1      | output | optional | EL1 Virtual timer event (active high)                                     |
| CNTPSIRQ_CPU7_T1     | output | optional | EL3 Physical timer event (active high)                                    |
| CNTPNSIRQ_CPU7_T1    | output | optional | EL1 Physical timer event (active high)                                    |
| CNTPHPIRQ_CPU7_T1    | output | optional | Non-secure EL2 Physical timer event (active high)                         |
| CNTHVIRQ_CPU7_T1     | output | optional | Non-secure EL2 Virtual timer event (active high)                          |
| IRQOUT_CPU7_T1       | output | optional | IRQ wakeup                                                                |
| FIQOUT_CPU7_T1       | output | optional | FIQ wakeup                                                                |
| RVBARADDRx_CPU7_T1   | input  | optional | Configure AArch64 Reset Vector Base Address at reset                      |
| VINITH1_CPU7_T1      | input  | optional | Configure HIVECS mode (SCTLR.V)                                           |
| CFGEND_CPU7_T1       | input  | optional | Configure exception endianness (SCTLR.EE)                                 |
| CFGTE_CPU7_T1        | input  | optional | Configure exception state at reset (SCTLR.TE)                             |
| reset_CPU7_T1        | input  | optional | Processor reset, active high                                              |

|                      |        |          |                                                                           |
|----------------------|--------|----------|---------------------------------------------------------------------------|
| fiq_CPU7_T1          | input  | optional | FIQ interrupt, active high (negation of nFIQ)                             |
| irq_CPU7_T1          | input  | optional | IRQ interrupt, active high (negation of nIRQ)                             |
| sei_CPU7_T1          | input  | optional | System error interrupt, active on rising edge (negation of nSEI)          |
| vfiq_CPU7_T1         | input  | optional | Virtual FIQ interrupt, active high (negation of nVFIQ)                    |
| virq_CPU7_T1         | input  | optional | Virtual IRQ interrupt, active high (negation of nVIRQ)                    |
| vsei_CPU7_T1         | input  | optional | Virtual system error interrupt, active on rising edge (negation of nVSEI) |
| haltReason_CPU7_T1   | output | optional | Indicates why core is halted                                              |
| AXI_SLVERR_CPU7_T1   | input  | optional | AXI external abort type (DECERR=0, SLVERR=1)                              |
| CP15SDISABLE_CPU7_T1 | input  | optional | CP15SDISABLE (active high)                                                |
| PMUIRQ_CPU7_T1       | output | optional | Performance monitor event (active high)                                   |
| syncCluster_CPU7_T1  | output | optional | Cluster synchronization required                                          |
| updateTimer_CPU7_T1  | output | optional | Internal timer update                                                     |

Table 6.1: Net Ports

## Chapter 7

# FIFO Ports

This model has no FIFO ports.

## Chapter 8

# Formal Parameters

| Name                   | Type        | Description                                                                                                                                        |
|------------------------|-------------|----------------------------------------------------------------------------------------------------------------------------------------------------|
| verbose                | Boolean     | Specify verbosity of output                                                                                                                        |
| suppressCPSWarnings    | Boolean     | Suppress duplicate warnings generated using ARM_CP_CPSI or ARM_CP_CPSD message identifiers                                                         |
| showHiddenRegs         | Boolean     | Show hidden registers during register tracing                                                                                                      |
| UAL                    | Boolean     | Disassemble using UAL syntax                                                                                                                       |
| disableGICModel        | Boolean     | Disable the internal GIC model entirely                                                                                                            |
| enableGICv3            | Boolean     | Enable/disable GICv3 support                                                                                                                       |
| enableGICv2_64kB_Page  | Boolean     | Enable 64kB page size for GICv2 memory-mapped register groups (Xilinx Zynq Ultra-scale support)                                                    |
| supportSTATUSR         | Boolean     | Enable/disable support for GICv3 GIC[CDV]_STATUSR registers                                                                                        |
| enableVFPAAtReset      | Boolean     | Enable vector floating point (SIMD and VFP) instructions at reset. (Enables cp10/11 in CPACR and sets FPEXC.EN)                                    |
| SVEImplementedSizes    | Uns32       | For processors with ARMv8.2 SVE extension, mask of configurable vector sizes (vector length N is configurable if mask contains $1 < ((N/128)-1)$ ) |
| SVEFaultUnknown        | Uns64       | For processors with ARMv8.2 SVE extension, UNKNOWN value returned for suppressed or inactive FFR elements                                          |
| enableSystemBus        | Boolean     | Add 32-bit artifact System bus port, allowing system registers to be externally implemented                                                        |
| enableSystemMonitorBus | Boolean     | Add 32-bit artifact SystemMonitor bus port, allowing system register accesses to be externally monitored                                           |
| distinctMTCores        | Boolean     | For multi-threaded (MT) processors, simulate threads as separate cores (otherwise, simulate MT threads as a single entity)                         |
| compatibility          | Enumeration | Specify compatibility mode                                                                                                                         |
|                        | ISA         |                                                                                                                                                    |
|                        | gdb         |                                                                                                                                                    |
|                        | nopSVC      |                                                                                                                                                    |
| unpredictableR15       | Enumeration | Specify behavior for UNPREDICTABLE uses of AArch32 R15 register                                                                                    |
|                        | undefined   |                                                                                                                                                    |
|                        | nop         |                                                                                                                                                    |
|                        | raz_wi      |                                                                                                                                                    |

|                           |             |                                                                                                                                                                                      |
|---------------------------|-------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                           | execute     |                                                                                                                                                                                      |
|                           | assert      |                                                                                                                                                                                      |
| unpredictableModal        | Enumeration | Specify behavior for UNPREDICTABLE instructions in certain AArch32 modes (for example, MRS using SPSR in System mode)                                                                |
|                           | undefined   |                                                                                                                                                                                      |
|                           | nop         |                                                                                                                                                                                      |
|                           | assert      |                                                                                                                                                                                      |
| maxSIMDUnroll             | Uns32       | If SIMD operations are supported, specify the maximum number of parallel SIMD operations to unroll (unrolled operations can be faster, but produce more verbose JIT code)            |
| override_debugMask        | Uns32       | Specifies debug mask, enabling debug output for model components                                                                                                                     |
| ASIDCacheSize             | Uns32       | Specifies the number of different ASIDs for which TLB entries are cached; a value of 0 implies no limit                                                                              |
| thumbNoCond               | Boolean     | Specify whether trapped Thumb instructions set CV=1 and COND field in syndrome (if False, both are zero)                                                                             |
| enableHostAtomics         | Boolean     | Enable use of host atomic instructions to emulate load/store exclusive operations (not architecturally accurate, accelerates parallel simulation)                                    |
| enableWFEHostAtomics      | Boolean     | Enable WFE and SEV instructions when using host atomics (does nothing otherwise)                                                                                                     |
| override_numCPUs          | Uns32       | Specify the number of cores in a multiprocessor (maximum of 8 for GICv1/GICv2)                                                                                                       |
| override_affinityMask     | Uns32       | Specify bitmask of implemented affinity bits in format Aff3:Aff2:Aff1:Aff0 (each a byte)                                                                                             |
| override_MPIDR_MT         | Boolean     | Specifies that processor is multithreaded                                                                                                                                            |
| override_MPIDR_Aff0       | Uns32       | Override Aff0 field in MPIDR/MPIDR_EL1 register                                                                                                                                      |
| override_MPIDR_Aff1       | Uns32       | Override Aff1 field in MPIDR/MPIDR_EL1 register (also possible by writing CLUSTERIDAFF1 configuration net)                                                                           |
| override_MPIDR_Aff2       | Uns32       | Override Aff2 field in MPIDR/MPIDR_EL1 register (also possible by writing CLUSTERIDAFF2 configuration net)                                                                           |
| override_MPIDR_Aff3       | Uns32       | Override Aff3 field in MPIDR_EL1 register (also possible by writing CLUSTERIDAFF3 configuration net)                                                                                 |
| override_fcsePresent      | Boolean     | Specifies that FCSE is present (if true)                                                                                                                                             |
| override_fpexcDexPresent  | Boolean     | Specifies that the FPEXC.DEX register field is implemented (if true)                                                                                                                 |
| override_advSIMDPresent   | Boolean     | Specifies that Advanced SIMD extensions are present (if true)                                                                                                                        |
| override_vfpPresent       | Boolean     | Specifies that VFP extensions are present (if true)                                                                                                                                  |
| override_physicalBits     | Uns32       | Specifies the implemented physical bus bits (defaults to connected physical bus width)                                                                                               |
| override_timerScaleFactor | Uns32       | Specifies the fraction of MIPS rate to use for MPCore timers (generic timers or global/local/watchdogs depending on implementation). Defaults to 20 for generic timers, 2 for others |

|                                |         |                                                                                                                                 |
|--------------------------------|---------|---------------------------------------------------------------------------------------------------------------------------------|
| override_GICD_NSACRPresent     | Boolean | Specifies that optional GICD_NSACR distributor registers are present (GICv2 only)                                               |
| override_GICD_PPISRPresent     | Boolean | Specifies that implementation-specific GICD_PPISR distributor register is present (GICv1 ICDPPIS/ICPPISR, GICv1 and GICv2 only) |
| override_GICD_SPISRPresent     | Boolean | Specifies that implementation-specific GICD_SPISR distributor registers are present (GICv1 ICDSPIS/ICSPISR)                     |
| override_GICv3_DistributorBase | Uns64   | Specify distributor register block base address (GICv3 only)                                                                    |
| override_GICv3_E1NWFPresent    | Boolean | Specifies that GICR_CTLR.E1NWF is implemented (GICv3 only)                                                                      |
| override_GICv3_ROAffinity      | Boolean | Specifies that affinity bits in the GICD_IROUTER<n> registers are initialised from MPIDR and Read-Only                          |
| override_GIC_PPIMask           | Uns32   | Specify bitmask of implemented PPIs in the GIC (e.g. ID16 is 0x0001, ID31 is 0x8000)                                            |
| override_GICCDISABLE           | Boolean | Specify initial value of GICCDISABLE                                                                                            |
| allowMSRToCurrentBank          | Boolean | Allow access to the current mode registers via the MSR/MRS (Banked Register) instructions                                       |
| override_SCTLR_V               | Boolean | Override SCTLR.V with the passed value (enables high vectors; also configurable using VINITHI pin)                              |
| override_SCTLR_EE              | Boolean | Override SCTLR.EE with the passed value (configures exception data endianness; also configurable using CFGEE pin)               |
| override_SCTLR_TE              | Boolean | Override SCTLR.TE with the passed value (configures Thumb state for exception handling; also configurable using TEINIT pin)     |
| override_SCTLR_NMFI            | Boolean | Override SCTLR.NMFI with the passed value (configures NMFI state for exception handling; also configurable using CFGNMFI pin)   |
| override_SCTLR_CP15BEN_Present | Boolean | Enable ARMv7 SCTLR.CP15BEN bit (CP15 barrier enable)                                                                            |
| override_MIDR                  | Uns32   | Override MIDR/MIDR_EL1 register                                                                                                 |
| override_CTR                   | Uns32   | Override CTR/CTR_EL0 register                                                                                                   |
| override_TLBTR                 | Uns32   | Override TLBTR register                                                                                                         |
| override_CLIDR                 | Uns32   | Override CLIDR/CLIDR_EL1 register                                                                                               |
| override_ACTLR_SMP             | Boolean | Override ACTLR SMP enable bit                                                                                                   |
| override_AIDR                  | Uns32   | Override AIDR/AIDR_EL1 register                                                                                                 |
| override_CBAR                  | Uns32   | Override Configuration Base Address Register (corresponds to value on PERIPHBASE configuration input)                           |
| override_PFR0                  | Uns32   | Override ID_PFR0/ID_PFR0_EL1 register                                                                                           |
| override_PFR1                  | Uns32   | Override ID_PFR1/ID_PFR1_EL1 register                                                                                           |
| override_PFR2                  | Uns32   | Override ID_PFR2/ID_PFR2_EL1 register                                                                                           |
| override_DFR0                  | Uns32   | Override ID_DFR0/ID_DFR0_EL1 register                                                                                           |
| override_DFR1                  | Uns32   | Override ID_DFR1/ID_DFR1_EL1 register                                                                                           |
| override_AFR0                  | Uns32   | Override ID_AFR0/ID_AFR0_EL1 register                                                                                           |
| override_MMFR0                 | Uns32   | Override ID_MMFR0/ID_MMFR0_EL1 register                                                                                         |
| override_MMFR1                 | Uns32   | Override ID_MMFR1/ID_MMFR1_EL1 register                                                                                         |
| override_MMFR2                 | Uns32   | Override ID_MMFR2/ID_MMFR2_EL1 register                                                                                         |

|                                |         |                                                                                   |
|--------------------------------|---------|-----------------------------------------------------------------------------------|
| override_MMFR3                 | Uns32   | Override ID_MMFR3/ID_MMFR3_EL1 register                                           |
| override_MMFR4                 | Uns32   | Override ID_MMFR4/ID_MMFR4_EL1 register                                           |
| override_MMFR5                 | Uns32   | Override ID_MMFR5/ID_MMFR5_EL1 register                                           |
| override_ISAR0                 | Uns32   | Override ID_ISAR0/ID_ISAR0_EL1 register                                           |
| override_ISAR1                 | Uns32   | Override ID_ISAR1/ID_ISAR1_EL1 register                                           |
| override_ISAR2                 | Uns32   | Override ID_ISAR2/ID_ISAR2_EL1 register                                           |
| override_ISAR3                 | Uns32   | Override ID_ISAR3/ID_ISAR3_EL1 register                                           |
| override_ISAR4                 | Uns32   | Override ID_ISAR4/ID_ISAR4_EL1 register                                           |
| override_ISAR5                 | Uns32   | Override ID_ISAR5/ID_ISAR5_EL1 register                                           |
| override_ISAR6                 | Uns32   | Override ID_ISAR6/ID_ISAR6_EL1 register                                           |
| override_PMCr                  | Uns32   | Override PMCR/PMCR_EL0 register (not functionally significant in the model)       |
| override_PMCEID0               | Uns64   | Override PMCEID0/PMCEID0_EL0 register (not functionally significant in the model) |
| override_PMCEID1               | Uns64   | Override PMCEID1/PMCEID1_EL0 register (not functionally significant in the model) |
| override_PMMIR                 | Uns32   | Override PMMIR/PMMIR_EL1 register (not functionally significant in the model)     |
| override_DBGDIDR               | Uns32   | Override DBGDIDR register (not functionally significant in the model)             |
| override_DBGDEVID              | Uns32   | Override DBGDEVID register (not functionally significant in the model)            |
| override_DBGDEVID1             | Uns32   | Override DBGDEVID1 register (not functionally significant in the model)           |
| override_DBGDEVID2             | Uns32   | Override DBGDEVID2 register (not functionally significant in the model)           |
| override_FPSID                 | Uns32   | Override SIMD/VFP FPSID register                                                  |
| override_MVFR0                 | Uns32   | Override SIMD/VFP MVFR0/MVFR0_EL1 register                                        |
| override_MVFR1                 | Uns32   | Override SIMD/VFP MVFR1/MVFR1_EL1 register                                        |
| override_MVFR2                 | Uns32   | Override SIMD/VFP MVFR2/MVFR2_EL1 register                                        |
| override_FPEXC                 | Uns32   | Override SIMD/VFP FPEXC/FPEXC32_EL2 register                                      |
| override_GICC_IIDR             | Uns32   | Override GICC_IIDR register (GICv1 ICCI-IDR)                                      |
| override_GICD_TYPER            | Uns32   | Override GICD_TYPER register (GICv1 IC-DICTR)                                     |
| override_GICD_TYPER_ITLines    | Uns32   | Override ITLinesNumber field of GICD_TYPER register (GICv1 ICDICTR)               |
| override_GICD_TYPER_ESPI       | Boolean | Override ESPI field of GICD_TYPER register (GICv3.1 and later)                    |
| override_GICD_TYPER_ESPI_range | Uns32   | Override ESPI_range field of GICD_TYPER register (GICv3.1 and later)              |
| override_GICD_ICFGRN           | Uns32   | Override reset value of GICD_ICFGR2...GICD_ICFGRn (GICv1 ICDICFR2...ICDICFRn)     |
| override_GICD_IIDR             | Uns32   | Override GICD_IIDR register (GICv1 ICDI-IDR)                                      |
| override_GICH_VTR              | Uns32   | Override GICH_VTR register                                                        |
| override_GICR_IIDR             | Uns32   | Override GICR_IIDR register (GICv3 and later)                                     |

|                            |       |                                                                      |
|----------------------------|-------|----------------------------------------------------------------------|
| override_GICR_TYPER        | Uns64 | Override GICR_TYPER register (GICv3 and later)                       |
| override_GICR_TYPER_PPInum | Uns32 | Override PPInum field of GICR_TYPER register (GICv3.1 and later)     |
| override_GITS_IIDR         | Uns32 | Override GITS_IIDR register (GICv3 and later)                        |
| override_GITS_TYPER        | Uns64 | Override GITS_TYPER register (GICv3 and later)                       |
| override_ICCPMRBits        | Uns32 | Specify the number of writable bits in GICC_PMR (GICv1 ICCPMR)       |
| override_minICCBPR         | Uns32 | Specify the minimum possible value for GICC_BPR (GICv1 ICCBPR)       |
| override_ERG               | Uns32 | Specifies exclusive reservation granule                              |
| override_CCSIDR_1I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 1 instruction)                     |
| override_CCSIDR_1D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 1 data)                            |
| override_CCSIDR_2I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 2 instruction)                     |
| override_CCSIDR_2D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 2 data)                            |
| override_CCSIDR_3I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 3 instruction)                     |
| override_CCSIDR_3D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 3 data)                            |
| override_CCSIDR_4I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 4 instruction)                     |
| override_CCSIDR_4D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 4 data)                            |
| override_CCSIDR_5I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 5 instruction)                     |
| override_CCSIDR_5D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 5 data)                            |
| override_CCSIDR_6I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 6 instruction)                     |
| override_CCSIDR_6D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 6 data)                            |
| override_CCSIDR_7I         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 7 instruction)                     |
| override_CCSIDR_7D         | Uns64 | Override CCSIDR/CCSIDR_EL1 (level 7 data)                            |
| override_RMR               | Uns32 | Override RMR register alias at highest-implemented exception level   |
| override_RVBAR             | Uns64 | Override RVBAR register alias at highest-implemented exception level |
| override_AA64PFR0_EL1      | Uns64 | Override ID_AA64PFR0_EL1 register                                    |
| override_AA64PFR1_EL1      | Uns64 | Override ID_AA64PFR1_EL1 register                                    |
| override_AA64DFR0_EL1      | Uns64 | Override ID_AA64DFR0_EL1 register                                    |
| override_AA64DFR1_EL1      | Uns64 | Override ID_AA64DFR1_EL1 register                                    |
| override_AA64AFR0_EL1      | Uns64 | Override ID_AA64AFR0_EL1 register                                    |
| override_AA64AFR1_EL1      | Uns64 | Override ID_AA64AFR1_EL1 register                                    |
| override_AA64ISAR0_EL1     | Uns64 | Override ID_AA64ISAR0_EL1 register                                   |
| override_AA64ISAR1_EL1     | Uns64 | Override ID_AA64ISAR1_EL1 register                                   |
| override_AA64ISAR2_EL1     | Uns64 | Override ID_AA64ISAR2_EL1 register                                   |
| override_AA64MMFR0_EL1     | Uns64 | Override ID_AA64MMFR0_EL1 register                                   |
| override_AA64MMFR1_EL1     | Uns64 | Override ID_AA64MMFR1_EL1 register                                   |

|                                 |         |                                                                                                                                          |
|---------------------------------|---------|------------------------------------------------------------------------------------------------------------------------------------------|
| override_AA64MMFR2_EL1          | Uns64   | Override ID_AA64MMFR2_EL1 register                                                                                                       |
| override_DCZID_EL0              | Uns32   | Override DCZID_EL0 register                                                                                                              |
| override_LORID_EL1              | Uns32   | Override LORID_EL1 register (ARMv8.1 only)                                                                                               |
| override_STROffsetPC12          | Boolean | Specifies that STR/STR of PC should do so with 12:byte offset from the current instruction (if true), otherwise an 8:byte offset is used |
| override_fcseRequiresMMU        | Boolean | Specifies that FCSE is active only when MMU is enabled (if true)                                                                         |
| override_ignoreBadCp15          | Boolean | Specifies whether invalid coprocessor 15 access should be ignored (if true) or cause Invalid Instruction exceptions (if false)           |
| override_SGIDisable             | Boolean | Override whether GIC SGIs may be disabled (if true) or are permanently enabled (if false)                                                |
| override_condUndefined          | Boolean | Force undefined instructions to take Undefined Instruction exception even if they are conditional                                        |
| override_deviceStrongAligned    | Boolean | Force accesses to Device and Strongly Ordered regions to be aligned                                                                      |
| override_stage1SZMinFault       | Boolean | Enable Level 0 Translation faults when stage 1 TCR_ELx.TxSZ <minimum (by default, clamp to minimum)                                      |
| override_stage1SZMaxFault       | Boolean | Enable Level 0 Translation faults when stage 1 TCR_ELx.TxSZ >maximum (by default, clamp to maximum)                                      |
| override_stage2SZMinFault       | Boolean | Enable Level 0 Translation faults when stage 2 VTCR_EL2.T0SZ <minimum (by default, clamp to minimum)                                     |
| override_stage2SZMaxFault       | Boolean | Enable Level 0 Translation faults when stage 2 VTCR_EL2.T0SZ >maximum (by default, clamp to maximum)                                     |
| override_mask_ACTLR_EL1         | Uns64   | Override mask of writable bits in AArch64 ACTLR_EL1 register, or AArch32 non-secure ACTLR/ACTLR2 pair, if implemented                    |
| override_mask_ACTLR_EL2         | Uns64   | Override mask of writable bits in AArch64 ACTLR_EL2 register, or AArch32 HACTLR/HACTLR2 pair, if implemented                             |
| override_mask_ACTLR_EL3         | Uns64   | Override mask of writable bits in AArch64 ACTLR_EL3 register, or AArch32 secure ACTLR/ACTLR2 pair, if implemented                        |
| override_Control_V              | Boolean | Override SCTLR.V with the passed value (deprecated, use override_SCTLR_V)                                                                |
| override_MainId                 | Uns32   | Override MIDR register (deprecated, use override_MIDR)                                                                                   |
| override_CacheType              | Uns32   | Override CTR register (deprecated, use override_CTR)                                                                                     |
| override_TLBType                | Uns32   | Override TLBTR register (deprecated, use override_TLBTR)                                                                                 |
| override_InstructionAttributes0 | Uns32   | Override ID_ISAR0 register (deprecated, use override_ISAR0)                                                                              |
| override_InstructionAttributes1 | Uns32   | Override ID_ISAR1 register (deprecated, use override_ISAR1)                                                                              |
| override_InstructionAttributes2 | Uns32   | Override ID_ISAR2 register (deprecated, use override_ISAR2)                                                                              |
| override_InstructionAttributes3 | Uns32   | Override ID_ISAR3 register (deprecated, use override_ISAR3)                                                                              |

|                                 |       |                                                             |
|---------------------------------|-------|-------------------------------------------------------------|
| override_InstructionAttributes4 | Uns32 | Override ID_ISAR4 register (deprecated, use override_ISAR4) |
| override_InstructionAttributes5 | Uns32 | Override ID_ISAR5 register (deprecated, use override_ISAR5) |

Table 8.1: Parameters that can be set in: MPCORE

## 8.1 Parameter values and limits

These are the formal parameter limits and actual parameter values

| Name                   | Min | Max            | Default            | Actual             |
|------------------------|-----|----------------|--------------------|--------------------|
| <b>(Others)</b>        |     |                |                    |                    |
| variant                |     |                |                    | Cortex-A65AEMPx4   |
| verbose                |     |                | t                  | t                  |
| suppressCPSWarnings    |     |                | f                  | f                  |
| showHiddenRegs         |     |                | f                  | f                  |
| UAL                    |     |                | t                  | t                  |
| disableGICModel        |     |                | f                  | f                  |
| enableGICv3            |     |                | t                  | t                  |
| enableGICv2_64kB_Page  |     |                | f                  | f                  |
| supportSTATUSR         |     |                | t                  | t                  |
| enableVFPAAtReset      |     |                | f                  | f                  |
| SVEImplementedSizes    | 1   | 0xffff         | 15                 | 15                 |
| SVEFaultUnknown        | 0   | 0xffffffffffff | 0xdfdfdfdfdfdfdfdf | 0xdfdfdfdfdfdfdfdf |
| enableSystemBus        |     |                | f                  | f                  |
| enableSystemMonitorBus |     |                | f                  | f                  |
| distinctMTCores        |     |                | f                  | f                  |
| compatibility          |     |                | ISA                | ISA                |
| unpredictableR15       |     |                | undefined          | undefined          |
| unpredictableModal     |     |                | undefined          | undefined          |
| maxSIMDUnroll          | 1   | 16             | 2                  | 2                  |
| override_debugMask     | 0   | 0xffffffff     | 0                  | 0                  |
| ASIDCacheSize          | 0   | 0x100          | 8                  | 8                  |
| thumbNoCond            |     |                | f                  | f                  |
| enableHostAtomics      |     |                | f                  | f                  |
| enableWFEHostAtomics   |     |                | f                  | f                  |
| endian                 |     |                | none               | none               |
| override_numCPUs       | 0   | 32             | 16                 | 16                 |
| override_affinityMask  | 0   | 0xffffffff     | 0xffff0701         | 0xffff0701         |
| override_MPIDR_MT      |     |                | t                  | t                  |
| override_MPIDR_Aff0    | 0   | 255            | 0                  | 0                  |
| override_MPIDR_Aff1    | 0   | 255            | 0                  | 0                  |
| override_MPIDR_Aff2    | 0   | 255            | 0                  | 0                  |
| override_MPIDR_Aff3    | 0   | 255            | 0                  | 0                  |
| override_fcsePresent   |     |                | f                  | f                  |

|                                |    |                |            |            |
|--------------------------------|----|----------------|------------|------------|
| override_fpexcDexPresent       |    |                | t          | t          |
| override_advSIMDPresent        |    |                | f          | f          |
| override_vfpPresent            |    |                | f          | f          |
| override_physicalBits          | 32 | 52             | 32         | 32         |
| override_timerScaleFactor      | 1  | 0x1ff          | 20         | 20         |
| override_GICD_NSACRPresent     |    |                | f          | f          |
| override_GICD_PPISRPresent     |    |                | t          | t          |
| override_GICD_SPISRPresent     |    |                | t          | t          |
| override_GICv3_DistributorBase | 0  | 0xffffffffffff | 0x2f000000 | 0x2f000000 |
| override_GICv3_E1NWFPresent    |    |                | f          | f          |
| override_GICv3_ROAffinity      |    |                | f          | f          |
| override_GIC_PPIMask           | 0  | 0xffff         | 0          | 0          |
| override_GICCDISABLE           |    |                | f          | f          |
| allowMSRToCurrentBank          |    |                | f          | f          |
| override_SCTLR_V               |    |                | f          | f          |
| override_SCTLR_EE              |    |                | f          | f          |
| override_SCTLR_TE              |    |                | f          | f          |
| override_SCTLR_NMFI            |    |                | f          | f          |
| override_SCTLR_CP15BEN_Present |    |                | t          | t          |
| override_MIDR                  | 0  | 0xffffffff     | 0x411fd430 | 0x411fd430 |
| override_CTR                   | 0  | 0xffffffff     | 0x84448004 | 0x84448004 |
| override_TLBTR                 | 0  | 0xffffffff     | 0          | 0          |
| override_CLIDR                 | 0  | 0xffffffff     | 0xc3000123 | 0xc3000123 |
| override_ACTLR_SMP             |    |                | f          | f          |
| override_AIDR                  | 0  | 0xffffffff     | 0          | 0          |
| override_CBAR                  | 0  | 0xffffffff     | 0          | 0          |
| override_PFR0                  | 0  | 0xffffffff     | 0x10010131 | 0x10010131 |
| override_PFR1                  | 0  | 0xffffffff     | 0x10011011 | 0x10011011 |
| override_PFR2                  | 0  | 0xffffffff     | 17         | 17         |
| override_DFR0                  | 0  | 0xffffffff     | 0x4010088  | 0x4010088  |
| override_DFR1                  | 0  | 0xffffffff     | 0          | 0          |
| override_AFR0                  | 0  | 0xffffffff     | 0          | 0          |
| override_MMFR0                 | 0  | 0xffffffff     | 0x10201105 | 0x10201105 |
| override_MMFR1                 | 0  | 0xffffffff     | 0x40000000 | 0x40000000 |
| override_MMFR2                 | 0  | 0xffffffff     | 0x1260000  | 0x1260000  |
| override_MMFR3                 | 0  | 0xffffffff     | 0x2122211  | 0x2122211  |
| override_MMFR4                 | 0  | 0xffffffff     | 0x21110    | 0x21110    |
| override_MMFR5                 | 0  | 0xffffffff     | 0          | 0          |
| override_ISAR0                 | 0  | 0xffffffff     | 0x2101110  | 0x2101110  |
| override_ISAR1                 | 0  | 0xffffffff     | 0x13112111 | 0x13112111 |
| override_ISAR2                 | 0  | 0xffffffff     | 0x21232042 | 0x21232042 |
| override_ISAR3                 | 0  | 0xffffffff     | 0x1112131  | 0x1112131  |
| override_ISAR4                 | 0  | 0xffffffff     | 0x10142    | 0x10142    |
| override_ISAR5                 | 0  | 0xffffffff     | 0x1011121  | 0x1011121  |
| override_ISAR6                 | 0  | 0xffffffff     | 16         | 16         |

|                                |   |                  |            |            |
|--------------------------------|---|------------------|------------|------------|
| override_PMCR                  | 0 | 0xffffffff       | 0x414a3000 | 0x414a3000 |
| override_PMCEID0               | 0 | 0xffffffffffffff | 0xfbff7f3f | 0xfbff7f3f |
| override_PMCEID1               | 0 | 0xffffffffffffff | 0x1f1ae7b  | 0x1f1ae7b  |
| override_PMMIR                 | 0 | 0xffffffff       | 0          | 0          |
| override_DBGDIDR               | 0 | 0xffffffff       | 0x3518c000 | 0x3518c000 |
| override_DBGDEVID              | 0 | 0xffffffff       | 0x100f10   | 0x100f10   |
| override_DBGDEVID1             | 0 | 0xffffffff       | 0          | 0          |
| override_DBGDEVID2             | 0 | 0xffffffff       | 0          | 0          |
| override_FPSID                 | 0 | 0xffffffff       | 0x41034080 | 0x41034080 |
| override_MVFR0                 | 0 | 0xffffffff       | 0x10110222 | 0x10110222 |
| override_MVFR1                 | 0 | 0xffffffff       | 0x13211111 | 0x13211111 |
| override_MVFR2                 | 0 | 0xffffffff       | 67         | 67         |
| override_FPEXC                 | 0 | 0xffffffff       | 0          | 0          |
| override_GICC_IIDR             | 0 | 0xffffffff       | 0x4043b    | 0x4043b    |
| override_GICD_TYPER            | 0 | 0xffffffff       | 0x7bfc02   | 0x7bfc02   |
| override_GICD_TYPER_ITLines    | 0 | 31               | 2          | 2          |
| override_GICD_TYPER_ESPI       |   |                  | f          | f          |
| override_GICD_TYPER_ESPI_range | 0 | 31               | 0          | 0          |
| override_GICD_ICFGRN           | 0 | 0xffffffff       | 0          | 0          |
| override_GICD_IIDR             | 0 | 0xffffffff       | 0x102043b  | 0x102043b  |
| override_GICH_VTR              | 0 | 0xffffffff       | 0x90000003 | 0x90000003 |
| override_GICR_IIDR             | 0 | 0xffffffff       | 0x43b      | 0x43b      |
| override_GICR_TYPER            | 0 | 0xffffffffffffff | 9          | 9          |
| override_GICR_TYPER_PPInum     | 0 | 2                | 0          | 0          |
| override_GITS_IIDR             | 0 | 0xffffffff       | 0x43b      | 0x43b      |
| override_GITS_TYPER            | 0 | 0xffffffffffffff | 0x9ef79    | 0x9ef79    |
| override_ICCPMRBits            | 4 | 8                | 5          | 5          |
| override_minICCBPR             | 0 | 7                | 2          | 2          |
| override_ERG                   | 3 | 11               | 4          | 4          |
| override_CCSIDR_1I             | 0 | 0xffffffffffffff | 0x701fe01a | 0x701fe01a |
| override_CCSIDR_1D             | 0 | 0xffffffffffffff | 0x201fe01a | 0x201fe01a |
| override_CCSIDR_2I             | 0 | 0xffffffffffffff | 0x703fe03a | 0x703fe03a |
| override_CCSIDR_2D             | 0 | 0xffffffffffffff | 0x703fe03a | 0x703fe03a |
| override_CCSIDR_3I             | 0 | 0xffffffffffffff | 0x73ffe07a | 0x73ffe07a |
| override_CCSIDR_3D             | 0 | 0xffffffffffffff | 0x73ffe07a | 0x73ffe07a |
| override_CCSIDR_4I             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_4D             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_5I             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_5D             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_6I             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_6D             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_7I             | 0 | 0xffffffffffffff | 0          | 0          |
| override_CCSIDR_7D             | 0 | 0xffffffffffffff | 0          | 0          |
| override_RMR                   | 0 | 0xffffffff       | 1          | 1          |
| override_RVBAR                 | 0 | 0xffffffffffffff | 0          | 0          |

|                                 |   |                |            |            |
|---------------------------------|---|----------------|------------|------------|
| override_AA64PFR0_EL1           | 0 | 0xffffffffffff | 0x11111111 | 0x11111111 |
| override_AA64PFR1_EL1           | 0 | 0xffffffffffff | 16         | 16         |
| override_AA64DFR0_EL1           | 0 | 0xffffffffffff | 0x10305408 | 0x10305408 |
| override_AA64DFR1_EL1           | 0 | 0xffffffffffff | 0          | 0          |
| override_AA64AFR0_EL1           | 0 | 0xffffffffffff | 0          | 0          |
| override_AA64AFR1_EL1           | 0 | 0xffffffffffff | 0          | 0          |
| override_AA64ISAR0_EL1          | 0 | 0xffffffffffff | 0x10211120 | 0x10211120 |
| override_AA64ISAR1_EL1          | 0 | 0xffffffffffff | 0x100001   | 0x100001   |
| override_AA64ISAR2_EL1          | 0 | 0xffffffffffff | 0          | 0          |
| override_AA64MMFR0_EL1          | 0 | 0xffffffffffff | 0x101124   | 0x101124   |
| override_AA64MMFR1_EL1          | 0 | 0xffffffffffff | 0x10212122 | 0x10212122 |
| override_AA64MMFR2_EL1          | 0 | 0xffffffffffff | 0x1011     | 0x1011     |
| override_DCZID_EL0              | 0 | 9              | 4          | 4          |
| override_LORID_EL1              | 0 | 0xffffffff     | 0x40004    | 0x40004    |
| override_STROffsetPC12          |   |                | t          | t          |
| override_fcseRequiresMMU        |   |                | f          | f          |
| override_ignoreBadCp15          |   |                | f          | f          |
| override_SGIDisable             |   |                | f          | f          |
| override_condUndefined          |   |                | f          | f          |
| override_deviceStrongAligned    |   |                | t          | t          |
| override_stage1SZMinFault       |   |                | f          | f          |
| override_stage1SZMaxFault       |   |                | f          | f          |
| override_stage2SZMinFault       |   |                | f          | f          |
| override_stage2SZMaxFault       |   |                | f          | f          |
| override_mask_ACTLR_EL1         | 0 | 0xffffffffffff | 0          | 0          |
| override_mask_ACTLR_EL2         | 0 | 0xffffffffffff | 0x1ca3     | 0x1ca3     |
| override_mask_ACTLR_EL3         | 0 | 0xffffffffffff | 0x1ca3     | 0x1ca3     |
| override_Control_V              |   |                | f          | f          |
| override_MainId                 | 0 | 0xffffffff     | 0x411fd430 | 0x411fd430 |
| override_CacheType              | 0 | 0xffffffff     | 0x84448004 | 0x84448004 |
| override_TLBType                | 0 | 0xffffffff     | 0          | 0          |
| override_InstructionAttributes0 | 0 | 0xffffffff     | 0x2101110  | 0x2101110  |
| override_InstructionAttributes1 | 0 | 0xffffffff     | 0x13112111 | 0x13112111 |
| override_InstructionAttributes2 | 0 | 0xffffffff     | 0x21232042 | 0x21232042 |
| override_InstructionAttributes3 | 0 | 0xffffffff     | 0x1112131  | 0x1112131  |
| override_InstructionAttributes4 | 0 | 0xffffffff     | 0x10142    | 0x10142    |
| override_InstructionAttributes5 | 0 | 0xffffffff     | 0x1011121  | 0x1011121  |

Table 8.2: Parameter values and limits

| Name                    | Type    | Description                                                                                                     |
|-------------------------|---------|-----------------------------------------------------------------------------------------------------------------|
| enableVFPAAtReset       | Boolean | Enable vector floating point (SIMD and VFP) instructions at reset. (Enables cp10/11 in CPACR and sets FPEXC.EN) |
| override_advSIMDPresent | Boolean | Specifies that Advanced SIMD extensions are present (if true)                                                   |

|                                |         |                                                                                                                               |
|--------------------------------|---------|-------------------------------------------------------------------------------------------------------------------------------|
| override_vfpPresent            | Boolean | Specifies that VFP extensions are present (if true)                                                                           |
| override_SCTLR_V               | Boolean | Override SCTLR.V with the passed value (enables high vectors; also configurable using VINITHI pin)                            |
| override_SCTLR_EE              | Boolean | Override SCTLR.EE with the passed value (configures exception data endianness; also configurable using CFGEE pin)             |
| override_SCTLR_TE              | Boolean | Override SCTLR.TE with the passed value (configures Thumb state for exception handling; also configurable using TEINIT pin)   |
| override_SCTLR_NMFI            | Boolean | Override SCTLR.NMFI with the passed value (configures NMFI state for exception handling; also configurable using CFGNMFI pin) |
| override_SCTLR_CP15BEN_Present | Boolean | Enable ARMv7 SCTLR.CP15BEN bit (CP15 barrier enable)                                                                          |
| override_ACTLR_SMP             | Boolean | Override ACTLR SMP enable bit                                                                                                 |
| override_RVBAR                 | Uns64   | Override RVBAR register alias at highest-implemented exception level                                                          |

Table 8.3: Parameters that can be set in: CORE

## 8.2 Parameter values and limits

These are the formal parameter limits and actual parameter values

| Name                           | Min | Max              | Default | Actual |
|--------------------------------|-----|------------------|---------|--------|
| <b>(Others)</b>                |     |                  |         |        |
| enableVFPAAtReset              |     |                  | f       | f      |
| override_advSIMDPresent        |     |                  | f       | f      |
| override_vfpPresent            |     |                  | f       | f      |
| override_SCTLR_V               |     |                  | f       | f      |
| override_SCTLR_EE              |     |                  | f       | f      |
| override_SCTLR_TE              |     |                  | f       | f      |
| override_SCTLR_NMFI            |     |                  | f       | f      |
| override_SCTLR_CP15BEN_Present |     |                  | t       | t      |
| override_ACTLR_SMP             |     |                  | f       | f      |
| override_RVBAR                 | 0   | 0xffffffffffffff | 0       | 0      |

Table 8.4: Parameter values and limits

## Chapter 9

# Execution Modes

| Mode | Code |
|------|------|
| EL0t | 0    |
| EL1t | 4    |
| EL1h | 5    |
| EL2t | 8    |
| EL2h | 9    |
| EL3t | 12   |
| EL3h | 13   |

Table 9.1: Modes implemented in: THREAD

## Chapter 10

# Exceptions

| <b>Exception</b>  | Code |
|-------------------|------|
| Reset             | 0    |
| Undefined         | 1    |
| SupervisorCall    | 2    |
| SecureMonitorCall | 3    |
| HypervisorCall    | 4    |
| PrefetchAbort     | 5    |
| DataAbort         | 6    |
| HypervisorTrap    | 7    |
| IRQ               | 8    |
| FIQ               | 9    |
| IllegalState      | 10   |
| MisalignedPC      | 11   |
| MisalignedSP      | 12   |
| SError            | 13   |

Table 10.1: Exceptions implemented in: THREAD

## Chapter 11

# Hierarchy of the model

A CPU core may be configured to instance many processors of a Symmetrical Multi Processor (SMP). A CPU core may also have sub elements within a processor, for example hardware threading blocks.

OVP processor models can be written to include SMP blocks and to have many levels of hierarchy. Some OVP CPU models may have a fixed hierarchy, and some may be configured by settings in a configuration register. Please see the register definitions of this model.

This model documentation shows the settings and hierarchy of the default settings for this model variant.

### 11.1 Level 1: MPCORE

This level in the model hierarchy has 2 commands.

This level in the model hierarchy has no register groups.

This level in the model hierarchy has 8 children:

CPU0, CPU1, CPU2, CPU3, CPU4, CPU5, CPU6 and CPU7.

### 11.2 Level 2: CORE

This level in the model hierarchy has 2 commands.

This level in the model hierarchy has no register groups.

This level in the model hierarchy has 2 children:

CPU0\_T0 and CPU0\_T1.

### 11.3 Level 3: THREAD

This level in the model hierarchy has 6 commands.

This level in the model hierarchy has 14 register groups:

| Group name            | Registers |
|-----------------------|-----------|
| Core_AArch64          | 33        |
| SIMD_FP_AArch64       | 32        |
| AArch64_system        | 346       |
| AArch64_secure_system | 19        |

|                                    |     |
|------------------------------------|-----|
| AArch64_non_secure_system          | 19  |
| AArch64_system_artifact            | 1   |
| AArch64_SYS_instruction_registers  | 58  |
| Integration_support                | 37  |
| MPCore_distributor                 | 146 |
| MPCore_physical_redistributor      | 43  |
| MPCore_processor_interface         | 16  |
| MPCore_virtual_interface_control   | 11  |
| MPCore_virtual_processor_interface | 31  |
| MPCore_ITS                         | 14  |

Table 11.1: Register groups

This level in the model hierarchy has no children.

# Chapter 12

## Model Commands

A Processor model can implement one or more **Model Commands** available to be invoked from the simulator command line, from the OP API or from the Imperas Multiprocessor Debugger.

### 12.1 Level 1: MPCORE

#### 12.1.1 isync

specify instruction address range for synchronous execution

| Argument   | Type  | Description                                  |
|------------|-------|----------------------------------------------|
| -addresshi | Uns64 | end address of synchronous execution range   |
| -addresslo | Uns64 | start address of synchronous execution range |

Table 12.1: isync command arguments

#### 12.1.2 itrace

enable or disable instruction tracing

| Argument          | Type    | Description                                                                                                                                           |
|-------------------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| -access           | String  | show memory accesses by this instruction. Argument can be any combination of X (execute), A (load or store access) and S (system)                     |
| -after            | Uns64   | apply after this many instructions                                                                                                                    |
| -enable           | Boolean | enable instruction tracing                                                                                                                            |
| -full             | Boolean | turn on all trace features                                                                                                                            |
| -instructioncount | Boolean | include the instruction number in each trace                                                                                                          |
| -memory           | String  | (Alias for access). show memory accesses by this instruction. Argument can be any combination of X (execute), A (load or store access) and S (system) |
| -mode             | Boolean | show processor mode changes                                                                                                                           |
| -off              | Boolean | disable instruction tracing                                                                                                                           |
| -on               | Boolean | enable instruction tracing                                                                                                                            |
| -processorname    | Boolean | Include processor name in all trace lines                                                                                                             |

|                 |         |                                            |
|-----------------|---------|--------------------------------------------|
| -registerchange | Boolean | show registers changed by this instruction |
| -registers      | Boolean | show registers after each trace            |

Table 12.2: itrace command arguments

## 12.2 Level 2: CORE

### 12.2.1 isync

specify instruction address range for synchronous execution

| Argument   | Type  | Description                                  |
|------------|-------|----------------------------------------------|
| -addresshi | Uns64 | end address of synchronous execution range   |
| -addresslo | Uns64 | start address of synchronous execution range |

Table 12.3: isync command arguments

### 12.2.2 itrace

enable or disable instruction tracing

| Argument          | Type    | Description                                                                                                                                           |
|-------------------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| -access           | String  | show memory accesses by this instruction. Argument can be any combination of X (execute), A (load or store access) and S (system)                     |
| -after            | Uns64   | apply after this many instructions                                                                                                                    |
| -enable           | Boolean | enable instruction tracing                                                                                                                            |
| -full             | Boolean | turn on all trace features                                                                                                                            |
| -instructioncount | Boolean | include the instruction number in each trace                                                                                                          |
| -memory           | String  | (Alias for access). show memory accesses by this instruction. Argument can be any combination of X (execute), A (load or store access) and S (system) |
| -mode             | Boolean | show processor mode changes                                                                                                                           |
| -off              | Boolean | disable instruction tracing                                                                                                                           |
| -on               | Boolean | enable instruction tracing                                                                                                                            |
| -processorname    | Boolean | Include processor name in all trace lines                                                                                                             |
| -registerchange   | Boolean | show registers changed by this instruction                                                                                                            |
| -registers        | Boolean | show registers after each trace                                                                                                                       |

Table 12.4: itrace command arguments

## 12.3 Level 3: THREAD

### 12.3.1 debugflags

show or modify the processor debug flags

| Argument | Type    | Description                                                 |
|----------|---------|-------------------------------------------------------------|
| -get     | Boolean | print current processor flags value                         |
| -mask    | Boolean | print valid debug flag bits                                 |
| -set     | Int32   | new processor flags (only flags 0x000003e4 can be modified) |

Table 12.5: debugflags command arguments

### 12.3.2 dumpTLB

report TLB contents

| Argument | Type    | Description                                                         |
|----------|---------|---------------------------------------------------------------------|
| -all     | Boolean | show the contents of all TLBs (if False, show just the current TLB) |

Table 12.6: dumpTLB command arguments

### 12.3.3 isync

specify instruction address range for synchronous execution

| Argument   | Type  | Description                                  |
|------------|-------|----------------------------------------------|
| -addresshi | Uns64 | end address of synchronous execution range   |
| -addresslo | Uns64 | start address of synchronous execution range |

Table 12.7: isync command arguments

### 12.3.4 itrace

enable or disable instruction tracing

| Argument          | Type    | Description                                                                                                                                           |
|-------------------|---------|-------------------------------------------------------------------------------------------------------------------------------------------------------|
| -access           | String  | show memory accesses by this instruction. Argument can be any combination of X (execute), A (load or store access) and S (system)                     |
| -after            | Uns64   | apply after this many instructions                                                                                                                    |
| -enable           | Boolean | enable instruction tracing                                                                                                                            |
| -full             | Boolean | turn on all trace features                                                                                                                            |
| -instructioncount | Boolean | include the instruction number in each trace                                                                                                          |
| -memory           | String  | (Alias for access). show memory accesses by this instruction. Argument can be any combination of X (execute), A (load or store access) and S (system) |
| -mode             | Boolean | show processor mode changes                                                                                                                           |
| -off              | Boolean | disable instruction tracing                                                                                                                           |
| -on               | Boolean | enable instruction tracing                                                                                                                            |
| -processorname    | Boolean | Include processor name in all trace lines                                                                                                             |

|                 |         |                                            |
|-----------------|---------|--------------------------------------------|
| -registerchange | Boolean | show registers changed by this instruction |
| -registers      | Boolean | show registers after each trace            |

Table 12.8: itrace command arguments

### 12.3.5 listSysRegsAA64

#### 12.3.5.1 Argument description

List all AArch64 system registers

### 12.3.6 validateTLB

check TLB contents against page tables in memory and report incoherent entries

| Argument | Type    | Description                                                   |
|----------|---------|---------------------------------------------------------------|
| -all     | Boolean | check all TLBs (if False, validate just the current TLB)      |
| -verbose | Boolean | show all TLB entries (if False, show only incoherent entries) |

Table 12.9: validateTLB command arguments

# Chapter 13

## Registers

### 13.1 Level 1: MPCORE

No registers.

### 13.2 Level 2: CORE

No registers.

### 13.3 Level 3: THREAD

#### 13.3.1 Core\_AArch64

Registers at level:3, type:THREAD group:Core\_AArch64

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|-------------|
| x0   | 64   | 0           | rw |             |
| x1   | 64   | 0           | rw |             |
| x2   | 64   | 0           | rw |             |
| x3   | 64   | 0           | rw |             |
| x4   | 64   | 0           | rw |             |
| x5   | 64   | 0           | rw |             |
| x6   | 64   | 0           | rw |             |
| x7   | 64   | 0           | rw |             |
| x8   | 64   | 0           | rw |             |
| x9   | 64   | 0           | rw |             |
| x10  | 64   | 0           | rw |             |
| x11  | 64   | 0           | rw |             |
| x12  | 64   | 0           | rw |             |
| x13  | 64   | 0           | rw |             |
| x14  | 64   | 0           | rw |             |
| x15  | 64   | 0           | rw |             |
| x16  | 64   | 0           | rw |             |
| x17  | 64   | 0           | rw |             |
| x18  | 64   | 0           | rw |             |
| x19  | 64   | 0           | rw |             |
| x20  | 64   | 0           | rw |             |
| x21  | 64   | 0           | rw |             |
| x22  | 64   | 0           | rw |             |

|     |    |   |    |                 |
|-----|----|---|----|-----------------|
| x23 | 64 | 0 | rw |                 |
| x24 | 64 | 0 | rw |                 |
| x25 | 64 | 0 | rw |                 |
| x26 | 64 | 0 | rw |                 |
| x27 | 64 | 0 | rw |                 |
| x28 | 64 | 0 | rw |                 |
| x29 | 64 | 0 | rw | frame pointer   |
| x30 | 64 | 0 | rw |                 |
| sp  | 64 | 0 | rw | stack pointer   |
| pc  | 64 | 0 | rw | program counter |

Table 13.1: Registers at level 3, type:THREAD group:Core\_AArch64

### 13.3.2 SIMD\_FP\_AArch64

Registers at level:3, type:THREAD group:SIMD\_FP\_AArch64

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|-------------|
| v0   | 128  | -           | rw |             |
| v1   | 128  | -           | rw |             |
| v2   | 128  | -           | rw |             |
| v3   | 128  | -           | rw |             |
| v4   | 128  | -           | rw |             |
| v5   | 128  | -           | rw |             |
| v6   | 128  | -           | rw |             |
| v7   | 128  | -           | rw |             |
| v8   | 128  | -           | rw |             |
| v9   | 128  | -           | rw |             |
| v10  | 128  | -           | rw |             |
| v11  | 128  | -           | rw |             |
| v12  | 128  | -           | rw |             |
| v13  | 128  | -           | rw |             |
| v14  | 128  | -           | rw |             |
| v15  | 128  | -           | rw |             |
| v16  | 128  | -           | rw |             |
| v17  | 128  | -           | rw |             |
| v18  | 128  | -           | rw |             |
| v19  | 128  | -           | rw |             |
| v20  | 128  | -           | rw |             |
| v21  | 128  | -           | rw |             |
| v22  | 128  | -           | rw |             |
| v23  | 128  | -           | rw |             |
| v24  | 128  | -           | rw |             |
| v25  | 128  | -           | rw |             |
| v26  | 128  | -           | rw |             |
| v27  | 128  | -           | rw |             |
| v28  | 128  | -           | rw |             |
| v29  | 128  | -           | rw |             |
| v30  | 128  | -           | rw |             |
| v31  | 128  | -           | rw |             |

Table 13.2: Registers at level 3, type:THREAD group:SIMD\_FP\_AArch64

### 13.3.3 AArch64\_system

Registers at level:3, type:THREAD group:AArch64\_system

| Name                   | Bits | Initial-Hex | RW | Description                                        |
|------------------------|------|-------------|----|----------------------------------------------------|
| ACTLR_EL1              | 64   | 0           | rw | Auxiliary Control (EL1)                            |
| ACTLR_EL2              | 64   | 0           | rw | Auxiliary Control (EL2)                            |
| ACTLR_EL3              | 64   | 0           | rw | Auxiliary Control (EL3)                            |
| AFSR0_EL1              | 32   | 0           | rw | Auxiliary Fault Status 0 (EL1)                     |
| AFSR0_EL2              | 32   | 0           | rw | Auxiliary Fault Status 0 (EL2)                     |
| AFSR0_EL3              | 32   | 0           | rw | Auxiliary Fault Status 0 (EL3)                     |
| AFSR0_EL12             | 32   | 0           | rw | Auxiliary Fault Status 0 (EL1) Alias               |
| AFSR1_EL1              | 32   | 0           | rw | Auxiliary Fault Status 1 (EL1)                     |
| AFSR1_EL2              | 32   | 0           | rw | Auxiliary Fault Status 1 (EL2)                     |
| AFSR1_EL3              | 32   | 0           | rw | Auxiliary Fault Status 1 (EL3)                     |
| AFSR1_EL12             | 32   | 0           | rw | Auxiliary Fault Status 1 (EL1) Alias               |
| AIDR_EL1               | 32   | 0           | r- | Auxiliary ID                                       |
| AMAIR_EL1              | 64   | 0           | rw | Auxiliary Memory Attribute Indirection (EL1)       |
| AMAIR_EL2              | 64   | 0           | rw | Auxiliary Memory Attribute Indirection (EL2)       |
| AMAIR_EL3              | 64   | 0           | rw | Auxiliary Memory Attribute Indirection (EL3)       |
| AMAIR_EL12             | 64   | 0           | rw | Auxiliary Memory Attribute Indirection (EL1) Alias |
| ATCR_EL1               | 32   | 0           | rw | Auxiliary Translation Control (EL1)                |
| ATCR_EL2               | 32   | 0           | rw | Auxiliary Translation Control (EL2)                |
| ATCR_EL3               | 32   | 0           | rw | Auxiliary Translation Control (EL3)                |
| ATCR_EL12              | 64   | 0           | rw | Auxiliary Translation Control (EL1) Alias          |
| AVTCR_EL2              | 32   | 0           | rw | Auxiliary Virtualized Translation Control (EL2)    |
| CCSIDR_EL1             | 32   | 701fe01a    | r- | Current Cache Size ID                              |
| CLIDR_EL1              | 32   | c3000123    | r- | Cache Level ID                                     |
| CLUSTERACPSID_EL1      | 32   | 0           | rw | Cluster ACP Scheme ID                              |
| CLUSTERACTLR_EL1       | 32   | 0           | rw | Cluster Auxiliary Control                          |
| CLUSTERBUSQOS_EL1      | 32   | eeeeeeee    | rw | Cluster Bus QoS Control                            |
| CLUSTERCFR_EL1         | 32   | 3fd097      | rw | Cluster Configuration                              |
| CLUSTERECTLR_EL1       | 32   | 500         | rw | Cluster Extended Control                           |
| CLUSTERIDR_EL1         | 32   | 2           | rw | Cluster Main Revision ID                           |
| CLUSTERL3HIT_EL1       | 32   | 0           | rw | Cluster L3 Hit Counter                             |
| CLUSTERL3MISS_EL1      | 32   | 0           | rw | Cluster L3 Miss Counter                            |
| CLUSTERPARTCR_EL1      | 32   | 0           | rw | Cluster Partition Control                          |
| CLUSTERPMCCTR_EL1      | 64   | 0           | rw | Cluster Performance Monitors Cycle Count           |
| CLUSTERPMCEID0_EL1     | 32   | 66020000    | r- | Cluster Common Event ID 0                          |
| CLUSTERPMCEID1_EL1     | 32   | 1e00        | r- | Cluster Common Event ID 1                          |
| CLUSTERPMCCLAIMCLR_EL1 | 32   | 0           | rw | Cluster Performance Monitor Claim Tag Clear        |
| CLUSTERPMCCLAIMSET_EL1 | 32   | 0           | rw | Cluster Performance Monitor Claim Tag Set          |
| CLUSTERPMCNTENCLR_EL1  | 32   | 0           | rw | Cluster Count Enable Clear                         |
| CLUSTERPMCNTENSET_EL1  | 32   | 0           | rw | Cluster Count Enable Set                           |
| CLUSTERPMCRR_EL1       | 32   | 41413040    | rw | Cluster Performance Monitors Control               |
| CLUSTERPMINTENCLR_EL1  | 32   | 0           | rw | Cluster Interrupt Enable Clear                     |
| CLUSTERPMINTENSET_EL1  | 32   | 0           | rw | Cluster Interrupt Enable Set                       |
| CLUSTERPMMDCR_EL3      | 32   | 0           | rw | Cluster Monitor Debug Configuration                |
| CLUSTERPMOVSLR_EL1     | 32   | 0           | rw | Cluster Overflow Flag Status Clear                 |
| CLUSTERPMOVSET_EL1     | 32   | 0           | rw | Cluster Overflow Flag Status Set                   |
| CLUSTERPMSELR_EL1      | 32   | 0           | rw | Cluster Event Counter Selection                    |
| CLUSTERPMXEVCNTR_EL1   | 32   | 0           | rw | Cluster Selected Event Count                       |
| CLUSTERPMXEVTYPER_EL1  | 32   | 0           | rw | Cluster Selected Event Type                        |
| CLUSTERPWRCTLR_EL1     | 32   | 0           | rw | Cluster Power Control                              |

|                         |    |        |    |                                                  |
|-------------------------|----|--------|----|--------------------------------------------------|
| CLUSTERPWRDN_EL1        | 32 | 0      | rw | Cluster Powerdown                                |
| CLUSTERPWRSTAT_EL1      | 32 | 0      | rw | Cluster Power Status                             |
| CLUSTERREVIDR_EL1       | 32 | 0      | rw | Cluster Revision ID                              |
| CLUSTERSTASHSID_EL1     | 32 | 0      | rw | Cluster Stash Scheme ID                          |
| CLUSTERTHREADSIDOVR_EL1 | 32 | 0      | rw | Cluster Thread Scheme ID Override                |
| CLUSTERTHREADSID_EL1    | 32 | 0      | rw | Cluster Thread Scheme ID                         |
| CNTFRQ_EL0              | 32 | 4c4b40 | rw | Counter-Timer Frequency                          |
| CNTHCTL_EL2             | 32 | 3      | rw | Counter-Timer Hypervisor Control                 |
| CNTHP_CTL_EL2           | 32 | 0      | rw | Counter-Timer Physical Timer Control (EL2)       |
| CNTHP_CVAL_EL2          | 64 | 0      | rw | Counter-Timer Physical Timer CompareValue (EL2)  |
| CNTHP_TVAL_EL2          | 32 | 0      | rw | Counter-Timer Physical Timer TimerValue (EL2)    |
| CNTHV_CTL_EL2           | 32 | 0      | rw | Counter-Timer Virtual Timer Control (EL2)        |
| CNTHV_CVAL_EL2          | 64 | 0      | rw | Counter-Timer Virtual Timer CompareValue (EL2)   |
| CNTHV_TVAL_EL2          | 32 | 0      | rw | Counter-Timer Virtual Timer TimerValue (EL2)     |
| CNTKCTL_EL1             | 32 | 0      | rw | Counter-Timer Kernel Control                     |
| CNTKCTL_EL12            | 32 | 0      | rw | Counter-Timer Kernel Control Alias               |
| CNTPCT_EL0              | 64 | 0      | r- | Counter-Timer Physical Count                     |
| CNTPS_CTL_EL1           | 32 | 0      | rw | Counter-Timer Secure Physical Timer Control      |
| CNTPS_CVAL_EL1          | 64 | 0      | rw | Counter-Timer Secure Physical Timer CompareValue |
| CNTPS_TVAL_EL1          | 32 | 0      | rw | Counter-Timer Secure Physical Timer TimerValue   |
| CNTP_CTL_EL0            | 32 | 0      | rw | Counter-Timer Physical Timer Control             |
| CNTP_CTL_EL02           | 32 | 0      | rw | Counter-Timer Physical Timer Control Alias       |
| CNTP_CVAL_EL0           | 64 | 0      | rw | Counter-Timer Physical Timer CompareValue        |
| CNTP_CVAL_EL02          | 64 | 0      | rw | Counter-Timer Physical Timer CompareValue Alias  |
| CNTP_TVAL_EL0           | 32 | 0      | rw | Counter-Timer Physical Timer TimerValue          |
| CNTP_TVAL_EL02          | 32 | 0      | rw | Counter-Timer Physical Timer TimerValue Alias    |
| CNTVCT_EL0              | 64 | 0      | r- | Counter-Timer Virtual Count                      |
| CNTVOFF_EL2             | 64 | 0      | rw | Counter-Timer Virtual Offset                     |
| CNTV_CTL_EL0            | 32 | 0      | rw | Counter-Timer Virtual Timer Control              |
| CNTV_CTL_EL02           | 32 | 0      | rw | Counter-Timer Virtual Timer Control Alias        |
| CNTV_CVAL_EL0           | 64 | 0      | rw | Counter-Timer Virtual Timer CompareValue         |
| CNTV_CVAL_EL02          | 64 | 0      | rw | Counter-Timer Virtual Timer CompareValue Alias   |
| CNTV_TVAL_EL0           | 32 | 0      | rw | Counter-Timer Virtual Timer TimerValue           |
| CNTV_TVAL_EL02          | 32 | 0      | rw | Counter-Timer Virtual Timer TimerValue Alias     |
| CONTEXTIDR_EL1          | 32 | 0      | rw | Context ID (EL1)                                 |
| CONTEXTIDR_EL2          | 32 | 0      | rw | Context ID (EL2)                                 |
| CONTEXTIDR_EL12         | 32 | 0      | rw | Context ID (EL1) Alias                           |
| CPACR_EL1               | 32 | 0      | rw | Architectural Feature Access Control             |
| CPACR_EL12              | 32 | 0      | rw | Architectural Feature Access Control Alias       |
| CPTR_EL2                | 32 | 33ff   | rw | Architectural Feature Trap (EL2)                 |

|                   |    |          |    |                                       |
|-------------------|----|----------|----|---------------------------------------|
| CPTR_EL3          | 32 | 0        | rw | Architectural Feature Trap (EL3)      |
| CPUACTLR2_EL1     | 64 | 0        | rw | CPU Auxiliary Control 2               |
| CPUACTLR3_EL1     | 64 | 0        | rw | CPU Auxiliary Control 3               |
| CPUACTLR_EL1      | 64 | 0        | rw | CPU Auxiliary Control                 |
| CPUAMCFGR_EL0     | 32 | 3f04     | r- | Activity Monitors Configuration       |
| CPUAMCNTENCLR_EL0 | 32 | 0        | rw | Activity Monitor Enable Clear         |
| CPUAMCNTENSET_EL0 | 32 | 0        | rw | Activity Monitor Enable Set           |
| CPUAMEVCNTR0_EL0  | 64 | 0        | rw | Activity Monitor Event Counter 0      |
| CPUAMEVCNTR1_EL0  | 64 | 0        | rw | Activity Monitor Event Counter 1      |
| CPUAMEVCNTR2_EL0  | 64 | 0        | rw | Activity Monitor Event Counter 2      |
| CPUAMEVCNTR3_EL0  | 64 | 0        | rw | Activity Monitor Event Counter 3      |
| CPUAMEVCNTR4_EL0  | 64 | 0        | rw | Activity Monitor Event Counter 4      |
| CPUAMEVTYPER0_EL0 | 32 | 11       | rw | Activity Monitor Event Type 0         |
| CPUAMEVTYPER1_EL0 | 32 | ef       | rw | Activity Monitor Event Type 1         |
| CPUAMEVTYPER2_EL0 | 32 | 8        | rw | Activity Monitor Event Type 2         |
| CPUAMEVTYPER3_EL0 | 32 | 0        | rw | Activity Monitor Event Type 3         |
| CPUAMEVTYPER4_EL0 | 32 | 0        | rw | Activity Monitor Event Type 4         |
| CPUAMUSERENR_EL0  | 32 | 0        | rw | Activity Monitor EL0 Enable Access    |
| CPUCFR_EL1        | 32 | 0        | r- | CPU Configuration                     |
| CPUECTLR_EL1      | 64 | 1400bc00 | rw | CPU Extended Control                  |
| CPUPCR_EL3        | 64 | 0        | rw | CPU Private Control                   |
| CPUPMR_EL3        | 64 | 0        | rw | CPU Private Mask                      |
| CPUPOR_EL3        | 64 | 0        | rw | CPU Private Operation                 |
| CPUPSELR_EL3      | 32 | 0        | rw | CPU Private Selection                 |
| CPUPWRCTLR_EL1    | 32 | 0        | rw | CPU Power Control                     |
| CSSELR_EL1        | 32 | 0        | rw | Current Size Selection                |
| CTR_EL0           | 32 | 84448004 | r- | Cache Type                            |
| CurrentEL         | 32 | c        | r- | Current Exception Level               |
| DAIF              | 32 | 3c0      | rw | Interrupt Mask Bits                   |
| DBGAUTHSTATUS_EL1 | 32 | aa       | r- | Debug Authentication Status           |
| DBGBCR0_EL1       | 32 | 1e0      | rw | Debug Breakpoint Control 0            |
| DBGBCR1_EL1       | 32 | 1e0      | rw | Debug Breakpoint Control 1            |
| DBGBCR2_EL1       | 32 | 1e0      | rw | Debug Breakpoint Control 2            |
| DBGBCR3_EL1       | 32 | 1e0      | rw | Debug Breakpoint Control 3            |
| DBGBCR4_EL1       | 32 | 1e0      | rw | Debug Breakpoint Control 4            |
| DBGBCR5_EL1       | 32 | 1e0      | rw | Debug Breakpoint Control 5            |
| DBGBVR0_EL1       | 64 | 0        | rw | Debug Breakpoint Value 0              |
| DBGBVR1_EL1       | 64 | 0        | rw | Debug Breakpoint Value 1              |
| DBGBVR2_EL1       | 64 | 0        | rw | Debug Breakpoint Value 2              |
| DBGBVR3_EL1       | 64 | 0        | rw | Debug Breakpoint Value 3              |
| DBGBVR4_EL1       | 64 | 0        | rw | Debug Breakpoint Value 4              |
| DBGBVR5_EL1       | 64 | 0        | rw | Debug Breakpoint Value 5              |
| DBGCLAIMCLR_EL1   | 32 | 0        | rw | Debug Claim Tag Clear                 |
| DBGCLAIMSET_EL1   | 32 | 0        | rw | Debug Claim Tag Set                   |
| DBGDTRTRX_EL0     | 32 | 0        | rw | Debug Data Transfer, Transmit/Receive |
| DBGDTR_EL0        | 64 | 0        | rw | Debug Data Transfer                   |
| DBGPRCR_EL1       | 32 | 0        | rw | Debug Power Control                   |
| DBGWCR0_EL1       | 32 | 0        | rw | Debug Watchpoint Control 0            |
| DBGWCR1_EL1       | 32 | 0        | rw | Debug Watchpoint Control 1            |
| DBGWCR2_EL1       | 32 | 0        | rw | Debug Watchpoint Control 2            |
| DBGWCR3_EL1       | 32 | 0        | rw | Debug Watchpoint Control 3            |
| DBGWVR0_EL1       | 64 | 0        | rw | Debug Watchpoint Value 0              |
| DBGWVR1_EL1       | 64 | 0        | rw | Debug Watchpoint Value 1              |
| DBGWVR2_EL1       | 64 | 0        | rw | Debug Watchpoint Value 2              |
| DBGWVR3_EL1       | 64 | 0        | rw | Debug Watchpoint Value 3              |
| DCZID_EL0         | 32 | 4        | r- | Data Cache Zero ID                    |

|                 |    |          |    |                                                           |
|-----------------|----|----------|----|-----------------------------------------------------------|
| DISR_EL1        | 32 | 0        | rw | Deferred Interrupt Status                                 |
| DLR_EL0         | 64 | 0        | rw | Debug Link                                                |
| DSPSR_EL0       | 32 | 0        | rw | Debug Saved Program Status                                |
| ELR_EL1         | 64 | 0        | rw | Exception Link (EL1)                                      |
| ELR_EL2         | 64 | 0        | rw | Exception Link (EL2)                                      |
| ELR_EL3         | 64 | 0        | rw | Exception Link (EL3)                                      |
| ELR_EL12        | 32 | 0        | rw | Exception Link (EL1) Alias                                |
| ERRIDR_EL1      | 32 | 0        | r- | Error Record ID                                           |
| ERRSELR_EL1     | 32 | 0        | rw | Error Record Select                                       |
| ERXADDR_EL1     | 64 | 0        | rw | Selected Error Record Address                             |
| ERXCTLR_EL1     | 64 | 0        | rw | Selected Error Record Control                             |
| ERXFR_EL1       | 64 | 0        | r- | Selected Error Record Feature                             |
| ERXMISC0_EL1    | 64 | 0        | rw | Selected Error Record Miscellaneous 0                     |
| ERXMISC1_EL1    | 64 | 0        | rw | Selected Error Record Miscellaneous 1                     |
| ERXPFPGCDNR_EL1 | 32 | 0        | rw | Selected Error Pseudo Fault Generation Count Down         |
| ERXPFPGCTLR_EL1 | 32 | 0        | rw | Selected Error Pseudo Fault Generation Control            |
| ERXPFPGFR_EL1   | 32 | 0        | r- | Selected Error Pseudo Fault Generation Feature            |
| ERXSTATUS_EL1   | 32 | 0        | rw | Selected Error Record Status                              |
| ESR_EL1         | 32 | 0        | rw | Exception Syndrome (EL1)                                  |
| ESR_EL2         | 32 | 0        | rw | Exception Syndrome (EL2)                                  |
| ESR_EL3         | 32 | 0        | rw | Exception Syndrome (EL3)                                  |
| ESR_EL12        | 32 | 0        | rw | Exception Syndrome (EL1) Alias                            |
| FAR_EL1         | 64 | 0        | rw | Fault Address (EL1)                                       |
| FAR_EL2         | 64 | 0        | rw | Fault Address (EL2)                                       |
| FAR_EL3         | 64 | 0        | rw | Fault Address (EL3)                                       |
| FAR_EL12        | 64 | 0        | rw | Fault Address (EL1) Alias                                 |
| FPCR            | 32 | 0        | rw | Floating Point Control                                    |
| FPSR            | 32 | 0        | rw | Floating Point Status                                     |
| HACR_EL2        | 32 | 0        | rw | Hypervisor Auxiliary Control                              |
| HCR_EL2         | 64 | 80000002 | rw | Hypervisor Configuration                                  |
| HPFAR_EL2       | 64 | 0        | rw | Hypervisor IPA Fault Address                              |
| HSTR_EL2        | 32 | 0        | rw | Hypervisor System Trap                                    |
| ICC_AP0R0_EL1   | 32 | 0        | rw | Interrupt Controller Active Priorities Group 0, 0         |
| ICC_AP1R0_EL1   | 32 | 0        | rw | Interrupt Controller Active Priorities Group 1, 0         |
| ICC_ASGI1R_EL1  | 64 | -        | -w | Interrupt Controller Alias SGI Group 1                    |
| ICC_BPR0_EL1    | 32 | 2        | rw | Interrupt Controller Binary Point 0                       |
| ICC_BPR1_EL1    | 32 | 2        | rw | Interrupt Controller Binary Point 1                       |
| ICC_CTLR_EL1    | 32 | 400      | rw | Interrupt Controller Control (EL1)                        |
| ICC_CTLR_EL3    | 32 | 400      | rw | Interrupt Controller Control (EL3)                        |
| ICC_DIR_EL1     | 32 | -        | -w | Interrupt Controller Deactivate Interrupt                 |
| ICC_EOIR0_EL1   | 32 | -        | -w | Interrupt Controller End of Interrupt 0                   |
| ICC_EOIR1_EL1   | 32 | -        | -w | Interrupt Controller End of Interrupt 1                   |
| ICC_HPPIR0_EL1  | 32 | 3ff      | r- | Interrupt Controller Highest Priority Pending Interrupt 0 |
| ICC_HPPIR1_EL1  | 32 | 3ff      | r- | Interrupt Controller Highest Priority Pending Interrupt 1 |
| ICC_IAR0_EL1    | 32 | 3ff      | r- | Interrupt Controller Interrupt Acknowledge 0              |
| ICC_IAR1_EL1    | 32 | 3ff      | r- | Interrupt Controller Interrupt Acknowledge 1              |

|                  |    |                      |    |                                                             |
|------------------|----|----------------------|----|-------------------------------------------------------------|
| ICC_IGRPEN0_EL1  | 32 | 0                    | rw | Interrupt Controller Interrupt Group 0 Enable               |
| ICC_IGRPEN1_EL1  | 32 | 0                    | rw | Interrupt Controller Interrupt Group 1 Enable               |
| ICC_IGRPEN1_EL3  | 32 | 0                    | rw | Interrupt Controller Interrupt Group 1 Enable (EL3)         |
| ICC_PMR_EL1      | 32 | 0                    | rw | Interrupt Controller Priority Mask                          |
| ICC_RPR_EL1      | 32 | ff                   | r- | Interrupt Controller Running Priority                       |
| ICC_SGI0R_EL1    | 64 | -                    | -w | Interrupt Controller SGI Group 0                            |
| ICC_SGI1R_EL1    | 64 | -                    | -w | Interrupt Controller SGI Group 1                            |
| ICC_SRE_EL1      | 32 | 1                    | rw | Interrupt Controller System Register Enable (EL1)           |
| ICC_SRE_EL2      | 32 | 9                    | rw | Interrupt Controller System Register Enable (EL2)           |
| ICC_SRE_EL3      | 32 | 9                    | rw | Interrupt Controller System Register Enable (EL3)           |
| ICH_AP0R0_EL2    | 32 | 0                    | rw | Interrupt Controller Hyp Active Priorities Group 0 (Word 0) |
| ICH_AP1R0_EL2    | 32 | 0                    | rw | Interrupt Controller Hyp Active Priorities Group 1 (Word 0) |
| ICH_EISR_EL2     | 32 | 0                    | r- | Interrupt Controller End of Interrupt Status                |
| ICH_ELRSR_EL2    | 32 | f                    | r- | Interrupt Controller Empty List Register Status             |
| ICH_HCR_EL2      | 32 | 0                    | rw | Interrupt Controller Hypervisor Control                     |
| ICH_LR0_EL2      | 64 | 0                    | rw | Interrupt Controller List 0                                 |
| ICH_LR1_EL2      | 64 | 0                    | rw | Interrupt Controller List 1                                 |
| ICH_LR2_EL2      | 64 | 0                    | rw | Interrupt Controller List 2                                 |
| ICH_LR3_EL2      | 64 | 0                    | rw | Interrupt Controller List 3                                 |
| ICH_MISR_EL2     | 32 | 0                    | r- | Interrupt Controller Maintenance Interrupt State            |
| ICH_VMCR_EL2     | 32 | 4c0000               | rw | Interrupt Controller Virtual Machine Control                |
| ICH_VTR_EL2      | 32 | 90100003             | r- | Interrupt Controller VGIC Type                              |
| ID_AA64AFR0_EL1  | 64 | 0                    | r- | AArch64 Auxiliary Feature 0                                 |
| ID_AA64AFR1_EL1  | 64 | 0                    | r- | AArch64 Auxiliary Feature 1                                 |
| ID_AA64DFR0_EL1  | 64 | 10305408             | r- | AArch64 Debug Feature 0                                     |
| ID_AA64DFR1_EL1  | 64 | 0                    | r- | AArch64 Debug Feature 1                                     |
| ID_AA64ISAR0_EL1 | 64 | 1000<br>10211120     | r- | AArch64 Instruction Set Attribute 0                         |
| ID_AA64ISAR1_EL1 | 64 | 100001               | r- | AArch64 Instruction Set Attribute 1                         |
| ID_AA64MMFR0_EL1 | 64 | 101124               | r- | AArch64 Memory Model Feature 0                              |
| ID_AA64MMFR1_EL1 | 64 | 10212122             | r- | AArch64 Memory Model Feature 1                              |
| ID_AA64MMFR2_EL1 | 64 | 1011                 | r- | AArch64 Memory Model Feature 2                              |
| ID_AA64PFR0_EL1  | 64 | 11000000<br>11111111 | r- | AArch64 Processor Feature 0                                 |
| ID_AA64PFR1_EL1  | 64 | 10                   | r- | AArch64 Processor Feature 1                                 |
| ID_AFR0_EL1      | 32 | 0                    | r- | Auxiliary Feature 0                                         |
| ID_DFR0_EL1      | 32 | 0                    | r- | Debug Feature 0                                             |
| ID_ISAR0_EL1     | 32 | 0                    | r- | Instruction Set Attribute 0                                 |
| ID_ISAR1_EL1     | 32 | 0                    | r- | Instruction Set Attribute 1                                 |
| ID_ISAR2_EL1     | 32 | 0                    | r- | Instruction Set Attribute 2                                 |
| ID_ISAR3_EL1     | 32 | 0                    | r- | Instruction Set Attribute 3                                 |
| ID_ISAR4_EL1     | 32 | 0                    | r- | Instruction Set Attribute 4                                 |
| ID_ISAR5_EL1     | 32 | 0                    | r- | Instruction Set Attribute 5                                 |
| ID_ISAR6_EL1     | 32 | 0                    | r- | Instruction Set Attribute 6                                 |
| ID_MMFR0_EL1     | 32 | 0                    | r- | Memory Model Feature 0                                      |

|                |    |                      |    |                                          |
|----------------|----|----------------------|----|------------------------------------------|
| ID_MMFR1_EL1   | 32 | 0                    | r- | Memory Model Feature 1                   |
| ID_MMFR2_EL1   | 32 | 0                    | r- | Memory Model Feature 2                   |
| ID_MMFR3_EL1   | 32 | 0                    | r- | Memory Model Feature 3                   |
| ID_MMFR4_EL1   | 32 | 0                    | r- | Memory Model Feature 4                   |
| ID_PFR0_EL1    | 32 | 0                    | r- | Processor Feature 0                      |
| ID_PFR1_EL1    | 32 | 0                    | r- | Processor Feature 1                      |
| ID_PFR2_EL1    | 32 | 0                    | r- | Processor Feature 2                      |
| ISR_EL1        | 32 | 0                    | r- | Interrupt Status                         |
| LORC_EL1       | 32 | 0                    | rw | LORegion Control                         |
| LOREA_EL1      | 64 | 0                    | rw | LORegion End Address                     |
| LORID_EL1      | 32 | 40004                | r- | LORegion ID                              |
| LORN_EL1       | 32 | 0                    | rw | LORegion Number                          |
| LORSA_EL1      | 64 | 0                    | rw | LORegion Start Address                   |
| MAIR_EL1       | 64 | 44e048e0<br>00098aa4 | rw | Memory Attribute Indirection (EL1)       |
| MAIR_EL2       | 64 | 0                    | rw | Memory Attribute Indirection (EL2)       |
| MAIR_EL3       | 64 | 44e048e0<br>00098aa4 | rw | Memory Attribute Indirection (EL3)       |
| MAIR_EL12      | 64 | 0                    | rw | Memory Attribute Indirection (EL1) Alias |
| MDCCINT_EL1    | 32 | 0                    | rw | Monitor DCC Interrupt Enable             |
| MDCCSR_EL0     | 32 | 0                    | r- | Monitor DCC Status                       |
| MDCR_EL2       | 32 | 6                    | rw | Monitor Debug Configuration (EL2)        |
| MDCR_EL3       | 32 | 0                    | rw | Monitor Debug Configuration (EL3)        |
| MDRAR_EL1      | 64 | 0                    | r- | Monitor Debug ROM Address                |
| MDSCR_EL1      | 32 | 0                    | rw | Monitor Debug System Control             |
| MIDR_EL1       | 32 | 411fd430             | r- | Main ID                                  |
| MPIDR_EL1      | 64 | 81000000             | r- | Multiprocessor Affinity                  |
| MVFR0_EL1      | 32 | 0                    | r- | Media and VFP Feature 0                  |
| MVFR1_EL1      | 32 | 0                    | r- | Media and VFP Feature 1                  |
| MVFR2_EL1      | 32 | 0                    | r- | Media and VFP Feature 2                  |
| NZCV           | 32 | 0                    | rw | Condition Flags                          |
| OSDLR_EL1      | 32 | 0                    | rw | OS Double Lock                           |
| OSDTRRX_EL1    | 32 | 0                    | rw | OS Lock Data Transfer, Receive           |
| OSDTRTX_EL1    | 32 | 0                    | rw | OS Lock Data Transfer, Transmit          |
| OSECCR_EL1     | 32 | 0                    | rw | OS Lock Exception Catch Control          |
| OSLAR_EL1      | 32 | -                    | -w | OS Lock Access                           |
| OSLSR_EL1      | 32 | a                    | r- | OS Lock Status                           |
| PAN            | 32 | 0                    | rw | Privileged Access Never                  |
| PAR_EL1        | 64 | 0                    | rw | Physical Address                         |
| PMCCFILTR_EL0  | 32 | 0                    | rw | Performance Monitors Cycle Count Filter  |
| PMCCNTR_EL0    | 64 | 0                    | rw | Performance Monitors Cycle Count         |
| PMCEID0_EL0    | 64 | fbff7f3f             | r- | Performance Monitors Common Event ID 0   |
| PMCEID1_EL0    | 64 | 1flae7b              | r- | Performance Monitors Common Event ID 1   |
| PMCNTENCLR_EL0 | 32 | 0                    | rw | Performance Monitors Count Enable Clear  |
| PMCNTENSET_EL0 | 32 | 0                    | rw | Performance Monitors Count Enable Set    |
| PMCR_EL0       | 32 | 414a3040             | rw | Performance Monitors Control             |
| PMEVCNTR0_EL0  | 32 | 0                    | rw | Performance Monitors Event Count 0       |
| PMEVCNTR1_EL0  | 32 | 0                    | rw | Performance Monitors Event Count 1       |
| PMEVCNTR2_EL0  | 32 | 0                    | rw | Performance Monitors Event Count 2       |
| PMEVCNTR3_EL0  | 32 | 0                    | rw | Performance Monitors Event Count 3       |
| PMEVCNTR4_EL0  | 32 | 0                    | rw | Performance Monitors Event Count 4       |
| PMEVCNTR5_EL0  | 32 | 0                    | rw | Performance Monitors Event Count 5       |
| PMEVTYPE0_EL0  | 32 | 0                    | rw | Performance Monitors Event Type 0        |
| PMEVTYPE1_EL0  | 32 | 0                    | rw | Performance Monitors Event Type 1        |
| PMEVTYPE2_EL0  | 32 | 0                    | rw | Performance Monitors Event Type 2        |
| PMEVTYPE3_EL0  | 32 | 0                    | rw | Performance Monitors Event Type 3        |

|                |    |          |    |                                                 |
|----------------|----|----------|----|-------------------------------------------------|
| PMEVTYPER4_EL0 | 32 | 0        | rw | Performance Monitors Event Type 4               |
| PMEVTYPER5_EL0 | 32 | 0        | rw | Performance Monitors Event Type 5               |
| PMINTENCLR_EL1 | 32 | 0        | rw | Performance Monitors Interrupt Enable Clear     |
| PMINTENSET_EL1 | 32 | 0        | rw | Performance Monitors Interrupt Enable Set       |
| PMOVSCLR_EL0   | 32 | 0        | rw | Performance Monitors Overflow Flag Status Clear |
| PMOVSSET_EL0   | 32 | 0        | rw | Performance Monitors Overflow Flag Status Set   |
| PMSELR_EL0     | 32 | 0        | rw | Performance Monitors Event Counter Selection    |
| PMSWINC_EL0    | 32 | -        | -w | Performance Monitors Software Increment         |
| PMUSERENR_EL0  | 32 | 0        | rw | Performance Monitors User Enable                |
| PMXEVCNTR_EL0  | 32 | 0        | rw | Performance Monitors Selected Event Count       |
| PMXEVTYPER_EL0 | 32 | 0        | rw | Performance Monitors Selected Event Type        |
| REVIDR_EL1     | 32 | 0        | r- | Revision ID                                     |
| RVBAR_EL3      | 64 | 0        | r- | Reset Vector Base Address (EL3)                 |
| SCR_EL3        | 32 | 430      | rw | Secure Configuration                            |
| SCTLR_EL1      | 64 | 30d50998 | rw | System Control (EL1)                            |
| SCTLR_EL2      | 64 | 30c50838 | rw | System Control (EL2)                            |
| SCTLR_EL3      | 64 | 30c50838 | rw | System Control (EL3)                            |
| SCTLR_EL12     | 64 | 0        | rw | System Control (EL1) Alias                      |
| SPSR_EL1       | 32 | 0        | rw | Saved Program Status (EL1)                      |
| SPSR_EL2       | 32 | 0        | rw | Saved Program Status (EL2)                      |
| SPSR_EL3       | 32 | 0        | rw | Saved Program Status (EL3)                      |
| SPSR_EL12      | 32 | 0        | rw | Saved Program Status (EL1) Alias                |
| SPSR_abt       | 32 | 0        | rw | Saved Program Status (Abort Mode)               |
| SPSR_fiq       | 32 | 0        | rw | Saved Program Status (FIQ Mode)                 |
| SPSR_irq       | 32 | 0        | rw | Saved Program Status (IRQ Mode)                 |
| SPSR_und       | 32 | 0        | rw | Saved Program Status (Undefined Mode)           |
| SPSel          | 32 | 1        | rw | Stack Pointer Select                            |
| SP_EL0         | 64 | 0        | rw | Stack Pointer (EL0)                             |
| SP_EL1         | 64 | 0        | rw | Stack Pointer (EL1)                             |
| SP_EL2         | 64 | 0        | rw | Stack Pointer (EL2)                             |
| SP_EL3         | 64 | 0        | rw | Stack Pointer (EL3)                             |
| TCR_EL1        | 64 | 0        | rw | Translation Control (EL1)                       |
| TCR_EL2        | 64 | 80000000 | rw | Translation Control (EL2)                       |
| TCR_EL3        | 32 | 80800000 | rw | Translation Control (EL3)                       |
| TCR_EL12       | 64 | 0        | rw | Translation Control (EL1) Alias                 |
| TPIDRRO_EL0    | 64 | 0        | rw | Thread Pointer/ID, Read-Only (EL0)              |
| TPIDR_EL0      | 64 | 0        | rw | Thread Pointer/ID (EL0)                         |
| TPIDR_EL1      | 64 | 0        | rw | Thread Pointer/ID (EL1)                         |
| TPIDR_EL2      | 64 | 0        | rw | Thread Pointer/ID (EL2)                         |
| TPIDR_EL3      | 64 | 0        | rw | Thread Pointer/ID (EL3)                         |
| TTBR0_EL1      | 64 | 0        | rw | Translation Table Base 0 (EL1)                  |
| TTBR0_EL2      | 64 | 0        | rw | Translation Table Base 0 (EL2)                  |
| TTBR0_EL3      | 64 | 0        | rw | Translation Table Base 0 (EL3)                  |
| TTBR0_EL12     | 64 | 0        | rw | Translation Table Base 0 (EL1) Alias            |
| TTBR1_EL1      | 64 | 0        | rw | Translation Table Base 1 (EL1)                  |
| TTBR1_EL2      | 64 | 0        | rw | Translation Table Base 1 (EL2)                  |
| TTBR1_EL12     | 64 | 0        | rw | Translation Table Base 1 (EL1) Alias            |
| UAO            | 32 | 0        | rw | Unprivileged Access Override                    |
| VBAR_EL1       | 64 | 0        | rw | Vector Base Address (EL1)                       |
| VBAR_EL2       | 64 | 0        | rw | Vector Base Address (EL2)                       |
| VBAR_EL3       | 64 | 0        | rw | Vector Base Address (EL3)                       |
| VBAR_EL12      | 64 | 0        | rw | Vector Base Address (EL1) Alias                 |

|            |    |          |    |                                       |
|------------|----|----------|----|---------------------------------------|
| VDISR_EL2  | 32 | 0        | rw | Virtual Deferred Interrupt Status     |
| VMPIDR_EL2 | 64 | 81000000 | rw | Virtualization Multiprocessor ID      |
| VPIDR_EL2  | 32 | 411fd430 | rw | Virtualization Processor ID           |
| VSESR_EL2  | 32 | 0        | rw | Virtual SError Exception Syndrome     |
| VTTCR_EL2  | 32 | 80000000 | rw | Virtualization Translation Control    |
| VTTBR_EL2  | 64 | 0        | rw | Virtualization Translation Table Base |

Table 13.3: Registers at level 3, type:THREAD group:AArch64\_system

### 13.3.4 AArch64\_secure\_system

Registers at level:3, type:THREAD group:AArch64\_secure\_system

| Name              | Bits | Initial-Hex | RW | Description                                               |
|-------------------|------|-------------|----|-----------------------------------------------------------|
| ICC_APIR0_EL1.S   | 32   | 0           | rw | Interrupt Controller Active Priorities Group 1, 0         |
| ICC_ASGI1R_EL1.S  | 64   | -           | -w | Interrupt Controller Alias SGI Group 1                    |
| ICC_BPR1_EL1.S    | 32   | 2           | rw | Interrupt Controller Binary Point 1                       |
| ICC_CTLR_EL1.S    | 32   | 400         | rw | Interrupt Controller Control (EL1)                        |
| ICC_DIR_EL1.S     | 32   | -           | -w | Interrupt Controller Deactivate Interrupt                 |
| ICC_EOIR0_EL1.S   | 32   | -           | -w | Interrupt Controller End of Interrupt 0                   |
| ICC_EOIR1_EL1.S   | 32   | -           | -w | Interrupt Controller End of Interrupt 1                   |
| ICC_HPPIR0_EL1.S  | 32   | 3ff         | r- | Interrupt Controller Highest Priority Pending Interrupt 0 |
| ICC_HPPIR1_EL1.S  | 32   | 3ff         | r- | Interrupt Controller Highest Priority Pending Interrupt 1 |
| ICC_IAR0_EL1.S    | 32   | 3ff         | r- | Interrupt Controller Interrupt Acknowledge 0              |
| ICC_IAR1_EL1.S    | 32   | 3ff         | r- | Interrupt Controller Interrupt Acknowledge 1              |
| ICC_IGRPEN0_EL1.S | 32   | 0           | rw | Interrupt Controller Interrupt Group 0 Enable             |
| ICC_IGRPEN1_EL1.S | 32   | 0           | rw | Interrupt Controller Interrupt Group 1 Enable             |
| ICC_IGRPEN1_EL3.S | 32   | 0           | rw | Interrupt Controller Interrupt Group 1 Enable (EL3)       |
| ICC_PMR_EL1.S     | 32   | 0           | rw | Interrupt Controller Priority Mask                        |
| ICC_RPR_EL1.S     | 32   | ff          | r- | Interrupt Controller Running Priority                     |
| ICC_SGI0R_EL1.S   | 64   | -           | -w | Interrupt Controller SGI Group 0                          |
| ICC_SGI1R_EL1.S   | 64   | -           | -w | Interrupt Controller SGI Group 1                          |
| ICC_SRE_EL1.S     | 32   | 1           | rw | Interrupt Controller System Register Enable (EL1)         |

Table 13.4: Registers at level 3, type:THREAD group:AArch64\_secure\_system

### 13.3.5 AArch64\_non\_secure\_system

Registers at level:3, type:THREAD group:AArch64\_non\_secure\_system

| Name               | Bits | Initial-Hex | RW | Description                                               |
|--------------------|------|-------------|----|-----------------------------------------------------------|
| ICC_APIR0_EL1.NS   | 32   | 0           | rw | Interrupt Controller Active Priorities Group 1, 0         |
| ICC_ASGI1R_EL1.NS  | 64   | -           | -w | Interrupt Controller Alias SGI Group 1                    |
| ICC_BPR1_EL1.NS    | 32   | 3           | rw | Interrupt Controller Binary Point 1                       |
| ICC_CTLR_EL1.NS    | 32   | 400         | rw | Interrupt Controller Control (EL1)                        |
| ICC_DIR_EL1.NS     | 32   | -           | -w | Interrupt Controller Deactivate Interrupt                 |
| ICC_EOIR0_EL1.NS   | 32   | -           | -w | Interrupt Controller End of Interrupt 0                   |
| ICC_EOIR1_EL1.NS   | 32   | -           | -w | Interrupt Controller End of Interrupt 1                   |
| ICC_HPPIR0_EL1.NS  | 32   | 3ff         | r- | Interrupt Controller Highest Priority Pending Interrupt 0 |
| ICC_HPPIR1_EL1.NS  | 32   | 3ff         | r- | Interrupt Controller Highest Priority Pending Interrupt 1 |
| ICC_IAR0_EL1.NS    | 32   | 3ff         | r- | Interrupt Controller Interrupt Acknowledge 0              |
| ICC_IAR1_EL1.NS    | 32   | 3ff         | r- | Interrupt Controller Interrupt Acknowledge 1              |
| ICC_IGRPEN0_EL1.NS | 32   | 0           | rw | Interrupt Controller Interrupt Group 0 Enable             |
| ICC_IGRPEN1_EL1.NS | 32   | 0           | rw | Interrupt Controller Interrupt Group 1 Enable             |
| ICC_IGRPEN1_EL3.NS | 32   | 0           | rw | Interrupt Controller Interrupt Group 1 Enable (EL3)       |

|                  |    |    |    |                                                   |
|------------------|----|----|----|---------------------------------------------------|
| ICC_PMR_EL1_NS   | 32 | 0  | rw | Interrupt Controller Priority Mask                |
| ICC_RPR_EL1_NS   | 32 | ff | r- | Interrupt Controller Running Priority             |
| ICC_SGI0R_EL1_NS | 64 | -  | -w | Interrupt Controller SGI Group 0                  |
| ICC_SGI1R_EL1_NS | 64 | -  | -w | Interrupt Controller SGI Group 1                  |
| ICC_SRE_EL1_NS   | 32 | 1  | rw | Interrupt Controller System Register Enable (EL1) |

Table 13.5: Registers at level 3, type:THREAD group:AArch64\_non\_secure\_system

### 13.3.6 AArch64\_system\_artifact

Registers at level:3, type:THREAD group:AArch64\_system\_artifact

| Name | Bits | Initial-Hex | RW | Description |
|------|------|-------------|----|-------------|
| cpsr | 32   | 3cd         | rw |             |

Table 13.6: Registers at level 3, type:THREAD group:AArch64\_system\_artifact

### 13.3.7 AArch64\_SYS\_instruction\_registers

Registers at level:3, type:THREAD group:AArch64\_SYS\_instruction\_registers

| Name        | Bits | Initial-Hex | RW | Description |
|-------------|------|-------------|----|-------------|
| ATS1E0R     | 64   | -           | -w |             |
| ATS1E0W     | 64   | -           | -w |             |
| ATS1E1R     | 64   | -           | -w |             |
| ATS1E1RP    | 64   | -           | -w |             |
| ATS1E1W     | 64   | -           | -w |             |
| ATS1E1WP    | 64   | -           | -w |             |
| ATS1E2R     | 64   | -           | -w |             |
| ATS1E2W     | 64   | -           | -w |             |
| ATS1E3R     | 64   | -           | -w |             |
| ATS1E3W     | 64   | -           | -w |             |
| ATS12E0R    | 64   | -           | -w |             |
| ATS12E0W    | 64   | -           | -w |             |
| ATS12E1R    | 64   | -           | -w |             |
| ATS12E1W    | 64   | -           | -w |             |
| DCCISW      | 32   | -           | -w |             |
| DCCIVAC     | 64   | -           | -w |             |
| DCCSW       | 32   | -           | -w |             |
| DCCVAC      | 64   | -           | -w |             |
| DCCVAP      | 64   | -           | -w |             |
| DCCVAU      | 64   | -           | -w |             |
| DCISW       | 32   | -           | -w |             |
| DCIVAC      | 64   | -           | -w |             |
| DCZVA       | 32   | -           | -w |             |
| ICIALLU     | 32   | -           | -w |             |
| ICIALUIS    | 32   | -           | -w |             |
| ICIVAU      | 64   | -           | -w |             |
| TLBIALLE1   | 64   | -           | -w |             |
| TLBIALLE1IS | 64   | -           | -w |             |
| TLBIALLE2   | 64   | -           | -w |             |
| TLBIALLE2IS | 64   | -           | -w |             |
| TLBIALLE3   | 64   | -           | -w |             |
| TLBIALLE3IS | 64   | -           | -w |             |
| TLBIASIDE1  | 64   | -           | -w |             |

|                 |    |   |    |  |
|-----------------|----|---|----|--|
| TLBIASIDE1IS    | 64 | - | -w |  |
| TLBIIPAS2E1     | 64 | - | -w |  |
| TLBIIPAS2E1IS   | 64 | - | -w |  |
| TLBIIPAS2LE1    | 64 | - | -w |  |
| TLBIIPAS2LE1IS  | 64 | - | -w |  |
| TLBIVAAE1       | 64 | - | -w |  |
| TLBIVAAE1IS     | 64 | - | -w |  |
| TLBIVAALE1      | 64 | - | -w |  |
| TLBIVAALE1IS    | 64 | - | -w |  |
| TLBIVAE1        | 64 | - | -w |  |
| TLBIVAE1IS      | 64 | - | -w |  |
| TLBIVAE2        | 64 | - | -w |  |
| TLBIVAE2IS      | 64 | - | -w |  |
| TLBIVAE3        | 64 | - | -w |  |
| TLBIVAE3IS      | 64 | - | -w |  |
| TLBIVALE1       | 64 | - | -w |  |
| TLBIVALE1IS     | 64 | - | -w |  |
| TLBIVALE2       | 64 | - | -w |  |
| TLBIVALE2IS     | 64 | - | -w |  |
| TLBIVALE3       | 64 | - | -w |  |
| TLBIVALE3IS     | 64 | - | -w |  |
| TLBIVALLE1      | 64 | - | -w |  |
| TLBIVALLE1IS    | 64 | - | -w |  |
| TLBIVALLS12E1   | 64 | - | -w |  |
| TLBIVALLS12E1IS | 64 | - | -w |  |

Table 13.7: Registers at level 3, type:THREAD group:AArch64\_SYS\_instruction\_registers

### 13.3.8 Integration support

Registers at level:3, type:THREAD group:Integration\_support

| Name            | Bits | Initial-Hex | RW | Description                                                                                                                                       |
|-----------------|------|-------------|----|---------------------------------------------------------------------------------------------------------------------------------------------------|
| transactPL      | 32   | 3           | r- | privilege level of current memory transaction                                                                                                     |
| transactAT      | 32   | 0           | r- | current memory transaction type: PA=1, VA=0                                                                                                       |
| artifactPAR     | 64   | 0           | r- | result of address translation for artifact write to ATS1CPR etc                                                                                   |
| PTWBankSelect   | 8    | 0           | rw | select PTW bank (0 is stage 1, 1 is stage 2, 2-5 are stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively)                    |
| PTWBankValid    | 8    | 0           | r- | bitmask of valid banks (0x01 is stage 1, 0x02 is stage 2, 0x04-0x20 are stage 2 walks initiated by stage 1 level 0-3 entry lookups, respectively) |
| PTWAddressValid | 8    | 0           | r- | bitmask of valid bits for each of PTWAddressL0...PTWAddressL3, PTWBase, PTWInput and PTWOutput in current bank                                    |
| PTWAddressNS    | 8    | 0           | r- | bitmask of Non-Secure bits for each of PTWAddressL0...PTWAddressL3, PTWBase and PTWOutput in current bank (PTWInput bit is always 0)              |
| PTWValueValid   | 8    | 0           | r- | bitmask of valid bits for each of PTWValueL0...PTWValueL3 in current bank                                                                         |
| PTWAddressL0    | 64   | 0           | r- | current bank PTW address, level 0                                                                                                                 |
| PTWAddressL1    | 64   | 0           | r- | current bank PTW address, level 1                                                                                                                 |
| PTWAddressL2    | 64   | 0           | r- | current bank PTW address, level 2                                                                                                                 |
| PTWAddressL3    | 64   | 0           | r- | current bank PTW address, level 3                                                                                                                 |
| PTWValueL0      | 64   | 0           | r- | current bank PTW value, level 0                                                                                                                   |
| PTWValueL1      | 64   | 0           | r- | current bank PTW value, level 1                                                                                                                   |

|              |    |   |    |                                                                                            |
|--------------|----|---|----|--------------------------------------------------------------------------------------------|
| PTWValueL2   | 64 | 0 | r- | current bank PTW value, level 2                                                            |
| PTWValueL3   | 64 | 0 | r- | current bank PTW value, level 3                                                            |
| PTWBase      | 64 | 0 | r- | current bank PTW table base address                                                        |
| PTWInput     | 64 | 0 | r- | current bank PTW input address                                                             |
| PTWOutput    | 64 | 0 | r- | current bank PTW output address                                                            |
| PTWPgSize    | 64 | 0 | r- | current bank PTW page size (Valid only when PTWOutput is valid)                            |
| PTWIE_L1S    | 64 | 0 | -w | perform secure EL1 stage 1 page table walk for fetch, filling PTW query registers          |
| PTWD_EL1S    | 64 | 0 | -w | perform secure EL1 stage 1 page table walk for load/store, filling PTW query registers     |
| PTWIE_L1NS   | 64 | 0 | -w | perform non-secure EL1 stage 1 page table walk for fetch, filling PTW query registers      |
| PTWD_EL1NS   | 64 | 0 | -w | perform non-secure EL1 stage 1 page table walk for load/store, filling PTW query registers |
| PTWIE_L2     | 64 | 0 | -w | perform non-secure EL2 page table walk for fetch, filling PTW query registers              |
| PTWD_EL2     | 64 | 0 | -w | perform non-secure EL2 page table walk for load/store, filling PTW query registers         |
| PTWLS2       | 64 | 0 | -w | perform non-secure stage 2 page table walk for fetch, filling PTW query registers          |
| PTWD_S2      | 64 | 0 | -w | perform non-secure stage 2 page table walk for load/store, filling PTW query registers     |
| PTWIE_L3     | 64 | 0 | -w | perform EL3 page table walk for fetch, filling PTW query registers                         |
| PTWD_EL3     | 64 | 0 | -w | perform EL3 page table walk for load/store, filling PTW query registers                    |
| PTWI_current | 64 | 0 | -w | perform current mode page table walk for fetch, filling PTW query registers                |
| PTWD_current | 64 | 0 | -w | perform current mode page table walk for load/store, filling PTW query registers           |
| ResetTLBs    | 8  | 0 | -w | reset all implemented TLBs to initial state                                                |
| HaltReason   | 8  | 0 | r- | bit field indicating halt reason                                                           |
| atomicType   | 8  | 0 | r- | current atomic instruction type (1:atomic, 2:exclusive)                                    |
| WakeWFINow   | 8  | 0 | -w | wake up core from WFI state                                                                |
| ambaResponse | 64 | 0 | rw | external AMBA-PV response                                                                  |

Table 13.8: Registers at level 3, type:THREAD group:Integration\_support

### 13.3.9 MPCore\_distributor

Registers at level:3, type:THREAD group:MPCore\_distributor

| Name            | Bits | Initial-Hex | RW | Description              |
|-----------------|------|-------------|----|--------------------------|
| GICD_CIDR0      | 32   | d           | r- | Component ID 0           |
| GICD_CIDR1      | 32   | f0          | r- | Component ID 1           |
| GICD_CIDR2      | 32   | 5           | r- | Component ID 2           |
| GICD_CIDR3      | 32   | b1          | r- | Component ID 3           |
| GICD_CLRSPLNSR  | 32   | 0           | -w | Clear SPI                |
| GICD_CLRSPLSR   | 32   | 0           | -w | Clear SPI, Secure        |
| GICD_CTLR       | 32   | 30          | rw | Distributor Control      |
| GICD_ICACTIVER0 | 32   | 0           | rw | Interrupt Clear-Active 0 |
| GICD_ICACTIVER1 | 32   | 0           | rw | Interrupt Clear-Active 1 |
| GICD_ICACTIVER2 | 32   | 0           | rw | Interrupt Clear-Active 2 |
| GICD_ICENABLER0 | 32   | fff         | rw | Interrupt Clear-Enable 0 |
| GICD_ICENABLER1 | 32   | 0           | rw | Interrupt Clear-Enable 1 |
| GICD_ICENABLER2 | 32   | 0           | rw | Interrupt Clear-Enable 2 |

|                   |    |          |    |                            |
|-------------------|----|----------|----|----------------------------|
| GICD_ICFGR0       | 32 | aaaaaaaa | rw | Interrupt Configuration 0  |
| GICD_ICFGR1       | 32 | 0        | rw | Interrupt Configuration 1  |
| GICD_ICFGR2       | 32 | 0        | rw | Interrupt Configuration 2  |
| GICD_ICFGR3       | 32 | 0        | rw | Interrupt Configuration 3  |
| GICD_ICFGR4       | 32 | 0        | rw | Interrupt Configuration 4  |
| GICD_ICFGR5       | 32 | 0        | rw | Interrupt Configuration 5  |
| GICD_ICPENDR0     | 32 | 0        | rw | Interrupt Clear-Pending 0  |
| GICD_ICPENDR1     | 32 | 0        | rw | Interrupt Clear-Pending 1  |
| GICD_ICPENDR2     | 32 | 0        | rw | Interrupt Clear-Pending 2  |
| GICD_IGROUPR0     | 32 | 0        | rw | Interrupt Group 0          |
| GICD_IGROUPR1     | 32 | 0        | rw | Interrupt Group 1          |
| GICD_IGROUPR2     | 32 | 0        | rw | Interrupt Group 2          |
| GICD_IGRPMODR0    | 32 | 0        | rw | Interrupt Group Modifier 0 |
| GICD_IGRPMODR1    | 32 | 0        | rw | Interrupt Group Modifier 1 |
| GICD_IGRPMODR2    | 32 | 0        | rw | Interrupt Group Modifier 2 |
| GICD_IIDR         | 32 | 102043b  | r- | Distributor Implementor ID |
| GICD_IPRIORITYR0  | 32 | 0        | rw | Interrupt Priority 0       |
| GICD_IPRIORITYR1  | 32 | 0        | rw | Interrupt Priority 1       |
| GICD_IPRIORITYR2  | 32 | 0        | rw | Interrupt Priority 2       |
| GICD_IPRIORITYR3  | 32 | 0        | rw | Interrupt Priority 3       |
| GICD_IPRIORITYR4  | 32 | 0        | rw | Interrupt Priority 4       |
| GICD_IPRIORITYR5  | 32 | 0        | rw | Interrupt Priority 5       |
| GICD_IPRIORITYR6  | 32 | 0        | rw | Interrupt Priority 6       |
| GICD_IPRIORITYR7  | 32 | 0        | rw | Interrupt Priority 7       |
| GICD_IPRIORITYR8  | 32 | 0        | rw | Interrupt Priority 8       |
| GICD_IPRIORITYR9  | 32 | 0        | rw | Interrupt Priority 9       |
| GICD_IPRIORITYR10 | 32 | 0        | rw | Interrupt Priority 10      |
| GICD_IPRIORITYR11 | 32 | 0        | rw | Interrupt Priority 11      |
| GICD_IPRIORITYR12 | 32 | 0        | rw | Interrupt Priority 12      |
| GICD_IPRIORITYR13 | 32 | 0        | rw | Interrupt Priority 13      |
| GICD_IPRIORITYR14 | 32 | 0        | rw | Interrupt Priority 14      |
| GICD_IPRIORITYR15 | 32 | 0        | rw | Interrupt Priority 15      |
| GICD_IPRIORITYR16 | 32 | 0        | rw | Interrupt Priority 16      |
| GICD_IPRIORITYR17 | 32 | 0        | rw | Interrupt Priority 17      |
| GICD_IPRIORITYR18 | 32 | 0        | rw | Interrupt Priority 18      |
| GICD_IPRIORITYR19 | 32 | 0        | rw | Interrupt Priority 19      |
| GICD_IPRIORITYR20 | 32 | 0        | rw | Interrupt Priority 20      |
| GICD_IPRIORITYR21 | 32 | 0        | rw | Interrupt Priority 21      |
| GICD_IPRIORITYR22 | 32 | 0        | rw | Interrupt Priority 22      |
| GICD_IPRIORITYR23 | 32 | 0        | rw | Interrupt Priority 23      |
| GICD_IROUTER32    | 64 | 0        | rw | Interrupt Routing 32       |
| GICD_IROUTER33    | 64 | 0        | rw | Interrupt Routing 33       |
| GICD_IROUTER34    | 64 | 0        | rw | Interrupt Routing 34       |
| GICD_IROUTER35    | 64 | 0        | rw | Interrupt Routing 35       |
| GICD_IROUTER36    | 64 | 0        | rw | Interrupt Routing 36       |
| GICD_IROUTER37    | 64 | 0        | rw | Interrupt Routing 37       |
| GICD_IROUTER38    | 64 | 0        | rw | Interrupt Routing 38       |
| GICD_IROUTER39    | 64 | 0        | rw | Interrupt Routing 39       |
| GICD_IROUTER40    | 64 | 0        | rw | Interrupt Routing 40       |
| GICD_IROUTER41    | 64 | 0        | rw | Interrupt Routing 41       |
| GICD_IROUTER42    | 64 | 0        | rw | Interrupt Routing 42       |
| GICD_IROUTER43    | 64 | 0        | rw | Interrupt Routing 43       |
| GICD_IROUTER44    | 64 | 0        | rw | Interrupt Routing 44       |
| GICD_IROUTER45    | 64 | 0        | rw | Interrupt Routing 45       |
| GICD_IROUTER46    | 64 | 0        | rw | Interrupt Routing 46       |
| GICD_IROUTER47    | 64 | 0        | rw | Interrupt Routing 47       |

|                 |    |     |    |                         |
|-----------------|----|-----|----|-------------------------|
| GICD_IROUTER48  | 64 | 0   | rw | Interrupt Routing 48    |
| GICD_IROUTER49  | 64 | 0   | rw | Interrupt Routing 49    |
| GICD_IROUTER50  | 64 | 0   | rw | Interrupt Routing 50    |
| GICD_IROUTER51  | 64 | 0   | rw | Interrupt Routing 51    |
| GICD_IROUTER52  | 64 | 0   | rw | Interrupt Routing 52    |
| GICD_IROUTER53  | 64 | 0   | rw | Interrupt Routing 53    |
| GICD_IROUTER54  | 64 | 0   | rw | Interrupt Routing 54    |
| GICD_IROUTER55  | 64 | 0   | rw | Interrupt Routing 55    |
| GICD_IROUTER56  | 64 | 0   | rw | Interrupt Routing 56    |
| GICD_IROUTER57  | 64 | 0   | rw | Interrupt Routing 57    |
| GICD_IROUTER58  | 64 | 0   | rw | Interrupt Routing 58    |
| GICD_IROUTER59  | 64 | 0   | rw | Interrupt Routing 59    |
| GICD_IROUTER60  | 64 | 0   | rw | Interrupt Routing 60    |
| GICD_IROUTER61  | 64 | 0   | rw | Interrupt Routing 61    |
| GICD_IROUTER62  | 64 | 0   | rw | Interrupt Routing 62    |
| GICD_IROUTER63  | 64 | 0   | rw | Interrupt Routing 63    |
| GICD_IROUTER64  | 64 | 0   | rw | Interrupt Routing 64    |
| GICD_IROUTER65  | 64 | 0   | rw | Interrupt Routing 65    |
| GICD_IROUTER66  | 64 | 0   | rw | Interrupt Routing 66    |
| GICD_IROUTER67  | 64 | 0   | rw | Interrupt Routing 67    |
| GICD_IROUTER68  | 64 | 0   | rw | Interrupt Routing 68    |
| GICD_IROUTER69  | 64 | 0   | rw | Interrupt Routing 69    |
| GICD_IROUTER70  | 64 | 0   | rw | Interrupt Routing 70    |
| GICD_IROUTER71  | 64 | 0   | rw | Interrupt Routing 71    |
| GICD_IROUTER72  | 64 | 0   | rw | Interrupt Routing 72    |
| GICD_IROUTER73  | 64 | 0   | rw | Interrupt Routing 73    |
| GICD_IROUTER74  | 64 | 0   | rw | Interrupt Routing 74    |
| GICD_IROUTER75  | 64 | 0   | rw | Interrupt Routing 75    |
| GICD_IROUTER76  | 64 | 0   | rw | Interrupt Routing 76    |
| GICD_IROUTER77  | 64 | 0   | rw | Interrupt Routing 77    |
| GICD_IROUTER78  | 64 | 0   | rw | Interrupt Routing 78    |
| GICD_IROUTER79  | 64 | 0   | rw | Interrupt Routing 79    |
| GICD_IROUTER80  | 64 | 0   | rw | Interrupt Routing 80    |
| GICD_IROUTER81  | 64 | 0   | rw | Interrupt Routing 81    |
| GICD_IROUTER82  | 64 | 0   | rw | Interrupt Routing 82    |
| GICD_IROUTER83  | 64 | 0   | rw | Interrupt Routing 83    |
| GICD_IROUTER84  | 64 | 0   | rw | Interrupt Routing 84    |
| GICD_IROUTER85  | 64 | 0   | rw | Interrupt Routing 85    |
| GICD_IROUTER86  | 64 | 0   | rw | Interrupt Routing 86    |
| GICD_IROUTER87  | 64 | 0   | rw | Interrupt Routing 87    |
| GICD_IROUTER88  | 64 | 0   | rw | Interrupt Routing 88    |
| GICD_IROUTER89  | 64 | 0   | rw | Interrupt Routing 89    |
| GICD_IROUTER90  | 64 | 0   | rw | Interrupt Routing 90    |
| GICD_IROUTER91  | 64 | 0   | rw | Interrupt Routing 91    |
| GICD_IROUTER92  | 64 | 0   | rw | Interrupt Routing 92    |
| GICD_IROUTER93  | 64 | 0   | rw | Interrupt Routing 93    |
| GICD_IROUTER94  | 64 | 0   | rw | Interrupt Routing 94    |
| GICD_IROUTER95  | 64 | 0   | rw | Interrupt Routing 95    |
| GICD_ISACTIVER0 | 32 | 0   | rw | Interrupt Set-Active 0  |
| GICD_ISACTIVER1 | 32 | 0   | rw | Interrupt Set-Active 1  |
| GICD_ISACTIVER2 | 32 | 0   | rw | Interrupt Set-Active 2  |
| GICD_ISENABLER0 | 32 | fff | rw | Interrupt Set-Enable 0  |
| GICD_ISENABLER1 | 32 | 0   | rw | Interrupt Set-Enable 1  |
| GICD_ISENABLER2 | 32 | 0   | rw | Interrupt Set-Enable 2  |
| GICD_ISPENDR0   | 32 | 0   | rw | Interrupt Set-Pending 0 |
| GICD_ISPENDR1   | 32 | 0   | rw | Interrupt Set-Pending 1 |

|                |    |        |    |                                       |
|----------------|----|--------|----|---------------------------------------|
| GICD_ISPENDR2  | 32 | 0      | rw | Interrupt Set-Pending 2               |
| GICD_NSACR0    | 32 | 0      | rw | Interrupt Non-secure Access Control 0 |
| GICD_NSACR1    | 32 | 0      | rw | Interrupt Non-secure Access Control 1 |
| GICD_NSACR2    | 32 | 0      | rw | Interrupt Non-secure Access Control 2 |
| GICD_NSACR3    | 32 | 0      | rw | Interrupt Non-secure Access Control 3 |
| GICD_NSACR4    | 32 | 0      | rw | Interrupt Non-secure Access Control 4 |
| GICD_NSACR5    | 32 | 0      | rw | Interrupt Non-secure Access Control 5 |
| GICD_PIDR0     | 32 | 92     | r- | Peripheral ID 0                       |
| GICD_PIDR1     | 32 | b4     | r- | Peripheral ID 1                       |
| GICD_PIDR2     | 32 | 3b     | r- | Peripheral ID 2                       |
| GICD_PIDR3     | 32 | 0      | r- | Peripheral ID 3                       |
| GICD_PIDR4     | 32 | 44     | r- | Peripheral ID 4                       |
| GICD_PIDR5     | 32 | 0      | r- | Peripheral ID 5                       |
| GICD_PIDR6     | 32 | 0      | r- | Peripheral ID 6                       |
| GICD_PIDR7     | 32 | 0      | r- | Peripheral ID 7                       |
| GICD_SETSPINSR | 32 | 0      | -w | Set SPI                               |
| GICD_SETSPISR  | 32 | 0      | -w | Set SPI, Secure                       |
| GICD_SPISR0    | 32 | 0      | r- | SPI Status 0                          |
| GICD_SPISR1    | 32 | 0      | r- | SPI Status 1                          |
| GICD_STATUSR   | 32 | 0      | rw | Distributor Status                    |
| GICD_TYPER     | 32 | 7b0402 | r- | Interrupt Controller Type             |

Table 13.9: Registers at level 3, type:THREAD group:MPCore\_distributor

### 13.3.10 MPCore\_physical\_redistributor

Registers at level:3, type:THREAD group:MPCore\_physical\_redistributor

| Name             | Bits | Initial-Hex | RW | Description                              |
|------------------|------|-------------|----|------------------------------------------|
| GICR_CIDR0       | 32   | d           | r- | Redistributor Component ID 0             |
| GICR_CIDR1       | 32   | f0          | r- | Redistributor Component ID 1             |
| GICR_CIDR2       | 32   | 5           | r- | Redistributor Component ID 2             |
| GICR_CIDR3       | 32   | b1          | r- | Redistributor Component ID 3             |
| GICR_CLRLPIR     | 64   | 0           | -w | Clear LPI Pending                        |
| GICR_CTLR        | 32   | 0           | rw | Redistributor Control                    |
| GICR_ICACTIVER0  | 32   | 0           | rw | Interrupt Clear-Active 0                 |
| GICR_ICENABLER0  | 32   | ffff        | rw | Interrupt Clear-Enable 0                 |
| GICR_ICFGR0      | 32   | aaaaaaaa    | rw | Interrupt Configuration 0                |
| GICR_ICFGR1      | 32   | 0           | rw | Interrupt Configuration 1                |
| GICR_ICPENDR0    | 32   | 0           | rw | Interrupt Clear-Pending 0                |
| GICR_IGROUPR0    | 32   | 0           | rw | Interrupt Group 0                        |
| GICR_IGRPMODR0   | 32   | 0           | rw | Interrupt Group Modifier 0               |
| GICR_IIDR        | 32   | 43b         | r- | Redistributor Implementer Identification |
| GICR_INVALLR     | 64   | 0           | -w | Redistributor Invalidate All             |
| GICR_INVLPIR     | 64   | 0           | -w | Redistributor Invalidate LPI             |
| GICR_IPRIORITYR0 | 32   | 0           | rw | Interrupt Priority 0                     |
| GICR_IPRIORITYR1 | 32   | 0           | rw | Interrupt Priority 1                     |
| GICR_IPRIORITYR2 | 32   | 0           | rw | Interrupt Priority 2                     |
| GICR_IPRIORITYR3 | 32   | 0           | rw | Interrupt Priority 3                     |
| GICR_IPRIORITYR4 | 32   | 0           | rw | Interrupt Priority 4                     |
| GICR_IPRIORITYR5 | 32   | 0           | rw | Interrupt Priority 5                     |
| GICR_IPRIORITYR6 | 32   | 0           | rw | Interrupt Priority 6                     |
| GICR_IPRIORITYR7 | 32   | 0           | rw | Interrupt Priority 7                     |
| GICR_ISACTIVER0  | 32   | 0           | rw | Interrupt Set-Active 0                   |
| GICR_ISENABLER0  | 32   | fff         | rw | Interrupt Set-Enable 0                   |

|                |    |    |    |                                              |
|----------------|----|----|----|----------------------------------------------|
| GICR.ISPENDR0  | 32 | 0  | rw | Interrupt Set-Pending 0                      |
| GICR.NSACR     | 32 | 0  | rw | Interrupt Non-secure Access Control          |
| GICR.PENDBASER | 64 | 0  | rw | Redistributor LPI Pending Table Base Address |
| GICR.PIDR0     | 32 | 93 | r- | Redistributor Peripheral ID 0                |
| GICR.PIDR1     | 32 | b4 | r- | Redistributor Peripheral ID 1                |
| GICR.PIDR2     | 32 | 3b | r- | Redistributor Peripheral ID 2                |
| GICR.PIDR3     | 32 | 0  | r- | Redistributor Peripheral ID 3                |
| GICR.PIDR4     | 32 | 44 | r- | Redistributor Peripheral ID 4                |
| GICR.PIDR5     | 32 | 0  | r- | Redistributor Peripheral ID 5                |
| GICR.PIDR6     | 32 | 0  | r- | Redistributor Peripheral ID 6                |
| GICR.PIDR7     | 32 | 0  | r- | Redistributor Peripheral ID 7                |
| GICR.PROPBASER | 64 | 0  | rw | Redistributor Properties Base Address        |
| GICR.SETLPIR   | 64 | 0  | -w | Set LPI Pending                              |
| GICR.STATUSR   | 32 | 0  | rw | Redistributor Status                         |
| GICR.SYNCR     | 32 | 0  | r- | Redistributor Synchronize                    |
| GICR.TYPER     | 64 | 9  | r- | Redistributor Type                           |
| GICR.WAKER     | 32 | 6  | rw | Redistributor Wake                           |

Table 13.10: Registers at level 3, type:THREAD group:MPCore\_physical\_redistributor

### 13.3.11 MPCore\_processor\_interface

Registers at level:3, type:THREAD group:MPCore\_processor\_interface

| Name         | Bits | Initial-Hex | RW | Description                                |
|--------------|------|-------------|----|--------------------------------------------|
| GICC_ABPR    | 32   | 3           | rw | Aliased Binary Point                       |
| GICC_AEOIR   | 32   | 0           | -w | Aliased End of Interrupt                   |
| GICC_AHPIR   | 32   | 3ff         | r- | Aliased Highest Priority Pending Interrupt |
| GICC_AIAR    | 32   | 3ff         | r- | Aliased Interrupt Acknowledge              |
| GICC_APR0    | 32   | 0           | rw | Active Priorities 0                        |
| GICC_BPR     | 32   | 2           | rw | Binary Point                               |
| GICC_CTLR    | 32   | 0           | rw | CPU Interface Control                      |
| GICC_DIR     | 32   | 0           | -w | Deactivate Interrupt                       |
| GICC_EOIR    | 32   | 0           | -w | End of Interrupt                           |
| GICC_HPIR    | 32   | 3ff         | r- | Highest Priority Pending Interrupt         |
| GICC_IAR     | 32   | 3ff         | r- | Interrupt Acknowledge                      |
| GICC_IIDR    | 32   | 4043b       | r- | CPU Interface ID                           |
| GICC_NSAPR0  | 32   | 0           | rw | Non-secure Active Priorities 0             |
| GICC_PMR     | 32   | 0           | rw | Interrupt Priority Mask                    |
| GICC_RPR     | 32   | ff          | r- | Running Priority                           |
| GICC_STATUSR | 32   | 0           | rw | CPU Interface Status                       |

Table 13.11: Registers at level 3, type:THREAD group:MPCore\_processor\_interface

### 13.3.12 MPCore\_virtual\_interface\_control

Registers at level:3, type:THREAD group:MPCore\_virtual\_interface\_control

| Name       | Bits | Initial-Hex | RW | Description                  |
|------------|------|-------------|----|------------------------------|
| GICH_APR0  | 32   | 0           | rw | Active Priorities 0          |
| GICH_EISR0 | 32   | 0           | r- | End of Interrupt Status 0    |
| GICH_ELSR0 | 32   | f           | r- | Empty List Register Status 0 |
| GICH_HCR   | 32   | 0           | rw | Hypervisor Control           |
| GICH_LR0   | 32   | 0           | rw | List 0                       |
| GICH_LR1   | 32   | 0           | rw | List 1                       |

|           |    |          |    |                              |
|-----------|----|----------|----|------------------------------|
| GICH_LR2  | 32 | 0        | rw | List 2                       |
| GICH_LR3  | 32 | 0        | rw | List 3                       |
| GICH_MISR | 32 | 0        | r- | Maintenance Interrupt Status |
| GICH_VMCR | 32 | 4c0000   | rw | Virtual Machine Control      |
| GICH_VTR  | 32 | 90000003 | r- | VGIC Type                    |

Table 13.12: Registers at level 3, type:THREAD group:MPCore\_virtual\_interface\_control

### 13.3.13 MPCore\_virtual\_processor\_interface

Registers at level:3, type:THREAD group:MPCore\_virtual\_processor\_interface

| Name            | Bits | Initial-Hex | RW | Description                                   |
|-----------------|------|-------------|----|-----------------------------------------------|
| GICV_ABPR       | 32   | 3           | rw | VM Aliased Binary Point                       |
| GICV_AEOIR      | 32   | 0           | -w | VM Aliased End of Interrupt                   |
| GICV_AHPPIR     | 32   | 3ff         | r- | VM Aliased Highest Priority Pending Interrupt |
| GICV_AIAR       | 32   | 3ff         | r- | VM Aliased Interrupt Acknowledge              |
| GICV_APR0       | 32   | 0           | rw | VM Active Priorities 0                        |
| GICV_BPR        | 32   | 2           | rw | VM Binary Point                               |
| GICV_CTLR       | 32   | 0           | rw | Virtual Machine Control                       |
| GICV_DIR        | 32   | 0           | -w | VM Deactivate Interrupt                       |
| GICV_EOIR       | 32   | 0           | -w | VM End of Interrupt                           |
| GICV_HPPIR      | 32   | 3ff         | r- | VM Highest Priority Pending Interrupt         |
| GICV_IAR        | 32   | 3ff         | r- | VM Interrupt Acknowledge                      |
| GICV_IIDR       | 32   | 4043b       | r- | VM CPU Interface ID                           |
| GICV_PMR        | 32   | 0           | rw | VM Priority Mask                              |
| GICV_RPR        | 32   | ff          | r- | VM Running Priority                           |
| GICV_STATUSR    | 32   | 0           | rw | VM CPU Interface Status                       |
| ICV_APR0_EL1    | 32   | 0           | rw | VM Group 0 Active Priorities 0                |
| ICV_APIR0_EL1   | 32   | 0           | rw | VM Group 1 Active Priorities 0                |
| ICV_BPR0_EL1    | 32   | 2           | rw | VM Group 0 Binary Point                       |
| ICV_BPR1_EL1    | 32   | 3           | rw | VM Group 1 Binary Point                       |
| ICV_CTLR_EL1    | 32   | 400         | rw | Virtual Machine Control                       |
| ICV_DIR_EL1     | 32   | 0           | -w | VM Deactivate Interrupt                       |
| ICV_EOIR0_EL1   | 32   | 0           | -w | VM Group 0 End of Interrupt                   |
| ICV_EOIR1_EL1   | 32   | 0           | -w | VM Group 1 End of Interrupt                   |
| ICV_HPPIR0_EL1  | 32   | 3ff         | r- | VM Group 0 Highest Priority Pending Interrupt |
| ICV_HPPIR1_EL1  | 32   | 3ff         | r- | VM Group 1 Highest Priority Pending Interrupt |
| ICV_IAR0_EL1    | 32   | 3ff         | r- | VM Group 0 Interrupt Acknowledge              |
| ICV_IAR1_EL1    | 32   | 3ff         | r- | VM Group 1 Interrupt Acknowledge              |
| ICV_IGRPEN0_EL1 | 32   | 0           | rw | VM Group 0 Interrupt Enable                   |
| ICV_IGRPEN1_EL1 | 32   | 0           | rw | VM Group 1 Interrupt Enable                   |
| ICV_PMR_EL1     | 32   | 0           | rw | VM Priority Mask                              |
| ICV_RPR_EL1     | 32   | ff          | r- | VM Running Priority                           |

Table 13.13: Registers at level 3, type:THREAD group:MPCore\_virtual\_processor\_interface

### 13.3.14 MPCore\_ITS

Registers at level:3, type:THREAD group:MPCore\_ITS

| Name        | Bits | Initial-Hex | RW | Description                        |
|-------------|------|-------------|----|------------------------------------|
| GITS_BASER0 | 64   | 0           | rw | ITS Translation Table Descriptor 0 |
| GITS_BASER1 | 64   | 0           | rw | ITS Translation Table Descriptor 1 |

|              |    |          |    |                                    |
|--------------|----|----------|----|------------------------------------|
| GITS.BASER2  | 64 | 0        | rw | ITS Translation Table Descriptor 2 |
| GITS.BASER3  | 64 | 0        | rw | ITS Translation Table Descriptor 3 |
| GITS.BASER4  | 64 | 0        | rw | ITS Translation Table Descriptor 4 |
| GITS.BASER5  | 64 | 0        | rw | ITS Translation Table Descriptor 5 |
| GITS.BASER6  | 64 | 0        | rw | ITS Translation Table Descriptor 6 |
| GITS.BASER7  | 64 | 0        | rw | ITS Translation Table Descriptor 7 |
| GITS.CBASER  | 64 | 0        | rw | ITS Command Queue Descriptor       |
| GITS.CREADR  | 64 | 0        | rw | ITS Read                           |
| GITS.CTLR    | 32 | 80000000 | rw | ITS Control                        |
| GITS.CWRITER | 64 | 0        | rw | ITS Write                          |
| GITS.IIDR    | 32 | 43b      | r- | ITS Identification                 |
| GITS.TYPER   | 64 | 9ef79    | r- | ITS Type                           |

Table 13.14: Registers at level 3, type:THREAD group:MPCore ITS