



Pairing instructions - New*

Verification	Topic	Category	Child Topic	Related P...
Empty	Connection	User Guide	Pair + 3	Neo60... + 2

*This guide is for 65% and 60% layout keyboards

If you've tried all of the instructions but still didn't get it to work, consider:

1. if you are pressing the correct keys
2. consider using a different USB port, preferably the back of your PC and skip USB hubs/front panel of PC at all cost
3. remove all the other USB devices if possible until the pairing is completed

Combination Keys	Tap	Hold for 3 Seconds
FN + Tab	Switch to wired mode	N/A
FN + Q	Switch to Bluetooth device 1	Re-pair Bluetooth device 1
FN + W	Switch to Bluetooth device 2	Re-pair Bluetooth device 2
FN + E	Switch to Bluetooth device 3	Re-pair Bluetooth device 3
FN + R	Switch to 2.4G mode	Re-pair 2.4G device

BT pairing method

- Step 1 - Make sure the keyboard is either connected to a power source or that the battery switch is turned to the ON position.
- Step 2 - Tap FN+Q / FN+W / FN+E to switch the keyboard to the Bluetooth mode. If it's never paired before, the indicator under the respective key will flash rapidly, indicating the keyboard is ready to pair.
- Step 3 - Now, you should see the keyboard appear in your PC's Bluetooth settings. Click "Connect" to complete the pairing process.
- Step 4 - The indicator under Q/W/E should stop flashing now to indicate that the pairing process is finished. You can try typing to test.
- If you want to connect to a new device, press and hold FN+Q / FN+W / FN+E for 3 seconds to enter pairing mode again.

2.4ghz pairing method

- Step 1 - Make sure the keyboard is either connected to a power source or that the battery switch is turned to the ON position.

Unplug the USB dongle if you've already plugged it in.

- Step 2 - Tap FN+R to switch the keyboard to 2.4G mode. If it's never paired before, the indicator under 4 will flash rapidly, indicating the keyboard is ready to pair.
- Step 3 - Plug the 2.4G dongle into your PC. **Ensure your keyboard is within 20 cm (about 8 inches) of the dongle.** Avoid plugging it into a port next to another dongle if one is already plugged in.
- Step 4 - The indicator under R should stop flashing now to indicate that the pairing process is finished. You can try typing to test.
- If you want to connect to a new device, press and hold FN+R for 3 seconds to enter pairing mode again.

Note: The white indicator flashes quickly during pairing and slowly when reconnecting.

If pairing isn't successful within 60 seconds or reconnection fails within 20 seconds, the keyboard will revert to sleep mode.