

### PROJECT DESCRIPTION<sup>1</sup>

In this project, you are required to generate a network model for a wireless sensor network and calculate the network's lifetime.

It is recommended to use Matlab for the required simulations. However, it is not mandatory. Any other network simulator or programming tool can be used.

The wireless sensor network under study is composed of homogeneous sensor nodes that are deployed in the area of interest. Sensors are randomly distributed in the deployment area. It should be noted also that sensor nodes need to be located close to each other to ensure that they always have correlated data.

The sink node is assumed to be static and located far away from the sensors field. Although it may be more energy effective that the sink is located in a nearby location to minimize the communication distances, but in some cases this may be impractical. In some scenarios, the sink may be a mobile one, but this project is targeting static networks in which the sensor nodes, as well as the sink are static.

#### A. Assumptions

In the model under study, several basic assumptions are considered:

- All the sensors are homogeneous and energy constrained. This imposes the challenge of lifetime elongation subject to this constrained energy.
- All the sensors are sensing the environment at a fixed rate, and thus they all always have data to send at predetermined time instants.
- All the sensors can transmit with enough power to reach the sink if needed. This assumption becomes more valid for small sized networks such as the network example under study.
- The sensors can use power control to vary the amount of transmit power. This allows the sensor nodes to use the minimum amount of energy to ensure that the required message reaches its destination.
- Each sensor has the computational power to perform different signal processing functions. This enables any sensor to be selected for tasks that require high computational power.
- The sensors have a method to be aware of their position after deployment. This can be guaranteed via many methods. Sensor nodes may be equipped with a position finding system (e.g. GPS). Signal strength measurements may be also used to have knowledge about locations.

#### B. Energy Consumption Model

A sensor node uses its available energy in order to carry out three main functions:

- Acquisition: The energy consumed to carry out the acquisition is generally negligible.
- Communication: This consumes more energy than any other task. This covers the communication in terms of transmission and reception.
- Data processing: The energy consumed for the calculation operations is very low as compared to the communication energy. This processing may be data aggregation, diffusion, packetization and/or coding.

<sup>1</sup>The problem described in this project, as well as the energy and radio models are adopted from:

**Samy S. Soliman**, "Hierarchically Clustered Wireless Sensor Networks: Lifetime Optimization Techniques," ISBN 978-384-840-321-9, LAP LAMBERT Academic Publishing, Mar. 2012.

### C. Transceiver Radio Energy Model

A simplistic radio model is considered here. Although there may be more realistic and complex models, yet this model is still used in the literature due to its simplicity.

The model assumes that for transmission, the radio dissipates  $E_{elec}$ , which represents the energy dissipated in the electronic circuitry of the transceiver block as well as other electronic circuitry, to run the transmitter circuitry and  $E_{amp}$ , which is the energy used by the transmit amplifier to provide the signal with power gain in order to achieve an acceptable signal-to-noise ratio. For reception, the radio dissipates only  $E_{elec}$  to run the receiver circuitry.

### D. Channel Propagation Model

In a wireless channel, the electromagnetic wave propagation can be modeled as falling off as a power law function of the distance between the transmitter and receiver. So, generally the received power decreases as the distance between the transmitter and receiver increases.

In this project, both the free space model and the multi-path fading model are used, depending on the distance between the transmitter and receiver. For short distance communications,  $d \leq d_0$ , the free space model, for which the path loss factor is equal to 2, is used. For long distance communications,  $d > d_0$ , a fading model with path loss factor equals to 4 is used.

To transmit a “ $k$ ” bits message over a distance  $d$ , the transmitter consumes

$$E_{tx-short} = k E_{elec} + k \varepsilon_{amp-short} d^2, \text{ for short distances}$$

$$E_{tx-long} = k E_{elec} + k \varepsilon_{amp-long} d^4, \text{ for long distances}$$

where  $\varepsilon_{amp-short}$  and  $\varepsilon_{amp-long}$  are the amplifier gains at the transmitter for short and long distance communications, respectively. To receive a “ $k$ ” bits message, the receiver consumes

$$E_{rx} = k E_{elec}.$$

Network and system parameters are summarized in Table I.

### REQUIRED

- Part A Generate a WSN that consists of  $N = 100$  identical sensor nodes, randomly distributed in a network area  $A = 100m \times 100m$ .  
You may need to use the same network realization of Project 1.
- Part B Consider the sink is located at the network center. Assume that all the sensor nodes start with an initial energy of 2 joules. Assume that both direct transmission and dual-hop transmission are used, and that  $d_0 = \sqrt{\frac{\epsilon_{\text{amp-short}}}{\epsilon_{\text{amp-long}}}}$ .  
Define a cycle as the duration from sensing the data by the sensor till it reaches the sink.  
For every  $C$  cycles, 5% of the sensor nodes are elected as cluster heads (CH) and clusters are formed such that each sensor node sends its data to the nearest CH, and each CH sends the aggregated data to the sink. Note that CH consume  $E_{agg}$  to aggregate the received packets into one data packet of 500 bytes. After  $C$  cycles, another 5% of the sensor nodes are elected as new cluster heads.  
**Write** an .m file to implement the function of the CH election. Your function should check that the elected nodes can receive, aggregate and transmit to the sink for at least  $C$  cycles.  
**Plot** a graph of the number of active (not dead) nodes versus the number of cycles, till the death of the last node, for  $C = 5$ .
- Part C On the graph obtained in Part B, **Identify** the network's lifetime,  $T_1$ , to the death of the first node.  
**Plot** the remaining energies of the  $N$  nodes after  $T_1$  cycles.

TABLE I: Network and System Parameters

Parameter	Symbol	Value
Network size	$M \times M$	100 m $\times$ 100 m
Number of sensors	$N$	100 sensors
Transmitter / Receiver electronics	$E_{elec}$	50 nJ/bit
TX Amplifier for short distance	$\epsilon_{\text{amp-short}}$	10 nJ/bit/m <sup>2</sup>
TX Amplifier for long distance	$\epsilon_{\text{amp-long}}$	0.0013 nJ/bit/m <sup>4</sup>
Aggregation energy	$E_{agg}$	50 nJ/bit/signal
Data packet size		500 Byte
Overhead packet size		125 Byte

- Part D It is required to find the number of cycles  $C$  that achieves the longest lifetime  $T_1$ . You need to choose the appropriate range and step of  $C$ .  
**Plot** the lifetime  $T_1$  versus  $C$ .  
**Find** the optimum  $C$  that maximizes  $T_1$ .  
**Plot** the remaining energies of the  $N$  nodes after  $T_1$  cycles for the case of optimum  $C$ .  
**Comment** on your results.
- Part E **Repeat** Parts B - D assuming that, instead of choosing 5% of the sensor nodes as cluster heads, five special nodes, of initial energy of 4 joules, are added to the network uniformly distributed along the circumference of a circle of radius  $R$  meters centered around the sink.  
For  $R = 25$ ;  
**Compare** the figures to those of Parts B - D.  
**Comment** on your results.  
**Note** that for this part,  $C$  is meaningless since there is no CH rotation.
- Part F For the network described in Part E, it is required to find the optimum  $R$  to locate the CHs.  
**Comment** on your findings.
- Part G **Compare** Part D and Part F to judge which solution is preferred. Your comparison should be assisted with graphs.  
You have to choose the appropriate points of comparison.

### **Deliverable**

Deliver, electronically, the following in a .zip file

- 1) **Source codes** (.m files) of all parts.
- 2) **Figures** in .fig format.  
Label the axes of each figure properly. Choose meaningful figure names.
- 3) **A complete .pdf report**, divided according to the required parts, with requirements labeled clearly.  
Make sure to write your observations and your comments of such observations.
- 4) A **5-minutes comprehensive recorded video** showing your functioning simulation and your comments on the results.

### **Instructions**

- This is a **team** project, teams can be composed of 2 – 3 students.
- All team members are accountable for all project parts.
- Team reports (including source codes, figures or comments) are not to be shared with others, neither before nor after submission. However, in-person discussions are encouraged.
- Any copied reports, either fully or partially, will receive 0 points. This applies to both the original and the copy.
- Late submission will be penalized at the rate of 15% for the first 2 days, another 15% for the next 2 days, after which no submissions will be considered.
- In submission, you have to submit **.m files** separately. In addition, the figure should be submitted in **.fig format** and should be **included** in the **.pdf report**. Reports should be comprehensive and readable on their own.
- The **.pdf report** is the main document to be evaluated, *i.e.* no credit is given for the source codes. However, source codes are to be checked against plagiarism.
- The grading criteria will be as follows:
  - **40%**: Completeness and correctness of every deliverable (as per the .pdf report).
  - **20%**: Clarity of figures, and proper labeling (as per the .pdf report).
  - **20%**: Report writing and organization.
  - **20%**: Comprehensiveness and clarity of content in the recorded video.