🔭 AiBridgeMCP Quick Setup Guide

Streamable HTTP Edition ~~v1.8.8 SSE Edition (deprecated)~~

Version: v2.0.1 | Date: 2026-02-28 | Protocol: Streamable HTTP (MCP 2025-03-26)

> ⚠️ **Important: Protocol Change Notice**
>
> The **SSE (Server-Sent Events)** protocol used in the previous version (v1.8.8) has been **officially announced for deprecation by Anthropic (Claude)** within the coming months.
>
> **Streamable HTTP** is now the **required protocol** for all MCP servers. Once SSE support is removed, MCP servers that rely solely on SSE will no longer be able to connect to Claude Desktop.
>
> **AiBridgeMCP v2 fully supports Streamable HTTP.** Please use the new connector: `aibridge-connector-v2.exe` .

Thank you for using **AiBridgeMCP**.
This tool acts as a bridge that allows Claude Desktop to communicate directly with your ESP32 device.

📦 What's Included

- **connector** folder
  - `aibridge-connector-v2.exe` — connection proxy program (**v2, new**)
  - This guide (PDF)

> ℹ️ This is a different file from the old `aibridge-connector.exe` (used for v1.8.8 SSE). Always use the **v2** file.

🚀 Setup Steps (3 Steps)

1. Place the Folder

Move the downloaded `connector` folder to a convenient location on your PC.

> Recommended location: `C:\AiBridgeMCP`
> ※ The Desktop or Downloads folder also works, but **do not move the folder after placing it** — the path in the config must stay the same.

2. Find Your ESP32's STA IP Address

Note the **STA IP address** assigned to your AiBridgeMCP (ESP32) on your Wi-Fi network.

> Example: `192.168.3.154`

3. Edit the Claude Desktop Configuration

This is the most important step — please follow carefully.

1. **Fully quit Claude Desktop.**
   Clicking the ✕ button alone may not close it completely. Use Task Manager to force-quit:

> **How to Force Quit via Task Manager**
> ① Press **Ctrl + Shift + Esc** simultaneously — Task Manager will open.
> ② Find **Claude** or **Claude Desktop** in the "Processes" list.
> ③ Right-click it → click "**End Task**".
> ④ Close Task Manager.

2. Open the Claude Desktop configuration folder:

> **How to Open the Folder**
> ① Press **Windows key (⊞) + R** at the same time.
> → A small "Run" dialog box will appear.
> ② Copy and paste the following into the input field, then press **Enter**:
> `%APPDATA%\Roaming\Claude`
> ③ The Claude configuration folder will open automatically.

3. Open `claude_desktop_config.json` in the folder using Notepad or any text editor.
4. Replace the entire contents with the following and save:

```
{
  "mcpServers": {
    "AiBridgeMCP": {
      "command": "C:\\AiBridgeMCP\\connector\\aibridge-connector-v2.exe",
      "args": [
        "your.ESP32.IP.address"
      ]
    }
  }
}
```

> ⚠️ **Important Notes**
> · Backslashes: Each `\` in the path must be written as `\\` (doubled).
> · IP address: Replace `"your.ESP32.IP.address"` with the actual IP, e.g. `"192.168.3.154"` .
> · Make sure the filename contains `-v2` : `aibridge-connector-v2.exe` .

✅ Verify the Connection

1. Launch Claude Desktop.
2. Click the **"+" icon** at the bottom-left of the chat input area.
3. Select "**Connectors >**" from the menu.
4. If **AiBridgeMCP** appears with a 🔵 **blue toggle switch (ON)**, the connection is successful!
5. To confirm it's working, ask Claude:

   `"Tell me the status of the ESP32."`

   If Claude responds with ESP32 details (IP address, CPU speed, free memory, etc.), everything is working perfectly.

🛠 Troubleshooting

- **AiBridgeMCP does not appear under "+" → "Connectors":** Check `claude_desktop_config.json` for typos (missing commas or brackets). Try restarting Claude Desktop.

- **Wrong file:** Confirm the filename is `aibridge-connector-v2.exe` (with `-v2`). The old `aibridge-connector.exe` is not compatible with v2.
- **Communication error:** Make sure your ESP32 and PC are connected to the **same Wi-Fi network** and that the IP address is correct.

⚖️ License / Copyright © 2026 Nishioka Sadahiko
This software is a dedicated connection proxy for AiBridgeMCP.