


Ooonana OS



Ooonana OS 0.9.9 field guide

What it is

Ooonana OS is a scratch-built Linux project with its own rootfs, boot flow, installer experiments, WSL export, and custom ooonana package manager.

Debian or Ubuntu are host build tools only. Alpine APKs are imported into Ooonana .pkg repos; the target OS installs Ooonana packages, not live Alpine APKs.

Editions

minimal: BusyBox-style rootfs, kernel, GRUB disk, installer ISO, WSL rootfs, command line AI.

full-i3: minimal plus i3, Xorg, Spotlight-style launcher, movable GTK apps, wallpaper, GUI installer, AI desktop app, and full WSL rootfs.

Package install

```
oonana update
oonana search nano
oonana show nano
oonana get nano --dry-run
oonana get nano
oonana files nano
oonana verify nano
oonana upgrade
oonana remove nano
oonana purge nano
oonana fix nano --reinstall
```

Cloud repo

Default cloud path is the GitLab Pages direct repository:

<https://oonana.gitlab.io/oonana-repo>

Run `oonana update && ooonana upgrade`. Metadata syncs first; package archives download only when install or upgrade needs them.

GitHub Releases remains a backup tarball repository path.

Installer

Full-i3 live ISO boots i3. Installer requires explicit target and dry-run preview.

Erase-disk mode offers optional swap; custom root, home, swap and EFI must share target disk.

USB live modes

Normal live mode mounts ISO and rootfs read-only. It uses a cleared temporary overlay on OOONANA_PERSIST when available on the same boot USB, with RAM fallback.

Persistent live mode accepts only an ext4 OOONANA_PERSIST partition on the same physical boot USB. Its full writable overlay saves files, settings, Wi-Fi, Bluetooth pairings, packages, and system changes.

GRUB boot UUID and same-parent checks protect unrelated media. Cloned UUIDs, unsafe paths, missing/unwritable persistence, and mismatched ISO base identity stop in recovery; no silent RAM fallback or automatic repair.

Other disks may be probed read-only. Live mode writes only to matching boot USB persistence. Only the confirmed installer target can be partitioned or formatted.

First boot

oonana setup --first-boot --gui can create user, set password, write network config, choose theme, set zram and disk-swap policy, add cloud repo, and mark setup complete.

WSL

Import full-i3 with scripts/install-wsl-distro.sh --distro Ooonana --tarball /var/tmp/oonana-os/release/oonana-full-i3-wsl-rootfs.tar.gz --force

Launch desktop with: wsl.exe -d Ooonana -u ooonana --exec start-oonana-i3

WSL GUI needs WSLg and Xephyr, or an X server with DISPLAY set. Nested mode keeps i3 panel and dock together in one window.

Update an imported distro with: oonana update && oonana upgrade

AI

Ooonana AI runs as ooonana ai ... or ooonana-ai. It supports cloud providers, offline Intel OpenVINO, ask/chat, tools, tasks, audit, history, status, and a native GUI.

The full-i3 desktop includes a ChatGPT-style AI workspace, Settings, Wi-Fi, Bluetooth, Packages, and Spotlight-style application launcher.

Desktop and hardware

The i3 desktop uses solid graphite and orange styling, rounded controls, a top music/window bar, and a centered opaque dock with running dots, click-to-restore apps, and right-click window actions.

Core 0.9.9 includes matching native icons, focus-neutral dock previews, responsive panel spacing, AI loading/RAM/storage indicators, and larger third-party controls that exclude hidden tabs and fullscreen-covered windows. Alt+F4 closes; Alt+F10 toggles fullscreen.

Ctrl+Shift+Esc opens native Task Manager with processes, performance, and available temperature and fan sensors. Unavailable hardware counters are labeled, not guessed. Live USB starts compressed zram swap. OpenVINO setup requires persistent USB storage or an installed system; RAM-only live storage cannot hold its runtime and models.

Ooonana OpenVINO Chat 0.2.1 has a browser GUI through an authenticated loopback bridge. Windows-only computer-control tools are unavailable on Linux.

Wi-Fi supports personal and enterprise profiles. NetworkManager, BlueZ, D-Bus, Intel Wi-Fi/Bluetooth firmware, Chromium, Python 3, sudo, su, and doas are included in full-i3.

Desktop and hardware (continued)

Installed password-login handoff passed diskless VM tests as UID 1000. Physical Xorg, wireless, audio, sensors and inference remain hardware checks; no sound was played. OpenVINO Linux dependencies use exact wheel hashes and a pinned Ubuntu image/APT snapshot. Signing private key stays local; public CI signing is deferred.

Bootable PDF

docs/oonana.pdf uses native RISC-V64 Linux 6.18.37 and BusyBox 1.37.0. Embedded VM boot, stable input, native/virtual Backspace, version and package sync passed. Actual Chromium PDF interaction remains a manual gate.

RV64 JavaScript emulator clock is scaled down 16x for CPU progress. Guest time is slower than real time. This terminal PDF is not the x86 i3 desktop.

docs/oonana-lite.pdf is a legacy artifact, not the current optimized runtime.

Persistence maintenance

bunana --shutdown and --restart request orderly init shutdown, stopping writers before sync, swapoff and unmount/remount read-only. No forced fallback. Live storage warnings are silent; no files are deleted automatically.

oonana-persistence backup requires explicit read-only ext4 mount, matching UUID and a new destination on another filesystem. Ownership, hardlinks and xattrs are verified. Active live overlay operations are refused.

oonana-persistence migrate requires matching verified backup and explicit data-only confirmation. It atomically switches to a fresh base, keeps home data, and preserves the complete old overlay. Accounts, packages and system configuration must be recreated; see docs/persistent-usb-safety.md.

Build proof markers

OOONANA_CLI_OK

OOONANA_BOOT_OK

OOONANA_INSTALL_OK

OOONANA_FULL_I3_OK

More detail lives in README.md, docs/oonana-ai.md, and docs/jarvis-agi-research.md.