OCS INTELLIGENCE · HARDWARE

Rig 1

ocs-intelligence-rig · Production inference for the public API

NETBIRD 100.75.123.203

ENDPOINT ai.opencodingsociety.com

AS OF 2026-10-20

8	64 GB	1,480 W	16 GB
GPUS · GTX 1070	TOTAL VRAM	MAX GPU POWER	SYSTEM RAM

GPUs, by worker

Numbered by nvidia-smi index, not physical position. Workers pin cards by UUID.

Worker A `qwen3.8:27b`

port 8081 · 4 cards

GPU		
GPU 1	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 07:00.0 · GPU-728d79b7
GPU 3	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 0B:00.0 · GPU-71f15481
GPU 5	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 0D:00.0 · GPU-fb4eb983
GPU 7	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 0F:00.0 · GPU-24899ea8

Worker B `gemma4:26b`

port 8082 · 4 cards

GPU		
GPU 0	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 03:00.0 · GPU-a25606af
GPU 2	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 0A:00.0 · GPU-4de8c392
GPU 4	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 0C:00.0 · GPU-2a70bbf9
GPU 6	8 GB	GTX 1070 · EVGA FTW Hybrid · 185 W · bus 0E:00.0 · GPU-bc07dc85

Every card reaches the board over a **PCIe Gen1 ×1 riser** (~250 MB/s). Cards in a worker pass activations to each other over these links. **No NVLink**

Platform

BOARD	**ASUS B250 Mining Expert** · BIOS 0403
CPU	**Intel Celeron G3930** · 2 cores · 2.9 GHz
MEMORY	**16 GB DDR4** · 2 × 8 GB Corsair Vengeance LPX · 2133 MT/s
STORAGE	**Samsung 860 EVO 250 GB** Boot + models. A second SSD (480 GB) is installed but not detected by the OS.
NETWORK	**Wired Ethernet** · onboard Intel I219-V · NetBird overlay
OS	**Ubuntu 24.04.4 LTS** · kernel 7.0.0-38
GPU STACK	**NVIDIA 580.178.04** (DKMS) · CUDA 12.6 · Pascal sm_61
INFERENCE	**llama.cpp** llama-server · layer split across cards

Power

1800 W brand unknown	board + CPU ▯▯▯▯▯	5 GPUs
1300 W Antec	▯▯▯	3 GPUs

Team-reported. Which card is on which supply isn't recorded. Each 1070 is limited to 185 W.

Services

:9000	**Orchestrator** routes by model, reached from EC2 over NetBird	●
:8081	**Worker A** llama-server, localhost only	●
:8082	**Worker B** llama-server, localhost only	●
:3000	**Open WebUI** Docker, the chat site at /	●
–	**Ollama** stopped, kept as fallback	○

Verified over NetBird SSH 2026-10-20 (`nvidia-smi`, `dmidecode`, `lsblk`). Power supplies are team-reported. Source of truth: **docs/architecture/hardware.md**