

Weather Stream OGC API: Collections Paths

This document includes only the `/collections/*` endpoints from the provided OpenAPI document.

/collections

GET Collections

Lists available collections.

Query parameters

Name	Type	Required	Notes
f	string	No	Output format. Default: <code>json</code> . Allowed: <code>json</code> , <code>html</code> , <code>jsonld</code>

Responses

Status	Meaning
200	Success
400	Invalid parameter
500	Server error

/collections/sensors

GET Get Sensors metadata

Returns metadata for the `sensors` collection.

Query parameters

Name	Type	Required	Notes
f	string	No	Output format. Default: <code>json</code> . Allowed: <code>json</code> , <code>html</code> , <code>jsonld</code>

Responses

Status	Meaning
200	Collection metadata
400	Invalid parameter
404	Not found
500	Server error

/collections/sensors/items

GET Get Sensors items

Returns items from the **sensors** collection.

Query parameters

Name	Type	Required	Notes
f	string	No	Default: json . Allowed: json , csv
bbox	number[]	No	4 or 6 numbers
properties	string[]	No	Allowed: sensor_id , sensor_name , available_variables , valid_start_datetime , valid_end_datetime
datetime	external ref	No	Datetime filter
sensor_id	string	No	Filter by sensor id
sensor_name	string	No	Filter by sensor name
available_variables	string	No	Filter by available variables
valid_start_datetime	string(date-time)	No	Filter by valid start datetime
valid_end_datetime	string(date-time)	No	Filter by valid end datetime

Responses

Status	Meaning
200	Features returned
400	Invalid parameter
404	Not found
500	Server error

POST Add item

Creates a new item

Request body

Content-Type	Meaning
application/geo+json	Add item to collection

To add an item to the collection, properties should contain:

Name	Type
Sensor_id	str
Sensor_name	str
available_variables	str (comma-separated list)
valid_start_datetime	str (date-time)
valid_end_datetime	str (date-time) or None

Responses

Status	Meaning
200	Features returned
201	Successful creation
400	Invalid parameter
500	Server error

/collections/sensors/items/{featureId}

GET Get Sensors item by id

Returns a single sensor item.

Path parameters

Name	Type	Required	Notes
featureId	string	Yes	Feature identifier

Query parameters

Name	Type	Required	Notes
f	string	No	Output format

Responses

Status	Meaning
200	Feature returned
400	Invalid parameter
404	Not found
500	Server error

Responses

Status	Meaning
200	Options response

/collections/sensors/locations

GET Get pre-defined locations of Sensor locations

Returns predefined locations for the **sensors** collection.

Query parameters

Name	Type	Required	Notes
bbox	external ref	No	bbox parameter
datetime	external ref	No	Datetime filter
f	string	No	Output format

Responses

Status	Meaning
200	Features returned
400	Invalid parameter
500	Server error

/collections/sensors/locations/{locId}

GET Retrieve coverage data by location

Returns coverage data for a specific location.

Path parameters

Name	Type	Required	Notes
locId	string	Yes	Location identifier

Query parameters

Name	Type	Required	Notes
datetime	external ref	No	Datetime filter. It can be range, this is the time of the forecast and will be decomposed to time (Forecast_reference_time) and step (forecast_period). The forecast with the lowest step value is returned for every datetime requested. A datetime between modeled times will be interpolated from the nearest available forecast. Intervals may be bounded or half-bounded (double-dots at start or end). A date-time: "2018-02-

Name	Type	Required	Notes
			12T23:20:50Z" A bounded interval: "2018-02-12T00:00:00Z/2018-03-18T12:31:12Z" Half-bounded intervals: "2018-02-12T00:00:00Z/.." or "../2018-03-18T12:31:12Z"
<code>parameter-name</code>	external ref	No	EDR parameter selector. Available names are those in the icechunk repo
<code>method</code>	external ref	No	interpolation method at the sensor location and requested time. Defaults to linear and will eventually support a method for bias corrected forecast.
<code>crs</code>	string	No	CRS for results
<code>f</code>	string	No	Output format

Responses

Status	Meaning
200	CoverageJSON response (<code>application/prs.coverage+json</code>)