Frontend

Deployed · owner dashboard

A React and Vite dashboard for seeing building conditions, reviewing service requests, and following repairs. The hosted site uses Supabase owner sign-in.

Views and navigation

View	What it shows
Overview	Controller status, building cards, open incidents, approvals, maintenance queue, and recent activity.
Activity	Timeline of detection, proposals, approval, service, verification, and connection events. Filter by building.
Sensor Data	Choose a building, inspect the latest reading and fan state, switch sensor charts, and review recent timestamped readings.
3D	Inspect the two models, click represented equipment, and view sensor or status information and the building's incident history. Settings switches between 3D and Normal.

Office and data-center cards

The office shows ambient light in ADC counts, temperature in °C and °F when available, and the controller-reported fan state. The data center shows flame sensor clear, alert detected, or brief activation, plus temperature and fan state. Both show the latest capture time or last known sample.

The LEDs and fans are represented for monitoring. No on/off buttons appear in the dashboard. A running fan is a controller report, and speed is unavailable. Ambient light remains relative and a flame signal is evidence for inspection.

Hosted proplink dashboard

Sensor history and evidence labels

FRONTEND

Condition	Owner-facing behavior
Fresh / stale / no data	Fresh readings are attributed to the current sample. Stale readings remain visible as last known. No upload shows awaiting data. The API error notice is separate from controller status.
Temperature estimate	Show °C and °F together. The room-based estimate is marked approximate. Use raw counts if calibration is absent or the estimate is beyond the supported range.
Office light	Plot ADC ratio over time and list raw counts. Surrounding illumination and shadows can affect the sensor.
Data-center flame/IR	Distinguish an active signal from an activation observed between reports. Keep the incident visible until verified.
Source and cadence	Sensor history identifies Hardware or Simulated. Dashboard state polls about every two seconds, with sensor history refreshing about every 2.5 seconds.

Example from the real board

In the verified Nov 8 snapshot, the office displayed 545 ADC counts and about 21.1 °C / 70.0 °F. The data center's flame input was clear and its temperature was about 22.5 °C / 72.5 °F. Both fans were reported running. These are examples from one stored sample.

The room estimates use a 71.7 °F reference and separate baseline counts for each sensor. History plots estimated temperatures in Celsius and the sample list shows both units.

Maintenance flow and demo

FRONTEND

01 Open a pending request, read the sensor evidence and proposed inspection, and approve or decline. An approval enables the next service step. A decline leaves the issue visible as unresolved.

02 Record technician contact, explicit acceptance and repair findings in order. Production labels are records of owner-entered events. The local demo labels contact and acceptance as simulations.

03 After findings are entered, verify office recovery with fresh readings in range or record a manual check. Use manual verification for data-center IR. Verified work closes the incident and updates the timeline.

Demo rehearsal

For a hardware-free walkthrough, run the local demo and use Demo controls to darken or restore office lighting, toggle the simulated IR input, or pause and resume the simulated controller. Keep the hardware source label visible when demonstrating the deployed system.

Rehearse owner sign-in, approval and decline, the service steps, and the stale/reconnect transition on the target browser. Production office low-light detection needs a measured threshold. Nemotron recommendations and Photon updates will enter the existing workflow after their adapters are implemented.

Repository and local demo instructions