



AUDIO NETWORK — SWITCH-BY-SWITCH PORT REFERENCE

22× Cisco Catalyst 1300 — every port, its VLAN, and its device — parsed directly from the Clearwing closeout configs

Organized by switch hostname (not by rack) — look up a switch directly by its management IP, which is the reliable identifier; physical labels/stickers on some units are wrong (see Hormel FOH/Booth note below). VLANs: V1 Mgmt (10.18.1.x) · V10 Dante Primary (10.18.10.x) · V11 Audio Control/WWB (10.18.11.x) · V12 Interdepartmental OSC (10.18.12.x) · V16 ClearCom HelixNet · V17 ClearCom AES67 · V24 Dante Secondary (10.18.24.x) · V52 Assisted-Listen Test · V151 Visionary Video (10.200.151.x).

Known label problem: the Hormel FOH pair is physically stickered ASW-1014/1015, but is actually programmed as ASW-1020/1021 (confirmed on-site 2026-07-06 by reading the management IP off the unit). The true ASW-1014/1015 config lives in the Hormel Booth. This reference is organized by the config's real hostname, which matches the mgmt IP — not the (possibly wrong) sticker.

New finding, not yet resolved: every switch's config banner claims location "Stephenson Theater," including switches confirmed elsewhere to be in Hormel (1014/1015/1017/1018/1019/1020) — almost certainly a copy-paste template left over from Clearwing's closeout paperwork, consistent with several other known data-entry errors in this same package, not a real location change. ASW-1021's banner separately claims "Location: Hardes," which also doesn't match its confirmed Hormel FOH role. Banner text is shown per switch below for completeness but should not be trusted over the confirmed venue assignments.

PRIMARY NETWORK — Dante Primary (V10) / Control (V11) / Interdept (V12) / Video (V151)

ASW-2001

C1300-24XS · mgmt 10.18.1.10 · STP priority 4096

Primary Core — Stephenson ER1 (10G aggregation, STP root) (config banner: "Rack: ER1-2"; extra: Stephenson Thater)

Port(s)	VLAN	Device / notes
te1	trunk (SFP+ 10G, allowed 1,10-12,52)	—
te2	trunk (SFP+ 10G, allowed 1,10-11)	—
te3	trunk (SFP+ 10G, allowed 1,10-11)	—
te4	trunk (SFP+ 10G, allowed 1,10-12,151)	—
te5	trunk (SFP+ 10G, allowed 1,10-12)	—
te6	trunk (SFP+ 10G, allowed 1,10-12)	—
te7	trunk (SFP+ 10G, allowed 1,10-12)	—
te8	trunk (SFP+ 10G, allowed 1,10-12)	—
te9	trunk (SFP+ 10G, allowed 1,10-12)	—
te10	trunk (SFP+ 10G, allowed 1,10-12)	—
te11	trunk (SFP+ 10G, allowed 1,10-12)	—
te12	trunk (SFP+ 10G, allowed 1,10-12)	—
te13	trunk (SFP+ 10G, allowed 1,10-11)	—
te14	trunk (SFP+ 10G, allowed 1,10-12)	—
te15	trunk (SFP+ 10G, allowed 1,10)	—
te16	trunk (SFP+ 10G, allowed 1,10-12)	—
te17	trunk (SFP+ 10G, allowed 1,10-12)	—
te18	trunk (SFP+ 10G, allowed 1,10,151)	—
te19	trunk (SFP+ 10G, allowed 1,11,52)	—
te20	trunk (SFP+ 10G, allowed 1,10-12)	—
te21	trunk (SFP+ 10G, allowed 1,10-12,151)	—
te22	trunk (SFP+ 10G, allowed 1,10-12)	—
te23	trunk (SFP+ 10G, allowed 1,10-12,151)	—
te24	trunk (SFP+ 10G, allowed 1,10-12,151)	—

ASW-1001

C1300-48FP-4X · mgmt 10.18.1.21 · STP priority 16384

Stephenson DSP/amps rack (ER1) — Dante Primary leg (extra: Rack ER1-2; Switch ASW-1001)

Port(s)	VLAN	Device / notes
1	V10	DSP-1001
2	V10	AMP-2001
3	V10	AMP-2002
4	V10	TS-1001
5	V10	AV16-1
6	V10	AV16-2
7	V10	AV16-3
8	V10	GPIO-1001
9-15	V10	—
16	V10	HUB-1001
17	V10	ALS-1001
18	V10	AV17-1
19	V10	AV17-2
20	V10	AV17-3
21-46	V10	—
47	trunk	—
48	trunk (native V10)	—
te3	trunk (SFP+ 10G, allowed 1,10)	—
te4	trunk (SFP+ 10G, allowed 1,10)	—

ASW-1005

C1300-48FP-4X · mgmt 10.18.1.25 · STP priority 8192

Building-wide video edge (VS decoders, cameras) (extra: Rack ER1-2; Switch ASW-1005)

Port(s)	VLAN	Device / notes
1	V151	AV13-9
2	V151	AV13-10
3	V151	AV13-12
4	V151	AV13-13
5	V151	AV13-1
6	V151	AV13-2
7	V151	AV13-3
8	V151	AV13-4
9	V151	AV07
10	V151	AV08
11	V151	AV09
12	V151	AV13-5
13	V151	AV13-7
14	V151	AV13-8
15	V151	AV13-8
16	V151	AV13-11
17	V151	AV14-1
18	V151	AV14-2
19	V151	AV13-14
20	V151	Dec-1020 AV13-15
21	V151	LOW LIGHT AV15-1
22	V151	HIGH REZ AV15-1
23	V151	PTZ VID AV15-1
24	V151	LOW LIGHT AV10-1
25	V151	HIGH REZ AV10-1
26	V151	PTZ VID AV10-1
27	V151	LOW LIGHT AV5-1
28	V151	HIGH REZ AV5-1
29	V151	PTZ VID AV5-1
30	V151	DEC - 2001
31	V151	DEC - 2002
32	V151	DEC-3001
33	V151	DEC-3002
34	V151	DEC-3003
35-37	V151	—
38	V151	IP VID PATCH 1
39	V151	IP VID PATCH 2
40	V151	IP VID PATCH 3
41	V151	IP VID PATCH 4
42	V151	IP VID PATCH 5
43	V151	IP VID PATCH 6
44	V151	IP VID PATCH 7
45	V151	IP VID PATCH 8
46	V151	IP VID PATCH 9
47	V151	IP VID PATCH 10

Port(s)	VLAN	Device / notes
48	trunk	CONFIG
te4	trunk (SFP+ 10G, allowed 1,10,151)	—

ASW-1006

C1300-48FP-4X · mgmt 10.18.1.26 · STP priority 32768 (default) · firmware 4.1.3.36

Lobby / FOH control — OLD FIRMWARE (v4.1.3.36) (extra: Rack ER1-2; Switch ASW-1006)

Port(s)	VLAN	Device / notes
1-20	V11	—
21	V11	Lobby-1st level-Left
22	V11	Lobby-1st level-Right
23	V11	Lobby-2nd level-Left
24	V11	Lobby-2nd level-Right
25-29	V11	—
30	V11	HR TV Global Cache IP to IR
31-44	V11	—
45-46	V52	—
47	V11	—
48	trunk	—
te4	trunk (SFP+ 10G, allowed 1,11,52)	—

ASW-1008

C1300-48FP-4X · mgmt 10.18.1.28 · STP priority 32768 (default)

Stephenson FOH (Rivage PM5 area) — primary (config banner: "Rack: Front of House")

Port(s)	VLAN	Device / notes
1-8	V10	—
9	V10	hearing assis-auri-dante
10-24	V10	—
25-28	trunk (native V10)	—
29-30	V10	—
31-33	V11	—
34	V11	Auri-Hearing-Assist-Charger
35	V11	—
36	V11	Hearing assist-auri-control
37-40	V11	—
41-42	V12	—
43	V52	—
44-46	V12	—
47	trunk (native V12)	Stephenson-AP-FOH
48	trunk	—
te3	trunk (SFP+ 10G, allowed 1,10-12)	—
te4	trunk (SFP+ 10G, allowed 1,10-12,52)	—

ASW-1010

C1300-24FP-4X · mgmt 10.18.1.30 · STP priority 32768 (default)

Stephenson Pit / Band rack — primary (config banner: "Rack: ERK2-1")

Port(s)	VLAN	Device / notes
1-11	V10	—
12-21	V11	—
22	V11	S-Pit Band Rack AP
23	V11	S-Pit Band Rack-ME-CTL
24	trunk	—
te4	trunk (SFP+ 10G, allowed 1,10-11)	—

ASW-1012

C1300-48FP-4X · mgmt 10.18.1.32 · STP priority 8192

RF rack (AD4Q/WLS receivers) — primary (config banner: "Rack: ERK4-1 (wireless)")

Port(s)	VLAN	Device / notes
1	V10	WLS-1001-Dante-Pri
2-24	V10	—
25	V10	WLS-1001-CTL
26	V10	WLS-1002-CTL
27	V10	WLS-1003-CTL
28	V10	WLS-1004-CTL
29-43	V10	—
44-45	V11	—
46-47	trunk (native V11)	—
48	trunk	—
te4	trunk (SFP+ 10G, allowed 1,10-11)	—

ASW-1014

C1300-48FP-4X · mgmt 10.18.1.34 · STP priority 16384

Hormel BOOTH — confirmed on-site 2026-07-06 (physical sticker correct here) (config banner: "Rack: Main Stage FOH")

Port(s)	VLAN	Device / notes
1-18	V10	—
19-36	V11	—
37-43	V12	—
44-46	V151	—
47	trunk (native V12)	—
48	trunk	—
te4	trunk (SFP+ 10G, allowed 1,10-12,151)	—

ASW-1018

C1300-24FP-4X · mgmt 10.18.1.38 · STP priority 32768 (default)

Hormel Band/Deck-ME rack — primary (config banner: "Rack: Main Stage Band")

Port(s)	VLAN	Device / notes
1	V10	—
2	V10	Hormel-ME-U-
3-11	V10	—
12-20	V11	—
21	V11	Hormel-ME-U-Monitor-control
22-23	trunk (native V11)	—
24	trunk	—
te4	trunk (SFP+ 10G, allowed 1,10-11)	—

ASW-1020

C1300-48FP-4X · mgmt 10.18.1.40 · STP priority 16384

Hormel FOH (mix position) — confirmed on-site 2026-07-06 (physical sticker here reads 1014, wrong) (config banner: "Rack: Main stage FOH"; extra: Primary)

Port(s)	VLAN	Device / notes
1-23	V10	—
24	V10	H-Shure Chargers
25	trunk (native V10)	—
26	trunk (native V10)	H-FOH-Qlab
27	trunk (native V10)	H-windows PC-RF
28	V11	H-windows PC-Nundo-CTL
29-30	V10	—
31-34	V11	—
35	V11	H-CL5 CTL
36	V11	H-Mac Studio-VST
37	V11	H-FOH-AP
38	V11	dave-tech-ctl
39-40	V11	—
41-44	V12	—
45	trunk (native V12)	—
46-48	trunk	—
te4	trunk (SFP+ 10G, allowed 1,10-12)	—

ASW-1021

C1300-24FP-4X · mgmt 10.18.1.41 · STP priority 16384

Hormel FOH — secondary/edge (pairs with 1020) (config banner: "Rack: FOH"; extra: Location: Hardes; ASW-1021)

Port(s)	VLAN	Device / notes
1-14	V10	—
15-22	V11	—
23-24	trunk	—
te4	trunk (SFP+ 10G, allowed 1,10-11)	—

SECONDARY NETWORK — Dante Secondary (V24)

ASW-2002

C1300-24XS · mgmt 10.18.1.11 · STP priority 4096

Secondary Core — Stephenson ER1 (10G aggregation) (config banner: "Rack: ER1-2")

Port(s)	VLAN	Device / notes
te1	trunk (SFP+ 10G, allowed 1,12,24)	—
te2	trunk (SFP+ 10G, allowed 1,24)	—
te3	trunk (SFP+ 10G, allowed 1,24)	—
te4	trunk (SFP+ 10G, allowed 1,12,24)	—
te5	trunk (SFP+ 10G, allowed 1,24)	—
te6	trunk (SFP+ 10G, allowed 1,24)	—
te7	trunk (SFP+ 10G, allowed 1,24)	—
te8	trunk (SFP+ 10G, allowed 1,24)	—
te9	trunk (SFP+ 10G, allowed 1,24)	—
te10	trunk (SFP+ 10G, allowed 1,24)	—
te11	trunk (SFP+ 10G, allowed 1,24)	—
te12	trunk (SFP+ 10G, allowed 1,24)	—
te13	trunk (SFP+ 10G, allowed 1,24)	—
te14	trunk (SFP+ 10G, allowed 1,24)	—
te15	trunk (SFP+ 10G, allowed 1,24)	—
te16	trunk (SFP+ 10G, allowed 1,24)	—
te17	trunk (SFP+ 10G, allowed 1,24)	—
te18	trunk (SFP+ 10G, allowed 1,24)	—
te19	trunk (SFP+ 10G, allowed 1,24)	—
te20	trunk (SFP+ 10G, allowed 1,24)	—
te21	trunk (SFP+ 10G, allowed 1,24)	—
te22	trunk (SFP+ 10G, allowed 1,24)	—
te23	trunk (SFP+ 10G, allowed 1,24)	—
te24	trunk (SFP+ 10G, allowed 1,12,24)	—

ASW-1002

C1300-48FP-4X · mgmt 10.18.1.22 · STP priority 16384

Stephenson DSP/amps rack (ER1) — Dante Secondary leg (mirrors 1001) (extra: Rack ER1-2; Switch ASW-1002)

Port(s)	VLAN	Device / notes
1	V24	DSP-1001
2	V24	AMP-2001
3-15	V24	—
16	V24	HUB-1001
17-37	V24	—
38	V24	Patch N01-0204
39	V24	Patch No1-0205
40	V24	Patch No1-0206
41	V24	Patch No1-0207
42	V24	Patch No1-0208
43	V24	Patch No1-0209
44	V24	Patch No1-0210
45	V24	Patch No1-0211
46	V24	Patch No1-0212
47	V24	Patch No1-0213
48	trunk	Config
te4	trunk (SFP+ 10G, allowed 1,24)	SFP 15 / ASW-2002

ASW-1009

C1300-48FP-4X · mgmt 10.18.1.29 · STP priority 16384

Stephenson FOH — secondary (pairs with 1008) (config banner: "Rack: Front of House")

Port(s)	VLAN	Device / notes
1-18	V24	—
19-36	V11	—
37-47	V12	—
48	trunk	—
te4	trunk (SFP+ 10G, allowed 1,11-12,24)	—

ASW-1011

C1300-24FP-4X · mgmt 10.18.1.31 · STP priority 32768 (default)

Stephenson Pit / Band rack — secondary (pairs with 1010) (config banner: "Rack: ERK2-1")

Port(s)	VLAN	Device / notes
1-23	V24	—
24	trunk	—
te4	trunk (SFP+ 10G, allowed 1,24)	—

ASW-1013

C1300-48FP-4X · mgmt 10.18.1.33 · STP priority 16384

RF rack — secondary (pairs with 1012) (config banner: "Rack: ER4-1"; extra: Stephenson Thater)

Port(s)	VLAN	Device / notes
1-30	V24	—
31-44	unassigned	—
45-48	trunk	—
te4	trunk (SFP+ 10G, allowed 1,24)	—

ASW-1015

C1300-48FP-4X · mgmt 10.18.1.35 · STP priority 16384

Hormel Booth — secondary (pairs with 1014) (config banner: "Rack: Main Stage FOH")

Port(s)	VLAN	Device / notes
1-5	V24	—
6	V24	CL5-Slot-1-Sec
7-24	V24	—
25-46	V12	—
47	trunk (native V12)	Uplink-H-USL-Secondary-sw
48	trunk	config
te4	trunk (SFP+ 10G, allowed 1,11-12,24)	—

ASW-1016

C1300-24FP-4X · mgmt 10.18.1.36 · STP priority 16384

Hormel Booth — secondary mix (banner confirms "Main Stage booth") (config banner: "Rack: Main Stage booth")

Port(s)	VLAN	Device / notes
1-10	V24	—
11-16	V11	—
17-20	V12	—
21-24	trunk	—
te4	trunk (SFP+ 10G, allowed 1,11-12,24)	—

ASW-1019

C1300-24FP-4X · mgmt 10.18.1.39 · STP priority 32768 (default)

Hormel Band/Deck-ME rack — secondary (pairs with 1018) (config banner: "Rack: Main Stage Band")

Port(s)	VLAN	Device / notes
1-11	V24	—
12-21	V11	—
22-23	trunk (native V11)	—
24	trunk	—
te4	trunk (SFP+ 10G, allowed 1,11,24)	—

COMMS NETWORK — ClearCom HelixNet (V16) / AES67 (V17)

ASW-1003

C1300-48FP-4X · mgmt 10.18.1.23 · STP priority 4096

Comms root — Arcadia Central Station (Com-1001) (extra: Rack ER1-2; Switch ASW-1003)

Port(s)	VLAN	Device / notes
1	V16	Com-1001 (Arcadia)
2	V17	AV19-2
3	V17	AV13-8
4	V17	AV13-5
5-11	V17	—
12	V16	AV1-1
13	V16	AV1-1
14	V16	AV1-1
15	V16	AV1-1
16	V16	AV1-2
17	V16	AV1-2
18	V16	AV1-2
19	V16	AV1-2
20	V16	AV2-1
21	V16	AV2-1
22	V16	AV2-1
23	V16	AV2-1
24	V16	AV2-2
25	V16	AV2-2
26	V16	AV2-2
27	V16	AV2-2
28	V16	AV3-1
29	V16	AV3-1
30	V16	AV3-1
31	V16	AV3-1
32	V16	AV4-1
33	V16	AV4-1
34	V16	AV4-1
35	V16	AV4-1
36	V16	AV5-1
37	V16	AV5-1
38	V16	AV5-1
39	V16	AV5-1
40	V16	AV5-3
41	V16	AV5-3
42	V16	AV5-3
43	V16	AV5-3
44	V16	AV6-1
45	V16	AV6-1
46	V16	AV6-1
47	V16	AV6-1
48	trunk	Config
te4	trunk (SFP+ 10G, allowed 1,16-17)	SFP 16 from ASW-2001

ASW-1004

C1300-48FP-4X · mgmt 10.18.1.24 · STP priority 16384

Comms — beltpack drops, HKB-1001/1002, Com Patch (extra: Rack ER1-2; Switch ASW-1004)

Port(s)	VLAN	Device / notes
1	V16	AV7-1
2	V16	AV7-2
3	V16	AV8-1
4	V16	AV8-1
5	V16	AV8-1
6	V16	AV8-1
7	V16	AV10-2
8	V16	AV10-2
9	V16	AV10-2
10	V16	AV10-2
11	V16	AV10-3
12	V16	AV11-1-HKB-1001
13	V16	AV11-1
14	V16	AV11-2
15	V16	AV11-2-HKB-1002
16	V16	AV12-1
17	V16	AV12-1
18	V16	AV18-1
19	V16	AV18-1
20-37	V16	—
38	V16	Com Patch 1
39	V16	Com Patch 2
40	V16	Com Patch 3
41	V16	Com Patch 4
42	V16	Com Patch 5
43	V16	Com Patch 6
44	V16	Com Patch 7
45	V16	Com Patch 8
46	V16	Com Patch 9
47	V16	Com Patch 10
48	trunk	Config
te3	trunk (SFP+ 10G, allowed 1,16-17)	—
te4	trunk (SFP+ 10G, allowed 1,16-17)	SFP17 from ASW-2001

ASW-1017

C1300-24FP-4X · mgmt 10.18.1.37 · STP priority 8192

Hormel Booth comms (HelixNet + AES67) (extra: Main stage booth; ASW-1017)

Port(s)	VLAN	Device / notes
1-16	V16	—
17-23	V17	—
24	trunk	—
te4	trunk (SFP+ 10G)	—