

# MPSoC-MPI WIKI

## Definition

A Message Passing Interface (MPI) uses an object model to distinguish the general function from the specific implementations. The invoking program sends a message and relies on the object to select and execute the appropriate code. Using an intermediate layer essentially falls into two categories: encapsulation and distribution. Objects should be able to invoke services on other objects without knowing or caring about how those services are implemented.

## FRONT-END Open Source Tools

### Verilator

SystemVerilog System Description Language Simulator

*A System Description Language Simulator (translator) is a computer program that translates computer code written in a Programming Language (the source language) into a Hardware Design Language (the target language). The compiler is primarily used for programs that translate source code from a high-level programming language to a low-level language to create an executable program.*

```
git clone http://git.veripool.org/git/verilator
```

```
cd verilator
autoconf
./configure
make
sudo make install

cd sim/verilog/regression/wb/vtor
source SIMULATE-IT

cd sim/verilog/regression/ahb3/vtor
source SIMULATE-IT
```

### Icarus Verilog

Verilog Hardware Description Language Simulator

*A Hardware Description Language Simulator uses mathematical models to replicate the behavior of an actual hardware device. Simulation software allows for modeling of circuit operation and is an invaluable analysis tool. Simulating a circuit's behavior before actually building it can greatly improve design efficiency*

*by making faulty designs known as such, and providing insight into the behavior of electronics circuit designs.*

```
git clone https://github.com/steveicarus/iverilog
```

```
cd iverilog
./configure
make
sh autoconf.sh
sudo make install

cd sim/verilog/regression/wb/iverilog
source SIMULATE-IT

cd sim/verilog/regression/ahb3/iverilog
source SIMULATE-IT
```

## **GHDL**

VHDL Hardware Description Language Simulator

*A Hardware Description Language Simulator uses mathematical models to replicate the behavior of an actual hardware device. Simulation software allows for modeling of circuit operation and is an invaluable analysis tool. Simulating a circuit's behavior before actually building it can greatly improve design efficiency by making faulty designs known as such, and providing insight into the behavior of electronics circuit designs.*

```
git clone https://github.com/ghdl/ghdl
```

```
cd ghdl
./configure --prefix=/usr/local
make
sudo make install

cd sim/vhdl/regression/wb/ghdl
source SIMULATE-IT

cd sim/vhdl/regression/ahb3/ghdl
source SIMULATE-IT
```

## **Yosys-ABC**

Verilog Hardware Description Language Synthesizer

*A Hardware Description Language Synthesizer turns a RTL implementation into a Logical Gate Level implementation. Logical design is a step in the standard design cycle in which the functional design of an electronic circuit is converted*

*into the representation which captures logic operations, arithmetic operations, control flow, etc. In EDA parts of the logical design is automated using synthesis tools based on the behavioral description of the circuit.*

#### Hardware Description Language Optimizer

*A Hardware Description Language Optimizer finds an equivalent representation of the specified logic circuit under specified constraints (minimum area, pre-specified delay). This tool combines scalable logic optimization based on And-Inverter Graphs (AIGs), optimal-delay DAG-based technology mapping for look-up tables and standard cells, and innovative algorithms for sequential synthesis and verification.*

```
git clone https://github.com/YosysHQ/yosys
```

```
cd yosys
make
sudo make install

cd synthesis/yosys
source SYNTHESIZE-IT
```

## BACK-END Open Source Tools

```
mkdir qflow
cd qflow
```

### Magic

#### Floor-Planner

*A Floor-Planner of an Integrated Circuit (IC) is a schematic representation of tentative placement of its major functional blocks. In modern electronic design process floor-plans are created during the floor-planning design stage, an early stage in the hierarchical approach to Integrated Circuit design. Depending on the design methodology being followed, the actual definition of a floor-plan may differ.*

#### Standard Cell Checker

*A Standard Cell Checker is a geometric constraint imposed on Printed Circuit Board (PCB) and Integrated Circuit (IC) designers to ensure their designs function properly, reliably, and can be produced with acceptable yield. Design Rules for production are developed by hardware engineers based on the capability of their processes to realize design intent. Design Rule Checking (DRC) is used to ensure that designers do not violate design rules.*

#### Standard Cell Editor

*A Standard Cell Editor allows to print a set of standard cells. The standard cell methodology is an abstraction, whereby a low-level VLSI layout is encapsulated into a logical representation. A standard cell is a group of transistor and interconnect structures that provides a boolean logic function (AND, OR, XOR, XNOR, inverters) or a storage function (flipflop or latch).*

```
git clone https://github.com/RTimothyEdwards/magic
```

```
cd magic
./configure
make
sudo make install
```

## Graywolf

Standard Cell Placer

*A Standard Cell Placer takes a given synthesized circuit netlist together with a technology library and produces a valid placement layout. The layout is optimized according to the aforementioned objectives and ready for cell resizing and buffering, a step essential for timing and signal integrity satisfaction. Physical design flow are iterated a number of times until design closure is achieved.*

```
git clone https://github.com/rubund/graywolf
cd graywolf
mkdir build
cd build
cmake ..
make
sudo make install
```

## OpenSTA

Standard Cell Timing-Analizer

*A Standard Cell Timing-Analizer is a simulation method of computing the expected timing of a digital circuit without requiring a simulation of the full circuit. High-performance integrated circuits have traditionally been characterized by the clock frequency at which they operate. Measuring the ability of a circuit to operate at the specified speed requires an ability to measure, during the design process, its delay at numerous steps.*

```
git clone https://github.com/The-OpenROAD-Project/OpenSTA
cd OpenSTA
mkdir build
cd build
cmake ..
```

```
make
sudo make install
```

## Qrouter

### Standard Cell Router

*A Standard Cell Router takes pre-existing polygons consisting of pins on cells, and pre-existing wiring called pre-routes. Each of these polygons are associated with a net. The primary task of the router is to create geometries such that all terminals assigned to the same net are connected, no terminals assigned to different nets are connected, and all design rules are obeyed.*

```
git clone https://github.com/RTimothyEdwards/qrouter
cd qrouter
./configure
make
sudo make install
```

## Irsim

### Standard Cell Simulator

*A Standard Cell Simulator treats transistors as ideal switches. Extracted capacitance and lumped resistance values are used to make the switch a little bit more realistic than the ideal, using the RC time constants to predict the relative timing of events. This simulator represents a circuit in terms of its exact transistor structure but describes the electrical behavior in a highly idealized way.*

```
git clone https://github.com/RTimothyEdwards/irsim
cd irsim
./configure
make
sudo make install
```

## Netgen

### Standard Cell Verifier

*A Standard Cell Verifier compares netlists, a process known as LVS (Layout vs. Schematic). This step ensures that the geometry that has been laid out matches the expected circuit. The greatest need for LVS is in large analog or mixed-signal circuits that cannot be simulated in reasonable time. LVS can be done faster than simulation, and provides feedback that makes it easier to find errors.*

```
git clone https://github.com/RTimothyEdwards/netgen
cd netgen
./configure
make
sudo make install
```

## **Qflow**

Back-End Workflow

```
git clone https://github.com/RTimothyEdwards/qflow
cd qflow
./configure
make
sudo make install

cd synthesis/qflow
source FLOW-IT
```

## **for WINDOWS users!**

open Microsoft Store and install Ubuntu

type:

```
sudo apt update
sudo apt upgrade
```

```
sudo apt install bison cmake flex freeglut3-dev libcairo2-dev libgsl-dev \
libncurses-dev libx11-dev m4 python-tk python3-tk swig tcl tcl-dev tk-dev tcsh
```

## **FRONT-END**

type:

```
sudo apt install verilator
sudo apt install iverilog
sudo apt install ghdl
```

```
sudo apt install yosys
```

## **BACK-END**

type:

```
mkdir qflow
cd qflow
```

```
git clone https://github.com/RTimothyEdwards/magic
git clone https://github.com/rubund/graywolf
git clone https://github.com/The-OpenROAD-Project/OpenSTA
git clone https://github.com/RTimothyEdwards/qrouter
git clone https://github.com/RTimothyEdwards/irsim
git clone https://github.com/RTimothyEdwards/netgen
git clone https://github.com/RTimothyEdwards/qflow
```

## Instruction INPUTS/OUTPUTS AMBA3 AHB-Lite Bus

Port	Size	Direction	Description
HRESETn	1	Input	Asynchronous Active Low Reset
HCLK	1	Input	System Clock Input
IHSEL	1	Output	Instruction Bus Select
IHADDR	PLEN	Output	Instruction Address Bus
IHRDATA	XLEN	Input	Instruction Read Data Bus
IHWDATA	XLEN	Output	Instruction Write Data Bus
IHWRITE	1	Output	Instruction Write Select
IHSIZE	3	Output	Instruction Transfer Size
IHBURST	3	Output	Instruction Transfer Burst Size
IHPROT	4	Output	Instruction Transfer Protection Level
IHTRANS	2	Output	Instruction Transfer Type
IHMASTLOCK	1	Output	Instruction Transfer Master Lock
IHREADY	1	Input	Instruction Slave Ready Indicator
IHRESP	1	Input	Instruction Transfer Response

## Instruction INPUTS/OUTPUTS Wishbone Bus

Port	Size	Direction	Description
rst	1	Input	Synchronous Active High Reset
clk	1	Input	System Clock Input
iadr	AW	Input	Instruction Address Bus
idati	DW	Input	Instruction Input Bus
idato	DW	Output	Instruction Output Bus
isel	DW/8	Input	Byte Select Signals
iwe	1	Input	Write Enable Input
istb	1	Input	Strobe Signal/Core Select Input

Port	Size	Direction	Description
icyc	1	Input	Valid Bus Cycle Input
iack	1	Output	Bus Cycle Acknowledge Output
ierr	1	Output	Bus Cycle Error Output
iint	1	Output	Interrupt Signal Output

### Data INPUTS/OUTPUTS AMBA3 AHB-Lite Bus

Port	Size	Direction	Description
HRESETn	1	Input	Asynchronous Active Low Reset
HCLK	1	Input	System Clock Input
DHSEL	1	Output	Data Bus Select
DHADDR	PLEN	Output	Data Address Bus
DHRDATA	XLEN	Input	Data Read Data Bus
DHWDATA	XLEN	Output	Data Write Data Bus
DHWRITE	1	Output	Data Write Select
DHSIZE	3	Output	Data Transfer Size
DHBURST	3	Output	Data Transfer Burst Size
DHPROT	4	Output	Data Transfer Protection Level
DHTRANS	2	Output	Data Transfer Type
DHMASTLOCK	1	Output	Data Transfer Master Lock
DHREADY	1	Input	Data Slave Ready Indicator
DHRESP	1	Input	Data Transfer Response

### Data INPUTS/OUTPUTS Wishbone Bus

Port	Size	Direction	Description
rst	1	Input	Synchronous Active High Reset
clk	1	Input	System Clock Input
dadr	AW	Input	Data Address Bus
ddati	DW	Input	Data Input Bus
ddato	DW	Output	Data Output Bus
dsel	DW/8	Input	Byte Select Signals
dwe	1	Input	Write Enable Input
dstb	1	Input	Strobe Signal/Core Select Input
dcyc	1	Input	Valid Bus Cycle Input
dack	1	Output	Bus Cycle Acknowledge Output
derr	1	Output	Bus Cycle Error Output



Port	Size	Direction	Description
<b>dint</b>	1	Output	Interrupt Signal Output