

```

int segmentPins[] = { 2, 3, 4, 5, 6, 7, 9 };
int digits[10][7] = {
    {1, 1, 1, 1, 1, 1, 0}, // 0
    {0, 1, 1, 0, 0, 0, 0}, // 1
    {1, 1, 0, 1, 1, 0, 1}, // 2
    {1, 1, 1, 1, 0, 0, 1}, // 3
    {0, 1, 1, 0, 0, 1, 1}, // 4
    {1, 0, 1, 1, 0, 1, 1}, // 5
    {1, 0, 1, 1, 1, 1, 1}, // 6
    {1, 1, 1, 0, 0, 0, 0}, // 7
    {1, 1, 1, 1, 1, 1, 1}, // 8
    {1, 1, 1, 1, 0, 1, 1}, // 9
};
int buzzerPin=8;
int numSegments=7;

void showDigit(int n){
    for(int i=0; i< numSegments;i++){
        digitalWrite (segmentPins[i],digits[n][i]);
    }
}

void setup(){
    Serial.begin(9600);

    pinMode(buzzerPin, OUTPUT);

    for(int i=0; i< numSegments;i++){
        pinMode(segmentPins[i],OUTPUT);
    }

    Serial.println("=== Beeping Countdown Started ===");
    int count= 9;
    while (count>=0){
        Serial.print ("Counting: ");
        Serial.print (count);

        showDigit (count);
        tone (buzzerPin,1000,200);

        delay(1000);
        count--;
    }
}

void loop(){
}

```

