

ETHERCHANNEL



SW1

SW1#conf t
Enter configuration commands, one per line. End with CNTL/Z.
SW1(config)#interface range e0/0 , e0/1
SW1(config-if-range)#channel-group 1 mode desirable
Creating a port-channel interface Port-channel 1

SW1(config-if-range)#
*Sep 18 10:16:12.474: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/0, changed state to down
*Sep 18 10:16:12.474: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/1, changed state to down
SW1(config-if-range)#
*Sep 18 10:16:21.958: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/1, changed state to up
*Sep 18 10:16:22.470: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/0, changed state to up
SW1(config-if-range)#exit
SW1(config)#do sh etherchannel summary
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use N - not in use, no aggregation
f - failed to allocate aggregator

M - not in use, minimum links not met
m - not in use, port not aggregated due to minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

A - formed by Auto LAG

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
-----+-----+-----+-----
1 Pol(SD) PAgP Et0/0(I) Et0/1(I)

SW2

SW2#conf t
Enter configuration commands, one per line. End with CNTL/Z.
SW2(config)#int range e0/0 , e0/1
SW2(config-if-range)#channel-group 1 mode auto
Creating a port-channel interface Port-channel 1

SW2(config-if-range)#
*Sep 18 10:20:07.686: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/0, changed state to down
*Sep 18 10:20:07.687: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/1, changed state to down
SW2(config-if-range)#exit
SW2(config)#do sh e
*Sep 18 10:20:16.711: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/1, changed state to up
*Sep 18 10:20:16.907: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/0, changed state to up
SW2(config)#do sh etherchannel summary
Flags: D - down P - bundled in port-channel
I - stand-alone s - suspended
H - Hot-standby (LACP only)
R - Layer3 S - Layer2
U - in use N - not in use, no aggregation
f - failed to allocate aggregator

M - not in use, minimum links not met
m - not in use, port not aggregated due to minimum links not met
u - unsuitable for bundling
w - waiting to be aggregated
d - default port

A - formed by Auto LAG

Number of channel-groups in use: 1
Number of aggregators: 1

Group Port-channel Protocol Ports
-----+-----+-----+-----
1 Pol(SD) PAgP Et0/0(I) Et0/1(I)