

Arch Lab: Optimizing the Performance of a Pipelined Processor

1 Introduction

In this lab, you will learn about the design and implementation of a pipelined Y86 processor, optimizing both it and a benchmark program to maximize performance. You are allowed to make any semantics preserving transformations to the benchmark program, or to make enhancements to the pipelined processor, or both. When you have completed the lab, you will have a keen appreciation for the interactions between code and hardware that affect the performance of your programs.

The lab is organized into three parts, each with its own handin. In Part A you will write some simple Y86 programs and become familiar with the Y86 tools. In Part B, you will extend the SEQ simulator with two new instructions. These two parts will prepare you for Part C, the heart of the lab, where you will optimize the Y86 benchmark program and the processor design.

2 Logistics

- You will work on this lab alone.
- You will be working on this assignment on your own laptop inside a VirtualBox Ubuntu Linux virtual machine (VM).

3 Handout Instructions

1. Start by copying the file `archlabx-handout.tar` from the course Web page to the home directory of your virtual machine.
2. Then give the command: `tar xvf archlabx-handout.tar`. This will cause the following files to be unpacked into the directory: `README`, `Makefile`, `sim.tar`, and `simguide.pdf`.
3. Next, give the command `tar xvf sim.tar`. This will create the directory `sim`, which contains your personal copy of the Y86 tools. You will be doing all of your work inside this directory.
4. Finally, change to the `sim` directory and build the Y86 tools:

```
unix> cd sim
unix> make clean; make
```

Now you're ready to begin!

4 Part A

You will be working in directory `sim/misc` in this part.

Your task is to **write and simulate the following three Y86 programs**. The required behavior of these programs is defined by the example C functions in `examples.c`. Be sure to put your name and ID in a comment at the beginning of each program. You can test your programs by first assembling them with the program `YAS` and then running them with the instruction set simulator `YIS`.

In all of your Y86 functions, you should follow the IA32 conventions for the structure of the stack frame and for register usage instructions, including saving and restoring any callee-save registers that you use.

sum.y: Iteratively sum linked list elements 迭代求和列表元素

Write a Y86 program `sum.y` that iteratively sums the elements of a linked list. Your program should consist of some code that sets up the stack structure, invokes a function, and then halts. In this case, the function should be Y86 code for a function (`sum_list`) that is functionally equivalent to the C `sum_list` function in Figure 1. Test your program using the following three-element list:

```
# Sample linked list
.align 4
ele1:
    .long 0x00a
    .long ele2
ele2:
    .long 0x0b0
    .long ele3
ele3:
    .long 0xc00
    .long 0
```

rsum.y: Recursively sum linked list elements

Write a Y86 program `rsum.y` that recursively sums the elements of a linked list. This code should be similar to the code in `sum.y`, except that it should use a function `rsum_list` that recursively sums a list of numbers, as shown with the C function `rsum_list` in Figure 1. Test your program using the same three-element list you used for testing `list.y`.

```

1 /* linked list element */
2 typedef struct ELE {
3     int val;
4     struct ELE *next;
5 } *list_ptr;
6
7 /* sum_list - Sum the elements of a linked list */
8 int sum_list(list_ptr ls)
9 {
10     int val = 0;
11     while (ls) {
12         val += ls->val;
13         ls = ls->next;
14     }
15     return val;
16 }
17
18 /* rsum_list - Recursive version of sum_list */
19 int rsum_list(list_ptr ls)
20 {
21     if (!ls)
22         return 0;
23     else {
24         int val = ls->val;
25         int rest = rsum_list(ls->next);
26         return val + rest;
27     }
28 }
29
30 /* copy_block - Copy src to dest and return xor checksum of src */
31 int copy_block(int *src, int *dest, int len)
32 {
33     int result = 0;
34     while (len > 0) {
35         int val = *src++;
36         *dest++ = val;
37         result ^= val;
38         len--;
39     }
40     return result;
41 }

```

Figure 1: **C versions of the Y86 solution functions.** See `sim/misc/examples.c`

copy.y: Copy a source block to a destination block

Write a program (`copy.y`) that **copies a block of words from one part of memory to another** (non-overlapping area) area of memory, computing the checksum (Xor) of all the words copied.

Your program should consist of code that sets up a stack frame, invokes a function `copy_block`, and then halts. The function should be functionally equivalent to the C function `copy_block` shown in Figure Figure 1. Test your program using the following three-element source and destination blocks:

```
.align 4
# Source block
src:
    .long 0x00a
    .long 0x0b0
    .long 0xc00

# Destination block
dest:
    .long 0x111
    .long 0x222
    .long 0x333
```

5 Part B

You will be working in directory `sim/seq` in this part.

Your task in Part B is to extend the SEQ processor to support two new instructions: `iaddl` (described in Homework problems 4.47 and 4.49)¹. `leave` (described in Homework problems 4.48 and 4.50)². To add these instructions, you will modify the file `seq-full.hcl`, which implements the version of SEQ described in the CS:APP2e textbook. In addition, it contains declarations of some constants that you will need for your solution.

Your HCL file must begin with a header comment containing the following information:

- Your name and ID.
- A description of the computations required for the `iaddl` instruction. Use the descriptions of `irmovl` and `opl` in Figure 4.18 in the CS:APP2e text as a guide.
- A description of the computations required for the `leave` instruction. Use the description of `popl` in Figure 4.20 in the CS:APP2e text as a guide.

Building and Testing Your Solution

Once you have finished modifying the `seq-full.hcl` file, then you will need to build a new instance of the SEQ simulator (`ssim`) based on this HCL file, and then test it:

¹In the international edition, `iaddl` is described in problems 4.48 and 4.50

²In the international edition, `leave` is described in problems 4.47 and 4.49

- *Building a new simulator.* You can use `make` to build a new SEQ simulator:

```
unix> make VERSION=full
```

This builds a version of `ssim` that uses the control logic you specified in `seq-full.hcl`. To save typing, you can assign `VERSION=full` in the Makefile.

- *Testing your solution on a simple Y86 program.* For your initial testing, we recommend running simple programs such as `asumi.yo` (testing `iaddl`) and `asuml.yo` (testing `leave`) in TTY mode, comparing the results against the ISA simulation:

```
unix> ./ssim -t ../y86-code/asumi.yo
unix> ./ssim -t ../y86-code/asuml.yo
```

If the ISA test fails, then you should debug your implementation by single stepping the simulator in GUI mode:

```
unix> ./ssim -g ../y86-code/asumi.yo
unix> ./ssim -g ../y86-code/asuml.yo
```

- *Retesting your solution using the benchmark programs.* Once your simulator is able to correctly execute small programs, then you can automatically test it on the Y86 benchmark programs in `../y86-code`:

```
unix> (cd ../y86-code; make testssim)
```

This will run `ssim` on the benchmark programs and check for correctness by comparing the resulting processor state with the state from a high-level ISA simulation. Note that none of these programs test the added instructions. You are simply making sure that your solution did not inject errors for the original instructions. See file `../y86-code/README` file for more details.

- *Performing extensive regression tests.* Once you can execute the benchmark programs correctly, then you should run the extensive set of autogenerated regression tests in `../ptest`. To test everything except `iaddl` and `leave`:

```
unix> (cd ../ptest; make SIM=../seq/ssim)
```

To test your implementation of `iaddl`:

```
unix> (cd ../ptest; make SIM=../seq/ssim TFLAGS=-i)
```

To test your implementation of `leave`:

```
unix> (cd ../ptest; make SIM=../seq/ssim TFLAGS=-l)
```

To test both `iaddl` and `leave`:

```
unix> (cd ../ptest; make SIM=../seq/ssim TFLAGS=-il)
```

For more information on the SEQ simulator refer to the handout *CS:APP2e Guide to Y86 Processor Simulators* (`simguide.pdf`).

```

1 /*
2  * ncopy - copy src to dst, returning number of positive ints
3  * contained in src array.
4  */
5 int ncopy(int *src, int *dst, int len)
6 {
7     int count = 0;
8     int val;
9
10    while (len > 0) {
11        val = *src++;
12        *dst++ = val;
13        if (val > 0)
14            count++;
15        len--;
16    }
17    return count;
18 }

```

Figure 2: **C version of the ncopy function.** See `sim/pipe/ncopy.c`.

6 Part C

You will be working in directory `sim/pipe` in this part.

The `ncopy` function in Figure 2 copies a `len`-element integer array `src` to a non-overlapping `dst`, returning a count of the number of positive integers contained in `src`. Figure 3 shows the baseline Y86 version of `ncopy`. The file `pipe-full.hcl` contains a copy of the HCL code for PIPE, along with a declaration of the constant value `IIADDL`.

Your task in Part C is to modify `ncopy.y86` and `pipe-full.hcl` with the goal of making `ncopy.y86` run as fast as possible.

You will be handing in two files: `pipe-full.hcl` and `ncopy.y86`. Each file should begin with a header comment with the following information:

- Your name and ID.
- A high-level description of your code. In each case, describe how and why you modified your code.

Coding Rules

You are free to make any modifications you wish, with the following constraints:

- Your `ncopy.y86` function must work for arbitrary array sizes. You might be tempted to hardwire your solution for 64-element arrays by simply coding 64 copy instructions, but this would be a bad idea because we will be grading your solution based on its performance on arbitrary arrays.

```

1 #####
2 # ncopy.ys - Copy a src block of len ints to dst.
3 # Return the number of positive ints (>0) contained in src.
4 #
5 # Include your name and ID here.
6 #
7 # Describe how and why you modified the baseline code.
8 #
9 #####
10 # Do not modify this portion
11 # Function prologue.
12 ncopy:  pushl %ebp                # Save old frame pointer
13         rrmovl %esp,%ebp         # Set up new frame pointer
14         pushl %esi              # Save callee-save regs
15         pushl %ebx
16         pushl %edi
17         mrmovl 8(%ebp),%ebx      # src
18         mrmovl 16(%ebp),%edx     # len
19         mrmovl 12(%ebp),%ecx     # dst
20
21 #####
22 # You can modify this portion
23     # Loop header
24     xorl %eax,%eax              # count = 0;
25     andl %edx,%edx              # len <= 0?
26     jle Done                    # if so, goto Done:
27
28 Loop:   mrmovl (%ebx), %esi      # read val from src...
29         rmmovl %esi, (%ecx)     # ...and store it to dst
30         andl %esi, %esi         # val <= 0?
31         jle Npos                # if so, goto Npos:
32         irmovl $1, %edi
33         addl %edi, %eax          # count++
34 Npos:   irmovl $1, %edi
35         subl %edi, %edx         # len--
36         irmovl $4, %edi
37         addl %edi, %ebx         # src++
38         addl %edi, %ecx         # dst++
39         andl %edx,%edx          # len > 0?
40         jg Loop                 # if so, goto Loop:
41 #####
42 # Do not modify the following section of code
43 # Function epilogue.
44 Done:
45     popl %edi                  # Restore callee-save registers
46     popl %ebx
47     popl %esi
48     rrmovl %ebp, %esp
49     popl %ebp
50     ret
51 #####
52 # Keep the following label at the end of your function
53 End:

```

Figure 3: **Baseline Y86 version of the ncopy function.** See `sim/pipe/ncopy.ys`.

- Your `ncopy.yo` function must run correctly with YIS. By correctly, we mean that it must correctly copy the `src` block *and* return (in `%eax`) the correct number of positive integers.
- The assembled version of your `ncopy` file must not be more than 1000 bytes long. You can check the length of any program with the `ncopy` function embedded using the provided script `check-len.pl`:

```
unix> ./check-len.pl < ncopy.yo
```

- Your `pipe-full.hcl` implementation must pass the regression tests in `../y86-code` and `../ptest` (without the `-il` flags that test `iaddl` and `leave`).

Other than that, you are free to implement the `iaddl` instruction if you think that will help. You may make any semantics preserving transformations to the `ncopy.yo` function, such as reordering instructions, replacing groups of instructions with single instructions, deleting some instructions, and adding other instructions. You may find it useful to read about loop unrolling in Section 5.8 of CS:APP2e.

Building and Running Your Solution

In order to test your solution, you will need to build a driver program that calls your `ncopy` function. We have provided you with the `gen-driver.pl` program that generates a driver program for arbitrary sized input arrays. For example, typing

```
unix> make drivers
```

will construct the following two useful driver programs:

- `sdriver.yo`: A *small driver program* that tests an `ncopy` function on small arrays with 4 elements. If your solution is correct, then this program will halt with a value of 2 in register `%eax` after copying the `src` array.
- `ldriver.yo`: A *large driver program* that tests an `ncopy` function on larger arrays with 63 elements. If your solution is correct, then this program will halt with a value of 31 (`0x1f`) in register `%eax` after copying the `src` array.

Each time you modify your `ncopy.yo` program, you can rebuild the driver programs by typing

```
unix> make drivers
```

Each time you modify your `pipe-full.hcl` file, you can rebuild the simulator by typing

```
unix> make psim VERSION=full
```

If you want to rebuild the simulator and the driver programs, type

```
unix> make VERSION=full
```


To test your solution in GUI mode on a small 4-element array, type

```
unix> ./psim -g sdriver.yo
```

To test your solution on a larger 63-element array, type

```
unix> ./psim -g ldriver.yo
```

Once your simulator correctly runs your version of `ncopy.yo` on these two block lengths, you will want to perform the following additional tests:

- *Testing your driver files on the ISA simulator.* Make sure that your `ncopy.yo` function works properly with YIS:

```
unix> make drivers
unix> ../misc/yis sdriver.yo
```

- *Testing your code on a range of block lengths with the ISA simulator.* The Perl script `correctness.pl` generates driver files with block lengths from 0 up to some limit (default 65), plus some larger sizes. It simulates them (by default with YIS), and checks the results. It generates a report showing the status for each block length:

```
unix> ./correctness.pl
```

This script generates test programs where the result count varies randomly from one run to another, and so it provides a more stringent test than the standard drivers.

If you get incorrect results for some length K , you can generate a driver file for that length that includes checking code, and where the result varies randomly:

```
unix> ./gen-driver.pl -f ncopy.yo -n K -rc > driver.yo
unix> make driver.yo
unix> ../misc/yis driver.yo
```

The program will end with register `%eax` having the following value:

0xaaaa : All tests pass.

0xbbbb : Incorrect count

0xcccc : Function `ncopy` is more than 1000 bytes long.

0xdddd : Some of the source data was not copied to its destination.

0xeeee : Some word just before or just after the destination region was corrupted.

- *Testing your pipeline simulator on the benchmark programs.* Once your simulator is able to correctly execute `sdriver.yo` and `ldriver.yo`, you should test it against the Y86 benchmark programs in `../y86-code`:

```
unix> (cd ../y86-code; make testpsim)
```

This will run `psim` on the benchmark programs and compare results with YIS.

- *Testing your pipeline simulator with extensive regression tests.* Once you can execute the benchmark programs correctly, then you should check it with the extensive regression tests in `../ptest`. To test everything except `iaddl` and `leave`:

```
unix> (cd ../ptest; make SIM=../pipe/psim)
```

If your solution implements the `iaddl` instruction:

```
unix> (cd ../ptest; make SIM=../pipe/psim TFLAGS=-i)
```

- *Testing your code on a range of block lengths with the pipeline simulator.* You should also run the same code tests on the pipeline simulator that you did earlier with the ISA simulator

```
unix> ./correctness.pl -p
```

- *Testing your code for performance.* Finally, to check the performance of your code:

```
unix> ./benchmark.pl
```

The next section has more details on performance.

7 Evaluation

The lab is worth 190 points: 30 points for Part A, 60 points for Part B, and 100 points for Part C.

Part A

Part A is worth 30 points, 10 points for each Y86 solution program. Each solution program will be evaluated for correctness, including proper handling of the stack and registers, as well as functional equivalence with the example C functions in `examples.c`.

The programs `sum.js` and `rsum.js` will be considered correct if the graders do not spot any errors in them, and their respective `sum_list` and `rsum_list` functions return the sum `0xcba` in register `%eax`.

The program `copy.js` will be considered correct if the graders do not spot any errors in them, and the `copy_block` function returns the sum `0xcba` in register `%eax`, copies the three words `0x00a`, `0x0b`, and `0xc` to the 12 contiguous memory locations beginning at address `dest`, and does not corrupt other memory locations.

Part B

This part of the lab is worth 60 points:

- 10 points for your description of the computations required for the `iaddl` instruction.
- 10 points for your description of the computations required for the `leave` instruction.
- 10 points for passing the benchmark regression tests in `y86-code`, to verify that your simulator still correctly executes the benchmark suite.
- 15 points for passing the regression tests in `ptest` for `iaddl`.
- 15 points for passing the regression tests in `ptest` for `leave`.

Part C

This part of the Lab is worth 100 points: **You will not receive any credit if either your code for `ncopy.y86` or your modified simulator fails any of the tests described earlier.**

- 20 points each for your descriptions in the headers of `ncopy.y86` and `pipe-full.hcl` and the quality of these implementations.
- 60 points for performance. To receive credit here, your solution must be correct, as defined earlier. That is, `ncopy` runs correctly with YIS, and `pipe-full.hcl` passes all tests in `y86-code` and `pptest`.

We will express the performance of your function in units of *cycles per element* (CPE). That is, if the simulated code requires C cycles to copy a block of N elements, then the CPE is C/N . The PIPE simulator displays the total number of cycles required to complete the program. The baseline version of the `ncopy` function running on the standard PIPE simulator with a large 63-element array requires 914 cycles to copy 63 elements, for a CPE of $914/63 = 14.51$.

Since some cycles are used to set up the call to `ncopy` and to set up the loop within `ncopy`, you will find that you will get different values of the CPE for different block lengths (generally the CPE will drop as N increases). We will therefore evaluate the performance of your function by computing the average of the CPEs for blocks ranging from 1 to 64 elements. You can use the Perl script `benchmark.pl` in the `pipe` directory to run simulations of your `ncopy.y86` code over a range of block lengths and compute the average CPE. Simply run the command

```
unix> ./benchmark.pl
```

to see what happens. For example, the baseline version of the `ncopy` function has CPE values ranging between 46.0 and 14.51, with an average of 16.44. Note that this Perl script does not check for the correctness of the answer. Use the script `correctness.pl` for this:

```
unix> correctness.pl -p
```

You should be able to achieve an average CPE of less than 10.0. Our best version averages 9.27. If your average CPE is c , then your score S for this portion of the lab will be:

$$S = \begin{cases} 0, & c > 13.0 \\ 60 \cdot ((13.0 - c)/(13.0 - 10.0)), & 10.0 \leq c \leq 13.0 \\ 60, & c < 10.0 \end{cases}$$

By default, `benchmark.pl` and `correctness.pl` compile and test `ncopy.y86`. Use the `-f` argument to specify a different file name. The `-h` flag gives a complete list of the command line arguments.

8 Handin Instructions

- You will be handing in three sets of files:

- Part A: `sum.ys`, `rsum.ys`, and `copy.ys`.
- Part B: `seq-full.hcl`.
- Part C: `ncopy.ys` and `pipe-full.hcl`.
- Make sure you have included your name and `userID` in a comment at the top of each of your handin files.
- To create your handin files for part X, go to your `archlab-handout` directory and type:

```
unix> make handin-partX USER=userID
```

where X is a, b, or c, and where `userID` is your unique `userID`. For example, if your `userID` is `studID@pku.edu.cn`, then to handin Part A you would type:

```
unix> make handin-parta USER=studID@pku.edu.cn
```

- To handin your work, select your handin tarballs in archlab webpage:
 - `userID-parta.tar`
 - `userID-partb.tar`
 - `userID-partc.tar`

9 Hints

- By design, both `sdriver.yo` and `ldriver.yo` are small enough to debug with in GUI mode. We find it easiest to debug in GUI mode, and suggest that you use it.
- With some X servers, the “Program Code” window begins life as a closed icon when you run `psim` or `ssim` in GUI mode. Simply click on the icon to expand the window.
- With some X servers, the “Memory Contents” window will not automatically resize itself. You’ll need to resize the window by hand.
- The `psim` and `ssim` simulators terminate with a segmentation fault if you ask them to execute a file that is not a valid Y86 object file.