Rwanda oRn BSS Project

Interface Definition

<MTM Interface - Top-up>

Doc. ID	
Version	1.9
First Created	2020.10.14
Last Modified	2022.03.08

[Version Infomation]

Project	Rwanda oRn BSS Project				
Doc. Name	Interface Definition	Version	1.9	Date	2022.03.08
Config. Mng. ID		Team	nTels	Writer	Julian

[Revision History]

Version	Revised Date	Revision Contents	Revisor
1.0	2020.10.14	This report's draft was created.	JK
1.1	2020.11.03	Add HPOP403	JK
1.2	2020.11.16	Add HPOP402	JK
1.3	2020.11.16	Added Activation Service	JK
1.4	2020.12.28	Add HPOP501	JK
1.5	2021.01.11	Changed HPOP003	JK
1.6	2021.04.26	Add HPOP101	JK
1.7	2021.10.27	Add HP00005-HPOP303	Julian
1.8	2021.11.16	Changed HP00005-HPOP303	Julian
1.9	2022.03.08	Add HPOP305 Add HPOP306	Julian

Table of Contents

1. INTERFACE OVERVIEW 4
1.1 Interface Summary 4
2. BUSINESS 5
2.1 Service (HP00001) 5
2.1.1 Searching Balance (svccode: HP00001, opcode: HPOP001) 5
2.1.2 Searching MSISDN (svccode: HP00001, opcode: HPOP003) 7
2.1.3 Searching available bundles (SVCCODE: HP00001, OPCODE: HPOP005) 8
2.1.4 Searching usage balance (SVCCODE: HP00001, OPCODE: HPOP008) 9
2.1.5 Searching balance (SVCCODE: HP00005, OPCODE: HPOP101) 11
2.2 Recharge Service (HP00002) 13
2.2.1 Request for recharge (svccode: HP00002, opcode: HPOP001) 13
2.2.2 Cancel for recharging (svccode: HP00002, opcode: HPOP002) 14
2.2.3 Request for recharge voucher (svccode: HP00002, opcode: HPOP003) 15
2.3 Purchase Product Service (HP00002) 16
2.3.1 Request Bundle Purchase (SVCCODE: HP00002, OPCODE: HPOP004) 16
2.4 Request Bundle Purchase Checking (HP00005) 17
2.4.1 Request Bundle Purchase Checking (SVCCODE: HP00005, OPCODE: HPOP403) 17
2.4.2 Request E-Wallet Amount (SVCCODE: HP00005, OPCODE: HPOP402) 19
2.5 Activation Service (HPOP301~) 21
2.5.1 Request searching price plan (SVCCODE: HP00005, OPCODE: HPOP301) 21
2.5.2 Request for Simple activation (SVCCODE: HP00005, OPCODE: HPOP302) 22
2.5.3 Request for NIDA getCitizen API (SVCCODE: HP00005, OPCODE: HPOP303) 24
2.5.4 Request for Get company information with TIN from RRA (SVCCODE: HP00005, OPCODE: HPOP305) 26
2.5.5 Request for Get foreigner information with passport number from DGIE (SVCCODE: HP00005, OPCODE: HPOP306) 28
2.6 Subscribe Customer Info (HPOP501~) 30
2.6.1 Subscribe Customer Info (SVCCODE:HP00005 , OPCODE:HPOP501) 30
2.6.2 Searching Customer Info (SVCCODE : HP00005, OPCODE : HPOP502) 32
2.7 Searching MSISDN (HPOP601~) 34
2.7.1 Checking MSISDN status (svccode: HP00005, opcode: HPOP601) 34
2.7.2 Recommend 5 MSISDNS (svccode: HP00005, opcode: HPOP602) 35

1. INTERFACE OVERVIEW

System for interworking protocol is defined as follows. And it provides a service based on the conventions defined.

1.1 Interface Summary

For data linkage of various business, the ORN BSS System provides the information service of the interworking.

■ Common Message

Message Code	Message Description
1001	It has been successfully processed.
-4001	Activator identifier can not be found from the gateway.
-4002	Error of data type that can not be converted at the gateway has occurred.
-4003	An error has occurred in the business process.
-6001	XXXX is missing. (when the parameter is missing)
-6002	Undefined value/incorrect value(XXXX) was entered.
-7001	Work that can not be processed has occurred.(XX…XXXX)
-7002	Data is not found..

2. BUSINESS

2.1 Service (HP00001)

2.1.1 Searching Balance (svccode: HP00001, opcode: HPOP001)

■ Summary
You can be searching balace.

■ Telecommunication Protocol for Request

Request URI	http://www.4glte.rw/api_access.jsp		
Protocol Type	http	Method	POST
Port	80	Contents Type	Application/xml
I/F Cycle	Every Request time		

■ Request Item / Schema
Send parameters (Name, Value) : (REQ_XML, XML comprising the following elements)

Element	M/O	Format	Description
request	M		Request Root
header	M		Request Header
svccode	M	String(7)	Service Code
opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
body	M		Request Parameter Body
MSISDN	M	String(15)	MSISDN
ISP_CD	M	String(3)	Business No (defined by ORN)

■ Response Item / Schema

Element	M/O	Format	Description
response	M		Response Root
header	M		Response Header
svccode	M	String(7)	Service Code
opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
msgcode	O	String(5)	Message Code
message	O	String(30)	Message Description
body	M		Response Parameter Body
REMAIN_AMT	M	String(15)	Remaining Money

■ Example :

You should send the parameter that is set to the string is containing the following Request XML.(The Parameter's name is REQ_XML)

- Request XML

```
<?xml version='1.0' encoding='UTF-8' standalone='yes' ?>
<request>
 <header>
   <svcode>HP00001</svcode>
   <opcode>HPOP001</opcode>
   <CHCODE>A</CHCODE>
 </header>
 <body>
       <MSISDN>0771000050</MSISDN>
       <ISP_CD>62</ISP_CD>
</body>
</request>
```

2.1.2 Searching MSISDN (svccode: HP00001, opcode: HPOP003)

■ Summary

You can be searching MSISDN.

■ Telecommunication Protocol for Request

Request URI	http://www.4glte.rw/api_access.jsp		
Protocol Type	http	Method	POST
Port	80	Contents Type	Application/xml
I/F Cycle	Every Request time		

■ Request Item / Schema

Send parameters (Name, Value) : (REQ_XML, XML comprising the following elements)

Element	M/O	Format	Description
request	M		Request Root
header	M		Request Header
svccode	M	String(7)	Service Code
opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
body	M		Request Parameter Body
ICCID	M	STRING(18)	ICCID
NATIONAL_ID	O	String(16)	National ID or TIN
ISP_CD	O	String(3)	Business No (defined by ORN)

■ Response Item / Schema

Element	M/O	Format	Description
response	M		Response Root
header	M		Response Header
svccode	M	String(7)	Service Code
opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
msgcode	O	String(5)	Message Code
message	O	String(30)	Message Description
body	M		Response Parameter Body
SO_ID	M	STRING(3)	RETAILER CODE
SO_NM	M	STRING(100)	RETAILER NAME
MSISDN	M	String(15)	MSISDN

■ Example :

You should send the parameter that is set to the string is containing the following Request XML.(The Parameter's name is REQ_XML)

- Request XML

```
<?xml version='1.0' encoding='UTF-8' standalone='yes' ?>
<request>
 <header>
    <svcode>HP00001</svcode>
    <opcode>HPOP003</opcode>
    <CHCODE>A</CHCODE>
 </header>
 <body>
       <ICCID>9999999</ ICCID>
       <NATIONAL_ID></NATIONAL_ID>
       <ISP_CD>62</ISP_CD>
```

</body>
</request>

2.1.3 Searching available bundles (SVCCODE: HP00001, OPCODE: HPOP005)

■ Summary

YOU CAN BUNDLE LIST THAT AVAILABLE FOR PURCHASE AT THE NUMBER MATCH ON MSISDN.

■ Telecommunication Protocol for Request

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request Item / Schema

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
MSISDN	M	STRING(10)	MSISDN (CUSTMER PHONE NUMBER)
ISP_CD	M	String(3)	Business No (defined by ORN)

■ Response Item / Schema

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY
PROD_LIST	M	STRING(2048)	THE PRODUCT LIST ORDER IS MADE UP OF THE PRODUCT CODE, THE PRODUCT NAME, AND THE PRODUCT PRICE, AND THE DELIMITER OF THE PRODUCT IS " | "

■ Example :
YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING
REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
 <HEADER>
   <SVCODE>HP00001</SVCODE>
   <OPCODE>HPOP005</OPCODE>
   <CHCODE>A</CHCODE>
 </HEADER>
 <BODY>
      <MSISDN>0771000050</MSISDN>
      <ISP_CD>62</ISP_CD>
</BODY>
</REQUEST>
```

- RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
   <HEADER>
      <SVCODE>HP00005</SVCODE>
      <OPCODE>HPOP102</OPCODE>
      <CHCODE>A</CHCODE>
      <MSGCODE>XXXX</MSGCODE>
      <MESSAGE>….</MESSAGE>
   </HEADER>
   <BODY>
      <PROD_LIST>
         PD00000574,ORN 500MB BUNDLE(PRE),2300   |
         PD00000575,ORN 10GB BUNDLE(PRE),39600
      </PROD_LIST>
   </BODY>
</RESPONSE>
```

2.1.4 Searching usage balance (SVCCODE: HP00001, OPCODE: HPOP008)

■ Summary
You can be searching usage

■ Telecommunication Protocol for Request

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request Item / Schema
SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT			M/O	FORMAT	DESCRIPTION
REQUEST			M		REQUEST ROOT
	HEADER		M		REQUEST HEADER
		SVCCODE	M	STRING(8)	SERVICE CODE
		OPCODE	M	STRING(8)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
	BODY		M		REQUEST PARAMETER BODY
		MSISDN	M	STRING(10)	MSISDN (CUSTMER PHONE NUMBER)
		ISP_CD	M	String(3)	Business No (defined by ORN)

■ Response Item / Schema

ELEMENT			M/O	FORMAT	DESCRIPTION
RESPONSE			M		RESPONSE ROOT
	HEADER		M		RESPONSE HEADER
		SVCCODE	M	STRING(8)	SERVICE CODE
		OPCODE	M	STRING(8)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
		MSGCODE	O	STRING(8)	MESSAGE CODE
		MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
	BODY		M		RESPONSE PARAMETER BODY
		PURCHASED_LIST	M	STRING(2048)	PRODUCT CODE, PRODUCT NAME, PRODUCT FLAG(V-BUNDLE,B-BASE), ALLOWANCE, USAGE, REMAINING |

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
 <HEADER>
   <SVCODE>HP00001</SVCODE>
   <OPCODE>HPOP008</OPCODE>
   <CHCODE>A</CHCODE>
 </HEADER>
 <BODY>
      <MSISDN>0771000050</MSISDN>
      <ISP_CD>62</ISP_CD>
</BODY>
</REQUEST>
```

2.1.5 Searching balance (SVCCODE: HP00005, OPCODE: HPOP101)

■ Summary

YOU CAN BE SEARCHING BALANCE.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ request ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
MSISDN	O	STRING(10)	MSISDN (CUSTMER PHONE NUMBER)
ICCID	O	STRING(19)	ICCID

■ Response ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY
MSISDN	M	STRING(10)	MSISDN (CUSTMER PHONE NUMBER)
SO_ID	M	STRING(3)	RETAILER ID
SO_NM	M	STRING(100)	RETAILER NAME
REMAIN_AMT	M	STRING(128)	REMAIN 4G MONEY
TOTAL_VOLUME	M	STRING(128)	PURCHASED VOLUME
AMOUNT_USED	M	STRING(128)	TOTAL USAGE

	TODAY_VOLUME	M	STRING(128)	TODAY USAGE
	REMAIN_VOLUME	M	STRING(128)	REMAIN VOLUME
	BUNDLE_HIST	O	STRING(1024)	PURCHASE BUNDLE HISTORY (ONLY PREPAID, PREPAIDHYBRID)
	PROD_NM	O	STRING(75)	PRODUCT NAME (ONLY POSTPAID)
	PROD_GRP	M	STRING(1)	a : PREPAID, b : POSTPAID, d : PREPAIDHYBRID
	APP_USE_YN	M	STRING(1)	APPLICATION USE OR NOT(Y/N)

☠MESSAGE

MESSAGE CODE	MESSAGE DESCRIPTION
-8001	THERE IS NO MATCHING INFORMATION FOR MSISDN OR DISTINGUISH_ID.
-5002	MSISDN'S BUSINESS NO. AND TRANSFER XML'S BUSINESS NO. DO NOT MATCH.

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
 <HEADER>
   <SVCODE>HP00005</SVCODE>
   <OPCODE>HPOP101</OPCODE>
   <CHCODE>A</CHCODE>
 </HEADER>
 <BODY>
      <MSISDN>0771000050</MSISDN>
</BODY>
</REQUEST>
```

- RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP101</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>1001</MSGCODE>
        <MESSAGE>IT HAS BEEN SUCCESSFULLY PROCESSED.</MESSAGE>
    </HEADER>
    <BODY>
        <MSISDN>0771000050</MSISDN>
        <REMAIN_AMT>23000</REMAIN_AMT>
        <TOTAL_VOLUME>5000</TOTAL_VOLUME>
        <AMOUNT_USED>2200</AMOUNT_USED>
        <TODAY_VOLUME>500</TODAY_VOLUME>
        <PROD_GRP>a</PROD_GRP>
        <REMAIN_VOLUME>2800</REMAIN_VOLUME>
```

<BUNDLE_HIST>CANCEL,14/05/2018 16:29:24,G-MAX NEW MONTHLY UNLIMITED 1GB BUNDLE(PRE),-25000,09/06/2018 23:59:59,Y;PURCHASE,11/05/2018 11:53:04,G-MAX NEW MONTHLY UNLIMITED 1GB BUNDLE(PRE),25000,09/06/2018 23:59:59,Y;PURCHASE,29/03/2018 15:22:46,G-MAX NEW MONTHLY UNLIMITED 1GB BUNDLE(PRE),26500,27/04/2018 23:59:59,Y;PURCHASE,17/02/2018 20:28:41,G-MAX NEW MONTHLY UNLIMITED PACK SMART 1GB BUNDLE(PRE),18000,18/03/2018 23:59:59,Y;PURCHASE,24/02/2018 00:02:38,G-MAX MUP 4GB PROMO BUNDLE(PRE),0,24/02/2018 23:59:59,Y</BUNDLE_HIST>
</BODY>
</RESPONSE>

2.2 Recharge Service (HP00002)

2.2.1 Request for recharge (svccode: HP00002, opcode: HPOP001)

■ Summary

You can make a recharge request.

■ Telecommunication Protocol for Request

Request URI	http://www.4glte.rw/api_access.jsp		
Protocol Type	http	Method	POST
Port	80	Contents Type	Application/xml
I/F Cycle	Every Request time		

■ Request Item / Schema

Send parameters (Name, Value) : (REQ_XML, XML comprising the following elements)

Element	M/O	Format	Description
request	M		Request Root
header	M		Request Header
Svccode	M	String(7)	Service Code
Opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
body	M		Request Parameter Body
MSISDN	M	String(15)	MSISDN
NATIONAL_ID	M	String(16)	National ID or TIN
ISP_CD	M	String(3)	Business No (defined by ORN)
REQ_SYS_ID	M	String(2)	Distinguished Request Type 01 : Pivot Access
RCHRG_TP	M	String	Recharge Type 100 : Recharge Data
RCHRG_STAT	M	String	Recharge Status 10 : Recharge
RCHRG_APPR_NO	M	String	Pivot Access's Approval No
RCHRG_AMT	M	String	Recharge Money

■ Response Item / Schema

Element	M/O	Format	Description
response	M		Response Root
header	M		Response Header
svccode	M	String(7)	Service Code
opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
msgcode	O	String(5)	Message Code
message	O	String(30)	Message Description

■ Example :

You should send the parameter that is set to the string is containing the following Request XML.(The Parameter's name is REQ_XML)

- Request XML

```
<?xml version='1.0' encoding='UTF-8' standalone='yes' ?>
<request>
 <header>
   <svcode>HP00002</svcode>
   <opcode>HPOP001</opcode>
   <CHCODE>A</CHCODE>
 </header>
 <body>
       <MSISDN>0771000050</MSISDN>
       <NATIONAL_ID>8012101234567890</NATIONAL_ID>
       <ISP_CD>62</ISP_CD>
       <REQ_SYS_ID>01</REQ_SYS_ID>
       <RCHRG_TP>100</RCHRG_TP>
       <RCHRG_STAT>10</RCHRG_STAT>
       <RCHRG_APPR_NO>9999999999</RCHRG_APPR_NO>
       <RCHRG_AMT>10000</RCHRG_AMT>
</body>
</request>
```

2.2.2 Cancel for recharging (svccode: HP00002, opcode: HPOP002)

■ Summary

You can make a recharge cancel..

■ Telecommunication Protocol for Request

Request URI	http://www.4glte.rw/api_access.jsp		
Protocol Type	http	Method	POST
Port	80	Contents Type	Application/xml
I/F Cycle	Every Request time		

■ Request Item / Schema

Send parameters (Name, Value) : (REQ_XML, XML comprising the following elements)

Element			M/O	Format	Description
request			M		Request Root
	header		M		Request Header
		Svccode	M	String(7)	Service Code
		Opcode	M	String(7)	Operation Code
		chcode	M	String(2)	Incoming Channel (default : A)
	body		M		Request Parameter Body
		MSISDN	M	String(15)	MSISDN
		NATIONAL_ID	M	String(16)	National ID or TIN
		ISP_CD	M	String(3)	Business No (defined by ORN)
		REQ_SYS_ID	M	String(2)	Distinguished Request Type 01 : Pivot Access
		RCHRG_TP	M	String	Recharge Type 100 : Recharge Data
		RCHRG_STAT	M	String	Recharge Status 30 : Cancel Recharge
		RCHRG_APPR_NO	M	String	Pivot Access's Approval No
		CNL_AMT	M	String	Cancel money

■ Response Item / Schema

Element	M/O	Format	Description
response	M		Response Root
header	M		Response Header
svccode	M	String(7)	Service Code
opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
msgcode	O	String(5)	Message Code
message	O	String(30)	Message

■ Example :

You should send the parameter that is set to the string is containing the following Request XML.(The Parameter's name is REQ_XML)

- Request XML

```
<?xml version='1.0' encoding='UTF-8' standalone='yes' ?>
<request>
 <header>
    <svcode>HP00001</svcode>
    <opcode>HPOP001</opcode>
    <CHCODE>A</CHCODE>
 </header>
 <body>
       <MSISDN>0771000050</MSISDN>
       <NATIONAL_ID>8012101234567890</NATIONAL_ID>
       <ISP_CD>62</ISP_CD>
       <REQ_SYS_ID>01</REQ_SYS_ID>
       <RCHRG_TP>100</RCHRG_TP>
       <RCHRG_STAT>30</RCHRG_STAT>
       <RCHRG_APPR_NO>9999999999</RCHRG_APPR_NO>
       <CNL_AMT>10000</CNL_AMT>
</body>
</request>
```

2.2.3 Request for recharge voucher (svccode: HP00002, opcode: HPOP003)

■ Summary

You can make a recharge request by voucher number.

■ Telecommunication Protocol for Request

Request URI	http://www.4glte.rw/api_access.jsp		
Protocol Type	http	Method	POST
Port	80	Contents Type	Application/xml
I/F Cycle	Every Request time		

■ Request Item / Schema

Send parameters (Name, Value) : (REQ_XML, XML comprising the following elements)

Element	M/O	Format	Description
request	M		Request Root
header	M		Request Header
Svccode	M	String(7)	Service Code
Opcode	M	String(7)	Operation Code
chcode	M	String(2)	Incoming Channel (default : A)
body	M		Request Parameter Body
MSISDN	M	String(15)	MSISDN
ISP_CD	M	String(3)	Business No (defined by ORN)
RCHRG_TP	M	String	Recharge Type

					300 : Recharge Data voucher
		RCHRG_STAT	M	String	Recharge Status 10 : Recharge
		VO_SEQ_NO	M	String	Voucher number

■ Response Item / Schema

Element			M/O	Format	Description
response			M		Response Root
	header		M		Response Header
		svccode	M	String(7)	Service Code
		opcode	M	String(7)	Operation Code
		chcode	M	String(2)	Incoming Channel (default : A)
		msgcode	O	String(5)	Message Code
		message	O	String(30)	Message Description

■ Example :

You should send the parameter that is set to the string is containing the following Request XML.(The Parameter's name is REQ_XML)

- Request XML

```
<?xml version='1.0' encoding='UTF-8' standalone='yes' ?>
<request>
 <header>
    <svccode>HP00002</svccode>
    <opcode>HPOP003</opcode>
    <CHCODE>A</CHCODE>
 </header>
 <body>
       <MSISDN>0771000050</MSISDN>
       <ISP_CD>62</ISP_CD>
       <RCHRG_TP>300</RCHRG_TP>
       <RCHRG_STAT>10</RCHRG_STAT>
       <VO_SEQ_NO>AB2132GSAER</VO_SEQ_NO>
</body>
</request>
```

2.3 Purchase Product Service (HP00002)

2.3.1 Request Bundle Purchase (SVCCODE: HP00002, OPCODE: HPOP004)

■ Summary

YOU CAN PURCHASE THE BUNDLE PRODUCT.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
MSISDN	M	String(15)	MSISDN
ISP_CD	M	String(3)	Business No (defined by ORN)
RCHRG_TP	M	String	Recharge Type 500 : Purchase Bundle
RCHRG_STAT	M	String	Recharge Status 10 : Purchase
PROD_CD	M	STRING(10)	SELECTED PRODUCT CODE

■ Response ITEM / SCHEMA'

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCODE	M	STRING(7)	SERVICE CODE
OPCODE	M	STRING(7)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY
RESULT	M	STRING(2048)	OK : SUCCESS

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
    <HEADER>
        <SVCODE>HP00002</SVCODE>
        <OPCODE>HPOP004</OPCODE>
        <CHCODE>A</CHCODE>
    </HEADER>
    <BODY>
        <MSISDN>0771000050</MSISDN>
        <SO_ID>62</SO_ID>
        <RCHRG_TP>500</RCHRG_TP>
        <RCHRG_STAT>10</RCHRG_STAT>
        <PROD_CD>PD00000574</PROD_CD>
    </BODY>
</REQUEST>
```

2.4 Request Bundle Purchase Checking (HP00005)

2.4.1 Request Bundle Purchase Checking (SVCCODE: HP00005, OPCODE:

HPOP403)

■ Summary

■ YOU CAN CHECK THE BUNDLE PRODUCT PURCHASE OR NOT.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
SO_ID	M	STRING(3)	RETAILER CODE
PROD_CD	M	STRING(10)	SELECTED PRODUCT CODE
MSISDN	M	STRING(10)	SERVICE TEL NUMBER
PAYMENT_TYPE	M	STRING(4)	PAYMENT_TYPE (DEFAULT :01)
REQ_SYS_ID	M	STRING(2)	DISTINGUISHED REQUEST TYPE (DEFAULT :01)

■ Response ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCODE	M	STRING(7)	SERVICE CODE
OPCODE	M	STRING(7)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY
RESULT	M	STRING(2048)	OK : Y

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION='1.0' ENCODING='UTF-8'?>
<REQUEST>
```

```
<HEADER>
<SVCODE>HP00005</SVCODE>
<OPCODE>HPOP403</OPCODE>
<CHCODE>A</CHCODE>
</HEADER>
<BODY>
<SO_ID>00</SO_ID>
<PROD_CD>PD00014751</PROD_CD>
<MSISDN>0771000727</MSISDN>
<PAYMENT_TYPE>01</PAYMENT_TYPE>
<REQ_SYS_ID>01</REQ_SYS_ID>
</BODY>
</REQUEST>
```

- RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP403</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>1001</MSGCODE>
        <MESSAGE>IT HAS BEEN SUCCESSFULLY PROCESSED. PLEASE PRESS THE CHECK BALANCE BUTTON TO CONFIRM THE RESULTS.</MESSAGE>
    </HEADER>
    <BODY>
        <RESULT>Y</RESULT>
    </BODY>
</RESPONSE>
```

2.4.2 Request E-Wallet Amount (SVCCODE: HP00005, OPCODE: HPOP402)

■ Summary
  ■ YOU CAN PURCHASE THE BUNDLE PRODUCT BY E-WALLET BALANCE.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA
SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY

		SO_ID	M	STRING(3)	RETAILER CODE
		PROD_CD	M	STRING(10)	SELECTED PRODUCT CODE

■ Response ITEM / SCHEMA

ELEMENT			M/O	FORMAT	DESCRIPTION
RESPONSE			M		RESPONSE ROOT
	HEADER		M		RESPONSE HEADER
		SVCODE	M	STRING(7)	SERVICE CODE
		OPCODE	M	STRING(7)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
		MSGCODE	O	STRING(8)	MESSAGE CODE
		MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
	BODY		M		RESPONSE PARAMETER BODY
		RESULT	M	STRING(1)	Y : CAN PURCAHSE N : CANNOT PURCHASE

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION='1.0' ENCODING='UTF-8'?>
<REQUEST>
<HEADER>
<SVCODE>HP00005</SVCODE>
<OPCODE>HPOP402</OPCODE>
<CHCODE>A</CHCODE>
</HEADER>
<BODY>
<SO_ID>00</SO_ID>
<PROD_CD>PD00014751</PROD_CD>
</BODY>
</REQUEST>
```

RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP403</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>….</MSGCODE>
        <MESSAGE>….</MESSAGE>
    </HEADER>
    <BODY>
        <RESULT>Y</RESULT>
    </BODY>
</RESPONSE>
```

2.5 Activation Service (HPOP301~)

2.5.1 Request searching price plan (SVCCODE: HP00005, OPCODE: HPOP301)

■ Summary
- FOR SEARCHING PRICE PLAN CAN BE AVAILABLE SIMPLE ACTIVATION

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA
SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
MSISDN	M	STRING(10)	MSISDN
ICCID	M	STRING(19)	ICCID

■ Response ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY
SO_ID	M	STRING(2)	BUSINESS NO
PROD_CNT	M	STRING(8)	PRICE PLAN COUNT
PROD_CD	O	STRING(10)	PRICE PLAN CODE
PROD_NM	O	STRING(64)	PRICE PLAN NAME
PROD_GRP	O	STRING(64)	PRODUCT TYPE (a : PREPAID, b : POSTPAID, d : PREPAIDHYBRID)

■ Example :
YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP301</OPCODE>
                <CHCODE>A</CHCODE>
        </HEADER>
        <BODY>
                <MSISDN>07XXXXXXXX</MSISDN>
                <ICCID>89XXXXXXXXXXXXXXXXX</ICCID>
                 <DISTINGUISH_NO>
JWTERSBGCAZ3TKH2MAOZCND6UUC=</DISTINGUISH_NO>
        </BODY>
</REQUEST>
```

- RESPONSE XML

```
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP301</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>XXXX</MSGCODE>
        <MESSAGE>…</MESSAGE>
    </HEADER>
    <BODY>
        <SO_ID>01</SO_ID>
        <MSISDN>07XXXXXXXX</MSISDN>
        <PROD_CNT>3</PROD_CNT>
        <PROD_NM>ORN 500MB BUNDLE(PRE),
                 ORN 20GB BUNDLE(PRE),
                 ORN 10GB BUNDLE(PRE)
        </PROD_NM>
        <PROD_CD>PD00000574,PD00000575,PD00000576</PROD_CD>
        <PROD_GRP>a,a,a</PROD_GRP>
    </BODY>
</RESPONSE>
```

2.5.2 Request for Simple activation (SVCCODE: HP00005, OPCODE: HPOP302)

■ Summary

■ SIMPLE ACTIVATION IS ONLY AVAILABLE TO PREPAY CUSTOMERS.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
SO_ID	M	STRING(3)	RETAILER CODE
MSISDN	M	STRING(10)	MSISDN
PROD_CD	M	STRING(10)	PRICE PLAN CODE WHICH IS SELECTED FROM PRICE PLAN LIST.
LOGIN_ID	M	STRING(15)	LOGIN ID
ORG_ID	M	STRING(10)	ORGANIZATION ID
ICCID	M	STRING(64)	ICCID
CUST_ID	M	STRING(10)	CUSTOMER ID
REQ_SYS_ID	M	STRING(2)	DISTINGUISHED REQUEST TYPE 01 : PIVOT ACCESS 02 : APP ACCESS 03 : USSD ACCESS

■ Response ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY
RESULT	M	STRING(2048)	RESULT DETAIL MESSAGE
PROD_RATE	M	STRING(128)	PRODUCT RATE

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP302</OPCODE>
        <CHCODE>A</CHCODE>
    </HEADER>
    <BODY>
        <SO_ID>62</SO_ID>
        <MSISDN>070XXXXXXXX</MSISDN>
        <PROD_CD>PDXXXXXXXX</PROD_CD>
        <LOGIN_ID> armapoc </LOGIN_ID>
        <ORG_ID> NZ00000221 </ORG_ID
```

```
                <ICCID>89XXXXXXXXXXXXXXXX</ICCID>
                <CUST_ID>C000111222</CUST_ID>
                <REQ_SYS_ID>02</REQ_SYS_ID>
            </BODY>
        </REQUEST>
```

- RESPONSE XML

```
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP302</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>XXXX</MSGCODE>
        <MESSAGE>…</MESSAGE>
    </HEADER>
    <BODY>
        <RESULT>SUCCESS</RESULT>
        <PROD_RATE>23000</PROD_RATE>
</BODY>
</RESPONSE>
```

2.5.3 Request for NIDA getCitizen API (SVCCODE: HP00005, OPCODE: HPOP303)

☠SUMMARY

GET CITIZEN INFORMATION FROM NIDA

☠TELECOMMUNICATION PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/voucher/api/external_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

☠REQUEST ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
NID	M	STRING(20)	NATIONAL ID
PHOTO	M	STRING(2048)	CUSTOMER PHOTO (BASE 64)

☠RESPONSE ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)

	MSGCODE	O	STRING(8)	MESSAGE CODE
	MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY		M		RESPONSE PARAMETER BODY
	RESULT	M	STRING(1)	SUCCESS Y/N
	MSG	M	STRING(128)	MESSAGE
	PHOTO		STRING(2048)	CITIZEN PHOTO (BASE64)
	SIGNATURE		STRING(2048)	CITIZEN SIGNATURE (BASE64)
	NID		STRING(20)	NATIONAL ID
	NAME		STRING(50)	NAME
	BIRTHDAY		STRING(20)	BIRTHDAY
	GENDER		STRING(1)	GENDER

☠EXAMPLE :
YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING
REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP303</OPCODE>
                <CHCODE>A</CHCODE>
        </HEADER>
        <BODY>
                <NID>1194070023836062</NID>
                <PHOTO>/9J/4AAQSKZJRGABAAEAIQA
                 ....
                 HWF/WCVI+/+PVHTZ9WCUZ//2Q==
                 </PHOTO>
        </BODY>
</REQUEST>
```

- RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP303</OPCODE>
                <CHCODE>A</CHCODE>
                <MSGCODE>1001</MSGCODE>
                <MESSAGE>IT HAS BEEN SUCCESSFULLY PROCESSED. PLEASE
PRESS THE CHECK BALANCE BUTTON TO CONFIRM THE RESULTS.
                </MESSAGE>
        </HEADER>

        <BODY>
                <RESULT>Y</RESULT>
                <MSG />
                <PHOTO>
                        /9J/4AAQSKZJRGABAAEAIQAUAAD
                        ...
                        KEMXSZPEEOXYNUA3DHTY047V2ZDQDX+0CJ//2Q==
```

```
                </PHOTO>
                <SIGNATURE>
                        /9J/4AAQSKZJRGABAQEAYAB
                        ...
                        OOOOAKKKKACIIIGD//Z
                </SIGNATURE>
                <NID>1194070023836062</NID>
                <NAME>VENANTIE MUKARUTEMBYA</NAME>
                <BIRTHDAY>01/01/1940</BIRTHDAY>
                <GENDER>F</GENDER>
        </BODY>
</RESPONSE>
```

2.3.4 Request for Get company information with TIN from RRA (SVCCODE: HP00005, OPCODE: HPOP305)

- SUMMARY
  GET COMPANY INFORMATION FROM RRA WITH TIN

- TELECOMMUNICATION PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/voucher/api/external_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

- REQUEST ITEM / SCHEMA
  SEND PARAMETERS (**NAME, VALUE**) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	**M**		**REQUEST ROOT**
HEADER	**M**		**REQUEST HEADER**
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	**M**		**REQUEST PARAMETER BODY**
TIN	M	STRING(20)	TIN
REGR_ID	M	STRING(20)	REGISTER ID

- RESPONSE ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	**M**		**RESPONSE ROOT**
HEADER	**M**		**RESPONSE HEADER**
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE

	MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY		**M**		**RESPONSE PARAMETER BODY**
	MESSAGECODE	M	STRING(5)	MESSAGECODE
	MESSAGEDESCRIPTION	M	STRING(128)	MESSAGEDESCRIPTION
	SUPPLIERNAME	O	STRING(128)	SUPPLIERNAME
	EMAILADDRESS	O	STRING(128)	EMAIL ADDRESS
	PHONENUMBER	O	STRING(20)	PHONE NUMBER
	PROVINCE	O	STRING(50)	PROVINCE
	DETAILEDADDRESS	O	STRING(50)	DETAILEDADDRESS
	DISTRICT	O	STRING(50)	DISTRICT
	CATEGORY	O	STRING(50)	CATEGORY
	CELL	O	STRING(50)	CELL
	SECTOR	O	STRING(50)	SECTOR

☠EXAMPLE :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

REQUEST XML.(THE PARAMETER'S NAME IS **REQ_XML**)

- **REQUEST XML**

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP305</OPCODE>
                <CHCODE>A</CHCODE>
        </HEADER>
        <BODY>
                <TIN>999999999</TIN>
                <REGR_ID>CCBS</ REGR_ID >
        </BODY>
</REQUEST>
```

- **RESPONSE XML**

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP305</OPCODE>
                <CHCODE>A</CHCODE>
                <MSGCODE>1001</MSGCODE>
                <MESSAGE>IT HAS BEEN SUCCESSFULLY PROCESSED. PLEASE
PRESS THE CHECK BALANCE BUTTON TO CONFIRM THE RESULTS.
                </MESSAGE>
        </HEADER>

        <BODY>
                <SUPPLIERNAME>KT RWANDA NETWORKS
LTD</SUPPLIERNAME>
                <CELL>KIMIHURURA</CELL>
                <MANAGERNAMES>SANDRA RWAMUSHAIJA</MANAGERNAMES>
```

```
        <EMAILADDRESS>ROBERT.KARANGWA@KTRN.RW</EMAILADDRESS>
            <PHONENUMBER>729200100</PHONENUMBER>
            <PROVINCE>KIGALI CITY</PROVINCE>
            <DETAILEDADDRESS>5440</DETAILEDADDRESS>
            <DISTRICT>GASABO</DISTRICT>
            <MESSAGECODE>1</MESSAGECODE>
            <MESSAGEDESCRIPTION>RRA SUCCESS MESSAGE - SUPPLIER
DETAILS FOUND</MESSAGEDESCRIPTION>
            <CATEGORY>LARGE TAXPAYER</CATEGORY>
            <VILLAGE>RUGARAMA</VILLAGE>
            <SECTOR>KIMIRURA</SECTOR>
            <SUPPLIERTIN>103077243</SUPPLIERTIN>
        </BODY>
</RESPONSE>
```

2.3.5 Request for Get foreigner information with passport number from DGIE (SVCCODE: HP00005, OPCODE: HPOP306)

☠SUMMARY

GET FOREIGNER INFORMATION WITH PASSPORT NUMBER FROM DGIE

☠TELECOMMUNICATION PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/voucher/api/external_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

☠REQUEST ITEM / SCHEMA

SEND PARAMETERS (**NAME, VALUE**) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT			M/O	FORMAT	DESCRIPTION
REQUEST			**M**		**REQUEST ROOT**
	HEADER		**M**		**REQUEST HEADER**
		SVCODE	M	STRING(8)	SERVICE CODE
		OPCODE	M	STRING(8)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
	BODY		**M**		**REQUEST PARAMETER BODY**
		DOCNUMBER	M	STRING(20)	PASSPORT NUMBER
		ISSUEDBY	M	STRING(20)	ISSUED BY
		LEFTFINGER	O	STRING(4096)	LEFT FINGERPRINT
		RIGHTFINGER	O	STRING(4096)	RIGHT FINGERPRINT
		REGR_ID	M	STRING(20)	REGISTER ID

☠RESPONSE ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION

RESPONSE		**M**		**RESPONSE ROOT**
	HEADER	**M**		**RESPONSE HEADER**
	SVCODE	M	STRING(8)	SERVICE CODE
	OPCODE	M	STRING(8)	OPERATION CODE
	CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
	MSGCODE	O	STRING(8)	MESSAGE CODE
	MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
	BODY	**M**		**RESPONSE PARAMETER BODY**
	STATUS	M	STRING(1)	INTERFACE STATUS
	MESSAGE	M	STRING(128)	RESULT MESSAGE
	PERSONID	O	STRING(128)	PERSON ID FROM DGIE
	FIRSTNAME	O	STRING(128)	FIRST NAME
	LASTNAME	O	STRING(128)	LAST NAME
	DATEOFBIRTH	O	STRING(50)	DATE OF BIRTH
	DOCNUMBER	O	STRING(20)	PASSPORT NUMBER
	ISSUEDBY	O	STRING(20)	ISSUED BY
	NATIONALITY	O	STRING(20)	NATIONALITY
	EXPIRYDATE	O	STRING(20)	EXPIRY DATE
	SEX	O	STRING(20)	SEX
	PHOTO	O	STRING(2048)	PHOTO

☠EXAMPLE :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

REQUEST XML.(THE PARAMETER'S NAME IS **REQ_XML**)

- **REQUEST XML**

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP303</OPCODE>
                <CHCODE>A</CHCODE>
        </HEADER>
        <BODY>
                <DOCNUMBER>565549442</ DOCNUMBER >
                <ISSUEDBY>USA</ ISSUEDBY >
                <REGR_ID>CCBS</REGR_ID>
        </BODY>
</REQUEST>
```

- **RESPONSE XML**

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
                <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP306</OPCODE>
                <CHCODE>A</CHCODE>
                <MSGCODE>1001</MSGCODE>
```

```
            <MESSAGE>IT HAS BEEN SUCCESSFULLY PROCESSED. PLEASE
PRESS THE CHECK BALANCE BUTTON TO CONFIRM THE RESULTS.
            </MESSAGE>
      </HEADER>

      <BODY>
            <STATUS>1</STATUS>
            <PERSONID>3</PERSONID>
            <LASTNAME>ALEXANDRA VALERIA</LASTNAME>
            <FIRSTNAME>KULINKINA</FIRSTNAME>
            <TOKEN />
            <DATEOFBIRTH>1986-10-21</DATEOFBIRTH>
            <SEX>F</SEX>
            <DOCNUMBER>565549442</DOCNUMBER>
            <ISSUEDBY>USA</ISSUEDBY>
            <NATIONALITY>USA</NATIONALITY>
            <EXPIRYDATE>2027-06-12</EXPIRYDATE>
            <PHOTO />
            <MESSAGE>SUCCESS BUT NO FINGER FOUND IN
AFIS</MESSAGE>
      </BODY>
</RESPONSE>
```

2.6 Subscribe Customer Info (HPOP501~)

2.6.1 Subscribe Customer Info (SVCCODE:HP00005 , OPCODE:HPOP501)

- Summary
  FOR NEW CUSTOMER REGISTRATION
- TELECOMMUNICATION PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

- Request ITEM / SCHEMA
  SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
SO_ID	O	STRING(3)	RETAILER ID
LOGIN_ID	O	STRING(15)	LOGIN ID
ORG_ID	M	STRING(10)	ORGANIZATION ID
CUST_TP	M	STRING(2)	customer type A: Individual B: Self-Employee C: Foreigner D: Corporate

					E: Public Sector
		CUST_NM	M	STRING(50)	Customer name
		CORP_REG_NO	M	STRING(50)	Corporation number (CUST_TP: A,B,C,D Mandatory) (ENCRYPTED WITH AES, 256BIT) KEY : aes256-ktrn-key1
		BIZ_REG_NO	M	STRING(10)	Business number (CUST_TP: B,D,E mandatory)
		BIRTH_DAY	M	STRING(8)	Customer birth day (A,B,C mandatory) EX) 20180101
		EMAIL	O	STRING(30)	EMAIL
		PHONE_NUM	O	STRING(20)	PHONE NUMBER
		ADDR_DTL	M	STRING(300)	ADDRESS DETAIL

■ Response ITEM / SCHEMA

ELEMENT			M/O	FORMAT	DESCRIPTION
RESPONSE			M		RESPONSE ROOT
	HEADER		M		RESPONSE HEADER
		SVCODE	M	STRING(8)	SERVICE CODE
		OPCODE	M	STRING(8)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
		MSGCODE	O	STRING(8)	MESSAGE CODE
		MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
	BODY		M		RESPONSE PARAMETER BODY
	CUST_ID		M	STRING(10)	CUSTOMER ID
	CUST_NM		M	STRING(50)	Customer name
	BIRTH_DAY		M	STRING(8)	Customer birth day (A,B,C mandatory) EX) 20180101
	ADDR_DTL		M	STRING(300)	ADDRESS DETAIL
	EMAIL		O	STRING(30)	EMAIL
	PHONE_NUM		O	STRING(20)	PHONE NUMBER

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP501</OPCODE>
        <CHCODE>A</CHCODE>
    </HEADER>
    <BODY>
        <SO_ID>62</SO_ID>
```

```
                    <LOGIN_ID> armapoc</LOGIN_ID>
                    <ORG_ID> NZ00000221</ORG_ID>
                    <CUST_TP>A</CUST_TP>
                    <CUST_NM>DAVID</CUST_NM>
                    <CORP_REG_NO>431DFDAS1212123</CORG_REG_NO>
                    <BIRTH_DAY>20100101</BIRTH_DAY>
                    <EMAIL>KTRN@GMAIL.COM</EMAIL>
                    <PHONE_NUM>0708897789</PHONE_NUM>
                    <ADDR_DTL>NYARUTARAMA</ADDR_DTL>
        </BODY>
 </REQUEST>
```

- RESPONSE XML

```
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP501</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>1001</MSGCODE>
        <MESSAGE>…</MESSAGE>
    </HEADER>
    <BODY>
    </BODY>
</RESPONSE>
```

2.6.2 Searching Customer Info (SVCCODE : HP00005, OPCODE : HPOP502)

■ Summary

FOR SERCHING CUSTOMER INFOMATION

■ TELECOMMUNICATION PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
SO_ID	M	STRING(4)	RETAILER ID
CUST_TP	M	STRING(2)	customer type A: Individual B: Self-Employee C: Foreigner D: Corporate E: Public Sector
CUST_NM	M	STRING(50)	Customer name

		CORP_REG_NO	M	STRING(50)	Corporation number (CUST_TP: A,B,C,D Mandatory) If the customer type is 'E', send it the Business number. (ENCRYPTED WITH AES, 256BIT) KEY : aes256-ktrn-key1

■ Response ITEM / SCHEMA

ELEMENT			M/O	FORMAT	DESCRIPTION
RESPONSE			M		RESPONSE ROOT
	HEADER		M		RESPONSE HEADER
		SVCODE	M	STRING(8)	SERVICE CODE
		OPCODE	M	STRING(8)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
		MSGCODE	O	STRING(8)	MESSAGE CODE
		MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
	BODY		M		RESPONSE PARAMETER BODY
		CUST_ID	M	STRING(10)	CUSTOMER ID
		CUST_NM	M	STRING(50)	CUSTOMER NAME

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING

REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
        <HEADER>
                <SVCODE>HP00005</SVCODE>
                <OPCODE>HPOP502</OPCODE>
                <CHCODE>A</CHCODE>
        </HEADER>
        <BODY>
                <SO_ID>02</SO_ID>
                <CUST_TP>A</CUST_TP>
                <CUST_NM>DAVID</CUST_NM>
                <CORP_REG_NO>01SD3152=2QWSDF</CORP_REG_NO>
        </BODY>
</REQUEST>
```

- RESPONSE XML

```
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP501</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>1001</MSGCODE>
```

```
        <MESSAGE>…</MESSAGE>
    </HEADER>
    <BODY>
        <CUST_ID>C000111222</CUST_ID>
        <CUST_NM>DAVID</CUST_NM>
    </BODY>
</RESPONSE>
```

2.7 Searching MSISDN (HPOP601~)

2.7.1 Checking MSISDN status (svccode: HP00005, opcode: HPOP601)

■ Summary
- YOU CAN BE SEARCHING MSISDN STATUS.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA
SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY
MSISDN	M	STRING(10)	MSISDN (CUSTMER PHONE NUMBER)
SO_ID	M	STRING(3)	RETAILER CODE

■ Response ITEM / SCHEMA

ELEMENT	M/O	FORMAT	DESCRIPTION
RESPONSE	M		RESPONSE ROOT
HEADER	M		RESPONSE HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
MSGCODE	O	STRING(8)	MESSAGE CODE
MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
BODY	M		RESPONSE PARAMETER BODY

		RESULT	M	STRING(1)	Y : AVAILABLE N : NOT AVAILABLE

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
 <HEADER>
   <SVCODE>HP00005</SVCODE>
   <OPCODE>HPOP601</OPCODE>
   <CHCODE>A</CHCODE>
 </HEADER>
 <BODY>
      <MSISDN>0771000050</MSISDN>
      <SO_ID>62</SO_ID>
</BODY>
</REQUEST>
```

- RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP601</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>1001</MSGCODE>
        <MESSAGE>IT HAS BEEN SUCCESSFULLY PROCESSED.</MESSAGE>
    </HEADER>
    <BODY>
        <RESULT>Y</RESULT>
    </BODY>
</RESPONSE>
```

2.7.2 Recommend 5 MSISDNS (svccode: HP00005, opcode: HPOP602)

■ Summary

■ YOU CAN GET RECOMMENDED 5 MSISDNS WITHIN SPECIFIC ISP.

■ Telecommunication PROTOCOL FOR REQUEST

REQUEST URI	http://www.4glte.rw/api_access.jsp		
PROTOCOL TYPE	HTTP	METHOD	POST
PORT	80	CONTENTS TYPE	APPLICATION/XML
I/F CYCLE	EVERY REQUEST TIME		

■ Request ITEM / SCHEMA

SEND PARAMETERS (NAME, VALUE) : (REQ_XML, XML COMPRISING THE FOLLOWING ELEMENTS)

ELEMENT	M/O	FORMAT	DESCRIPTION
REQUEST	M		REQUEST ROOT
HEADER	M		REQUEST HEADER
SVCCODE	M	STRING(8)	SERVICE CODE
OPCODE	M	STRING(8)	OPERATION CODE
CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
BODY	M		REQUEST PARAMETER BODY

		SO_ID	M	STRING(3)	RETAILER ID

■ Response ITEM / SCHEMA

ELEMENT			M/O	FORMAT	DESCRIPTION
RESPONSE			M		RESPONSE ROOT
	HEADER		M		RESPONSE HEADER
		SVCCODE	M	STRING(8)	SERVICE CODE
		OPCODE	M	STRING(8)	OPERATION CODE
		CHCODE	M	STRING(2)	INCOMING CHANNEL (DEFAULT : A)
		MSGCODE	O	STRING(8)	MESSAGE CODE
		MESSAGE	O	STRING(32)	MESSAGE DESCRIPTION
	BODY		M		RESPONSE PARAMETER BODY
		MSISDN	M	STRING(512)	RECOMMENDED 5 MSISDN LIST

■ Example :

YOU SHOULD SEND THE PARAMETER THAT IS SET TO THE STRING IS CONTAINING THE FOLLOWING
REQUEST XML.(THE PARAMETER'S NAME IS REQ_XML)

- REQUEST XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<REQUEST>
 <HEADER>
   <SVCODE>HP00005</SVCODE>
   <OPCODE>HPOP602</OPCODE>
   <CHCODE>A</CHCODE>
 </HEADER>
 <BODY>
      <SO_ID>03</SO_ID>
</BODY>
</REQUEST>
```

- RESPONSE XML

```
<?XML VERSION="1.0" ENCODING="UTF-8"?>
<RESPONSE>
    <HEADER>
        <SVCODE>HP00005</SVCODE>
        <OPCODE>HPOP602</OPCODE>
        <CHCODE>A</CHCODE>
        <MSGCODE>XXXX</MSGCODE>
        <MESSAGE>….</MESSAGE>
    </HEADER>
    <BODY>
        <MSISDN >
            0770111111,0770111112,0770111113,0770111114,0770111115
        </MSISDN>
    </BODY>
</RESPONSE>
```