

This document provides additional assistance with wiring your Extron IP Link Pro Control Processor to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific IP Link Pro Control Processor or the documentation supplied by the manufacturer of the controlled device.

For more information on using Global Scriptor Modules, refer to the "[Guide to Using Scriptor Modules](#)" document.

Device Specifications

Device Type: Blu-ray
Manufacturer: TASCAM
Firmware Version: N/A
Model(s): BD-MP1

Tested on the Following Software and Firmware Versions

IP Link Pro Control Processor Firmware	Global Scriptor Version
3.17.0000-b002	2.21.0.5

Version History

Module Version	Date	Notes
1_2_0_0	2/21/2024	Initial Version

Module Notes

- A command pacing of 0.3 seconds is required between all commands.

Supported Classes and Examples

SerialClass
InterfaceName = ModuleName.SerialClass(ProcessorName, 'COM1', Model='BD-MP1')
SerialOverEthernetClass
InterfaceName = ModuleName.SerialOverEthernetClass('192.168.254.254', 2001, Model='BD-MP1')
EthernetClass
InterfaceName = ModuleName.EthernetClass('192.168.254.254', 9030, Model='BD-MP1')

Control Commands

Format with Qualifier:

```
InterfaceName.Set(Command, Value, {'Qualifier Key': 'Qualifier Value'})
```

Format without Qualifier:

```
InterfaceName.Set(Command, Value)
```

Command DiscTray	Value 'Open'	Value 'Close'	
# DiscTray example InterfaceName.Set('DiscTray', 'Open')			
Command Keypad	Value '0' – '9'		
# Keypad example InterfaceName.Set('Keypad', '0')			
Command MenuControl	Value 'Setup Menu' 'Pop Up Menu' 'Enter' 'Right'	Value 'Top Menu' 'Display/Info' 'Home' 'Up'	Value 'Option Menu' 'Return' 'Left' 'Down'
# MenuControl example InterfaceName.Set('MenuControl', 'Setup Menu')			
Command Mute	Value 'On'	Value 'Off'	
# Mute example InterfaceName.Set('Mute', 'On')			
Command OSD	Value 'On'	Value 'Off'	
# OSD example InterfaceName.Set('OSD', 'On')			
Command Power ¹	Value 'On'	Value 'Off'	
# Power example InterfaceName.Set('Power', 'On')			
Command PowerOff ²	Value None		
# PowerOff example InterfaceName.Set('PowerOff', None)			
Command Scan	Value 'Forward'	Value 'Reverse'	
Qualifier Key 'Speed'	Qualifier Value 'Fast'	Qualifier Value 'Slow'	
# Scan example InterfaceName.Set('Scan', 'Forward', {'Speed': 'Fast'})			
Command Subtitle	Value None		
# Subtitle example InterfaceName.Set('Subtitle', None)			

Command	Value	Value	Value
Transport	'Stop'	'Play'	'Pause'
	'Chapter Jump Next'	'Chapter Jump Previous'	'Title Jump Next'
	'Title Jump Previous'		
# Transport example InterfaceName.Set('Transport', 'Stop')			

¹ Only supported for Serial control.

² Only supported for Ethernet control.

Cable and Adapter Requirements

Captive Screw to Male DB9 RS-232 Serial Cable

Notes for the Device

Serial communication

Port Type: RS-232

Baud Rate: 115200


Data Bits: 8

Parity: None


Stop Bits: One

Flow Control: None

Pin Assignments Diagram



Signal	Main Cable	Pin	Signal
TxD		2	TxD
RxD		3	RxD
GND		5	GND



Network communication

When configuring the Ethernet module, be sure device settings match those of the Global Scriptor ethernet interface.

Port Type: Ethernet (TCP)

Default Port: 9030

Logon Credentials Supported: No

Multi-Connection Capabilities: No

Port Changeability: No

Ethernet Module Configuration Description

Please refer to user manual for settings and changes to the network communication

Notes for the Device

- When the device is powered off, the TCP port closes. Because of this, Power On and module status are not supported for Ethernet. To turn the device back on, please use Wake-on-LAN along with this module.

Appendix A. Set Commands

Disc Tray Close	!70PCCL\x0D
Disc Tray Open	!70PCOP\x0D
Keypad 0	!7NUM0\x0D
Keypad 9	!7NUM9\x0D
Menu Control Display/Info	!7DSP\x0D
Menu Control Down	!7OSD4\x0D
Menu Control Enter	!7ENT\x0D
Menu Control Home	!7HOM\x0D
Menu Control Left	!7OSD1\x0D
Menu Control Option Menu	!7OMN\x0D
Menu Control Pop Up Menu	!7PMN\x0D
Menu Control Return	!7RET\x0D
Menu Control Right	!7OSD2\x0D
Menu Control Setup Menu	!7SMN\x0D
Menu Control Top Menu	!7TMN\x0D
Menu Control Up	!7OSD3\x0D
Mute Off	!7MUT01\x0D
Mute On	!7MUT00\x0D
OSD Off	!7OSD01\x0D
OSD On	!7OSD00\x0D
Power Off	!7PWR00\x0D
Power Off None	!7PWR00\x0D
Power On	!7PWR01\x0D
Scan Forward Speed Fast	!7SCNFF\x0D
Scan Forward Speed Slow	!7SCNFS\x0D
Scan Reverse Speed Fast	!7SCNRF\x0D
Scan Reverse Speed Slow	!7SCNRS\x0D
Subtitle None	!7SBT1\x0D
Transport Chapter Jump Next	!7SKPNX\x0D
Transport Chapter Jump Previous	!7SKPPV\x0D
Transport Pause	!7PAS\x0D
Transport Play	!7PLY\x0D
Transport Stop	!7STP\x0D
Transport Title Jump Next	!7GSKNX\x0D
Transport Title Jump Previous	!7GSKPV\x0D