4.18 N4 — Geographic Location

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ ├ **0310** — Loop 0310	1 .. 1		070		
│ │ ├ **N4** — Geographic Location	0 .. 1		100		
│ │ │ ├ **19** — City Name	0 .. 1	String	01	2 .. 30	
│ │ │ ├ **156** — State or Province Code	0 .. 1	Token	02	2 .. 2	
│ │ │ ├ **116** — Postal Code	0 .. 1	Token	03	3 .. 15	
│ │ │ └ **26** — Country Code	0 .. 1	Token	04	2 .. 3	ISO_3166-1

Documentation

Definition To specify the geographic place of the named party

Properties

Identifier N4

Name Geographic Location

Cardinality min: 0 max: 1

Syntax Type Related

External Category Segment

Position 100

Level 4

Notes

Leaf Elements

Identifier/Name	Description/Notes/Code Values	Properties
19 City Name	Free-form text for city name	**Cardinality** min: 0 max: 1 **Primitive Type** String **Length** min: 2 max: 30 **External Category** Simple Data Element **Data Type** AN **Position** 01
156 State or Province Code	Code (Standard State/Province) as defined by appropriate government agency **Constraint 1** Sent only if city name (N401) is in the U.S. or Canada.	**Cardinality** min: 0 max: 1 **Primitive Type** Token **Length** min: 2 max: 2 **External Category** Simple Data Element **Data Type** ID **Position** 02
116 Postal Code	Code defining international postal zone code excluding punctuation and blanks (zip code for United States)	**Cardinality** min: 0 max: 1 **Primitive Type** Token **Length** min: 3 max: 15 **External Category** Simple Data Element **Data Type** ID **Position** 03
26 Country Code	Code identifying the country **Selected Values** All Values in Codelist	**Cardinality** min: 0 max: 1 **Primitive Type** Token **Length** min: 2 max: 3 **External Category** Simple Data Element **Data Type** ID **Position** 04 **Codelist Id** ISO_3166-1

		Type System ISO_CodelistsAndSchemes **Version Mode** Latest **Version** 2013

4.19 G61 [365 = “TE”] — Contact - Telephone

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ ├ **0310** — Loop 0310	1 .. 1		070		
│ │ ├ **G61** — Contact - Telephone	0 .. 1		120		
│ │ │ ├ **366** — Contact Function Code	1 .. 1	Token	01	2 .. 2	366
│ │ │ ├ **93** — Name - Shipper Contact	1 .. 1	String	02	1 .. 60	
│ │ │ ├ **365** — Communication Number Qualifier	1 .. 1	Token	03	2 .. 2	365
│ │ │ └ **364** — Communication Number	1 .. 1	String	04	1 .. 80	

Documentation

Definition To identify a person or office to whom communications should be directed

Properties

Identifier G61

Name Contact - Telephone

Cardinality min: 0 max: 1

Syntax Type Related

External Category Segment

Position 120

Level 4

Notes

Comment 1 G6103 qualifies G6104.

Leaf Elements

Identifier/Name	Description/Notes/Code Values	Properties
366 Contact Function Code	Code identifying the major duty or responsibility of the person or group named **Selected Values** **Code** SH **Name** Shipper Contact	**Cardinality** min: 1 max: 1 **Primitive Type** Token **Length** min: 2 max: 2 **External Category** Simple Data Element **Data Type** ID **Position** 01 **Codelist Id** 366 **Type System** ASC_X12 **Version Mode** Current **Version** 004010
93 [366 = “SH”] Name - Shipper Contact	Free-form name	**Cardinality** min: 1 max: 1 **Primitive Type** String **Length** min: 1 max: 60 **External Category** Simple Data Element **Data Type** AN **Position** 02
365 Communication Number Qualifier	Code identifying the type of communication number **Selected Values** **Code** TE **Name** Telephone	**Cardinality** min: 1 max: 1 **Primitive Type** Token **Length** min: 2 max: 2 **External Category** Simple Data Element **Data Type** ID **Position** 03 **Codelist Id** 365 **Type System** ASC_X12 **Version Mode** Current

		Version 004010
364 Communication Number	Complete communications number including country or area code when applicable	**Cardinality** **min:** 1 **max:** 1 **Primitive Type** String **Length** **min:** 1 **max:** 80 **External Category** Simple Data Element **Data Type** AN **Position** 04

4.20 G61 [365 = “EM”] — Contact - Electronic Mail

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ ├ **0310** — Loop 0310	1 .. 1		070		
│ │ └ **G61** — Contact - Electronic Mail	0 .. 1		120		
│ │ ├ **366** — Contact Function Code	1 .. 1	Token	01	2 .. 2	366
│ │ ├ **93** — Name - Shipper Contact	1 .. 1	String	02	1 .. 60	
│ │ ├ **365** — Communication Number Qualifier	1 .. 1	Token	03	2 .. 2	365
│ │ └ **364** — Communication Number	1 .. 1	String	04	1 .. 80	

Documentation

Definition To identify a person or office to whom communications should be directed

Properties

Identifier G61

Name Contact - Electronic Mail

Cardinality min: 0 max: 1

Syntax Type Related

External Category Segment

Position 120

Level 4

Notes

Comment 1 G6103 qualifies G6104.

Leaf Elements

Identifier/Name	Description/Notes/Code Values	Properties
366 Contact Function Code	Code identifying the major duty or responsibility of the person or group named **Selected Values** **Code** SH **Name** Shipper Contact	**Cardinality** min: 1 max: 1 **Primitive Type** Token **Length** min: 2 max: 2 **External Category** Simple Data Element **Data Type** ID **Position** 01 **Codelist Id** 366 **Type System** ASC_X12 **Version Mode** Current **Version** 004010
93 [366 = “SH”] Name - Shipper Contact	Free-form name	**Cardinality** min: 1 max: 1 **Primitive Type** String **Length** min: 1 max: 60 **External Category** Simple Data Element **Data Type** AN **Position** 02
365 Communication Number Qualifier	Code identifying the type of communication number **Selected Values** **Code** EM **Name** Electronic Mail	**Cardinality** min: 1 max: 1 **Primitive Type** Token **Length** min: 2 max: 2 **External Category** Simple Data Element **Data Type** ID **Position** 03 **Codelist Id** 365 **Type System** ASC_X12 **Version Mode** Current

		Version 004010
364 Communication Number	Complete communications number including country or area code when applicable	**Cardinality** **min:** 1 **max:** 1 **Primitive Type** String **Length** **min:** 1 **max:** 80 **External Category** Simple Data Element **Data Type** AN **Position** 04

4.21 0350 — Loop 0350

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ └ **0350** — Loop 0350	0 .. 999		150		
│ ├ **OID** — Order Identification Detail	1 .. 1		150		
│ └ **0360** — Loop 0360	0 .. 99		190		

Properties

Identifier 0350

Name Loop 0350

Cardinality min: 0 max: 999

Syntax Type Related

External Category Loop

Position 150

Level 3

4.22 OID — Order Identification Detail

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ └ **0350** — Loop 0350	0 .. 999		150		
│ ├ **OID** — Order Identification Detail	1 .. 1		150		
│ │ ├ **127** — Reference Identification	0 .. 1	String	01	1 .. 30	
│ │ └ **324** — Purchase Order Number	0 .. 1	String	02	1 .. 22	

Documentation

Definition To specify order identification detail

Properties

Identifier OID

Name Order Identification Detail

Cardinality min: 1 max: 1

Syntax Type Related

External Category Segment

Position 150

Level 4

Notes

Usage 1 OID01 is the seller's order identification number.

Usage 2 OID03 is the number assigned by the consignee to further define the purchase order number.

Constraint 1 R0102 Required - At least one of those noted must be used

Constraint 2 C0302 Conditional - If the first element is present, then the others must be present

Constraint 3 P0405 Paired Multiple - If any are used, all must be used

Constraint 4 P0607 Paired Multiple - If any are used, all must be used

Constraint 5 P0809 Paired Multiple - If any are used, all must be used

Leaf Elements

Identifier/Name	Description/Notes/Code Values	Properties
127 Reference Identification	Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier	**Cardinality** min: 0 max: 1 **Primitive Type** String **Length** min: 1 max: 30 **External Category** Simple Data Element **Data Type** AN **Position** 01
324 Purchase Order Number	Identifying number for Purchase Order assigned by the orderer/purchaser	**Cardinality** min: 0 max: 1 **Primitive Type** String **Length** min: 1 max: 22 **External Category** Simple Data Element **Data Type** AN **Position** 02

4.23 0360 — Loop 0360

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ └ **0350** — Loop 0350	0 .. 999		150		
│ └ **0360** — Loop 0360	0 .. 99		190		
│ ├ **L5** — Description, Marks and Numbers	1 .. 1		190		
│ ├ **AT8** — Shipment Weight, Packaging and Quantity Data	0 .. 1		195		
│ └ **0365** — Loop 0365	0 .. 99		200		

Properties

Identifier 0360

Name Loop 0360

Cardinality min: 0 max: 99

Syntax Type Related

External Category Loop

Position 190

Level 4

4.24 L5 — Description, Marks and Numbers

Structure

Node	Card.	Prim.Type	Pos.	Length	Codelists
204 — Motor Carrier Load Tender	1 .. 1				
├ **0300** — Loop 0300 - Complete or Others	2 .. 999		010		
│ └ **0350** — Loop 0350	0 .. 999		150		
│ └ **0360** — Loop 0360	0 .. 99		190		
│ ├ **L5** — Description, Marks and Numbers	1 .. 1		190		
│ │ ├ **213** — Lading Line Item Number	0 .. 1	Integer	01	1 .. 3	
│ │ ├ **79** — Lading Description	0 .. 1	String	02	1 .. 50	
│ │ └ **103** — Packaging Code	0 .. 1	String	05	3 .. 5	103

Documentation

Definition To specify the line item in terms of description, quantity, packaging, and marks and numbers

Properties

Identifier L5

Name Description, Marks and Numbers

Cardinality min: 1 max: 1

Syntax Type Related

External Category Segment

Position 190

Level 5

Notes

Constraint 1 P0304 Paired Multiple - If any are used, all must be used

Constraint 2 C0706 Conditional - If the first element is present, then the others must be present

Constraint 3 P0809 Paired Multiple - If any are used, all must be used

Comment 1 L502 may be used to send quantity information as part of the product description.

Leaf Elements

Identifier/Name	Description/Notes/Code Values	Properties
213 Lading Line Item Number	Sequential line number for a lading item	**Cardinality** min: 0 max: 1 **Primitive Type** Integer **Length** min: 1 max: 3 **Fraction Digits** 0 **Total Digits** 3 **External Category** Simple Data Element **Data Type** N0 **Position** 01
79 Lading Description	Description of an item as required for rating and billing purposes **Tech. Info. 1** The following characters, which are used in ANSI X12 as delimiter characters, are replaced by spaces in the lading description (data element 79): Asterisk * Tilde ~ Double quote “	**Cardinality** min: 0 max: 1 **Primitive Type** String **Length** min: 1 max: 50 **External Category** Simple Data Element **Data Type** AN **Position** 02
103 Packaging Code	Code identifying the type of packaging; Part 1: Packaging Form, Part 2: Packaging Material; if the Data Element is used, then Part 1 is always required	**Cardinality** min: 0 max: 1 **Primitive Type** String **Length** min: 3 max: 5 **External Category** Simple Data Element