



R U N T I M E

LIVE MACHINE

PRO

v 1.15.33

*On Air. **In Control.***

U S E R M A N U A L

Second Edition · Version 1.15.33 · English

ECOSYSTEM.RUNTIME · SIMONE PIZZÌ · 2026





REAL-TIME AUDIO SHOW-CONTROL SYSTEM

Runtime Live Machine **Pro**

v1.15.33

User Manual

Simone Pizzi

Second Edition · 2026

Aligned with version 1.15.33



Runtime Live Machine Pro — User Manual

Second Edition · 2026 · Aligned with version 1.15.33

© 2026 Simone Pizzi (Runtime Radio)

Free software, released under the MIT licence.

This manual is part of the project and follows its licence: it may be copied, modified and redistributed freely, provided the copyright notice and the text of the MIT licence are kept.

Runtime Live Machine Pro is a Runtime Radio project. Trademarks mentioned belong to their respective owners.

Software designed and developed by SIMONE PIZZI with the help of large language models: Gemini 3.0 and 3.1; Claude Sonnet 4.6, Opus 4.7, Opus 4.8, Sonnet 5, Opus 5 and Fable 5. Source code: github.com/Pitz72/RRLMP. Typeset with Typst; headings in Sora, body in Inter, code in Source Code Pro.

Contents

Runtime Live Machine Pro: a philosophy	6
1.1 Who it was built for	6
1.2 The “Single Show” philosophy	7
1.3 The Main-Side-Heavy architecture	7
1.4 The broadcast grid: a visual grammar	7
1.5 Current version and updates	8
Installation and first launch	9
2.1 System requirements	9
2.2 Installation on Windows	9
2.3 macOS: building from source	10
2.4 Installation on Linux	10
2.5 The welcome screen	11
2.6 The first launch: what to expect	12
The working interface	13
3.1 The Control Bar (Header)	13
3.2 The ON AIR banner	14
3.3 The six-column grid	15
3.4 The audio card (Clip)	16
The basic workflow: load and play	18
4.1 Importing the audio files	18
4.2 Playback: starting and stopping clips	19
4.3 Organizing the running order	19
4.4 Structure cues: INTRO and OUTRO	20
Clip properties and the Waveform Editor	21
5.1 Basic properties	21
5.2 The waveform editor	22
5.3 Behaviours and automation	23
5.4 Fades (Fade In and Fade Out)	24
5.5 Assigning controls	24
The mixing engine	25
6.1 The audio hierarchy	25
6.2 Automatic ducking	25
6.3 Music Dominance: intelligent management of beds	26
6.4 Rising above the hierarchy: effects and voices	26
6.5 Volume levelling (loudness)	26
6.6 Master Chain: the processor chain on the master bus	27
The Pad FX and the Automix view	28
7.1 The pad FX: the jingle machine	28
7.2 The Automix view	29
Hardware, keyboard and MIDI	31
8.1 Audio routing	31
8.2 Keyboard control	31
8.3 MIDI controllers	32

Session recording	34
9.1 Starting the recording	34
9.2 Stopping the recording and choosing the format	34
9.3 Practical considerations	35
Project management and data safety	36
10.1 The project file (.Imp)	36
10.2 Saving	36
10.3 Auto-Backup and autosave	37
10.4 Export project with audio	37
Remote Control	39
11.1 How it works	39
11.2 Activation	39
11.3 Connecting from the remote device	39
11.4 What you control remotely	40
11.5 Security and limits	40
Updates	41
12.1 The startup check	41
12.2 The update window	41
12.3 The “never during a live show” rule	41
12.4 Platform differences	42
Advanced features	43
13.1 NoteBoard: the script in the control room	43
13.2 Column colour customization	43
13.3 Transitions between clips	43
13.4 The General Settings window	44
13.5 Playout Log	45
13.6 Undo and Redo	45
13.7 Toast notification system	45
Troubleshooting and FAQ	46
14.1 Audio problems	46
14.2 Red clips and missing files	46
14.3 MIDI problems	47
14.4 Startup problems	47
14.5 Frequently asked questions	47

CHAPTER 1

Runtime Live Machine Pro: a philosophy

Author's note

Fifteen years of open microphones leave a distinct mark on anyone who has lived through them. I have run podcasts, hosted talk shows, kept a web radio on the air, and for much of that time I did everything alone: the running order, the music, the interviews, the levels, the timing. I know what it feels like to realize, live, that the song is about to end while you are still shaping the thought you want to express. I know what it means to pull down a fader with one hand and find the right clip with the other, while the third hand — the one you don't have — is supposed to hold the thread of what you are saying.

Runtime Live Machine Pro grew out of that frustration, and out of a simple conviction: audio production shouldn't be a job in its own right. It should be transparent. The presenter, the podcaster, the content creator hosting a late-night talk show alone, with no engineer to lean on, needs to concentrate on what they do best: talking, thinking, holding a rapport with the listener. The software takes care of the rest.

I built into RLMP the rules a good sound director applies automatically: the hierarchy between audio events, the ducking that kicks in when you speak, the music that stops and resumes at the right moment. Complex rules, hidden beneath an interface that asks for a single gesture: clicking the right clip at the right time.

This software is designed above all for people running small and mid-sized talk radio, for anyone producing podcasts with professional ambition, for anyone streaming live without a technical crew around them. That said, it isn't exclusive by nature: people working in more structured settings will find tools suited to their needs too. The goal is single-minded: to make the presenter independent of the support roles that aren't always there, and aren't always needed.

Every tool is born from an answer. Runtime Live Machine Pro answers a precise problem: live audio production (radio, podcasts, events, theatre) is a performance activity, not an automation task. It demands instant control, steady nerves and software that won't betray you at the wrong moment. The software installed on your computer is not a 24/7 music scheduler, nor a DAW for post-production, nor a simple player with a queue. It is a **real-time broadcast machine**, built around the idea that every show is a one-off, unrepeatable act that deserves a dedicated container and precise control over every transition.

1.1 Who it was built for

Runtime Live Machine Pro is aimed at two kinds of users who, despite their different contexts, share the same fundamental need.

The **broadcast professional** — the director of a commercial radio station, the engineer of an audio or video live stream, the presenter running their own show — will find in RLMP a system on a par

with high-end professional tools, with an operational agility those systems often sacrifice on the altar of complexity.

The **content creator** — the independent podcaster, the web-radio host, the live-event organizer — will find a tool that doesn't take years of technical training to master, yet makes no compromises on the quality of the result.

Both get an interface that responds to the key instantly, a stable audio engine, and a save system that doesn't forget.

1.2 The “Single Show” philosophy

The founding concept of Runtime Live Machine Pro is the **isolated project**. Every show you produce — a podcast episode, a live radio broadcast, a theatre performance — lives in a self-contained `.lmp` file that holds everything: the clip layout, the volumes, the MIDI mappings, the cue points, the production notes. When you load that file, you find the show exactly as you left it.

This approach has concrete consequences. You don't have to reconfigure the software every time you move from one show to another. You can carry a project to any computer through the Export project with audio feature and know it will work. You can archive past episodes and reopen them months later without surprises.

The `.lmp` file doesn't contain the physical audio files: it stores their paths on disk. To move a project between computers, the **Export project with audio** feature physically copies everything needed into a self-contained folder.

1.3 The Main-Side-Heavy architecture

Understanding the internal architecture isn't essential to using the software, but it helps explain why certain problems common to other players don't occur here.

Runtime Live Machine Pro is built on **Electron**, a platform that cleanly separates the main process (Main Process, in Node.js) from the interface rendering process (Renderer Process). This separation is used deliberately.

All the heavy operations — audio decoding via FFmpeg, reading files from disk, analysing waveforms, managing backups — are delegated to the Main Process. The Renderer deals solely with the interface: displaying clips, animating the VU meters, responding to clicks. The result is an interface that stays fluid even during intensive operations, and an audio engine that doesn't compete for resources with the pixels on screen.

The custom `media://` protocol keeps audio files from ever being loaded entirely into RAM: they stream straight from disk to the player. You can handle uncompressed WAV files hours long without the application's memory footprint changing appreciably.

1.4 The broadcast grid: a visual grammar

RLMP's operating interface is organized into vertical columns, each with a precise semantic role. Before you even launch the software, it's worth fixing this grammar in mind.

Six columns are visible in the main grid. A seventh surface, the **pad FX** (the effects jingle machine), lives outside the grid, in a dedicated panel described in Chapter 7.

Column	Colour	Function
Show Assets	Green	Idents, beds, structural backing tracks for the show
Jingle	Amber	Recurring identifying jingles and stingers
Promo	Cyan	Promos, self-promotion, scheduled announcements
Episode Songs	Red	The music playlist
Voice / Recordings	Orange	Interviews, voice messages, spoken segments
Pre-Show	Purple	Warm-up music before going live, with jingle and promo rotation

The first three columns (Show Assets, Jingle and Promo) share the same audio nature: they are structural and service elements, treated identically by the mixing engine. The distinction is organizational: keeping idents separate from jingles and promos keeps the running order readable even when it's crowded.

Each column has distinct audio behaviours — mixing priority, exclusion rules, fade values — detailed in Chapter 6. For now it's enough to know that a clip's position in the grid is not decorative: it determines how the software will treat it on air. Columns you don't need can be hidden from view (Settings → General → Broadcast layout) without losing the clips they contain.

1.5 Current version and updates

This manual describes version **1.15.33** of Runtime Live Machine Pro. At startup, the software silently checks whether a newer version is available and, if it finds one, opens an update notice, never during a live show. The update system is described in Chapter 12. The `.lmp` project files are compatible with later versions: updating the software doesn't entail losing or manually migrating existing projects.

CHAPTER 2

Installation and first launch

Installing Runtime Live Machine Pro is designed to require the least possible interaction: a few clicks, no manual configuration, no prerequisites to install separately. The audio engine (FFmpeg) is bundled into the installation package and requires nothing from you.

2.1 System requirements

Before proceeding, check that your computer meets the minimum requirements. The recommended specifications ensure the best experience during long sessions or with many clips loaded at once.

	Minimum	Recommended
Operating system (Windows)	Windows 10 64-bit	Windows 11 64-bit
Operating system (macOS)	macOS 11 Big Sur, building from source	macOS 13 Ventura or later
Operating system (Linux)	Ubuntu 20.04 / Debian 11	Ubuntu 22.04 LTS
RAM	4 GB	8 GB or more
Disk space	300 MB (application)	1 GB + space for audio files
CPU	Any modern dual-core	Quad-core or better

Ready-made packages are available for Windows and Linux. There is no official installer for macOS: the program is built from source (section 2.3).

A dedicated sound card is not required: RLMP works with any audio device recognized by the operating system, from the built-in sound card up to professional USB mixers such as the Rødecaster Pro or the RØDECaster Duo.

2.2 Installation on Windows

1. Download the file [Runtime-Live-Machine-Pro-1.15.33.exe](https://github.com/Pitz72/RLMP/releases) from the project's **Releases** page on GitHub (github.com/Pitz72/RLMP/releases).
2. Double-click the executable. The NSIS installer starts and copies the files to the appropriate directories.
3. When it finishes, a shortcut is created on the Desktop and in the Start menu.
4. The application launches automatically once installation is complete.

A note on Windows SmartScreen. The installers are not signed with a commercial certificate, so SmartScreen doesn't recognize them automatically. If the warning "Windows protected your PC" appears, click More info and then Run anyway. The software is free of malware; the official installers are published exclusively on the project's Releases page, and the source code is public.

2.3 macOS: building from source

There is no official installer for macOS. Runtime Live Machine Pro is free software: if you have a Mac, you can download the source code and build the program on your own computer.

1. Install **Node.js 20** (and git, if you want to clone the repository).
2. Download the code from github.com/Pitz72/RRLMP, with the Code button or with `git clone`.
3. In the project folder run, in order: `npm ci`, `npm run build:main`, `npm run build:preload`, `npx vite build` and `npx electron-builder --mac --publish never`.
4. The `.dmg` file is in the `builds/` folder: open it and drag the application into Applications.

A package built this way is not signed: on first launch macOS shows a Gatekeeper warning. Right-click the application and choose Open, or allow it from System Settings → Privacy & Security, in the Security section. Always up-to-date instructions are in the project's `CONTRIBUTING.md` file.

NOTE

An application you build yourself reports new versions but can't install them: to update, download the updated code and build again (Chapter 12). `.lmp` projects stay compatible.

2.4 Installation on Linux

Two distribution formats are available:

- **AppImage** — a portable executable, no installation required. Make the file executable (`chmod +x`) and launch it directly.
- **.deb package** — for Debian/Ubuntu/Mint distributions. Install with `sudo dpkg -i filename.deb` or open it with the graphical package manager.

On some distributions you may need to install the `libasound2` package for ALSA audio support. Consult your distribution's documentation if the application won't start.

2.5 The welcome screen




Figure 2.1 — The welcome screen: software identity, update status, main actions and the language drop-down in the top-right corner.

On first launch — and at every subsequent launch, until you open a project — RLMP presents the **welcome screen**, the gateway to all preliminary operations. In the centre you find the software identity and actions; in the top-right corner, the language drop-down.

Identity and actions. The software logo (the bars of a VU meter with the play symbol) identifies the Pro edition. Below the title and slogan is the installed version number, accompanied by the status of the update system:

- **“Latest Version”** (green) — you are running the most recent version available.
- **“Update Available”** (amber, flashing) — this is a button: click it to open the update window (Chapter 12).
- **“OFFLINE”** (dim red) — the update service could not be reached; the software works all the same.

Below that are the main actions:

- **New Project** — creates an empty session with the columns ready to load.
- **Load Project** — opens an existing `.lmp` file. Before making it operational, RLMP runs an **integrity check**: it verifies that every referenced audio file still exists at the stored path. Missing files are flagged immediately with a red border on their clip.
- **User Manual** — opens this manual as a PDF in the browser, in the interface language (English or Italian). An internet connection is required.
- **Quick Guide** — a short getting-started guide that opens inside the software and can be read offline too.

Language (top-right corner). RLMP supports two interface languages: English and Italian. The drop-down in the top-right corner shows the flag and name of the active language: click it and pick the other one. The selection takes effect immediately and is remembered from one session to the next.

2.6 The first launch: what to expect

When you first open a project, you'll notice in the header the logo with the **PRO** badge and its iridescent gradient. Behind the interface, opening the project starts the audio engine in the background: FFmpeg is initialized and the `media://` streaming protocol begins listening, ready to serve files from disk without loading them into memory.

The software starts preferably in full-screen mode. If the window opens resized, press `F11` (Windows/Linux) or `Ctrl+Cmd+F` (macOS) to bring it full screen — the ideal condition for production work.

The **On Air timer** in the header stays at `--:--:--` until the first clip of the session is launched. From that moment it starts counting the time elapsed on air: a useful reference for anyone working with fixed-time running orders.

CHAPTER 3

The working interface

The Runtime Live Machine Pro interface is built for the most demanding operating context: the live show. Every visual choice answers a functional requirement. The dark theme, the high contrast, the size of the controls: this is ergonomics, not aesthetics for their own sake.

When you open a project, the screen divides into three bands: the **Control Bar** at the top, which manages the project and the system; the **ON AIR banner** just below it, which puts the playing track front and centre; and the **broadcast grid** in the centre, where the actual work happens.

3.1 The Control Bar (Header)

The header spans the full width of the screen. From left to right, it gathers the software identity, the file commands, the monitoring and transport controls, the tools menu and the session indicators.

Identity

Logo and PRO badge. On the left, the logo sits beside the wordmark **RLM PRO**, with the word “PRO” rendered in an iridescent gradient running from cyan to green, amber and red. Next to it, in monospaced type, is the installed version (`v1.15.33`). Hover over the logo to reveal the full software name and version number.

File menu

The **FILE** button opens a menu with the project operations:

- New Project — opens an empty session. If there are unsaved changes, the software asks for confirmation.
- Save Project — a quick save to the current `.lmp` file. The entry turns yellow when there are unsaved changes.
- Save As... — always opens the dialog box, for creating progressive versions (e.g. `Ep47_draft.lmp` , `Ep47_final.lmp`).
- Export project with audio — consolidates all the audio inside the project (an `audio/` subfolder) and repoints the clips to it, so you can safely delete the originals. Described in Chapter 10.
- Load Project — opens a `.lmp` project from disk.
- Import M3U — imports a playlist in M3U format as a sequence of clips.

Monitoring and transport

Stereo VU meter (L/R). Two horizontal bars show the real output level after the Master Volume. The colour scale is intuitive: green up to about 85% of the way, then yellow, and finally red near full scale. Persistent red signals clipping: lower the level.

Master Volume. The fader controls the software’s overall output volume, from 0 to 100%. It acts as a master fader: brought to zero, no sound comes out, regardless of the state of the individual clips. If you have mapped a MIDI control to the Master Volume, a small badge shows the assignment.

STOP ALL (red “ALL” button). Instantly stops every active clip and cancels any fades in progress. It is the system’s emergency command. The `Esc` key does the same when the application is in focus, even while you are typing in a text field.

NOTE

Unlike previous versions, **Esc** is no longer registered as a system-wide global shortcut: it acts when RLMP is the active window. This choice lets dialog boxes use **Esc** to close without stopping the live show.

ARM (microphone). Arms and disarms the microphone for **Smart Mic** (Chapter 6). Disarmed, the button is grey; armed, it turns red, and it lights up and pulses while you speak. Next to it appear a small eight-bar VU with the microphone level and the **Mic Vol** slider; the **On Mix** badge shows that the voice is also going into the mix. Smart Mic must be enabled in the Microphone tab of the Settings (Chapter 13): if you turn it off, the microphone is disarmed.

FX. Opens and closes the pad FX, the effects jingle machine (Chapter 7). A small counter shows how many effects are playing at that moment.

MIX. Opens and closes the Automix view, the deck dedicated to the Music column (Chapter 7).

Tools

The **Tools** menu (wrench icon) gathers:

- Undo and Redo — the running-order edit history (**Ctrl+Z** / **Ctrl+Y**).
- MIDI Learn — enables MIDI learning mode (Chapter 8).
- Keybinds — the window for assigning keys to clips.
- Settings — the software's global preferences (Chapter 13).
- Info — version, credits and manual update check.

Just below the menu, the Auto-saved indicator appears briefly to confirm that the project has been saved automatically.




Figure 3.1 — The Control Bar and the open Tools menu (Undo/Redo, MIDI Learn, Keybinds, General Settings, Info).

Session indicators

On the right side of the header sit the **Playout Log** button (the chronological launch log, Chapter 13), the **Recording** button (Chapter 9), the **On Air timer** (which, when live, shows **ON AIR HH:MM:SS** on a red background) and the digital **studio clock** in 24-hour format, synchronized with the system clock.

The header area can also show unobtrusive notifications (**toasts**) about completed operations or system warnings. Unlike blocking dialogs, toasts disappear on their own after a few seconds and don't interrupt playback.

3.2 The ON AIR banner

Between the Control Bar and the grid sits a full-width banner that puts the track on air front and centre, readable even from across the room. It is **always there**: with nothing playing it shows the **OFF AIR** state in muted colours and the words "No track on air"; when a clip starts it lights up in green, without changing size or shifting the columns.

From left to right you find:

- **ON AIR** — the indicator with the red dot, which pulses while a track is on air.

- **Title and column** — the “ON AIR” label followed by the column name, the clip title in large type and, below it, the artist (or “In loop” for looping clips).
- **Progress bar** — fills with green as the track plays; two vertical ticks mark the Intro point (cyan) and the Outro point (orange), if configured (Chapter 5).
- **Timer** — the time left until the end of the track, in a colour that changes with the phase: **cyan** during the intro (counting down to the end of the intro), **white** in the body of the track, **orange** from the Outro point on, **flashing red** in the last 10 seconds. For looping clips it shows “LOOP”. In the 15 seconds before the Outro, the **OUTRO IN** warning appears below the timer with its countdown.
- **UP NEXT** — the title of the clip that will start next, when the clip on air is set to Play Next; otherwise the box stays dimmed.

If several clips are playing together, the banner shows the one from the highest-priority column, in this order: Episode Songs, Pre-Show, Voice, then the other columns. Pad FX effects never appear in the banner. When one track hands over to the next in a sequence, the banner holds the track that just ended for a moment instead of flashing OFF AIR.

3.3 The six-column grid




Figure 3.2 — The working interface: the ON AIR banner with a track on air and the six-column grid with the audio cards.

The grid is the software’s operational centre: six vertical columns side by side, each with its own colour-coded header and its own audio-behaviour logic. Sound effects have no column in the grid: they live in the pad FX (Chapter 7).

Column headers

Each header shows the column name and type, and doubles as a status indicator. Under normal conditions it is static and coloured in the column’s characteristic tone. When the playing clip is the last one available in the column, is not looping, and less than **20 seconds** remain until the end, the header goes into a **DEAD AIR** alarm: it pulses, turns amber, shows a warning icon and the **END** badge. It’s the advance notice that gives you time to prepare the next track before silence.

Each column’s colour is customizable: click the coloured dot in the header to open a palette of **30 shades**. The choice is saved in the project file.

When a column contains at least one clip, a **trash** icon appears in its header: the **Clear column** command removes every clip in that column in one go. For safety it always asks for confirmation, stating how many clips will be removed, and the operation can be reversed with Undo (**Ctrl+Z**). On empty columns the icon does not appear.

The **Pre-Show** column header also carries a **rotation** button: when active, the pre-broadcast queue automatically inserts jingles and promos at regular intervals (Chapter 13).

The six columns

Show Assets (Green) The structural elements of the show: idents, backing tracks, beds, institutional stingers. They behave as background elements: they yield space when voices or songs come in, but keep their internal rotation until they are stopped.

Jingle (Amber) and Promo (Cyan) Two columns dedicated, respectively, to identifying jingles and to promos or self-promotion. In audio terms they behave exactly like Show Assets (they belong to the same family), but keeping them separate keeps the running order tidy and readable.

Episode Songs (Red) The music playlist. Clips in this column take an active part in the automatic mixing: they are lowered when voices play and, in turn, silence the Asset beds when they start playing (Chapter 6). On music clips the software automatically detects the **BPM**, shown with a dedicated badge.

Voice / Recordings (Orange) Interviews, pre-recorded spoken segments, voice messages. This column has the **highest priority** in the mixing system: when a clip here is playing, all other signals are lowered to a background level.

Pre-Show (Purple) The pre-broadcast warm-up playlist. It works as a self-contained music queue, with optional rotation of jingles and promos. When the show proper begins, this column is typically emptied or disabled.

3.4 The audio card (Clip)

Every imported audio file materializes in the grid as a rectangular **card**. The card is the operating unit of the system: you see it, launch it, configure it, move it.

Anatomy of a card

Title and artist. The file name, or the custom name assigned in the properties. The custom title changes only the label inside the software; the original file on disk stays untouched. For music clips, the artist name may appear below the title.

Timer. At rest, it shows the clip's total duration in **MM:SS** format. During playback it switches to a **countdown**, with the negative prefix (e.g. **-01:20**). When less than 15 seconds remain, the timer turns **red**.

Status badges. Small labels communicate the configured properties at a glance:

- **LOOP** — the clip will restart from the beginning when playback ends.
- **NEXT** — when this clip ends, the next one in the column will start automatically.
- **► UP NEXT** — highlights which clip will be next to start in the automatic sequence.
- **### BPM** — the detected tempo, on music clips, shown on a high-visibility fluorescent-yellow badge.
- **I ##s** — the clip has an Intro point configured (Chapter 5): the badge, in cyan, shows its duration in seconds and is always visible, even when the clip is stopped.
- **TRIM...** — silence analysis in progress (Auto-Trim).
- **FADE OUT** — appears on the outgoing clip during a crossfade or a fade.
-  — the clip has a note attached in the NoteBoard (Chapter 13).

Assignments. If the clip has a keyboard key assigned, the letter appears in a badge in the column's colour; if it has a MIDI binding, the label  appears followed by the note number (e.g. ).

Structure cues. If markers are configured, the countdowns  (in cyan) and  (in orange) appear during playback, up to the  **OUTRO** warning when the tail has begun.

Playback indicator. When a clip is playing, the card lights up: green border, background with a luminous glow, a pulsing dot and the title highlighted. The progress bar sweeps across the card's background.

Interacting with the cards

- **Left click** — starts the clip if it is stopped; stops it (with a fade out) if it is playing.
- **Ctrl + Click** (Windows/Linux) or **Cmd + Click** (macOS) — selects the clip without starting it. The border turns blue. Useful for multiple selection and bulk deletion.
- **Delete key** (or Delete / Backspace) — removes the selected clips from the grid. If more than one clip is selected, the software asks for confirmation.
- **Right click** — opens the **Clip Settings**: properties, waveform editor, notes (Chapter 5).
- **Drag & Drop** — drag a card to reorder it within the column or move it to another. A luminous blue indicator shows the insertion point while dragging.

Cards in an error state

A card marked **MISSING FILE** with a red border signals that the referenced audio file is no longer reachable: it has been moved, renamed, or is on an external disk that is not connected. The clip is not playable until the file returns to its original path. Handling path errors is covered in Chapter 14.

CHAPTER 4

The basic workflow: load and play

The fundamental operating cycle of Runtime Live Machine Pro breaks down into three phases: importing the audio files, organizing them in the grid, playing them during the live show. This chapter describes each phase with the precision needed to work safely even under pressure.

4.1 Importing the audio files

RLMP has no internal browser and no centralized library. Importing is done by **drag & drop** directly from the operating system's file manager (File Explorer on Windows, Finder on macOS, Nautilus or equivalents on Linux). Alternatively, from the FILE menu you can import an **M3U** playlist and turn it into a sequence of clips.

The basic gesture

1. Open the folder on your computer where the audio files are.
2. Select one or more files. To select several files: `Ctrl+Click` for a discontinuous selection, `Shift+Click` for a continuous one.
3. Drag the selected files over one of the grid columns and drop them. For sound effects, drag them straight onto the pad FX (Chapter 7).

Each file creates a card in the destination column. If you drag several files at once, the cards are created in the order the files appear in the file manager, from top to bottom.

Insertion indicator. During the drag, a luminous blue line runs along the column, showing exactly where the cards will be inserted. You can add new clips at the top, at the bottom, or at an intermediate position with precision.

Supported formats

The bundled FFmpeg engine ensures compatibility with a wide range of audio formats:

Format	Extension	Notes
MP3	<code>.mp3</code>	All bitrates
WAV	<code>.wav</code>	Uncompressed PCM, any bit depth
FLAC	<code>.flac</code>	Lossless, any sample rate
AAC / M4A	<code>.aac</code> , <code>.m4a</code>	Includes files from iTunes/Apple Music
OGG Vorbis	<code>.ogg</code>	
Opus	<code>.opus</code>	
WMA	<code>.wma</code>	Windows Media Audio
WebM / MP4	<code>.webm</code> , <code>.mp4</code>	Audio tracks held in these containers

A note on performance. The `media://` streaming protocol ensures that audio files are not loaded into RAM at import time. An uncompressed 2 GB WAV file behaves exactly like a 5 MB MP3: loading is instant and the impact on system memory is negligible. CPU resources are engaged only during active decoding, that is, during playback.

The file path

RLMP stores the **absolute path** of the file on disk, not a copy of the file itself. If you move, rename or delete the original file, the corresponding card turns red and is no longer playable. To work

across several computers or create portable archives, use the **Export project with audio** feature described in Chapter 10.

4.2 Playback: starting and stopping clips

Starting a clip

A **left click** on the card is enough to start playback. The feedback is immediate: the card lights up in the green of the active state, the timer switches to a countdown, and the VU meters in the header reflect the output signal.

If a keyboard key has been assigned to the clip (see Chapter 8), that key works as an alternative to the click, handy when you are operating on another part of the interface and don't want to move the mouse.

Stopping a clip

Click the active clip — the clip enters the **fade out** phase and stops within the time set in its properties (see Chapter 5).

Esc key — stops all active clips instantly. It is the emergency command. It works when RLMP is the active window, even while you are typing in a text field.

STOP ALL button in the header — identical to **Esc**, accessible with the mouse.

The per-column exclusion logic

In most columns, RLMP applies the “**one clip at a time**” rule: if you are playing Track A in the Songs column and click Track B in the same column, Track A stops (with a fade out) and Track B starts. There's no need to manually stop the current clip before starting another.

The **pad FX effects** are the exception: they overlap everything, including other effects, and don't interrupt whatever is playing. A round of applause can start while a song is playing without cutting off its playback.

4.3 Organizing the running order

Reordering clips

While preparing the show, or even while it's under way, you can rearrange the order of the clips at any time.

Internal dragging. Click a card, hold and drag it up or down within the same column. The blue guide line shows the insertion point. The clip slots into its new position without interrupting anything currently playing.

Moving between columns. You can drag a clip from one column to another. When you do, the clip **inherits the rules of the destination column**: a pre-recorded voice moved into the Songs column will start being ducked exactly like a music track.

Moving clips between columns changes their behaviour, so use it deliberately, especially during a live show.

Multiple selection and deletion

To remove several clips from the grid in a single operation:

1. **Ctrl+Click** (Windows/Linux) or **Cmd+Click** (macOS) on each clip to select. The border turns blue.
 2. Press **Delete** or **Backspace**. The software asks for confirmation if more than one clip is selected.
- Deleting from the grid removes the clips from the current project, not the audio files from disk. If you make a mistake, **Ctrl+Z** undoes the operation.

TIP

Once the show is live, emptying the Pre-Show column with a multiple selection and [Delete](#) is the quickest way to free up visual space in the interface and switch to operating mode.

4.4 Structure cues: INTRO and OUTRO

Every clip can have two **structural markers** configured in the waveform editor (Chapter 5):

- **Intro Marker** — the point where the track's main melody actually enters, after the instrumental intro. Useful for knowing exactly when to start talking over the intro.
- **Outro Marker** — the point where the track's final tail begins. It flags the right moment to prepare the transition to the next track.

When a clip's playback approaches these points, a visual warning appears on the card:

- **INTRO: -MM:SS** — countdown to the Intro Marker.
- **OUTRO IN: -MM:SS** — countdown to the Outro Marker, followed by 🎧 **OUTRO** once the tail has begun.

These warnings appear only if the markers have been configured. On clips without markers, the card shows only the standard countdown to the end of the track.

CHAPTER 5

Clip properties and the Waveform Editor

Every audio file has a history before it reaches the grid: recordings with seconds of silence at the start, tracks with endless tails, interviews with a level too low against the rest of the show. Rather than reaching for an external audio editor every time a file isn't "broadcast-ready", RLMP provides a configuration panel for each clip and a visual waveform editor with trimming and marking features. Every change made through these tools is **non-destructive**: the original file on disk stays unchanged. RLMP stores the settings in the `.lmp` project file and applies them on the fly during playback.

To open a clip's settings, **right-click** on the card.

5.1 Basic properties




Figure 5.1 — The clip settings: name, colour label, Volume Gain, behaviour, Next Action and key assignment.

Name and appearance

Clip Name. You can give the clip a custom name, independent of the original file name. The name is displayed on the card in the grid. Use descriptive names that are operationally useful during the live show: "OPENING THEME" is easier to read than `theme_rev3_final_def.mp3` when you have three seconds to find the right clip.

Custom colour. By default, the clip inherits the colour of its column. Here you can assign a specific colour to make it stand out visually. Useful for marking critical clips (e.g. the closing theme) or for distinguishing thematic groups within the same column.

Volume (Gain)

The Volume Gain slider runs from 0% to 150% and acts as a pre-fader on the specific clip, before the global Master Volume.

The most common use case is level alignment: if you have a voice message recorded at low intensity (e.g. a WhatsApp message or a phone recording), you can push it beyond 100% to bring it closer to the volume of the other tracks. Conversely, you can lower a particularly “hot” clip without touching the Master Volume.

5.2 The waveform editor




Figure 5.2 — The waveform editor: Trim handles, Intro and Outro markers, Auto-Trim, Smart Cues and fades.

The visual editor is the heart of the configuration panel. It occupies the central area and shows a graphical representation of the entire clip’s audio.

Navigating the editor

Horizontal zoom. You can zoom the waveform view from 1× (full view) up to 8×, with intermediate steps (1×, 2×, 3×, 4×, 6×, 8×), using the zoom slider or the mouse wheel over the editor. At high zoom, the view scrolls to follow the current position.

Adaptive ruler. The time axis at the top of the editor adjusts automatically to the zoom: at full view it shows sparse references, at maximum zoom it packs them down to the second.

Playhead. During preview playback, a white vertical indicator moves in real time along the waveform, showing the current position. A click on the waveform moves playback to that point.

The four handles

The editor has four draggable **handles**, each with a precise function and colour:

Trim Start (red handle, left). Defines the clip’s actual start point. Everything to its left is skipped during playback. Drag it right to remove silences or unwanted parts from the beginning.

Trim End (red handle, right). Defines the actual end point. Everything to its right is ignored. Drag it left to shorten the tail. Trim Start and Trim End cannot overlap.

Intro Marker (cyan handle). Marks the structural point where the main melody enters the track, after any intro. Once set, the countdown **INTRO: –MM:SS** appears on the playing card.

Outro Marker (orange handle). Marks the point where the track's tail begins, typically the moment to start talking to fill the transition. The countdown **OUTRO IN: -MM:SS** appears on the card. If the value turns out to be inconsistent with the trim or the duration, the software disables it and warns you.

Besides dragging, four Set buttons place each handle at the playhead's current position, for marking on the fly while listening. The values remain precisely editable in their respective fields.

Auto-Trim (Magic Wand)

The button with the **magic wand** icon starts automatic silence detection via FFmpeg. The threshold is not fixed: the software first estimates the file's average level and sets the silence threshold about 25 dB below it (within a safety range between -55 and -20 dB; if no estimate is available, it falls back to -40 dB). Trim Start and Trim End are set automatically, removing leading silences and mute tails without manual work.

This is especially useful for unprocessed voice recordings: phone calls, voice messages, interviews recorded on mobile devices. Running Auto-Trim over the entire Voice column before a show takes less than a minute and makes the transitions cleaner.

NOTE

The analysis happens in the Main Process via FFmpeg, without loading the file into the Renderer's memory. On large files, the analysis time stays in the order of a few seconds.

Smart Cues (automatic marker detection)

Alongside Auto-Trim, the **Smart Cues** feature automatically proposes the Intro and Outro markers. Using a more aggressive threshold, it finds the point where the audio reaches full energy (Intro) and the point where the final fade begins (Outro), placing the two markers without your having to find them by ear.

Transition preview

If there is a **next** clip in the same column, the **"Test →"** button plays the last few seconds of the current clip and lets the transition into the next one trigger, right there in the editor. During the preview a Stop button ends the test.

5.3 Behaviours and automation

Overlap: the column decides

When a clip is started, it interrupts any other clip playing in the same column (with a fade out): one song excludes the others. Only the **pad FX** effects overlap freely, playing on top of anything without stopping it.

If an element has to "ride" what's on air — a station ID ("You're listening to...") over a track's intro, a short jingle over a looping bed — no clip setting is needed: put it in the **pad FX** (it plays at full volume over the music) or in the **Voice** column (which additionally lowers everything else with ducking). A clip's purpose is determined by the column it lives in; the old per-clip "Stacco (Jingle)" behaviour of previous versions has been removed.

Next Action (end-of-clip automation)

Defines what happens when the clip reaches the Trim End point.

Stop — the default behaviour for Songs, Voice and Assets. The clip ends and stops.

Play Next — when the clip nears the end, it automatically starts the next clip in the column with the configured transition. The **NEXT** badge appears on the card. It's the default behaviour of the Pre-

Show column and effectively creates an automatic playlist: you can set it on several consecutive clips to build blocks that flow without breaks.

Loop playback is a separate option: when active, the clip restarts from the beginning (from Trim Start) seamlessly, and the **LOOP** badge appears on the card. Use it for music beds, sound environments or background idents that should keep running until explicitly stopped. The transition modes — Crossfade, Segue, Gapless — are described in Chapter 13.

5.4 Fades (Fade In and Fade Out)

The panel lets you set, per clip, the duration of the incoming and outgoing fades. Values range from 0 to 60,000 milliseconds (60 seconds) and the curve applied is linear.

Fade In. The time the volume takes to reach its maximum level from the start. A value of 2000 ms produces a gradual two-second rise. Use it on music beds that should emerge gently; keep it at 0 for voices and effects that need to be heard immediately.

Fade Out. The fade time at close, both when you click an active clip and during transitions. Typical values: 2000–3000 ms for songs, 500–1000 ms for beds, 0 ms for hard stingers.

A 0 ms fade out produces an immediate close (“hard cut”). On a music track, live, it can be perceived as a technical error: consider carefully when it is appropriate.

5.5 Assigning controls

Every clip can also be launched from a keyboard key or a MIDI controller.

Trigger Keybind. The keyboard key assigned to the clip. You can set it from the dedicated field in the clip settings (click and press the desired key) or from the **Keybinds** window reachable from the Tools menu. The corresponding badge appears on the card. If the key is already assigned to another clip, the software reports the conflict before overwriting.

MIDI Bind. The assigned MIDI note (e.g. `NOTE:60`). The assignment is made through **MIDI Learn** mode (see Chapter 8), not by typing the number by hand.

Clip bindings are saved in the project file: carry the project to another computer with the same MIDI controller and the mappings will work without reconfiguration.

CHAPTER 6

The mixing engine

The underlying problem of manual radio production is the multiplication of simultaneous actions: start a track, lower the music, speak into the microphone, prepare the next clip, keep an eye on the clock. Every extra operation is an opportunity for error, in a setting where the error is public and immediate.

Runtime Live Machine Pro's mixing engine eliminates most of these intermediate actions by delegating them to the software. It doesn't do things behind your back. It automates the rules you would apply yourself if you had enough hands to carry them all out.

6.1 The audio hierarchy

The automatic mixing system is based on a **priority hierarchy** among the types of clip. The easiest way to grasp it is to picture it as a scale of "the right to speak".

Voice / Recordings — absolute priority. When a voice clip is playing, it stays at its nominal volume and everything else drops. No other signal can override this rule.

Episode Songs. They yield space to Voice, but they rule over the Asset beds. When a song comes in, the Asset music beds go to zero (they don't stop: they keep running in silence, ready to return). This is Music Dominance, described further on.

Show Assets, Jingle and Promo — the service beds. They are lowered by Voice and silenced by Songs.

Pad FX effects. Sound effects stay outside the hierarchy: they play at their own volume, overlap whatever is on air, and are never silenced. There is one courtesy toward speech: when a voice is active, the effects drop to half volume (50%) so as not to cover it, then rise again on their own.

6.2 Automatic ducking

Ducking is the mechanism by which a signal is lowered when a higher-priority signal starts playing. The most common case: a song is playing at full dynamics; you launch a pre-recorded interview from the Voice column. At that moment RLMP brings the song to about **20% of its volume** (a reduction of roughly 14 dB) with a soft half-second fade, so the voice occupies the sonic space intelligibly. As soon as the interview ends, the song rises back to its original volume with an equally smooth fade in.

The operator touches nothing. The gesture performed was a single click: starting the interview. The amount of the reduction and its speed are adjustable in the Settings (Chapter 13).

Smart Mic: the microphone that lowers the music

Ducking can also be triggered by your voice, without launching any clip. With **Smart Mic**, RLMP listens to the microphone and, when you speak, automatically lowers the music; when you stop, it brings it back up.

1. In the Settings, Microphone tab, enable **Smart Mic** and choose the input device (Chapter 13).

2. In the Control Bar, press **ARM**: the button turns red and the small VU next to it shows the microphone level.
3. Speak: when your voice goes above the threshold, ARM lights up and the music drops; shortly after you stop, it comes back up.

▲ WARNING

Smart Mic is designed for a **USB microphone connected directly to the computer**. If the microphone goes through a USB mixer (Rodecaster, Zoom LiveTrak and the like), the computer's input also carries the music on air: detection mistakes it for your voice and triggers by itself. In that case leave Smart Mic off and let the mixer handle the ducking.

Smart Mic is off by default and the microphone stays disarmed until you press ARM: if you don't use the feature, nothing changes.

6.3 Music Dominance: intelligent management of beds

A classic sonic mistake is the moment when a song and a music bed overlap: two rhythmic elements colliding, two kick drums that don't line up, and the result is muddled.

RLMP handles this scenario with **Music Dominance**.

The typical scenario. A bed is looping in the Assets column, under the host's voice. The host launches a track from the Songs column.

What RLMP does. It doesn't stop the bed, because stopping it would then require restarting it by hand. Instead it silently brings it to **zero volume**, keeping it playing "as a ghost": the file keeps running, the loop continues, but nothing is heard.

The sonic result. Only the song is heard. The bed has vanished without the operator doing anything.

The return. When the song ends, the bed re-emerges with an automatic fade in, resuming from the point it had reached in the loop. The flow (bed → song → bed) happens without a single extra click.

6.4 Rising above the hierarchy: effects and voices

If an element has to rise above what's on air, there are two ways, and they depend on where you put the clip.

The **pad FX**: the effect plays at full volume over the music and stops nothing — ideal for stingers and short jingles that must "punch through" the mix without touching it.

The **Voice** column: the clip stays at its nominal volume and everything else is lowered with ducking — ideal for the spoken station ID ("You're listening to...") that has to be clearly audible while the bed underneath keeps running. For a more polished entrance, pair it with a short fade in (300–500 ms): the attack will be soft, not abrupt.

Previous versions had a per-clip behaviour called "Stacco" that reversed the hierarchy. It has been removed: a clip's position in the hierarchy depends solely on the column it lives in, with no exceptions hidden in its properties.

6.5 Volume levelling (loudness)

Clips from different sources almost always arrive at different levels: a properly mastered ident, a quietly recorded phone voice, a track downloaded at its own volume. To avoid constant manual

Gain adjustments, RLMP applies by default a **volume levelling** based on the EBU R128 loudness standard, with a target of **-16 LUFS**.

In practice, the software evaluates the perceived loudness of each clip and brings it closer to a common reference, so that songs, voices and beds start out on a coherent footing. The feature is enabled by default and the target value is adjustable in Settings → Master Chain.

6.6 Master Chain: the processor chain on the master bus




Figure 6.1 — The Master Chain: volume levelling (-16 LUFS), HPF at 30 Hz, multiband glue and brickwall limiter.

The combined signal of all playing clips, after the Master Volume, passes through a **processor chain** on the master bus before reaching the output device. The chain is enabled by default and designed for a broadcast-grade sound without requiring advanced configuration.

It comprises three stages in series.

High-Pass Filter (HPF) at 30 Hz. Removes the useless sub-bass frequencies that eat up headroom and can muddy playback systems, with a gentle slope. The cutoff frequency is adjustable (20–200 Hz). When disabled, the stage becomes completely transparent.

Multiband glue. Not a single compressor, but three “gentle” compressors working in parallel across three frequency bands (lows, mids, highs), separated by a crossover. Each band has thresholds and ratios calibrated to “glue” the mix without crushing it, and to hold the dynamic variance between clips of different levels in check. The style is selectable among a few presets (Neutral, Rock, Jazz, Electronic); the default preset is Neutral.

Brickwall limiter. Threshold at -1 dBFS, with a high limiting ratio and a very fast reaction. It guarantees the signal never exceeds the maximum allowed level, preventing digital distortion (clipping) whatever happens upstream.

The whole chain, and each individual stage, is configurable and can be disabled from Settings → Master Chain, where you’ll also find a button to restore the defaults. In a context where the signal is already processed by a hardware mixer or an external chain, you can disable it to avoid double processing.

CHAPTER 7

The Pad FX and the Automix view

Two working surfaces live above the grid, each summoned with a key and built for opposite moments of production. The **pad FX** fires off effects and stingers reliably without interrupting anything. The **Automix view** handles the music flow the way a DJ would. Neither takes space away from the grid: they open when you need them and close with a click.

7.1 The pad FX: the jingle machine




Figure 7.1 — The pad FX: the 5×5 jingle machine of sound effects, with overlapping playback.

Sound effects have no column in the grid. They live in the **pad FX**, a grid panel of cells (a jingle machine) that opens from the **FX** button in the header and stays floating in a corner of the screen. The pad is a **non-blocking overlay**: it doesn't obscure the board and doesn't intercept clicks elsewhere. You can launch an effect and, at the same moment, keep operating on the columns or the header controls. For that reason the **Esc** key doesn't close the pad: it remains the STOP ALL command, always available. The pad closes from its own close button or by toggling FX again.

Loading and launching effects

The pad starts with a grid of 25 cells (5×5) and grows in rows as you add more effects. To populate it, **drag audio files straight onto the pad's cells**, exactly as you would with a grid column.

A click on a cell **launches the effect**. The pad effects are polyphonic and overlap: several cells can play together, over anything on air, without stopping it. The audio behaviour is identical to a normal clip; only the launch surface changes. A counter next to the FX button in the header shows how many effects are playing at that moment.

Configuring an effect

Effects are configured on two levels, meant for two different needs:

- **Quick settings** — the common case for a jingle machine: name, colour, volume, loop. It takes a few seconds.
- **Full settings** — the same window as the grid clips (waveform editor, trim, markers, fades, key assignment), reachable from the “Full settings...” entry within the quick settings.

Pad position

The pad can sit in the bottom-left or bottom-right corner of the screen: the preference is set with the arrows on the pad itself and is remembered across sessions. On the right it covers the NoteBoard and the last column; choose the side based on how you’ve laid out your running order.

NOTE

In MIDI Learn mode, a click on a pad cell **selects** the effect for assignment instead of playing it — so you don’t send a jingle on air while mapping the controls (see Chapter 8).

7.2 The Automix view




Figure 7.2 — The Automix view: the Music-column deck, BPM compatibility and automatic end-of-track mode.

The **Automix view** is the deck of the Music column: a full-screen display, summoned from the **MIX** button in the header, that presents the music running order like a DJ console. It opens above the board but below the pad FX, so the effects stay usable even while Automix is open. As with the pad, **Esc** doesn’t close it: it remains the emergency command, and the STOP ALL button stays reachable in the header.

The deck

At the centre you find the track **on air** and, in the queue, the **next** track in the Music column, with the time remaining. From here you can start a track and manage the passage from one track to the next with a single command: the big transition button applies the same crossfade you would use from the grid, but with the added care of rhythmic locking.

Compatibility and beat-matched transitions

Next to each track, a **compatibility dot** with the previous track shows their rhythmic affinity:

- **Green** — the two tempos lock well: the transition can be beat-matched.

- **Yellow** — locking is possible but with some reservations.
- **Red** — the tempos are too far apart for a clean lock.

When rhythmic locking isn't practical (BPM not detected, uncertain beat, tempos too different), the software declares it and automatically falls back to a **classic crossfade**, with no surprises on air.

Automatic mode

At the bottom of the view there's a switch for **end-of-track automation**. When it's active, RLMP starts the passage to the next track on its own when the track on air nears the end.

This mode is a deliberate exception to the software's philosophy, which by design does not automate the show. That's why it is **disabled by default** and works **only while the Automix view is open**: closing the view disables the automation. It's the right tool for a continuous music block, the half-hour of music-only before returning to the mic, not for the entire live show.

CHAPTER 8

Hardware, keyboard and MIDI

Runtime Live Machine Pro is designed to integrate with the hardware already in the studio without requiring elaborate configurations. This chapter describes how to route the audio output, how to use the computer keyboard as a controller, and how to connect physical MIDI devices for tactile control of the production.

8.1 Audio routing

Selecting the output device

By default, RLMP outputs to the operating system's default audio device. In a professional or semi-professional setting, with USB mixers, external sound cards or multitrack systems, it's useful to select the signal destination explicitly.

1. Open the **Settings** from the Tools menu.
2. On the Audio & Mix tab, open the output-device menu: you'll find the list of audio devices available on the system.
3. Select the device you want.

If the chosen device is unplugged, RLMP falls back automatically to the system default; the app monitors connections and reacts to the insertion or removal of USB devices.

USB mixers and multichannel setups

USB mixers such as the Rødecaster Pro, the RØDECaster Duo or the Focusrite Scarlett typically expose several USB channels to the operating system (Main Mix, Sounds/Chat, Monitor, and so on). RLMP appears as a single stereo source; the choice of which USB channel to route it to is in your hands.

Recommended setup with a USB mixer. Assign RLMP to a secondary channel of the mixer (e.g. "Sounds" on the Rødecaster Pro) rather than to the main channel. This way you control RLMP's volume with a dedicated physical fader, keep it separate from the physical microphone signal, and apply any hardware processing to that channel only.

Latency and buffer

RLMP uses the operating system's native audio APIs. The output latency is determined by the audio device's buffer, not by the software. With professional sound cards the latency is in the order of a few milliseconds, imperceptible in a playout context.

If you notice audio artefacts (crackles, dropouts), the device's buffer value is probably too low. Raise it from the sound card's control panel (not from RLMP, which doesn't manage the driver directly): a buffer of 256 or 512 samples is the ideal balance between latency and stability.

8.2 Keyboard control

The computer keyboard is the fastest controller available on air: it works in the dark and is always within reach. RLMP provides a set of global shortcuts and lets you assign keys to individual clips.

Global shortcuts

Key	Action
Esc	STOP ALL — stops all active clips
Delete / Backspace	Delete the selected clips
Ctrl+Z	Undo the last change to the running order
Ctrl+Y (or Ctrl+Shift+Z)	Redo the undone change
Ctrl+Shift+D	Show/hide the Debug Overlay
Ctrl+Shift+M	Open the MIDI simulator (for testing without a controller)
F1, F2, F3...	Launch the matching column, counting the visible columns from the left

Esc acts as STOP ALL when RLMP is the active window, even while the cursor is in a text field. It is no longer a shortcut registered at the operating-system level: if the app is in the background, bring the window to the foreground first.

The other shortcuts are suspended while a window is open (Settings, the clip editor and the like), so **Ctrl+Z** or **Delete** don't touch the running order while you work elsewhere. With a window open, **Esc** closes it without stopping the live show.

Function keys: one column per key

The **F1, F2, F3...** keys launch the first available clip of the columns **visible** in the grid, in the order you see them from left to right. With the default layout: F1 Show Assets · F2 Jingle · F3 Promo · F4 Episode Songs · F5 Voice · F6 Pre-Show. If you hide a column from the Settings (Chapter 13), the keys shift accordingly: F1 is always the first column you see. If you have assigned a function key to a specific clip, that assignment takes precedence.

▲ WARNING

F1 normally launches Show Assets, and a clip from that column launched by hand stops everything on air except the pad FX effects, exactly like clicking the same clip.

Custom keys per clip

In addition to the global shortcuts, every clip can have a dedicated key. The corresponding badge appears on the card.

To assign a key: 1. Open the clip settings (right-click the card) or the **Keybinds** window from the Tools menu. 2. Click in the key field. 3. Press the key you want.

Available keys. Almost any key: letters (A–Z), numbers (0–9), numeric keypad, spacebar, unused function keys. If the key is already assigned to another clip, the software reports the conflict before overwriting, so you don't create invisible duplicates.

Safety while typing. Custom keys are disabled automatically when you're in text-entry mode (renaming a clip or writing a note). This prevents accidental launches while you type.

8.3 MIDI controllers

MIDI is the professional choice when you want physical, reliable control under your fingers. RLMP supports USB-MIDI controllers: keyboards, pads (e.g. Novation Launchpad), fader controllers (e.g. Korg nanoKONTROL2), hybrid control surfaces.

Connecting

Connect the USB controller to the computer and start RLMP. The software detects devices through the system's Web MIDI API and recognizes the connection and disconnection of a controller in real time. Most USB-MIDI controllers are class-compliant and need no driver; for professional surfaces with proprietary drivers, install the driver before connecting the device.

MIDI Learn

RLMP doesn't require you to know MIDI note numbering or to configure messages by hand. Learning is done through **MIDI Learn** mode, from the Tools menu (or from the Keybinds window).

To map a clip to a key/pad: 1. Enable MIDI Learn. The cards enter a waiting state. 2. Select the clip (or the pad FX cell) to map. 3. Play the note, press the pad or the key on the controller. The  badge with the note number appears on the card.

To map the global functions: - Select **STOP ALL** and press a key on the controller: that key will perform the Stop All. - Select the **Master Volume** and move a fader or a knob: that control will manage the master volume continuously.

When finished, disable MIDI Learn to return to operating mode.

Supported message types

Note On — messages generated by buttons, pads and keys. Ideal for launching clips and global actions; RLMP responds to the key press and recognizes all MIDI channels. Note Off messages are ignored.

Control Change (CC) — messages generated by faders and potentiometers, with a continuous value from 0 to 127. Ideal for the Master Volume: a physical fader mapped to the master offers the most natural control of the output level.

Portability of the mappings

The MIDI mappings of the **clips** are saved in the  project file: carry the project to another computer with the same controller and they will work without reconfiguration. The mappings of the **global functions** (Stop All, Master Volume) are instead tied to the computer, saved in the application's local preferences, and remain valid for all projects on that machine.

CHAPTER 9

Session recording

Session recording turns Runtime Live Machine Pro from a playout tool into a complete production tool. You don't need separate recording software or a virtual routing chain. RLMP captures the **post-processed master mix** directly, everything that leaves the application (including the Master Chain effects), into an audio file on disk.

9.1 Starting the recording

The recording control is in the header, identified by the record icon.

Start. Click the record button. A red indicator and a counter show that capture is under way. Recording starts immediately: everything that leaves the software's output from that moment on is captured.

You don't need clips playing to start recording: you can begin capture ahead of the show's start, so you don't lose the first few seconds in case of an early start.

What gets recorded. The captured signal is the **master after the limiter**: it includes the mix of all playing clips and the processing of the entire Master Chain (HPF, multiband glue, limiter). It is exactly the signal that reaches the audio output device.

The internal format. During capture, RLMP writes a compressed Opus stream (in a WebM container) at 320 kbps: very light on disk and transparent to the ear. Continuous recording has a safety limit of about **four hours**; beyond that duration the capture stops automatically so as not to saturate memory.

System overhead. Capture happens downstream of the audio engine, without burdening the Renderer. You can record sessions hours long without worrying about resource consumption.

9.2 Stopping the recording and choosing the format

When you click the button again to stop the recording, the **export window** opens. This is where you choose which format to save the file in: converting from the internal stream to the final format is handled by FFmpeg.

Available formats

Format	Extension	Characteristics
WAV	<code>.wav</code>	Uncompressed lossless. Maximum quality, large files. Ideal for archiving and post-production.
FLAC	<code>.flac</code>	Compressed lossless. Same quality as WAV, smaller size. Ideal for archiving.
MP3	<code>.mp3</code>	Lossy. Selectable bitrate. Ideal for distribution and podcasts.
OGG	<code>.ogg</code>	Open-source lossy. Good quality-to-size ratio.
WEBM	<code>.webm</code>	Lossy, optimized for the web. Matches the internal capture format.

Quality options

For the lossless formats (WAV and FLAC) you can select the **bit depth**: 16-bit (CD standard), 24-bit (professional broadcast standard, the default) or 32-bit float (maximum precision, if the recording will be mastered later).

For the lossy formats (MP3, OGG, WEBM) you can select the **bitrate** among 128, 192, 256 and 320 kbps. For a podcast intended for online distribution, 192 kbps stereo is the recommended minimum; 256 kbps is the current standard for “transparent” quality.

Choosing the save location

In the export window you choose the destination folder and the file name. If you don’t specify a name, RLMP generates one based on the session’s date and time. When the conversion finishes, a confirmation toast shows the path of the saved file.

9.3 Practical considerations

Synchronizing with the show

The recording captures all the time elapsed between Start and Stop, including the silences. If you started capture 30 seconds before the show’s actual start, the resulting file will include those first 30 seconds. For a distribution-ready result without post-editing, start the recording exactly when the show begins.

Recording and backup at the same time

The project’s autosave system (see Chapter 10) and session recording operate independently. You can record a show while the autosave silently saves the project state: the two operations don’t interfere.

Recommended format for different contexts

Podcast — MP3 256 kbps stereo or FLAC 16-bit. The first if you distribute the file directly, the second if it will pass through an editor.

Long-term archive — WAV 24-bit or FLAC 24-bit. Generous sizes, maximum flexibility for any future remasters.

Radio / Streaming — check your platform’s requirements. Most accept MP3 128–192 kbps; some require uncompressed WAV. RLMP exports in the most common formats to cover every scenario.

CHAPTER 10

Project management and data safety

Preparing a show takes time: selecting the files, organizing them in the columns, configuring the volumes, setting the fades, assigning the keys. That work is an operational asset that must survive any mishap: a system crash, a move to another computer, the return to an episode archived months earlier.

RLMP addresses data safety on several levels, each designed to cover a specific risk.

10.1 The project file (.lmp)

The entire state of a show (the layout of clips in the columns, the custom names, the volumes and fades, the editor cue points, the NoteBoard notes, the MIDI and keyboard mappings, the column colours) is saved in a file with the `.lmp` extension (Live Machine Project).

The format is JSON: a structured text file, readable by any editor, non-proprietary. If RLMP were one day unavailable, the project data would remain accessible.

What the `.lmp` file contains: all the settings listed above, including the absolute paths to the referenced audio files.

What it doesn't contain: the audio files themselves. The `.lmp` stores where the files are on disk, it doesn't copy their content. A project file is typically in the order of kilobytes, regardless of how many or how large the audio files it references are.

On opening, RLMP validates the file: it rebuilds any duplicate identifiers, brings out-of-range values back within sane limits, and, if you open a project created with an earlier version, automatically adds the columns introduced in the meantime (Jingle, Promo) without touching the existing data.

10.2 Saving

Quick save

The Save Project entry in the FILE menu performs an immediate save to the open `.lmp` file. The save is silent: no dialog box. The entry turns yellow when there are unsaved changes, a visual reminder at a glance. Use it often while preparing the show.

The save is **atomic**: the file is first written to a temporary copy and then renamed on the fly. If the computer shuts down during the write, the original `.lmp` is never left half-written.

Save As

The Save As... entry always opens the dialog box, even if the project already has a name. Use it to:

- Create progressive versions of the same show (`Ep47_draft.lmp` , `Ep47_v2.lmp` , `Ep47_final.lmp`).
- Save a variant with different configurations.
- Create a new file without overwriting the current one.

Protection on close

RLMP continuously monitors the state of changes. If you try to close the software (or open a new project) with unsaved changes, the operation is suspended and a confirmation request appears with three choices: save, discard the changes, or cancel. It is not possible to lose work through an accidental click on the window close.

10.3 Auto-Backup and autosave

Beyond the saves you decide on, the software maintains an automatic safety net.

Project backup copy. Every time an already-saved project is updated in the background, RLMP keeps a `.bak` copy alongside the `.lmp` with the last valid state.

Rotating autosave. In parallel, RLMP writes snapshots of the current state to a dedicated application folder, `autosaves`, with a name based on date and time. The **ten most recent snapshots** are kept: the oldest are deleted as new ones are made. This net also captures work on an “untitled” project that was never saved to disk.

The `autosaves` folder is in the application data directory:

- **Windows:** `%APPDATA%\runtime-live-machine-pro\autosaves\`
- **macOS:** `~/Library/Application Support/runtime-live-machine-pro/autosaves/`
- **Linux:** `~/.config/runtime-live-machine-pro/autosaves/`

How to recover. If the main `.lmp` file has become corrupted or the computer shut down unexpectedly, open the `autosaves` folder, find the snapshot with the date and time closest to the moment of the interruption, and load it in RLMP like a normal project file. Alternatively, rename the `.bak` file next to the project to `.lmp` and open it.

10.4 Export project with audio

Because the `.lmp` file contains only the paths to the audio files, not the files themselves, a project is fragile: if you move, rename or delete even a single one of the source files, the corresponding clip turns red. The **Export project with audio** feature, in the FILE menu (right below Save As...), solves the problem at the root by consolidating all the audio inside the project.

How it works

RLMP analyses all the audio-file paths in the project, creates an `audio/` subfolder next to the `.lmp` file, and **physically copies** every referenced file into it. Files already present and identical are not re-copied; any name duplicates are renamed so they don't overwrite each other, and orphan files (no longer referenced) are removed from the folder.

The difference from a simple backup is what happens **after** the copy: RLMP **repoints every clip to the new copy** inside `audio/` and **re-saves the project**. From that moment on, the `audio/` folder is not a spare archive sitting next to the project, but the source the session actually reads its audio from.

The result: you can delete the originals

Because the project now points to the copies in `audio/`, **the audio files in their original location are no longer needed** and you can safely delete them: the show keeps working by reading from the archive. This is the difference from earlier versions, where the `audio/` folder stayed an orphan duplicate and deleting the originals broke the clips.

The project folder thus becomes self-contained: the `.lmp` plus the `audio/` subfolder, everything needed to run the show, ready to archive, copy, or carry to another computer with RLMP installed.

A few useful details:

- The operation is **repeatable**: if you add new clips and export again, RLMP copies only the new files and realigns the project, without duplicating the ones already archived.
- RLMP **only deletes files inside `audio/` folders it created itself**: the first export leaves a small text file, `.rrlmp-archive`, in the folder to mark it as an archive. If an `audio/` folder of your own already sits next to the project (or one created by versions up to 1.15.16), RLMP removes nothing: it tells you how many files are not part of the project and marks the folder, which it will manage normally from the next export. Move elsewhere anything you want to keep. If you delete `.rrlmp-archive`, RLMP stops treating the folder as its own.
- Repointing to the archive **does not enter the Undo/Redo history**: an Undo would send the clips back to the originals, which you may already have deleted.
- The project folder (`.lmp` + `audio/`) can be **moved, renamed, zipped and taken to another computer**: on opening, any file that isn't found at its old location is automatically searched for in the `audio/` folder next to the `.lmp` and relinked by itself. The project is marked as modified: the next save consolidates the new paths.

TIP

Use Export project with audio at the end of preparing each show to consolidate the audio inside the project. You'll have a compact, portable "master", and you can free up space by deleting the scattered files you imported from.

Integrity check on opening

Every time you open a `.lmp` file, RLMP runs an automatic **integrity check**: it verifies that each referenced audio file is reachable. Missing files are flagged with a red border and the MISSING FILE label on the corresponding card. The rest of the project — all the clips with reachable files — stays fully functional.

CHAPTER 11

Remote Control

The person presenting isn't always seated at the computer. Sometimes the host is on the other side of the studio, behind glass, or moving around with a guest. The **Remote Control** in Runtime Live Machine Pro lets you drive the show's essential moves from a second device (a tablet, a phone, a laptop) connected to the same local network, straight from the browser. Nothing needs to be installed on the remote device.

The feature is currently marked as **Beta**.

11.1 How it works

When you enable it, RLMP starts a small **local web server** inside itself. The remote device connects to this server by opening an address in the browser: from there a control page appears that mirrors the state of the Music column and lets you act on it.

Everything happens **inside the local network**: the server is reachable from devices connected to the studio's same Wi-Fi or LAN, and it doesn't go through the internet.

11.2 Activation

1. Open the **Settings** from the Tools menu and go to the General tab.
2. Turn on the **Remote Control (Beta)** toggle.
3. A **six-digit PIN**, the server **port** and the **network addresses** the remote device can connect to appear.
4. The **Copy link** button copies the ready-to-use address to the clipboard (in the form `http://<computer-address>:8787`).

The server listens on port **8787**. The PIN is **regenerated on every launch** of the application and is not stored: closing and reopening RLMP produces a new PIN. Remote Control itself also always starts off at every launch, to be re-enabled when needed.

If startup fails, typically because port 8787 is already taken (by another copy of RLMP left open or by another program), the switch turns back off and a message shows the reason.

11.3 Connecting from the remote device

1. On the tablet or phone, open the browser and type the address shown in the Settings (or paste it from the copied link).
2. A page with a keypad appears: enter the **six-digit PIN**.
3. Once the PIN is correct, the page shows the list of clips in the **Music** column, with the playback controls, and a **Stop All** button. A dedicated button takes the page full screen, handy on a tablet.

From here you can start and stop the tracks in the Music column and, if needed, stop everything. The state updates in real time: whatever starts or stops on the main computer is reflected on the remote page, and vice versa.

11.4 What you control remotely

Remote Control is deliberately minimal. From the remote device you can:

- **Start** a clip in the Music column.
- **Stop** a clip in the Music column.
- Perform a **Stop All**.

These are the only actions allowed. The rest of the production (the other columns, the pad FX, the editor, the settings) stays on the main computer. It's a safety choice: the remote is there to manage the music flow from a distance, not to replace the production desk.

11.5 Security and limits

- **PIN required.** No device can send commands without passing the six-digit PIN check.
- **Only from the remote control page.** The server accepts connections only from the page it serves itself: a web page from another site, opened on a device on the same network, is rejected before it can even ask for the PIN.
- **Attempt protection.** PIN entry attempts are rate-limited: after several failed attempts in quick succession, access from that device is temporarily blocked.
- **Whitelisted commands.** The server accepts only the three intended commands (start, stop, Stop All): any other request is ignored.
- **Local network only.** The server is meant for the studio network. If your Wi-Fi is open or shared, consider carefully who can reach it.
- **No persistence.** The PIN and the activation state are not saved: at every restart you begin from a clean configuration.

NOTE

As a Beta feature, the set of available commands may expand in future versions. For now it is tuned to the most frequent use case: managing the music from a distance during hosting.

CHAPTER 12

Updates

Runtime Live Machine Pro updates itself, but never at your expense. Two rules govern everything: no update may interfere with a live show, and no download starts without your consent. This chapter explains how the software checks for new versions, how it installs them, and why it sometimes behaves differently depending on the operating system.

12.1 The startup check

Shortly after startup (about three seconds), RLMP silently checks whether a newer version exists. The outcome appears on the welcome screen, next to the version number:

- **“Latest Version”** (green) — you are running the most recent version.
- **“Update Available”** (amber) — a newer version is available. It is a button: click it to open the update window.
- **“OFFLINE”** — the service could not be reached; try again later. The software works normally.

The check is optional and non-blocking: if you’re offline, RLMP starts and works without any trouble.

12.2 The update window

When an update is available, the dedicated window shows the current version, the new version and the **release notes**: the real list of what’s new in that version (the same changelog as this software), formatted and readable, not a bare list of files. The notes stay visible even once the download is complete, right before installing, so you always know what you’re about to apply. From here you decide:

- **Later** — closes the window without doing anything. You can reopen it whenever you like.
- **Download** — starts downloading the new version. The download **never starts on its own**: it begins only when you press this button. A progress bar shows its progress.
- **Restart and install** — appears when the download is complete: it closes the application and applies the update. If the open project has unsaved changes, RLMP asks what to do before installing, with the same choices as when closing: **Save** (save, then install), **Don’t Save** (install and discard the changes) or **Cancel** (install nothing; the app stays open). If saving fails, the installation doesn’t start. Once past this question, the shutdown is clean and immediate and the software doesn’t stay open behind the installer.

12.3 The “never during a live show” rule

The automatic check may find an update right while you’re on air. In that case, RLMP **does not interrupt you**: the update window waits and opens on its own only when the live show is over (when you stop everything). The priority is always the show in progress.

There is one exception, and it’s intentional: the **Check for updates now** button, in the Info panel (Tools menu), is an explicit action of yours and opens the window immediately, even live. If you press it, it’s because you want to.

12.4 Platform differences

How the update is installed depends on the operating system.

Windows and Linux (ApplImage). The update is fully integrated: you download the new version from the window and the software installs it at the next restart, with no manual steps.

Linux (.deb package). With this format RLMP can't install the update reliably. Instead of automatic installation, the window notifies you and opens the browser on the download page for the new version: from there you download the package and install it as you would for a fresh install (Chapter 2). Your projects and `.lmp` files stay intact.

macOS (built from source). There is no official package to download: the window reports the new version and opens the project page, but to update you download the updated code and build again (section 2.3).

NOTE

In all cases, updating RLMP doesn't entail losing your projects: the `.lmp` files are compatible across versions and require no manual migration.

CHAPTER 13

Advanced features

This chapter gathers the features that sit outside the basic workflow but tend to stick once you find them: the NoteBoard, column colour management, transitions, the general settings, the launch log and the edit history.

13.1 NoteBoard: the script in the control room

The **NoteBoard** is the note system built into the clips. It lets you attach written text to any clip (operating instructions, running orders, notes on an interview, the full script of a spot) and have it appear automatically on screen the moment that clip starts playing.

Adding a note

1. Open the clip settings (right-click the card) and go to the Notes section.
2. Write the text in the free field. There is no length limit.

Clips with a note show the  badge on the card.

The panel during the live show

When a clip with notes starts playing, the **NoteBoard panel** appears at the bottom of the screen with the associated text, headed by the clip's name and colour. The panel stays visible for the whole duration of playback and closes on its own when the clip ends. If several clips with notes play together, the panel shows the one with the highest priority.

Use cases

- **Spoken production.** Attach to each ident the first lines of the spoken block that follows: when the ident starts, the text is already in front of your eyes.
- **Content to read.** An advertising spot with the full text in the note: as soon as it starts, you read it.
- **Operating instructions.** "Lower the monitor", "Check the guest's headphone level", "Start the recording".
- **Interviews.** The questions for the guest stay visible for the whole duration of the clip.

13.2 Column colour customization

The default colours have an established meaning (green for Assets, red for Songs, and so on), but every column is customizable. Click the **coloured dot** in the column header: a palette of **30 colours** opens. Choose one and the column (header, cards, indicators) takes on the new colour immediately. The choice is saved in the project file.

The cards inherit the column's colour dynamically: at rest they appear in a muted shade, in playback in the full colour. Each project can thus have its own colour identity.

13.3 Transitions between clips

When a clip is set to Play Next, the passage to the next clip in the column happens according to the configured transition mode:

- **Crossfade.** The outgoing clip fades while the incoming one rises, overlapping. Default duration: 2 seconds.
- **Segue.** The outgoing clip fades out while the next one starts immediately at full volume. Default fade duration: 0.8 seconds.
- **Gapless (hard cut).** The outgoing clip stops abruptly and the next starts immediately, with no fade.

You can set a transition at the level of a single clip or leave **Global Default**, which applies the general choice defined in the Settings. The Pre-Show column uses crossfade as its default. All the modes can be tried out without going on air, using the “Test →” button in the editor (Chapter 5).

13.4 The General Settings window

The **Settings** (Tools menu) gather the software's global preferences, organized into tabs.

General

- **Language.** Select the interface language: English or Italian. The change is immediate.
- **Remote Control (Beta).** Enables the browser remote and shows PIN, port and addresses (Chapter 11).
- **Broadcast layout.** Shows or hides the grid columns individually. Hiding a column doesn't delete its clips: they stay in the project. It's a global preference, valid for all projects.

Audio & Mix

- **Output device.** The audio destination (Chapter 8).
- **Mixing intelligence.** The amount of ducking (how far the music drops when a voice speaks, default 20%) and its speed (default 500 ms).
- **Transitions.** The default transition mode and the crossfade and segue durations.

Microphone

- **Smart Mic — Auto-Ducking.** Enables the microphone that lowers the music when you speak (Chapter 6). At the top of the tab, a notice reminds you that the feature is designed for USB microphones connected directly to the computer, not for USB mixers.
- **Input Device.** The microphone to listen to: USB microphones and audio interfaces appear here automatically.
- **Activation threshold.** The level above which your voice triggers the ducking (default -30 dBFS); release happens 12 dB lower.
- **Activation and release hold.** How many milliseconds your voice must stay above the threshold before the music drops, and below it before the music comes back up.
- **Microphone Mix Channel.** With In Mix, your voice also goes into RLMP's output, with its own **Microphone Volume**. The **Bypass Master Chain** option decides how it comes out: off, the voice goes through a high-pass filter, compressor and limiter; on, it comes out as it is, with no added latency. A warning about the risk of **feedback** (howling), to be confirmed, reminds you to use headphones or a professional mixer: with the speakers on, your voice can leak back into the microphone.

Recording

A summary of the capture point (after the limiter) and the choice of default format proposed at export (Chapter 9).

Master Chain

- **Volume levelling.** Enables/disables loudness normalization and sets its target (default -16 LUFS).
- **Master Chain.** Enables or bypasses the whole chain, and adjusts the individual stages: HPF frequency, multiband glue style, limiter threshold. A button restores the defaults (Chapter 6).

13.5 Playout Log

The **Playout Log** (icon in the header) is the chronological launch log: it tracks what went on air and when, up to the last several thousand events. It's useful for reconstructing a running order after the fact, verifying what was broadcast, or compiling a report of the live show.

13.6 Undo and Redo

Changes to the running order (additions, moves, deletions) are reversible. `Ctrl+Z` undoes the last operation, `Ctrl+Y` (or `Ctrl+Shift+Z`) redoes it, with a history several dozen steps deep. The same entries are available in the Tools menu. It's the safety net for operations done in a hurry during preparation.

13.7 Toast notification system

RLMP doesn't use blocking windows for routine communications. Non-critical notifications appear as **toasts**: small, unobtrusive banners in a corner of the screen that stay for a few seconds and disappear on their own without interrupting playback. They are used to confirm a save, the end of an export, a MIDI Learn operation, or to warn of missing files.

The **confirmation windows**, needed when an action is irreversible (deleting clips, closing an unsaved project), are instead modal and require a response, but they are designed not to cut off the playback in progress: the audio continues while you decide.

CHAPTER 14

Troubleshooting and FAQ

This chapter collects the most common problems in the daily use of Runtime Live Machine Pro, with their solutions. Each section describes the symptom, the most likely cause and the procedure to resolve it.

14.1 Audio problems

The timer runs and the VU meters move, but nothing is heard

The software is playing correctly (the signal is present on the internal bus), but it isn't reaching the monitoring device.

Check in order:

1. **Master Volume.** Is the slider in the header at zero? Bring it to 100%.
2. **Output device.** Open Settings → Audio & Mix and check which device is selected. Windows and macOS can change the identifier of USB devices when they are unplugged and reconnected. If the name doesn't match the one physically connected, select it again.
3. **External mixer.** If the signal reaches a hardware mixer, check that the channel fader isn't down or muted, and that the mixer output is connected to the monitors or the broadcast chain.

The audio skips, crackles or has dropouts

Under normal conditions the audio engine doesn't produce these artefacts. If they occur, the cause is almost always external to the software.

- **CPU under extreme load.** Close heavy applications running at the same time (video editing, rendering, intensive backups).
- **Audio buffer too low.** With a professional sound card, check the buffer value in the driver's control panel. A value of 256 or 512 samples is the right balance; below 128 samples, dropouts can appear.
- **Slow or stressed disk.** RLMP streams the audio from disk. A slow mechanical disk, or an almost-full SSD, can cause interruptions on large files.

The audio level is too low or too high

- **Per-clip Gain.** Adjust the Gain in the clip properties (right-click → Volume section).
- **Master Volume.** If the overall level is wrong, act on the slider in the header.
- **Levelling and Master Chain.** Volume levelling brings the clips' levels closer to a common reference; the Master Chain glue can make the sound more compact. If a result doesn't convince you, you can adjust or disable these stages in Settings → Master Chain.

14.2 Red clips and missing files

A card has turned red ("MISSING FILE") and doesn't respond to the click

The red border indicates that the audio file isn't reachable at the path stored in the project.

Possible causes:

- The file was moved or renamed on disk.

- The file was on an external disk or a USB stick that is now disconnected.
- The project was opened on a different computer, where the paths don't match.

Solutions:

1. **Reconnect the disk.** If the file was on an external drive, plug it back in.
2. **Return the file to its original location.** If it was moved, put it back at the original path.
3. **Replace the clip.** Drag the correct file into the grid again and delete the red card.
4. **Use Export project with audio in future.** The most effective prevention is to consolidate the audio into the project before moving or transferring it (Chapter 10).

14.3 MIDI problems

The controller isn't detected

1. **Connection.** Check that the controller is connected and recognized by the operating system. RLMP detects the connection and disconnection of devices in real time; if it doesn't appear, unplug and reconnect the USB cable.
2. **Driver.** Most USB-MIDI controllers are class-compliant and need no driver. For professional surfaces with proprietary drivers, check that the driver is installed.
3. **Check in Learn mode.** Enable MIDI Learn and press a key on the controller: if the card receives the mapping, the controller is detected.

The mapped clips don't respond to the controller keys

- **MIDI Learn mode is still active.** In MIDI Learn the controller keys register new mappings instead of triggering the clips. Disable the mode from the Tools menu.
- **The mapping was lost.** The clip mappings are in the `.lmp` file; check that the project was saved after the MIDI Learn session. The global-function mappings are instead tied to the individual computer.

14.4 Startup problems

The application you built won't start on macOS (Gatekeeper warning)

See section 2.3: right-click the application → Open, or unblock it from System Settings → Privacy & Security.

The application won't start on Windows (SmartScreen warning)

See section 2.2. Click More info and then Run anyway.

Abnormal behaviour at startup

If the software behaves unexpectedly on opening, close and reopen RLMP. If the problem persists, check that the installation path doesn't contain special characters that might interfere with loading the FFmpeg components.

14.5 Frequently asked questions

Can RLMP run a radio station unattended for 24 hours? No. RLMP is designed for live production: shows attended by an operator. It has no hourly scheduling and no automatic playlist rotation. The Automix view offers a limited, voluntary automation of the music flow only, active while the view is open (Chapter 7). For 24/7 automation there are dedicated tools (Zara Radio, PlayIt Live, Rivendell): they answer different needs.

What's the difference between Save and Save As? Save Project overwrites the open `.lmp` file, silently. Save As... always opens the dialog box and creates a new file, without touching the current one.

Can I use RLMP on an iPad or on mobile devices? Not as the main application: RLMP is desktop software for Windows and Linux, and can also be built on macOS. A tablet or a phone can, however, act as a **remote** via the browser, through Remote Control (Chapter 11).

Are `.lmp` files from earlier versions compatible with 1.15.33? Yes. When you open a project created with an earlier version, RLMP automatically updates its structure, including the columns added in the meantime, without modifying the file until you perform a save.

How do I update RLMP to a new version? The software checks for updates at startup and notifies you. On Windows and Linux ApplImage the installation is automatic from the update window; on Linux `.deb` the browser is opened on the download page; on macOS you build again from source. All the details are in Chapter 12.

Where are the automatic backups saved? In the `autosaves` folder inside the application data directory (`%APPDATA%\runtime-live-machine-pro\autosaves\` on Windows; equivalent paths on macOS and Linux, Chapter 10). The ten most recent snapshots are kept.

Does the software work offline? Yes, completely. RLMP doesn't require an internet connection to work. The network is used only for the update check (optional) and for Remote Control on the local network (optional).

Remote Control won't connect. Why? Check that the remote device is on the **same network** as the computer, that you entered the **correct PIN** (it changes at every launch), and that you're using the address shown in the Settings. Remember that Remote Control starts off at every launch of the application (Chapter 11). If the switch turned itself off with a message, port 8787 is in use: close the other copy of RLMP or the program using it, then turn it back on.