VACUUM-FLUCTUATION PROJECT · SIMULATION SUMMARY

Terahertz resonators for coupling to the $NbOCl_2$ ferron

We design gold resonators that trap terahertz light at 4.8 THz, the frequency of the ferron (a collective lattice vibration) in the crystal $NbOCl_2$. The more of the resonator's field that reaches the crystal, the more strongly light and crystal interact.

GOAL	Couple terahertz light strongly to the $NbOCl_2$ crystal at 4.8 THz.
STATUS	Two resonator designs simulated and on target; crystal placement and substrate identified.
NEXT	Add the crystal to both designs and compute the coupling strength.

Two designs, explored side by side

We are developing two complementary resonators in parallel: a **split ring (SRR)**, a gold ring with one gap, and a **slot ring (CSRR)**, the inverse pattern cut as slots into a gold sheet. For each design we:

1. size the pattern so it resonates at 4.8 THz;
2. map where its electric field is strongest;
3. decide where the crystal should sit and which substrate to use.




Figure 1. The two designs. (a, b) Electric field (darker blue is stronger) over each gold pattern at resonance: the split ring concentrates it in its single gap; the slot ring spreads it along its slots. (c) Both resonate at the 4.8 THz target.

What we found

- **Put the crystal over the gap (Fig. 2a).** On the split ring, the same piece of crystal shifts the resonance about ten times more when it sits over the gap (88 GHz) than beside the arm (8 GHz).
- **Sapphire is the best substrate (Fig. 2b).** It keeps the largest share of the field in the crystal region; silicon is the better alternative, GaAs the weakest.
- **The slot ring reaches the crystal more.** It places 12.6% of its field in the crystal region on sapphire, against 10.7% for the split ring.




Figure 2. (a) Resonance shift caused by the same small, higher-index patch placed over the gap or beside the arm of the split ring. (b) Share of the electric field inside the crystal region for both designs, each resized to 4.8 THz on three substrates.

Next steps

1. Add the $NbOCl_2$ crystal and its ferron to both designs and compute the coupling strength.
2. Choose between the split ring and the slot ring, and provide fabrication dimensions.
3. Fabricate and measure, and compare with the simulations.