



BATTERY PACK 6-CELL

21.6V

2100 mAh



BATTERY BMS (STANDARD | ECO)

OPERATIONAL & CHARGING

- SOLID BLUE** Vacuum is ON
 - BREATHING BLUE** Battery is Charging
 - FLASHING BLUE 3x3** Battery Low
 - SOLID GREEN** Charging Complete
-

DIAGNOSTICS & SAFETY

- SOLID WHITE** Charging Pause / Cell Stabilization
 - SOLID YELLOW** Temp Normalization Lock
 - FLASHING RED** **FAULT / ERROR CODE**
-

BATTERY CAPACITY (After Trigger Release)

- 1 FLASH** 0% - 33%
 - 2 FLASHES** 33% - 66%
 - 3 FLASHES** 66% - 100%
-

ON CHARGER CONNECT / DISCONNECT (Dual-Function)

- FLASHING BLUE** Cell Balance in **STANDARD** mode (1 Flash = 50mV)
 - FLASHING GREEN** Cell Balance in **ECO** mode (1 Flash = 50mV)
-

TO CHANGE MODE: Hold trigger down while connecting charger cable

- 10 x WHITE + 2 x BLUE** → **STANDARD MODE** (4.15V max.)
- 10 x WHITE + 2 x GREEN** → **ECO MODE** (4.00V max.)

For the Error codes and more information about custom firmware, please scan QR code.