

AMENDMENT NO. 1 JANUARY 2006
TO
IS 418:2004 TUNGSTEN FILAMENT LAMPS FOR
DOMESTIC AND SIMILAR GENERAL LIGHTING
PURPOSES

(*Fourth Revision*)

(*General*) — Substitute IS 15518 (Part 1) 2004 for Doc ET 23 (5291) wherever it appears

(*Page 1 clause 1.1 para 2 first line*) Substitute mm' for mn'

(*Page 1 clause 1.1 Notes*) — Add the following note after NOTE 2

3 Lamp data sheets for equivalently coated finishes or while finishes are under consideration

(*Page 1 clause 2.1*) — Insert the following at the appropriate place

'IS	No	Title
-----	----	-------

1112 (Part 1) 1989	Glass shells for general lighting service lamps Part 1 – 60 to 80 mm shell diameter (<i>second revision</i>)	
----------------------	--	--

12897 2001	Filaments for general service lamps — Guide (<i>first revision</i>)'	
---------------	--	--

(*Page 2, clause 5.3*) — Insert the following Note after 5.3

NOTE — The life test may be carried out as per the alternative method given in Annex J
This alternative method shall be valid up to 31 December 2000

(*Page 2 clause 5.3*) — Insert the following after 5.3

'5.4 For guidance, see IS 1112 (Part 1) 1989 for Glass shells and IS 12897 2001 for Tungsten filaments

(*Page 4, clause 11.2.4. informal table*) - Insert the following Note after the table

'NOTE The sample size for I TQ shall be 20 and qualifying limit for average life and life are 960 hours and 4 hours respectively when tested as per Annex J

(*Page 8, clause A-4.4.1 line 3*) — Substitute Table J-I of IS 15518 (Part 1) 2004' for 'Table K-I of Doc ET 23 (5291)'

Price Gr 2

Amend No. 1 to IS 418 : 2004

(Page 8 clause A-4.5. Note) Add the following at the end

'When testing is done at voltages in excess of the rated voltage, the lamps shall first be switched on at the rated voltage and then raised immediately to test voltage within 5???

(Page 15, Annex F, informal table, col 1, row 4) — Substitute 'V' for 'B'

(Page 16,. Annex G, col 3, rows 1 to 9 and 14 to 22) – Add 'A55' before 'A60'

(Page 17, Annex H) — Add the following Annex after Annex H

ANNEX J

(Clauses 5.4 and 11.2.4)

LIFE TEST PROCEDURE

J-1 CONDITION OF TESTING

J-1.1 Position of Burning

Lamp shall burn in a vertical position with cap up The lamp holders axis on the test-racks shall not deviate from the vertical by more than 5°

Lamps shall burn free from noticeable vibrations No vibrations or shocks should be perceptible when touching the lamp holders, either during burning or when switching 'on' or 'off'.

J-1.2 Lamp Holders

Lamp holders on life-test racks shall be of sturdy construction and shall be designed to ensure adequate electrical contact and to prevent overheating

The voltage drop between the point of measurement on the supply line and the holder contacts shall not exceed 0.1 percent of the test voltage

For bayonet lamp holders, the cap shall be substantially at the same potential as the contact which is not connected to the main supply lead equipped with a fuse

NOTES

- 1 It is recommended that lamp holders of the spring loaded plunger type shall not be used for prolonged testing