

AMENDMENT NO. 2 MAY 1978
TO
IS : 5142-1969 SPECIFICATION FOR
CONTINUOUSLY VARIABLE VOLTAGE
AUTO-TRANSFORMER S

Alteration

(Page 11, clause 10.9) — Substitute the following for the existing clause:

'10.9 Induced Voltage Test — To test the inter-turn insulation of the winding an ac voltage shall be applied to the terminals of winding for a single phase transformer and to the terminals of one winding at a time for a three phase transformer. The magnitude of the test voltage between any two terminals shall be twice the voltage appearing between those terminals when rated input voltage is applied to the input terminals. The test voltage shall be applied for 60 seconds for any frequency up to and including twice the rated frequency. When the test frequency exceeds twice the rated frequency the duration of the test shall be:

$$\frac{120 \times (\text{rated frequency})}{\text{test frequency}} \text{ seconds}$$

but not less than 15 seconds. The voltage shall be satisfactorily withstood.'

Addendum

(Page 7, clause 9.2) — Add the following new clause after 9.2:

'9.2.1 The transformers may also be marked with the ISI Certification Mark.

NOTE — The use of the ISI Certification Mark is governed by the provisions of the Indian Standards Institution (Certification Marks) Act and the Rules and Regulations made thereunder. The ISI Mark on products covered by an Indian Standard conveys the assurance that they have been produced to comply with the requirements of that standard under a well-defined system of inspection, testing and quality control which is devised and supervised by ISI and operated by the producer. ISI marked products are also continuously checked by ISI for conformity to that standard as a further safeguard. Details of conditions under which a licence for the use of the ISI Certification Mark may be granted to manufacturers or processors, may be obtained from the Indian Standards Institution.'