ETSI TS 103 973 V1.2.1 (2026-03)



TECHNICAL SPECIFICATION

Coded Multisource Media Format (CMMF) for Content Distribution and Delivery

EBU

Reference
RTS/JTC-121

Keywords
broadband, broadcast, CDN, container,
distribution, multimedia, multi-path, multi-source,
network coding, robustness

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
ETSI Search & Browse Standards application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on ETSI deliver repository.

Users should be aware that the present document may be revised or have its status changed,
this information is available in the Milestones listing.

If you find errors in the present document, please send your comments to
the relevant service listed under Committee Support Staff.

If you find a security vulnerability in the present document, please report it through our
Coordinated Vulnerability Disclosure (CVD) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.
No recommendation as to products and services or vendors is made or should be implied.
No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.
In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part may be reproduced or utilized in any form or by any means, electronic or mechanical, including photocopying and microfilm except as authorized by written permission of ETSI.
The content of the PDF version shall not be modified without the written authorization of ETSI.
The copyright and the foregoing restriction extend to reproduction in all media.

© ETSI 2026.
© European Broadcasting Union 2026.
All rights reserved.

Contents

Intellectual Property Rights 17
Foreword 17
Modal verbs terminology 17
Introduction 18
1 Scope 19
2 References 19
2.1 Normative references 19
2.2 Informative references 20
3 Definition of terms, symbols and abbreviations 20
3.1 Terms 20
3.2 Symbols 22
3.3 Abbreviations 23
4 Overview 24
4.0 Introduction 24
4.1 Source data 25
4.2 CMMF bitstream creation 26
4.2.1 Encoding CMMF 26
4.2.2 Symbol groups in CMMF 27
4.2.3 Decoding CMMF 28
4.2.4 Mapping to/from CMMF 29
4.3 Media delivery using CMMF 31
4.3.1 Overview 31
4.3.2 CMMF transport objects and transport sessions 31
4.3.3 CMMF delivery architecture reference points 32
4.3.4 CMMF delivery procedure 35
4.3.5 CMMF Configuration Information 38
4.3.6 CMMF as a Content Delivery Protocol 38
4.4 Overview of the specification 38
5 Bitstream syntax 39
5.0 Bitstream organization 39
5.1 Semantics of syntax specification 41
5.1.1 Pseudocode syntax 41
5.1.2 Bitstream variable syntax 41
5.1.3 Bitstream structure syntax 41
5.1.4 Iteration and conditional operators 42
5.1.5 Boolean operations 42
5.1.6 Labels and comments 42
5.1.7 Operational variables not in the bitstream 43
5.1.8 Arrays 43
5.1.9 Bit field encoding 43
5.2 Syntax specification 44
5.2.1 cmmf_bitstream() 44
5.2.2 subatom() 44
5.2.3 sync() 45
5.2.4 bitstream_header() 45
5.2.5 block_header() 46
5.2.6 addl_cce_parameters() 48
5.2.7 prng_parameters() 48
5.2.8 packet() 48
5.2.9 packet_header() 49
5.2.10 encoder_content_info() 49
5.2.11 media_segment_info() 50
5.2.12 cmmf_time() 53

5.2.13 chunked_subatom() 53
5.2.14 block_group_directory() 54
5.2.15 fb_integrity() 54
5.2.16 packet_integrity() 55
5.2.17 coefficient_vector() 55
5.2.18 extension() 55
5.2.19 packet_header_only() 55
5.2.20 rfc5052_information() 56
5.2.21 packet_group() 56
5.2.22 packet_group_header() 57
5.2.23 num_bits_code() 58
5.2.24 block_index_or_count_value() 58
5.2.25 multi_block_packet_group() 58
5.2.26 mbpg_header() 59

6 Bitstream description 60
6.0 Introduction 60
6.1 Description of bitstream elements 60
6.1.1 cmmf_bitstream() 60
6.1.2 subatom() 60
6.1.2.0 Introduction 60
6.1.2.1 subatom_id, subatom_id_ext 60
6.1.2.2 b_bitstream_id_present 61
6.1.2.3 sas_bits 61
6.1.2.4 bitstream_id 61
6.1.2.5 subatom_size 61
6.1.3 sync() 61
6.1.3.0 Introduction 61
6.1.3.1 syncword 61
6.1.3.2 version 62
6.1.3.3 b_content_encode_uuid 62
6.1.3.4 content_encode_uuid 62
6.1.4 bitstream_header() 62
6.1.4.0 Introduction 62
6.1.4.1 content_source_size 62
6.1.4.2 content_source_type 62
6.1.4.3 b_content_source_split 62
6.1.4.4 content_soure_split_start, content_source_split_end 62
6.1.4.5 code_type, code_type_ext 63
6.1.4.6 b_rfc5052, rfc5052_information(), b_addl_rfc5052_information_present 63
6.1.4.7 block_count_minus1, block_count 63
6.1.4.8 b_content_block_separate_sources 64
6.1.4.9 num_content_block_sources_minus1 64
6.1.4.10 b_profile_information_present 64
6.1.4.11 profile_type_size, profile_type 64
6.1.4.12 profile_description 64
6.1.4.13 b_block_cc_encrypted 64
6.1.4.14 bitstream_encryption_key_id_size_exp 65
6.1.4.15 bitstream_encryption_key_id 65
6.1.5 block_header() 65
6.1.5.0 Introduction 65
6.1.5.1 block_index 65
6.1.5.2 block_size 65
6.1.5.3 block_symbol_size 65
6.1.5.4 bns_bits 65
6.1.5.5 block_num_symbols 65
6.1.5.6 b_block_max_symbol_index_present 66
6.1.5.7 bmsi_bits 66
6.1.5.8 block_max_symbol_index 66
6.1.5.9 b_block_content_source_index_present 66
6.1.5.10 block_content_source_index 66
6.1.5.11 b_block_composite_sources 66

6.1.5.12 block_num_composite_sources_minus1 66
6.1.5.13 bcss_bits 66
6.1.5.14 block_composite_source_size 66
6.1.5.15 b_addl_block_coding_info_present 67
6.1.5.16 addl_block_coding_mask 67
6.1.5.17 b_addl_window_info_present 67
6.1.5.18 b_reserved_block_coding_params_present 67
6.1.5.19 block_mask 67
6.1.5.20 b_sufficient_symbols_present 68
6.1.5.21 bsp_bits 68
6.1.5.22 block_symbols_present 68
6.1.5.23 block_field_size_exp 68
6.1.5.24 Encrypted Coefficients 69
6.1.5.24.0 Introduction 69
6.1.5.24.1 block_cc_encryption_info_size_bits_code 69
6.1.5.24.2 byte_align 70
6.1.5.24.3 block_cc_encryption_info_size 70
6.1.5.24.4 block_cc_encryption_algorithm 70
6.1.5.24.5 block_cc_encryption_mode 70
6.1.5.24.6 block_cce_key_size_exp, block_cce_key 70
6.1.5.24.7 b_addl_block_cce_params_present 71
6.1.5.24.8 addl_cce_parameters() 71
6.1.5.25 Pseudorandom Noise Generator (PRNG) 71
6.1.5.25.0 Introduction 71
6.1.5.25.1 prng_type 72
6.1.5.25.2 prng_seed_bits_code 72
6.1.5.25.3 prng_seed 72
6.1.5.25.4 prng_density_percentage 73
6.1.6 packet() 73
6.1.6.0 Introduction 73
6.1.6.1 packet_block_index 73
6.1.6.2 coded_symbol 73
6.1.7 packet_header() 73
6.1.7.0 Introduction 73
6.1.7.1 b_systematic_symbol 74
6.1.7.2 packet_mask 74
6.1.7.3 psi_bits 75
6.1.7.4 packet_symbol_index 75
6.1.7.5 Encryption Parameters 75
6.1.7.5.0 Introduction 75
6.1.7.5.1 b_systematic_symbol_encrypted 76
6.1.7.5.2 b_addl_packet_cce_params_present 76
6.1.7.6 window_start_index, window_stop_index 76
6.1.7.7 byte_align 76
6.1.8 encoder_content_info() 76
6.1.8.0 Introduction 76
6.1.8.1 b_encoder_id_present 76
6.1.8.2 encoder_uuid 77
6.1.8.3 Content Identification 77
6.1.8.4 b_content_id_present 77
6.1.8.4.0 Introduction 77
6.1.8.4.1 content_id_type 77
6.1.8.4.2 content_id_size_minus1 77
6.1.8.4.3 content_id 77
6.1.8.5 b_content_location_present 77
6.1.8.6 content_location_size, content_location 78
6.1.8.7 b_content_type_present 78
6.1.8.8 content_type_size, content_type 78
6.1.8.9 b_content_header_present 78
6.1.8.10 content_header_size, content_header 78
6.1.8.11 b_file_integrity_present 78
6.1.8.12 b_media_preso_dur_present 78

6.1.9 media_segment_info() 79
6.1.9.0 Introduction 79
6.1.9.1 media_segment_block_index, media_segment_block_index_ext 79
6.1.9.2 media_segment_index, media_segment_index_ext 79
6.1.9.3 b_composite_source_index _present 79
6.1.9.4 media_segment_composite_source_index 79
6.1.9.5 b_asset_name_present 79
6.1.9.6 asset_name_size, asset_name 79
6.1.9.7 segment_tag_mask 80
6.1.9.8 segidx_bits, segcnt_bits 80
6.1.9.9 segment_index 80
6.1.9.10 segment_count 80
6.1.9.11 b_media_mime_type_present 80
6.1.9.12 media_mime_type_size, media_mime_type 80
6.1.9.13 b_media_codec_present 80
6.1.9.14 media_codec_size, media_codec 80
6.1.9.15 b_bit_rate_present 81
6.1.9.16 bit_rate_bits_code 81
6.1.9.17 bit_rate 81
6.1.9.18 b_ms_content_type_present 81
6.1.9.19 ms_content_type 81
6.1.9.20 b_ms_content_type_info_present 81
6.1.9.21 b_aspect_ratio_present 81
6.1.9.22 sample_aspect_ratio 81
6.1.9.23 sar_width, sar_height 82
6.1.9.24 b_dynamic_resolution_video 82
6.1.9.25 b_resolution_present 82
6.1.9.26 resolution_width, resolution_height 82
6.1.9.27 b_frame_rate_present 82
6.1.9.28 frame_rate 82
6.1.9.29 b_hdr_info_present 82
6.1.9.30 hdr_compatibility_mask 83
6.1.9.31 b_addl_hdr_info_present 83
6.1.9.32 hdr_compat_mask_index 83
6.1.9.33 hdr_profile 83
6.1.9.34 hdr_level 83
6.1.9.35 hdr_compatibility_id 83
6.1.9.36 b_addl_video_info_present 83
6.1.9.37 b_sampling_freq_present 83
6.1.9.38 b_sampling_freq_is_48k 84
6.1.9.39 sampling_frequency 84
6.1.9.40 b_audio_config_present 84
6.1.9.41 audio_channel_config 84
6.1.9.42 b_audio_props_present 85
6.1.9.43 b_virtualized_bin 85
6.1.9.44 b_object_audio 85
6.1.9.45 b_complexity_index_present 85
6.1.9.46 complexity_index 85
6.1.9.47 b_addl_audio_info_present 86
6.1.9.48 b_addl_ms_content_type_info_present 86
6.1.9.49 accessibility_mask 86
6.1.9.50 language_size, language 86
6.1.10 cmmf_time() 86
6.1.10.0 Introduction 86
6.1.10.1 b_ddhhmmss 86
6.1.10.2 DD:HH:MM:SS format 87
6.1.10.3 int_seconds_bits_code 87
6.1.10.4 int_seconds 87
6.1.10.5 b_fract_seconds_present 87
6.1.10.6 fract_seconds_bits_code 87
6.1.10.7 fract_seconds 88
6.1.11 chunked_subatom() 88

6.1.11.0 Introduction 88
6.1.11.1 chunk_segment_id 88
6.1.11.2 chunk_segment_index 88
6.1.11.3 num_chunk_segments 88
6.1.11.4 original_subatom_id, original_subatom_id_ext 88
6.1.11.5 oss_bits 89
6.1.11.6 original_subatom_size 89
6.1.11.7 byte_align 89
6.1.11.8 chunked_subatom_segment_data 89
6.1.12 block_group_directory() 89
6.1.12.0 Introduction 89
6.1.12.1 block_group_dir_mask 89
6.1.12.2 block_header_subatom_offset[block] 90
6.1.12.3 num_packet_groups[block] 90
6.1.12.4 packet_group_index[block][pg] 90
6.1.12.5 packet_group_subatom_offset[block][pg] 90
6.1.12.6 num_multi_block_packet_groups 90
6.1.12.7 multi_block_packet_group_subatom_offset[mbpg] 90
6.1.13 fb_integrity() 90
6.1.13.0 Introduction 90
6.1.13.1 fb_hash_type 90
6.1.13.2 fb_hash_algorithm 91
6.1.13.3 fb_hash_size 91
6.1.13.4 b_fb_integrity_ext 91
6.1.13.5 fb_hash 91
6.1.14 packet_integrity() 92
6.1.14.0 Introduction 92
6.1.14.1 packet_hash_algorithm 92
6.1.14.2 packet_hash_size 92
6.1.14.3 b_packet_integrity_ext 92
6.1.14.4 packet_hash 93
6.1.15 coefficient_vector() 93
6.1.15.0 Introduction 93
6.1.15.1 coded_symbol_coeff[index] 93
6.1.16 extension() 93
6.1.16.0 Introduction 93
6.1.16.1 extension_byte_size 93
6.1.17 packet_header_only() 93
6.1.18 packet_group() 94
6.1.18.0 Introduction 94
6.1.18.1 packet_group_block_index 94
6.1.18.2 packet_group_index 94
6.1.18.3 pgns_bits 94
6.1.18.4 packet_group_num_symbols 94
6.1.18.5 packet_group_type 94
6.1.18.6 coded_symbol 94
6.1.19 packet_group_header() 95
6.1.19.0 Introduction 95
6.1.19.1 packet_group_symbol_arrangement 95
6.1.19.2 packet_group_mask 95
6.1.19.3 pgsi_bits 96
6.1.19.4 packet_group_symbol_index 96
6.1.19.5 pgfsi_bits 96
6.1.19.6 packet_group_first_symbol_index 96
6.1.19.7 packet_group_index_difference 96
6.1.19.8 pgfsii_bits 97
6.1.19.9 Symbol Arrangements in a Packet Group 97
6.1.19.10 Encryption Parameters 97
6.1.19.10.0 Introduction 97
6.1.19.10.1 b_addl_packet_group_cce_params_present 98
6.1.20 num_bits_code() 98
6.1.20.0 Introduction 98

6.1.20.1 bits_code 98
6.1.21 block_index_or_count_value() 98
6.1.21.0 Introduction 98
6.1.21.1 block_index_or_count, block_index_or_count_ext 98
6.1.22 multi_block_packet_group() 98
6.1.22.0 Introduction 98
6.1.22.1 mbpg_index 99
6.1.22.2 mbpg_start_block_index 99
6.1.22.3 mbpg_num_blocks 99
6.1.22.4 mbpg_num_symbols 99
6.1.22.5 coded_symbol 99
6.1.23 mbpg_header() 100
6.1.23.0 Introduction 100
6.1.23.1 mbpg_symbol_arrangement 100
6.1.23.2 mbpgsi_bits 100
6.1.23.3 mbpg_source_block_index, mbpg_symbol_index 101
6.1.23.4 mbpgfsi_bits 101
6.1.23.5 mbpg_first_symbol_index, b_mbpg_is_symbol_group_subset, mbpg_symbol_group_subset_index 101
6.1.23.6 mbpg_index_difference 101
6.1.23.7 mbpgsai_bits_code 101
6.1.23.8 Symbol Arrangements in a Multiple Block Packet Group 102
6.1.23.9 b_mbpg_integrity_present 106
6.1.23.10 b_mbpg_header_ext_present 106

7 Design considerations 106
7.0 Introduction 106
7.1 Coding coefficients 106
7.1.0 Generating coding coefficients using a PRNG 106
7.1.1 Coefficient density control 108
7.1.2 Mersenne twister PRNG type 108
7.2 Handling variable source symbol size 108
7.3 Encrypting coding coefficient information 109
7.3.0 Introduction 109
7.3.1 Using a bitstream/session key and symmetric keys 110

Annex A (normative): xCD-1 112

A.0 Introduction 112

A.1 Encoding 112

A.2 Decoding 114

Annex B (informative): Media service architecture Examples 117

B.0 Introduction 117

B.1 MPEG-DASH HTTP adaptive streaming service example 117

Annex C (informative): Example bitstreams 122

C.0 Introduction 122

C.1 Multisource Video-on-Demand 122
C.1.0 Multisource Video-on-Demand example using code_type xCD-1 122
C.1.1 Bitstream construction 122
C.1.2 Sync construction 123
C.1.3 Subatom construction 124
C.1.3.1 Bitstream header subatom construction 124
C.1.3.2 Block header subatom construction 126
C.1.3.3 Encoder content information subatom construction 129
C.1.3.4 Media segment information subatom construction 131
C.1.3.5 Packet subatom construction - systematic symbol 135
C.1.3.6 Packet subatom construction - coded symbol 137

C.2 Encrypted coding coefficient information example using CMMF 139

Annex D (normative): Content Delivery Protocol instantiations 141

D.0 Introduction 141

D.1 General principles of CMMF Content Delivery Protocols based on FEC Building Block 141
D.1.1 Introduction 141
D.1.2 FEC Building Block principles 141
D.1.3 FEC Schemes and related information 142
D.1.4 FEC Scheme information in CMMF 142
D.1.5 Configuration Information parameters 144
D.1.6 Example CDP instantiations 145

D.2 FDT-based CDP Instantiation 145
D.2.1 Introduction 145
D.2.2 Procedures for FDT-based CDP instantiation 146
D.2.3 Extended File Delivery Table 147
D.2.3.1 Semantics 147
D.2.3.2 Extended FDT Schema for CMMF 148
D.2.3.3 Extended FDT Description for CMMF 149
D.2.3.4 IANA registration for Extended FDT Description 150
D.2.4 Transport object formats 151
D.2.4.1 General 151
D.2.4.2 Source objects 151
D.2.4.3 Coded/repair objects 151
D.2.4.3.1 General 151
D.2.4.3.2 Mapping of FEC Payload ID information to transport blocks 153
D.2.4.3.2.1 General 153
D.2.4.3.2.2 Symbol group arrangement 3: encoding symbol interleaving 155
D.2.4.3.2.3 Symbol group arrangement 2: source symbol interleaving 156
D.2.5 Examples 157
D.2.5.1 Single file - source and partial encoding object 157
D.2.5.2 Multiple files - self-contained objects including source symbols 158
D.2.6 Potential receiver operation 158

D.3 URL Translation-based CDP instantiation 159
D.3.1 Introduction 159
D.3.2 Procedures for URL Translation-based CDP instantiation 159
D.3.2.1 Introduction 159
D.3.2.2 Procedure for URL Translation-based CMMF CDP provisioning, content ingest, and CMMF Transport Object preparation 160
D.3.2.3 Procedure for URL Translation-based CMMF CDP delivery 162
D.3.3 CMMF Configuration Information for URL Translation-based CDP 163
D.3.3.1 Introduction 163
D.3.3.2 Source Object URL to CMMF Transport Object URL mapping procedures 163
D.3.3.2.1 General 163
D.3.3.2.2 Mapping complete object URLs 163
D.3.3.2.3 Mapping sub-object URLs using byte range requests 164
D.3.3.2.4 Mapping HTTP headers and query parameters 164
D.3.3.3 URL Translation-based CMMF Configuration Information document 165
D.3.3.3.1 General 165
D.3.3.3.2 Semantics 165
D.3.3.3.3 Schema 167
D.3.3.3.4 IANA registration of CMMF Configuration Information document for the URL Translation-based CMMF CDP 170
D.3.3.3.4.1 General 170
D.3.3.3.4.2 Registration of MIME media type for CMMF Configuration Information document 170
D.3.3.3.4.3 cmmfProfiles parameter 171
D.3.3.3.4.4 cmmfCodeTypes parameter 172
D.3.4 Example CMMF Configuration Information document 172

Annex E (normative): CMMF Encoder configurations 175

E.0 Introduction 175
E.1 Base CMMF Encoder configuration 175
E.1.1 Introduction 175
E.1.2 Semantics of the CMMF Encoder configuration 175
E.1.3 Schema of the CMMF Encoder configuration 179
E.1.4 IANA registration of CMMF Encoder configuration 183
E.1.4.1 General 183
E.1.4.2 Registration of MIME media type for CMMF Encoder configuration 183
E.1.4.3 profile parameter 184
E.1.4.4 codeType parameter 184
E.1.5 Example use of CMMF Encoder configuration 184
Annex F (normative): CMMF bitstream profiles 186
F.0 Introduction 186
F.1 CMMF bitstream profile A 186
F.1.1 Introduction 186
F.1.2 CMMF bitstream layout 186
F.1.3 Profile description 187
F.1.3.1 Introduction 187
F.1.3.2 Syntax specification 188
F.1.3.3 Bitstream description 188
F.1.3.3.0 Introduction 188
F.1.3.3.1 coefficient_method 188
F.1.3.3.2 b_systematic_symbols_used 189
F.1.3.3.3 b_encrypted_coefficients 189
F.1.3.3.4 b_block_integrity 189
F.1.3.3.5 b_packet_integrity 189
F.1.3.3.6 target_symbols_present_percentage 189
F.1.3.3.7 padding 189
F.1.4 Required fields and their values 189
F.1.4.1 Introduction 189
F.1.4.2 Required Fields and values applying to all CMMF bitstreams 190
F.1.4.3 code_type 0 (xCD-1) required fields and values 190
F.1.4.3.1 Introduction 190
F.1.3.3.2 Block PRNG coefficient information 191
F.1.4.3.3 Packet PRNG coefficient information 191
F.1.4.3.3 Coefficient vectors coefficient information 191
F.1.4.3.4 PRNG parameters 192
F.1.4.3.5 Systematic coded_symbol 192
F.1.4.3.6 Encrypted coefficient information 193
F.1.4.3.6.0 General 193
F.1.4.3.6.1 Encrypted block PRNG coefficient information 193
F.1.4.3.6.2 Encrypted packet PRNG coefficient information 194
F.1.4.3.6.3 Encrypted coefficient vector information 195
F.1.4.3.6.4 Encrypted systematic coded_symbol 196
F.1.4.4 code_type 1 (Raptor), 5 (Reed-Solomon), and 6 (RaptorQ) required fields and values 196
F.1.4.5 Block integrity required fields and values 197
F.1.4.6 Packet integrity required fields and values 197
F.1.5 Object-based sources providing complete objects 198
F.1.6 Object-based live or streaming sources 199
F.1.7 CMMF bitstream/Transport Object deployment 199
History 201

List of figures

Figure 1: CMMF layer within multimedia transport stack 25
Figure 2: CMMF encode example 27
Figure 3: Example symbol groups 28
Figure 4: CMMF decode example 29
Figure 5: CMMF bitstream encoding/packaging 30
Figure 6: CMMF bitstream decoding 30
Figure 7: Generic Example CMMF delivery/transport sessions 31
Figure 8: Delivery session model for CMMF 32
Figure 9: CMMF delivery architecture reference points 33
Figure 10: HTTP-Based Adaptive Streaming CMMF Delivery Procedure Example 36
Figure 11: High-level CMMF bitstream organization 40
Figure 12: Example symbol arrangement for mbpg_symbol_arrangement=0010b (Source-Symbol Interleaved Arrangement) 104
Figure 13: Example symbol arrangement for mbpg_symbol_arrangement=0011b (Encoded-Symbol Interleaved Arrangement) 106
Figure 14: Block PRNG 107
Figure 15: Packet PRNG 107
Figure 16: Handling variable size data 109
Figure 17: Bitstream, block, key management 110
Figure 18: Client process for decryption 111
Figure 19: Bitstream and key download process 111
Figure A.1: xCD-1 segment to symbols 113
Figure A.2: xCD-1 symbol vector and coefficient matrix 113
Figure A.3: xCD-1 coefficient matrix 114
Figure A.4: xCD-1 coded symbol vector and decoded coefficient matrix 115
Figure A.5: xCD-1 symbol reconstruction 115
Figure A.6: xCD-1 data extraction 116
Figure B.1: MPEG-DASH with CMMF Delivery System Example 117
Figure B.2: CMMF reference architecture in relation to MPEG-DASH HTTP adaptive streaming example 118
Figure B.3: Example MPEG-DASH master manifest 118
Figure B.4: CMMF bitstreams generated to deliver the MPEG-DASH packaged content 119
Figure B.5: CMMF request and content delivery example for MPEG-DASH 120
Figure C.1: Multi-source CDN-client communication 122
Figure C.2: CMMF multisource example bitstream arrangement 123

Figure C.3: Bitstream with example encrypted coding coefficient information....140
Figure D.1: High-level procedure for CMMF delivery using FDT-based CDP....146
Figure D.2: Formation of transport objects from source objects....154
Figure D.3: Symbol arrangement for arrangement 3....156
Figure D.4: Symbol arrangement for arrangement 2....157
Figure D.5: High-level procedure for URL translation-based CMMF provisioning and preparation....160
Figure D.6: High-level procedure for URL Translation-based CMMF CDP delivery....162
Figure F.1: CMMF bitstream layout for CMMF bitstream profile A....187

List of tables

Table 1: Example mapping....30
Table 2: Example of bitstream variable....41
Table 3: Example of bitstream structure....41
Table 4: Example of shorthand If syntax format....42
Table 5: Example of expanded If syntax format....42
Table 6: Example of Boolean operation syntax format....42
Table 7: Example of bitstream label....42
Table 8: Example of bitstream comment....43
Table 9: Example of operational variable format....43
Table 10: Bit field descriptors....43
Table 11: Syntax of cmmf_bitstream()....44
Table 12: Syntax of subatom()....44
Table 13: Syntax of sync()....45
Table 14: Syntax of bitstream_header()....45
Table 15: Syntax of block_header()....46
Table 16: Syntax of addl_cce_parameters()....48
Table 17: Syntax of prng_parameters()....48
Table 18: Syntax of packet()....48
Table 19: Syntax of packet_header()....49
Table 20: Syntax of encoder_content_info()....49
Table 21: Syntax of media_segment_info()....50
Table 22: Syntax of cmmf_time()....53
Table 23: Syntax of chunked_subatom()....53
Table 24: Syntax of block_group_directory()....54
Table 25: Syntax of fb_integrity()....54
Table 26: Syntax of packet_integrity()....55
Table 27: Syntax of coefficient_vector()....55
Table 28: Syntax of extension()....55
Table 29: Syntax of packet_header_only()....55
Table 30: Syntax of rfc5052_information()....56
Table 31: Syntax of packet_group()....56
Table 32: Syntax of packet_group_header()....57
Table 33: Syntax of num_bits_code()....58

Table 34: Syntax of block_index_or_count_value() 58
Table 35: Syntax of multi_block_packet_group() 58
Table 36: Syntax of mbpg_header() 59
Table 37: subatom_id meaning 60
Table 38: Subatom dependencies 61
Table 39: content_source_type meaning 62
Table 40: code_type meaning 63
Table 41: Object Transmission Information Fields 63
Table 42: addl_block_coding_mask meaning 67
Table 43: block_mask meaning 67
Table 44: block_field_size_exp information 69
Table 45: block_cc_encryption_info_size_bits_code meaning 69
Table 46: block_cc_encryption_algorithm meaning 70
Table 47: block_cc_encryption_mode meaning 70
Table 48: cce_parameter_type meaning 71
Table 49: block_prng_type meaning 72
Table 50: block_prng_seed_bits_code meaning 72
Table 51: packet_mask meaning 74
Table 52: content_id_type description 77
Table 53: segment_tag_mask meaning 80
Table 54: bit_rate_bits_code meaning 81
Table 55: ms_content_type description 81
Table 56: frame_rate values 82
Table 57: hdr_compatibility_mask values 83
Table 58: sampling_frequency values 84
Table 59: audio_channel_config values 84
Table 60: accessibility_mask meaning 86
Table 61: DD:HH:MM:SS format fields and meaning 87
Table 62: int_seconds_bits_code meaning 87
Table 63: fract_seconds_bits_code meaning 87
Table 64: fract_seconds range and divisor 88
Table 65: block_group_dir_mask meaning 89
Table 66: fb_hash_type meaning 90
Table 67: fb_hash_algorithm meaning 91
Table 68: fb_hash_size meaning 91

Table 69: Allowed fb_hash_size values based on fb_hash_algorithm 91
Table 70: packet_hash_algorithm meaning 92
Table 71: packet_hash_size meaning 92
Table 72: Allowed packet_hash_size values based on packet_hash_algorithm 92
Table 73: packet_group_type meaning 94
Table 74: packet_group_symbol_arrangement Meaning 95
Table 75: packet_group_mask meaning 95
Table 76: Arithmetic coded symbol arrangement in a packet group pseudocode 97
Table 77: bits_code meaning 98
Table 78: mbpg_symbol_arrangement Meaning 100
Table 79: mbpgsai_bits_code meaning 101
Table 80: Separate systematic and interleaved coded symbol arithmetic sequences symbol arrangement in a multi-block group pseudocode 102
Table 81: Interleaved by block coded symbol arithmetic sequences symbol arrangement in a multi-block group pseudocode 105
Table 82: Density controller pseudocode 108
Table 83: Mersenne twister pseudocode 108
Table C.1: sync() structure construction 123
Table C.2: Bitstream header subatom construction 124
Table C.3: Block header subatom construction 126
Table C.4: Encoder content info subatom construction 129
Table C.5: Media segment info subatom construction 131
Table C.6: Packet subatom - systematic packet construction 135
Table C.7: Packet subatom - coded packet construction 137
Table D.1: Parameters and Coding of FEC schemes used in CMMF 143
Table D.2: FEC scheme parameters to CMMF mapping 143
Table D.3: Example Configuration Information parameters 144
Listing D.1: Extended FDT schema for CMMF 148
Listing D.2: Extended FDT example for a single file 157
Listing D.3: Extended FDT example for multiple files 158
Table D.4: Semantics of the URL Translation-based CMMF Configuration Information document 165
Listing D.4: CMMF Configuration Information document schema 167
Table D.5: cmmfProfiles parameter definition for CMMF Configuration Information document MIME media type 171
Table D.6: cmmfCodeTypes parameter definition for CMMF Configuration Information document MIME media type 172
Listing D.5: Example MPEG-DASH MPD 173

Listing D.6: Example CMMF Configuration Information document....174
Table E.1: Semantics of the CMMF Encoder configuration....175
Listing E.1: CMMF Encoder configuration schema....179
Table E.2: profile parameter definition for CMMF Encoder configuration MIME media type....184
Table E.3: codeType parameter definition for CMMF Encoder configuration MIME media type....184
Listing E.2: Example CMMF Encoder configuration....184
Table F.1: Syntax of CMMF Bitstream Profile A profile_description....188
Table F.2: coefficient_method meaning....188
Table F.3: Required CMMF bitstream fields and values....190
Table F.4: Required CMMF bitstream fields and values for code_type 0 using a block PRNG....191
Table F.5: Required CMMF bitstream fields and values for code_type 0 using a packet PRNG....191
Table F.6: Required CMMF bitstream fields and values for code_type 0 using coefficient vectors....192
Table F.7: Required CMMF bitstream fields and values when prng_parameters() is present....192
Table F.8: Required CMMF bitstream fields when coded_symbol is systematic....192
Table F.9: Field values when encrypted coefficient information is not used....193
Table F.10: Field values when block PRNG coefficient information is encrypted....193
Table F.11: Field values when packet PRNG coefficient information is encrypted....194
Table F.12: Field values when packet coefficient vector information is encrypted....195
Table F.13: Field values when systematic coded_symbol is encrypted....196
Table F.14: Required CMMF bitstream fields and values for code_type 1, 5, and 6....197
Table F.15: Required CMMF bitstream fields and values for block integrity verification....197
Table F.16: Required CMMF bitstream fields and values for packet integrity verification....198
Table F.17: Required CMMF bitstream fields and values for sources providing complete objects....198
Table F.18: Required CMMF bitstream fields and values for live or streaming sources....199

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI IPR online database.

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM**® and the GSM logo are trademarks registered and owned by the GSM Association.

Foreword

This Technical Specification (TS) has been produced by Joint Technical Committee (JTC) Broadcast of the European Broadcasting Union (EBU), Comité Européen de Normalisation ELECtrotechnique (CENELEC) and the European Telecommunications Standards Institute (ETSI).

NOTE: The EBU/ETSI JTC Broadcast was established in 1990 to co-ordinate the drafting of standards in the specific field of broadcasting and related fields. Since 1995 the JTC Broadcast became a tripartite body by including in the Memorandum of Understanding also CENELEC, which is responsible for the standardization of radio and television receivers. The EBU is a professional association of broadcasting organizations whose work includes the co-ordination of its members' activities in the technical, legal, programme-making and programme-exchange domains. The EBU has active members in about 60 countries in the European broadcasting area; its headquarters is in Geneva.

European Broadcasting Union
CH-1218 GRAND SACONNEX (Geneva)
Switzerland
Tel: +41 22 717 21 11
Fax: +41 22 717 24 81

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the ETSI Drafting Rules (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Introduction

The Coded Multisource Media Format (CMMF) is an extensible container format designed to facilitate the management and interchange of audio-visual media and metadata in one or more coded representations (e.g. encoded with application-layer, linear, network, or channel codes).

The coded media representations supported by CMMF enable the efficient use of multisource, multipath and multi-access connectivity for network-delivered media applications.

Additionally, CMMF supports signalling and encapsulations of:

- Coding type.
- Media-related information and metadata.
- Payload integrity information.
- Encoder UUID.

This bitstream format provides a standard to the industry so that a single container format can be used for a wide variety of content and use cases.

Motivation

CMMF provides a generic container format that supports multimedia (e.g. video and audio streaming, broadcast, XR, video conferencing, and online gaming) delivery through coding the underlying content. This format supports multiple types of codes (currently xCD-1, RaptorQ, and Reed-Solomon) and can be optimized for a range of networks and use cases. Specifically, CMMF supports efficient decentralized multi-source and multi-path content delivery for use cases such as audio and video streaming that require high availability/robustness but also have strict latency and bandwidth constraints. CMMF is designed to operate with existing and future streaming source formats (e.g. HLS, MPEG-DASH, CMAF, etc.) and network protocols (e.g. HTTP, TCP, UDP, WebRTC, etc.), while remaining protocol-agnostic. A multisource media encoder is envisioned to take an existing packaged media format as a source and generate CMMF bitstreams for delivery over networks to clients for rendering.

CMMF provides a flexible and extensible framework for managing the delivery of encoded multimedia content. Standardizing the container format rather than a code type enables cooperation within the industry by creating a common interchange format for the distribution and delivery of encoded content. This allows Service Providers (e.g. Mobile Network Operators or media platforms) to distribute media in an encoded format that can be interpreted and decoded by their partners.

Document structure

Clause 4 gives an overview of the functionality provided by the CMMF bitstream format.

Clause 5 provides the definition of the CMMF bitstream format, with clause 5.1 defining the semantics, and clause 5.2 the syntax.

Clause 6 provides a description of the bitstream elements.

Clause 7 gives guidance for implementations of the CMMF container format.

Annex A provides the definition of the xCD-1 coding format.

Annex B provides a high-level example of a Media Service Architecture with CMMF.

Annex C provides application examples of the CMMF container format, with different use cases and coding formats.

Annex D provides a mapping of CMMF to IETF RFC 5052 [15] principles, specifies multiple Content Delivery Protocols, and includes application examples.

Annex E provides the definition of a CMMF Encoder configuration.

Annex F provides the definitions of CMMF bitstream profiles.

1 Scope

The present document specifies a Coded Multisource Media Format (CMMF) container. This format is used to support storage and delivery of linear, network or channel coded multisource audio/video media over networks. It also specifies the xCD-1 linear coding type. The present document also includes examples.

2 References

2.1 Normative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

Referenced documents which are not found to be publicly available in the expected location might be found in the ETSI docbox.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long-term validity.

The following referenced documents are necessary for the application of the present document.

[1] IETF RFC 9562: "Universally Unique IDentifiers (UUIDs)".

[2] EIDR: "EIDR: ID Format", V1.51, October 5, 2017.

[3] IETF RFC 8107: "Advertising Digital Identifier (Ad-ID) URN Namespace Definition".

[4] ISO 639: "Code for individual languages and language groups".

[5] IETF RFC 6381: "The 'Codecs' and 'Profiles' Parameters for "Bucket" Media Types".

[6] IETF RFC 4646: "Tags for Identifying Languages".

[7] ISO/IEC 646:1991: "Information technology — ISO 7-bit coded character set for information interchange".

[8] Mersenne Twister Home Page: "A very fast random number generator Of period 2^{19937}-1".

[9] FIPS PUB 180-4: "Secure Hash Standard (SHS)", August 2015.

[10] ISO/IEC 23091-2: "Information technology — Coding-independent code point — Part 2: Video".

[11] IETF RFC 3629: "UTF-8, a transformation format of ISO 10646".

[12] IETF RFC 4648: "The Base16, Base32, and Base64 Data Encodings".

[13] IETF RFC 6330: "RaptorQ Forward Error Correction Scheme for Object Delivery".

[14] IETF RFC 5510: "Reed-Solomon Forward Error Correction (FEC) Schemes".

[15] IETF RFC 5052: "Forward Error Correction (FEC) Building Block".

[16] IETF RFC 5053: "Raptor Forward Error Correction Scheme for Object Delivery".

[17] IETF RFC 5775: "Asynchronous Layered Coding (ALC) Protocol Instantiation".

[18] IETF RFC 6726: " FLUTE - File Delivery over Unidirectional Transport".

[19] ETSI TS 126 346: "Universal Mobile Telecommunications System (UMTS); LTE; 5G; Multimedia Broadcast/Multicast Service (MBMS); Protocols and codecs (3GPP TS 26.346)".

[20] Recommendation ITU-R BS.2051-3: "Advanced sound system for programme production".

[21] IETF RFC 1321: "The MD5 Message-Digest Algorithm".

[22] IETF RFC 4337: "MIME Type Registration for MPEG-4".

[23] IETF RFC 2046: "Multipurpose Internet Mail Extensions (MIME) Part Two: Media Types".

[24] IETF RFC 9110: "HTTP Semantics".

[25] IETF RFC 8259: "The JavaScript Object Notation (JSON) Data Interchange Format".

2.2 Informative references

References are either specific (identified by date of publication and/or edition number or version number) or non-specific. For specific references, only the cited version applies. For non-specific references, the latest version of the referenced document (including any amendments) applies.

NOTE: While any hyperlinks included in this clause were valid at the time of publication, ETSI cannot guarantee their long-term validity.

The following referenced documents may be useful in implementing an ETSI deliverable or add to the reader's understanding, but are not required for conformance to the present document.

[i.1] IETF RFC 8446: "The Transport Layer Security (TLS) Protocol Version 1.3".

[i.2] ISO/IEC 23009-1: "Information technology — Dynamic adaptive streaming over HTTP (DASH) -- Part 1: Media presentation description and segment formats".

[i.3] ISO/IEC 23000-19: "Information technology — Multimedia application format (MPEG-A) — Part 19: Common media application format (CMAF) for segmented media".

[i.4] IETF RFC 2616: "Hypertext Transfer Protocol - HTTP/1.1".

[i.5] Void.

[i.6] IETF RFC 9113: "HTTP/2".

[i.7] IETF RFC 9114: "HTTP/3".

[i.8] IANA: "Reliable Multicast Transport (RMT) FEC Encoding IDs and FEC Instance IDs".

3 Definition of terms, symbols and abbreviations

3.1 Terms

For the purposes of the present document, the following terms apply:

bitstream: sequence of bits

block: unit of data on which a block-based code is applied

NOTE: All coding operations (encoding and decoding) on one block are independent of all coding operations on another block.

block coding: coding technique where the input is first be segmented into a sequence of blocks, or chunks; then encoding and decoding are performed independently on a per-block basis

block size: number of bytes that a block of data contains

block symbol count: number of source symbols belonging to a block

byte: 8 bits

channel: generic term for any type of communication technology

EXAMPLE: An Ethernet link, a Wi-Fi® network, or a full path between two nodes within a network.

code rate: ratio between the number of source symbols, and the number of source plus coded or repair symbols

NOTE: The code rate is greater than zero, and less or equal to one, where a code rate close to one indicates that a small number of coded or repair symbols have been produced during the encoding process, while a code rate close to zero indicates a large number of coded or repair symbols.

code type: type of coding (linear, network, or channel coding scheme) used to create coded symbols

coded symbol, encoded symbol, or **repair symbol:** unit of data that is the result of a coding operation

coding or **encoding:** operation that takes source symbols as input and produces coded symbols as output

coding coefficient: coefficient chosen from the same finite field encoding and decoding operations are performed over

NOTE: Methods of choosing this coefficient may include: randomly (e.g. LT codes), in a predefined table (e.g. Reed-Solomon, etc.), or using a predefined algorithm plus a seed (e.g. LDPC, RaptorQ, etc.).

coding matrix, generator matrix, or coefficient matrix: matrix (G) that transforms the set of input symbols (X) into a set of coded or repair symbols (Y): $Y = X \bullet G$

NOTE: Defining a generator matrix is typical with block codes. The set of input symbols X can consist only of source symbols.

coding vector or **coefficient vector:** set of coding coefficients used to generate a certain coded or repair symbol through linear coding

NOTE: The number of nonzero coefficients in the Coding Vector defines its density.

decoding: operation that takes coded symbols as input and produces source symbols as output

encoding: operation that takes source symbols as input and produces coded symbols as output

encoding block: See block.

encoding symbol: See coded symbol.

encoding window or **coding window:** set of source symbols used as input to the coding operations

NOTE: The set of symbols will typically change over time, as the coding window slides over the input flow.

encoding window size or **coding window size:** number of source symbols in the current encoding window

NOTE: This size may change over the time.

erasure: drop or loss of information along a communication path

erasure channel: communication path where information is either dropped or received without any error

finite field, **galois field**, or **coding field:** finite fields, used in linear codes, have the desired property of having all elements (except zero) invertible for the + and × operators, and all operations over any elements do not result in an overflow or underflow

finite field size or **coding field size:** number of elements in a finite field

EXAMPLE: The binary extension field $\{0..2^m-1\}$ has size $q = 2^m$.

flow or stream: stream of information (or packets) that are logically grouped

input or source symbol: unit of data that is an input to an encoding operation or an output of a decoding operation

linear coding: process in which a linear combination of a set of source symbols is generated using a given set of coefficients and resulting in a coded symbol or repair symbol

multipath coding: coding that enables transmission over multiple routes that have multiple (at least partially) disjoint paths from the source to each given destination

multisource coding: coding that enables transmission from multiple sources over (at least partially) disjoint paths to each given destination

network: interconnected set of nodes that communicate over a collection of links or channels

node: point of connection in a communication network

object: ordered sequence of data and associated metadata delivered as part of a flow. an object can be a source object, or a coded/repair object

output symbol: See coded symbol.

packet: unit of data that is sent over a network

rank or encoding rank: number of linearly independent linearly encoded symbols, or equivalently the number of linearly independent equations of the linear system

repair flow: flow containing repair packets after FEC encoding

single-path coding: coding over a route that has a single path from the source to each destination(s). in case of multicast or broadcast traffic, this route is a tree

sliding window coding: coding technique that generates coded or repair symbol(s) on the fly, from the set of source symbols present in the sliding encoding window at that time

NOTE: The sliding window may be either of fixed size (Fixed Sliding Window), or of variable size over time (Elastic Sliding Window).

sliding window size, **encoding window size**, or **coding window size:** number of symbols in the current window

NOTE: This size may change over the time.

source coding: process of removing redundant and/or (perceptually) irrelevant information from an information source, i.e. compression of data or media (audio, video)

source data, source file, or original data: unit of data that may be partitioned into blocks where each block is an input to an encoding operation

source flow: flow of source information to which coding is to be applied, potentially along with other source flows

source node: node that generates one or more source flows

source symbol, **information symbol**, **systematic symbol:** unit of data originating from the source that is used as input to encoding operations

symbol: unit of data that is manipulated during encoding and decoding operations

symbol size: size of each symbol on which encode and decode operations are performed

systematic coding: coding technique where source symbols are part of the output flow generated by an encoder

3.2 Symbols

For the purposes of the present document, the following symbols apply:

^ Exponentiation: a^b is equivalent to a^b

3.3 Abbreviations

For the purposes of the present document, the following abbreviations apply:

Ad-ID	Advertising digital Identifier
AES	Advanced Encryption Standard
ASCII	American Standard Code for Information Interchange
CBC	Cipher Block Chaining
CDN	Content Delivery Network
CDP	Content Delivery Protocol
CFB	Cipher FeedBack
CI	Configuration Information
CMMF	Coded Multisource Media Format
CRC	Cyclic Redundancy Check
CTR	CounTeR
DASH	Dynamic Adaptive Streaming over HTTP
ECB	Electronic Code Book
EFD	Extended FDT Description
EFDT	Extended File Delivery Table
EIDR	Entertainment IDentifier Registry
ESI	Encoding Symbol ID
FDT	File Delivery Table
FEC	Forward Erasure Correction
HAS	HTTP Adaptive Streaming
HDR	High Dynamic Range
HLS	HTTP Live Streaming
HTTP	Hyper-Text Transfer Protocol
IV	Initialization Vector
KMS	Key Management System
LDPC	Low-Density Parity-Check
LT code	Luby Transform code
MIME	Multipurpose Internet Mail Extensions
MT	Mersenne Twister
OFB	Output FeedBack
OTI	Object Transmission Information
PGP	Pretty Good Privacy
PRNG	PseudoRandom Number Generator
SBN	Source Block Number
SHA-1	Secure Hash Algorithm 1
TCP	Transmission Control Protocol
TLS	Transport Layer Security
TOI	Transport Object Identifier
TSI	Transport Session Identifier
UDP	User Datagram Protocol
UTF	Unicode Transformation Format
UUID	Universally Unique IDentifier
VoD	Video-on-Demand
xCD-1	eXperience Coding and Delivery

NOTE: Multisource Media Coding.

4 Overview

4.0 Introduction

Media delivery over the internet today relies on using a single representation for coded media across storage, distribution, and delivery systems. Within a server-client single-path streaming model, traditional source coding techniques are applied to the media and segment-based media formatting is utilized for storage and delivery. This allows clients to download appropriate bit rates and/or resolutions of media during streaming sessions, aiming to provide a high-quality experience across varying network conditions.

Content Delivery Networks (CDNs) are commonly used to copy media across multiple Points of Presence (PoPs) to help improve Quality of Service (QoS) and Quality of Experience (QoE) by distributing and caching media closer to viewers. Client traffic from a CDN is commonly delivered through a single network path and relies on a single representation of the media. The CDN server fulfils client requests during the streaming session until the client (or related steering mechanism) requests switching to a different CDN due to network conditions, performance metrics, or other metrics that impact QoE. Switching among available CDNs is not always seamless and can result in clients experiencing delays and/or periods of degraded QoE.

Content services using multiple CDNs replicate identical media representations across each of them. This redundancy limits the efficiency in settings where, the downloading of media over a multiple network paths to a client device from two or more CDNs, content origins, network storage locations, or in multi-access settings, is necessary to ensure the highest degree of network QoS is continuously available.

The Coded Multisource Media Format (CMMF) provides a framework to enable efficient use of multiple information sources and network pathways to improve network QoS and client QoE in cloud-based or network-powered settings. By redesigning the media format from using a single representation, single encoded version of the source media to using multiple representations of the source media (multisource), CMMF enables seamless load balancing among the most performant network pathways and information sources (e.g. CDN servers, storage servers, etc.) and limits or eliminates the amount of redundant information stored and transmitted since each CMMF source contains a unique/useful coded version of the source media. This method efficiently enhances network performance (e.g. increased throughput/rendered bit rate, lower rebuffering and start times) and resilience without having to rely on centralized orchestration or complex download scheduling.

CMMF is designed to carry multisource-coded representations of media, where multiple CMMF bitstreams can be generated with each containing unique/useful coded versions of the source content. Multisource representations (or CMMF encoded versions) are generated using various linear, network, or channel coding methods. A single CMMF bitstream may contain all of the necessary information needed to reconstruct the original source information; or in some use cases, multiple CMMF bitstreams may be required to fully reconstruct the original source content.

Different coding methods are supported in CMMF. Some coding methods are typically employed in Forward Error Correction (FEC) applications, such as FEC codes/schemes that follow IETF RFC 5052 [15]. The coded data generated by these codes can be mapped to and carried within a CMMF bitstream. As such, similar concepts for partitioning of media data, ancillary data to aid in transmission and delivery, are re-used and expanded upon for the context of creating multisource representations (or simply to leverage a common bitstream format for carrying a single source representation). While the terms "repair" or "FEC" appear in the present document, this is done to provide a foundation for comparison with terminology used for these existing codes/schemes and is not necessarily meant to imply that CMMF is solely used to repair some form of loss or corruption.

CMMF has been designed in accordance with standard networking principles as an additional, independent layer within the media delivery stack. Moreover, CMMF is agnostic to how the underlying source content has been prepared (i.e. encoded and packaged) and is also agnostic to the underlying methods used to store and transport content within a network.




Figure 1: CMMF layer within multimedia transport stack

A system utilizing CMMF is envisaged to:

- Take elementary media streams in an already packaged media format as the source data.
- Encode the source media using an appropriate CMMF coding method.
- Generate multiple CMMF bitstreams according to the syntax and semantics described in clauses 5 and 6.
- Deliver the CMMF bitstreams (either on-the-fly or taken from storage) and possibly ancillary configuration data over networks using an appropriate transport protocol(s) to clients.
- Decode the received CMMF bitstreams.
- Client renders the CMMF-decoded media.

Annex C provides different examples illustrating how CMMF can be used to provide multisource media delivery.

4.1 Source data

Source data is used to create multiple CMMF encoded versions. CMMF can be applied to any media object type, such as a WAV audio clip, an MPEG-4 video clip, an MPEG Dynamic Adaptive Streaming over HTTP (DASH) [i.2] video segment, or an MPEG Common Media Application Format (CMAF) [i.3] addressable resource.

In a common practice, a CMMF encoder will take an existing packaged media format (e.g. ISO BMFF/CMAF). CMMF is not a replacement for these formats. Rather, CMMF supplements these formats by enabling more efficient and flexible strategies to deploy and manage these existing formats within the network. Staying agnostic to the packaging format allows CMMF to operate in a decentralized manner by avoiding the requirement of establishing and maintaining manifests. For any given asset, new CMMF bitstreams can be dynamically generated and/or destroyed without the need to touch existing CMMF bitstreams for that asset or updating manifests in all the places they are located.

The source data encoded within a CMMF bitstream may have additional assigned metadata associated with it that may be used by an application or a network delivery protocol to properly process the data or deliver it across a network. Examples may include manifests, URLs to the source data (as referred to by an application), the content type, timing information, etc. It is not intended for CMMF to replace this metadata. Depending on the application, use case, network architecture, etc., this metadata may or may not be communicated using CMMF.

4.2 CMMF bitstream creation

4.2.1 Encoding CMMF

Generating a CMMF encoded version can be either a real-time process, or a file-based process depending on the application. In this process, the application of linear, network or channel coding to source coded and packaged audio-visual media (i.e. the source data) typically follows these basic steps:

1) Partitioning of the source data into `block_count` number of source blocks. The value of `block_count` may be small (e.g. 1) or large depending on the size of the source data and the code type (the specific linear, network, or channel coding scheme) that is applied.

2) Partition each of the source blocks into `block_num_symbols` worth of source symbols, x_i, where *i* is the index of the original source symbol in the source block. Each symbol is of size `block_symbol_size` (in bytes), padding the final symbol with zero-valued bytes if necessary. The value of `block_symbol_size` is typically chosen by the application, for example taking into account the size of the data to be encoded. In a similar way, the value of `block_num_symbols` is typically chosen based on the specific application and the code type used.

3) Based on the code type used, encode the source symbols to create at least `block_num_symbols` worth of `coded_symbol` instances (depending on code type), y_i. The number of coded symbols generated is typically a function of the code type, use case, and network. Each code type will take in certain coding parameters (e.g. `block_count`, `block_num_symbols`) and generate additional coding parameters (e.g. `block_symbol_size`).

A graphical representation of these steps is illustrated by the example in Figure 2. In this example, the original source (media) data file or stream is partitioned into three source blocks. Each source block is further partitioned into eight source symbols $x_{n,i}$, where n is the block index (generally n=0, 1, …, `block_count` - 1) and $i = 0, 1, \ldots,$ `block_num_symbols` - 1. These source symbols are then encoded by one of the supported CMMF code types to produce the resulting coded symbols $y_{n,j}$, $i \leq j$.




Figure 2: CMMF encode example

The resulting coded symbols and associated coding parameters are formatted per the CMMF syntax as described in clauses 5 and 6, for storage, interchange, or delivery. The coding parameters are necessary to ensure that a compliant CMMF decoder can reconstruct the original (media) source symbols and the source file. Depending on the type of code utilized, the coding parameters can include an Encoding Symbol Index (ESI), a block index or Source Block Number (SBN), coefficient vector, Pseudo-Random Number Generator (PRNG) seed, etc. along with the `block_num_symbols`, `block_symbol_size`, etc. An implementor may choose the code type and how the source data is partitioned into blocks and symbols. In some cases (for example if the code type is an FEC code/scheme based on IETF RFC 5052 [15]) an implementor may follow the block partitioning algorithm specified in section 9 of IETF RFC 5052 [15] or the partitioning defined in a specific FEC scheme.

CMMF supports multiple methods of data partitioning and coding. In addition to block coding, where the source data and source blocks are available in their entirety at the time of CMMF bitstream generation, CMMF also supports sliding-window constructions for use cases that may have rigid latency requirements and the availability of the source data is variable in both time and size.

Depending on the application, encoding of a CMMF bitstream may or may not be an active process (i.e. real-time). A CMMF bitstream may be generated at the time of a request by an application/client, within a CMMF-aware network delivery protocol, or the generation can occur offline and bitstreams stored for future delivery and/or processing.

4.2.2 Symbol groups in CMMF

Coded/repair symbols (including systematic or source symbols) can be grouped and packaged in different ways within the CMMF bitstream. The symbol grouping can be chosen to best fit the needs of a given application. Example symbol groups include:

- Individual symbol group (i.e. not grouped): Each coded/repair symbol is packaged individually within the bitstream. See also clause 6.1.6.

- Single block symbol group: Coded/repair symbols from the same block can be grouped and packaged collectively within the bitstream. See also clause 6.1.18.
- Multiple block symbol group: Coded/repair symbols from multiple blocks can be grouped and packaged collectively within the bitstream. See also clause 6.1.22.

Example symbol groups are shown in Figure 3.




Figure 3: Example symbol groups

In Figure 3, a file is split into two blocks, each partitioned into five symbols, and each encoded to ten coded/repair symbols (including the five source/systematic symbols):

a) Shows each coded/repair symbol as its own individual symbol group.

b) Shows examples of four single block symbol groups.

c) Shows examples of two multiple block symbol groups.

The arrangement of symbols within a symbol group may follow a specific pattern. Symbol groups may be distinct, i.e. each unique coded/repair symbol is added exactly once to exactly one *symbol group*. Symbol groups may also have a property of *completeness*, i.e. the source object can be recovered from all symbols in the symbol group.

4.2.3 Decoding CMMF

The CMMF bitstream specifies and enables carriage and signalling of essential coding parameters required for reconstruction of the original source symbols in a decoder.

The basic steps for decoding include:

1) For each block, decode the received coded symbols $y_{n,j}$ recreating the source symbols $x_{n,i}$.

2) Concatenate each source symbol $x_{n,i}$ and removing any zero-padding from the last symbol if necessary to reform the original source block.

3) Concatenate each of the reassembled source blocks to reform the original source coded media file/data.

These steps are illustrated in Figure 4.




Figure 4: CMMF decode example

4.2.4 Mapping to/from CMMF

The coding CMMF employs is essentially a mapping of information from one form to another to enable additional methods and approaches to communicate or store that information across a network. CMMF supports multiple code types to help ensure applicability in different use cases. A CMMF encoder and decoder may include native support for one or more code types. For some code types, existing and/or standardized encoders, decoders, and bitstream formats may already exist. To improve interoperability and make use of CMMF as an interchange and container format, in some applications a CMMF encoder may contain a bitstream mapper used to translate the coding parameter(s) and coded symbol(s) information produced by existing/standardized linear, network or channel encoders to the equivalent bitfield information and format(s) in the CMMF bitstream as defined in clause 6. Conversely, a receiver, upon parsing a CMMF bitstream, may be required to implement a de-mapping function to translate the relevant CMMF bitfield information back into the original bitfield syntax or format to use with existing/standardized decoder components. High-level representative functional components for generating and parsing a CMMF bitstream are shown in Figure 5 and Figure 6.




Figure 5: CMMF bitstream encoding/packaging




Figure 6: CMMF bitstream decoding

Although shown as a single processing block in the figures above, the mapper and de-mapper functions may be specific for each code type. The code type specific encoders and decoders may be either tightly integrated or only loosely integrated depending on the availability of existing components, it is left for the integrator to determine the level of integration.

As an example of the mapping process when using a Reed-Solomon code type, some of the coding parameters may include:

- Galois Field Size.
- Source Block Number (for each coded symbol).
- Encoding Symbol ID (for each coded symbol).

Table 1 shows a sample mapping to CMMF for these two coding parameters.

Table 1: Example mapping

Original coding parameter	CMMF coding parameter	Mapping function	Relevant clause
Galois Field Size {where size = 2^^m}		`if (m==1) {block_mask = BBBBB0Bb} else {block_field_size_exp = m}`	6.1.5.16, 6.1.5.19
Source Block Number (SBN)	packet_block_index	`packet_block_index = SBN`	6.1.6.1
Encoding Symbol ID (ESI)	packet_symbol_index	`packet_symbol_index = ESI`	6.1.7.4

4.3 Media delivery using CMMF

4.3.1 Overview

CMMF supplements existing methods to stream/deliver media across networks by enabling content to be delivered from multiple sources and/or across multiple network paths. In general, CMMF can be integrated into existing workflows through the addition of a minimal set of new components. All that is required is a CMMF bitstream generator/encoder located at the entry point into or within the network and a CMMF receiver located near or on a media client. CMMF bitstreams created by one or more CMMF bitstream encoders can then be cached and/or delivered from multiple network sources or across multiple network paths using existing network protocols (e.g. HTTP/TCP, webRTC, FLUTE, etc.). Figure 7 shows generic example of some possible delivery/transport scenarios that might occur in a many-to-one multisource application using CMMF. There are six scenarios shown where the creation, storage/caching, and delivery of CMMF bitstreams containing encoded representations of the original source media differ.




Figure 7: Generic Example CMMF delivery/transport sessions

In Figure 7, objects are delivered, or flow, from the original source media to a CMMF receiver. An object can be a source object (which is essentially the source data), or a coded/repair object (i.e. a CMMF bitstream) generated by a CMMF encoder. In the first scenario, the source object is delivered to the CMMF receiver as would occur in an existing "legacy" application. While not shown, this source object may be stored and/or cached within the network prior to delivery to the CMMF receiver. In the second and fifth scenarios, a real-time CMMF encoder creates a coded representation (i.e. a CMMF bitstream) from the source data which is then transmitted immediately to the CMMF receiver. The third, fourth, and sixth scenarios show a CMMF encoder creating another coded representation of the source, but the output of this CMMF encoder is stored and/or cached where it sits until accessed by a CMMF receiver. Other scenarios and integrations are possible that are not depicted within the diagram, including scenarios where the CMMF encoder and an existing network component (e.g. storage, cache, network protocol) are tightly integrated.

Any single scenario, multiple of a single scenario, or combination of scenarios can be used in the delivery of a source object using CMMF. Objects, whether source and/or coded/repair objects, are collected by the CMMF receiver where they are processed and the decoded yielding the original source media. Further details regarding the delivery/transport of CMMF based on existing use cases and network protocols are provided in annex A, annex B, and annex C.

4.3.2 CMMF transport objects and transport sessions

Objects to be delivered using CMMF in the context of the present document may be organized using transport objects where transport objects are organized in a delivery session composed of one or more transport sessions:

- A transport session consists of one or multiple transport objects. Each transport object can be uniquely identified within the session, for example, by a Transport Object Identifier (TOI).
- Each transport object is assigned to exactly one transport session within the delivery session. Transport sessions can be uniquely identified by a Transport Session Identifier (TSI).

- Transport objects within a transport session are uniquely identified by a TOI and may be ordered.
- Transport objects within a transport session may share common metadata and other properties.
- Transport objects within a transport session may have associated timing, for example media time.
- Transport objects in different transport sessions may contain source and/or coded/repair objects generated from the same source data.

An overview of a CMMF session model is provided in Figure 8. A delivery session consists of *S* transport sessions, each identified by a TSI = 0, …, *S*-1, and each transport session consists of *N*[TSI] transport objects, each identified by a TOI = 0, …, *N*[TSI]-1. Note that this model applies if only a single transport session with a single transport object is created.




Figure 8: Delivery session model for CMMF

The method used to form transport objects and map them to TSI/TOI combinations within a delivery session is application and use case dependent. Object formation and mapping may be dependent on numerous factors including the formatting of the underlying source data, application requirements, network protocols, content delivery protocols, etc.

4.3.3 CMMF delivery architecture reference points

CMMF provides a general framework for multisource-coded media that can be utilized across many different media delivery architectures and use cases. While many of these architectures and scenarios differ in one way or another, many common concepts and approaches are often shared. Figure 9 provides a notional reference architecture comprising of common components within media delivery architectures and illustrates how CMMF can be integrated within them.




Figure 9: CMMF delivery architecture reference points

Figure 9 shows four major components:

- Application Provider: The application provider is responsible for producing source media and configuring their service. Sub-components within the Application Provider include:
  - Source Transport Objects: Source Transport Objects consist of original source media intended to be delivered to a Media Application/Client. Examples may include CMAF/MPEG-DASH/HLS video/audio segments, etc.
  - Media Information: Depending on the method used to prepare the source media for delivery or the use case, information may be defined that describes the characteristics of that media. Examples may include MPEG-DASH/HLS manifests, etc. This information may include details on how the source transport objects are structured within a delivery session.
  - CMMF Configuration Information: Depending on the use case and delivery architecture, global configuration information necessary for the delivery of source media using CMMF may be defined. This information may include details about how to configure either the CMMF encoder or decoder, provide information about where a CMMF receiver can access CMMF bitstreams, etc. In some use cases, the CMMF Configuration Information may fully include the Media Information or in other cases the CMMF Configuration Information may be used as a supplement to the Media Information. While the reference architecture shows that the Application Provider is aware of CMMF's use and defines the CMMF Configuration Information, use cases and delivery architectures exists where the Application Provider is agnostic to the CMMF's use. In these use cases and delivery architectures, the CMMF Configuration Information may be defined by a network provider or other entity responsible for delivering the Application Providers' media.
- CMMF Bitstream Generator/Source: CMMF Bitstream Generators/Sources are responsible for generation of CMMF bitstreams containing coded representations of Source Transport Objects. Depending on the use case and/or network architecture, one or more CMMF Bitstream Generators/Sources may be used. Their location(s) may be centralized or distributed across a network. In some deployments, a single CMMF Bitstream Generator/Source may be collocated with the Application Provider and create every CMMF bitstream used in delivery of the required media. In other deployments, CMMF Bitstream Generators/Sources may be located at each PoP within the network where content is cached and only responsible for creating CMMF bitstreams intended to be cached only on that specific PoP. These generators/sources may also create Coded/Repair Objects as part of an active process (i.e. in real-time) or off-line as the use case/delivery architecture dictates.

- CMMF Receiver: CMMF Receivers are responsible for obtaining one or more CMMF bitstreams created by one or more CMMF Bitstream Generators/Sources, decoding those CMMF bitstreams, and recovering the original source media. A CMMF receiver does not necessarily require any one CMMF bitstream in its entirety. Rather, it requires enough information from all received bitstreams to be able to decode, at which point delivery of the remainder of any outstanding CMMF bitstream(s) may be terminated. The CMMF receiver may also use parts of source objects together with CMMF bitstreams to recover the entire source objects. The CMMF Receiver may be collocated with the Media Application/Client or located elsewhere in the network at a point where multisource/multipath delivery is no longer desired. The CMMF Receiver may require Media Information, CMMF Configuration Information, and/or information from the Media Application/Client to obtain the required CMMF bitstreams and recover the associated source media. The CMMF Receiver outputs recovered Source Transport Objects. Depending on the implementation of the interface between the CMMF Receiver and Media Application/Client, these recovered Source Transport Objects may be cached within the CMMF Receiver until the media application requires them or they may be immediately delivered to the media application as they are recovered.

- Media Application/Client: The Media Application/Client is responsible for playback of the recovered source media. In some use cases, the Media Application/Client may control which source media is selected (using the Media Configuration Information) for playback. In these cases, the Media Application/Client may provide input via a Media Control process to the CMMF Receiver.

Figure 9 also shows reference points between the components listed above. Depending on the use case and delivery architecture, these reference points may or may not be utilized:

- C1: This reference point is included as reference only and is not intended to replace or replicate the process other protocols (e.g. MPEG-DASH, HLS, etc.) use to transfer media information between an Application Provider and Media Application/Client. It describes the Media Information that is sent from the Application Provider to the Media Application/Client. This information generally describes the source media; and an example may include a MPEG-DASH or HLS manifest.

- C2: This reference point describes the Media Information used in defining the CMMF Configuration Information. For example, this information may be used to define source blocks within CMMF bitstreams based the structure defined in the Media Information.

- C3: This reference point describes the Media Information that is sent to and used by the CMMF Bitstream Generator/Source to produce coded/repair transport objects.

- C4: This reference point describes the CMMF Configuration Information that is sent to and used by the CMMF Bitstream Generator/Source. This information may be used to configure the CMMF Bitstream Generator/Source and/or used in the production of coded/repair transport objects.

- C5: This reference point describes the CMMF Configuration Information that is sent to and used by the CMMF Receiver. This information may contain details not otherwise specified within clauses 5 and 6. For example, it may contain information that is used by the CMMF Receiver for purposes such as transport object discovery, how Coded/Repair Transport Objects are formed, system operation, etc.

- C6: This reference point describes the Media and/or CMMF Configuration Information that is sent by the CMMF Bitstream Generator/Source to the CMMF receiver. Unlike the other interfaces, this interface may contain configuration information that is specific to a given transport session and/or network protocol. An example may include the delivery of an EFDT.

- S1: This reference point provides Source Transport Objects between the Application Provider and one or more CMMF Bitstream Generators/Sources. These objects are unmodified from the original media/data. These objects may be used in the creation of Coded/Repair Transport Objects encapsulated within one or more CMMF Bitstreams.

- S2: This reference point provides Source Transport Objects between the Application Provider and the CMMF Receiver. These objects are unmodified from the original media/data.

- S3: This reference point provides Source Transport Objects between the CMMF Receiver and the Media Application/Client. These objects may have been obtained by the CMMF Receiver from reference point S2 or recovered from Coded/Repair Transport Objects received over reference point R1.

- R1: This reference point provides Coded/Repair Transport Objects between one or more CMMF Bitstream Generators/Sources and the CMMF Receiver. Details on the formats used to communicate these transport objects are provided in clauses 5 and 6.
- M1: This reference point provides control and/or configuration information from a Media Application/Client to the CMMF Receiver. For example, this control/information may include details regarding which Source and/or Coded/Repair Transport Objects the CMMF Receiver should obtain.

Examples of deployment options along with other details on the CMMF sender and CMMF receiver architectures are provided in annex D.

4.3.4 CMMF delivery procedure

The procedure for delivering source media using CMMF is highly dependent on the use case, delivery architecture, and network protocols utilized. As a result, defining one generic procedure is not possible. However, Figure 10 provides an example delivery procedure for HTTP-based adaptive streaming scenarios.

NOTE: Other delivery procedures are also possible for the same scenario.




Figure 10: HTTP-Based Adaptive Streaming CMMF Delivery Procedure Example

Within this example, an Application Provider encodes, prepares, and packages source media into an MPEG-DASH or HLS stream. This results in multiple segmented representations of the source media at different bit rates and/or resolutions along with a MPEG-DASH or HLS manifest. Each segment is assumed to be a unique source transport object with a unique TOI. This source media is streamed to clients using the following procedure:

Content Provisioning:

- The Application Provider in this example provisions an origin server with the source transport objects thereby making the source media available to Media Applications/Clients.
- The Application Provider publishes the Media Configuration Information (e.g. MPEG-DASH or HLS manifest).
- The Application Provider establishes global settings CMMF (e.g. CMMF code type, coded/repair transport object to source transport object mappings, source locations, etc.) for how to encode and distribute CMMF bitstreams to clients. These settings are stored within the CMMF Configuration Information.

Media Application/Client Initialization:

- During initialization, a Media Application/Client will obtain all or a subset of the CMMF Configuration Information from the Application Provider. This CMMF Configuration Information, at a minimum, provides the Media Application/Client information about where to obtain source and/or coded/repair transport objects once a media selection has been made.

Media Player Initialization:

- Upon selection of the media to be played, the media player is initialized. As part of this process, the media player obtains the Media Configuration Information (e.g. MPEG-DASH or HLS manifest) from the Application Provider.

Source Transport Object Delivery:

- Once the Media Application/Client has obtained the Media Configuration Information, it selects the source transport objects it wants to fetch and play. These source transport objects are requested from the CMMF Receiver. In the case of this example, source transport object TOI = i is requested.
- The CMMF Receiver replicates the request for TOI = i across S transport sessions where each transport session provides a unique source and/or coded/repair transport objects created from source transport object TOI = i. Each transport session is terminated at one of S sources (e.g. cache, CDN PoP, etc.).
- Each source s determines whether the transport object TOI = i for transport session TSI = s is cached locally. If so (i.e. a cache hit), it replies to the CMMF Receiver with the necessary transport object. If not, it obtains the transport object for the transport session from the CMMF Bitstream Generator/Source.
- In this example, the CMMF Bitstream Generator/Source is collocated with an origin server that stores the original source transport object TOI = i. Upon a request from source s (i.e. a cache miss), the CMMF Bitstream Generator/Source obtains the source transport object TOI = i from the origin server, encodes the transport object associated with TSI = s and TOI = i, and responds to the request from source s.
- Once the CMMF receiver obtains enough information from the combination of source and/or coded/repair transport objects from the different transport sessions, it decodes and recovers the original source transport object TOI = i and responds to the Media Application/Client.
- This process repeats for each source transport object requested by the Media Application/Client.

4.3.5 CMMF Configuration Information

Additional information may need to be communicated between components of the reference CMMF delivery architecture shown in clause 4.3.3 to enable multi-source delivery using CMMF. In general, this information is specific to the operation of CMMF and intended to supplement existing information defined for the media delivery protocol (e.g. MPEG-DASH, HLS, etc.) in use. The method used to communicate this information is dependent on the use case and/or scenario. In some implementations, this information can be transmitted via a configuration file or supplied via an API. In other implementations, this information can be provided in the form of an EFDT as described in clause D.2.3 or a CMMF Configuration Information document as specified in clause D.3.3. Examples of the type of information that may be contained with the CMMF Configuration Information include:

- code type the CMMF encoder should use;
- host URLs of the locations for each source where CMMF encoded content is available;
- arrangement of symbols that are included in each of the transport objects;
- etc.

Specific examples of different versions of CMMF Configuration Information are provided in annex B, annex C and annex D.

4.3.6 CMMF as a Content Delivery Protocol

As described in clause 4.3.1, CMMF provides a means to generate coded/repair transport objects for transport/delivery sessions and can be implemented as a Content Delivery Protocol (CDP).

In one instantiation, the CMMF coded/repair framework can be based on the Forward Error Correction (FEC) Building Block as defined in IETF RFC 5052 [15], CMMF can be considered as a CDP specification as defined in clause 8 of IETF RFC 5052 [15]. In such cases, additional requirements on CMMF apply in order to support applications requiring reliable delivery according to IETF RFC 5052 [15].

The CMMF FEC Building Block CDP Framework, example CDP instantiations, and alignment to the Extended FDT [18] are further described in clause D.2.

In another instantiation, the CMMF coded/repair framework can be implemented as a general CDP. In such cases, additional requirements on CMMF apply and a CDP as specified in clause D.3 can be used.

4.4 Overview of the specification

The remainder of the present document defines a bitstream syntax for communicating multi-source encoded media and provides examples of delivery architectures that utilize CMMF for multi-source delivery:

- Clauses 5 and 6 provide the bitstream's syntax and semantics respectively. These clauses define the syntax used on interface R1 of Figure 9.
- Clause 7 provides additional information that should be considered in the design of CMMF encoders, parsers, and decoders.
- Annex A provides the normative definition of the xCD-1 code type that can be used within CMMF to encode media for multi-source delivery.
- Annex D provides normative CMMF Content Delivery Protocol (CDP) instantiations for use in delivering content. It provides a normative mapping between CMMF and the principles defined in IETF RFC 5052 [15] and an instantiation for a Configuration Information, namely an Extended file delivery table, aligned with IETF RFC 6726 [18]. It also provides a normative CMMF CDP instantiation and Configuration Information that uses URL translation to map between source objects and CMMF Transport Objects.
- Annex E defines normative configurations for use by a CMMF Encoder to create CMMF bitstreams/Transport Objects.

- Annex F provides normative definitions of CMMF bitstream profiles that can be used to create compliant CMMF bitstreams.
- Finally, annex B, annex C and clauses D.2.5, D.3.4 and E.1.5 provide examples of possible implementations of CMMF within existing content delivery systems.

5 Bitstream syntax

5.0 Bitstream organization

The syntax specification presented in clause 5.2 shows how the CMMF bitstream (`cmmf_bitstream()`) is the top-level structure of a bitstream. Every bitstream begins with a `sync()` structure, and contains one or more subatom (`subatom()`) structures.

A subatom is a generic container that can be populated with different types of data. Because a subatom can carry only one type of data, the type of data carried within defines a subatom type, and the associated data structure. For example, a bitstream header subatom is an instance of the `subatom()` syntactical structure carrying a `bitstream_header()` syntactical structure. In the present document the subatom type may be referred to by a name (e.g. bitstream header subatom) or its associated syntactical structure (`bitstream_header()`).

Figure 11 shows the high-level hierarchical organization for a CMMF bitstream with N subatoms.




Figure 11: High-level CMMF bitstream organization

There are several types of subatom data types defined for the CMMF bitstream, including:

- Sync (`sync()`)
- Bitstream header (`bitstream_header()`)
- Encoder and content information (`encoder_content_info()`)
- Media segment information (`media_segment_info()`)
- Block header (`block_header()`)
- Packet (`packet()`)
- Chunked subatom (`chunked_subatom()`)
- Block group directory (`block_group_directory()`)

- Packet header only (`packet_header_only()`)
- Packet group (`packet_group()`)
- Multiple block packet group (`multi_block_packet_group()`)

While a bitstream containing a single subatom would be technically valid, a decoder typically needs to receive multiple subatoms, for example receipt of a bitstream header, block header(s), and packet(s) subatoms would allow for successful decode a CMMF bitstream and reconstruction the original source data.

The syntax permits additional subatom data types to be defined for future applications.

5.1 Semantics of syntax specification

5.1.1 Pseudocode syntax

The following pseudocode within syntax boxes describes the order of arrival of information within the CMMF bitstream. This pseudocode is roughly based on C language syntax, but simplified for ease of reading. For bitstream elements that are larger than one bit, the order of the bits in the serial bitstream is either most-significant-bit-first (for numerical values), or left-bit-first (for bit-field values). Fields or elements contained in the bitstream are indicated with **bold** type. Syntactic elements are typographically distinguished by the use of a different font (e.g. `block_count_minus1`).

5.1.2 Bitstream variable syntax

The variable syntax is described in the format of a three-column table in the present document.

In these tables, first column entries in **bold** signify the occurrence of the corresponding variable in the bitstream; the second column specifies the bit-field length and way of encoding (according to the notation in clause 5.1.9); the third column provides (where applicable) a reference to a clause containing more information about the variable.

Table 2 provides an example of the bitstream variable syntax format for the **block_count_minus1** metadata field.

Table 2: Example of bitstream variable

Syntax	Encoding	Clause
code_type	u(4)	6.1.4.5

5.1.3 Bitstream structure syntax

Bitstream structures (also referred to as elements) are defined using the C procedure syntax.

The substructure is expanded by the C call syntax name (`<arguments>`).

Table 3 shows an example of the bitstream structure syntax format.

Table 3: Example of bitstream structure

Syntax	Encoding	Clause

`name(<optional arguments>)`
`{`
`  .`
`  .`
`}`		

5.1.4 Iteration and conditional operators

Iteration is expressed using the usual C statements `for`, `while`, and `do...while`. Conditional expansion uses these constructs:

- if (…) ...
- if (…) ... else ...
- if (…) ... else if () ...

These examples demonstrate the procedure of reading a flag from the stream and performing an `<action>` if the flag is `set` (binary 1).

Table 4 provides an example of a shorthand `if` syntax format.

Table 4: Example of shorthand If syntax format

Syntax	Encoding	Clause
`if (`**`flag`**`) <action>`	b(1)	

Table 5 provides an example of an expanded if syntax format, which is the expansion of the preceding shorthand `if` syntax format.

Table 5: Example of expanded If syntax format

Syntax	Encoding	Clause

`flag`
`if (flag) {`
`  <action>`
`}`
	b(1)	

5.1.5 Boolean operations

The Boolean operators `&&` and `||` follow normal C conventions.

For example, for an `&&` operation, the right-hand side is not evaluated if the left-hand side is FALSE, as listed in Table 6.

Table 6: Example of Boolean operation syntax format

Syntax	Encoding	Clause

`if (paramA &&` **`paramB`**`) {`
`  <action>`
`}`
	b(1)	

5.1.6 Labels and comments

Labels are flush against the left margin and are indicated as comments in the code.

Table 7 shows an example label:

Table 7: Example of bitstream label

Syntax	Encoding	Clause
`/* Label */`		

Labels are regarded as markers within the expanded bitstream, not as textual markers within the syntax description.

Comments are indented and aligned with associated syntax.

Table 8 shows an example comment:

Table 8: Example of bitstream comment

Syntax	Encoding	Clause

`if (flag)`
`{`
`  /* Comment */`
`  field`
`}`		

5.1.7 Operational variables not in the bitstream

Some operational variables that are not present in the bitstream but are useful for performing certain operations (such as parsing the bitstream) are presented in not bold, as shown in the example in Table 9.

Table 9: Example of operational variable format

Syntax	Encoding	Clause
`block_count = block_count_minus1 + 1`		

5.1.8 Arrays

Some bitstream elements naturally form arrays. Even if bitstreams are naturally included in arrays, this syntax specification treats all bitstream elements individually. Where appropriate, arrays are described as multiple elements (for example, `block_header_subatom_offset[blk]`) within control structures, such as for loops, that are employed to increment the index (`blk` for block in this example).

5.1.9 Bit field encoding

The encoded data can be thought of as a serial bitstream containing items of data that occupy fields of varying length (for example, three bits to specify a number in the range [0…7]). The bits occupying each field are presented with the most-significant bit first.

Because fields can be of variable length, they can generally straddle word boundaries. However, the complete CMMF bitstream and some of its substructures are aligned with 8-bit word (or byte) boundaries.

Values are encoded in signed or unsigned bit fields and are referred to in the syntax description using the notation listed in Table 10.

Table 10: Bit field descriptors

Bit field encoding	Description
b(n)	Boolean, n bit field: `1` is `TRUE`, `0` is `FALSE`.
v(n)	Bit field taking n bits, with arbitrary representation.
s(n)	Signed integer taking n bits (n ≥ 1), represented in two's complement.
u(n)	Unsigned integer taking n bits (n ≥ 0, u(0) = 0).
pad(n)	Pad with n zero bits.
pad	Pad with an arbitrary number of zero bits. The number is determined by a specified variable.

If a Boolean bitstream element is defined to signal a *whether statement* then the *statement* is true if the Boolean is set (TRUE), i.e. the corresponding bit is set to `1`. A subsequent *otherwise statement* is true if the Boolean is cleared (FALSE), i.e. the corresponding bit is set to `0`.

Bit fields indicated as `reserved` are encoded as v(n) with all bits set to `0` and shall be ignored by bitstream parsers that conform to this version of CMMF.

When present in the syntax, the `byte_align` field uses the `pad` bitfield encoding with 0 to 7 zero bits. The field ensures that there exists a whole number of bytes relative to a reference starting point.

5.2 Syntax specification

5.2.1 cmmf_bitstream()

Table 11: Syntax of cmmf_bitstream()

Syntax	Encoding	Clause

cmmf_bitstream()
{
  sync()
  while (*true*)
  {
  subatom()
  }
}
		6.1.1
		
		5.2.3
		
		5.2.2

5.2.2 subatom()

Table 12: Syntax of subatom()

Syntax	Encoding	Clause

subatom()
{
/* subatom header start */
  subatom_id
  if (subatom_id == 0xF) {
  subatom_id_ext
  subatom_id = subatom_id + subatom_id_ext
  }
 	
  b_bitstream_id_present
  reserved
 	
  sas_bits = num_bits_code()
 	
  if (b_bitstream_id_present) {
  bitstream_id
  }
 	
  subatom_size
/* subatom header end */
/* subatom data start */
  switch(subatom_id)
  {
  case SUBATOM_ID_SYNC:
  sync()
  break
  case SUBATOM_ID_BITSTREAM_HEADER:
  bitstream_header()
  break
  case SUBATOM_ID_ENCODER_CONTENT_INFO:
  encoder_content_info()
  break
  case SUBATOM_ID_MEDIA_SEGMENT_INFO:
  media_segment_info()
  break
  case SUBATOM_ID_BLOCK_HEADER:
  block_header()
  break
  case SUBATOM_ID_PACKET:
  packet()
  break
  case SUBATOM_ID_CHUNKED_SUBATOM:
	
	u(4)
	
	u(8)
	
	b(1)
	v(1)
	
	v(16)
	
	u(sas_bits)

Syntax	Encoding	Clause
chunked_subatom() break case SUBATOM_ID_BLOCK_GROUP_DIRECTORY: block_group_directory() break case SUBATOM_ID_PACKET_HEADER_ONLY: packet_header_only() break case SUBATOM_ID_PACKET_GROUP: packet_group() break case SUBATOM_ID_MULTI_BLOCK_PACKET_GROUP: multi_block_packet_group() break default: **UNKNOWN** }	 v(subatom_size × 8)	5.2.13 5.2.14 5.2.19 5.2.21 5.2.25
padding /* subatom data end */ }	pad	

5.2.3 sync()

Table 13: Syntax of sync()

Syntax	Encoding	Clause

sync()
{
syncword
version
b_content_encode_uuid
reserved
if (b_content_encode_uuid){
content_encode_uuid
}
}
	
	v(64)
	v(4)
	b(1)
	v(3)
	
	v(128)
		6.1.3
		
		6.1.3.1
		6.1.3.2
		6.1.3.3
		
		6.1.3.4

5.2.4 bitstream_header()

Table 14: Syntax of bitstream_header()

Syntax	Encoding	Clause

bitstream_header() {
content_source_size
content_source_type
reserved
b_content_source_split
if (b_content_source_split){
content_source_split_start
content_source_split_end
}
code_type
if (code_type == 0xF){
code_type_ext
code_type = code_type + code_type_ext
}
b_rfc5052
if (b_rfc5052){
rfc5052_information()
}
block_count_minus1 = block_index_or_count_value()
	
	u(64)
	v(3)
	v(1)
	b(1)
	
	u(64)
	u(64)
	
	u(4)
	
	u(8)
	
	b(1)
	
		6.1.4
		6.1.4.1
		6.1.4.2
		
		6.1.4.3
		
		6.1.4.4
		6.1.4.4
		
		6.1.4.5
		
		6.1.4.5
		
		6.1.4.6
		
		5.2.20
		
		6.1.4.7,
		5.2.24

Syntax	Encoding	Clause
block_count = block_count_minus1 + 1		6.1.4.7
b_content_block_separate_sources	b(1)	6.1.4.8
if (b_content_block_separate_sources){		
num_content_block_sources_minus1	u(8)	6.1.4.9
}		
b_profile_information_present	b(1)	6.1.4.10
if (b_profile_information_present){		
profile_type_size	u(4)	6.1.4.11
profile_type	v(profile_type_size × 8)	6.1.4.11
profile_description	v(32)	6.1.4.12
}		
b_block_cc_encrypted	b(1)	6.1.4.13
if (b_block_cc_encrypted){		
bitstream_encryption_key_id_size_exp	u(4)	6.1.4.14
bseki_bits = 2^ bitstream_encryption_key_id_size_exp		
bitstream_encryption_key_id	v(bseki_bits)	6.1.4.15
}		
}		

5.2.5 block_header()

Table 15: Syntax of block_header()

Syntax	Encoding	Clause
block_header()		6.1.5
{		
block_index = block_index_or_count_value()		6.1.5.1, 5.2.24
block_size	u(32)	6.1.5.2
block_symbol_size	u(32)	6.1.5.3
bns_bits = num_bits_code()		6.1.5.4, 5.2.23
block_num_symbols	u(bns_bits)	6.1.5.5
b_block_max_symbol_index_present	b(1)	6.1.5.6
if (b_block_max_symbol_index_present)		
{		
bmsi_bits = num_bits_code()		6.1.5.7, 5.2.23
block_max_symbol_index	u(bmsi_bits)	6.1.5.8
}		
b_block_content_source_index_present	b(1)	6.1.5.9
if (b_block_content_source_index_present)		
{		
block_content_source_index	u(8)	6.1.5.10
}		
b_block_composite_sources	b(1)	6.1.5.11
if (b_block_composite_sources)		
{		
block_num_composite_sources_minus1	u(8)	6.1.5.12
blk_num_cmp_sources = block_num_composite_sources_minus1 + 1		
for (cmpsrc=0; cmpsrc < blk_num_cmp_sources; cmpsrc++) {		
bcss_bits = num_bits_code()		6.1.5.13, 5.2.23
block_composite_source_size	u(bcss_bits)	6.1.5.14
}		
}		
b_addl_block_coding_info_present	b(1)	6.1.5.15
if (b_addl_block_coding_info_present)		
{		

Syntax	Encoding	Clause
addl_block_coding_mask	v(3)	6.1.5.16
if (addl_block_coding_mask & 0x1) {		
b_addl_window_info_present	b(1)	6.1.5.17
if (b_addl_window_info_present) {		
addl_window_info() = extension(4)		
}		
}		
if (addl_block_coding_mask & 0x2) {		
b_reserved_block_coding_params_present	b(1)	6.1.5.18
if (b_reserved_block_coding_params_present) {		
reserved_block_coding_params() = extension(4)		
}		
}		
if (addl_block_coding_mask & 0x4) {		
reserved_block_coding_info() = extension(4)		
}		
}		
block_mask	v(6)	6.1.5.19
if (block_mask & 0x1)		
{		
b_sufficient_symbols_present	b(1)	6.1.5.20
if (!b_sufficient_symbols_present)		
{		
bsp_bits = num_bits_code()		6.1.5.21, 5.2.23
block_symbols_present	u(bsp_bits)	6.1.5.22
}		
}		
else		
{		
/* Symbols present count not available */		
}		
if (block_mask & 0x2)		
{		
block_field_size_exp	v(3)	6.1.5.23
}		
else		
{		
/* GF{2^1}, block_field_size_exp_val=1 */		
}		
if (block_mask & 0x4)		
{		
/* Coding coeff info in packet header subatoms */		
}		
if (block_mask & 0x8)		
{		
block_cc_encryption_info_size_bits_code	v(1)	6.1.5.24.1
byte_align	pad	6.1.5.24.2
bcceis_bits = (block_cc_encryption_info_size_bits_code + 1) × 8		
block_cc_encryption_info_size	u(bcceis_bits)	6.1.5.24.3
/* block encryption info start */		
reserved	v(1)	
block_cc_encryption_algorithm	v(3)	6.1.5.24.4
block_cc_encryption_mode	v(4)	6.1.5.24.5
block_cce_key_size_exp	u(4)	6.1.5.24.6
bck_bits = 2^block_cce_key_size_exp		
block_cce_key	v(bck_bits)	6.1.5.24.6
b_addl_block_cce_params_present	b(1)	6.1.5.24.7
if (b_addl_block_cce_params_present)		
{		
addl_cce_parameters()		5.2.6
}		
padding	pad	
/* block encryption info end */		
}		
if (block_mask & 0x10)		

Syntax	Encoding	Clause

{
  prng_parameters()
}
if (block_mask & 0x20)
{
  block_integrity() = fb_integrity()
}
}
		5.2.7
		
		5.2.15

5.2.6 addl_cce_parameters()

Table 16: Syntax of addl_cce_parameters()

Syntax	Encoding	Clause

addl_cce_parameters()
{
num_addl_cce_params_minus1
for (eprm = 0; eprm < (num_addl_cce_params_minus1 + 1); eprm++)
{
cce_parameter_type
cce_parameter_size_exp
ccep_bits = 2 ^ cce_parameter_size_exp
cce_parameter
}
}
	
	u(2)
	
	v(3)
	u(4)
	
	v(ccep_bits)
		6.1.5.24.8
		
		6.1.5.24.8.1
		
		6.1.5.24.8.2
		6.1.5.24.8.3
		
		6.1.5.24.8.3

5.2.7 prng_parameters()

Table 17: Syntax of prng_parameters()

Syntax	Encoding	Clause

prng_parameters()
{
prng_type
prng_seed_bits_code
ps_bits = 2 ^ (prng_seed_bits_code + 4)
/* prng_parameters() encryption info start */
prng_seed
prng_density_percentage
reserved
/* prng_parameters() encryption info end */
}
	
	v(3)
	v(2)
	
	u(ps_bits)
	u(7)
	v(1)
		6.1.5.25
		
		6.1.5.25.1
		6.1.5.25.2
		
		6.1.5.25.3
		6.1.5.25.4

5.2.8 packet()

Table 18: Syntax of packet()

Syntax	Encoding	Clause

packet()
{
if (block_count > 1)
{
packet_block_index = block_index_or_count_value()
}
else
{
packet_block_index = 0
}
packet_header()
		6.1.6
		
		6.1.6.1,
		5.2.24
		
		6.1.6.1
		
		5.2.9

Syntax	Encoding	Clause
coded_symbol	v(css_bits)	6.1.6.2
}		

5.2.9 packet_header()

Table 19: Syntax of packet_header()

Syntax	Encoding	Clause
packet_header()		6.1.7
{		
b_systematic_symbol	b(1)	6.1.7.1
packet_mask	v(7)	6.1.7.2
if (packet_mask & 0x1)		
{		
psi_bits = num_bits_code()		6.1.7.3, 5.2.23
packet_symbol_index	u(psi_bits)	6.1.7.4
}		
if (packet_mask & 0x2)		
{		
if (b_systematic_symbol) {		
b_systematic_symbol_encrypted	b(1)	6.1.7.5.1
} else {		
reserved	v(1)	
}		
b_addl_packet_cce_params_present	b(1)	6.1.7.5.2
if (b_addl_packet_cce_params_present) {		
addl_cce_parameters()		5.2.6
}		
}		
if (packet_mask & 0x4) {		
window_start_index	u(16)	6.1.7.6
window_stop_index	u(16)	6.1.7.6
window_size = (window_stop_index - window_start_index + 1) % 65536		
} else {		
window_size = block_num_symbols		
}		
if (packet_mask & 0x8) {		
prng_parameters()		5.2.7
}		
if (packet_mask & 0x10) {		
coefficient_vector(window_size, block_field_size_exp_val)		5.2.17
}		
if (packet_mask & 0x20) {		
packet_integrity()		5.2.16
}		
if (packet_mask & 0x40){		
packet_header_extension() = extension(5)		5.2.18
}		
byte_align	pad	6.1.7.7
}		

5.2.10 encoder_content_info()

Table 20: Syntax of encoder_content_info()

Syntax	Encoding	Clause
encoder_content_info()		6.1.8
{		
b_encoder_id_present	b(1)	6.1.8.1
if (b_encoder_id_present)		

Syntax	Encoding	Clause
{		
encoder_uuid	v(128)	6.1.8.2
}		
b_content_id_present	b(1)	6.1.8.4
if (b_content_id_present)		
{		
content_id_type	v(4)	6.1.8.4.1
content_id_size_minus1	u(8)	6.1.8.4.2
content_id	v((content_id_size_minus1+1) × 8)	6.1.8.4.3
}		
b_content_location_present	b(1)	6.1.8.5
if (b_content_location_present)		
{		
content_location_size_minus1	u(11)	6.1.8.6
content_location	v((content_location_size_minus1+1) ×8)	6.1.8.6
}		
b_content_type_present	b(1)	6.1.8.7
if (b_content_type_present)		
{		
content_type_size	u(8)	6.1.8.8
content_type	v(content_type_size×8)	6.1.8.8
}		
b_content_header_present	b(1)	6.1.8.9
if (b_content_header_present)		
{		
content_header_size	u(7)	6.1.8.10
content_header	v(content_header_size×8)	6.1.8.10
}		
b_file_integrity_present	b(1)	6.1.8.11
if (b_file_integrity_present)		
{		
file_integrity() = fb_integrity()		5.2.15
}		
b_media_preso_dur_present	b(1)	6.1.8.12
if (b_media_preso_dur_present)		
{		
media_presentation_duration() = cmmf_time()		5.2.12
}		
reserved	v(4)	
}		

5.2.11 media_segment_info()

Table 21: Syntax of media_segment_info()

Syntax	Encoding	Clause
media_segment_info()		6.1.9
{		
media_segment_block_index = block_index_or_count_value()		6.1.9.1, 5.2.24
reserved	v(4)	
b_composite_source_index_present	b(1)	6.1.9.3
if (b_composite_source_index_present)		
{		
media_segment_composite_source_index	u(8)	6.1.9.4
}		
media_segment_index	u(2)	6.1.9.2
if (media_segment_index == 0x3)		
{		
media_segment_index_ext	u(6)	6.1.9.2
media_segment_index = media_segment_index + media_segment_index_ext		
}		
if (**b_asset_name_present**)	b(1)	6.1.9.5

Syntax	Encoding	Clause
{		
asset_name_size	u(8)	6.1.9.6
for (i = 0; i < asset_name_size; i++)		
{		
asset_name[i]	v(8)	6.1.9.6
}		
}		
segment_tag_mask	v(4)	6.1.9.7
if (segment_tag_mask & 0x1) {		
segment_duration() = cmmf_time()		5.2.12
}		
if (segment_tag_mask & 0x2) {		
segment_start_time() = cmmf_time()		5.2.12
}		
if (segment_tag_mask & 0x4) {		
segidx_bits = num_bits_code()		6.1.9.8, 5.2.23
segment_index	u(segidx_bits)	6.1.9.9
}		
if (segment_tag_mask & 0x8) {		
segcnt_bits = num_bits_code()		6.1.9.8, 5.2.23
segment_count	u(segcnt_bits)	6.1.9.10
}		
if (**b_media_mime_type_present**) {	b(1)	6.1.9.11
media_mime_type_size	u(6)	6.1.9.12
for (i = 0; i < media_mime_type_size; i++) {		
media_mime_type[i]	v(8)	6.1.9.12
}		
}		
if (**b_media_codec_present**) {	b(1)	6.1.9.13
media_codec_size	u(6)	6.1.9.14
for (i = 0; i < media_codec_size; i++) {		
media_codec[i]	v(8)	6.1.9.14
}		
}		
if (**b_bit_rate_present**) {	b(1)	6.1.9.15
bit_rate_bits_code	v(1)	6.1.9.16
bps_bits = (bit_rate_bits_code + 3) × 8		
bit_rate	u(bps_bits)	6.1.9.17
}		
if (**b_ms_content_type_present**) {	b(1)	6.1.9.18
ms_content_type	v(3)	6.1.9.19
b_ms_content_type_info_present	b(1)	6.1.9.20
}		
else		
{		
/* b_ms_content_type_info_present = 0b */		
}		
if (b_ms_content_type_info_present) {		
switch (ms_content_type) {		
case 0x0:		
if (**b_aspect_ratio_present**) {	b(1)	6.1.9.21
sample_aspect_ratio	u(8)	6.1.9.22
if (sample_aspect_ratio == 255) {		
sar_width	u(8)	6.1.9.23
sar_height	u(8)	6.1.9.23
}		
}		
b_dynamic_resolution_video	b(1)	6.1.9.24
if (**b_resolution_present**) {	b(1)	6.1.9.25
resolution_width	u(16)	6.1.9.26
resolution_height	u(16)	6.1.9.26
}		
if (**b_frame_rate_present**) {	b(1)	6.1.9.27
frame_rate	v(5)	6.1.9.28
}		

Syntax	Encoding	Clause
reserved	v(4)	
if (**b_hdr_info_present**) {	b(1)	6.1.9.29
hdr_compatibility_mask	v(16)	6.1.9.30
if (**b_addl_hdr_info_present**) {	b(1)	6.1.9.31
hdr_compat_mask_index	u(4)	6.1.9.32
hdr_profile	u(8)	6.1.9.33
hdr_level	u(8)	6.1.9.34
hdr_compatibility_id	u(8)	6.1.9.35
}		
}		
if (**b_addl_video_info_present**) {	b(1)	6.1.9.36
addl_video_info = extension(6)		5.2.18
}		
break		
case 0x1:		
if (**b_sampling_freq_present**) {	b(1)	6.1.9.37
b_sampling_freq_is_48k	b(1)	6.1.9.38
if (!b_audio_fs_is_48k) {		
sampling_frequency	v(4)	6.1.9.39
}		
}		
if (**b_audio_config_present**) {	b(1)	6.1.9.40
audio_channel_config	v(24)	6.1.9.41
}		
if (**b_audio_props_present**) {	b(1)	6.1.9.42
reserved	v(1)	
b_virtualized_bin	b(1)	6.1.9.43
reserved	v(2)	
b_object_audio	b(1)	6.1.9.44
if (**b_complexity_index_present**) {	b(1)	6.1.9.45
complexity_index	u(8)	6.1.9.46
}		
}		
if (**b_addl_audio_info_present**) {	b(1)	6.1.9.47
addl_audio_info = extension(6)		5.2.18
}		
break		
default:		
if (**b_addl_ms_content_type_info_present**) {	b(1)	6.1.9.48
addl_ms_content_type_info() = extension(6)		5.2.18
}		
}		
}		
accessibility_mask	v(4)	6.1.9.49
if (accessibility_mask & 0x1) {		
language_size	u(6)	6.1.9.50
for (i = 0; i < language_size; i++) {		
language[i]	v(8)	6.1.9.48
}		
}		
if (accessibility_mask & 0x2) {		
reserved	v(3)	
}		
if (accessibility_mask & 0x4) {		
reserved	v(4)	
}		
if (accessibility_mask & 0x8) {		
addl_accessibility_info() = extension(4)		5.2.18
}		
}		

5.2.12 cmmf_time()

Table 22: Syntax of cmmf_time()

Syntax	Encoding	Clause
cmmf_time()		6.1.10
{		
b_ddhhmmss_format	b(1)	6.1.10.1
if (b_ddhhmmss_format) {		
if (**b_dd_present) (**	b(1)	6.1.10.2
days	u(5)	6.1.10.2
}		
if (**b_hh_present) (**	b(1)	6.1.10.2
hours	u(5)	6.1.10.2
}		
if (**b_mm_present) (**	b(1)	6.1.10.2
minutes	u(6)	6.1.10.2
}		
if (**b_ss_present) (**	b(1)	6.1.10.2
seconds	u(6)	6.1.10.2
}		
} else {		
int_seconds_bits_code	v(2)	
is_bits = (int_seconds_bits_code) × 8		
int_seconds	u(is_bits)	6.1.10.4
}		
b_fract_seconds_present	b(1)	6.1.10.5
if (b_fract_seconds_present) {		
fract_seconds_bits_code	v(2)	
fs_bits = 10 × 2^ fract_seconds_bits_code		
fract_seconds	u(fs_bits)	6.1.10.7
}		
}		

5.2.13 chunked_subatom()

Table 23: Syntax of chunked_subatom()

Syntax	Encoding	Clause
chunked_subatom()		6.1.11
{		
/* chunk subatom info start */		
chunk_segment_id	u(16)	6.1.11.1
chunk_segment_index	u(24)	6.1.11.2
if (chunk_segment_index == 0)		
{		
num_chunk_segments	u(24)	6.1.11.3
original_subatom_id	u(4)	6.1.11.4
if (original_subatom_id == 0xF)		
{		
original_subatom_id_ext	u(8)	6.1.11.4
original_subatom_id = original_subatom_id + original_subatom_id_ext		
}		
oss_bits = num_bits_code()		6.1.11.5, 5.2.23
original_subatom_size	u(oss_bits)	6.1.11.6
}		
byte_align	pad	6.1.11.7
/* chunk subatom info stop */		
chunk_subatom_segment_data	u(cssd_bits)	6.1.11.8
}		

5.2.14 block_group_directory()

Table 24: Syntax of block_group_directory()

Syntax	Encoding	Clause
block_group_directory()		6.1.12
{		
block_group_dir_mask	v(8)	6.1.12.1
block_count_minus1 = block_index_or_count_value()		6.1.4.7, 5.2.24
if (block_group_dir_mask & 0x1)		
{		
for (block = 0; block < (block_count_minus1 + 1); block++) {		
block_header_subatom_offset[block]	u(64)	6.1.12.2
}		
}		
if (block_group_dir_mask & 0x2)		
{		
for (block = 0; block < (block_count_minus1 + 1); block++) {		
num_packet_groups[block]	u(8)	6.1.12.3
for (pg = 0; pg < num_packet_groups[block]; pg++) {		
if (block_group_dir_mask & 0x4)		
{		
packet_group()		5.2.21
}		
else		
{		
packet_group_index[block][pg]	u(8)	6.1.12.4
}		
}		
}		
for (block = 0; block < (block_count_minus1 + 1); block++) {		
for (pg = 0; pg < num_packet_groups[block]; pg++) {		
packet_group_subatom_offset[block][pg]	u(64)	6.1.12.5
}		
}		
}		
if (block_group_dir_mask & 0x8)		
{		
num_multi_block_packet_groups	u(16)	6.1.12.6
for (mbpg = 0; mbpg <; mbpg++) {		
multi_block_packet_group_subatom_offset[mbpg]	u(64)	6.1.12.7
}		
}		
/* directory end */		
}		

5.2.15 fb_integrity()

Table 25: Syntax of fb_integrity()

Syntax	Encoding	Clause
fb_integrity()		6.1.13
{		
fb_hash_type	v(2)	6.1.13.1
fb_hash_algorithm	v(3)	6.1.13.2
fb_hash_size	v(4)	6.1.13.3
reserved	v(6)	
b_fb_integrity_ext	b(1)	6.1.13.4
if (b_fb_integrity_ext)		
{		
fb_integrity_extension() = extension(3)		5.2.18
}		
fb_hash	v(fb_hash_bits)	6.1.13.5
}		

5.2.16 packet_integrity()

Table 26: Syntax of packet_integrity()

Syntax	Encoding	Clause
packet_integrity()		6.1.14
{		
packet_hash_algorithm	v(3)	6.1.14.1
packet_hash_size	v(3)	6.1.14.2
reserved	v(1)	
b_packet_integrity_ext	b(1)	6.1.14.3
if (b_packet_integrity_ext)		
{		
packet_integrity_extension() = extension(3)		5.2.18
}		
packet_hash	v(pkt_hash_bits)	6.1.14.4
}		

5.2.17 coefficient_vector()

Table 27: Syntax of coefficient_vector()

Syntax	Encoding	Clause
coefficient_vector(window_size, block_field_size_exp_val)		6.1.15
{		
for (index = 0; index < window_size; index++)		
{		
coded_symbol_coeff[index]	u(block_field_size_exp_val)	6.1.15.1
}		
}		

5.2.18 extension()

Table 28: Syntax of extension()

Syntax	Encoding	Clause
extension(num_bits)		6.1.16
{		
extension_byte_size	u(num_bits)	6.1.16.1
for (i = 0; i < extension_byte_size; i++)		
{		
reserved	v(8)	
}		
}		

5.2.19 packet_header_only()

Table 29: Syntax of packet_header_only()

Syntax	Encoding	Clause
packet_header_only()		6.1.17
{		
if (block_count > 1)		
{		
packet_block_index = block_index_or_count_value()		6.1.6.1, 5.2.24
}		
else		
{		
packet_block_index = 0		
}		
packet_header()		5.2.9

Syntax	Encoding	Clause
}		

5.2.20 rfc5052_information()

Table 30: Syntax of rfc5052_information()

Syntax	Encoding	Clause
rfc5052_information() {		6.1.4.6
encoding_symbol_length	u(32)	6.1.4.6
if (code_type == 5)		
{		
maximum_source_block_length	u(32)	6.1.4.6
max_number_of_encoding_symbols	u(32)	6.1.4.6
}		
b_addl_rfc5052_information_present	b(1)	
if (b_rfc5052_information_present)		
{		
addl_rfc5052_information() = extension(7)		
}		
}		

5.2.21 packet_group()

Table 31: Syntax of packet_group()

Syntax	Encoding	Clause
packet_group()		6.1.18
{		
if (block_count > 1)		
{		
packet_group_block_index = block_index_or_count_value()		6.1.18.1, 5.2.24
}		
else		
{		
packet_group_block_index = 0		6.1.18.1
}		
packet_group_index	u(8)	6.1.18.2
reserved	v(4)	
pgns_bits = num_bits_code()		6.1.18.3, 5.2.23
packet_group_num_symbols	u(pgns_bits)	6.1.18.4
packet_group_type	v(2)	6.1.18.5
if ((packet_group_type == 0x0) || (packet_group_type == 0x1))		
(		
packet_group_header()		5.2.22
}		
if ((packet_group_type == 0x0) || (packet_group_type == 0x2))		
(		
/* start hash */		
for (index=0; index < packet_group_num_symbols; index++)		
{		
coded_symbol	u(block_symbol_size * 8)	6.1.18.6
}		
/* end hash */		
}		
}		

5.2.22 packet_group_header()

Table 32: Syntax of packet_group_header()

Syntax	Encoding	Clause
packet_group_header()		6.1.19
{		
packet_group_symbol_arrangement	v(4)	6.1.19.1
packet_group_mask	v(6)	6.1.19.2
if (packet_group_mask & 0x1)		
{		
reserved	v(32)	
}		
if (packet_group_mask & 0x2)		
{		
switch (packet_group_symbol_arrangement)		
{		
case 0:		
case 1:		
reserved	v(4)	
pgsi_bits = num_bits_code()		6.1.19.3, 5.2.23
for (index=0; index < packet_group_num_symbols; index++)		
{		
packet_group_symbol_index	u(pgsi_bits)	6.1.19.4
}		
break		
case 2:		
reserved	v(4)	
pgfsi_bits = num_bits_code()		5.2.23
packet_group_first_symbol_index	u(pgfsi_bits)	
packet_group_index_difference	u(16)	
break		
default:		
reserved	v(2)	
pgsii_bits = num_bits_code()		
packet_group_symbol_index_info = extension(pgsii)		5.2.18
break		
}		
}		
if (packet_group_mask & 0x4)		
{		
b_addl_packet_group_cce_params_present	b(1)	6.1.19.1
if (b_addl_packet_group_cce_params_present)		
{		
addl_cce_parameters()		5.2.6
}		
}		
if (packet_group_mask & 0x8)		
{		
/* start packet_group encryption */		
for (index=0; index < packet_group_num_symbols; index++)		
{		
coefficient_vector(block_num_symbols, block_field_size_exp_val)		5.2.17
}		
/* stop packet_group encryption */		
}		
if (packet_group_mask & 0x10)		
{		
packet_group_integrity() = packet_integrity()		5.2.16
}		
if (packet_group_mask & 0x20)		
{		
packet_group_header_extension = extension(5)		5.2.18
}		
byte_align	pad	
}		

5.2.23 num_bits_code()

Table 33: Syntax of num_bits_code()

Syntax	Encoding	Clause

num_bits_code()
{
bits_code
num_bits = (bits_code + 1) × 8
return num_bits
}
	u(2)	6.1.20
		
		6.1.20.1

5.2.24 block_index_or_count_value()

Table 34: Syntax of block_index_or_count_value()

Syntax	Encoding	Clause

block_index_or_count_value()
{
block_index_or_count
if (block_index_or_count == 0xFF)
{
block_index_or_count_ext
}
else
{
block_index_or_count_ext = 0
}
block_index_or_count_val = block_index_or_count +
block_index_or_count_ext
return block_index_or_count_val
}
	u(8)
	
	u(32)
		6.1.21
		
		6.1.21.1
		
		6.1.21.1
		
		6.1.21.1

5.2.25 multi_block_packet_group()

Table 35: Syntax of multi_block_packet_group()

Syntax	Encoding	Clause

multi_block_packet_group()
{
mbpg_index
mbpg_start_block_index = block_index_or_count_value()
 	
mbpg_num_blocks = block_index_or_count_value()
 	
mbpg_num_symbols
mbpg_header()
/* start hash */
for (symbol=0; symbol<num_mbpg_symbols; symbol++)
{
coded_symbol
 	
}
/* end hash */
}
	u(16)
	
	u(64)
	
	u(block_symbol_size × 8)
		6.1.22
		
		6.1.22.1
		5.2.24,
		6.1.22.2
		5.2.24,
		6.1.22.3
		6.1.22.4
		5.2.26
		
		6.1.22.5

5.2.26 mbpg_header()

Table 36: Syntax of mbpg_header()

Syntax	Encoding	Clause
mbpg_header()		6.1.23
{		
mbpg_symbol_arrangement	v(4)	6.1.23.1
reserved	v(4)	
switch (mbpg_group_symbol_arrangement)		
{		
case 0:		
case 1:		
reserved	v(4)	
mbpgsi_bits = num_bits_code()		5.2.23, 6.1.23.2
for (index=0; index < mbpg_num_symbols; index++)		
{		
mbpg_source_block_index = block_index_or_count_value()		5.2.24, 6.1.23.3
mbpg_symbol_index	u(mbpgsi_bits)	6.1.23.3
}		
break		
case 2:		
case 3:		
reserved	v(4)	
mbpg_index_difference	u(16)	6.1.23.6
mbpgfsi_bits = num_bits_code()		5.2.23, 6.1.23.4
mbpg_first_symbol_index	u(mbpgfsi_bits)	6.1.23.7
b_mbpg_is symbol_group_subset	b(1)	
if (b_mbpg_is_symbol_group_subset)		
{		
mbpg_symbol_group_subset_index	u(64)	6.1.23.5
)		
else		
{		
mbpg_symbol_group_subset_index = 0		
}		
break		
default:		
reserved	v(4)	
mbpgsai_bits_code	v(2)	6.1.23.7
mbpgsai_bits = 8 × 2^mbpgsai_bits_code		
mbpg_symbol_arrangement_info = extension(mbpgsai_bits)		5.2.18
break		
}		
b_mbpg_integrity_present	b(1)	6.1.23.9
if (b_mbpg_integrity_present)		
{		
mbpg_integrity() = packet_integrity()		5.2.16
}		
b_mbpg_header_ext_present	b(1)	6.1.23.10
if (b_mbpg_header_ext_present)		
{		
mbpg_header_extension = extension(6)		5.2.18
}		
byte_align	pad	
}		

6 Bitstream description

6.0 Introduction

This clause describes the meaning of the fields in the CMMF bitstream syntax. Bit fields that are similar in purpose and/or meaning have been grouped and described only once.

6.1 Description of bitstream elements

6.1.1 cmmf_bitstream()

The `cmmf_bitstream()` is the top-level structure containing the `sync()` and all `subatom()` instances for the encoded CMMF bitstream.

6.1.2 subatom()

6.1.2.0 Introduction

The subatom (`subatom()`) is a generic structure that represents various types of data present in the CMMF bitstream.

Subatoms inherit values from previously received subatoms with a matching `bitstream_id` (if present the bitstream). For example, the `packet_header()` structure should be able to use `block_field_size_exp` field present in a previously received `block_header()` with the same associated `block_index` / `packet_block_index`.

6.1.2.1 subatom_id, subatom_id_ext

The `subatom_id` field, which is extendable by the `subatom_id_ext` field, identifies the type of data in contained within the subatom. This field indicates which syntactical structure is present in the subatom.

Subatom identification values are provided in Table 37.

Table 37: subatom_id meaning

`subatom_id` value	Associated Constant Identifier	Subatom Data Type
0		Reserved
1	SUBATOM_ID_SYNC	Bitstream synchronization
2	SUBATOM_ID_BITSTREAM_HEADER	Bitstream header
3	SUBATOM_ID_ENCODER_CONTENT_INFO	Encoder and content information
4	SUBATOM_ID_MEDIA_SEGMENT_INFO	Media segment information
5	SUBATOM_ID_BLOCK_HEADER	Block header
6	SUBATOM_ID_PACKET	Packet
7	SUBATOM_ID_CHUNKED_SUBATOM	Chunked subatom
8	SUBATOM_ID_BLOCK_GROUP_DIRECTORY	Block header and packet group directory
9	SUBATOM_ID_PACKET_HEADER_ONLY	Packet header only
10	SUBATOM_ID_PACKET_GROUP	Packet group
11	SUBATOM_ID_MULTI_BLOCK_PACKET_GROUP	Multiple block packet group header
12 - 270		Reserved

If a reserved subatom data type is received, a parser shall skip over the subatom.

While a valid bitstream can contain a single subatom type, decoding requires receipt of multiple subatoms, either in a single bitstream or cumulatively across multiple bitstreams depending on the application.

Although not syntactically hierarchical, subatoms can inherit information from previously received subatom instances. As such, each subatom is not independent, and may require data from a different/previous `subatom()` instance to be parsed and/or decoded correctly. Subatom dependencies are provided in Table 38.

Table 38: Subatom dependencies

Subatom Data Type (`subatom_id`)	Subatom Dependency (`subatom_id`)
Block header (5)	Bitstream header (2)
Packet (6)	Block header (5)
Packet header only (9)	Block header (5)
Packet group (10)	Block header (5)
Multiple block packet group header (11)	Block header (5)

Any additional subatom requirements are described within the definition for each subatom.

6.1.2.2 b_bitstream_id_present

This Boolean indicates whether the `bitstream_id` is present the bitstream. This bit shall be set to the same value in every `subatom()` instance in a `cmmf_bitstream()`.

6.1.2.3 sas_bits

The operational variable `sas_bits` is used in the syntax to specify the number of bits used to encode the subatom data and is represented by the `num_bits_code()` structure.

6.1.2.4 bitstream_id

The `bitstream_id` field identifies different subatoms as belonging to the same bitstream. In applications where simultaneous bitstreams are transmitted, this identification enables a receiver/decoder to determine which subatoms belong to which bitstream.

`bitstream_id`, if present in the bitstream, shall be set to the same value in every `subatom()` instance in the bitstream.

6.1.2.5 subatom_size

The `subatom_size` field describes the size of the subatom data, in bytes. The subatom data is marked by the 'subatom data start' and 'subatom data end' labels. That is, the subatom data type as indicated by the `subatom_id` field, and any additional padding required to ensure that the `subatom_size` is a whole number of bytes. Packet subatoms and block directory subatoms shall have no additional padding.

6.1.3 sync()

6.1.3.0 Introduction

The synchronization (`sync()`) structure appears at the beginning of every bitstream and identifies the stream as being a CMMF bitstream. Depending on the application, the `sync()` structure can also be contained within a `subatom()` as needed in order to resynchronize in the middle of a stream.

6.1.3.1 syncword

The `syncword` field is a synchronization word used to identify a CMMF bitstream.

The value of the `syncword` field shall be `0x89780D430044AC31`.

6.1.3.2 version

The `version` field specifies the version of the CMMF bitstream syntax. Encoders conforming to the present document shall use a value of `0` for this field. Bitstream parsers conforming to the present document shall be able to parse version 0. Bitstream parsers conforming to the present document shall reject bitstreams with a version higher than 0.

Bitstream parsers capable of parsing a specific version of the CMMF bitstream shall be able to parse all lesser versions and shall reject all higher versions.

6.1.3.3 b_content_encode_uuid

This Boolean indicates whether the `content_encode_uuid` field is present in the bitstream.

6.1.3.4 content_encode_uuid

The `content_encode_uuid` field identifies a specific encode of a piece of content. This field should carry a version 4, variant 1 universally unique identifier as specified in IETF RFC 9562 [1].

6.1.4 bitstream_header()

6.1.4.0 Introduction

The bitstream header (`bitstream_header()`) structure contains high-level general file information about the encoded data and encoding method.

6.1.4.1 content_source_size

The `content_source_size` field describes the size of the source data, in bytes. If the source data exceeds the size practical for an application, the source data can be split, and multiple bitstreams used.

If the `content_source_size` field is zero, it indicates the source data has a size of 0 bytes, or the size of the source data is not relevant to the application, or the source data is of an undetermined size.

6.1.4.2 content_source_type

The `content_source_type` field describes the source of the encoded data within the bitstream as listed in Table 39.

Table 39: content_source_type meaning

`content_source_type` value	Meaning
`000b`	Not indicated
`001b`	Original data file
`010b`	Reserved
`011b`	Live streaming source
`100b-111b`	Reserved

6.1.4.3 b_content_source_split

This Boolean indicates whether the source data has been split and carried in multiple bitstreams. When True, the `content_source_split_start` and `content_source_split_end` fields are present in the bitstream.

6.1.4.4 content_soure_split_start, content_source_split_end

The `content_source_split_start` and `content_source_split_end` fields describe the start and end byte range of the original source data that is carried in the bitstream. A parser can use this information to reassemble the original source data.

6.1.4.5 code_type, code_type_ext

The `code_type` field, which is extendable by the `code_type_ext` field, identifies the type of code applied to the data in the bitstream. The different coding types are listed in Table 40. Client rendering devices shall support decoding a minimum of one of the supported code types.

Table 40: code_type meaning

`code _type` value	Meaning
0	xCD-1, as defined in annex A
1	Raptor as defined in IETF RFC 5053 [16]
2	Reserved
3	Reserved
4	Reserved
5	Reed-Solomon (GF{2^8}), as defined in IETF RFC 5510 [14]
6	RaptorQ, as defined in IETF RFC 6330 [13]
7 - 270	Reserved

6.1.4.6 b_rfc5052, rfc5052_information(), b_addl_rfc5052_information_present

This Boolean indicates that CMMF is used as a Content Delivery Protocol (CDP) as defined in IETF RFC 5052 [15]. When True, data shall be partitioned according to the algorithm described in section 9.1 of IETF RFC 5052 [15], and the additional fields contained within the `rfc5052_information()` structure that describe the mandatory, common, and scheme-specific Object Transmission Information (OTI) are present in the bitstream. Some of these additional fields have meaning related to, or identical to, other fields in the bitstream. The OTI fields, their meaning, and related CMMF fields are specified in Table 41.

Table 41: Object Transmission Information Fields

Field	Meaning	Related CMMF Field
`encoding_symbol_length`	See section 6.2.4 of IETF RFC 5052 [15]	`block_symbol_size` (see clause 6.1.5.3)
`maximum_source_block_length`	See section 6.2.4 of IETF RFC 5052 [15]	`block_num_symbols` (see clause 6.1.5.5)
`max_number_of_encoding_symbols`	See section 6.2.4 of IETF RFC 5052 [15]	N/A

When the `b_rfc5052` field is True and the `rfc5052_information()` structure is present, related fields with identical meaning, the `encoding_symbol_length` and `block_symbol_size`, as well as `maximum_source_block_length` and `block_size`, can both be transmitted within the bitstream. In this case, both fields in the shall have the same value.

If the `b_rfc5052` field is True, then blocks shall have identical symbol size (`block_symbol_size`) and the blocks represent the source blocks according to the source blocking of the IETF RFC 5052 [15] FEC scheme.

The mapping from mandatory, common, and scheme-specific OTI parameters to CMMF bitstream elements/fields and values is provided in Table D.2 in clause D.1.4.

The `b_addl_rfc5052_information_present` Boolean indicates whether the `addl_rfc5052_information()` structure is present in the bitstream. The `addl_rfc5052_information()`structure provides a mechanism to transmit additional IETF RFC 5052 [15] information when needed and is an instance of the `extension()` structure.

6.1.4.7 block_count_minus1, block_count

The operational variable `block_count_minus1` which is represented by the `block_index_or_count_value()` structure, describes the total number of blocks present in the bitstream, minus one.

The operational variable `block_count` is used throughout the syntax and is calculated as follows:

```
block_count = block_count_minus1 + 1
```

The equation assumes that the `block_count_minus1` operand has accounted for the `block_count_ext` field when present in the bitstream.

For live streaming applications where the source data stream may continue indefinitely, three options are available. First, the value of `block_index_or_count` in the `block_index_or_count_value()` structure, and thereby the value of `block_count_minus1` may be `0`, meaning there is only a single block present in the bitstream. Other parameters, such as the `window_start_index` and `window_stop_index` fields contained within the packet subatom can be used to differentiate between encoding blocks. Second, the value of `block_index_or_count` in the `block_index_or_count_value()` structure may be `255`. If the `block_index` exceeds 256 blocks, a subsequent bitstream shall be created with the `block_index` reset to `0`. This second option can also be used when an application or code type require more than 256 blocks, e.g. Reed-Solomon coding. Third, the extension `block_index_or_count_ext` in the `block_index_or_count_value()` structure can be used to signal a significant number of additional blocks if necessary.

`block_count_minus1` may appear in multiple subatoms, such as the bitstream header and block directory subatoms. All instances of this operational variable within a bitstream shall be set to the same value.

6.1.4.8 b_content_block_separate_sources

This Boolean indicates whether blocks contain data from separate (but possibly related) sources. For example, block 0 may contain a video segment, while block 1 may contain an audio segment for the same content. When this field is TRUE the `num_content_block_sources_minus1` field is present in the bitstream.

An individual block may be composed of multiple smaller sources (see clause 6.1.5.11 b_block_composite_sources). When a block is composed of multiple smaller sources (i.e. `b_block_composite_sources` is TRUE), for the purposes of setting `b_content_block_separate_sources` (and the related `b_block_content_source_index_present` field in `block_header()`) it shall be considered as having a single source.

For more information on `b_block_content_source_index_present`, see clause 6.1.5.9.

6.1.4.9 num_content_block_sources_minus1

`num_content_block_sources_minus1` describes the number of sources of data that populate the blocks in the bitstream, minus one. The number of sources shall be less than or equal to the number of blocks (indicated by the `block_count` variable) present in the bitstream.

6.1.4.10 b_profile_information_present

This Boolean indicates whether information about the profile that this bitstream conforms to, as indicated by the `profile_type_size`, `profile_type`, and `profile_description` fields, is present in the bitstream.

6.1.4.11 profile_type_size, profile_type

The `profile_type` field is a string of ASCII [7] or UTF-8 [11] characters describing the entity defining the profile. The size (in bytes) of the `profile_type` field is indicated by the `profile_type_size` field.

`profile_type` shall not be set to a value of `0`.

6.1.4.12 profile_description

The `profile_description` field identifies the profile which the bitstream conforms to, as defined by the entity indicated by the `profile_type` field.

A profile may impose constraints on the coding type used, number of blocks, number of symbols or other encoding parameters. Determining whether a bitstream conforms to a specific profile may be useful to applications to quickly determine whether a bitstream is suitable for a specific decoder/parser with restricted or limited capabilities.

6.1.4.13 b_block_cc_encrypted

This Boolean indicates whether the coding coefficient information in one or more blocks is encrypted.

In this case, the `bitstream_encryption_key_id_size_exp` and `bitstream_encryption_key_id` fields are present in the bitstream. The `bitstream_encryption_key_id` can then be used to retrieve the required `bitstream_encryption_key` from a secure/trusted third-party.

6.1.4.14 bitstream_encryption_key_id_size_exp

The `bitstream_encryption_key_id_size_exp` field contains the exponent used to determine the size (in bits) used to transmit the subsequent `bitstream_encryption_key_id`. The size is given by the following equation:

```
bseki_bits = 2^ bitstream_encryption_key_id_size_exp
```

6.1.4.15 bitstream_encryption_key_id

The `bitstream_encryption_key_id` field identifies the key used to symmetrically encrypt certain block encryption parameters.

The identification can be a simple numeric identifier, or for example, a hash of the key.

The encryption method is outside the scope of the present document.

6.1.5 block_header()

6.1.5.0 Introduction

The block header (`block_header()`) structure provides information about how the portion of the data within that block is encoded. It contains fields that describe the coding parameters used for the indicated block.

6.1.5.1 block_index

The operational variable `block_index`, which is represented by the `block_index_or_count_value()` structure, describes which block this `block_header()` instance is associated with.

6.1.5.2 block_size

The `block_size` field describes the number of bytes from the original data the block contains.

A `block_size` value of `0` may be used to indicate that the block size is either not relevant, or the block is empty, or the size is undetermined. A `block_size` value of `0` shall only be used when `block_count` is `1`.

6.1.5.3 block_symbol_size

The `block_symbol_size` field describes the size in bytes of each symbol and coded symbol in the block.

A `block_symbol_size` value of `0` is used to indicate that the coded symbols in the block have a varying size, and the size shall be determined by other means. The `block_symbol_size` shall not have a value of `0` when packet group subatoms are present.

For more information on `coded_symbol`, see clause 6.1.6.2.

6.1.5.4 bns_bits

The operational variable `bns_bits` is used in the syntax to specify the number of bits used to encode the `block_num_symbols` field and is represented by the `num_bits_code()` structure.

6.1.5.5 block_num_symbols

The `block_num_symbols` field describes the number of symbols that the original block of data has been divided into.

A block_num_symbols value of 0 may be used to indicate that the block has an unknown number of symbols. A block_num_symbols value of 0 shall only be used when block_count is 1.

6.1.5.6 b_block_max_symbol_index_present

This Boolean indicates whether the maximum encoded symbol index (or row index) value for the given block is present in the bitstream. When TRUE, the block_max_symbol_index field is present in the bitstream.

6.1.5.7 bmsi_bits

The operational variable bmsi_bits is used in the syntax to specify the number of bits used to encode the block_max_symbol_index field and is represented by the num_bits_code() structure.

6.1.5.8 block_max_symbol_index

The block_max_symbol_index field identifies either the value of the maximum symbol index when encoded symbol indexes are used to identify coded symbols, or the value of the maximum row index when a pseudo-random number generator is used to determine the coding coefficients for the block.

For example, if a block contains 20 coded symbols with symbol index values 0-19, then the block_max_symbol_index value for the block would be 19.

6.1.5.9 b_block_content_source_index_present

This Boolean indicates whether the given block contains data from a different source than the other blocks present in the bitstream. When TRUE, the block_content_source_index field is present in the bitstream.

If the b_block_content_separate_sources field in the bitstream_header() is TRUE, then b_block_content_source_index_present field shall be TRUE.

6.1.5.10 block_content_source_index

The block_content_source_index field identifies which source, of the num_content_block_sources the data in this block is associated with. The field has a range of [0, num_content_block_sources - 1].

6.1.5.11 b_block_composite_sources

This Boolean indicates whether the given block contains composite data from multiple different sources. The b_block_composite_sources field indicates whether additional fields that describe the number and size of each composite source are present in the bitstream.

6.1.5.12 block_num_composite_sources_minus1

The block_num_composite_sources_minus1 field describes the number of composite sources that make up the data contained within the block, minus 1. The field has a range of [1, 256]. For each composite source, there will be an instance of num_bits_code() and the block_composite_source_size field in the bitstream.

6.1.5.13 bcss_bits

The operational variable bcss_bits contains the number of bits the subsequent related field requires and is represented by the num_bits_code() structure.

6.1.5.14 block_composite_source_size

The block_composite_source_size field describes the size of the composite source data, in bytes, that is present within the block.

6.1.5.15 b_addl_block_coding_info_present

This Boolean indicates whether additional information describing the coding used in the given block follows in the bitstream.

Otherwise, no sliding window is used and the coding information is described by other fields in the bitstream (e.g. `code_type`, `block_mask`).

6.1.5.16 addl_block_coding_mask

The `addl_block_coding_mask` field is a bit mask that describes additional coding information and indicates which subsequent fields are present in the bitstream as specified in Table 42.

Table 42: addl_block_coding_mask meaning

`addl_block_coding_mask` bit	Meaning
0	Sliding window coding used: This bit indicates whether a sliding window is used. The start and stop indexes of the sliding window are present in the packet subatom or the packet header only subatom.
1	Reserved: This bit indicates whether the `b_reserved_block_coding_params_present` element is present in the bitstream. See clause 6.1.5.15.
2	Reserved: This bit indicates whether the `reserved_block_coding_info()` structure is present in the bitstream. This structure is an instance of the `extension()` structure, and shall be ignored by bitstream parsers that conform to this version of CMMF.

6.1.5.17 b_addl_window_info_present

This Boolean indicates whether the `addl_window_info()` element follows. The `addl_window_info()` element is an instance of the `extension()` structure.

6.1.5.18 b_reserved_block_coding_params_present

This Boolean indicates whether the `reserved_block_coding_params()` element follows. The `reserved_block_coding_params()` element is an instance of the `extension()` structure, and shall be ignored by bitstream parsers that conform to this version of CMMF.

6.1.5.19 block_mask

The `block_mask` field is an array of Booleans that indicates which subsequent fields are present and follow in the bitstream as listed in Table 43.

Table 43: block_mask meaning

`block_mask` bit	Meaning
0	Sufficient symbols present: This Boolean indicates whether fields describing the number of encoded symbols contained within the bitstream are present in the bitstream. Otherwise, the number of encoded symbols contained within the bitstream cannot be immediately ascertained without attempting to parse the full bitstream and a system is unable to determine if enough symbols are present to perform a full decode of the given block.
1	Block Field size: This Boolean indicates whether fields specifying the Galois field size used during the encoding process are present in the bitstream. Otherwise, the default Galois field size, GF{2}, `block_field_size_exp_val` = 1, is used for `code_type` values that support different Galois field sizes. `code_type` values where the Galois field size is irrelevant shall set this bit to False.

block_mask bit	Meaning
2	Separated coding coefficients: This Boolean indicates whether the coding coefficient information is carried separately, either in the packet_header() structure as part of the packet header only subatoms, or within the packet_group_header() structure as part of the packet group header only subatoms. Otherwise, the coding coefficient information is included in the packet_header() within the packet subatoms or the packet_group_header() within the packet group subatoms. When this Boolean is FALSE, packet header only subatoms and packet group header only subatoms shall not be present in the bitstream.
3	Encrypted coding coefficient information: This Boolean indicates whether the coding coefficient information (and in some cases the coded symbol itself) is encrypted using symmetric encryption described by fields that follow in the bitstream.
4	Block seed: This Boolean indicates whether fields indicating the pseudorandom number generator seed used to generate the coding coefficients for every coded symbol in the block are present in the bitstream. Otherwise, the coding coefficients are transmitted by other means in the bitstream.
5	Block integrity: This Boolean indicates whether the block_integrity() structure is present in the bitstream. This structure provides a mechanism to verify that the received and decoded data in the block matches that of the original source. This structure is an instance of the fb_integrity() structure.

Bit 2 (separated coding coefficients) and bit 4 (block seed) of block_mask are mutually exclusive., and shall not both be set simultaneously.

EXAMPLE: A block_mask value of 100010b, with bit 1 set indicating an alternate block field size, and bit 5 set indicating the presence of the block integrity check.

6.1.5.20 b_sufficient_symbols_present

This Boolean indicates whether a sufficient number of encoded symbols (greater than or equal to block_num_symbols) are present in the bitstream to decode the current block. Otherwise, the block_symbols_present field is present in the bitstream.

6.1.5.21 bsp_bits

The operational variable bsp_bits is used in the syntax to specify the number of bits used to encode the block_symbols_present field and is represented by the num_bits_code() structure.

6.1.5.22 block_symbols_present

The block_symbols_present field describes the number of encoded symbols present within the bitstream associated with the current block.

In a multisource network there may be multiple CMMF bitstreams, with some bitstreams containing a sufficient number of encoded symbols to decode the current block and others with only a partial set of symbols. The block_symbols_present field describes the number of encoded symbols present within the bitstream, associated with the current block. A system may use this information to determine whether it needs to seek alternate sources (i.e. bitstreams) to obtain additional encoded symbols.

6.1.5.23 block_field_size_exp

If block_field_size_exp is present in the bitstream, coding coefficients are used to create encoded symbols. These coefficients come from a finite field set, a Galois field. The size of this Galois field is given by a characteristic prime, 2 in this case, and an exponent. This determines the number of possible coding coefficients in the field set. In addition to the field size, a Galois field set is also defined by the characteristic polynomial.

block_field_size_exp specifies both the field size exponent, and characteristic polynomial (given by *P(x)*) used to define the Galois field used for the block. The field is interpreted as listed in Table 44.

Table 44: block_field_size_exp information

block_field_size_exp value	Field Size Exponent	Characteristic polynomial *P(x)*
000b	2	$x^2 + x + 1$
001b	4	$x^4 + x + 1$
010b	8	$x^8 + x^4 + x^3 + x^2 + 1$
011b	16	$x^{16} + x^{12} + x^3 + x + 1$
100b-111b	Reserved	

For example, if block_field_size_exp has a value of 001b, then the field size exponent is 4 and the resulting Galois field size is GF{2^4} or GF{16}, meaning there are only 16 possible coding coefficients. Also, the characteristic polynomial is given by $P(x) = x^4 + x + 1$.

If the block_field_size_exp field is not present in the bitstream, i.e. if bit 1 of block_mask is set to 0, then the field size exponent takes on a default value of 1.

If the reserved values of block_field_size_exp (100b-111b) is received, it is considered an error.

The syntax uses an operational variable, block_field_size_exp_val. This variable takes on the field size exponent value indicated by the block_field_size_exp field or has the default value (1) when the block_field_size_exp field is not present in the bitstream.

6.1.5.24 Encrypted Coefficients

6.1.5.24.0 Introduction

When bit 3 of the block_mask field is set, the coding coefficient information in the bitstream is encrypted. The coding coefficient information can be any of:

- prng_seed and prng_density_percentage within prng_parameters() in block_header().
- coefficient_vector() in packet_header() within the packet subatom or the packet header only subatom.
- coefficient_vector() instances in packet_group_header() within the packet group subatom.
- prng_seed and prng_density_percentage within prng_parameters() in packet_header().
- coded_symbol in packet() for systematic packets.

When the coding coefficient information is encrypted, keys and other encryption parameters are needed in order to decrypt the coefficients and ultimately decode the encoded symbols.

The following fields describe the coding coefficient information encryption keys and parameters.

For more information on generating coding coefficients using a PRNG, see clause 7.1.0.

6.1.5.24.1 block_cc_encryption_info_size_bits_code

The block_cc_encryption_info_size_bits_code field describes the number of bits used to describe the size of the block encryption information size (indicated by the block_cc_encryption_info_size field). The meaning of this field is specified in Table 45.

Table 45: block_cc_encryption_info_size_bits_code meaning

block_cc_encryption_info_size_bits_code value	Meaning
0b	The subatom data size is indicated using 8 bits.
1b	The subatom data size is indicated using 16 bits.

The variable `bcceis_bits` is used in the syntax to specify the number of bits used to encode the block encryption information and is based on the `block_cc_encryption_info_size_bits_code` field according to the following equation:

```
bcceis_bits = (block_cc_encryption_info_size_bits_code + 1) × 8
```

6.1.5.24.2 byte_align

This bit field of size 0 to 7 bits is used for the byte alignment of the associated `block_header()` structure. Byte alignment is defined relative to the start of the enclosing syntactic element.

6.1.5.24.3 block_cc_encryption_info_size

The `block_cc_encryption_info_size` field describes the size of the block encryption information data, in bytes. The data comprises of several fields and is marked by the '*block encryption info start*' and '*block encryption info end*' labels including any additional padding required to ensure that the `block_cc_encrypton_info_size` is a whole number of bytes.

NOTE: All the fields between the '*block encryption info start*' and '*block encryption info end*' labels are themselves encrypted using the key identified by the `bitstream_encryption_key_id` field. This blob of data has to be decrypted first, then parsed according to the relevant `block_header()` syntax to obtain the actual bitstream field values.

6.1.5.24.4 block_cc_encryption_algorithm

`block_cc_encryption_algorithm` specifies the algorithm used to encrypt the coding coefficient information. The different algorithm types are listed in Table 46.

Table 46: block_cc_encryption_algorithm meaning

`block_cc_encryption_algorithm` Value	Meaning
000b	AES
001b-111b	Reserved

6.1.5.24.5 block_cc_encryption_mode

`block_cc_encryption_mode` specifies the mode of chaining operation used to encrypt the coding coefficient information. The different algorithm types are listed in Table 47.

Table 47: block_cc_encryption_mode meaning

`block_cc_encryption_mode` Value	Meaning
0000b	Electronic Code Book (ECB)
0001b	Cipher Block Chaining (CBC)
0010b	Cipher Feedback (CFB)
0011b	Output Feedback (OFB)
0100b	Counter (CTR)
0101b	Open Pretty Good Privacy (openPGP)
0110b-1111b	Reserved

6.1.5.24.6 block_cce_key_size_exp, block_cce_key

`block_cce_key` is the symmetric key used to encrypt the coding coefficient information. The key size (in bits) of the `block_cce_key` field is indicated by the `block_cce_key_size_exp` field according to the equation:

```
bck_bits = 2 ^ block_cce_key_size_exp
```

6.1.5.24.7 b_addl_block_cce_params_present

This Boolean indicates whether additional encryption parameters required to decrypt the coding coefficient information, contained in the `addl_cce_parameters()` structure, follow in the bitstream.

6.1.5.24.8 addl_cce_parameters()

6.1.5.24.8.0 Introduction

The `addl_cce_parameters()` structure contains additional encryption parameters. The context of `addl_cce_parameters()` is defined by the containing `block_header()`, `packet_header()`, or `packet_group_header()` structure.

6.1.5.24.8.1 num_addl_block_cce_params_minus1

`num_addl_block_cce_params_minus1` describes the number of additional encryption parameters, minus one. There can be up to 4 additional encryption parameters.

6.1.5.24.8.2 cce_parameter_type

`cce_parameter_type` specifies the type of encryption parameter that follows in the bitstream. The parameter types are listed in Table 48.

Table 48: cce_parameter_type meaning

`cce_parameter_type` Value	Meaning
`000b`	Number once (nonce)
`001b`	Initialization Vector (IV)
`010b`	Initial value
`011b`	Counter start value
`100b`	Counter (CTR)
`101b-111b`	Reserved

6.1.5.24.8.3 cce_parameter_size_exp, cce_parameter

`cce_parameter` is an encryption parameter used to encrypt the coding coefficient information. The type of parameter is described by the `cce_parameter_type` field. The parameter size (in bits) of the `cce_parameter` field is indicated by the `cce_parameter_size_exp` field according to the equation:

```
ccep_bits = 2 ^ cce_parameter_size_exp
```

6.1.5.25 Pseudorandom Noise Generator (PRNG)

6.1.5.25.0 Introduction

A PRNG is used to generate coding coefficients that are applied to source symbols to create encoded symbols. The generated coefficients can be transmitted verbatim in the bitstream, or the state of the PRNG, known as the seed, can be transmitted and a decoder can regenerate the same coding coefficient matrix calculated in an encoder. Using a row index, a decoder can select the appropriate row of the coding coefficient matrix. Transmission of the PRNG seed and row index can be more efficient than transmission of the coding coefficients.

Depending on the `code_type` value, a PRNG seed may be used to determine the coding coefficient(s) for all the coded symbols within a block, or the coded symbol in a packet.

To control the density of coding coefficients, i.e. the percentage of non-zero coefficients, a density value can be transmitted to modify the coefficients output from the PRNG can be transmitted.

The `prng_parameters()` structure contains fields that describe the PRNG seed and density values. The context of `prng_parameters()` is defined by the containing `block_header()`, or `packet_header()` structure.

If the coding coefficient information is encrypted (i.e. bit 3 of the block_mask field is set), then all fields between *'prng_parameters() encryption info start'* and *'prng_parameters() encryption info end'* labels in the prng_parameters() structure are symmetrically encrypted using the block_cce_key and associated parameters.

When a PRNG is used to generate a matrix of coding coefficients, a row index into this matrix is required in order to select the appropriate coding coefficients. This row index value is represented by:

- packet_symbol_index in the packet_header() in a packet subatom
- packet_group_symbol_index in the packet_group_header() in a packet group subatom
- mbpg_symbol_index in the mbpg_header() in a multiple block packet group subatom

If a coded symbol has a row index value less than the block_num_symbols value in the associated block header subatom, then that coded symbol shall be a systematic symbol, regardless of whether it is indicated as such (for example by the b_systematic_symbol flag in packet_header()). Further, when the row index is less than block_num_symbols, the identified row of coefficients generated by the PRNG shall be discarded and replaced with a coefficient vector consisting of all 0's except at the index identified by the row index value (as indicated by either packet_symbol_index, or packet_group_symbol_index, or mbpg_symbol_index), where the coefficient shall be 1.

For more information on generating coding coefficients using a PRNG, see clause 7.1.0.

6.1.5.25.1 prng_type

prng_type specifies the type of number generator to use to generate the coding coefficient(s) for the given block or packet. The different prng types are listed in Table 49.

Table 49: block_prng_type meaning

block_prng_type Value	Meaning
000b	Mersenne Twister (MT) [8]
001b-111b	Reserved

6.1.5.25.2 prng_seed_bits_code

The prng_seed_bits_code field describes the number of bits the prng_seed field is encoded with as indicated in Table 50.

Table 50: block_prng_seed_bits_code meaning

prng_seed_bits_code value	Meaning
0	16 bits
1	32 bits
2	64 bits
3	Reserved

The operational variable ps_bits uses the prng_seed_bits_code value to determine the number of bits the subsequent prng_seed field requires. It can also be calculated as follows:

```
ps_bits = 2^(prng_seed_bits_code + 4)
```

If the reserved value of prng_seed_bits_code (3) is received, it is considered an error.

6.1.5.25.3 prng_seed

prng_seed specifies the seed value used to initialize the PRNG for generating coefficients for the block or packet.

6.1.5.25.4 prng_density_percentage

`prng_density_percentage` describes the percentage of coding coefficients that are, on average, non-zero. The field is encoded as a fraction in range (0, 1] and the actual percentage is determined by the following equation:

density percentage = 100 × (`prng_density_percentage` + 1) / 128

An operational variable, `density_int` is defined as:

`density_int` = (`prng_density_percentage` + 1)

6.1.6 packet()

6.1.6.0 Introduction

The packet (`packet()`) structure contains the `packet_header()`, as well as a coded symbol (an individual symbol group), which is a fundamental piece of encoded data.

Packets, as well as other fields contained within larger structures, inherit values from previous `subatom()` instances. For example, the `packet()` structure inherits the value of the `block_field_size_exp` field specified in the associated `block_header()`, that is, the `block_header()` with the `block_index` value that matches the `packet_block_index` value.

6.1.6.1 packet_block_index

The operational variable `packet_block_index`, which is represented by the `block_index_or_count_value()` structure if `block_count` is greater than `1`, describes which block this `packet()` (or `packet_header_only()`) instance is associated with. If the bitstream only contains a single block (i.e. `block_count` is `1`), then the `block_index_or_count_value()` structure is not present in the bitstream and takes on a value of `0`.

As an example, if the `packet_block_index` is `1`, then the associated block and its related `block_header()` instance has a `block_index` value of `1` as well.

6.1.6.2 coded_symbol

A `coded_symbol` is either a systematic symbol or the encoded version of a number of source symbols, generated by applying coding to the original data symbols. The size of this field is determined by the operational variable `css_bits` calculated using the following formula:

```
                    css_bits = (subatom_size × 8) -
sizeof(packet_block_index,packet_block_index_ext,packet_header())
```

In the equation above, `subatom_size` is the size indicated in the subatom header for this instance of the `packet()` subatom. The `sizeof` function determines the number of bits used by the fields, or expansion of the structures, prior to the `coded_symbol_data` field.

If the value of the `block_symbol_size` field in the associated `block_header()` instance is not `0`, then the value of `css_bits` shall be equal to `block_symbol_size × 8`.

If the coding coefficient information is encrypted (i.e. bit `3` of the `block_mask` field is set), and the `b_systematic_symbol` field is also set, and the `b_systematic_symbol_encrypted` field is also set, then the `coded_symbol` field is symmetrically encrypted using the `block_cce_key` and associated parameters.

6.1.7 packet_header()

6.1.7.0 Introduction

The `packet_header()` structure provides information about how the coded symbols were encoded. The `packet_header()` will be different depending on whether it is encapsulated in a packet subatom or in a packet header only subatom.

6.1.7.1 b_systematic_symbol

When True, this boolean indicates that the coded symbol in the packet is systematic (i.e. not coded). In this case, a symbol index is present in the bitstream so that the original source symbol can be identified and used to decode the other packets. When this field is False, no immediate indication is given that the coded symbol is systematic, it may indeed be systematic but more information is needed, for example a coefficient vector, to determine wither it is a systematic symbol or not.

If the block contains separated coding coefficients in packet header only subatoms (i.e. bit 2 of the `block_mask` field is set), then the `b_systematic_symbol` field shall be cleared in the packet subatom, and its correct value shall be indicated in the `b_systematic_symbol` field of the associated packet header only subatom.

6.1.7.2 packet_mask

The `packet_mask` field is an array of Booleans that describes which subsequent fields are present in the bitstream as listed in Table 51.

Table 51: packet_mask meaning

`packet_mask` bit	Meaning
0	Symbol/row index present: This Boolean indicates whether index fields are present in the bitstream that identify the symbol or provide an encoding rank.
1	Coding coefficient encryption parameter(s) present: This Boolean indicates whether encryption parameters relevant to this packet are present in the bitstream. This bit can only be set if bit 3 of `block_mask` is also set.
2	Window size: This Boolean indicates whether the coded symbol in the packet is created from a subset of the original symbols contained within the block - a window of symbols, and the start and stop index are present in the bitstream. Otherwise, the coded symbol was created from all the symbols (as given by the coding coefficients) contained within the block.
3	Packet seed: This Boolean indicates whether fields specifying the pseudorandom number generator seed used to generate the coding coefficient for the coded symbol in the packet are present in the bitstream. Otherwise, the coding coefficients are transmitted by other means in the bitstream.
4	Coding vector present: This Boolean indicates whether the `coefficient_vector()` structure is present in the bitstream. This structure explicitly describes the coding coefficients that were used to generate the coded symbol in the packet.
5	Packet integrity: This Boolean indicates whether the `packet_integrity()` structure is present in the bitstream. This structure provides a mechanism to verify that the received data in the packet matches that of the original source bitstream.
6	Packet header extension: This Boolean indicates whether the `packet_header_extension()` structure is present in the bitstream. The `packet_header_extension()` structure provides a mechanism to extend the packet header syntax with additional information and is an instance of the `extension()` structure.

Certain bits of the `packet_mask` are set or cleared depending on the values of other fields. Including:

- If `b_systematic_symbol` is set, then:
  - Bit 0 of `packet_mask` shall be set.
  - Neither bit 2 (window start/stop indexes), nor bit 3 (packet seed), nor bit 4 (coefficient vector) shall be set. That is, the only allowed `packet_mask` value is `BB0001b` (see note below).
- Bit 3 (packet seed) and bit 4 (coefficient vector) are mutually exclusive, and shall not both be set simultaneously.
- If bit 1 of the `addl_block_coding_mask` is set, indicating that a sliding window is used, bit 2 of `packet_mask` shall be set.

- If bit 2 of block_mask is set, indicating that the coding coefficients are separated and described in the packet header only subatom, then:
  - Bit 0 shall be set in the packet_mask field in both the packet subatom as well as the associated packet header only subatom. The corresponding packet_symbol_index values shall have the same value in both instances.
  - Bits 1, 2, 3, 4, 5, and 6 of packet_mask in packet subatom shall be cleared. That is, the only allowed packet_mask value is 000001b (see note). These bits may be set as needed in the associated packet header only subatom packet_mask field.

NOTE: Bit values indicated as B mean that the value of this bit can be set, or not set depending on other settings in an encoder.

An example packet_mask can be 0100001b, with bit 0 set indicating the packet_symbol_index field is present in the bitstream, and bit 5 set indicating the presence of the packet integrity check.

6.1.7.3 psi_bits

The operational variable psi_bits is used in the syntax to specify the number of bits used to encode the packet_symbol_index field. psi_bits is represented by the num_bits_code() structure.

6.1.7.4 packet_symbol_index

The packet_symbol_index field defines an index whose meaning is context dependent:

- If the b_systematic_symbol is set, the packet_symbol_index value is the original symbol index number.
- For certain code_type values, (e.g. 1 (RaptorQ) or 2 (Reed-Solomon)), the packet_symbol_index value represents the encoded symbol index to identify each coded symbol.
- If bit 2 of block_mask is set, the packet_symbol_index value associates packet header only subatoms carrying the separated coding coefficient information, and the packet subatoms carrying the coded_symbol.
- If bit 4 of block_mask is set, the packet_symbol_index value is the row of the coding coefficient matrix generated by using the block PRNG. Further, if the b_systematic_symbol field is set for this packet, or the value of packet_symbol_index is less than block_num_symbols of the associated block header subatom, then the identified row of coefficients generated by the block PRNG shall be discarded and replaced with a coefficient vector consisting of all 0's except at the index identified by the packet_symbol_index value, where the coefficient shall be 1.

The value of the packet_symbol_index field is 0-indexed. For example, a packet_symbol_index value of 0 can reference the 1st original input symbol for a systematic packet.

6.1.7.5 Encryption Parameters

6.1.7.5.0 Introduction

When bit 1 of the packet_mask field is set, additional encryption parameters needed to decrypt the coding coefficient information within the packet_header() are present in the bitstream. The coding coefficient information within the packet_header() can be any of:

- coefficient_vector() in packet_header() within the packet subatom or the packet header only subatom
- packet_prng_seed in packet_header() or packet_header_only()
- coded_symbol in packet_header() for systematic packets

When the coding coefficient information is encrypted, keys and other encryption parameters are needed in order to decrypt the coefficient information and ultimately decode the coded symbols.

The following fields describe the additional packet or packet header only encryption parameters.

For more details on encrypting coding coefficient information, see clause 7.3.

6.1.7.5.1 b_systematic_symbol_encrypted

This Boolean indicates whether the `coded_symbol` field is encrypted. This field can only be set if the `b_systematic_symbol` field is also set.

6.1.7.5.2 b_addl_packet_cce_params_present

This Boolean indicates whether additional encryption parameters required to decrypt the coding coefficient information, contained in the `addl_cce_parameters()` structure, follow in the bitstream.

6.1.7.6 window_start_index, window_stop_index

The `window_start_index` and `window_stop_index` fields indicate the index of the first symbol present in the coded symbol, the start index, and the index of the last symbol present in the coded symbol, the stop index, to form a window of contiguous symbols from amongst the total set of symbols contained within the block.

The operational variable `window_size` is used in the syntax when the `window_start_index` and `window_stop_index` fields are present in the bitstream, the maximum `window_size` value is 65 536 and is calculated as follows:

```
window_size = modulo(window_stop_index - window_start_index + 1, 65 536)
```

NOTE: Although the maximum window_size value is 65 536 when the window_start_index and window_stop_index fields are present in the bitstream, other practical considerations may impose a stricter limit on the maximum window_size value.

If the `window_start_index` and `window_stop_index` fields are not present in the bitstream, the `window_size` variable is calculated as follows:

```
window_size = block_num_symbols
```

Where `block_num_symbols` is the value taken from the associated `block_header()`.

6.1.7.7 byte_align

This bit field of size 0 to 7 bits is used for the byte alignment of the associated `packet_header()` structure. Byte alignment is defined relative to the start of the enclosing syntactic element.

6.1.8 encoder_content_info()

6.1.8.0 Introduction

The CMMF bitstream has applications in online delivery of audio/video content. The optional encoder content information (`encoder_content_info()`) structure contains information about the specific encoder utilized, and the source assets, such as a content identification. This subatom is useful when CMMF bitstreams for a given asset are generated by multiple encoders in a distributed and/or decentralized fashion. The information contained within this subatom can be used to both validate that the encoder used to generate the bitstream is authorized and the associated bitstream is compatible with bitstreams created by other encoders.

6.1.8.1 b_encoder_id_present

This Boolean indicates whether the `encoder_uuid` field is present the bitstream.

6.1.8.2 encoder_uuid

The `encoder_id` field identifies the specific encoder used to create the bitstream. The field carries a version 4, variant 1 universally unique identifier as specified in IETF RFC 9562 [1]. This field enables efficient use of a plurality of encoders in decentralized settings.

6.1.8.3 Content Identification

The content encoded in an CMMF bitstream can have a content identification.

6.1.8.4 b_content_id_present

6.1.8.4.0 Introduction

This Boolean indicates whether the `content_id_type`, `content_id_size_minus1`, and `content_id`, fields are present the bitstream.

6.1.8.4.1 content_id_type

Several different identification options are supported. The `content_id_type` field indicates the type of identification present in the bitstream. The description of the values is specified in Table 52.

Table 52: content_id_type description

`content_id_type` Value	Identification Description Type
`0x0`	Entertainment Identification Registry (EIDR)
`0x1`	Advertising Digital Identifier (Ad-iD)
`0x2`	Custom identification defined by the user
`0x3`	Universally Unique Identifier (UUID)
`0x4 - 0xE`	Reserved
`0xF`	Unspecified

6.1.8.4.2 content_id_size_minus1

This field indicates the size (in bytes) of the `content_id` field that immediately follows this field, minus one. For example, a `content_id_size_minus1` value of '11' indicates a `content_id` of 12 bytes.

6.1.8.4.3 content_id

This field shall contain the content ID associated with the current content as specified by the `content_id_type`:

- EIDR: For an EIDR content ID type, the `content_id` field shall contain a 96-bit identifier that is registered with EIDR (http://eidr.org) in Compact Binary Format as defined by EIDR [2].
- Ad-ID: For an Ad-ID content ID type, the `content_id` field shall contain an Ad-ID String that represents an identifier registered with Ad-ID (http://www.ad-id.org/) as defined by Ad-ID [3].
- UUID: For a UUID content ID type, the `content_id` field shall contain a 128-bit UUID as defined by IETF RFC 9562 [1].
- Custom ID: For a custom ID type, the `content_id` field is "free-form" and can be populated with ASCII [7] or UTF-8 [11] data.

6.1.8.5 b_content_location_present

This Boolean indicates whether the `content_location_size` and `content_location` fields are present in the bitstream.

6.1.8.6 content_location_size, content_location

The `content_location` field provides the location of the content with size indicated by the `content_location_size` field (in bytes). This field is a string of ASCII [7] or UTF-8 [11] characters. The `content_location_size` field shall not have a value of `0`.

6.1.8.7 b_content_type_present

This Boolean indicates whether the `content_type_size` and `content_type` fields are present in the bitstream.

6.1.8.8 content_type_size, content_type

The `content_type` field is a human-readable description of the type of content with size indicated by the `content_type_size` field (in bytes). This field is a string of ASCII [7] or UTF-8 [11] characters. The `content_type_size` field shall not have a value of `0`.

6.1.8.9 b_content_header_present

This Boolean indicates whether the `content_type_size` and `content_type_size` fields are present in the bitstream.

6.1.8.10 content_header_size, content_header

The `content_header` field contains the first `content_type_size` bytes of the source data, unencoded. The `content_header` field can be parsed using existing methods to determine details about the content encoded within the bitstream. Example details include bit rate, resolution for video content, sampling frequency for audio content, etc. The `content_type_size` field shall not have a value of `0`.

6.1.8.11 b_file_integrity_present

This Boolean indicates whether the `file_integrity()` structure is present in the bitstream. The `file_integrity()` structure is just an instance of the `fb_integrity()` structure that applies to the full file.

6.1.8.12 b_media_preso_dur_present

This Boolean indicates whether the `media_presentation_duration()` structure is present in the bitstream. An encoded bitstream may only represent a segment of the overall source content, and the `media_presentation_duration()` structure indicates the duration of the entire presentation of the source content. This structure is an instance of the `cmmf_time()` structure. While this duration is optional, it, along with other fields in this subatom, is useful to a decoder to determine if the bitstream can be decoded with bitstreams received from other encoders.

6.1.9 media_segment_info()

6.1.9.0 Introduction

The media segment information (`media_segment_info()`) structure provides information about the underlying CMMF encoded media. This optional structure enables a system to inspect the underlying CMMF coded media without requiring a decode operation in settings that do not support access to a centralized service entity, manifest files, etc. e.g. information centric networks, peer-to-peer systems, distributed file systems, etc. The media information may be populated from a DASH or HLS manifest file as an example. The `media_segment_info()` subatom is useful when content is stored or cached across multiple endpoints (e.g. a CMMF bitstream containing only `packet()` subatoms is cached in one location while another CMMF bitstream containing other subatoms is cached in another location). In these cases, it may be useful to have information about the underlying essence attached to both bitstreams from both a network management and a delivery standpoint. As a more concrete example, assuming the encoding of an HLS asset. The HLS manifest is encoded within one CMMF bitstream while each segment of that stream is encoded into their own CMMF bitstreams. A management layer can be implemented that links the HLS manifest CMMF bitstream with all of the segment bitstreams. Alternatively, the `media_segment_info()` subatom can be used to perform this linking, which also adds the benefit of not having to duplicate the HLS manifest. This subatom complements the higher-level manifest and allows for processes within the network to manage how the overall asset is distributed within that network.

A media segment information subatom describes a single type of media (e.g. audio or video). If the media is multiplexed and contains multiple types of media, or if different blocks contain different types of media, then multiple instances of the media segment information subatom may be used.

6.1.9.1 media_segment_block_index, media_segment_block_index_ext

The `media_segment_block_index` field, which is extendable by the `media_segments_index_ext` field, describes which block this `media_segment_info()` instance is associated with.

6.1.9.2 media_segment_index, media_segment_index_ext

The `media_segment_index` field, which is extendable by the `media_segment_index_ext` field, identifies the media index of the instance of the `media_segment_info()` structure. The index is 0-based and shall have a value 0 except in cases where the media is multiplexed where each multiplexed stream shall have a unique `media_segment_index` value.

6.1.9.3 b_composite_source_index _present

This Boolean indicates whether `media_segment_composite_source_index` is present in the bitstream.

6.1.9.4 media_segment_composite_source_index

When the block associated with the relevant media segment (as indicated by the `media_segment_block_index` field) is a composite of different data sources, the `media_segment_composite_index` identifies which data source in that block the media segment applies to.

6.1.9.5 b_asset_name_present

This Boolean indicates whether an asset name is present in the bitstream.

6.1.9.6 asset_name_size, asset_name

The `asset_name` is the name of the media asset of size indicated by the `asset_name_size` field (in bytes). This field is free-form and can be any ASCII [7] or UTF-8 [11] string of characters. The `asset_name_size` field shall not have a value of `0`.

6.1.9.7 segment_tag_mask

The `segment_tag_mask` field is a bit mask that describes which subsequent fields are present in the bitstream as listed in Table 53.

Table 53: segment_tag_mask meaning

`segment_tag_mask` bit	Meaning
0	Segment duration present: This bit indicates whether the duration of the encoded media segment, as described by the `segment_duration()` structure, is present in the bitstream. This structure is an instance of the `cmmf_time()` structure. The duration is optional, and can be used to replicate the corresponding information from a manifest.
1	Segment start time present: This bit indicates whether the start time of the encoded media segment, as described by the `segment_start_time()` structure, is present in the bitstream. This structure is an instance of the `cmmf_time()` structure. The start time is optional, and can be used to replicate the corresponding information from a manifest.
2	Segment index present: This bit indicates whether the `segment_index` field is present in the bitstream.
3	Segment count present: This bit indicates whether the `segment_count` field is present in the bitstream.

6.1.9.8 segidx_bits, segcnt_bits

The operational variables `segidx_bits` and `segcnt_bits` are represented by the `num_bits_code()` structure.

6.1.9.9 segment_index

The `segment_index` field identifies which segment of the media is contained within the encoded data.

6.1.9.10 segment_count

The `segment_count` field describes how many segments of this media exist.

6.1.9.11 b_media_mime_type_present

This Boolean indicates whether information about the MIME type of the media is provided in the bitstream. In this case, the `media_mime_type` and `media_mime_type_size` fields are present in the bitstream.

6.1.9.12 media_mime_type_size, media_mime_type

`media_mime_type` is a string of ASCII [7] characters that describes the content using a discrete media type value as defined in section 4 of IETF RFC 2046 [23] and/or IETF RFC 4337 [22]. Up to the first 63 bytes of the media type can be indicated. The size (in bytes) of the `media_mime_type` field is indicated by the `media_mime_type_size` field. The `media_mime_type_size` field shall not have a value of `0`.

6.1.9.13 b_media_codec_present

This Boolean indicates whether information about the codec is provided in the bitstream. In this case, the `media_codec` and `media_codec_size` fields are present in the bitstream.

6.1.9.14 media_codec_size, media_codec

`media_codec` is a string of ASCII [7] or UTF-8 [11] characters conforming to either the simp-list or fancy-list productions of IETF RFC 6381 [5], section 3.2, without the enclosing DQUOTE characters. Up to the first 63 bytes of a single codec identifier for the media format, mapped into the name space for codecs as specified in IETF RFC 6381 [5], section 3.3, shall be used. The size (in bytes) of the `media_codec` field is indicated by the `media_codec_size` field. The `media_codec_size` field shall not have a value of `0`.

6.1.9.15 b_bit_rate_present

This Boolean indicates whether the `bit_rate` field is present in the bitstream.

6.1.9.16 bit_rate_bits_code

The `bit_rate_bits_code` field describes how many bits are used to describe the bit rate of the media segment.

Table 54: bit_rate_bits_code meaning

`bit_rate_bits_code` Value	Meaning
`0b`	24 bits
`1b`	32 bits

The operational variable `bps_bits` is used to specify the number of bits used to represent the bit rate and is calculated using the `bit_rate_bits_code` as follows:

```
bps_bits = (bit_rate_bits_code + 3) × 8
```

6.1.9.17 bit_rate

The `bit_rate` field describes the bit rate of the media segment and has units of bits per second.

6.1.9.18 b_ms_content_type_present

This Boolean indicates whether the `ms_content_type` field is present in the bitstream.

6.1.9.19 ms_content_type

The `ms_content_type` field describes the type of content contained within the media segment. The field is described in Table 55.

Table 55: ms_content_type description

`ms_content_type` value	Description
`0x0`	Video
`0x1`	Audio
`0x2`	Multiplexed media of different content types
`0x3`	Application data
`0x4`	Text
`0x5-0x7`	Reserved

6.1.9.20 b_ms_content_type_info_present

This Boolean indicates whether additional information based on the value of the `ms_content_type` field is present in the bitstream. It shall not be set unless `b_ms_content_type_present` is set.

6.1.9.21 b_aspect_ratio_present

This Boolean indicates whether information about the picture aspect ratio is provided in the bitstream. In this case, the `sample_aspect_ratio` and potentially the `sar_width` and `sar_height` fields are present in the bitstream.

6.1.9.22 sample_aspect_ratio

The picture aspect ratio describes the ratio of the width dimension to the height dimension of the video. The `sample_aspect_ratio` field has the same meaning as the SampleAspectRatio field as described in ISO/IEC 23091-2 [10].

6.1.9.23 sar_width, sar_height

The picture aspect ratio describes the ratio of the width dimension to the height dimension of the video. When the `sample_aspect_ratio` has a value of `255`, then the `sar_width` and `sar_height` fields are present in the bitstream and indicate the horizontal and vertical dimensions, respectively, of the sample aspect ratio of the media segment.

6.1.9.24 b_dynamic_resolution_video

This Boolean indicates whether the resolution of the video varies throughout the program. In this case, and if `b_resolution_present` is set, the `resolution_width` and `resolution_height` fields indicate the maximum resolution of the program.

6.1.9.25 b_resolution_present

This Boolean indicates whether the resolution of the video is provided in the bitstream. In this case, the `resolution_width` and `resolution_height` fields are present in the bitstream.

6.1.9.26 resolution_width, resolution_height

The `resolution_width` and `resolution_height` fields describe the horizontal pixel count and vertical line count, respectively, of the related video media segment.

6.1.9.27 b_frame_rate_present

This Boolean indicates whether the video frame rate is provided in the bitstream. In this case, the `frame_rate` field and a `reserved` field are present in the bitstream.

6.1.9.28 frame_rate

The `frame_rate` field describes how many frames per second (fps) appear in the associated video. The meaning of this field is specified in Table 56. In the case of interlaced video, the frame rate is 1/2 the field rate. Fractional frame rates expressed as decimal fractions, such as 23,976 fps or 59,94 fps, are approximations of the exact frame rate. The exact frame rate is calculated by applying a factor of 1 000 / 1 001 to the nearest adjacent integer frame rate (e.g. 23,976 fps represents 24 fps × 1 000 / 1 001).

Table 56: frame_rate values

frame_rate value	Frame rate (fps)
0	23,976
1	24
2	25
3	29,97
4	30
5	47,95
6	48
7	50
8	59,94
9	60
10	100
11	119,88
12	120
13 - 31	Reserved

6.1.9.29 b_hdr_info_present

This Boolean indicates whether High Dynamic Range (HDR) video information follows in the bitstream. Otherwise, the video should not be considered HDR.

6.1.9.30 hdr_compatibility_mask

The `hdr_compatibility_mask` field is a bit mask where each bit indicates that the video is compatible with a specific HDR format. The meaning of this field is specified in Table 57.

Table 57: hdr_compatibility_mask values

`hdr_compatibility_mask` Bit	Meaning (compatible with)
0	HDR10
1	HLG™
2	SMPTE 2094-10
3	SMPTE 2094-20
4	SMPTE 2094-30
5	SMPTE 2094-40
6	Reserved
7	Reserved
8	Dolby Vision™
9	HDR10+™
10	SL-HDR1™
11	SL-HDR2™
12	SL-HDR3™
13	Reserved
14	Reserved
15	Reserved

6.1.9.31 b_addl_hdr_info_present

This Boolean indicates whether additional High Dynamic Range (HDR) video information follows in the bitstream as indicated by the `hdr_compat_mask_index`, `hdr_profile`, `hdr_level`, and `hdr_compatibility_id` fields.

6.1.9.32 hdr_compat_mask_index

The `hdr_compat_mask_index` field is an index into `hdr_compatibility_mask` field to identify which HDR format the subsequent `hdr_profile`, `hdr_level`, and `hdr_compatibility_id` fields correspond to.

For example, if `hdr_compat_mask_index` has a value of `8`, then the subsequent fields relate to Dolby Vision™.

6.1.9.33 hdr_profile

The `hdr_profile` field specifies the profile of the HDR video.

6.1.9.34 hdr_level

The `hdr_level` field specifies the level of the HDR video.

6.1.9.35 hdr_compatibility_id

The `hdr_compatibility_id` field specifies a particular form of a base layer substream.

6.1.9.36 b_addl_video_info_present

This Boolean indicates whether the `addl_video_info()` structure is present in the bitstream. The `addl_video_info()` structure provides a mechanism to extend the video content type with additional information and is an instance of the `extension()` structure.

6.1.9.37 b_sampling_freq_present

This Boolean indicates whether the audio sampling frequency is provided in the bitstream. In this case, the `b_sampling_freq_is_48k` field is present in the bitstream.

6.1.9.38 b_sampling_freq_is_48k

This Boolean indicates whether the audio in this media segment has an audio sampling frequency of 48 000 Hz. Otherwise, the `sampling_frequency` field is present in the bitstream, providing the sampling frequency of the audio.

6.1.9.39 sampling_frequency

The `sampling_frequency` field describes the sampling rate of the audio in the media segment. The value of this field is specified in Table 58.

Table 58: sampling_frequency values

`sampling_frequency` value	Sampling frequency (kHz)
0	6
1	8
2	12
3	24
4	48
5	96
6	192
7	22,05
8	44,1
9	88,2
10	176,4
11 - 15	Reserved

6.1.9.40 b_audio_config_present

This Boolean indicates whether the audio channel configuration is described in the bitstream. In this case, the `audio_channel_config` field is present in the bitstream.

6.1.9.41 audio_channel_config

The `audio_channel_config` field defines the audio channel configuration of the media segment. The field is a bit mask of speaker groups present in the channel configuration.

The value of this field is specified in Table 59.

Table 59: audio_channel_config values

`audio_channel_config` Bit	Speaker group location(s)
0	Left (L)
	Right (R)
1	Centre (C)
2	Left surround (Ls)
	Right surround (Rs)
3	Left back (Lb)
	Right back (Rb)
4	Top front left (Tfl)
	Top front right (Tfr)
5	Top back left (Tbl)
	Top back right (Tbr)
6	Low-Frequency Effects (LFE)
7	Top Left (Tl)
	Top Right (Tr)
8	Top side left (Tsl)
	Top side right (Tsr)
9	Top front centre (Tfc)
10	Top back centre (Tbc)
11	Top centre (Tc)
12	Low-frequency effects 2 (LFE2)

audio_channel_config Bit	Speaker group location(s)
13	Bottom front left (Bfl)
	Bottom front right (Bfr)
14	Bottom front centre (Bfc)
15	Back centre (Bc)
16	Left screen (Lscr)
	Right screen (Rscr)
17	Left wide (Lw)
	Right wide (Rw)
18	Vertical height left (Vhl)
	Vertical height right (Vhr)
19	Reserved
20	Reserved
21	Reserved
22	Reserved
23	Reserved

All references to ITU channel names for each speaker group are with regard to Recommendation ITU-R BS.2051-3 [20].

Bit 23 indicates whether the audio presentation is object based and thus channel presence does not apply. In this case, bits 22...0 are reserved. Otherwise, bits 18...0 indicate the presence of individual channel groups in the audio presentation that together form the corresponding channel configuration. In this case bits 18...0 shall indicate the presence of channel groups in the original content.

For example, if the audio channel configuration contains the L and R channels, then Bit `0` is set to `1`. As another example, for a stream with a 5.1.2 channel configuration of L, C, R, Ls, Rs, LFE, Tsl, Tsr, the `audio_channel_config` value is `0x00 0147` (the hexadecimal equivalent of the binary value `0000 0000 0000 0001 0100 0111`).

6.1.9.42 b_audio_props_present

This Boolean indicates whether additional fields describing other audio properties are provided in the bitstream. In this case, the `b_virtualized_bin`, `b_object_audio` and `b_complexity_index_present` fields, as well as two `reserved` fields, are present in the bitstream.

6.1.9.43 b_virtualized_bin

This Boolean indicates whether the audio contains a binaural virtualized experienced. In this case, and if `b_audio_config_present` is set, then the `audio_channel_config` field shall have a value of `0x00 0001` indicating that only the L and R channels are present.

6.1.9.44 b_object_audio

This Boolean indicates whether the media segment contains an object-based audio presentation. Otherwise, the audio presentation is channel based.

6.1.9.45 b_complexity_index_present

This Boolean indicates whether the complexity index information is provided in the bitstream. In this case, the `complexity_index` field is present in the bitstream.

6.1.9.46 complexity_index

The `complexity_index` field specifies the number of channels and/or objects of the audio.

6.1.9.47 b_addl_audio_info_present

This Boolean indicates whether the `addl_audio_info()` structure is present in the bitstream. The `addl_audio_info()` structure provides a mechanism to extend the audio content type with additional information and is an instance of the `extension()` structure.

6.1.9.48 b_addl_ms_content_type_info_present

This Boolean indicates whether the `addl_ms_content_type_info()` structure is present in the bitstream. The `addl_ms_content_type_info()` structure provides a placeholder to define additional information for other `ms_content_type` values. This structure is an instance of the `extension()` structure.

6.1.9.49 accessibility_mask

The `accessibility_mask` field is a bit mask that describes which subsequent accessibility-related fields are present in the bitstream as listed in Table 60.

Table 60: accessibility_mask meaning

`accessibility_mask` bit	Meaning
0	Language present: If this bit is set, the language of the media segment is present in the bitstream.
1	Reserved present: If this bit is set, then a `reserved` field is present in the bitstream.
2	Reserved present: If this bit is set, then a `reserved` field is present in the bitstream.
3	Additional accessibility information present: If this bit is set, the `addl_accessibility_info()` structure is present in the bitstream. This structure is an instance of the `extension()` structure.

6.1.9.50 language_size, language

The `language` field contains a language tag that conforms to the syntax and semantics defined in IETF RFC 4646 [6]. The size (in bytes) of the field is indicated by the `language_size` field. The minimum sequence length shall be two bytes, supporting a two-character language tag as specified in ISO 639 [4]. The maximum supported length of the language tag shall be 42 bytes.

6.1.10 cmmf_time()

6.1.10.0 Introduction

The `cmmf_time()` structure represents temporal information, with a range of 31 days, 23 hours, 59 minutes, and 59,999 seconds, and a granularity of one microsecond (1 second / 1 000), one nanosecond (1 second / 1 000 000), or one picosecond (1 second / 1 000 000 000). Multiple instances of this syntax are present in the CMMF bitstream, e.g. `media_presentation_duration` and `start_time` fields.

6.1.10.1 b_ddhhmmss

This Boolean indicates whether the subsequent temporal information is presented in a days, hours, minutes, and seconds (DD:HH:MM:SS) format, and the `b_dd_present`, `b_hh_present`, `b_mm_present`, and `b_ss_present` fields are present in the bitstream. Otherwise, the temporal information is presented in seconds, and the `int_seconds_bits_code` and `int_seconds` fields are present in the bitstream.

6.1.10.2 DD:HH:MM:SS format

If the b_ddhhmmss field is set, the temporal information is indicated by the days, hours, minutes, and seconds fields. Each of these fields has an associated presence flag indicating whether the field is present in the bitstream. A field that is not present in the bitstream has a value of 0.

Table 61: DD:HH:MM:SS format fields and meaning

Presence flag	Associated field	Allowable range
b_dd_present	days	[0, 31]
b_hh_present	hours	[0, 23]
b_mm_present	minutes	[0, 59]
b_ss_present	seconds	[0, 59]

6.1.10.3 int_seconds_bits_code

The int_seconds_bits_code field describes the number of bits used to encode the int_seconds field. The meaning of this field is specified in Table 62.

Table 62: int_seconds_bits_code meaning

int_seconds_bits_code value	Meaning
00b	The value of int_seconds_bits_code is 8 bits.
01b	The value of int_seconds_bits_code is 16 bits.
10b	The value of int_seconds_bits_code is 24 bits.
11b	Reserved.

The operational variable is_bits can be calculated directly from the int_seconds_bits_code field according to the following equation:

$$is_bits = (int_seconds_bits_code + 1) \times 8$$

6.1.10.4 int_seconds

If the b_ddhhmmss field is cleared, the temporal information is indicated by the int_seconds field, describing the number of integer seconds. This field has a range of [0, 2 764 799] (up to 31 days, 23 hours, 59 minutes, 59 seconds).

6.1.10.5 b_fract_seconds_present

This Boolean indicates whether the fract_seconds field is present in the bitstream.

6.1.10.6 fract_seconds_bits_code

The fract_seconds_bits_code field describes the number of bits used to encode the fract_seconds field. The meaning of this field is specified in Table 63.

Table 63: fract_seconds_bits_code meaning

fract_seconds_bits_code value	Meaning
00b	The value of fract_seconds_bits_code is 10 bits.
01b	The value of fract_seconds_bits_code is 20 bits.
10b	The value of fract_seconds_bits_code is 40 bits.
11b	Reserved.

The operational variable s_bits can be calculated directly from the fract_seconds_bits_code field according to the following equation:

$$fs_bits = 10 \times 2^{fract_seconds_bits_code}$$

6.1.10.7 fract_seconds

The `fract_seconds` field describes the number of fractional seconds added to the integer seconds described above. The field has a range depending on the value of `fs_bits`, as shown in Table 64.

Table 64: fract_seconds range and divisor

`fs_bits` value	`fract_seconds` range	`fract_seconds` divisor
10 bits	[0, 999]	1 000
20 bits	[0, 999 999]	1 000 000
40 bits	[0, 999 999 999 999]	1 000 000 000 000

The number of fractional seconds is then calculated by dividing the `fract_seconds` value in the bitstream by the indicated divisor value as shown in the following equation:

fractional seconds = `fract_seconds / ` divisor

6.1.11 chunked_subatom()

6.1.11.0 Introduction

The `chunked_subatom()` structure contains a 'chunk' of subatom data. It provides a mechanism to partition large subatom data into multiple smaller chunk segments. For example if the coded symbol size in a packet subatom is very large for the transmission protocol in use, the subatom `packet()` data can be split into smaller chunk segments that fit the transmission requirements.

A `chunked_subatom()` cannot itself be chunked. When subatom data is chunked, it shall be split into more than one `chunked_subatom()` instances.

6.1.11.1 chunk_segment_id

The `chunk_segment_id` field identifies a series of `chunked_subatom()` instances as containing different portions of the same subatom data. When subatom data is chunked, all `chunked_subatom()` instances of that data shall have the same value in the `chunk_segment_id` field.

6.1.11.2 chunk_segment_index

The `chunk_segment_index` field identifies the index of the chunk segment of subatom data contained within the `chunked_subatom()`. A parser can use this information to reassemble the chunked subatom data to its original order.

If a chunk segment is lost in transmission, and a complete set of chunk segments is not received, it is up to the decoder implementation to determine how to recover. For instance, the decoder may introduce a timer, if all the chunk segments are not received within the appropriate time range, then that entire series of `chunked_subatom()` instances (i.e. all instances with the same `chunk_segment_id`), may be discarded.

6.1.11.3 num_chunk_segments

The `num_chunk_segments` field describes the number of chunk segments that the subatom data (associated with the indicated `chunk_segment_id`) has been split into. The value of this field shall be greater than 1.

6.1.11.4 original_subatom_id, original_subatom_id_ext

The `original_subatom_id` field, which is extendable by the `original_subatom_id_ext` field, specifies the `subatom_id` of the segment data contained within the `chunked_subatom()`.

6.1.11.5 oss_bits

The operational variable `oss_bits` is used in the syntax to specify the number of bits used to encode the original subatom data size and is represented by the `num_bits_code()` structure.

6.1.11.6 original_subatom_size

The `original_subatom_size` field describes the size of the original subatom data prior to being chunked, in bytes.

6.1.11.7 byte_align

This bit field of size 0 to 7 bits is used for the byte alignment of the associated `chunked_subatom()` structure. Byte alignment is defined relative to the start of the enclosing syntactic element.

6.1.11.8 chunked_subatom_segment_data

The `chunked_subatom_segment_data` field contains a chunk segment of the chunked subatom data.

The operational variable `cssd_bits` is used in the syntax to specify the number of bits used to encode `chunked_subatom_segment_data` and is based on several fields according to the following semantic equation:

```
cssd_bits = (subatom_size × 8) - sizeof(chunk_segment_id, chunk_segment_index,
num_chunk_segments, original_subatom_id, original_subatom_id_ext, num_bits_code(),
                        original_subatom_size, byte_align)
```

In the equation above, `subatom_size` is the size indicated in the subatom header for this instance of the `chunked_subatom()`. The `sizeof` function determines the number of bits used by the fields prior to the `chunked_subatom_segment_data`.

6.1.12 block_group_directory()

6.1.12.0 Introduction

The block group directory (`block_group_directory()`) contains fields to indicate the start of block header subatom (i.e. subatoms with the `block_header()` structure) or packet group subatom (i.e. subatoms with the `packet_group()` structure) instances in the bitstream. The block group directory subatom shall not contain any additional padding after the `block_group_directory()` structure.

6.1.12.1 block_group_dir_mask

The `block_group_dir_mask` field is an array of Booleans that describes which subsequent fields are present in the bitstream as listed in Table 65.

Table 65: block_group_dir_mask meaning

`block_group_dir_mask` bit	Meaning
0	Block header directory symbols present: This Boolean indicates whether fields that specify the offset to the block header subatoms are present in the bitstream.
1	Packet group directory: This Boolean indicates whether fields that specify the offset to the packet group subatoms are present in the bitstream.
2	Packet group headers present: This Boolean indicates whether instances of the `packet_group()` structure, one for each of the packet group subatoms, are present and follow in the bitstream. These `packet_group()` instances shall have a `packet_group_type` value of `01b` indicating that only the packet group header is present, no coded symbols. This bit shall only be set if and only if bit 1 is set.
3	Multiple block packet group directory present: This Boolean indicates whether fields that specify the offset to the multiple block packet group subatoms are present in the bitstream.
4-7	Reserved.

6.1.12.2 block_header_subatom_offset[block]

The `block_header_subatom_offset[block]` field describes the offset, in bytes, until the block header subatom with a `block_index` value of `block`. The offset is relative to the '*directory_end*' label.

6.1.12.3 num_packet_groups[block]

The `num_packet_groups[block]` field describes the number of packet group subatom instances present for `block'th` block.

6.1.12.4 packet_group_index[block][pg]

The `packet_group_index[block][pg]` field identifies the `pg'th` instance of the `packet_group()`associated with the `block'th` block.

This field is only present if bit 2 of the `block_group_dir_mask` field is `0`. Otherwise this field is present as part of the `packet_group()` structures in the block group directory.

6.1.12.5 packet_group_subatom_offset[block][pg]

The `packet_group_subatom_offset[block]` field describes the offset, in bytes, until the `pg'th` packet group subatom with a `packet_group_block_index` value of `block`. This field shall only describe the offset to packet group subatoms that have a `packet_group_type` value of `00b` or `10b`, i.e. the `coded_symbol` fields are present. The offset is relative to the '*directory_end*' label.

6.1.12.6 num_multi_block_packet_groups

The `num_multi_block_packet_groups` field describes the number of multiple block packet group subatom instances present.

6.1.12.7 multi_block_packet_group_subatom_offset[mbpg]

The `multi_block_packet_group_subatom_offset[mbpg]` field describes the offset, in bytes, until the instance of the multiple block packet group subatom with a `mpbg__index` value of `mbpg`. The offset is relative to the '*directory_end*' label.

6.1.13 fb_integrity()

6.1.13.0 Introduction

The `fb_integrity()` contains fields to verify the integrity of the received and decoded full file or block.

The `fb_integrity()` element provides a mechanism to verify the integrity of the decoded data in the full file or a given block. This element is referenced by other structures in the syntax When referenced in the `encoder_content_info()` this structure relates to the file. When referenced in the `block_header()` this structure relates to the indicated `block_index`.

6.1.13.1 fb_hash_type

The `fb_hash_type` field describes how the hash on the data is calculated. The meaning of this field is specified in Table 66.

Table 66: fb_hash_type meaning

`fb_hash_type` value	Meaning
`00b`	The hash is calculated on the full file or block data.
`01b`	The hash is a Merkel root hash of the original symbols.
`10b-11b`	Reserved.

6.1.13.2 fb_hash_algorithm

The `fb_hash_algorithm` field describes the algorithm used to calculate the hash of the data. The meaning of this field is specified in Table 67.

Table 67: fb_hash_algorithm meaning

`fb_hash_algorithm` value	Meaning
`000b`	The hash is calculated using the SHA-1 [9] algorithm.
`001b`	The hash is a CRC of the data, modulo the polynomial $x^8 + x^6 + x^5 + x + 1$ where the relevant shift register is initialized to `0xA2` before the computation.
`010b`	The hash is calculated using the MD5 [21] Message-Digest algorithm.
`010b-111b`	Reserved.

6.1.13.3 fb_hash_size

The `fb_hash_size` field describes the number of bits of the hash digest. The meaning of this field is specified in Table 68.

Table 68: fb_hash_size meaning

`fb_hash_size` value	Meaning
`0000b`	The hash digest size is 8 bits.
`0001b`	The hash digest size is 32 bits.
`0010b`	The hash digest size is 64 bits.
`0011b`	The hash digest size is 128 bits.
`0100b`	The hash digest size is 160 bits.
`0101b`	The hash digest size is 256 bits.
`0110b`	The hash digest size is 512 bits.
`0111b`	The hash digest size is 1 024 bits.
`1000b`	The hash digest size is 2 048 bits.
`1001b-1111b`	Reserved.

If the reserved values of `fb_hash_size` (`1001b-1111b`) is received, it is considered an error.

Depending on the value of `fb_hash_algorithm`, `fb_hash_size` is constrained as indicated in Table 69.

Table 69: Allowed fb_hash_size values based on fb_hash_algorithm

`fb_hash_algorithm` value: algorithm	Allowed `fb_hash_size` value: bits
`000b`: SHA-1	`0100b`: 160 bits
`001b`: CRC	`0000b`: 8 bits
`010b`: MD5	`0011b`: 128 bits

The operational variable `fb_hash_bits` is the number of bits indicated by the `fb_hash_size` field. For example, if the `fb_hash_size` field is `0111b`, then `fb_hash_bits = 1 024`.

6.1.13.4 b_fb_integrity_ext

This Boolean indicates whether the `fb_integrity_ext()` structure is present in the bitstream. The `fb_integrity_ext()` structure provides a mechanism to extend the file or block integrity check with additional information and is an instance of the extension() structure.

6.1.13.5 fb_hash

The `fb_hash` field is the hash calculated on the relevant data. Its size (in bits) is determined by the `fb_hash_bits` operational variable. A decoder can use this value to compare against its own calculated hash to ensure that the data was received without error.

6.1.14 packet_integrity()

6.1.14.0 Introduction

The `packet_integrity()` element provides a mechanism to verify the integrity of the data (i.e. coded symbols) in a packet, packet group, or multiple block packet group.

6.1.14.1 packet_hash_algorithm

The `packet_hash_algorithm` field describes the algorithm used to calculate the hash of the data. The meaning of this field is specified in Table 70.

Table 70: packet_hash_algorithm meaning

`packet_hash_algorithm` value	Meaning
`000b`	Reserved
`001b`	The hash is a CRC of the data, modulo the polynomial $x^8 + x^4 + x^3 + x2 + 1$ where the relevant shift register is initialized to zero before the computation.
`010b`	The hash is calculated using the MD5 [21] Message-Digest algorithm.
`010b-111b`	Reserved.

6.1.14.2 packet_hash_size

The `packet_hash_size` field describes the number of bits of the hash digest. The meaning of this field is specified in Table 71.

Table 71: packet_hash_size meaning

`packet_hash_size` value	Meaning
`000b`	The hash digest size is 8 bits.
`001b`	The hash digest size is 32 bits.
`010b`	The hash digest size is 64 bits.
`011b`	The hash digest size is 128 bits.
`100b`	The hash digest size is 256 bits.
`101b`	The hash digest size is 512 bits.
`110b`	The hash digest size is 1 024 bits.
`111b`	The hash digest size is 2 048 bits.

Depending on the value of `packet_hash_algorithm`, `packet_hash_size` is constrained as indicated in Table 72.

Table 72: Allowed packet_hash_size values based on packet_hash_algorithm

`packet_hash_algorithm` value: algorithm	Allowed `packet_hash_size` value: bits
`001b`: CRC	`000b`: 8 bits
`010b`: MD5	`011b`: 128 bits

The operational variable `pkt_hash_bits` is the number of bits indicated by the `packet_hash_size` field. For example, if the `packet_hash_size` field is `110b`, then `pkt_hash_bits = 1 024`.

6.1.14.3 b_packet_integrity_ext

This Boolean indicates whether the `packet_integrity_ext()` structure is present in the bitstream. The `packet_integrity_ext()` structure provides a mechanism to extend the packet integrity check with additional information and is an instance of the `extension()` structure.

6.1.14.4 packet_hash

The `packet_hash` field is the hash calculated on the coded symbol data. The size (in bits) of this field is indicated by the `packet_hash_size` field. A decoder can use this value to compare against its own calculated hash to ensure that the data was received without issue.

The hash is calculated on the `coded_symbol` field(s) contained within the packet, packet group, or multiple block packet group subatoms as indicated by the `/* start hash */` and `/* end hash */` labels.

6.1.15 coefficient_vector()

6.1.15.0 Introduction

The `coefficient_vector()` contains the explicit coding coefficients used to encode the original data symbols for the coded symbol contained within the packet. The element contains a `window_size` worth of coefficients, with each coefficient requiring `block_field_size_exp_val` number of bits.

If the coding coefficient information is encrypted (i.e. bit `3` of the `block_mask` field is set), then this field is symmetrically encrypted using the `block_cce_key` and associated parameters.

6.1.15.1 coded_symbol_coeff[index]

The `coded_symbol_coeff[index]` field is the coefficient for the index*th* original symbol used to encode the coded symbol in the packet. This field requires `block_field_size_exp_val` number of bits.

For more information on `block_field_size_exp`, see clause 6.1.5.23.

6.1.16 extension()

6.1.16.0 Introduction

The `extension()` element defines a mechanism to extend other structures in the bitstream. Multiple instances of this element are referenced in the bitstream and appear in place of substructures not yet defined.

6.1.16.1 extension_byte_size

The `extension_byte_size` field describes the number of subsequent bytes that follow as part of the `extension()` structure. These bytes should be skipped by a parser conforming to the version of the syntax in the present document.

6.1.17 packet_header_only()

The `packet_header_only()` structure contains only packet headers.

Packets, as well as other fields contained within larger structures, inherit values from previous `subatom()` instances. For example, the `packet()` structure inherits the value of the `block_field_size_exp` field specified in the associated field `block_header()`, that is, the `block_header()` with the `block_index` value that matches the `packet_block_index` value.

The `packet_header_only()` structure that is part of the packet header only subatom carries the coding coefficient information describing how the coded symbols were encoded. However, it does not contain the actual `coded_symbol` field. The `packet_header()` will be different depending on whether it is encapsulated in a packet subatom, or in a packet header only subatom.

For more information on `packet_header()`, see clause 6.1.7.

6.1.18 packet_group()

6.1.18.0 Introduction

The packet group (`packet_group()`) structure can contain a `packet_group_header()` as well as coded symbols. The structure is similar to a `packet()` structure. However, unlike the `packet()` structure which contains only single coded symbol, a `packet_group()`can have multiple coded symbols from the same block (i.e. a single block symbol group).

Packet groups, as well as other fields contained within larger structures, inherit values from previous `subatom()` instances. For example, the `packet_group()` structure inherits the value of the `block_field_size_exp` field specified in the associated `block_header()`, that is, the `block_header()` with the `block_index` value that matches the `packet_group_block_index` value.

6.1.18.1 packet_group_block_index

The `packet_group_block_index`, which is extendable by the `packet_group_block_index_ext` field, describes which block this `packet_group()` instance is associated with. If the bitstream only contains a single block (i.e. `block_count` is `1`), then this field is not present in the bitstream and takes on a value of `0`.

As an example, if the `packet_group_block_index` is `1`, then the associated block and its related `block_header()` instance has a `block_index` of `1` as well.

6.1.18.2 packet_group_index

The `packet_group_index` identifies the instance of the `packet_group()`.

6.1.18.3 pgns_bits

The operational variable `pgns_bits` is used in the syntax to specify the number of bits used to encode the `packet_group_num_symbols` field and is represented by the `num_bits_code()` structure.

6.1.18.4 packet_group_num_symbols

The `packet_group_num_symbols` field describes the number of coded symbols present within the packet group.

6.1.18.5 packet_group_type

The `packet_group_type` field describes the type of packet group instance and whether the packet group header and coded symbols are present. The meaning of this field is specified in Table 73.

Table 73: packet_group_type meaning

`packet_group_type` value	Meaning
`00b`	Standard packet group with both `packet_group_header()` and `coded_symbol` fields present.
`01b`	Only `packet_group_header()` present. `coded_symbol` fields are not present.
`10b`	Only `coded_symbol` fields present. `packet_group_header()` not present.
`11b`	Reserved.

6.1.18.6 coded_symbol

A `coded_symbol` is either a systematic symbol or the encoded version of a number of source symbols, generated by applying coding to the original data symbols. The size of this field is indicated by the `block_symbol_size` field in the associated `block_header()` instance. The `block_symbol_size` field shall not use the value `0` when packet group subatoms are present in the bitstream.

6.1.19 packet_group_header()

6.1.19.0 Introduction

The `packet_group_header()` structure provides information about how the coded symbols contained in the `packet_group()` are arranged and encoded.

Because a packet group contains multiple coded symbols, there are less options for how the group of coded symbols can be encoded compared to if each coded symbol had been individually contained within a packet subatom. Within a packet group, the coded symbols can be identified with either a symbol/row index, or a coefficient vector. Sliding windows are not supported within a packet group.

6.1.19.1 packet_group_symbol_arrangement

The `packet_group_symbol_arrangement` field describes the order that coded symbols (including systematic symbols) appear within the packet group subatom. The meaning of this field is specified in Table 74.

Table 74: packet_group_symbol_arrangement Meaning

`packet_group_symbol_arrangement` Value	Symbol Arrangement
`0000b`	Not indicated, the arrangement of coded symbols is not described by a pattern and each symbol is identified by the `packet_symbol_index` field, or by a coefficient vector.
`0001b`	Arbitrary, coded symbols are identified explicitly by the `packet_symbol_index` field.
`0010b`	Arithmetic sequence, symbols are arranged with a constant difference between symbol indexes (e.g. if the first coded symbol in the packet group contains symbol 11, the next coded symbol is 21, then the third coded symbol has symbol index 31 etc.). The sequence is determined using the `packet_group_index_difference` and `packet_group_first_symbol_index` fields.
`0011-1111b`	Reserved.

6.1.19.2 packet_group_mask

The `packet_group_mask` field is an array of Booleans that describes which subsequent fields are present in the bitstream as listed in Table 75.

Table 75: packet_group_mask meaning

`packet_group_mask` bit	Meaning
0	Reserved: This Boolean indicates whether a 32-bit reserved field is present in the bitstream.
1	Symbol index present: This Boolean indicates that an array of symbol indexes (`packet_group_symbol_index`), one for each coded symbol in the packet group, is present in the bitstream. The symbol indexes are either encoding symbol indexes, or row indexes in the case that a block PRNG seed is used.
2	Additional coding coefficient encryption parameter(s) present: This Boolean indicates whether additional encryption parameters relevant to this packet group are present in the bitstream. This bit can only be set if bit 3 of `block_mask` is also set.
3	Coding vector present: This Boolean indicates whether an array of the `coefficient_vector()` structure is present in the bitstream. This array explicitly describes the coding coefficients that were used to generate the coded symbols in the packet group. Note that the `coefficient_vector()` uses `block_num_symbols` instead of `window_size` as an input since sliding windows are not allowed within a packet group.
4	Packet group integrity: This Boolean indicates whether the `packet_group_integrity()` structure, which is an instance of `packet_integrity()`, is present in the bitstream. This structure provides a mechanism to verify that the received data in the packet group matches that of the original source of the bitstream.
5	Packet header extension: This Boolean indicates whether the `packet_header_extension()` structure is present in the bitstream. The `packet_header_extension()` structure provides a mechanism to extend the packet header syntax with additional information and is an instance of the `extension()` structure.

Certain bits of the packet_group_mask are set or cleared depending on the values of other fields. Including:

- Bit 1 (symbol index) and bit 3 (coefficient vector) are mutually exclusive, and shall not both be set simultaneously.
- If bit 3 (coefficient vector) is set, then the value of packet_group_symbol_arrangement shall be 0000b, meaning the coded symbol arrangement is not indicated.
- If addl_block_coding_mask is present in the relevant block_header() instance, bit 1 of the addl_block_coding_mask (indicating that a sliding window is used) shall be cleared.
- If bit 2 of block_mask is set, indicating that the coding coefficients are separated and described in the packet group header only subatom, then:
  - The packet_group_index and packet_group_num_symbols values in the packet group subatom and the associated packet group header only subatom shall have the same value.
  - Bits 1, 2, 3, 4, and 5 of packet_group_mask in packet group subatom shall be cleared. That is, the only allowed packet_group_mask value is 00000Bb (see note). These bits may be set as needed in the associated packet group header only subatom packet_group_mask field.
- If bit 3 of block_mask is set, indicating that the coding coefficients are encrypted, then bit 2 of packet_group_mask (additional encryption parameters) shall only be set if and only if bit 3 of packet_group_mask (coding vector present) is set.
- If bit 4 of block_mask is set, indicating that a block PRNG seed is used, then bit 1 of packet_group_mask (symbol index present) shall be set, and the value of packet_group_symbol_arrangement shall be 0000b, meaning the coded symbol arrangement is not indicated.

NOTE: Bit values indicated as B mean that the value of this bit can be set, or not set depending on other settings in an encoder.

An example packet_group_mask can be 011000b, with bit 3 set indicating the array of coefficient_vector fields is present in the bitstream, and bit 4 set indicating the presence of the packet group integrity check.

6.1.19.3 pgsi_bits

The operational variable pgsi_bits is used in the syntax to specify the number of bits used to encode the packet_group_symbol_index fields and is represented by the num_bits_code() structure.

6.1.19.4 packet_group_symbol_index

For each coded symbol in the packet group, the packet_group_symbol_index field provides either an encoded symbol index value (for code types such as Reed-Solomon, or RaptorQ), or row index value in the case that a block PRNG seed is used.

6.1.19.5 pgfsi_bits

The operational variable pgfsi_bits is used in the syntax to specify the number of bits used to encode the packet_group_first_symbol_index fields and is represented by the num_bits_code() structure.

6.1.19.6 packet_group_first_symbol_index

The packet_group_first_symbol_index field describes the symbol index of the first coded symbol in the packet group. Subsequent symbol indexes are then calculated using this value and the value of the packet_group_index_difference field.

6.1.19.7 packet_group_index_difference

The packet_group_index_difference field describes the symbol index difference between successive coded symbols in a packet group. The value 0 shall not be used for this field.

For example, if the first coded symbol in a packet group has a symbol index value of 6, and the packet_group_index_difference field has a value of 3, then the second coded symbol has a symbol index of 9.

6.1.19.8 pgfsii_bits

The operational variable pgsii_bits is used in the syntax to specify the number of bits used by the packet_group_symbol_index_info structure which is an instance of the extension() structure. pgsii_bits is represented by the num_bits_code() structure.

6.1.19.9 Symbol Arrangements in a Packet Group

Within a packet group subatom, a group of coded symbols from the packet_group_block_index'th block are arranged as described by the packet_group_symbol_arrangement field.

When the coded symbol arrangement in a packet group is not indicated (the value of the packet_group_symbol_arrangement is 0000b) or is arbitrary (the value of the packet_group_symbol_arrangement is 0001b), and bit 1 of packet_group_mask (symbol index present) is set, then each coded symbol can be identified by an instance of the packet_group_symbol_index field present in the bitstream.

When the coded symbols in a packet group are arranged in an arithmetic sequence (the value of the packet_group_symbol_arrangement is 0010b), and bit 1 of packet_group_mask (symbol index present) is set, then the value of packet_group_symbol_index for the n'th coded symbol in the packet group is calculated using the packet_group_first_symbol_index and packet_group_index_difference fields according to the equation:

```
packet_group_symbol_index[n] = packet_group_first_symbol_index +
                (n x packet_group_index_difference)
```

Where n = 0,1,2,… and represents the nth coded symbol in the packet group.

If the value of the packet_group_symbol_arrangement is 0010b, a CMMF decoder shall determine the packet_group_symbol_index value for each coded symbol using the pseudocode in Table 76.

Table 76: Arithmetic coded symbol arrangement in a packet group pseudocode

Pseudocode

```
packet_group_arithmetic_arrangement(packet_group_num_symbols, packet_group_first_symbol_index,
   packet_group_index_difference)
{
   packet_group_symbol_index[packet_group_num_symbols] = {0};
   symbol_index = packet_group_first_symbol_index;
   for (n = 0; n < packet_group_num_symbols; n++) {
      packet_group_symbol_index[n] = symbol_index;
      symbol_index = symbol_index + packet_group_index_difference;
   }
   return;
}
```

6.1.19.10 Encryption Parameters

6.1.19.10.0 Introduction

When bit 2 of the packet_group_mask field is set, additional encryption parameters needed to decrypt the coding coefficient information within the packet_group_header() are present in the bitstream. The encrypted coding coefficient information within the packet_group_header() can be the instances of the coefficient_vector() in packet_group_header() within the packet group subatom or the packet group header only subatom

When the coding coefficient information is encrypted, keys and other encryption parameters are needed in order to decrypt the coefficient information and ultimately decode the coded symbols.

The following fields describe the additional packet group or packet group header only encryption parameters.

For more information on encrypting coding coefficient information, see clause 7.3.

6.1.19.10.1 b_addl_packet_group_cce_params_present

This Boolean indicates whether additional encryption parameters required to decrypt the coding coefficient information, contained in the `addl_cce_parameters()` structure, follow in the bitstream.

6.1.20 num_bits_code()

6.1.20.0 Introduction

The `num_bits_code()`is a helper tool used to describe the number of bits used by a field in the bitstream. This tool returns the `num_bits` variable value.

6.1.20.1 bits_code

The `bits_code` field describes the number of bits a subsequent field in the bitstream uses and returned by the `num_bits` variable. The meaning of this field is specified in Table 77.

Table 77: bits_code meaning

`bits_code` value	Meaning
`00b`	The value of `num_bits` is 8 bits.
`01b`	The value of `num_bits` is 16 bits.
`10b`	The value of `num_bits` is 24 bits.
`11b`	The value of `num_bits` is 32 bits.

The operational variable `num_bits` can be calculated directly from the `bits_code` field according to the following equation:

```
num_bits = (bits_code + 1) × 8
```

6.1.21 block_index_or_count_value()

6.1.21.0 Introduction

The `block_index_or_count_value()` structure is a helper tool used to describe either the block index or block count as required within the context of the encompassing structure. This tool returns the `block_index_or_count_val` variable value.

6.1.21.1 block_index_or_count, block_index_or_count_ext

The `block_index_or_count` field, which is extendable by the `block_index_or_count_ext` field, describes either a block index or a block count as appropriate by the context.

The operational variable `block_index_or_count_val` can be calculated directly from the `block_index_or_count` and `block_index_or_count_ext` fields according to the following equation:

```
block_index_or_count_val = block_index_or_count + block_index_or_count_ext
```

6.1.22 multi_block_packet_group()

6.1.22.0 Introduction

The multiple block (or multi-block) packet group (`multi_block_packet_group()`) contains the `mbpg_header()` as well as coded symbols. The structure is similar to the `packet_group()`structure. However, unlike the `packet_group()` structure which contains coded symbols associated with a single block, a `multi_block_packet_group()` structure may carry coded symbols from multiple blocks (i.e. a multiple block symbol group).

There are several restrictions for the use of a multi-block packet group. Including:

- The multi-block packet group shall only be used when the associated code type utilizes encoded symbol indexes to identify each symbol or row indexes to identify the row of a coding coefficient matrix generated by a block PRNG. Code types that transmit coefficient vectors are not supported. The use of sliding windows is also not supported.
- Within a multi-block packet group, all blocks shall have identical symbol size (`block_symbol_size`), and if applicable, shall have identical field size (`block_field_size_exp_val`) values.
- The blocks represented in a multi-block packet group shall be from a contiguous set of blocks.
- If `addl_block_coding_mask` is present in the relevant `block_header()` instances, bit 1 of the `addl_block_coding_mask` (indicating that a sliding window is used) shall be cleared.
- The `block_mask` field in the relevant block header subatom instances for the blocks represented in a multi-block packet group shall have:
  - Bit 1 (block field size) and bit 4 (block seed) shall be set to the same value across all instances.
  - Bit 2 (separated coding coefficients) and bit 3 (encrypted coding coefficient information) cleared in all instances.

Multi-block packet groups, as well as other fields contained within larger structures, inherit values from previous `subatom()` instances. For example, the `multi_block_packet_group()` structure inherits the value of the `block_symbol_size` field specified in the associated block header subatom instances.

6.1.22.1 mbpg_index

The `mbpg_index` field identifies the `multi_block_packet_group()` instance.

6.1.22.2 mbpg_start_block_index

The `mbpg_start_block_index` field identifies the start block (i.e. first block) of the set of blocks represented in the multi-block packet group.

6.1.22.3 mbpg_num_blocks

The `mbpg_num_blocks` field describes the number of blocks present within the multi-block packet group.

The multi-block packet group contains blocks with `block_index` values in range [`mbpg_start_block_index`, `mbpg_start_block_index + mbpg_num_blocks - 1`]. For example, if `mbpg_start_block_index` has a value of 2, and `mbpg_num_blocks` has a value of 3, then the multi-block packet group contains symbols from blocks 2, 3, and 4.

6.1.22.4 mbpg_num_symbols

The `mbpg_num_symbols` field describes the number of coded symbols present within the multi-block packet group.

6.1.22.5 coded_symbol

A `coded_symbol` is either a systematic symbol or the encoded version of several source symbols, generated by applying coding to the original data symbols. The size of this field is indicated by the `block_symbol_size` field in the associated block header subatom instance as determined by the `mbpg_start_block_index` value. The `block_symbol_size` field shall not use the value `0` when multi-block packet group subatoms are present in the bitstream.

6.1.23 mbpg_header()

6.1.23.0 Introduction

The `mbpg_header()` structure provides information about how the coded symbols contained in the `multi_block_packet_group()` are arranged.

Because a multiple block (or multi-block) packet group contains multiple coded symbols from different blocks, there are less options for how the group of coded symbols can be encoded compared to if each coded symbol had been individually contained within a packet subatom. Within a multi-block packet group, the coded symbols can only be identified by a symbol/row index. Coefficient vectors, and sliding windows are not supported within a multi-block packet group. Further, encryption is not supported for any fields within a multi-block packet group.

6.1.23.1 mbpg_symbol_arrangement

The `mbpg_symbol_arrangement` field describes the order that coded symbols (including systematic symbols) appear within the multi-block packet group subatom. The meaning of this field is specified in Table 78.

Table 78: mbpg_symbol_arrangement Meaning

`mbpg_symbol_arrangement` value	Symbol Arrangement
`0000b`	Not indicated, the arrangement of coded symbols is not described by a pattern and each symbol is identified by the values of `mbpg_source_block_index` and the `mbpg_symbol_index` field.
`0001b`	Explicitly-Identified Symbol Arrangement: Arbitrary, coded symbols are identified explicitly by the values of the `mbpg_source_block_index` and the `mbpg_symbol_index` fields. The arrangement of coded symbols in this case may follow some unspecified pattern.
`0010b`	Source-Symbol Interleaved Arrangement: Separate systematic symbol and interleaved coded symbol arithmetic sequence, systematic symbols are arranged in an arithmetic sequence (i.e. constant difference between symbol index values) by block, then coded symbols are also arranged with a constant difference between symbol indexes, with each coded symbol being from a different block.
`0011b`	Coded-Symbol Interleaved Arrangement: Interleaved by block arithmetic sequence, coded symbols with the same symbol index from different blocks are placed followed by the set of symbols with the next symbol index (e.g. symbol 11 from block 0, symbol 11 from block 1, symbol 12 from block 0, symbol 12 from block 1, etc.).
`0100b-1111b`	Reserved.

Certain values of the `mbpg_symbol_arrangement` field impose additional constraints on other fields. Including:

- If the value of `mbpg_symbol_arrangement` is 0010b or 0011b, then the `b_block_max_symbol_index_present` shall be TRUE and the `block_max_symbol_index` field shall be present in each relevant block header subatom instance.
- If bit 4 of `block_mask` is set in the relevant block header subatom instance, indicating that a block PRNG seed is used, then the value of `mbpg_symbol_arrangement` shall be 0000b, meaning the coded symbol arrangement is not indicated.

6.1.23.2 mbpgsi_bits

The operational variable `mbpgsi_bits` is used in the syntax to specify the number of bits used to encode the `mbpg_symbol_index` field and is represented by the `num_bits_code()` structure.

6.1.23.3 mbpg_source_block_index, mbpg_symbol_index

For each coded symbol in the multiple block packet group the value of `mbpg_source_block_index` identifies the block the symbol comes from (i.e. the source block number), and the `mbpg_symbol_index` field provides either an encoded symbol index (for code types such as Reed-Solomon, or RaptorQ), or a row index in the case that a block PRNG seed is used. The block and symbol index uniquely identify the coded symbol.

6.1.23.4 mbpgfsi_bits

The operational variable `mbpgfsi_bits` is used in the syntax to specify the number of bits used to encode the `mbpg_first_symbol_index` field and is represented by the `num_bits_code()` structure.

6.1.23.5 mbpg_first_symbol_index, b_mbpg_is_symbol_group_subset, mbpg_symbol_group_subset_index

After arrangement to symbol groups, a multi-block packet group may contain a contiguous subset of symbols from a symbol group.

The `b_mbpg_is_symbol_group_subset` Boolean indicates whether multi-block packet group contains a subset or an entire symbol group. When TRUE, the multiple block packet group contains a subset of symbols from the symbol group and the `mbpg_symbol_group_subset_index` field is present in the bitstream.

The `mbpg_first_symbol_index` field defines the symbol index of the first symbol, from the first block (as indicated by `mbpg_start_block_index` field), of the contained symbols in the symbol group associated with the multi-block packet group.

The `mbpg_symbol_group_subset_index` field defines the index into the symbol group to form the subset contained within the multi-block packet group. When `b_mbpg_is_symbol_group_subset` is FALSE, the value of `mbpg_symbol_group_subset_index` shall be equal to 0.

6.1.23.6 mbpg_index_difference

The `mbpg_index_difference` field describes the symbol index difference between successive coded symbols in a multi-block packet group. The value of this field may also correspond to the total number of symbol groups. The value 0 shall not be used for this field.

For example, if the first coded symbol in a multi-block packet group has a symbol index value of 6, and the `mbpg_index_difference` field has a value of 3, then the next coded symbol from the same block has a symbol index of 9.

6.1.23.7 mbpgsai_bits_code

The `mbpgsai_bits_code` field describes the number of bits used by the `mbpg_symbol_arrangement_info` structure which is an instance of the `extension()` structure. The value of the `mbpgsai_bits_code` field is specified in Table 79.

Table 79: mbpgsai_bits_code meaning

`mbpgsai_bits_code` value	Meaning
0	8 bits
1	16 bits
2	32 bits
3	64 bits

The operational variable `mbpgsai_bits` uses the `mbpgsai_bits_code` value to determine the number of bits the subsequent `mbpg_symbol_arrangement_info` structure requires. It can also be calculated as follows:

```
mbpgsai_bits = 2^(mbpgsai_bits_code + 3)
```

6.1.23.8 Symbol Arrangements in a Multiple Block Packet Group

Within a multiple block packet group subatom, a group of coded symbols from blocks `mbpg_start_block_index` … `mbpg_start_block_index+mbpg_num_blocks-1` are arranged into symbol groups as described by the `mbpg_symbol_arrangement` field. This symbol group is either directly used in its entirety, or a subset is used to form the multiple block packet group.

When the coded symbol arrangement in a multi-block packet group is not indicated (the value of the `mbpg_symbol_arrangement` is 0000b) or is an explicitly-identified symbol arrangement (the value of the `mbpg_symbol_arrangement` is 0001b), then each coded symbol can be identified by instances of the `mbpg_source_block_index` field `mbpg_symbol_index` fields present in the bitstream.

When the coded symbols in a multi-block packet group are arranged in a source-symbol interleaved arrangement (the value of the `mbpg_group_symbol_arrangement` is 0010b), then the values of `mbpg_source_block_index` and `mbpg_symbol_index` are calculated using the `block_num_symbols` and `block_max_symbol_index` from each relevant block header subatom instance, `mbpg_first_source_block_index`, `mbpg_num_blocks`, `mbpg_first_symbol_index`, `mbpg_index_difference`, and `mbpg_symbol_group_subset_index` fields. An arithmetic sequence of systematic symbols from block `mbpg_start_block_index` are present, followed by an arithmetic sequence of systematic symbols from block `mbpg_start_block_index+1`, and so on until block `mbpg_start_block+mbpg_num_blocks-1`. In the context of a multi-block packet group, a systematic symbol has an `mbpg_symbol_index` value less than `block_num_symbols` for a given block. Then coded symbols are arranged with a constant difference between symbol indexes, however, each coded symbol comes from a different block.

If the value of the `mbpg_symbol_arrangement` is 0010b, a CMMF decoder shall determine the `mbpg_source_block_index` and `mbpg_symbol_index` values for each coded symbol using the pseudocode in Table 80.

Table 80: Separate systematic and interleaved coded symbol arithmetic sequences symbol arrangement in a multi-block group pseudocode

Pseudocode

```
def mbpg_arrangement_0010b(
      block_info, # contains block_num_symbols and block_max_symbol_index for each block
      mbpg_start_block_index,
      mbpg_num_blocks,
      mbpg_num_symbols,
      mbpg_index_difference,
      mbpg_first_symbol_index,
      mbpg_symbol_group_subset_index,
      ):
   # source and coded/repair symbol pattern arrays
   cr_pattern_block_indexes = []
   cr_pattern_symbol_indexes = []
   ss_pattern_block_indexes = []
   ss_pattern_symbol_indexes = []
   # symbol group arrays
   symbol_group_block_indexes = []
   symbol_group_symbol_indexes = []
   # multi-block packet group (or subset) arrays
   mbpg_source_block_index = []
   mbpg_symbol_index = []

   # ----- arrange all symbols according to pattern -----
   # arrange source symbols and get source symbols in symbol
   num_source_symbols = 0
   for blk in range(mbpg_start_block_index,(mbpg_start_block_index+mbpg_num_blocks)):
      for symbol in range(block_info[blk]['block_num_symbols']):
         ss_pattern_block_indexes.append(blk)
         ss_pattern_symbol_indexes.append(symbol)
         num_source_symbols += 1

   # create arrays for coded/repair symbols
   # find max number of coded/repair symbols of all blocks
```

Pseudocode

```
    max_num_cr_symbols = 0
    for blk in range(mbpg_start_block_index,(mbpg_start_block_index+mbpg_num_blocks)):
        num_cr_symbols_in_blk = block_info[blk]['max_symbol_index'] - block_info[blk]['block_num_symbols'] + 1
        max_num_cr_symbols = max(max_num_cr_symbols, num_cr_symbols_in_blk)

    # create arrays of length max_num_cr_symbols
    for blk in range(mbpg_start_block_index,(mbpg_start_block_index+mbpg_num_blocks)):
        cr_blocks = [-1] × max_num_cr_symbols
        cr_symbols = [-1] × max_num_cr_symbols
        idx = 0
        for si in range(block_info[blk]['block_num_symbols'], block_info[blk]['max_symbol_index']+1):
            cr_blocks[idx] = blk
            cr_symbols[idx] = si
            idx += 1
        cr_pattern_block_indexes.append(cr_blocks)
        cr_pattern_symbol_indexes.append(cr_symbols)

    # ----- extract symbol group -----
    # source symbols
    for idx in range(mbpg_first_symbol_index, num_source_symbols, mbpg_index_difference):
         symbol_group_block_indexes.append(ss_pattern_block_indexes[idx])
         symbol_group_symbol_indexes.append(ss_pattern_symbol_indexes[idx])

    # coded/repair symbols
    for idx in range(mbpg_first_symbol_index, max_num_cr_symbols, mbpg_index_difference):
        for blk in range(mbpg_start_block_index,(mbpg_start_block_index+mbpg_num_blocks)):
            if (cr_pattern_symbol_indexes[blk][idx] != -1) and (cr_pattern_symbol_indexes[blk][idx] <=
block_info[blk]['max_symbol_index']):
                symbol_group_block_indexes.append(cr_pattern_block_indexes[blk][idx])
                symbol_group_symbol_indexes.append(cr_pattern_symbol_indexes[blk][idx])

    # ----- extract multi-block-packet group (or smaller subset) from symbol group -----
    mbpg_source_block_index =
symbol_group_block_indexes[mbpg_symbol_group_subset_index:(mbpg_symbol_group_subset_index+mbpg_num_s
ymbols)]
    mbpg_symbol_index       =
symbol_group_symbol_indexes[mbpg_symbol_group_subset_index:(mbpg_symbol_group_subset_index+mbpg_num
_symbols)]

    return mbpg_source_block_index, mbpg_symbol_index
```

An example symbol arrangement 0010b (Source-Symbol Interleaved Arrangement) is shown in Figure 12. In this example, symbols from three blocks (0, 1, and 2) are represented, where:

- `block_num symbols` is 10 and `block_max_symbol_index` is 30 for block 0
- `block_num symbols` is 10 and `block_max_symbol_index` is 30 for block 1
- `block_num symbols` is 9 and `block_max_symbol_index` is 30 for block 2
- `mbpg_num_symbols` is 30, 30, 29
- `mbpg_symbol_group_subset_index` is 0, 0, 0
- `mbpg_first_symbol_index` is 0, 1, 2
- `mbpg_index_difference` is 3




Figure 12: Example symbol arrangement for mbpg_symbol_arrangement=0010b (Source-Symbol Interleaved Arrangement)

When the coded symbols in are arranged in a coded-symbol interleaved arrangement (the value of the `mbpg_symbol_arrangement` is 0011b), then the values of `mbpg_source_block_index` and `mbpg_symbol_index` are calculated using the `block_max_symbol_index` from each relevant block header subatom instance, `mbpg_start_block_index`, `mbpg_num_blocks`, `mbpg_first_symbol_index`, `mbpg_index_difference`, and `mbpg_symbol_group_subset_index` fields. The coded symbols are arranged in an arithmetic sequence; however, each coded symbol comes from a different block.

If the value of the `mbpg_symbol_arrangement` is 0011b, a CMMF decoder shall determine the `mbpg_source_block_index` and `mbpg_symbol_index` values for each coded symbol using the pseudocode in Table 81.

Table 81: Interleaved by block coded symbol arithmetic sequences symbol arrangement in a multi-block group pseudocode

Pseudocode

```
def mbpg_arrangement_0011b(
      block_info, # contains block_num_symbols and block_max_symbol_index for each block
      mbpg_start_block_index ,
      mbpg_num_blocks,
      mbpg_num_symbols,
      mbpg_index_difference,
      mbpg_first_symbol_index,
      mbpg_symbol_group_subset_index,
      ):
   # source and coded symbol pattern arrays
   coded_symbol_pattern_block_indexes = []
   coded_symbol_pattern_symbol_indexes = []
   # symbol group arrays
   symbol_group_block_indexes = []
   symbol_group_symbol_indexes = []
   # multi-block packet group (or subset) arrays
   mbpg_source_block_index = []
   mbpg_symbol_index = []

   # ----- arrange all symbols according to pattern -----
   # find max number of coded/repair symbols of all blocks
   max_num_coded_symbols = 0
   for blk in range(mbpg_start_block_index,(mbpg_start_block_index+mbpg_num_blocks)):
      num_coded_symbols_in_blk = block_info[blk]['max_symbol_index'] + 1
      max_num_coded_symbols = max(max_num_coded_symbols, num_coded_symbols_in_blk)

   # create arrays of length max_num_coded_symbols
   for blk in range(mbpg_start_block_index,(mbpg_start_block_index+mbpg_num_blocks)):
      cr_blocks = [-1] × max_num_coded_symbols
      cr_symbols = [-1] × max_num_coded_symbols
      idx = 0
      for si in range(block_info[blk]['max_symbol_index']+1):
         cr_blocks[idx] = blk
   return mbpg_source_block_index, mbpg_symbol_index
```

An example symbol arrangement 0011b (Encoded-Symbol Interleaved Arrangement) is shown in Figure 13. In this example, symbols from three blocks (0, 1, and 2) are represented, where:

- `block_num symbols` is 10 and `block_max_symbol_index` is 29 for block 0
- `block_num symbols` is 10 and `block_max_symbol_index` is 29 for block 1
- `block_num symbols` is 9 and `block_max_symbol_index` is 26 for block 2
- `mbpg_num_symbols` is 25, 25, 25
- `mbpg_symbol_group_subset_index` is 4 for each object
- `mbpg_first_symbol_index` is 0, 1, 2
- `mbpg_index_difference` is 3




Figure 13: Example symbol arrangement for mbpg_symbol_arrangement=0011b (Encoded-Symbol Interleaved Arrangement)

6.1.23.9 b_mbpg_integrity_present

This Boolean indicates whether the `mbpg_integrity()` structure is present in the bitstream. The `mbpg_integrity()` structure is an instance of the `packet_integrity()` structure that applies to the group of coded symbols within the multiple block packet group.

6.1.23.10 b_mbpg_header_ext_present

This Boolean indicates whether the `mbpg_header_extension()` structure is present in the bitstream. The `mbpg_header_extension()` structure provides a mechanism to extend the packet header syntax with additional information and is an instance of the `extension()` structure.

7 Design considerations

7.0 Introduction

This clause describes design considerations for encoders, and parsers/decoders.

7.1 Coding coefficients

7.1.0 Generating coding coefficients using a PRNG

A PRNG can be used to generate coding coefficients that are applied to source symbols to create coded symbols. Rather than transmit the coding coefficients in the bitstream, the means for generating the coefficients are parameterized and the resulting parameters are transmitted for a decoder to regenerate the coefficients.

The bitstream supports transmission of a seed per block or per packet via the fields in `prng_parameters()`. The block or packet seed in the bitstream is used to initialize the PRNG.

A density controller (that also uses the PRNG) controls the amount of non-zero coefficients. The density controller uses either the block or packet `prng_density_percentage` field(s) to determine whether the coefficient should be set to `0`.

When a block seed is used, rows of `block_num_symbols` worth of columns are generated, starting with the first index (`0`) until the last index (`block_num_symbols - 1`) for the first row, and repeating for the subsequent rows to generate a complete coding matrix. At least `block_num_symbols` worth of rows need to be generated to be able to represent the entire source block. Once the rows are generated, the `packet_symbol_index` value in arriving packet subatoms identifies which row of the generated coding matrix was applied to the `coded_symbol`.

For a given packet, packet group, or multi-block packet group subatom, if a block PRNG is used and the `b_systematic_symbol` field is set, or if the row index is less than `block_num_symbols`, then the identified row of coefficients generated by the block PRNG is discarded and replaced with a coefficient row vector consisting of all `0`'s except at the index identified by the `packet_symbol_index` , or `packet_group_symbol_index`, or `mbpg_symbol_index` value, where the coefficient is set to `1`. For example, assuming a `block_field_size_exp_val` of `1`, if a systematic packet's `packet_symbol_index` value is `2`, and the block PRNG generated has a coefficient row of [0 1 1 0 1 1], then this will be replaced with [0 0 1 0 0 0].




Figure 14: Block PRNG

When a packet seed is used, a `window_size` worth of symbols is generated starting with the first index (`0`) of the `coefficient_vector`, and ending with the final index (`window_size - 1`).




Figure 15: Packet PRNG

7.1.1 Coefficient density control

The density controller manages the sparsity of non-zero coefficients. The controller can be thought of a function that accepts a number generated by the PRNG and the density percentage value for either the block or packet (as an integer, `density_int`) and returns either a 0 or a 1. When the value is 1, then the block (or packet) coefficient generator block generates a coefficient. Pseudocode for the density control function is shown in Table 82.

Table 82: Density controller pseudocode

Pseudocode

```
density_controller(prng_generated_number, density_int)
{
   random_int = prng_number() % 128 + 1;
   if (random_int >= density_int) {
      return 0;
   } else {
      return 1;
   }
}
```

7.1.2 Mersenne twister PRNG type

When either the block or packet `prng_type` field has a value of `000b`, a Mersenne Twister (MT) based PRNG is used. The standardized MT19937 [8] shall be used. The PrngMT class shown in the pseudo-code in Table 83 takes the seed, density (as an integer) and the field size exponent, controls the density and subsequently generates coefficient numbers.

Table 83: Mersenne twister pseudocode

Syntax

```
class PrngMT {
public:
{
   prngMT(unsigned long seed) {
      m_mt.seed(seed)
   }

   unsigned long get_coefficient(unsigned int density_int, int field_size_exp)
   {
      // Step 1: use density to determine if coefficient should be zero
      auto density_rand = m_mt();
      if (density_rand % 128 + 1 >= density_int) {
         return 0;
      } else {
         // Step 2: Pick a random non-zero coefficient.
         if (field_size_exp == 1) {
            // Special case of binary field needs no random input
            return 1;
         }
         auto coeff_rand = m_mt();
         return (coeff_rand % ((1 << field_size_exp) - 1)) + 1;
      }
   }
private:
   std::mt19937 m_mt;
}
```

7.2 Handling variable source symbol size

Applications of the CMMF bitstream may include cases where the size of the data source symbols is not constant. Since most code types require equal-sized source symbols, the CMMF bitstream format was designed not to support explicit description of the size for each symbol.

When the source symbols have varying sizes, applications shall prepend the size of the source symbol to the data before passing it to the CMMF bitstream encoder. This size information becomes part of the data source symbol from the encoder's perspective and will be encoded. Within the encoder, an appropriate amount of zero-padding is applied to the data to equalize the lengths for encoding. The encoder may choose to make the length to be that of the largest data source symbol among the symbols to be encoded together. Another option available to the encoder is to apply a global maximum length and pad all the symbols to a uniform size. If the encoder chooses to transmit a symbol within a systematic packet, and the `block_symbol_size` field in the associated `block_header()` instance is `0`, then the subatom size can be shortened to omit the padding within the `coded_symbol`.

Following decoding, a size/padding peeler is used to parse the size marker, strip the size data and any excess padding to obtain the original source symbol and provide the data to the application.

An example of how such a system may work is shown in Figure 16.




Figure 16: Handling variable size data

In the example above, three symbols (P1, P2, P3) of different sizes are encoded together. Since P1 is the largest, the size marker sets the symbol length to the length of size prepended P1. Thus, P2 and P3 will be padded with zeros before encoding.

Again, the encoder may choose not to pad symbols that will be sent in systematic packets. When a decoder receives a systematic packet, the size prepended symbol is passed to the size/padding peeler which will parse the size revealing that there is no padding to remove, only the size marker. In Figure 16 above, assume transmission of P1 is successful, so the decoder receives the size prepended P1 with no additional padding, which is passed to the size/padding peeler.

For an encoded symbol, the encoder pads each source symbol to equal size. When the decoder receives an encoded symbol, after decoding the size marker will be present in the recovered symbol, and potentially may have some amount of padding. In the example above, assume the transmission of P2 failed, so P2 is retrieved via decoding of the coded packets. The decoded P2 has both the size marker and padding which will be removed by the size/padding peeler.

7.3 Encrypting coding coefficient information

7.3.0 Introduction

The CMMF bitstream supports encryption of coding coefficient information. Encrypting the coding coefficient information can provide an extra layer of security for protecting content. Depending on the infrastructure an application uses, different methods for handling the necessary encryption keys can be used.

7.3.1 Using a bitstream/session key and symmetric keys

As an example of one method to handle encryption of coding coefficient information, a bitstream or session key, and symmetric keys can be used. In this example, there a single bitstream consisting of multiple blocks.

This method uses a combination of keys to provide secure delivery of coefficient vectors to clients. Each coefficient vector is encrypted using a stream cypher keyed with a symmetric key unique to each block. These block unique symmetric keys are themselves encrypted using a stream cypher keyed with a symmetric key unique to each bitstream or session. The block symmetric keys are stored within the bitstream's block header subatoms. The bitstream symmetric key that is used to encrypt each block symmetric key is not stored within the bitstream. Rather a key identifier is stored within the bitstream header that enables the client to request the bitstream symmetric key from a Key Management System (KMS). Upon client authentication, the bitstream symmetric key is transmitted to the client using a secure channel encrypted using an asymmetric key (e.g. TLS [i.1]).

This approach limits the amount of communication between the client and KMS (only one key needs to be communicated). Once the bitstream key is obtained from the KMS, all encrypted fields within the bitstream are accessible.

The bitstream key does not necessarily have to be unique to each bitstream. Rather, this key can be shared across multiple bitstreams. For example, assume that a streaming session consists of segmented content where each segment is packaged within its own bitstream. Rather than having a unique key for each bitstream/segment, a session key can be used that is shared across all bitstreams. In this case, the session key is used to encrypt each of the block keys.

Figure 17 shows how the various keys are encrypted and stored within the bitstream and KMS.




Figure 17: Bitstream, block, key management

Figure 18 shows the client process for decrypting each coefficient vector.




Figure 18: Client process for decryption

Figure 19 demonstrates one possible method of downloading a bitstream.




Figure 19: Bitstream and key download process

Annex A (normative): xCD-1

A.0 Introduction

This annex defines the encoding and decoding processes for code type 0, xCD-1.

A.1 Encoding

Source data (e.g. segments of source coded audio-visual data) are partitioned into one or more blocks. Each block is encoded into multiple equal-sized xCD-1 encoded symbols. The encoded symbols are carried in one or more correlated CMMF bitstreams. Source data boundaries, number of blocks, symbols, and bitstreams may be chosen to optimize operations including processing, caching, transmission paths, or to increase redundancy as required for the specific application.

Source data is encoded using `code_type 0` (xCD-1) according to the following steps:

1) Source data is first partitioned into `block_count_minus1 + 1` blocks.

2) A value `block_num_symbols` is chosen for each block of source data.

3) The symbol size `block_symbol_size` may be calculated for each block of source data according to the following formula:

```
block_symbol_size = ceil(block_size / block_num_symbols)
```

4) Padding data of zero or more bytes is appended to the end of each block of source data, with the size calculated according to the following formula:

```
block_num_symbols × block_symbol_size - block_size
```

5) Each block of source data, along with any additional padding, is further partitioned into `block_num_symbols` source symbols, each of size `block_symbol_size`, forming the source symbol vector `X`.

6) A Galois field with size `2^block_field_size_exp` as specified in Table 44 is selected for each block.

7) A coefficient matrix `G` with `block_num_symbols` columns and greater than or equal to `block_num_symbols` rows is determined where each element in the matrix is an element in the chosen Galois field. This coefficient matrix may be either deterministically or randomly generated.

8) The encoded symbol vector `Y` is calculated according to the following formula:

```
Y = GX
```

   Where each source symbol in `X` is treated as a vector in the chosen Galois field determined in step 6.

Each element of the encoded symbol vector `Y` is a `coded_symbol` that may be communicated, along with its associated coefficient vector (i.e. row of `G`), within a CMMF bitstream `packet()` subatom.

Figure A.1 shows an example where an audio or video segment with size of 500 kBytes is: partitioned into one block (step 1), `block_num_symbols` of six is chosen (step 2) where each has a size of 83 334 bytes (step 3), four bytes of padding is appended to the source block (step 4), the source block is further partitioned into six source symbols (step 5), and the Galois field with `block_field_size_exp` of one is selected (step 6).




Figure A.1: xCD-1 segment to symbols

The source symbols x_1 through x_6 can be mathematically represented as a vector `X` of length `block_num_symbols`.

Figure A.2 shows an example where a coefficient matrix `G` with `block_num_symbols` of six columns and 12 rows is generated (step 7). Each of the coefficients within the matrix is an element of the Galois Field GF{2} (i.e. each coefficient is either a 0 or a 1) and each source symbol x_1 through x_6 is treated as a vector in the same Galois Field GF{2}.




Figure A.2: xCD-1 symbol vector and coefficient matrix

Figure A.3 shows the vector of source symbols `X` is multiplied with coefficient matrix `G` to create a vector of encoded symbols `Y` (step 8). Each of these encoded symbols, along with their respective row in matrix `G`, can then be packaged within individual `packet()` subatoms belonging to one or more CMMF bitstreams.




Figure A.3: xCD-1 coefficient matrix

In a simple case, these 12 encoded symbols are split equally between two CMMF bitstreams. Each CMMF bitstream carries one `block_header()` subatom with the `b_sufficient_symbols_present` field set, followed by `block_num_symbols` (equal to size) subatoms of the `packet()` type with:

- The `packet_block_index` field indicating the block number index of one.
- The `coded_symbol` field of each `packet()` subatom holding the data of one encoded symbol (i.e. one element of `Y`).
- Information about the encoded symbol's coefficient vector (see clause 6.1.7.2).

More complex cases are also possible (e.g. source data partitioned into more than one block, CMMF bitstreams containing less than `block_num_symbols` `packet()` subatoms, chunked subatoms, etc.).

A.2 Decoding

When receiving one or more CMMF bitstreams carrying the same source data encoded with xCD-1 (i.e. `code_type` field with a value of `0`), the decoder assures, at a minimum matching `content_encode_uuid` (if present), `content_source_size`, `content_source_type`, `code_type`, and `block_count_minus1` field values contained within the `sync()` and `bitstream_header()` subatoms across all received bitstreams. For each block in these received CMMF bitstreams, the decoder:

1) Assures, at a minimum, matching `block_index`, `block_size`, `block_num_symbols`, and `block_symbol_size` field values contained within the `block_header()` subatom of each of the matching CMMF bitstreams.

2) Initializes an empty encoded symbol vector `Y'` with an element size of `block_symbol_size`, and an empty coefficient matrix `G'` with `block_num_symbols` columns. The length of `Y'` as well as the row count of `G'` is at least `block_num_symbols`, and no more than `block_num_symbols` × *number of CMMF bitstreams*.

3) For each received `packet()` subatom from a matching CMMF bitstream and block, the encoded symbol `coded_symbol` is appended to the encoded symbol vector `Y'`. The corresponding coefficient vector is extracted from the `packet_header()` structure and is appended (as a row) to the coefficient matrix `G'`. This process is repeated until the decoder confirms that the coefficient matrix `G'` has a rank equal to `block_num_symbols`.

4) The source symbol vector `X'` is calculated according to the following formula:

$$X' = (G')^{-1}Y'$$

5) The source symbols in `X'` are appended together and the first `block_size` bytes are extracted to form the block's decoded source data.

6) If more than one block exists, each block's decoded source data is appended together in order of `block_index`.

Figure A.4 shows the result of steps 1 through 3 for an example where the source data was encoded using one block, the `block_num_symbols` is six, the encoded symbols were communicated within two CMMF bitstreams, and a sufficient number of encoded symbols was received by the decoder in the order of `packet_symbol_index` 1, 7, 8, 2, 9, 10.



Figure A.4: xCD-1 coded symbol vector and decoded coefficient matrix

The decoder inverts `G'` and multiplies it with the coded symbol vector `Y'` (step 4) to determine the source symbol vector `X'`. Figure A.5 shows an example with six symbols.




Figure A.5: xCD-1 symbol reconstruction

The decoder then appends each source symbol in `X'` together, removes any padding (if present, e.g. to create equal-sized source symbols) (steps 5 and 6), and finally delivers the decoded segment of source data.

Figure A.6 shows an example with a segment size of 500 kBytes in one block, decoded from six symbols, with 4 bytes of padding at the end of the final symbol.




Figure A.6: xCD-1 data extraction

Annex B (informative): Media service architecture Examples

B.0 Introduction

The Coded Multisource Media Format (CMMF) provides an extensible method for the management and interchange of source coded audio-visual media and related metadata in one or more unique representations resulting from the use of linear, network or channel coding methods (see note). The CMMF bitstream structure supports multiple linear, network or channel code types and related information for use in delivering audio-visual media over multipath and/or multi-access networks in settings targeted at improving cloud/network-powered QoS and rendered QoE. This annex provides various media service architecture examples showing how CMMF can be employed within existing media service architectures to enable multisource delivery.

NOTE: Where, linear, network or channel coding methods are directly applied to source coded (or source coded and packaged) audio-visual media.

B.1 MPEG-DASH HTTP adaptive streaming service example

A typical MPEG-DASH HTTP adaptive streaming system is setup similarly to the non-shaded blocks shown in Figure B.1. Source media (e.g. audio/video elementary streams) are segmented and encoded into multiple representations, each with a different quality and bit rate. These segments are packaged together using MPEG-DASH and stored on an origin server located within the network. One or more CDNs are setup to distribute and deliver this content to an OTT service providers' customer base. These CDNs obtain every requested MPEG-DASH segment from an origin server, caches these segments at the networks' edge, and delivers these segments to clients.

Enabling multisource using CMMF within this existing delivery architecture can be accomplished through the addition of a CMMF Bitstream Generator/Source before segments are delivered to the CDNs and a CMMF Receiver on each client as illustrated by the shaded boxes in Figure B.1.

While Figure B.1 shows the CMMF Bitstream Generator/Source between the Origin Server and the CDNs (i.e. CMMF bitstreams are created on demand), the CMMF Bitstream Generator/Source can just as easily be located between the MPEG-DASH Packager and Origin Server. In the former case, the original MPEG-DASH segments are stored on the Origin Server and CMMF representations of those segments are cached on each CDN. In the latter case, the CMMF Bitstream Generator/Source creates multiple CMMF representations of each segment produced by the MPEG-DASH Packager and stores them on the Origin Server for later retrieval by a CDN.




Figure B.1: MPEG-DASH with CMMF Delivery System Example

The reference architecture for this example is shown in Figure B.2. In this architecture, the Application Provider is responsible for segmenting, encoding, and packaging the media. Each MPEG-DASH segment is equivalent to a single Source Transport Object; and the Media Information consists of the media's corresponding MPEG-DASH master manifest. This master manifest (see Figure B.3) contains relative URLs to the files/segments (shown in a dotted outline) that make up the adaptation sets. This information is transferred via the C1 interface from the Application Provider to the Media Player (using a method preferred by the Application Provider) and is used by the Media Player to determine which segments are to be downloaded (via the CMMF Receiver) and played.




Figure B.2: CMMF reference architecture in relation to MPEG-DASH HTTP adaptive streaming example




Figure B.3: Example MPEG-DASH master manifest

The Application Provider for this example is also responsible for determining and setting up the delivery system (i.e. CDNs) to distribute CMMF encoded media. Information about this setup is captured within the CMMF Configuration Information as a list of host URLs to each of the CDNs. It is important to note that both the MPEG-DASH master manifest and the CMMF Configuration Information is required to download the media. It is assumed that the Application Provider is utilizing two CDNs and each segment listed in the MPEG-DASH master manifest is encoded and packaged into two unique CMMF bitstreams, one intended for the first CDN and the other for the second CDN according to the list of host URLs provided in the CMMF Configuration Information. An example of this is shown in Figure B.4. Furthermore, example bitstream constructions can be found in annex C.




Figure B.4: CMMF bitstreams generated to deliver the MPEG-DASH packaged content

The process for streaming this content is shown in Figure B.5.




Figure B.5: CMMF request and content delivery example for MPEG-DASH

An Application Provider provisions an origin server with the original source segments shown in Figure B.1. Upon client initialization, the CMMF Receiver requests the CMMF Configuration Information (in this case it is stored as a JSON file) from the Application Provider. This information communicates a list of host URLs specifying the locations for which the client can retrieve CMMF encoded content for every segment listed within the master manifest file. Upon media player/delivery session initialization, the media player retrieves and parses the master manifest file from the Application Provider and chooses the adaptation set(s) it wishes to stream. Once selected, the media player requests the appropriate segment from the CMMF Receiver using the relative URL communicated in the master manifest. The CMMF Receiver joins the relative URL with each of the host URLs from the CMMF Configuration Information file and requests two distinct CMMF bitstreams of that segment from the two available CDNs. Assuming the appropriate CMMF bitstream is cached, the CDN begins delivery. Otherwise, the CDN requests the segment from the CMMF Bitstream Generator/Source. At which point, the original segment is pulled from storage, encoded, and delivered to the CDN and to the client. The CMMF Receiver downloads the two CMMF bitstreams of that segment until it is capable of decoding (see annex A for an example). It then cancels any outstanding data that has yet to be delivered, decodes the segment, and delivers it to the media player. The media player selects the next segment to be downloaded and the process repeats.

In the case of a third CDN being introduced, a new CMMF bitstream can be generated and cached without replacing or modifying the existing CMMF bitstreams already cached in the initial two CDNs. All that is required is an update to the host URL list managed by the Application Provider.

Furthermore, the above example implies that CMMF bitstreams are retrieved from each CDN using HTTP. As noted earlier, CMMF is agnostic to the underlying transport protocol. Other transport protocols (e.g. webRTC, FLUTE, ROUTE, etc.) may also be used if appropriate.

Annex C (informative): Example bitstreams

C.0 Introduction

The CMMF bitstream is designed to be applicable in multiple use cases. This annex contains example CMMF bitstreams for different applications.

C.1 Multisource Video-on-Demand

C.1.0 Multisource Video-on-Demand example using code_type xCD-1

This example shows one method of implementing the bitstream to support multisource Video-on-Demand (VoD) HTTP Adaptive Streaming (HAS). In a generalized scenario, a client requests and receives, via HTTP, two CMMF bitstreams from two separate CDNs as shown in Figure C.1. The client then merges these bitstreams together allowing it to decode the bitstreams and extract the audio, video, and/or metadata. In this example, communication between the client and the CDNs is reliable and the bitstream served by the CDN is cached.




Figure C.1: Multi-source CDN-client communication

C.1.1 Bitstream construction

Multiple, correlated bitstreams can be constructed using the xCD-1 code type to enable efficient delivery of the underlying content. For this approach to work, each bitstream needs to utilize the same code type and encoder settings. Subatoms carrying this encoder setting information are transmitted in each bitstream. Each bitstream may contain different packet subatoms depending on the system's objectives. Figure C.2 shows two bitstreams created using the same data, and same encoder settings, and as a result has similar subatom arrangement.




Figure C.2: CMMF multisource example bitstream arrangement

In this example, the content is partitioned into eight packets. Four systematic packets are transmitted in bitstream A, and four systematic packets are transmitted in bitstream B. Four additional coded packet subatoms are included within each bitstream to ensure that the source content can be recovered if a failure to obtain one of the bitstreams occurs. Subatoms required to initialize playback and/or decoders on client devices are sent within each bitstream.

The following clauses provide examples of the `sync()` structure and each subatom's construction for one of the bitstreams shown in Figure C.2 above. Subatoms required to ensure recovery of the original symbols are shown. Examples of optional subatoms, such as the encoder content information and media segment information subatoms, are also provided.

C.1.2 Sync construction

The CMMF bitstream starts with a data structure for synchronization, shown in Table C.1.

Table C.1: sync() structure construction

Syntax	Encoding	Example Value	Notes
`sync()`			
`{`			
`syncword`	v(64)	0x89780D430044AC31	Predefined value.
`version`	v(4)	0x0	Predefined value.
`b_content_encode_uuid`	b(1)	1b (TRUE)	Content encode UUID is used to add another method to ensure that data from correlated bitstreams from multiple sources are matched together.
`reserved`	v(3)	000b	
`if (b_content_encode_uuid){`			
`content_encode_uuid`	v(128)	0x294d34081445441db44f3dd8c1695cf7	Randomly generated UUID
`}`			
`}`			

C.1.3 Subatom construction

C.1.3.1 Bitstream header subatom construction

A subatom containing the Bitstream header structure is shown in Table C.2.

Table C.2: Bitstream header subatom construction

Syntax	Encoding	Example Value	Notes
subatom() { /* subatom header start */ **subatom_id**	u(4)	2	SUBATOM_ID_BITSTREAM_HEADER

if (subatom_id == 0xF){
subatom_id_ext
subatom_id = subatom_id + subatom_id_ext
}
	u(8)	NULL	

b_bitstream_id_present	b(1)	1b (TRUE)	While optional, the bitstream_id is defined for bitstream identification purposes.
reserved	v(1)	0b	

sas_bits = num_bits_code()
{
bits_code
num_bits = (bits_code + 1) × 8
return num_bits
}
	u(2)	00b	Other instances of num_bits_code() are not expanded for brevity.
			The subatom data size is indicated using 8 bits.

if (b_bitstream_id_present){
bitstream_id
}
	v(16)	0	bitstream_id was chosen to be 0 in this example. The bitstream_id field can be unique to each source to help differentiate between them if necessary.

subatom_size	u(sas_bits)	11	Number of bytes contained between /* subatom data start */ and /* subatom data end */.
/* subatom header end */			
/* subatom data start */ bitstream_header() { **content_source_size**	u(64)	2 000 000	Content source size is 2 MB. This value has to be consistent between bitstreams from each source.
content_source_type	v(3)	001b	Source of the content is the original data file. This value has to be consistent between bitstreams from each source.
reserved **b_content_source_split**	v(1) b(1)	0b 0b (FALSE)	Bitstream represents the entire file.

Syntax	Encoding	Example Value	Notes
`if (b_content_source_split){`			
content_source_split_start	u(64)	NULL	
content_source_split_end	u(64)	NULL	
`}`			
code_type	u(4)	0000b	xCD-1. This value has to be consistent between bitstreams from each source.
`if (code_type == 0xF){`			
code_type_ext	u(8)	NULL	
`code_type = code_type + code_type_ext`			
`}`			
b_rfc5052	b(1)	0b (FALSE)	This CMMF bitstream is not being used as a content delivery protocol as per IETF RFC 5052 [15].
`if (b_rfc5052){`			
`rfc5052_information()`		NULL	
`}`			
`block_count_minus1 = block_index_or_count_value()`			Other instances of `block_index_or_count_value()` are not expanded for brevity.
`{`			
block_index_or_count	u(8)	0	There is only one block in this bitstream. This value has to be consistent between bitstreams from each source.
`if (block_index_or_count == 0xFF)`			
`{`			
block_index_or_count_ext	u(32)	NULL	
`}`			
`else`			
`{`			
`block_index_or_count_ext = 0`			
`}`			
`block_index_or_count_val = block_index_or_count + block_index_or_count_ext`			
`return block_index_or_count_val`			
`}`			
`block_count = block_count_minus1 + 1`			`block_count = 1`
b_content_block_separate_sources	b(1)	0b (FALSE)	The block is composed of a single source.
`if (b_content_block_separate_sources){`			
num_content_block_sources_minus1	u(8)	NULL	
`}`			
b_profile_information_present	b(1)	0b (FALSE)	Unknown whether this bitstream conforms to any profile.
`if (b_profile_information_present){`			
profile_type_size	u(4)	NULL	
profile_type	v(profile_type_size × 8)	NULL	
profile_description	v(32)	NULL	
`}`			
b_block_cc_encrypted	b(1)	0b (FALSE)	No blocks have encrypted coding coefficient information.
`if (b_block_cc_encrypted){`			
bitstream_encryption_key_id_size_exp	u(4)	NULL	
`bseki_bits = 2^ bitstream_encryption_key_id_size_exp`			
bitstream_encryption_key_id	v(bseki_bits)	NULL	

Syntax	Encoding	Example Value	Notes
} } **padding** /* subatom data end */ }	pad	000b	3 bits of padding are needed for byte alignment.

C.1.3.2 Block header subatom construction

A subatom containing the Block header structure is shown in Table C.3.

Table C.3: Block header subatom construction

Syntax	Encoding	Example Value	Notes
subatom() { /* subatom header start */ **subatom_id**	u(4)	6	SUBATOM_ID_BLOCK_HEADER

if (subatom_id == 0xF) {
subatom_id_ext
subatom_id = subatom_id + subatom_id_ext
}
	u(8)	NULL	

b_bitstream_id_present	b(1)	1b (TRUE)	While optional, the bitstream_id is defined for bitstream identification purposes.
reserved	v(1)	0b	
sas_bits = num_bits_code()			The subatom data size is indicated using 8 bits. 2 bits used within expansion of num_bits_code().
if (b_bitstream_id_present) { **bitstream_id**	v(16)	0	bitstream_id was chosen to be 0 in this example. The bitstream_id field can be unique to each source to help differentiate between them if necessary.
}			
subatom_size	u(sas_bits)	11	Number of bytes contained between /* subatom data start */ and /* subatom data end */.
/* subatom header end */			
/* subatom data start */ block_header() { block_index = block_index_or_count_value()			Block index is 0. 8 bits used in the expansion of block_index_or_count_value().
block_size	u(32)	2 000 000	Block size is 2 MB. This value is identical between bitstreams from each source.
block_symbol_size	u(32)	250 000	Block symbol size = 2 MB / 8. This value is identical between bitstreams from each source.

Syntax	Encoding	Example Value	Notes
bns_bits = num_bits_code()			block_num_symbols is represented by 8 bits. 2 bits used within expansion of num_bits_code().
block_num_symbols	u(bns_bits)	8	Number of symbols in each block is 8. This value is identical between bitstreams from each source.
b_block_max_symbol_index_present	b(1)	0b (FALSE)	Symbol indexes not used in this bitstream.
if (b_block_max_symbol_index_present)			
{			
bmsi_bits = num_bits_code()		NULL	
block_max_symbol_index	u(bmsi_bits)	NULL	
}			
b_block_content_source_index_present	b(1)	0b (FALSE)	
if (b_block_content_source_index_present)			
{			
block_content_source_index	u(8)	NULL	
}			
b_block_composite_sources	b(1)	0b (FALSE)	
if (b_block_composite_sources)			
{			
block_num_composite_sources_minus1	u(8)	NULL	
blk_num_cmp_sources = block_num_composite_sources_minus1 + 1			
for (cmpsrc=0; cmpsrc < blk_num_cmp_sources; cmpsrc++) {			
bcss_bits = num_bits_code()		NULL	
block_composite_source_size	u(bcss_bits)	NULL	
}			
}			
b_addl_block_coding_info_present	b(1)	0b (FALSE)	
if (b_addl_block_coding_info_present)			
{			
addl_block_coding_mask	v(3)	NULL	
if (addl_block_coding_mask & 0x1) {			
b_addl_window_info_present	b(1)	NULL	
if (b_addl_window_info_present) {			
addl_window_info() = extension(4)			
}			
}			
if (addl_block_coding_mask & 0x2) {			
b_reserved_block_coding_params_present	b(1)	NULL	
if (b_reserved_block_coding_params_present)			
{			
reserved_block_coding_params() = extension(4)		NULL	
}			
}			
if (addl_block_coding_mask & 0x4) {			

Syntax	Encoding	Example Value	Notes
reserved_block_coding_info() = extension(4) } }		NULL	
block_mask	v(6)	000001b	See below.
if (block_mask & 0x1) {			
b_sufficient_symbols_present	b(1)	1b (TRUE)	Sufficient symbols are present in the bitstream to decode. This value may be FALSE if the number of packet subatoms located at a source is less than 8.
if (!b_sufficient_symbols_present) {			
bsp_bits = num_bits_code()		NULL	
block_symbols_present }	u(bsp_bits)	NULL	

}
else
{			

/* Symbols present count not available */ }			
if (block_mask & 0x2) {			
block_field_size_exp }	v(3)	NULL	
else {			
/* GF{2^1}, block_field_size_exp_val=1 */ }			Block field size is GF{2}, `block_field_size_exp_val=1`.
if (block_mask & 0x4) {			
/* Coding coeff info in packet header subatoms */ }			Coding coefficient information is contained within each packet subatom.
if (block_mask & 0x8) {			Coding coefficient information is not encrypted.
block_cc_encryption_info_size_bits_code	v(1)	NULL	
byte_align	pad	NULL	
bcceis_bits = (block_cc_encryption_info_size_bits_code + 1) × 8			
block_cc_encryption_info_size	u(bcceis_bits)	NULL	
/* block encryption info start */			
reserved	v(1)	NULL	
block_cc_encryption_algorithm	v(3)	NULL	
block_cc_encryption_mode	v(4)	NULL	
block_cce_key_size_exp	u(4)	NULL	
bck_bits = 2^block_cce_key_size_exp			
block_cce_key	v(bck_bits)	NULL	
b_addl_block_cce_params_present	b(1)	NULL	
if (b_addl_block_cce_params_present) {			
addl_cce_parameters() }		NULL	
padding	pad	NULL	
/* block encryption info end */ }			
if (block_mask & 0x10) {			A block seed is not used.

Syntax	Encoding	Example Value	Notes

prng_parameters()
}
if (block_mask & 0x20)
{
block_integrity() = fb_integrity()
}
}
padding
 	
/* subatom data end */
}
	pad	NULL
		
		NULL
		
		00b
			
			Block integrity is not present.
			
			2 bits of padding are needed for byte alignment.

C.1.3.3 Encoder content information subatom construction

A subatom containing the encoder content information structure is shown in Table C.4.

Table C.4: Encoder content info subatom construction

Syntax	Encoding	Example Value	Notes

subatom()
{
/* subatom header start */
subatom_id
 	
if (subatom_id == 0xF){
subatom_id_ext
subatom_id = subatom_id + subatom_id_ext
}
 	
b_bitstream_id_present
 	
reserved
 	
sas_bits = num_bits_code()
 	
if (b_bitstream_id_present){
bitstream_id
 	
}
 	
subatom_size
 	
/* subatom header end */
	
	u(4)
	
	u(8)
	
	b(1)
	
	v(1)
	
	v(16)
	
	u(sas_bits)
		
		3
		
		NULL
		
		1b (TRUE)
		
		0b
		
		0
		
		35
			
			SUBATOM_ID_ENCODER_CONTENT_INFO
			
			While optional, the bitstream_id is defined for bitstream identification purposes.
			
			The subatom data size is indicated using 8 bits. 2 bits used within expansion of num_bits_code().
			
			bitstream_id was chosen to be 0 in this example. The bitstream_id field can be unique to each source to help differentiate between them if necessary.
			
			Number of bytes contained between /* subatom data start */ and /* subatom data end */.

/* subatom data start */ encoder_content_info() { **b_encoder_id_present** if (b_encoder_id_present) {	b(1)	1b (TRUE)	

Syntax	Encoding	Example Value	Notes
encoder_uuid	v(128)	0x 8a245264eb e144eba3bd 94db28b1af cb	Randomly generated UUID to represent the encoder that created this bitstream.
}			
b_content_id_present	b(1)	1b (TRUE)	Specifies Entertainment Identifier Registry (EIDR) to identify the content.
if (b_content_id_present)			
{			
content_id_type	v(4)	0x0	Specifies Entertainment Identifier Registry (EIDR) to identify the content.
content_id_size_minus1	u(8)	11	EIDR contains a 96-bit (12 byte) identifier. The value 11 is used because the field is encoded as minus 1.
content_id	v((content_id_size_minus1+1) × 8)	0x1478F85A E100B0685 B8FB1C8	Corresponds to an EIDR value of 10.5240/F85A-E100-B068-5B8F-B1C8-T.
}			
b_content_location_present	b(1)	0b (FALSE)	
if (b_content_location_present)			
{			
content_location_size_minus1	u(11)	NULL	
content_location	v((content_location_size_minus1+1)×8)	NULL	
}			
b_content_type_present	b(1)	0b (FALSE)	
if (b_content_type_present)			
{			
content_type_size	u(8)	NULL	
content_type	v(content_type_size×8)	NULL	
}			
b_content_header_present	b(1)	0b (FALSE)	
if (b_content_header_present)			
{			
content_header_size	u(7)	NULL	
content_header	v(content_header_size×8)	NULL	
}			
b_file_integrity_present	b(1)	0b	File integrity not present.
if (b_file_integrity_present)			
{			
file_integrity() = fb_integrity()		NULL	
}			
b_media_preso_dur_present	b(1)	1b (TRUE)	
if (b_media_preso_dur_present)			
{			
media_presentation_duration() = cmmf_time()			media_presentation_duration = 00:00:03:11.552.
{			
b_ddhhmmss_format	b(1)	1b (TRUE)	
if (b_ddhhmmss_format) {			
if (**b_dd_present**) (	b(1)	0b (FALSE)	
days	u(5)	NULL	
}			
if (**b_hh_present**) (	b(1)	0b (FALSE)	
hours	u(5)	NULL	
}			
if (**b_mm_present**) (	b(1)	1b (TRUE)	
minutes	u(6)	3	
}			

Syntax	Encoding	Example Value	Notes

`if (b_ss_present) (`
`  seconds`
`}`
`} else {`
`  is_bits = num_bits_code()`
`  int_seconds`
`}`
`b_fract_seconds_present`
`if (b_fract_seconds_present)`
`{`
`  fract_seconds_bits_code`
`  fs_bits = 10 × 2^fract_seconds_bits_code`
`  fract_seconds`
`}`
`}`
`}`
`reserved`
`}`
`padding`
`/* subatom data end */`
`}`
	b(1)
	u(6)
	
	u(is_bits)
	
	b(1)
	
	v(2)
	
	u(fs_bits)
	
	v(4)
	
	pad
		1b (TRUE)
		11
		
		NULL
		
		1b (TRUE)
		
		00b
		
		552
		
		0000b
		
		000b
			
			The `fract_seconds` field is indicated using 10 bits.
			
			3 bits of padding needed to ensure byte alignment.

C.1.3.4 Media segment information subatom construction

A subatom containing the media segment information structure is shown in Table C.5.

Table C.5: Media segment info subatom construction

Syntax	Encoding	Example Value	Notes

`subatom()`
`{`
`/* subatom header start */`
`subatom_id`
 	
`if (subatom_id == 0xF){`
`subatom_id_ext`
`subatom_id = subatom_id + subatom_id_ext`
`}`
 	
`b_bitstream_id_present`
 	
`reserved`
 	
`sas_bits = num_bits_code()`
 	
`if (b_bitstream_id_present){`
`bitstream_id`
 	
`}`
	
	u(4)
	
	u(8)
	
	b(1)
	
	v(1)
	
	v(16)
		
		4
		
		NULL
		
		1b (TRUE)
		
		0b
		
		0
			
			SUBATOM_ID_MEDIA_SEGMENT_INFO
			
			While optional, the `bitstream_id` is defined for bitstream identification purposes.
			
			The subatom data size is indicated using 8 bits. 2 bits are used in the expansion of num_bits_code().
			
			`bitstream_id` was chosen to be 0 in this example. The `bitstream_id` field can be unique to each source to help differentiate between them if necessary.

Syntax	Encoding	Example Value	Notes
subatom_size	u(sas_bits)	49	Number of bytes contained between `/* subatom data start */` and `/* subatom data end */`.
/* subatom header end */			
/* subatom data start */			
media_segment_info()			
{			
media_segment_block_index = block_index_or_count_value()		0	This media segment information pertains to the content in block 0. 8 bits were used in the expansion of `block_index_or_count_value()`.
reserved	v(4)	0000b	
b_composite_source_index_present	b(1)	0b	
if (b_composite_source_index_present)			
{			
media_segment_composite_source_index	u(8)	NULL	
}			
media_segment_index	u(2)	0	There is only one media segment present, its index is 0.
if (media_segment_index == 0x3)			
{			
media_segment_index_ext	u(6)	NULL	
media_segment_index = media_segment_index + media_segment_index_ext			
}			
if (**b_asset_name_present**)	b(1)	1b (TRUE)	
{			
asset_name_size	u(8)	36	
for (i = 0; i < asset_name_size; i++)			
{			
asset_name[i]	v(36)	repousse_180p_100kb/Number03d001.m4s	
}			
}			
segment_tag_mask	v(4)	1100b	
if (segment_tag_mask & 0x1)			
{			
segment_duration() = cmmf_time()		NULL	
}			
if (segment_tag_mask & 0x2)			
{			
segment_start_time() = cmmf_time()		NULL	
}			
if (segment_tag_mask & 0x4)			
{			
segidx_bits = num_bits_code()			The `segment_index` field is indicated using 8 bits. 2 bits were used in the expansion of `num_bits_code()`.
segment_index	u(segidx_bits)	1	Index of this segment.
}			
if (segment_tag_mask & 0x8)			
{			

Syntax	Encoding	Example Value	Notes
segcnt_bits = num_bits_code()			The segment_count field is indicated using 8 bits. 2 bits were used in the expansion of num_bits_code().
segment_count	u(segcnt_bits)	79	Number of segments in this program.
}			
if (**b_media_mime_type_present**) {	b(1)	0b (FALSE)	
media_mime_type_size	u(6)	NULL	
for (i = 0; i < media_mime_type_size; i++) {			
media_mime_type[i]	v(8)	NULL	
}			
}			
if (**b_media_codec_present**) {	b(1)	0b (FALSE)	
media_codec_size	u(6)	NULL	
for (i = 0; i < media_codec_size; i++) {			
media_codec[i]	v(8)	NULL	
}			
}			
if (**b_bit_rate_present**) {	b(1)	0b (FALSE)	
bit_rate_bits_code	v(1)	NULL	
bps_bits = (bit_rate_bits_code + 3) × 8			
bit_rate	u(bps_bits)	NULL	
}			
if (**b_ms_content_type_present**) {	b(1)	1b (TRUE)	
ms_content_type	v(3)	0x0	The content type of video.
b_ms_content_type_info_present	b(1)	1b (TRUE)	
}			
else			
{			
/* b_ms_content_type_info_present = 0b */			
}			
if (b_ms_content_type_info_present) {			
switch (ms_content_type) {			
case 0x0:			
if (**b_aspect_ratio_present**) {	b(1)	0b (FALSE)	
sample_aspect_ratio	u(8)	NULL	
if (sample_aspect_ratio == 255) {			
sar_width	u(8)	NULL	
sar_height	u(8)	NULL	
}			
}			
b_dynamic_resolution_video	b(1)	0b (FALSE)	
if (**b_resolution_present**) {	b(1)	NULL	
resolution_width	u(16)	NULL	
resolution_height	u(16)	NULL	
}			
if (**b_frame_rate_present**) {	b(1)	1b (TRUE)	
frame_rate	v(5)	4	This video is at 30 frames per second.
}			
reserved	v(4)	0000b	

Syntax	Encoding	Example Value	Notes
if (**b_hdr_info_present**) {	b(1)	0b (FALSE)	
hdr_compatibility_mask	v(16)	NULL	
if (**b_addl_hdr_info_present**) {	b(1)	0b (FALSE)	
hdr_compat_mask_index	u(4)	NULL	
hdr_profile	u(8)	NULL	
hdr_level	u(8)	NULL	
hdr_compatibility_id	u(8)	NULL	
}			
}			
if (**b_addl_video_info_present**) {	b(1)	0b (FALSE)	
addl_video_info = extension(4)		NULL	
}			
break			
case 0x1:			
if (**b_sampling_freq_present**) {	b(1)	NULL	
b_sampling_freq_is_48k	b(1)	NULL	
if (!b_audio_fs_is_48k) {			
sampling_frequency	v(4)	NULL	
}			
}			
if (**b_audio_config_present**) {	b(1)	NULL	
audio_channel_config	v(24)	NULL	
}			
if (**b_audio_props_present**) {	b(1)	NULL	
reserved	v(1)	NULL	
b_virtualized_bin	b(1)	NULL	
reserved	v(2)	NULL	
b_object_audio	b(1)	NULL	
if (**b_complexity_index_present**) {	b(1)	NULL	
complexity_index	u(8)	NULL	
}			
}			
if (**b_addl_audio_info_present**) {	b(1)	NULL	
addl_audio_info = extension(4)		NULL	
}			
break			
default:			
if (**b_addl_ms_content_type_info_present**) {	b(1)	NULL	
addl_ms_content_type_info() = extension(6)		NULL	
}			
}			
}			
accessibility_mask	v(4)	0001b	
if (accessibility_mask & 0x1) {			
language_size	u(6)	2	
for (i = 0; i < language_size; i++) {			

Syntax	Encoding	Example Value	Notes

language[i]
}
}
if (accessibility_mask & 0x2) {
reserved
}
if (accessibility_mask & 0x4) {
reserved
}
if (accessibility_mask & 0x8) {
addl_accessibility_info() = extension(4)
}
}
padding
/* subatom data end */
}
	v(8)
	
	v(3)
	
	v(4)
	
	pad
		en
		
		NULL
		
		NULL
		
		NULL
		
		0000000b
			Language is 'en' for English as specified in ISO 639 [4].
			
			Seven bits of padding needed to ensure byte alignment.

C.1.3.5 Packet subatom construction - systematic symbol

A subatom containing the packet structure for a systematic packet is shown in Table C.6.

Table C.6: Packet subatom - systematic packet construction

Syntax	Encoding	Example Value	Notes

subatom()
{
/* subatom header start */
subatom_id
if (subatom_id == 0xF){
subatom_id_ext
subatom_id = subatom_id + subatom_id_ext
}
 	
b_bitstream_id_present
 	
reserved
 	
sas_bits = num_bits_code()
 	
if (b_bitstream_id_present){
bitstream_id
 	
}
 	
subatom_size
 	
/* subatom header end */
/* subatom data start */
packet()
	
	u(4)
	
	u(8)
	
	b(1)
	
	v(1)
	
	v(16)
	
	u(sas_bits)
		
		6
		
		NULL
		
		1b (TRUE)
		
		0b
		
		0
		
		250 003
			
			SUBATOM_ID_PACKET
			
			While optional, the bitstream_id is defined for bitstream identification purposes.
			
			The subatom data size is indicated using 24 bits.
			
			bitstream_id was chosen to be 0 in this example. The bitstream_id field can be unique to each source to help differentiate between them if necessary.
			
			Number of bytes contained between /* subatom data start */ and /* subatom_data_end */.

Syntax	Encoding	Example Value	Notes
{			
if (block_count > 1)			
{			
packet_block_index = block_index_or_count_value()		NULL	
}			
else			
{			
packet_block_index = 0			The packet is associated with block 0.
}			
packet_header()			
{			
b_systematic_symbol	b(1)	1b (TRUE)	This packet subatom contains a systematic symbol.
packet_mask	v(7)	0000001b	See below.
if (packet_mask & 0x1)			
{			
psi_bits = num_bits_code()			The packet_symbol_index field is indicated using 8 bits. 2 bits were used in the expansion of num_bits_code().
packet_symbol_index	u(psi_bits)	0	The systematic packet corresponds to original symbol index 0, i.e. the first source symbol.
}			
if (packet_mask & 0x2)			Coding coefficient information is not encrypted.
{			
if (b_systematic_symbol)			
{			
b_systematic_symbol_encrypted	b(1)	NULL	
} else {			
reserved	v(1)	NULL	
}			
b_addl_packet_cce_params_present	b(1)	NULL	
if (b_addl_packet_cce_params_present)			
{			
addl_cce_parameters()		NULL	
}			
}			
if (block_mask & 0x4) {			Window boundaries are not defined.
window_start_index	u(16)	NULL	
window_stop_index	u(16)	NULL	
window_size = (window_stop_index - window_start_index + 1) % 65 536			
} else {			
window_size = block_num_symbols			
}			
if (packet_mask & 0x8) {			PRNG seed is not defined for systematic packets.
prng_parameters()		NULL	
}			
if (packet_mask & 0x10) {			Coefficient vectors are not defined for systematic packets.
coefficient_vector(window_size, block_field_size_exp_val)		NULL	
}			
if (packet_mask & 0x20) {			Packet integrity not present.
packet_integrity()		NULL	

Syntax	Encoding	Example Value	Notes

}
if (packet_mask & 0x40){
packet_header_extension() = extension(5)
}
byte_align
}
coded_symbol
}
padding
/* subatom data end */
}
	pad
	v(css_bits)
	pad
		NULL
		000000b
		NULL
			Packet header extension is not present.
			6 bits are necessary for byte alignment.
			Coded symbol size = 250 000 bytes.
			Padding not necessary to ensure byte alignment.

C.1.3.6 Packet subatom construction - coded symbol

A subatom containing the packet structure for a coded packet is shown in Table C.7.

Table C.7: Packet subatom - coded packet construction

Syntax	Encoding	Example Value	Notes

subatom()
{
/* subatom header start */
subatom_id
if (subatom_id == 0xF){
subatom_id_ext
subatom_id = subatom_id + subatom_id_ext
}
b_bitstream_id_present
reserved
sas_bits = num_bits_code()
if (b_bitstream_id_present){
bitstream_id
}
subatom_size
/* subatom header end */
	u(4)
	u(8)
	b(1)
	v(1)
	v(16)
	u(sas_bits)
		6
		NULL
		1b (TRUE)
		0b
		0
		250 002
			SUBATOM_ID_PACKET
			While optional, the bitstream_id is defined for bitstream identification purposes.
			The subatom data size is indicated using 24 bits.
			bitstream_id was chosen to be 0 in this example. The bitstream_id field can be unique to each source to help differentiate between them if necessary.
			Number of bytes contained between /* subatom data start */ and /* subatom_data_end */.

/* subatom data start */
packet()
{
if (block_count > 1)
{
packet_block_index =
block_index_or_count_value()
}
else
		NULL	

Syntax	Encoding	Example Value	Notes
{			
packet_block_index = 0			The packet is associated with block 0.
}			
packet_header()			
{			
b_systematic_symbol	b(1)	0b (FALSE)	
packet_mask	v(7)	0010000b	This packet subatom contains a coded symbol.
if (packet_mask & 0x1)			The pscket_symbol_index is not defined for this packet subatom.
{			
psi_bits = num_bits_code()			
packet_symbol_index	u(psi_bits)	NULL	
}			
if (packet_mask & 0x2)			Coding coefficient information is not encrypted.
{			
if (b_systematic_symbol)			
{			
b_systematic_symbol_encrypted	b(1)	NULL	
} else {			
reserved	v(1)	NULL	
}			
b_addl_packet_cce_params_present	b(1)	NULL	
if (b_addl_packet_cce_params_present)			
{			
addl_cce_parameters()		NULL	
}			
}			
if (block_mask & 0x4) {			Window boundaries are not defined.
window_start_index	u(16)	NULL	
window_stop_index	u(16)	NULL	
window_size = (window_stop_index - window_start_index + 1) % 65 536			
} else {			
window_size = block_num_symbols			
}			
if (packet_mask & 0x8) {			PRNG seed is not defined.
prng_parameters()			
}			
if (packet_mask & 0x10) {			
coefficient_vector(window_size, block_field_size_exp_val)		10110101b	Coefficient vector containing 8 coefficients (one for each original source symbol) where each coefficient is 1 bit.
}			
if (packet_mask & 0x20) {			Packet integrity not present.
packet_integrity()			
}			
if (packet_mask & 0x40){			
packet_header_extension() = extension(5)			Packet header extension is not present.
}			
byte_align	pad	NULL	No bits are required for byte alignment.
}			
coded_symbol	v(css_bits)	coded symbol data	Coded symbol size = 250 000 bytes.
}			
padding	pad	NULL	Padding not necessary to ensure byte alignment.
/* subatom data end */			

Syntax	Encoding	Example Value	Notes
}			

C.2 Encrypted coding coefficient information example using CMMF

The CMMF bitstream supports encryption of coding coefficient information. Following the example described in clause 7.3.1, Figure C.3 shows field values in the bitstream header, block header, and packet subatoms. Fields within the bitstream (such as the `block_cce_key`) and other information (such as the `bitstream_key`) that are encrypted are highlighted within a hatched box.

Figure C.3 also shows the communication between the application and the key management system to obtain the `bitstream_key`. The daisy-chain process of using the `bitstream_key` to decrypt the block encryption parameters in the block header subatom, which are in turn used to decrypt the encrypted coefficient vector within the packet subatom, is also shown.




Figure C.3: Bitstream with example encrypted coding coefficient information

Annex D (normative): Content Delivery Protocol instantiations

D.0 Introduction

This annex defines Content Delivery Protocol (CDP) instantiations for delivering content using CMMF as specified in clauses 5 and 6. A mapping of CMMF to IETF RFC 5052 [15] CDP principles is provided in clause D.1, a CDP instantiation using a File Delivery Table (FDT) is specified in clause D.2, and a CDP instantiation that uses URL translation to map between source objects and CMMF Transport Objects is specified in clause D.3.

D.1 General principles of CMMF Content Delivery Protocols based on FEC Building Block

D.1.1 Introduction

CMMF as introduced in the principles in clause 4, the bitstream syntax in clause 5, as well as the bitstream semantics in clause 6 can be, but not exclusively, considered as a CDP specification as defined in section 8 of IETF RFC 5052 [15]. This clause provides a mapping of CMMF to the IETF RFC 5052 [15] principles and vice versa and apply when the `b_rfc5052` flag is set to TRUE.

D.1.2 FEC Building Block principles

CMMF provides means to generate coded/repair objects and coded/repair object transport sessions as introduced in clause 4.3.2 of the present document. In one example instantiation, the CMMF repair framework is based on an existing Forward Error Correction (FEC) Building Block as defined in IETF RFC 5052 [15], where CMMF can be considered as a CDP specification as defined in section 8 of IETF RFC 5052 [15].

In the definition of the protocol, terminology defined in section 2 of IETF RFC 5052 [15], is used in this clause. Specifically, the terms for Object, Symbol, Source Symbol, Repair symbol, Encoding symbol, Encoder, Decoder, Receiver, Sender, and FEC Scheme are used in this clause.

IETF RFC 5052 [15] provides the definition and transport of three kinds of information from sender to receiver(s):

- encoding symbols (referred to as coded/repair symbols in the general context of CMMF) themselves;
- ancillary information associated with encoding symbols (or groups of such symbols), such as the group of symbols in a source or repair object; and
- ancillary information associated with the whole object being transferred.

In addition, for FEC the following information is defined and provided in IETF RFC 5052 [15]:

- FEC information associated with an object, referred to as *FEC Object Transmission Information (OTI)*. This includes for example the FEC Encoding ID that identifies the FEC scheme and is an integer assigned by IANA, the transfer length of the object or the encoding symbol length. For details refer to section 6.2 of IETF RFC 5052 [15].
- FEC information associated with specific encoding symbols for an object, referred to as *FEC Payload ID*. This information indicates how the associated repair symbols were constructed from the object. The semantics and encoding format of the FEC Payload ID, including its size, is defined by the FEC Scheme. CDPs specify how the FEC Payload ID is carried in the respective framework. For details, refer to section 6.3 of IETF RFC 5052 [15].

D.1.3 FEC Schemes and related information

IETF RFC 5052 [15] includes the concept of an *FEC Scheme*, this concept is different from the concept of an *FEC code* or *FEC algorithm*. An FEC scheme defines the ancillary information and procedures which, combined with an FEC code or algorithm specification, fully define how the FEC code can be used with CDPs. Requirements for FEC scheme specifications are defined in section 7 of IETF RFC 5052 [15].

CMMF, when used as a CDP, only permits the use of fully specified FEC schemes. For each FEC Scheme, the type, semantics, and an encoding format for the FEC Payload ID and the FEC Object Transmission Information (OTI) are defined.

The FEC OTI contains information which is essential to the decoder in order to decode the coded/repair object. Common FEC OTI elements for fully-specified FEC schemes are defined in section 6.2.4 of IETF RFC 5052 [15], and include: `Transfer-Length`, `Encoding-Symbol-Length`, `Maximum-Source-Block-Length`, and `Max-Number-of-Encoding-Symbols`.

In addition to common information, scheme-specific FEC OTI element may be used by an FEC Scheme to communicate information that is essential to the decoder and that cannot adequately be represented within the FEC OTI elements. The FEC Scheme defines the structure of this octet string, which may contain multiple distinct elements.

FEC schemes are identified by an *FEC Encoding ID*, which is an integer identifier assigned by IANA [i.8].

The *FEC Payload ID* contains information that indicates to the FEC decoder the relationships between the encoding symbols carried by a particular packet. For example, if packet subatom carries a source symbol, then the FEC Payload ID identifies which source symbol of the object are carried by the packet.

The FEC Payload ID may also contain information about larger groups of encoding symbols of which those contained in the packet (or packet group) are part of. For example, the FEC Payload ID may contain information about the source block the symbols are related to.

D.1.4 FEC Scheme information in CMMF

CDPs are required to provide a mechanism to transport the FEC Encoding ID, FEC Payload ID, common FEC OTI, and scheme-specific information defined by the FEC scheme. CMMF carries this information within the bitstream syntax defined in clauses 5 and 6 of the present document. Primarily this information is carried within the `rfc5052_information()` structure present when `b_rfc5052` is TRUE. The Payload ID information is defined as part of the `packet_header()`, `packet_group_header()`, and `mbpg_header()` structures that are part of packet, packet group, and multiple block packet groups respectively.

NOTE: FEC Schemes define a binary representation of the parameters, but for example the FDT-based Content Delivery Protocol in IETF RFC 6726 [18] (as instantiated in clause D.2 of the present document) specifies an XML-based encoding format for these elements to be used during delivery. The present document permits the use of the following fully specified FEC schemes when CMMF is used as a CDP (i.e. when `b_rfc5052` is TRUE):

- Raptor Forward Error Correction Scheme as defined in IETF RFC 5053 [16].
- RaptorQ Forward Error Correction Scheme as defined in IETF RFC 6330 [13].
- Reed-Solomon Forward Error Correction (FEC) with the special case of Reed-Solomon codes over GF{2^8} as defined in IETF RFC 5510 [14].

The parameters and coding size for the FEC scheme are provided in Table D.1. This table also describes how to map the FEC scheme information to CMMF bitstream elements.

Table D.1: Parameters and Coding of FEC schemes used in CMMF

Parameter	IETF RFC 5053 [16] (Raptor)	IETF RFC 6330 [13] (RaptorQ)	IETF RFC 5510 [14] (Reed-Solomon GF{2^8})
FEC Encoding ID value	1 (see section 3.2.1)	6 (see section 3.3.1)	5 (see section 5)
FEC Payload ID size	4 bytes (see section 3.1)	4 bytes (see section 3.2)	4 bytes (see section 5.1)
Source Block Number (SBN) size	16 bits	8 bits	24 bits
Encoding Symbol ID (ESI) size	16 bits	24 bits	8 bits
Maximum Transfer Length	2^{45} bytes (i.e. 32 terabytes)	2^{40} bytes (i.e. 1 terabyte)	2^{42} bytes (i.e. 4 terabytes)
Maximum Source Block size	8192	56403	255
FEC Object Transmission Information (FEC-OTI) Common	10 bytes (see section 3.2.2)	8 bytes (see section 3.3.2)	10 bytes (see section 5.2.4.1)
Transfer-Length size F	48 bits	40 bits	48 bits
Reserved	16 bits	8 bits	
Encoding-Symbol-Length T size	16 bits	16 bits	16 bits
Maximum Source Block Length size	Not applicable	Not applicable	8 bits
maximum number of encoding symbols max_n size	Not applicable	Not applicable	8 bits
FEC Object Transmission Information (FEC-OTI) Specific	4 bytes (see section 3.2.3)	4 bytes (see section 3.3.3)	See section 5.2.3
number of source blocks (Z)	16 bits	8 bits	Not applicable
number of sub-blocks (N)	8 bits	16 bits	Not applicable
symbol alignment parameter (Al)	8 bits	8 bits	Not applicable
FEC Object Transmission Information (FEC-OTI) size	14 bytes	12 bytes	10 bytes

The mapping from the FEC scheme parameters to CMMF bitstream elements/fields are provided in Table D.2. This table also describes how to map the FEC scheme information to CMMF bitstream elements.

Table D.2: FEC scheme parameters to CMMF mapping

Parameter	CMMF Bitstream Parameter	Mapping Function	Relevant clause(s)
FEC Encoding ID	`code_type` in `bitstream_header()`	`code_type` = FEC Encoding ID	6.1.4
FEC Payload ID			
Source Block Number (SBN)	Either `packet_block_index` in `packet()`, `packet_group_block_index` in `packet_group()`, or `mbpg_source_block_index` in `mbpg_header()`	packet_block_index = SBN, packet_group_block_index = SBN, or mbpg_source_block_index = SBN	6.1.6.1, 6.1.18.1, 6.1.23.3
Encoding Symbol ID (ESI)	Either `packet_symbol_index` in `packet_header()`, `packet_group_symbol_index` in `packet_group_header()`, or `mbpg_symbol_index` in `mbpg_header()`	packet_symbol_index = ESI, packet_group_symbol_index = ESI, mbpg_symbol_index = ESI	6.1.7.4, 6.1.19.4, 6.1.23.3
FEC Object Transmission Information (FEC-OTI) Common			
Transfer-Length size F	`content_source_size` in `bitstream_header()` (assuming source itself has not been coded	content_source_size = F transfer_length = F	6.1.4.1, 6.1.4.6
Reserved	--	--	--
Encoding-Symbol-Length T	`block_symbol_size` in `block_header()` `encoding_symbol_length` in `rfc5052_information()`	block_symbol_size = T	6.1.5.3, 6.1.4.6

Parameter	CMMF Bitstream Parameter	Mapping Function	Relevant clause(s)
Maximum Source Block Length (B)	`block_num_symbols` in `block_header()`	block_num_symbols = B	6.1.5.5
maximum number of encoding symbols (max_ns)	There is no equivalent for this parameter in CMMF. However a related parameter is `block_max_symbol_index` in `block_header()`	block_max_symbol_index = max_ns - 1	6.1.5.8

The present document does not define a complete binary representation of the FEC-OTI information, but a receiver, based on the information in Table D.1 and Table D.2 may reconstruct the FEC-OTI information in binary form for each FEC scheme.

D.1.5 Configuration Information parameters

The Configuration Information allows the CMMF client to map an application request to CMMF receiver operations. Table D.3 provides examples of possible Configuration Information that can be used where source and coded/repair transport objects are described. Some use cases may require additional information or only a subset of this information, and a simpler version of this parameter set may be used.

Table D.3: Example Configuration Information parameters

Parameter	Usage	Definition
Complete	OD	Indicates whether the Configuration Information is complete.
Location	O	Provides information where the Configuration Information can be accessed in carried externally.
Expires	M	Provides information when this Configuration Information is no longer valid and an update is needed, for example using a reload from Location.
Source Flow	1 … S	Provides 1 … S source flows.
TSI	M	Identifier of the source flow.
Object	1 … N	Provides 1 … N objects in the source flow.
TOI	M	Transport Object Identifier (TOI) value that represents the source object.
Size	M	Size of the transmission object in bytes.
Content-Type		Describes media type of file.
Encoding		Describes encoding of file, for example whether the file is zipped prior to transfer.
Message Digest		Message digest of file.
Associated URI		Name, Identification, and Location of file (specified by the URI).
Access URL		The URL where the source object can be accessed. If the field is not present, then the source flow is not directly accessible.
availabilityStartTime		Provides a wall-clock time when the resource is accessible.
availabilityStartTime		Provides a wall-clock time when the resource ceases to be available.
<Additional metadata>		May include cache or entity tag (E-Tag) metadata.
Representation		Refers to a DASH Representation in an MPD or a Track in an HLS manifest.
Coded/Repair Flow	1 … R	Provides 1 … R coded/repair flows.
TSI	M	Identifier of the coded/repair flow.
Object	1 … N	Provides 1 … N objects in the coded/repair flow.
TOI	M	Transport Object Identifier (TOI) value that represents the coded/repair object.
FEC-OTI		If object is coded using a scheme based on IETF RFC 5052 [15], FEC Object transmission information including the FEC Encoding ID and, if relevant, the FEC Instance ID.
includedSourceTOI	M	List of (TSI, TOI pairs) of the included source transport objects forming an aggregated object. Typically, only a single pair is provided.
Content-Type		Media Mime Type of the file.
completeObject	OD FALSE	Indicates whether the transport object includes sufficient information to recover all files included in this coded/repair object.

Parameter				Usage	Definition
			symbolArrangement	O	Provide this symbol arrangement in the object according to Table 78. If not present, the symbol Arrangement is unknown and only present in the bitstream.
			sAParameters	O	may be present if the symbolArrangement is present. If present, it provides the parameters assigned to the symbol arrangement as defined in Table 36. For arrangement 2 and 3, this is a comma-separated list of: • Index difference • Symbol group • Index in symbol group
			Access URLs	1, …, N	The URLs where the coded/repair object can be accessed.
			availabilityStartTime	OD	Provides a wall-clock time, when the resource is accessible. If not present, it is assumed that the resource is accessible during the validity time of the Configuration Information.
			availabilityEndTime	OD	Provides a wall-clock time, when the resource ceases to be available. If not present, it is assumed that the resource is accessible during the validity time of the Configuration Information.
			<Additional metadata>		Additional metadata may be present for example caching information, processing information, etc.
Usage M: Mandatory parameter O: Optional parameter OD: Optional parameter, if not set default value applies A, …, B: between A times (typically 0 or 1) and B times (typically 1 or N) parameters may be present					

D.1.6 Example CDP instantiations

Based on FEC schemes and FEC framework defined in the IETF, an instantiation for CMMF when being used as a CDP may provide the following information:

- The definition of a Delivery Session.
- An instantiation of the Configuration Information (CI), with related information and a delivery documents.
- The definition of source objects.
- The definition of coded/repair objects based on the bitstream format defined in clause 5.

D.2 FDT-based CDP Instantiation

D.2.1 Introduction

This clause defines an instantiation of the FEC Building Block CDP framework for CMMF based on the File Delivery Table (FDT) specified in section 3.4.2 of IETF RFC 6726 [18]. The CDP instantiation is aligned with IETF RFC 5052 [15], and reuses some of the extensions and concepts defined ETSI TS 126 346 [19], namely the FDT extensions.

The *FDT-based CDP instantiation* is defined as follows:

- Typical procedures for an FDT-based *CDP instantiation* are provided in clause D.2.2.
- The Configuration Information can be expressed as a File Delivery Table (FDT) as defined in IETF RFC 6726 [18] with minimum extensions to support CMMF, referred to as Extended FDT (EFDT). The EFDT is a document containing one instance. For details refer to clause D.2.3.

- The delivery session is a single Transport Session, and different coded/repair objects may be generated. Each transport object is identified by a unique Transport Object Identifier (TOI).
- Source objects may be distributed within a transport session.
- The coded/repair objects are compatible with CMMF Bitstream as defined in clause 6 (where the `b_rfc5052` field is set to TRUE), but also with ALC Payload formats as defined in IETF RFC 5775 [17] with some additional headers as documented in clause D.2.4.
- Only a single object is associated with a TOI.
- Only the fully specified FEC schemes listed in clause D.1.4 are allowed, i.e. the FEC Encoding ID shall either be set to 1 (Raptor), 5 (Read-Solomon over GF{2^8}), or 6 (RaptorQ).

D.2.2 Procedures for FDT-based CDP instantiation

A baseline procedure describing the establishment of an FDT-based CDP transport session is shown in Figure D.1.




Figure D.1: High-level procedure for CMMF delivery using FDT-based CDP

Prerequisites:

1) The CMMF Application Provider has provisioned the CMMF Sender and has set up content ingest to provide source objects. The CMMF Sender uses the source object to generate transport objects and the EFDT.
2) The CMMF Sender provides the EFDT URL to the Application provider.
3) The CMMF-Aware Application triggers Application Information and Content Discovery procedure. The Application information includes a URL to the EFDT.

Steps:

4) Content is selected.

5) The CMMF-aware Application triggers the CMMF receiver to start the accessing content. The Configuration Information location is provided to the CMMF Receiver.

6) The CMMF Receiver interacts with the CMMF Sender to acquire the Configuration Information.

7) The CMMF Receiver establishes the transport session with the CMMF Sender.

8) The CMMF Receiver sends requests for downloading partial or complete transport objects.

9) The CMMF Receiver receives the partial transport objects and uses those for recovery, when sufficient data is available.

10) The CMMF Receiver recovers source objects together with metadata.

11) The CMMF Receiver notifies the CMMF-Aware application on available source objects and the application access those at appropriate time based on the associated metadata.

12) The CMMF Receiver continuously receives additional transport objects, if not yet complete, based on the EFDT and updated instances of the EFDT.

D.2.3 Extended File Delivery Table

D.2.3.1 Semantics

In order to provide relevant Configuration Information to the CMMF receiver a document including an extended File Delivery Table (EFDT) is created to signal Configuration Information to the receiver as follows:

- The attributes and elements from the File Delivery Table in IETF RFC 6726 [18], section 3.2, are re-used as follows:
  - The `Expires` attribute expresses the validity of the EFDT instance, i.e. how long the binding is valid.
  - The `Complete` attribute, when `TRUE`, signals that this "EFDT Instance" includes the set of "File" entries that exhausts both the set of files delivered so far and the set of files to be provided in the session.
  - The following data may be set as default on instance level, or may set on file level. If set on file level, the instance level information is overwritten:
    - The `Content-Type` attribute is included to express the type of the delivered file according to IETF RFC 9110 [24].
    - The `Content-Encoding` attribute is included to express the encoding of the delivered file. For details refer to IETF RFC 6726 [18].
    - The `FEC-OTI-FEC-Encoding-ID` attribute provides the "FEC Encoding ID" Object Transmission Information element defined in IETF RFC 5052 [15].
    - The `FEC-OTI-Maximum-Source-Block-Length` attribute provides the "Maximum-Source-Block-Length" Object Transmission Information element defined in IETF RFC 5052 [15], if required by the FEC Scheme.
    - The `FEC-OTI-Max-Number-of-Encoding-Symbols` attribute provides the "Max-Number-of-Encoding-Symbols" Object Transmission Information element defined in IETF RFC 5052 [15], if required by the FEC Scheme.
  - The `TOI` value is a positive integer to express the Transport Object Identifier and identify the object.
  - The attribute `Content-Location` is used for the purpose defined in IETF RFC 9110 [24].
  - The attribute `Content-Length` is used for the purpose defined in IETF RFC 9110 [24].

- The attribute `Transfer-Length` is used to carry the transfer length if the file is content encoded before transport (and thus the "Content-Encoding" attribute is used), e.g. if compression is applied before transport to reduce the number of octets that need to be transferred, then the transfer length is generally different.
- The `Content-MD5` attribute is used for the purpose defined in IETF RFC 2616 [i.4].

- The following new elements and attributes are defined in order access the content:
  - A list of access objects assigned to a File, each defined by:
    - An `access-URL` where the object associated to the TOI can be accessed.
    - A `type` attribute that provides the type of the transport object, whether it is a source object or if it is an object according to the bitstream syntax of CMMF.
    - If the type is a CMMF bitstream, then an attribute `symbolArrangement` may be added and the value is set according to Table 78. If not present, the symbol Arrangement is unknown and only present in the bitstream. For details see the semantics in clause D.2.4.3.
    - If the type is a CMMF bitstream and attribute `symbolArrangement` is set to 2 or 3, the following information may be added as a comma-separated list:
      - the total amount of symbol groups, *C*.
      - the included symbol group, *c*.
      - the index of the first symbol of the symbol group.
    - An attribute `complete` if set to TRUE, the file includes sufficient information to recover the source object included in this transport object.
    - An availability time window expressed by a an `availabilityStartTime` and an `availabilityEndTime` attribute indicating when the URL is available. If not present, it is assumed that the objects are present at the time when accessing the EFDT until the Expires time of the EFDT.

D.2.3.2 Extended FDT Schema for CMMF

An extended FDT schema is provided in Listing D.1.

An informative copy of the XML Schema Definition with filename `cmmf_extended_fdt_schmea.xml` is included in archive ts_103973v010201p0.zip which accompanies the present document.

Listing D.1: Extended FDT schema for CMMF

```
<?xml version="1.0" encoding="UTF-8"?>
<xs:schema
 xmlns="urn:ETSI:CMMF:2023:EFD"
           xmlns:xs="http://www.w3.org/2001/XMLSchema"
           targetNamespace="urn:ETSI:CMMF:2023:EFD"
           elementFormDefault="qualified"
           version="1">
   <xs:element name="FDT-Instance" type="FDT-InstanceType"/>
   <xs:complexType name="FDT-InstanceType">
      <xs:sequence>
         <xs:element name="File" type="FileType" maxOccurs="unbounded"/>
         <xs:element name="schemaVersion" type="xs:unsignedInt"/>
         <xs:element name="delimiter" type="DelimiterType"/>
         <xs:any namespace="##other" processContents="skip" minOccurs="0" maxOccurs="unbounded"/>
      </xs:sequence>
      <xs:attribute name="Expires" type="xs:dateTime" use="required"/>
      <xs:attribute name="Complete" type="xs:boolean" use="optional"/>
      <xs:attribute name="Content-Type" type="xs:string" use="optional"/>
      <xs:attribute name="Content-Encoding" type="xs:string" use="optional"/>
      <xs:attribute name="FEC-OTI-FEC-Encoding-ID" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="FEC-OTI-FEC-Instance-ID" type="xs:unsignedLong" use="optional"/>
```

```
      <xs:attribute name="FEC-OTI-Maximum-Source-Block-Length" type="xs:unsignedLong"
use="optional"/>
      <xs:attribute name="FEC-OTI-Encoding-Symbol-Length" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="FEC-OTI-Max-Number-of-Encoding-Symbols" type="xs:unsignedLong"
use="optional"/>
      <xs:attribute name="FEC-OTI-Scheme-Specific-Info" type="xs:base64Binary" use="optional"/>
      <xs:anyAttribute processContents="skip"/>
   </xs:complexType>
   <xs:complexType name="FileType">
      <xs:sequence>
         <xs:element name="EncodedObjects" type="EncodedObjectType" minOccurs="1"
maxOccurs="unbounded"/>
         <xs:element name="delimiter" type="DelimiterType"/>
         <xs:any namespace="##other" processContents="skip" minOccurs="0" maxOccurs="unbounded"/>
      </xs:sequence>
      <xs:attribute name="Content-Location" type="xs:anyURI" use="required"/>
      <xs:attribute name="TOI" type="xs:positiveInteger" use="required"/>
      <xs:attribute name="Content-Length" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="Transfer-Length" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="Content-Type" type="xs:string" use="optional"/>
      <xs:attribute name="Content-Encoding" type="xs:string" use="optional"/>
      <xs:attribute name="Content-MD5" type="xs:base64Binary" use="optional"/>
      <xs:attribute name="FEC-OTI-FEC-Encoding-ID" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="FEC-OTI-FEC-Instance-ID" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="FEC-OTI-Maximum-Source-Block-Length" type="xs:unsignedLong"
use="optional"/>
      <xs:attribute name="FEC-OTI-Encoding-Symbol-Length" type="xs:unsignedLong" use="optional"/>
      <xs:attribute name="FEC-OTI-Max-Number-of-Encoding-Symbols" type="xs:unsignedLong"
use="optional"/>
      <xs:attribute name="FEC-OTI-Scheme-Specific-Info" type="xs:base64Binary" use="optional"/>
      <xs:anyAttribute processContents="skip"/>
   </xs:complexType>
   <xs:complexType name="EncodedObjectType">
      <xs:simpleContent>
         <xs:extension base="xs:anyURI">
            <xs:attribute name="symbolArrangement" type="interleavingType"/>
            <xs:attribute name="sAParameters" type="xs:string"/>
            <xs:attribute name="objectType" type="ObjectTypeType" default="source"/>
            <xs:attribute name="complete" type="xs:boolean" default="false"/>
            <xs:attribute name="availabilityStartTime" type="xs:dateTime"/>
            <xs:attribute name="availabilityEndTime" type="xs:dateTime"/>
            <xs:anyAttribute namespace="##other" processContents="skip"/>
         </xs:extension>
      </xs:simpleContent>
      <xs:anyAttribute processContents="skip"/>
   </xs:complexType>
   <xs:simpleType name="DelimiterType">
      <xs:restriction base="xs:byte"/>
   </xs:simpleType>
   <xs:simpleType name="ObjectTypeType">
      <xs:restriction base="xs:string">
         <xs:enumeration value="source"/>
         <xs:enumeration value="cmmf"/>
      </xs:restriction>
   </xs:simpleType>
   <xs:simpleType name="interleavingType">
      <xs:restriction base="xs:unsignedLong">
         <xs:enumeration value="0"/>
         <xs:enumeration value="1"/>
         <xs:enumeration value="2"/>
         <xs:enumeration value="3"/>
      </xs:restriction>
   </xs:simpleType>
</xs:schema>
```

D.2.3.3 Extended FDT Description for CMMF

The Extended FDT Description (EFD) is a document that contains metadata required by a CMMF Client/CMMF-Aware application to access Objects and to provide the CMMF session. The EFD is an XML document that shall be formatted according to the XML schema provided in clause D.2.3.2.

The EFD shall be authored in such a way that after removing any XML attributes or elements that are not part of the specified XML schema (documented in clause D.2.3.2), the remaining document should still be a valid XML document that conforms to the schema and the present document. Additionally, if all XML attributes and elements from the EFD namespace and other namespaces that are not part of the specified XML schema are removed, the resulting document should still be a valid XML document that complies with the present document.

The MIME type of the EFD document is defined in clause D.2.3.4. The encoding of the EFD and all data provided in extension namespaces shall be UTF-8 as defined in IETF RFC 3629 [11]. If binary data needs to be added, it shall be included in Base64 as described in IETF RFC 4648 [12] within a UTF-8 encoded element with a proper name space or identifier, such that an XML parser knows how to process or ignore it.

The delivery of the EFD is outside the scope of the present document. However, if the EFD is delivered over HTTP, then the EFD document may be transfer encoded for transport, as described in IETF RFC 9110 [24].

Selected EFD examples are provided in clause D.2.5.

D.2.3.4 IANA registration for Extended FDT Description

This clause provides the formal MIME type registration for the EFD. It is referenced from the registry at http://www.iana.org/.

The MIME Type and Subtype are defined as follows:

- MIME media type name: `application`
- MIME subtype name: `cmmf-efd+xml`
- Required parameters: None
- Optional parameters: None.
- Encoding considerations: UTF-8
- Security considerations: The EFD contains references to other resources. It is coded in XML, and there are risks that deliberately malformed XML can cause security issues. In addition, an EFD can be authored that causes receiving clients to access other resources; if widely distributed, this can be used to cause a denial-of-service attack.

  The EFD format does not incorporate any active or executable content. However, other forms of material from outside sources can be referenced by an EFD, and this material can contain active or executable content. Such material is expected to be identified by its own MIME type, and the security considerations of that format should be taken into account.

  If operating in an insecure environment and required by the content/service provider, elements and attributes of EFD may be encrypted to protect their confidentiality by using the syntax and processing rules specified in the W3C Recommendation "XML Encryption Syntax and Processing".

  If operating in an insecure environment and required by the content/service provider, the digital signing and verification procedures specified in the W3C Recommendation "XML Signature Syntax and Processing" may be used to protect data origin authenticity and integrity of the EFD.
- Interoperability considerations: The present document defines a platform-independent expression of a document, and it is intended that wide interoperability can be achieved.
- Published specification: ETSI TS 103 973 (the present document)
- Applications which use this media type: Various
- Additional information:
- File extension(s): `efd`
- Intended usage: common
- Other information/general comment: None

- Author/Change controller: ETSI

D.2.4 Transport object formats

D.2.4.1 General

Transport objects are either source transport objects or coded/repair objects.

Source transport objects are unmodified source objects, for details see clause D.2.4.2.

Coded/repair objects conform to the CMMF bitstream format, for details see clause D.2.4.3.

D.2.4.2 Source objects

If the EFD signals a `type` equal to `"source"`, then the object referenced in the `Access-URL` is the original source object. The value of the `Access-URL` may be identical to the value of the `Content-Location`, if the application can also access the object at the original location. The source object as a whole or partially may be used by the CMMF receiver to reconstruct the application object, possibly in combination with coded/repair objects.

D.2.4.3 Coded/repair objects

D.2.4.3.1 General

Coded/repair objects for the FDT-based CDP instantiation shall conform to the CMMF bitstream format. In addition, the coded/repair objects are aligned with ALC Payload formats as defined in IETF RFC 5775 [17], in a sense that it includes an encoding that allows the receiver to recover a list of FEC Payload IDs and the corresponding encoding symbols from the CMMF bitstream information. The FEC Payload ID semantics is the Source Block Number (SBN) and Encoding Symbol ID (ESI) assigned to each symbol.

Coded/repair objects are a restricted CMMF bitstream with the following constraints:

- The following subatoms shall be present in the following order:
  - Exactly one instance of `bitstream_header()` as defined in clauses 5.2.4 and 6.1.4.
  - Multiple instances of `block_header()` as defined in clauses 5.2.5 and 6.1.5, one instance per number of source blocks.
  - Exactly one instance of `multi_block_packet_group()` as defined in clauses 5.2.25 and 6.1.22.
- The `bitstream_header()` shall be restricted as follows:
  - `content_source_size` shall be set to the value of the `Transfer-Length` size as included in the FEC-OTI information as defined in clause D.1.4 and carries the FEC-OTI Information `Transfer-Length` size according to IETF RFC 5052 [15].
  - `content_source_type` shall be set to `000b`.
  - `code_type` shall be set to either 1, 5, or 6 and carries the FEC Encoding ID value according to IETF RFC 5052 [15].
  - `b_rfc5052` shall be set to 1.
  - The information in `rfc5052_information()` as defined in clauses 5.2.20 and 6.1.4.6 shall be set as follows (using the size headers in Table D.1):
    - the `encoding_symbol_length` shall be set to the value of the `FEC-OTI-Encoding-Symbol-Length` size as included in the FEC-OTI information as defined in clause D.1.4 and carries the `FEC-OTI-Encoding-Symbol-Length` according to IETF RFC 5052 [15].

NOTE 1: CMMF in general permits to have different encoding symbol length for each block. For IETF RFC 5052 [15] based `code types` this is not permitted and hence the encoding symbol length is signalled in the bitstream header.

- If `code_type` is set to 1 (Raptor) or set to 6 (RaptorQ), no additional parameters are set. The scheme-specific FEC-OTI parameters "number of sub-blocks (N)" and the "symbol alignment parameter (Al)" are assumed to be set to 1, i.e. sub-blocking shall not be used in the context of CMMF.
- If `code_type` is set to 5 (Reed-Solomon), two additional fields are added and set as follows:
  - The `maximum_source_block_length` shall be set to the `FEC-OTI-Maximum-Source-Block-Length (B)` as defined in IETF RFC 5510 [14].
  - Maximum number of encoding symbols `max_n` size shall be set to the shall be set to the `FEC-OTI-Max-Number-of-Encoding-Symbols (max_n)` as defined in IETF RFC 5510 [14].

- `block_count_minus1` shall be set to:
  - For `code_type` set to 1 and 6: FEC-OTI information "number of source blocks (Z)" minus 1 and carries the scheme-specific value number of source blocks (Z) as defined in IETF RFC 5053 [16] and IETF RFC 6330 [13], respectively.
  - For `code_type` set to 5: the number of source blocks (N) - 1 as defined in clause 9 of IETF RFC 5510 [14].

NOTE 2: With the above information, the FEC decoder following the respective IETF RFC may be instantiated by creating the encoded FEC Object Transmission Information as an octet field consisting of the concatenation of the encoded Common FEC Object Transmission Information and the encoded Scheme specific FEC Object Transmission Information.

- The following flags shall not be set:
  - `b_content_source_split.`
  - `b_content_block_separate_sources.`
  - `b_profile_information_present.`
  - `b_block_cc_encrypted.`

- The `block_header()` instances shall be restricted as follows:
  - There shall be exactly `block_count` instances of `block_header()`, where `block_count = block_count_minus1 + 1`.
  - `block_header()` instances shall have ascending `block_index` values from `0` to `block_count - 1`.
  - Some values shall be set to the values described by the mapping in Table D.2. This includes the values for:
    - `block_symbol_size` shall be set to the `encoding_symbol_length` as defined in the `rfc5052_information()` in the `bitstream_header()`.
    - `block_num_symbols` shall be set based according to the source block partitioning rules of the FEC scheme.
    - `block_max_symbol_index` (`b_block_max_symbol_index_present` shall be set to `TRUE`).
  - Other values shall be set to the values derived from the source blocking algorithm from the FEC scheme. This includes the values for:
    - `block_size` shall be set to `block_num_symbols` × `block_symbol_size` for all blocks except of the last one, i.e. `block_index` set to `block_count - 1`. The last one is set taking into account the remaining octets to fill up the transfer length.

- `block_mask` shall be set to `B0000Bb`, where values marked as B (bit 0: sufficient symbols present and bit 5: block integrity present) can be either 0 or 1 depending on the FEC scheme and CMMF encoder settings.
- The following flags shall not be set:
  - `b_block_content_source_index_present`.
  - `b_block_composite_sources`.
  - `b_addl_block_coding_info_present`.

- The `multi_block_packet_group()` shall be restricted as follows:
  - `mbpg_index` shall be set to 0.
  - `mbpg_start_block_index` shall be set to 0.
  - `mbpg_num_blocks` shall be set to `block_count`.
  - `mbpg_num_symbols` shall be set to the number of symbols contained in the transport object, i.e. `ceil(content_source_size/encoding_symbol_length)`.
  - The `mbpg_header()`shall be restricted as follows:
    - `mbpg_symbol_arrangement` shall be set to either 2 or 3.
    - The symbols are arranged according to clause D.2.4.3.2 with the:
      - `mbpg_index_difference` shall be set to the number of symbol groups *C*.
      - `mbpg_first_symbol_group_subset_index` shall be set to the index of the first symbol within the symbol group. If the value of `mbpg_symbol_group_subset_index` is 0, then `b_mbpg_is_symbol_group_subset` shall be set to FALSE.
      - `mbpg_first_symbol_index` shall be set to the symbol group that is included in the multi-block packet group, *c*.
  - `b_mbpg_integrity_present` shall be set to 0.
  - `b_mbpg_header_ext_present` shall be set to 0.

D.2.4.3.2 Mapping of FEC Payload ID information to transport blocks

D.2.4.3.2.1 General

The information in this clause relates to the Encoding of CMMF as defined in clause 4.2.1 and is specific when using the FDT-based CDP instantiation.

The following parameters are assumed to be available:

- A total number of source symbols *Kt*, available in `mbpg_num_symbols`.
- The source object is partitioned into `block_count` number of source blocks, referred to as *Z*.
- For each source block *z = 0, …, Z-1*:
  - Assuming that source blocks are covering the source object starting `block_index` *z*=0 at the beginning, and each of the source blocks has the same symbol size.
  - The source symbols for each source block *z* are defined as $x_{z,i}$ with source symbols index *i=0, .., Ks*[z]-1 and *Ks*[*z*] the source block size in symbols of source block *z* indicated by `block_num_symbols` in clause 4.2.1.

- The encoded symbols for each source block z are defined as $y_{z,j}$ with encoding symbol index $j = 0, .., Ke[z] - 1$ and $Ke[z]$ the number of encoding symbols assigned to source block z and $Ke[z] \geq Ks[z]$.

NOTE: For some codes/FEC schemes $Ke[z]$ may be quite restrictive (for example for Reed-Solomon codes), for other codes with a fountain property, such as Raptor codes, many symbols may be generated.

- For systematic codes, the first $Ks[z]$ encoding symbols are identical to the source symbols, i.e. $y_{z,j} = x_{z,j}$ for $j = 0, \ldots, Ks[z]$.

The encoding symbols of all source blocks are then distributed across one or multiple symbol groups.

Several *symbol groups* (as defined in clause 4.2.2) are formed, each including one or multiple symbols from one or multiple source blocks. As defined in clause 4.2.2, symbols groups may be distinct, i.e. each encoding symbols is added exactly once to exactly one *symbol group*. The arrangement of symbols in a symbol group may follow a specific pattern arrangement. Symbol groups may also have assigned a property of *completeness*, i.e. the source object can be recovered from all symbols in the symbol group.

Assume the definition of C symbols groups, indexed with c=0,…, C-1. Each symbol groups c includes $Kc[c]$ encoding symbols, indexed from k = 0, …, $Kc[c] - 1$. The symbols in the symbol group are referred to as $w_{c,k}$ for $k = 0, \ldots, Kc[c]$ and c=0,…, C-1. Symbols in a symbol group may come from different encoded blocks.

Based on these *symbol groups*, *multi-block packet groups* are formed. *Multi-block packet groups* represent a subset of symbol groups with a consecutive set of symbols of exactly one symbol group and fully defined by the *index of the first symbol* within the symbol group, and the *number of symbols* included in the *multi-block packet group*.

The information on which encoding symbols are included in the *multi-block packet group* as well their order is provided in a *multi-block packet group header* by the `mbpg_symbol_arrangement` field.

Figure D.2 provides an overview on the formation of transport objects based on a source object. Note the differences between the partitioning algorithm presented here compared to that described in clause 4.2.1.




Figure D.2: Formation of transport objects from source objects

On the symbol group arrangements, an arbitrary sequence of coded symbols for different source blocks may be collected in a symbol group. In this case, MBPG header needs to include the list of pairs of source block z and symbol identifier i assigned to each position k in the symbol group c.

The present document also defines symbol group arrangements that apply certain patterns, and for which only a few parameters need to be added to map the position k in the symbol group c and the position of source block z and symbol identifier i.

For the symbol group arrangement `mbpg_symbol_arrangement` with value set to 3 or 2, the arrangements are provided in clauses D.2.4.3.2.2 and D.2.4.3.2.3, respectively.

In Figure D.2 the formation of multi-block packet groups from symbol groups is accomplished by extracting a contiguous range of symbols from a symbol group, starting from `mbpg_first_symbol_index` in symbol group `mbpg_symbol_group`, c.

D.2.4.3.2.2 Symbol group arrangement 3: encoding symbol interleaving

This pre-defined symbol arrangement is motivated by a scenario for which typically the source symbols are not included in the transport object, either because the code is non-systematic, or only repair symbols are included. In addition, the symbols on each transport object are distinct. This symbol group arrangement corresponds to an `mbpg_symbol_arrangement` value of 0011b.

In this example, transport objects may be generated with encoding symbols included. On top of this:

1) the transport object includes sufficient information to recover the included source object;

2) if only a subset of several transport objects is accessible, then an initial byte range of a subset of transport objects is sufficient to recover the source object, and the required number of total bytes is small.

The only parameter for this symbol arrangement is the number of symbol groups *C*.

In order for the arrangement to be effective, it is assumed that the source blocks are of equal or at least similar size. In the case of the FDT-based CDP instantiation, this condition is fulfilled.

For defining the symbol group arrangement, the following is defined:

- Total symbol count *TOTAL* added to symbol groups, initialized to 0.
- Next position in symbol group *c* that can add a symbol, *POS*[*c*], initialized to 0.
- Next symbol index in source block *z* that has not yet been added to any transport object, ESI[*z*], initialized to the index of the first non-source symbol, i.e. 0 for non-systematic code, and *Ks*[*z*] for systematic codes.
- Counter for number of symbols included in container *c* from source block z, *SYMBOLS*[*o,z*], initialized to 0.

In addition, a completeness check is carried out for the entire arrangement across different symbol groups. Only if each symbol group includes a sufficient set of symbols to recover all included source blocks, adding symbols is stopped.

The arrangement as defined in clause 6.1.23.1.

Figure D.3 (aligned with Figure 13) provides an example for encoding symbol arrangement with *Kt=29*, *Z=3*, *Ks[0] = Ks[1]=10, Ks[2]=9, Ke[0]=Ke[1]=30, Ke[2]=27* across *C=3* symbol groups. The bold ESI number shows the symbols that makes a source block complete for each symbol group. Symbols are added to each symbol group until all symbol groups are complete.




Figure D.3: Symbol arrangement for arrangement 3

D.2.4.3.2.3 Symbol group arrangement 2: source symbol interleaving

This arrangement is motivated by a scenario for which the source symbols are included in the transport object. However, not all transport objects include all source symbols, but a number of transport objects include a distinct set of source symbols. If all transport objects are accessible then reading from the beginning each transport objects, the initial data of the source object can be aggregated. This symbol group arrangement corresponds to an `mbpg_symbol_arrangement` value of 0010b.

This configuration supports for example that transport objects are generated with source symbols included. In addition, the following properties hold:

1) the transport object includes sufficient information to recover the included source object;

2) if only a subset of the transport objects is accessible, then an initial byte range of the subset of transport objects is sufficient to recover the source object, and the total number of bytes is small.

To abstract the procedure, again symbol groups are used. These symbol groups may then be included into transport objects, either completely or partially.

The only parameter for this arrangement is the number of symbol groups C.

For defining the symbol group arrangement, the following is defined:

- Total symbol count *TOTAL* added to symbol groups, initialized to 0.
- Next position in symbol group c that can add a symbol, $POS[c]$, initialized to 0.
- Next symbol index in source block z that has not yet been added to any transport object, $ESI[z]$, initialized to 0.
- Counter for number of symbols included in container c from source block z, $SYMBOLS[o,z]$, initialized to 0.

The arrangement as defined in clause 6.1.23.1.

Figure D.4 provides an example for source and repair symbol arrangement with *Kt=29*, *Z=3*, *Ks[0] = Ks[1]=10*, *Ks[2]=9*, *Kr[0]=Kr[1]=21 and Kr[2]=22* across *C=3* symbol groups. The bold ESI number shows the symbols that makes a source block complete for each symbol group. Symbols are added to each symbol group until all symbol groups are complete. Obviously more symbols until completion may be added.




Figure D.4: Symbol arrangement for arrangement 2

D.2.5 Examples

D.2.5.1 Single file - source and partial encoding object

The following example is provided for a single file in Listing D.2, where the file is an MP4 file compatible to some MIME media type and in addition, for this file, three partial repair objects are provided that each contain 500 symbols of a single source block. The files are only partial, and the information is provided in the extended FDT. The FDT is complete, i.e. no new information is provided.

Listing D.2: Extended FDT example for a single file

```
<?xml version="1.0" encoding="UTF-8"?>
<FDTInstance xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
             xmlns="urn:ETSI:CMMF:2023:FDT"
             xsi:schemaLocation="urn:ETSI:CMMF:2023:FDT extendedFDT.xsd"
             Expires="2024-05-30T09:30:10Z"
             Complete="true"
             ContentType="video/mp4 codecs='avc1.42c01e,mp4a.40.29' profiles='iso8'"
             FEC-OTI-FEC-Encoding-ID="6"
             FEC-OTI-Encoding-Symbol-Length="64">
    <File ContentLocation="https://example.com/efd1.mp4"
          TOI="0"
          Content-Length="64000">
        <EncodedObjects type="source"
                        complete="true">https://example.com/efd1.mp4</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,0,0"
                        complete="true">https://example-cdn1.com/efd1-0.cmf</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,1,0"
```

```
                        complete="true">https://example-cdn2.com/efd1-1.cmf</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,2,0"
                        complete="true">https://example-cdn3.com/efd1-2.cmf</EncodedObjects>
    </File>
</FDTInstance>
```

D.2.5.2 Multiple files - self-contained objects including source symbols

In the example shown in Listing D.3, two files are provided, both encoded with RaptorQ and symbol length 64 bytes. In this case, only self-contained objects are provided, and these symbols are spread such that symbols 0, 3, 6 … are contained in one file, 1, 4, 7, … are contained in another file, and 2, 5, 8, …. are yet included in another file. At the same time, each encoded object is self-contained and can represent the files.

Listing D.3: Extended FDT example for multiple files

```
<?xml version="1.0" encoding="UTF-8"?>
<FDTInstance xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
             xmlns="urn:ETSI:CMMF:2023:FDT"
             xsi:schemaLocation="urn:ETSI:CMMF:2023:FDT extendedFDT.xsd"
             Expires="2024-05-30T09:30:10Z"
             Complete="true"
             FEC-OTI-FEC-Encoding-ID="6"
             FEC-OTI-Encoding-Symbol-Length="64">
   <File ContentLocation="https://example.com/efd1-video.mp4"
        ContentType="video/mp4 codecs='avc1.42c01e' profiles='iso8'"
         TOI="0"
         Content-Length="64000">
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,0,0"
                        complete="true">https://example-cdn1.com/efd1-video-0.cmf</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,1,0"
                        complete="true">https://example-cdn2.com/efd1-video-1.cmf</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,2,0"
                        complete="true">https://example-cdn3.com/efd1-video-2.cmf</EncodedObjects>
   </File>
   <File ContentLocation="https://example.com/efd1-audio.mp4"
        ContentType="audio/mp4 codecs='mp4a.40.29' profiles='iso8'"
         TOI="1"
         Content-Length="4800">
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,0,0"
                        complete="true">https://example-cdn1.com/efd1-audio-0.cmf</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,1,0"
                        complete="true">https://example-cdn2.com/efd1-audio-1.cmf</EncodedObjects>
        <EncodedObjects type="cmmf"
                        symbolArrangement="2"
                        sAParameters="3,2,0"
                        complete="true">https://example-cdn3.com/efd1-audio-2.cmf</EncodedObjects>
   </File>
</FDTInstance>
```

D.2.6 Potential receiver operation

Once a CMMF Receiver receives the Configuration Information in the form of an EFDT, it may access multiple coded versions of the same source object and operation can proceed as described in clause 4.3.6. A typical operation of the receiver is to collect symbols from different locations as quickly as possible in order to be able to recover the included objects while avoiding downloading unnecessary symbols.

The arrangements of symbols allow to minimize the network resource usage.

More details are for further study.

D.3 URL Translation-based CDP instantiation

D.3.1 Introduction

This clause defines a Content Delivery Protocol instantiation for CMMF that provides a method to dynamically map application resources to/from CMMF Transport Objects through URL translation and to obtain those application resources using CMMF. In some cases, this CDP instantiation may satisfy the requirements of a FEC Building Block CDP instantiation as defined in clause D.1 of the present document and in IETF RFC 5052 [15].

The URL Translation-based CMMF CDP instantiation is defined as follows:

- Typical procedures for the URL Translation-based CMMF CDP Instantiation are provided in clause D.3.2 where a pull-based process is assumed to obtain application resources.
- A Delivery Session comprises of one or more Transport Sessions. Each Transport Session is comprised of one or more Transport Objects where each Transport Object is identified by a unique Transport Object Identifier (TOI), for example a uniquely identifiable URL.
- A Transport Object shall be a compliant CMMF bitstream as specified in clauses 5 and 6. Clause D.1 also applies for CMMF bitstreams where the `b_rfc5052` flag as specified in clause 6.1.4.6 is set to TRUE.
- The retrieval of a single application service resource/source object constitutes a Delivery Session.
- The retrieval of an application service resource/source object shall be possible from some combination of Transport Objects created for a Delivery Session.
- The availability of Transport Objects created for a Delivery Session shall be the same as the availability of the application service resource/source object.
- Every source object and CMMF Transport Object shall be identifiable using a unique URL.
- CMMF Transport Objects may be retrieved by a CMMF Receiver using HTTP [24] (e.g. HTTP/1.1 [i.4], HTTP/2 [i.6], HTTP/3 [i.7], etc.).
- CMMF Configuration Information required by a CMMF Receiver may apply to a single Delivery Session or multiple Delivery Sessions.
- The CMMF Configuration Information can be expressed in a document or via an API providing information such as a mapping between application resources (e.g. identifiable by a unique URL) and Transport Sessions/Transport Objects contained within a Delivery Session. Further details are provided in clause D.3.3.

D.3.2 Procedures for URL Translation-based CDP instantiation

D.3.2.1 Introduction

This clause provides procedures for CMMF content preparation, provisioning and delivery for the URL Translation-based CMMF CDP instantiation. A standard HTTP-based content delivery model is assumed where:

- A CMMF Application Provider makes its content available to clients via one or more CMMF Senders (e.g. service locations, CDNs, CDN points of presence (PoPs), etc.).
- Clients obtain content via one or more of the CMMF Senders (e.g. using HTTP GET requests).

D.3.2.2 Procedure for URL Translation-based CMMF CDP provisioning, content ingest, and CMMF Transport Object preparation

A baseline procedure describing the network provisioning, content ingest, and CMMF Transport Object preparation required to support a URL Translation-based CDP Delivery Session is shown in Figure D.5.




Figure D.5: High-level procedure for URL translation-based CMMF provisioning and preparation

The procedure makes the following assumptions:

- A CMMF Application Provider is responsible for network provisioning and CMMF Delivery Session configuration/provisioning which may include:
  - Provisioning content hosting.
  - Preparation of CMMF Transport Objects and/or provisioning of compute resources to create CMMF Transport Objects.
  - Preparation of necessary CMMF Configuration Information.
- A CMMF Sender (e.g. CDN, CDN PoP, etc.) is used for distribution of source and/or CMMF Transport Objects to CMMF-Aware Clients. This CMMF Sender may:
  - Cache objects for later retrieval.
  - Encode ingested source objects or re-encode ingested CMMF Transport Objects.
  - Prepare CMMF Transport Objects.
  - Prepare or update the CMMF Configuration Information used by a CMMF-Aware Client.

- An HTTP pull-based architecture is assumed where a Delivery Session and the retrieval of CMMF Transport Objects is initiated by a CMMF-Aware Client.

Steps:

1) The CMMF Application Provider provisions content hosting within the CMMF Sender (e.g. CDN, CDN PoP, etc.) and establishes a service location where source and/or CMMF Transport Objects are made available to CMMF-Aware Clients. In the case where the CMMF Sender prepares the CMMF Configuration Information, the CMMF Sender may provide the CMMF Application Provider with a URL to the CMMF Configuration Information.

2) In the case were the CMMF Application Provider generates the CMMF Configuration Information, the CMMF Application Provider prepares the CMMF Configuration Information used by CMMF-Aware Clients to access CMMF Transport Objects during a Delivery Session. This CMMF Configuration Information should include information about the available CMMF Senders provisioned in step 1.

3) The CMMF-Aware Client triggers the Service and Content Discovery procedure. A URL pointing to where the CMMF Configuration Information is available may be provided to the CMMF-Aware Client. Alternatively, the CMMF Configuration Information may be provided to the CMMF-Aware Client by other means.

4) The CMMF-Aware Client requests the CMMF Configuration Information. The CMMF Configuration Information may be available from the CMMF Sender, the CMMF-Aware Application Provider, etc.

5) In the case where the CMMF Configuration Information is not cached by the CMMF Sender and the CMMF Configuration Information is prepared by the CMMF Application Provider, the CMMF Sender propagates the request for the CMMF Configuration Information to the CMMF Application Provider.

6) The CMMF Application Provider provides the CMMF Configuration Information to the CMMF Sender.

7) In the case where the CMMF Sender generates the CMMF Configuration Information, the CMMF Sender prepares the CMMF Configuration Information used by CMMF-Aware Clients to access CMMF Transport Objects during a Delivery Session. If the CMMF Application Provider originally prepared the CMMF Configuration Information, the CMMF Sender may be configured to update the CMMF Configuration Information before delivery to a CMMF-Aware Client.

8) The CMMF Configuration Information for a Delivery Session is provided to a CMMF-Aware Client.

9) The CMMF-Aware Client selects a CMMF Transport Object to download.

10) The CMMF-Aware Client requests a CMMF Transport Object from the CMMF Sender.

11) In the case where the CMMF Transport Object is not cached by the CMMF Sender, the CMMF Sender propagates the request for either the CMMF Transport Object or its associated source object (in the case where the CMMF Sender generates CMMF Transport Objects) to the CMMF Application Provider. If a source object is requested from the CMMF Application Provider, the CMMF Sender translates the URL of the CMMF Transport Object received from the CMMF-Aware Client into a URL for the source object to be obtained from the CMMF Application Provider as specified in clause D.3.3.2.

12) In the case where the CMMF Application Provider receives a request for a CMMF Transport Object, it may use the source object associated with the CMMF Transport Object to prepare one.

NOTE: CMMF Transport Objects may be prepared prior to receiving a request or in response to receiving a request.

13) The CMMF Application Provider provides either the requested CMMF Transport Object or its associated source object to the CMMF Sender. In either case, the received object may be cached for later use.

14) In the case where the CMMF Sender is provisioned to prepare CMMF Transport Objects, it may use either a source object or a cached CMMF Transport Object to generate a new CMMF Transport Object.

15) The CMMF Transport Object is provided to the CMMF-Aware Client.

D.3.2.3 Procedure for URL Translation-based CMMF CDP delivery

A baseline procedure describing the establishment of a URL Translation-based CDP Delivery Session is shown in Figure D.6.




Figure D.6: High-level procedure for URL Translation-based CMMF CDP delivery

The procedure makes the following assumptions:

- CMMF Transport Objects used to support a Delivery Session are available from one or more CMMF Senders (e.g. service locations, CDNs, CDN PoPs, etc.). These Transport Objects may be prepared so that each CMMF Sender hosts a different encoded representation or variation of the source content/object. These Transport Objects may be prepared by the CMMF Application Provider prior to provisioning of a CMMF Sender or at each CMMF Sender depending on the network configuration.
- CMMF Configuration Information may apply to all Delivery Sessions or be specific to a single Delivery Session. The procedure assumes the former.
- The CMMF Receiver in the Client has the necessary functionality to establish multiple Transport Sessions and retrieve multiple Transport Objects simultaneously from multiple CMMF Senders.

Prerequisites:

1) The CMMF Application Provider has provisioned each CMMF Sender to distribute CMMF Transport Objects to CMMF-Aware Applications.
2) The CMMF Application Provider provides the URL of the CMMF Configuration Information to the CMMF-Aware Application.

Steps:

3) The CMMF-Aware Application configures the CMMF Receiver to be used for obtaining content/source objects. This includes providing the CMMF Receiver with the URL to the CMMF Configuration Information.

4) The CMMF Receiver obtains the CMMF Configuration Information from either the CMMF Application Provider or one of the provisioned CMMF Senders and informs the CMMF-Aware Application that the CMMF Configuration Information has been received and processed.

5) Content or a source object is selected by the CMMF-Aware Application.

6) The CMMF-Aware Application provides the URL of the selected content/source object to the CMMF Receiver.

7) The CMMF Receiver translates the URL of the selected content/source object into URLs for CMMF Transport Objects using the procedures specified in clause D.3.2.2.

8) The CMMF Receiver requests and downloads the necessary CMMF Transport Objects required to recover the content/source object. CMMF Transport Objects may be downloaded in parallel from multiple CMMF Senders; and each CMMF Transport Object may be obtained in full or in part depending on the Delivery Session configuration and/or network conditions.

9) The CMMF Receiver decodes the information received from the obtained full or partial CMMF Transport Objects and extracts the content/source object.

10) The content/source object is provided to the CMMF-Aware Application Provider.

D.3.3 CMMF Configuration Information for URL Translation-based CDP

D.3.3.1 Introduction

This clause provides a template for the CMMF Configuration Information that can be used by a CMMF Receiver to translate between source objects needed by a CMMF-Aware Application and the CMMF Transport Objects used to deliver those source objects.

D.3.3.2 Source Object URL to CMMF Transport Object URL mapping procedures

D.3.3.2.1 General

Procedures to translate URLs of application service resources/source objects (i.e. URLs for resources/source objects that, for example, would have been expected to be retrieved using HTTP GET) into URLs of the CMMF Transport Objects containing encoded representations or variants of those resources are defined in this clause.

D.3.3.2.2 Mapping complete object URLs

An application service resource/source object and its corresponding URL is first identified or provided by the application. The URL is then mapped into one or more CMMF Transport Object URLs which are used to request those CMMF Transport Objects from one or more CMMF Senders (e.g. service locations, CDNs, CDN PoPs, etc.) by:

- Adding a scheme and domain name of the CMMF Sender for which the CMMF Transport Object is hosted to the application service resource URL; or replacing the scheme and domain name of the application service resource URL with a scheme and domain name of the CMMF Sender for which the CMMF Transport Object is hosted; and/or

- Inserting a pre-defined sub-path into the application service resource URL's path that is associated with the CMMF Transport Object. This sub-path may also indicate the CMMF representation or variant of the CMMF-encoded application service resource to retrieve from the identified CMMF Sender.

For example, an application service resource with the URL `https://example.com/path-to-media/segment-1.mp4` is mapped to two CMMF Transport Objects, each containing a different CMMF representation or variant of the application service resource.

- The first CMMF Transport Object is available from a CMMF Sender with base URL `https://host-a.example.com`. The sub-path `cmmf-variant-a`, which also is used to identify which CMMF-encoded representation or version of the application service resource to download from the CMMF Sender, is inserted into the path of the application service resource URL.
- Likewise, the second CMMF Transport Object is available at `https://host-b.example.com` and the sub-path `cmmf-variant-b` is inserted into the path of the application service resource URL.

The mapped request URLs for both CMMF Transport Objects are then:

```
https://host-a.example.com/path-to-media/cmmf-variant-a/segment-1.mp4
```

and

```
https://host-b.example.com/path-to-media/cmmf-variant-b/segment-1.mp4
```

respectively.

D.3.3.2.3 Mapping sub-object URLs using byte range requests

In the case where an application service resource/source object is identified by both a URL to an object and a byte range within that object (e.g. chunked CMAF), the mapping is similar to that described in clause D.3.3.2.2 above. The scheme and domain name to a CMMF Sender hosting a CMMF Transport Object containing a CMMF-encoded representation or variant of the application service resource is either added or replaced in the application service resource's URL and a sub-path is inserted. The byte range, which is usually communicated using the `Byte-Range` HTTP request header, is translated into an additional sub-path element and is also inserted into the mapped URL's path.

For example, an application service resource with the URL `https://example.com/path-to-media/segment-1.mp4` and byte range *startByte* to *endByte* is mapped to two CMMF Transport Objects containing different CMMF-encoded representations or variants of the application service resource:

- The first CMMF Transport Object is available at the CMMF Sender with base URL `https://host-a.example.com`. The sub-path `cmmf-variant-a`, which is also used to identify which CMMF-encoded representation or variant of the application service resource to download from the CMMF Sender, is inserted into the path of the application service resource URL. The byte range is also inserted into the path URL as `byte-range-<`*startByte*`>-<`*endByte*`>`.
- Likewise, the second CMMF Transport Object is available at `https://host-b.example.com` and the sub-paths `cmmf-variant-b` and `byte-range-<`*startByte*`>-<`*endByte*`>` are inserted into the path of the application service URL.

The mapped request URLs for both CMMF Transport Objects are:

`https://host-a.example.com/path-to-media/cmmf-variant-a/byte-range-<`*startByte*`>-<`*endByte*`>/segment-1.mp4`

and

`https://host-b.example.com/path-to-media/cmmf-variant-b/byte-range-<`*startByte*`>-<`*endByte*`>/segment-1.mp4`

respectively.

D.3.3.2.4 Mapping HTTP headers and query parameters

Besides the mapping of the `Byte-Range` HTTP request header discussed in clause D.3.3.2.3, any additional HTTP headers and/or query parameters that would be added to an HTTP GET request for the source object should be directly mapped to the HTTP requests for the CMMF Transport Objects. The CMMF Receiver may also add or modify HTTP headers and/or query parameters as necessary.

D.3.3.3 URL Translation-based CMMF Configuration Information document

D.3.3.3.1 General

A template for communicating necessary CMMF Configuration Information is specified in this clause. It may be used by a CMMF Receiver to configure a Delivery Session and obtain selected content/source objects using the URL Translation-based CMMF CDP.

D.3.3.3.2 Semantics

The semantics of the CMMF Configuration Information are provided in Table D.4.

Table D.4: Semantics of the URL Translation-based CMMF Configuration Information document

Property Name	Use	Description
`version`	M	The version of CMMF Configuration Information document. The present document defines CMMF Configuration Information document version 0. A CMMF Receiver shall refuse to use a CMMF Configuration Information document with an unrecognized value for this key.
`ttl`	O	Specifies how many seconds the CMMF Receiver shall wait before reloading the CMMF Configuration Information document. If absent, the CMMF Configuration Information document refresh rate is determined by the Media Application/Client.
`applicationResourceLocators`	O	An array of application resource locator objects providing one or more URLs to an application service resource for which this CMMF Configuration Information applies. An application resource locator object may consist of: • A single file or source object (e.g. media segment), or • An object comprising of a list of files or source objects (e.g. MPEG-DASH MPD, HLS playlist, etc.) in which case this CMMF Configuration Information is applied to all files or source objects contained in the list. If present, the array shall contain at least one application resource locator object. If omitted, the application resources this CMMF Configuration Information applies to are supplied via a process external to this configuration.
`locator`	M	Absolute URL pointing to an application service resource such as an MPD, HLS master playlist, file, etc.
`contentType`	M	The MIME media type of the resource at `locator`.
`isManifest`	M	A Boolean indicated whether the application resource at `locator` is a single file/source object or an object comprising of a list of files or source objects. If *true*, the application resource located at `locator` is an object comprising of a list of files or source objects. This CMMF Configuration Information shall be applied to all files or source objects contained in the list. If *false*, the CMMF Configuration Information shall only be applied to the application resource identified by `locator`.
`applicationResourceConfigurations`	M	An array of application resource configurations for the identified application resource(s). At least one shall be defined. In the case where multiple application resource configurations apply to an application resource, the first takes precedence.

Property Name	Use	Description
admissionRules	O	An object providing rules to determine if the application resource configuration applies to the application resource. The application resource configuration applies if any application resource satisfies `applicationResourcePathPattern` and/or `applicationResourceContentType`. If both `applicationResourcePathPattern` and `applicationResourceContentType` are defined, the application resource configuration applies only if the application resource satisfies both. If present, either `applicationResourcePathPattern` or `applicationResourceContentType` shall be defined. If absent, the application resource configuration applies to all application resources.
applicationResourcePathPattern	CM	An array of regular expressions against which the path of the application resource URL shall be compared. If any of the path patterns listed within the array are found within the URL, this application resource configuration applies. If present, the array shall contain at least one path pattern. If absent, path patterns are not used to determine if the application resource configuration applies.
applicationResourceContentType	CM	An array of MIME media types of the application resource for which this application resource configuration applies. If present, the array shall contain at least one MIME media type. If absent, MIME media types are not used to determine if the application resource configuration applies.
exclusionRules	O	An object providing rules to determine if the application resource configuration does not apply to the application resource. The rules provided within this object take precedence over those provided in `admissionRules`. The application resource configuration does not apply if an application resource satisfies either `applicationResourcePathPattern` and/or `applicationResourceContentType`. If both `applicationResourcePathPattern` and `applicationResourceContentType` are defined, the application resource configuration applies only if the application resource satisfies both. If present, either `applicationResourcePathPattern` or `applicationResourceContentType` shall be defined. If absent, the application resource configuration applies to all application resources as determined by `admissionRules`.
applicationResourcePathPattern	CM	An array of regular expressions against which the path of the application resource URL shall be compared. If any of the path patterns listed within the array are found within the URL, this application resource configuration does not apply. If present, the array shall contain at least one path pattern. If absent, path patterns are not used to determine if the application resource configuration applies.
applicationResourceContentType	CM	An array of MIME media types of the application resource for which this application resource configuration does not apply. If present, the array shall contain at least one MIME media type. If absent, MIME media types are not used to determine if the application resource configuration applies.
serviceLocations	M	An array of service location objects from which CMMF Transport Objects for this application resource configuration are available. At least one shall be indicated.
variantId	O	A CMMF bitstream variant identifier that may be used to distinguish between different variants of CMMF bitstreams/Transport Objects.
baseUrl	M	Base URL of the service location from which CMMF Transport Objects are made available. `baseUrl` overwrites any base URLs provided by the application resource locator objects (if they exist). `baseUrl` shall contain a scheme and the service location's domain name (e.g. https://example.com) at a minimum.
requestPathMaps	O	An array of request path mappings used to convert a received application resource URL into a CMMF Transport Object URL(s).

Property Name	Use	Description
requestPathPattern	M	A regular expression against which the path of the application resource URL, beginning from the leading "/", shall be compared.
mappedPath	M	A replacement for the portion of the application resource path URL that matches `requestPathPattern`.
additionalHttpHeaders	O	A list of key-value pairs indicating HTTP headers that should be added when accessing CMMF Transport Objects from the service location. HTTP headers provided in `additionalHttpHeaders` either adds to or, in the case of duplicate HTTP header key values, overwrites any HTTP headers provided by the Media Application/Client.
additionalHttpQueryParameters	O	A list of key-value pairs indicating HTTP query parameters that should be added when accessing CMMF Transport Objects from the service location. HTTP query parameters provided in `additionalHttpQueryParameters` either adds to or, in the case of duplicate HTTP query key values, overwrites any HTTP query parameters provided by the Media Application/Client.
cmmfCodingConfiguration	O	The CMMF coding configuration for this application resource configuration. If present, application resources for which this application resource configuration applies are encoded within CMMF Transport Objects that are retrieved by the CMMF Receiver from one or more `serviceLocations`. If absent, the application resources for which this application resource configuration applies will not be encoded within CMMF Transport Objects. Rather, the CMMF Receiver shall retrieve the source object for those application resources from one of the provided `serviceLocations`.
cmmfVersion	M	Version of the CMMF specification for which the CMMF Transport Objects conform.
cmmfCodeType	O	The CMMF `code_type` used to create the CMMF Transport Objects (see clause 6.1.4.5).
cmmfProfile	O	The CMMF `profile_type` used to create the CMMF Transport Objects (see clause 6.1.4.11).
cmmfProfileDescription	O	The CMMF `profile_description` used to create the CMMF Transport Objects (see clause 6.1.4.12).
Key M=mandatory, O=optional, OD=optional with default value, CM=conditionally mandatory		

D.3.3.3.3 Schema

A JSON schema for CMMF Configuration Information in connection with the URL Translation-based CDP is provided in Listing D.4 below. This schema may be used to define the parameters of the mappings between application resources/source objects and CMMF Transport Objects containing CMMF-encoded representations or variants of those application resources hosted by one or more CMMF Senders (e.g. service locations, CDNs, CDN PoPs, etc.). It also allows for different mappings to be defined depending on the application resource type (e.g. video, audio, etc.) and/or the pattern of the application resource URL.

An informative copy of the JSON Schema Definition with filename `cmmf_configuration_information_document_schema.json` is included in archive ts_103973v010201p0.zip which accompanies the present document.

Listing D.4: CMMF Configuration Information document schema

```
{
  "type": "object",
  "properties": {
    "version": {
      "description": "Version of the CMMF Configuration Information document syntax.",
      "type": "integer"
    },
    "ttl": {
      "description": [
        "The number of seconds a CMMF Receiver shall wait before reloading the CMMF",
        "Configuration Information document."
      ],
```

```
      "type": "number"
    },
    "applicationResourceLocators": {
      "description": "Array of application resource locator objects.",
      "type": "array",
      "items": {
        "type": "object",
        "properties": {
          "locator": {
            "description": "Absolute URL pointing to an application resource.",
            "type": "string"
          },
          "contentType": {
            "description": [
              "MIME media type of the application resource identified by locator."
            ],
            "type": "string"
          },
          "isManifest": {
            "description": [
              "Boolean to indicate if the application resource identified by locator is a
              "list of files/source objects or a single file/source object."
            ],
            "type": "boolean"
        },
        "required": ["locator", "contentType", "isManifest"]
      },
      "minItems": 1
    },
    "applicationResourceConfigurations": {
      "description": "Array of application resource configurations.",
      "type": "array",
      "items": {
        "type": "object",
        "properties": {
          "admissionRules": {
            "description": [
              "Rules used to determine if this application resource configuration should be ",
              "applied to the application resource."
            ],
            "type": "object",
            "properties": {
              "applicationResourcePathPattern": {
                "description": [
                  "Array of regular expressions against which the path of the application",
                  "resource URL shall be compared to determine if this application resource ",
                  "configuration should be applied to the application resource."
                ],
                "type": "array",
                "items": {
                  "type": "string",
                  "minItems": 1
                }
              },
              "applicationResourceContentType": {
                "description": [
                  "Array of MIME media type of the application resource for which ",
                  "this application resource configuration applies."
                ],
                "type": "array",
                "items": {
                  "type": "string",
                  "minItems": 1
                }
              }
            },
            "minProperties": 1
          },
          "exclusionRules": {
            "description": [
              "Rules used to determine if this application resource configuration should not be ",
              "applied to the application resource. The rules provided within this object",
              "take precedence over those provided in admissionRules."
            ],
            "type": "object",
            "properties": {
              "applicationResourcePathPattern": {
                "description": [
```

```
                "Array of regular expressions against which the path of the application",
                "resource URL shall be compared to determine if this application resource ",
                "configuration should be applied to the application resource."
              ],
              "type": "array",
              "items": {
                "type": "string",
                "minItems": 1
              }
            },
            "applicationResourceContentType": {
              "description": [
                "Array of MIME media type of the application service resource for which",
                "this application resource configuration applies."
              ],
              "type": "array",
              "items": {
                "type": "string",
                "minItems": 1
              }
            }
          },
          "minProperties": 1
        },
        "serviceLocations": {
          "description": [
            "Array of service location objects from which CMMF Transport Objects",
            "are available."
          ],
          "type": "array",
          "items": {
            "type": "object",
            "properties": {
              "variantId": {
                "description": "The CMMF  bitstream variant identifier",
                "type": "string"
              },
              "baseUrl": {
                "description": [
                  "Base URL of the service location from which CMMF Transport",
                  "Objects are made available."
                ],
                "type": "string"
              },
              "requestPathMaps": {
                "description": "",
                "type": "array",
                "items": {
                  "type": "object",
                  "properties": {
                    "requestPathPattern": {
                      "description": [
                        "A regular expression against which the path of the application",
                        "resource URL shall be compared to determine the location where",
                        "the URL sub-path for the CMMF Transport Object will be inserted."
                      ],
                      "type": "string"
                    },
                    "mappedPath": {
                      "description": [
                        "A replacement URL sub-path for the portion of the application",
                        "resource URL that matches requestPathPattern."
                      ],
                      "type": "string"
                    },
                  },
                  "required": ["requestPathPattern", "mappedPath"]
                },
                "minItems": 1
              },
              "additionalHttpHeaders": {
                "description": [
                  "A list of key-value pairs indicating HTTP headers that should be",
                  "added or modified when accessing CMMF Transport Objects from the service ",
                  "location."
                ],
                "type": "object",
                "properties": {}
```

```
                },
                "additionalHttpQueryParameters": {
                  "description": [
                    "A list of key-value pairs indicating HTTP query parameters that",
                    "should be added or modified when accessing CMMF Transport Objects from the ",
                    "service location."
                  ],
                  "type": "object",
                  "properties": {}
                },
              }
            },
            "required": ["baseUrl"]
          },
          "cmmfCodingConfiguration": {
            "description": [
              "CMMF coding configuration for this CMMF Transport Object",
              "configuration."
            ],
            "type": "object",
            "properties": {
               "cmmfVersion": {
                 "description": "Version of the CMMF bitstream used.",
                 "type": "number"
               },
               "cmmfCodeType": {
                 "description": "The CMMF code type used.",
                 "type": "integer"
               },
               "cmmfProfile": {
                 "description": "The CMMF profile used.",
                 "type": "string"
               },
               "cmmfProfileDescription": {
                 "description": "The CMMF profile description used.",
                 "type": "string"
               },
             },
             "required": ["cmmfVersion"]
           }
         },
         "required": ["serviceLocations"],
       }
     },
     "required": ["version", "applicationResourceConfigurations"]
}
```

D.3.3.3.4 IANA registration of CMMF Configuration Information document for the URL Translation-based CMMF CDP

D.3.3.3.4.1 General

This clause provides the formal MIME type registration for the CMMF Configuration Information document compliant with the JSON schema specified in clause D.3.3.3.3. It is referenced from the registry at http://www.iana.org/assignments/media-types.

D.3.3.3.4.2 Registration of MIME media type for CMMF Configuration Information document

The MIME Type and Subtype are defined as follows:

- MIME media type name: `application`
- MIME subtype name: `cmmf-configuration-information+json`
- Required parameters: None
- Optional parameters: `cmmfProfiles` (see clause D.3.3.3.4.3 of ETSI TS 103 973), `cmmfCodeTypes` (see clause D.3.3.3.4.4 of ETSI TS 103 973)

- Encoding considerations: This is a JSON document, and the encoding considerations are the same as for media type *application/json* defined in IETF RFC 8259 [25].
- Security considerations: This media format is a JSON document and inherits the security considerations provided in IETF RFC 8259 [25].

  The format does not incorporate any active or executable content. However, other forms of material from outside resources can be referenced by the format, and this material can contain active or executable content. Such material is expected to be identified by its own MIME type, and the security considerations of that format should be taken into account.

  This format is highly susceptible to manipulation or spoofing for attacks designed to inject fake information. Both integrity protection and source authentication are recommended to prevent misleading of the recipient.
- Interoperability considerations: None
- Published specification: ETSI TS 103 973 (the present document)
- Applications which use this media type: The CMMF Configuration Information document may be used by CMMF Receivers, either stand-alone or embedded within other applications, to provide necessary configuration information to identify, locate, and recover media resources from CMMF bitstreams/Transport Objects.
- Additional information:
  - File extension(s): `json`
  - Intended usage: `COMMON`
- Other information/general comment: None
- Restrictions on usage: None
- Author/Change controller: ETSI

D.3.3.3.4.3 cmmfProfiles parameter

The `cmmfProfiles` parameter to be used with the MIME media type registered in clause D.3.3.3.4.2 is specified in Table D.5.

Table D.5: cmmfProfiles parameter definition for CMMF Configuration Information document MIME media type

Parameter	Value
Parameter name	`cmmfProfiles`
Parameter value	A comma-separated list of CMMF bitstream profile identifiers as specified in annex F of ETSI TS 103 973 which are provided within `applicationResourceConfigurations.cmmfCodingConfiguration.cmmfProfile` field of the CMMF Configuration Information document. The purpose of the parameter is for capability conformance to be assessed by a recipient before attempting to retrieve and/or parse the contents of a received document.

EXAMPLE: `application/cmmf-configuration-information+json;`
`cmmfProfiles="org.etsi.cmmf.a";cmmfCodeTypes="0"`

D.3.3.3.4.4 cmmfCodeTypes parameter

The `cmmfCodeTypes` parameter to be used with the MIME media type registered in clause D.3.3.3.4.2 is specified in Table D.6.

Table D.6: cmmfCodeTypes parameter definition for CMMF Configuration Information document MIME media type

Parameter	Value
Parameter name	`cmmfCodeTypes`
Parameter value	A comma-separated list of CMMF code type values as specified in clause 6.1.4.5 of ETSI TS 103 973 which are provided within `applicationResourceConfigurations.cmmfCodingConfiguration.cmmfCodeType` field of the CMMF Configuration Information document. The purpose of the parameter is for capability conformance to be assessed by a recipient before attempting to retrieve and/or parse the contents of a received document.

EXAMPLE: `application/cmmf-configuration-information+json;`
`cmmfProfiles="org.etsi.cmmf.a";`**`cmmfCodeTypes="0"`**

D.3.4 Example CMMF Configuration Information document

An example of the CMMF Configuration Information document is provided in this clause. The example assumes the following:

- The application resource is the MPEG-DASH MPD shown in Listing D.5 below and available at the hypothetical location `https://www.example.com/manifest.mpd`.
- Video and audio segments are intended to be obtained from CMMF Transport Objects located at the identified service locations. However, the CMMF Receiver should obtain video and audio initialization segment source objects from the identified service locations instead of their corresponding CMMF Transport Objects.
- CMMF Transport Objects and source objects are hosted at service locations with base URLs `https://www.cdn-a.example.com` and `https://www.cdn-b.example.com`.

Listing D.5: Example MPEG-DASH MPD

```
<?xml version="1.0" encoding="UTF-8"?>
<MPD
    xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
    xmlns="urn:mpeg:dash:schema:mpd:2011"
    xsi:schemaLocation="urn:mpeg:dash:schema:mpd:2011 DASH-MPD.xsd"
    type="static"
    minBufferTime="PT4S"
    profiles="urn:mpeg:dash:profile:isoff-live:2011"

    <Period id="1">
        <!-- Video -->
        <AdaptationSet
            mimeType="video/mp4"
            codecs="avc1.4D401F"
            frameRate="30000/1001"
            segmentAlignment="true"
            startWithSAP="1">
            <SegmentTemplate timescale="90000" initialization="video/$Bandwidth%/init.mp4v"
            media="video/$Bandwidth%/$Number$.mp4v" startNumber="1">
                <SegmentTimeline>
                    <S t="0" d="180180" r="432"/>
                </SegmentTimeline>
            </SegmentTemplate>
            <Representation id="v0" width="320" height="240" bandwidth="250000"/>
            <Representation id="v1" width="640" height="480" bandwidth="500000"/>
            <Representation id="v2" width="960" height="720" bandwidth="1000000"/>
        </AdaptationSet>
        <!-- Audio -->
        <AdaptationSet mimeType="audio/mp4" codecs="mp4a.40" lang="en" segmentAlignment="0"
        startWithSAP="1">
            <SegmentTemplate timescale="48000" initialization="audio/en/init.mp4a"
            media="audio/en/$Number$.mp4a" startNumber="1">
                <SegmentTimeline>
                    <S t="0" d="96000" r="432"/>
                </SegmentTimeline>
            </SegmentTemplate>
            <Representation id="a0" bandwidth="64000"/>
        </AdaptationSet>
    </Period>
</MPD>
```

The CMMF Configuration Information document corresponding to the MPEG-DASH MPD shown above is provided in Listing D.6 below. It references the location of the MPEG-DASH MPD using the `applicationResourceLocators` parameter and its construction overwrites the service locations declared for the MPEG-DASH presentation. It defines two `applicationResourceConfigurations`. The first applies to all video and audio segments listed in the MPD and identified by the URL sub-paths `video/` and `audio/` except the initialization segments identified by the URL sub-paths `init.mp4v` and `init.mp4a`. The second applies to just the initialization segments.

Upon receipt of a request to obtain a media resource listed within the MPD belonging to the first application resource configuration, the CMMF Receiver creates two requests (since two service locations are provided) for the CMMF Transport Objects corresponding to the media resource. It replaces the scheme and host name of the requested media resource with the `baseURL` and inserts a CMMF bitstream variant tag (e.g. `cmmf-variant-a` or `cmmf-variant-b`) within the URL. As an example:

- A request for the video segment with URL `https://example.com/video/250000/1.mp4v` is made by the CMMF-Aware Client.
- Since `cmmfCodingConfiguration` is defined and assuming the CMMF receiver supports both `cmmfCodeType` `0` and `cmmfProfile` `org.etsi.cmmf.a`, the CMMF Receiver creates two requests for the CMMF Transport Objects associated with the video segment. These include: `https://cdn-a.example.com/video/250000/cmmf-variant-a/1.mp4v` and `https://cdn-b.example.com/video/250000/cmmf-variant-b/1.mp4v`.
- The CMMF Receiver requests the two CMMF Transport Objects simultaneously using the above URLs and recovers the video segment once it can fully decode the received CMMF Transport Object information.

Upon receipt of a request to obtain a media resource listed within the MPD belonging to the second application resource configuration, the CMMF Receiver creates a single request to obtain the source object since `cmmfCodingConfiguration` is not defined. The CMMF Receiver selects a service location to obtain the source object and retrieves it. For example, the initialization segment with URL `https://example.com/video/250000/init.mp4v` is downloaded using the URL `https://cdn-a.example.com/video/250000/1.mp4v`.

In both cases, the CMMF Receiver provides the requested media resource to the CMMF-Aware Application once the source object has been recovered.

Listing D.6: Example CMMF Configuration Information document

```
{
  "version": 0,
  "ttl": 600,
  "applicationResourceLocators": [
    {
      "locator": "https://www.example.com/manifest.mpd",
      "contentType": "application/dash+xml"
      "isManifest": true,
    },
  ],
  "applicationResourceConfigurations": [
    {
      "admissionRules": {
        "applicationResourcePathPattern": ["video/", "audio/"],
      },
      "exclusionRules": {
        "applicationResourcePathPattern": ["init.mp4v", "init.mp4a"],
      },
      "serviceLocations": [
        {
          "variantId": "cmmf-variant-a",
          "baseUrl": "https://cdn-a.example.com",
          "requestPathMaps": [
            {
              "requestPathPattern": "\/(?=[^\/]*$)",
              "mappedPath": "/cmmf-variant-a/"
            }
          ]
        },
        {
          "variantId": "cmmf-variant-b",
          "baseUrl": "https://cdn-b.example.com",
          "requestPathMaps": [
            {
              "requestPathPattern": "\/(?=[^\/]*$)",
              "mappedPath": "/cmmf-variant-b/"
            }
          ]
        }
      ],
      "cmmfCodingConfiguration": {
        "cmmfVersion": 0,
        "cmmfCodeType": 0,
        "cmmfProfile": "org.etsi.cmmf.a",
      }
    },
    {
      "serviceLocations": [
        {
          "baseUrl": "https://cdn-a.example.com",
        },
        {
          "baseUrl": "https://cdn-b.example.com",
        }
      ]
    }
  ]
}
```

Annex E (normative): CMMF Encoder configurations

E.0 Introduction

This annex defines configurations for use by a CMMF Encoder to create CMMF bitstreams/Transport Objects conforming to the CMMF bitstream specified in clauses 5 and 6.

E.1 Base CMMF Encoder configuration

E.1.1 Introduction

This clause defines a base CMMF encoder configuration for use when configuring a CMMF Encoder that generates CMMF bitstreams/Transport Objects conforming to the CMMF bitstream specified in clauses 5 and 6.

The CMMF encoder configuration specified within this clause is intended to be used to configure only the process for encoding CMMF bitstreams and/or creating CMMF Transport Objects. Therefore, the following apply:

- A process external to the CMMF Encoder receives and processes requests (e.g. from a CMMF Receiver) for a CMMF bitstream/Transport Object.
- A process external to the CMMF Encoder identifies and obtains the content required by the CMMF Encoder to create the requested CMMF bitstream/Transport Object. This content may consist of the original media resource/source object, a pre-existing CMMF bitstream/Transport Object, multiple pre-existing CMMF bitstreams/Transport Objects, etc.
- On receipt of a request to create a CMMF bitstream/Transport Object and the content to be encoded or re-encoded, the CMMF Encoder creates a new CMMF bitstream/Transport Object and makes it available to a process external to the CMMF Encoder for further processing (e.g. delivery, caching, etc.).

It is further assumed that the following information is made available to the CMMF Encoder when it is triggered to produce a new CMMF bitstream/Transport Object:

- The CMMF Encoder configuration as specified in clauses E.1.2 and E.1.3.
- In the case where the request URL is used to determine the construction of the CMMF bitstream/Transport Object (e.g. see clause D.3), the request URL containing the required representation/variant information.
- The media resource (e.g. source object, pre-existing CMMF bitstream/Transport Object, etc.) to be used when creating the new CMMF bitstream/Transport Object.

E.1.2 Semantics of the CMMF Encoder configuration

The semantics of the CMMF encoder configuration are specified in Annex E.

Table E.1: Semantics of the CMMF Encoder configuration

Property Name	Use	Description
`cmmfConfigurationInformationLocator`	`O`	A URL to the CMMF Configuration Information as specified in clause D.3.3. This URL may be used by the CMMF Encoder to obtain the CMMF Configuration Information which can then be used to determine which CMMF bitstream variant to create when a request URL is received for a CMMF Transport Object.
`bitstreamVersion`	`M`	The version of CMMF bitstream syntax as specified in clause 6.1.3.2. The present document specifies the CMMF bitstream syntax version 0.

Property Name	Use	Description
bitstreamId	O	A bitstream identifier as specified in clause 6.1.2.4. If present, all CMMF bitstreams shall have a bitstream_id of bitstreamId. If absent, the bitstream_id value is randomly generated.
contentSourceType	OD Default "000b"	A content source type as specified in clause 6.1.4.2. If absent, the default value shall be 000b (Not indicated)
codeType	M	A CMMF code type as specified in clause 6.1.4.5.
profile	M	A CMMF profile as specified in clause 6.1.4.11.
profileDescription	O	A profile description as specified in clause 6.1.4.12. If present, the profile-specific information contained in profileDescription takes precedence over the values contained in this configuration if defined. If absent, the profile_description field within the bitstream_header() structure is either generated by the CMMF Encoder based the settings contained in this configuration or is 0 depending on the profile semantics.
blockSizeToBlockNumSymbolsMaps	O	An array of block size map objects that provides a mapping between the source object size and block_num_symbols as specified in clause 6.1.5.5. If present, the map is used to determine block_num_symbols. If absent, the CMMF Encoder shall determine block_num_symbols.
blockSizeMin	M	The minimum source object size in bytes for which the block size map object applies.
blockSizeMax	M	The maximum source object size in bytes for which the block size map object applies.
blockNumSymbols	M	The block_num_symbols used if the source object size is within the range [blockSizeMin, blockSizeMax].
symbolsPresentTarget	O	The percentage of packet() subatoms present within the bitstream in the range (0, 100]. If present, the number of packet() subatoms in the bitstream shall be ceil(block_num_symbols x symbolsPresentTarget / 100). If absent, the number of packet() subatoms in the bitstream shall be equal to block_num_symbols.
liveStreamingBlockSymbolSize	OD Default 10 000	The block_symbol_size in bytes to use if contentSourceType is 011b and the source object size is unknown (i.e. content_source_size as specified in clause 6.1.4.1 is 0). This parameter is ignored otherwise. If absent, contentSourceType is 011b, and the source object size is unknown, the default block_symbol_size is 10 000 bytes.
symbolArrangementMap	O	An array of symbol arrangement map objects that provides the order of packet() subatoms within the bitstream based on the packet_symbol_index as specified in clause 6.1.7.4. This parameter is only valid when: - codeType is 0, xcdInformation.coefficientType is either block_prng or packet_prng, and signalSystematicSymbols is *True*; or - codeType is 1 (Raptor), 5 (Reed-Solomon), or 6 (RaptorQ). If present, the cmmfConfigurationInformationLocator shall also be present. If absent, the order of packet() subatoms is determined by the CMMF Encoder.
variantId	M	The CMMF bitstream variant for which the symbol order applies. The variantId may be provided to the CMMF Encoder within the received request URL (e.g. as a subpath) or via other means.

Property Name	Use	Description
symbolOrder	M	An array of symbol indexes (i.e. packet_symbol_index) providing the order in which packet() subatoms shall appear within the CMMF bitstream. When codeType is 0, xcdInformation.coefficientType is block_prng or packet_prng, and signalSystematicSymbols is *True*, the symbol indexes refer to the source symbol indexes of the systematically encoded symbols. When codeType is 1 (Raptor), 5 (Reed-Solomon), or 6 (RaptorQ), the symbol indexes refer to the encoding symbol ID (ESI).
xcdInformation	O	An object that provides additional configuration information. These parameters are only valid when codeType is 0 and shall be ignored otherwise.
blockFieldSizeExponent	OD Default 1	The field size exponent defining the Galois field used during encoding as specified in clause 6.1.5.23. If absent, the field size exponent shall be 1.
coefficientType	OD Default vector	The coding coefficient type to use. Possible values include block_prng (see clause F.1.3.3.2), packet_prng (see clause F.1.3.3.3), or vector (see clause F.1.3.3.4). If absent, coefficient information will be communicated within a coefficient vector.
signalSystematicSymbols	OD Default False	Determines if systematically encoded symbols are signaled within the bitstream. If absent, systematic encoded symbols are not signaled within the bitstream (i.e. b_systematic_symbol = False)
coefficientInformation	O	An object providing coding coefficient information for the generation/population of coefficient information within the CMMF bitstream. If absent, the default values for each property specified within this object are used.
prngParameters	O	An array of PRNG parameter objects providing the parameters used to produce a pseudo-random number describing the coding coefficients. These parameters only apply when coefficientType is either block_prng or packet_prng, and shall be ignored otherwise. If present, either blockPrngSeed or packetPrngSeeds shall be defined. If absent, the default values are used.
variantId	M	The CMMF bitstream variant for which the PRNG parameters apply. The variantId may be provided to the CMMF Encoder within the received request URL (e.g. as a subpath) or via other means.
blockPrngSeed	CM	A seed value used to initialize the PRNG for generating coding coefficients for the block as specified in clause 6.1.5.25.3. This parameter is only valid when coefficientType is block_prng and shall be ignored otherwise. If absent, a random seed value is used.
packetPrngSeeds	CM	An array of seed values used to initialize the PRNG for generating coding coefficients for each packet() as specified in clause 6.1.5.25.3. The array shall be greater than block_num_symbols long. This parameter is only valid when coefficientType is packet_prng and shall be ignored otherwise. If absent, random seed values are used.
prngDensityPercentage	O	The PRNG density as specified in clause 6.1.5.25.4. If absent, the density is maximized for the defined blockFieldSizeExponent.
coefficientVectorMaps	O	An array of coefficient vector maps providing pre-determined coding coefficient vectors for the CMMF bitstream variant indicated. The parameter is only valid when coefficientType is vector and ignored otherwise. If coefficientType is vector and the absent or a coefficient vector map is not defined for a particular variantId, numSymbols, and fieldSizeExp, the CMMF Encoder will randomly generate all necessary coding coefficient vectors.

Property Name	Use	Description
variantId	M	The CMMF bitstream variant the symbol order applies. The variantId may be provided to the CMMF Encoder within the received request URL (e.g. as a subpath) or via other means.
numSymbols	M	A number used to identify the coding coefficient vectors to use (e.g. the coefficient vector map is selected if numSymbols is equal to block_num_symbols).
fieldSizeExp	M	The field size exponent defining the Galois field for the provided coding coefficient vectors as specified in clause 6.1.5.23.
coefficientVectors	M	An array of coding coefficient vectors. Each element is a bit string of length numSymbols x fieldSizeExp as specified in clause 6.1.15.1.
encryptionParameters	O	An object providing CMMF bitstream encryption parameters used to encrypt coding coefficient information. If present, coding coefficient information is encrypted. If absent, coding coefficient information is not encrypted.
encryptionServiceEndpoint	M	A URL to the endpoint where a CMMF Encoder and Decoder can obtain a bitstream encryption key.
bitstreamEncryptionKeyId	O	A bitstream encryption key identifier as specified in clause 6.1.4.15. If absent, bitstream_encryption_key_id shall be obtained from encryptionServiceEndpoint.
blockEncryptionMode	OD Default 0100b	The block encryption mode as specified in clause 6.1.5.24.5. If absent, block_cc_encryption_mode is 0100b (Counter).
blockKeySizeExp	OD Default 8	The key size exponent used to encrypt coding coefficient information as specified in clause 6.1.5.24.6. If absent, block_cce_key_size_exp is 8.
blockIntegrity	O	An object that provides parameters when block integrity checks are to be used as specified in clause 6.1.13. If present, block integrity is used within the bitstream. If absent, block integrity is not used.
hashType	OD Default 00b	The hash type used on the source object as specified in clause 6.1.13.1. If absent, hash type shall be 00b (i.e. the hash is calculated on the full source object or block of source data)
hashAlgorithm	OD Default 000b	The algorithm used to calculate the hash as specified in clause 6.1.13.2. If absent, the hash algorithm shall be 000b (i.e. SHA-1 [9]).
packetIntegrity	O	An object that provides parameters when packet integrity checks are used to verify the integrity of data in packet() subatoms as specified in clause 6.1.14. If present, packet integrity is used. If absent, packet integrity is not used.
hashAlgorithm	OD Default 010b	The algorithm used to verify the integrity of data in packet() subatoms as specified in clause 6.1.14. If absent, the hash algorithm shall be 010b (i.e. MD5 [21])
hashSize	OD Default 011b	The hash size as specified in clause 6.1.14.2. If absent, the has size shall be 011b (i.e. 128 bits)

Key
M=mandatory, O=optional, OD=optional with default value, CM=conditionally mandatory

E.1.3 Schema of the CMMF Encoder configuration

A JSON schema is provided in Listing E.1 below for the CMMF Encoder configuration.

An informative copy of the JSON Schema Definition with filename `cmmf_encoder_configuration_schema.json` is included in archive ts_103973v010201p0.zip which accompanies the present document.

Listing E.1: CMMF Encoder configuration schema

```
{
  "type": "object",
  "properties": {
    "cmmfConfigurationInformationLocator": {
      "description": [
        "A URL to the CMMF Configuration Information associated with the CMMF Transport Objects"
        "the CMMF Encoder will generate."
      ],
      "type": "string"
    },
    "bitstreamVersion": {
      "description": "The version of CMMF bitstream syntax to use. The value shall be 0",
      "type": "integer",
      "const": 0
    },
    "bitstreamId": {
      "description": "A bitstream identifier that will be added to each CMMF bitstream.",
      "type": "string"
    },
    "contentSourceType": {
      "description": "A content source type as specified in clause 6.1.4.2.",
      "type": "string",
      "enum": ["000b", "001b", "011b"],
      "default": "000b"
    },
    "codeType": {
      "description": "A CMMF code type as specified in clause 6.1.4.5.",
      "type": "integer",
      "enum": [0, 1, 5, 6]
    },
    "profile": {
      "description": [
        "A CMMF profile as specified in clause 6.1.4.11. The value shall be org.etsi.cmmf.a."
      ],
      "type": "string"
    },
    "profileDescription": {
      "description": [
        "A CMMF profile description as in clause 6.1.4.12."
      ],
      "type": "string"
    },
    "blockSizeToBlockNumSymbolsMaps": {
      "description": "Array of block size map objects.",
      "type": "array",
      "items": {
        "type": "object",
        "properties": {
          "blockSizeMin": {
            "description": "The minimum source object size in bytes.",
            "type": "integer"
          },
          "blockSizeMax": {
            "description": "The maximum source object size in bytes.",
            "type": "integer"
          },
          "blockNumSymbols": {
            "description": [
               "The block_num_symbols used if the source object size is within",
               "the range [blockSizeMin, blockSizeMax]."
            ],
            "type": "integer"
          }
        },
        "required": ["blockSizeMin", "blockSizeMax", "blockNumSymbols"]
      }
    },
```

```
    "symbolsPresentTarget": {
      "description": "The percentage of packet() subatoms present within the bitstream.",
      "type": "integer",
      "minimum": 1,
      "maximum": 100
    },
    "liveStreamingBlockSymbolSize": {
      "description": [
        "The block_symbol_size in bytes if contentSourceType is 011b and the source object",
        "size is unknown."
      ],
      "type": "integer",
      "default": 10000
    },
    "symbolArrangementMap": {
      "description": "Array of symbol arrangement objects.",
      "type": "array",
      "items": {
        "type": "object",
        "properties": {
          "variantId": {
            "description": "The CMMF bitstream variant for which the symbol order applies.",
            "type": "string"
          },
          "symbolOrder": {
            "description": [
              "An array of symbol indexes describing the order in which packet() subatoms",
              "shall appear within the CMMF bitstream."
            ],
            "type": "array",
            "items": {
              "type": "integer"
            }
          }
        },
        "required": ["variantId", "symbolOrder"]
      }
    },
    "xcdInformation": {
      "description": [
        "An object providing additional configuration information when codeType is 0."
      ],
      "type": "object",
      "properties": {
        "blockFieldSizeExponent": {
          "description": "The field size exponent defining the Galois field used.",
          "type": "integer",
          "enum": [1, 2, 4, 8, 16],
          "default": 1
        },
        "coefficientType": {
          "description": "The coding coefficient type to use.",
          "type": "string",
          "enum": ["block_prng", "packet_prng", "vector"],
          "default": "vector"
        },
        "signalSystematicSymbols": {
          "description": [
            "Systematically encoded symbols are signalled within the bitstream."
          ],
          "type": "boolean",
          "default": false
        },
        "coefficientInformation": {
          "description": [
            "An object providing coding coefficient information."
          ],
          "type": "object",
          "properties": {
            "prngParameters": {
              "description": [
                "An object providing the parameters used to produce a pseudo-random number",
                "describing the coding coefficients."
              ],
              "type": "array",
              "items": {
                "type": "object",
                "properties": {
```

```
            "variantId": {
              "description": [
                "The CMMF bitstream variant for which the PRNG parameters apply."
              ],
              "type": "string"
            },
            "blockPrngSeed": {
              "description": [
                "A seed value to initialize the PRNG for generating coding coefficients",
                "when coefficientType is block_prng."
              ],
              "type": "integer"
            },
            "packetPrngSeeds": {
              "description": [
                "An array of seed values used to initialize the PRNG for generating coding",
                "coefficients for each packet() when coefficientType is packet_prng."
              ],
              "type": "array",
              "items": {
                "type": "integer"
              }
            },
            "prngDensityPercentage": {
              "description": "The PRNG density.",
              "type": "number",
              "minimum": 0.0,
              "maximum": 1.0,
            }
          },
          "oneOf": [
            {"required": ["variantId", "blockPrngSeed"]},
            {"required": ["variantId", "packetPrngSeeds"]}
          ]
        }
      },
      "coefficientVectorMaps": {
        "description": [
          "An array of coefficient vector maps providing pre-determined coding",
          "coefficient vectors."
        ],
        "type": "array",
        "items": {
          "type": "object",
          "properties": {
            "variantId": {
              "description": [
                "The CMMF bitstream variant for which the symbol order applies."
              ],
              "type": "string"
            },
            "numSymbols": {
              "description": [
                "The number of symbols for which the coding coefficient vectors are",
                "defined."
              ],
              "type": "integer",
            },
            "fieldSizeExp": {
              "description": [
                "The field size exponent defining the Galois field for which the",
                "coding coefficient is defined."
              ],
              "type": "integer",
              "enum": [1, 2, 4, 8, 16]
            },
            "coefficientVectors": {
              "description": [
                "An array of coding coefficient vectors."
              ],
              "type": "array",
              "items": {
                "type": "string",
              }
            }
          },
          "required": ["variantId", "numSymbols", "fieldSizeExp", "coefficientVectors"]
        }
```

```
            }
          }
        },
        "encryptionParameters": {
          "description": [
            "An object providing CMMF bitstream encryption parameters used to encrypt"
            "systematically encoded symbols and coding coefficient information."
          ],
          "type": "object",
          "properties": {
            "encryptionServiceEndpoint": {
              "description": [
                "A URL to the endpoint where a CMMF Encoder or Decoder can obtain a",
                "bitstream encryption key."
              ],
              "type": "string"
            },
            "bitstreamEncryptionKeyId": {
              "description": [
                "A bitstream encryption key identifier.",
              ],
              "type": "string"
            },
            "blockEncryptionMode": {
              "description": [
                "The block encryption mode.",
              ],
              "type": "string",
              "enum": ["0000b", "0001b", "0010b", "0011b", "0100b", "0101b"]
            },
            "blockKeySizeExp": {
              "description": [
                "The key size exponent used.",
              ],
              "type": "integer",
              "default": 8
            }
          },
          "required": ["encryptionServiceEndpoint"]
        }
      }
    },
    "blockIntegrity": {
      "description": [
        "An object providing parameters when block integrity checks are to be used."
      ],
      "type": "object",
      "properties": {
        "hashType": {
          "description": "The hash type used on the source object.",
          "type": "string",
          "enum": ["00b", "01b"],
          "default": "00b"
        },
        "hashAlgorithm": {
          "description": "The algorithm used to calculate the hash.",
          "type": "string",
          "enum": ["000b", "001b", "010b"],
          "default": "000b"
        }
      }
    },
    "packetIntegrity": {
      "description": [
        "An object providing parameters when packet integrity checks are to be used."
      ],
      "type": "object",
      "properties": {
        "hashAlgorithm": {
          "description": [
            "The algorithm used to verify the integrity of data provided in packet() subatoms."
          ],
          "type": "string",
          "enum": ["000b", "001b", "010b"],
          "default": "010b"
        },
        "hashSize": {
          "description": "The hash size used.",
```

```
          "type": "string",
          "enum": ["000b", "001b", "010b", "011b", "100b", "101b", "110b", "111b"],
          "default": "011b"
        },
      },
    },
  },
  "required": ["bitstreamVersion", "codeType", "profile"]
}
```

E.1.4 IANA registration of CMMF Encoder configuration

E.1.4.1 General

This clause provides the formal MIME type registration for the CMMF Encoder configuration compliant with the JSON schema specified in clause E.1.3. It is referenced from the registry at http://www.iana.org/assignments/media-types.

E.1.4.2 Registration of MIME media type for CMMF Encoder configuration

The MIME Type and Subtype are defined as follows:

- MIME media type name: `application`
- MIME subtype name: `cmmf-encoder-configuration+json`
- Required parameters: None
- Optional parameters: `profile` (see clause E.1.4.3 of ETSI TS 103 973)
  `codeType` (see clause E.1.4.4 of ETSI TS 103 973)
- Encoding considerations: This is a JSON document, and the encoding considerations are the same as for media type *application/json* defined in IETF RFC 8259 [25].
- Security considerations: This media format is a JSON document and inherits the security considerations provided in IETF RFC 8259 [25].

  The format does not incorporate any active or executable content. However, other forms of material from outside resources can be referenced by the format, and this material can contain active or executable content. Such material is expected to be identified by its own MIME type, and the security considerations of that format should be taken into account.

  This format is highly susceptible to manipulation or spoofing for attacks designed to inject fake information. Both integrity protection and source authentication are recommended to prevent misleading of the recipient.
- Interoperability considerations: None
- Published specification: ETSI TS 103 973 (the present document)
- Applications which use this media type: The CMMF Encoder configuration may be used by CMMF Bitstream Generators/Sources used to configure encoding of media resources into one or more CMMF bitstreams/Transport Objects.
- Additional information:
  - File extension(s): `json`
  - Intended usage: `COMMON`
- Other information/general comment: None
- Restrictions on usage: None

- Author/Change controller: ETSI

E.1.4.3 profile parameter

The `profile` parameter to be used with the MIME media type registered in clause E.1.4.2 is specified in Table E.2.

Table E.2: profile parameter definition for CMMF Encoder configuration MIME media type

Parameter	Value
Parameter name	profile
Parameter value	The CMMF bitstream profile identifier as specified in annex F of ETSI TS 103 973 which is provided within profile field of the CMMF Encoder configuration document. The purpose of the parameter is for capability conformance to be assessed by a recipient before attempting to retrieve and/or parse the contents of a received document.

EXAMPLE: `application/cmmf-encoder-configuration+json;`
`profile="org.etsi.cmmf.a";codeType="0"`

E.1.4.4 codeType parameter

The `codeType` parameter to be used with the MIME media type registered in clause E.1.4.2 is specified in Table E.3.

Table E.3: codeType parameter definition for CMMF Encoder configuration MIME media type

Parameter	Value
Parameter name	`codeType`
Parameter value	The CMMF code type value as specified in clause 6.1.4.5 of ETSI TS 103 973 which is provided within `codeType` field of the CMMF Encoder configuration document. The purpose of the parameter is for capability conformance to be assessed by a recipient before attempting to retrieve and/or parse the contents of a received document.

EXAMPLE: `application/cmmf-encoder-configuration+json;`
`profile="org.etsi.cmmf.a";codeType="0"`

E.1.5 Example use of CMMF Encoder configuration

An example of the CMMF Encoder configuration is provided in Listing E.2 below. For example, it can be used to create the CMMF bitstreams provided in clause C.1. The example makes the following assumptions:

- A difference between the subatom constructions in clause C.1 and the example is the inclusion of the profile information within the `bitstream_header()` subatom.
- The CMMF Configuration Information document (see clause D.3.3) describing the CMMF bitstream variants is available at `https://www.example.com/cmmf_ci_manifest.mpd`.

Listing E.2: Example CMMF Encoder configuration

```
{
  "cmmfConfigurationInformationLocator": "https://www.example.com/cmmf_ci_manifest.mpd",
  "bitstreamVersion": 0,
  "contentSourceType": "001b",
  "codeType": 0,
  "profile": "org.etsi.cmmf.a",
  "blockSizeToBlockNumSymbolsMaps": [
    {
      "blockSizeMin": 0,
      "blockSizeMax": 128,
      "blockNumSymbols": 1
    },
    {
      "blockSizeMin": 129,
      "blockSizeMax": 1048576,
      "blockNumSymbols": 4
```

```
    },
    {
      "blockSizeMin": 1048577,
      "blockSizeMax": 2097152,
      "blockNumSymbols": 8
    },
    {
      "blockSizeMin": 2097153,
      "blockSizeMax": 4194304,
      "blockNumSymbols": 16
    }
  ],
  "xcdInformation": {
    "signalSystematicSymbols": true,
    "coefficientInformation": {
      "coefficientVectorMaps": [
        {
          "variantId": "cmmf-a",
          "numSymbols": 4,
          "fieldSizeExp": 1,
          "coefficientVectors": ["1000b", "0010b", "0101b", "1111b"]
        },
        {
          "variantId": "cmmf-b",
          "numSymbols": 4,
          "fieldSizeExp": 1,
          "coefficientVectors": ["0100b", "0001b", "1010b", "1111b"]
        },
        {
          "variantId": "cmmf-a",
          "numSymbols": 8,
          "fieldSizeExp": 1,
          "coefficientVectors": [
            "10000000b", "00100000b", "00001000b", "00000010b",
            "00000001b", "00000100b", "00010000b", "11111111b"
          ]
        },
        {
          "variantId": "cmmf-b",
          "numSymbols": 8,
          "fieldSizeExp": 1,
          "coefficientVectors": [
            "01000000b", "00010000b", "00000100b", "00000001b",
            "00000010b", "00001000b", "00100000b", "11111111b"
          ]
        },
        {
          "variantId": "cmmf-a",
          "numSymbols": 16,
          "fieldSizeExp": 1,
          "coefficientVectors": […]
        },
        {
          "variantId": "cmmf-b",
          "numSymbols": 16,
          "fieldSizeExp": 1,
          "coefficientVectors": […]
        }
      ]
    }
  }
}
```

Annex F (normative): CMMF bitstream profiles

F.0 Introduction

This annex defines CMMF bitstream profiles for use when constructing CMMF bitstreams/Transport Objects.

A CMMF bitstream/Transport Object conforms to a CMMF bitstream profile defined within this annex if its construction meets all requirements specified within the defined profile. Conformance may be further parameterized with a specific code type, as specified in clause 6.1.4.5, used during construction of the CMMF bitstream/Transport Object.

A collection, or set, of CMMF bitstreams/Transport Objects associated with the same media resource or source object conforms to a CMMF bitstream profile for a specific code type as defined within this annex if the following conditions are met:

- Every CMMF bitstream/Transport Object within the set conforms to the CMMF bitstream profile for the specific code type in use.
- The set of CMMF bitstream/Transport Objects contains sufficient coded symbols, as specified in clause 6.1.6.2, such that a CMMF Receiver using a hypothetical decoder for the code type in use can reconstruct the entire media resource/source object upon receiving a mathematically sufficient set of coded symbols where each coded symbol is generated according to the encoder specification for the code type in use.

NOTE: Example decoders that fulfil the above requirement for each code type are described in: clause A.2 for `code_type 0` (xCD-1), section 5.5 of IETF RFC 5053 [16] for `code_type 1` (Raptor), section 8.3 of IETF RFC 5510 [14] for `code_type 5` (Reed-Solomon), and section 5.4 of IETF RFC 6330 [13] for `code_type 6` (RaptorQ).

A CMMF Receiver conforms to a CMMF bitstream profile for a specific code type, as specified in clause 6.1.4.5, if it can reconstruct an entire media resource/source object from a CMMF bitstream/Transport Object set conforming to the same CMMF bitstream profile for a specific code type.

F.1 CMMF bitstream profile A

F.1.1 Introduction

While multiple valid CMMF bitstream realizations are possible which conform to clauses 4 and 5, a CMMF bitstream construction profile is specified in this clause for use over HTTP/TCP or other reliable transport protocols. This profile is identified by the profile identifier `org.etsi.cmmf.a`.

F.1.2 CMMF bitstream layout

A single media resource (e.g. a CMAF segment, a media track, or a media file) is first prepared for encoding and encapsulation into a CMMF bitstream/Transport Object. Each media resource shall be treated as a single block for the purposes of encoding it using a supported CMMF code type. The media resource may first be partitioned into `block_num_symbols` equal-sized source symbols, where padding is added if necessary. These source symbols are encoded using a supported CMMF code type where at least `block_num_symbols` encoded symbols are generated. Each encoded symbol is packaged within an individual CMMF `packet()` subatom belonging to one CMMF bitstream/Transport Object (i.e. no two CMMF bitstreams/Transport Objects should contain an identical CMMF `packet()` subatom).

CMMF bitstreams/Transport Objects shall be constructed using the CMMF subatoms and structures as shown in Figure F.1 below. Each CMMF bitstream/Transport Object shall begin with the CMMF synchronization (`sync()`) structure, followed by one bitstream header subatom containing the `bitstream_header()` structure, one block header subatom containing the `block_header()` structure, and one or more packet subatoms each containing the `packet()` structure.




Figure F.1: CMMF bitstream layout for CMMF bitstream profile A

In the case of a live or streaming source where the size of the content being encoded is not known to the CMMF Encoder prior to creating the CMMF bitstream/Transport Object (i.e. the `content_source_size` in the `bitstream_header()` structure and the `block_size` in the `block_header()` structure is `0`), a second block header subatom that updates the original block header subatom may be inserted into the CMMF bitstream/Transport Object once the content's size has been determined. More details are provided in clause F.1.6.

F.1.3 Profile description

F.1.3.1 Introduction

The profile description as specified in clause 6.1.4.12 shall be used to identify the CMMF bitstream profile A options for which the CMMF bitstream/Transport Object conforms. It may be used by a decoder/parser with restricted or limited capabilities to quickly determine if the bitstream can be parsed and decoded.

F.1.3.2 Syntax specification

Table F.1: Syntax of CMMF Bitstream Profile A profile_description

Syntax	Encoding	Clause
`profile_description`		6.1.4.12
{		
`code_type`	u(4)	6.1.4.5
`if (code_type == 0){`		
`block_field_size_exp`	v(3)	6.1.5.23
`coefficient_method`	u(3)	F.1.3.3.1
`b_systematic_symbols_used`	b(1)	F.1.3.3.2
`b_encrypted_coefficients`	b(1)	F.1.3.3.3
}		
`b_block_integrity`	b(1)	F.1.3.3.4
`b_packet_integrity`	b(1)	F.1.3.3.5
`target_symbols_present_percentage`	u(7)	F.1.3.3.6
`padding`	pad	F.1.3.3.7
}		

F.1.3.3 Bitstream description

F.1.3.3.0 Introduction

This clause describes the meaning of the fields in the CMMF Bitstream Profile A `profile_description` syntax.

F.1.3.3.1 coefficient_method

The `coefficient_method` field identifies the method used to generate and/or communicate the coding coefficients for every coded symbol in the CMMF Bitstream/Transport Object when `code_type` is `0` (xCD-1). The different methods are listed in Table F.2.

Table F.2: coefficient_method meaning

`coefficient_method` value	**Meaning**
0	Coefficient vector as specified in clause 5.2.9.
1	Packet seed as specified in clause 5.2.9.
2	Block seed as specified in clause 5.2.5.
3 - 7	Reserved

Depending on the value of `coefficient_method`, certain bits of the `block_mask` in the `block_header()` subatom and the `packet_mask` in each `packet()` subatom contained within the bitstream are set or cleared. The following applies when `b_systematic_symbol` in the `packet()` subatom is cleared:

- If `coefficient_method` is `0`, then:
  - Bit 4 of the `block_mask` in the `block_header()` subatom is cleared.
  - Bit 3 of the `packet_mask` in each `packet()` subatom is cleared.
  - Bit 4 of the `packet_mask` in each `packet()` subatom is set.
- If `coefficient_method` is `1`, then:
  - Bit 4 of the `block_mask` in the `block_header()` subatom is cleared.
  - Bit 3 of the `packet_mask` in each `packet()` subatom is set.
  - Bit 4 of the `packet_mask` in each `packet()` subatom is cleared.

- If `coefficient_method` is 2, then:
  - Bit 4 of the `block_mask` in the `block_header()` subatom is set.
  - Bit 3 of the `packet_mask` in each `packet()` subatom is cleared.
  - Bit 4 of the `packet_mask` in each `packet()` subatom is cleared.

F.1.3.3.2 b_systematic_symbols_used

This Boolean indicates whether the `b_systematic_symbol` may be set within `packet()` subatoms contained within the bitstream. If not set, the `b_systematic_symbol` field shall not be set in any `packet()` subatoms within the bitstream.

F.1.3.3.3 b_encrypted_coefficients

This Boolean indicates whether the coefficient information is encrypted within the bitstream. If set, `b_block_cc_encrypted` shall be set in the `bitstream_header()` subatom.

F.1.3.3.4 b_block_integrity

This Boolean indicates whether the `block_integrity()` structure is present within the `block_header()` subatom. If set, bit 5 of the `block_mask` in the `block_header()` subatom shall be set.

F.1.3.3.5 b_packet_integrity

This Boolean indicates whether the `packet_integrity()` structure is present within each `packet()` subatom. If set, bit 5 of the `packet_mask` in each `packet()` subatom shall be set.

F.1.3.3.6 target_symbols_present_percentage

The field describes the percentage of `block_num_symbols` present within the bitstream. The field is encoded as a fraction in range (0, 1]. The actual percentage is determined by the following equation:

$$\texttt{percent_symbols_present} = 100 \times (\texttt{target_symbols_present_percentage} + 1) / 128$$

When `percent_symbols_present` is 100, `b_sufficient_symbols_present` shall be set in the `block_header()` subatom and the bitstream shall contain at least `block_num_symbols` `packet()` subatoms. When `percent_symbols_present` is less than 100, `b_sufficient_symbols_present` shall be cleared and `block_symbols_present` shall be greater than or equal to the following:

$$\texttt{block_symbols_present} = \texttt{ceil}(\texttt{block_num_symbols} \times \texttt{percent_symbols_present} / 100)$$

F.1.3.3.7 padding

This bit field is used to ensure the total size of `profile_description` is 32 bits.

F.1.4 Required fields and their values

F.1.4.1 Introduction

Several realizations of a CMMF bitstream/Transport Object conforming CMMF bitstream profile A are possible depending on the code type used, how coefficient information is communicated within the CMMF bitstream/Transport Object, etc. This clause provides the required values for the fields of each CMMF structure contained within a CMMF bitstream/Transport Object for each of these realizations.

F.1.4.2 Required Fields and values applying to all CMMF bitstreams

Requirements for the construction of the various structures shown in Figure F.1 are provided within this clause. These requirements shall apply to all CMMF bitstreams conforming to profile A regardless of the CMMF code type in use. Fields not specified in Table F.3 below are either determined during CMMF bitstream preparation, based on the settings of other fields, dependent on the CMMF code type in use, or optional.

Table F.3: Required CMMF bitstream fields and values

CMMF structure	CMMF field name	Value	Bit field encoding
sync()	*b_content_encode_uuid*	TRUE	b(1)
	content_encode_uuid	See clause 6.1.3.4	v(128)
subatom()	*b_bitstream_id_present*	TRUE	b(1)
	bitstream_id	See clause 6.1.2.4	v(16)
bitstream_header()	*b_content_source_split*	FALSE	b(1)
	b_rfc5052	FALSE	b(1)
	block_count_minus1	0	u(8)
	b_content_block_separate_sources	FALSE	b(1)
	b_profile_information_present	TRUE	b(1)
	profile_type_size	15	u(4)
	profile_type	*org.etsi.cmmf.a*	v(120)
	profile_description	See clause F.1.3	v(32)
block_header()	*block_index*	0	u(8)
	b_block_max_symbol_index_present	FALSE	b(1)
	b_block_content_source_index_present	FALSE	b(1)
	b_block_composite_sources	FALSE	b(1)
	b_addl_block_coding_info_present	FALSE	b(1)
	block_mask: Bit 0	1	v(1)
	block_mask: Bit 2	0	v(1)
packet_header()	*packet_mask*: Bit 2	0	v(1)
	packet_mask: Bit 6	0	v(1)
packet()	*coded_symbol*	See clause 6.1.6.2	

The `bitstream_id` in the `subatom()` structure may either be randomly generated at the time the CMMF bitstream/Transport Object is created or deterministically chosen prior to creating the CMMF bitstream/Transport Object.

The `block_size` field in the `block_header()` structure shall be equal to the `content_source_size` field contained within CMMF bitstream's `bitstream_header()` structure.

F.1.4.3 code_type 0 (xCD-1) required fields and values

F.1.4.3.1 Introduction

When `code_type 0` (xCD-1) is used to encode content as specified in annex A, the `code_type` field in the `bitstream_header()` structure and `profile_description` specified in clause F.1.3 shall be set to `0`.

The required fields to support communication of the necessary coefficient information shall also be set. These fields depend on the method in which the coefficient information is communicated within the bitstream. A compliant bitstream shall support only one of the following methods:

- Block PRNG
- Packet PRNG
- Coefficient vector

The required fields and their values for each method used to communicate coefficient information is provided within this clause. Additionally, the required fields and their values when the encoded symbol is systematic and/or coefficient information encryption is used are also provided.

F.1.3.3.2 Block PRNG coefficient information

The required fields and their settings for a bitstream using a block PRNG to communicate `code_type` `0` coefficient information is provided in Table F.4.

The value of `coefficient_method` in the `profile_description` shall also have a value of 2.

Table F.4: Required CMMF bitstream fields and values for code_type 0 using a block PRNG

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
block_header()	*block_mask*: Bit 4	1	v(1)
	prng_parameters()	See Table F.7	
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 0	1	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	0	v(1)
	packet_symbol_index	See clause 6.1.7.4	

F.1.4.3.3 Packet PRNG coefficient information

The required fields and their settings for a bitstream using a packet PRNG to communicate `code_type` `0` coefficient information is provided in Table F.5. The fields for the `packet_header()` structure show the required values when `coded_symbol` is not systematic (see clause F.1.4.3.5 for the required fields and their settings when `coded_symbol` is systematic).

The value of `coefficient_method` in the `profile_description` shall also have a value of 1.

Table F.5: Required CMMF bitstream fields and values for code_type 0 using a packet PRNG

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
block_header()	*block_mask*: Bit 4	0	v(1)
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 0	0	v(1)
	packet_mask: Bit 3	1	v(1)
	packet_mask: Bit 4	0	v(1)
	prng_parameters()	See Table F.7	

F.1.4.3.3 Coefficient vectors coefficient information

The required fields and their settings for a bitstream using a coefficient vector to communicate `code_type` `0` coefficient information is provided in Table F.6. The fields for the `packet_header()` structure show the required values when `coded_symbol` is not systematic or it is not signalled as systematic using the `b_systematic_symbol` field (i.e. the coefficient vector is used to signal `coded_symbol` is systematic). See clause F.1.4.3.5 for the required fields and their settings when `coded_symbol` is systematic and the `b_systematic_symbol` field is set.

The value of `coefficient_method` in the `profile_description` shall also have a value of 0.

Table F.6: Required CMMF bitstream fields and values for code_type 0 using coefficient vectors

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
block_header()	*block_mask*: Bit 4	0	v(1)
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 0	0	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	1	v(1)
	coefficient_vector()	See clause 6.1.15	

F.1.4.3.4 PRNG parameters

A CMMF bitstream using either a block PRNG or packet PRNG to communicate coefficient information shall contain the `prng_parameters()` structure in either the `block_header()` or `packet_header()` structures respectively. The required fields and their values when this structure is present are provided in Table F.7.

Table F.7: Required CMMF bitstream fields and values when prng_parameters() is present

CMMF structure	CMMF field name	Value	Bit field encoding
prng_parameters()	*prng_type*	000b	v(3)
	prng_seed_bits_code	See Table 50	v(2)
	prng_seed	See clause 6.1.5.25.3	
	prng_density_percentage	See clause 6.1.5.25.4	v(7)

F.1.4.3.5 Systematic coded_symbol

In such cases and where `coded_symbol` is systematic, the fields and corresponding values provided in Table F.8 shall be present in the CMMF bitstream.

`b_systematic_symbols_used` in the `profile_description` shall be set if any `packet()` subatoms within the CMMF bitstream has a `packet()` subatom where `b_systematic_symbol` is set. Otherwise, `b_systematic_symbols_used` shall be cleared.

Table F.8: Required CMMF bitstream fields when coded_symbol is systematic

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
packet_header()	*b_systematic_symbol*	TRUE	b(1)
	packet_mask: Bit 0	1	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	0	v(1)
	packet_symbol_index	See clause 6.1.7.4	

F.1.4.3.6 Encrypted coefficient information

F.1.4.3.6.0 General

Coefficient information may be encrypted within the CMMF bitstream when `code_type 0` (xCD-1) is used regardless of the method used to communicate the coefficient information.

When coefficient information is not encrypted, the fields and corresponding values in the CMMF bitstream shall be set according to Table F.9. `b_encrypted_coefficients` in the `profile_description` shall also be cleared.

Table F.9: Field values when encrypted coefficient information is not used

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
	b_block_cc_encrypted	FALSE	b(1)
block_header()	*block_mask*: Bit 3	0	v(1)
packet_header()	*packet_mask*: Bit 1	0	v(1)

When coefficient information is encrypted, the fields and values present in the CMMF bitstream are provided below. Furthermore, `b_encrypted_coefficients` in the `profile_description` shall be set.

F.1.4.3.6.1 Encrypted block PRNG coefficient information

Table F.10 provides the required fields and values when `code_type` is `0` (xCD-1), coefficient information is communicated using a block PRNG, the `coded_symbol` is not systematic, and the coefficient information is encrypted.

Table F.10: Field values when block PRNG coefficient information is encrypted

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
	b_block_cc_encrypted	TRUE	b(1)
	bitstream_encryption_key_id	See clause 6.1.4.15	
block_header()	*block_mask*: Bit 3	1	v(1)
	block_mask: Bit 4	1	v(1)
	block_cc_encryption_algorithm	000b	v(3)
	block_cc_encryption_mode	See clause 6.1.5.24.5	
	block_cce_key_size_exp	See clause 6.1.5.24.6	
	block_cce_key	See clause 6.1.5.24.6	
	b_addl_block_cce_params_present	See clause 6.1.5.24.7	
	addl_cce_parameters()	See clause 6.1.5.24.8	
	prng_parameters()	See Table F.7	
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 0	1	v(1)
	packet_mask: Bit 1	0	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	0	v(1)
	packet_symbol_index	See clause 6.1.7.4	

NOTE: All fields contained between `/* block encryption info start */` and `/* block encryption info end */` within the `block_header()` structure are encrypted using the bitstream encryption key with ID `bitstream_encryption_key_id` and all fields contained between `/* prng_parameters() encryption info start */` and `/* prng_parameters() encryption info end */` in the `prng_parameters()` structure contained within the `block_header()` structure is encrypted using the `block_cce_key` and `addl_cce_parameters()`.

F.1.4.3.6.2 Encrypted packet PRNG coefficient information

Table F.11 provides the required fields and values when `code_type` is `0` (xCD-1), coefficient information is communicated using a packet PRNG, the `coded_symbol` is not systematic, and the coefficient information is encrypted.

Table F.11: Field values when packet PRNG coefficient information is encrypted

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
	b_block_cc_encrypted	TRUE	b(1)
	bitstream_encryption_key_id	See clause 6.1.4.15	
block_header()	*block_mask*: Bit 3	1	v(1)
	block_mask: Bit 4	0	v(1)
	block_cc_encryption_algorithm	000b	v(3)
	block_cc_encryption_mode	See clause 6.1.5.24.5	
	block_cce_key_size_exp	See clause 6.1.5.24.6	
	block_cce_key	See clause 6.1.5.24.6	
	b_addl_block_cce_params_present	See clause 6.1.5.24.7	
	addl_cce_parameters()	See clause 6.1.5.24.8	
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 1	1	v(1)
	packet_mask: Bit 3	1	v(1)
	packet_mask: Bit 4	0	v(1)
	b_addl_packet_cce_params_present	See clause 6.1.7.5.2	
	addl_cce_parameters()	See clause 6.1.5.24.8	
	prng_parameters()	See Table F.7	

NOTE: All fields contained between `/* block encryption info start */` and `/* block encryption info end */` within the `block_header()` structure are encrypted using the bitstream encryption key with ID `bitstream_encryption_key_id`. All fields contained between `/* prng_parameters() encryption info start */` and `/* prng_parameters() encryption info end */` in the `prng_parameters()` structure is encrypted using the `block_cce_key` and `addl_cce_parameters()` contained within the `packet_header()` structure.

F.1.4.3.6.3 Encrypted coefficient vector information

Table F.12 provides the required fields and values when `code_type` is `0` (xCD-1), coefficient information is communicated using a coefficient vector, the `coded_symbol` is not systematic or signalled as being systematic (i.e. `b_systematic_symbol` is cleared), and the coefficient information is encrypted.

Table F.12: Field values when packet coefficient vector information is encrypted

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
	b_block_cc_encrypted	TRUE	b(1)
	bitstream_encryption_key_id	See clause 6.1.4.15	
block_header()	*block_mask*: Bit 3	1	v(1)
	block_mask: Bit 4	0	v(1)
	block_cc_encryption_algorithm	000b	v(3)
	block_cc_encryption_mode	See clause 6.1.5.24.5	
	block_cce_key_size_exp	See clause 6.1.5.24.6	
	block_cce_key	See clause 6.1.5.24.6	
	b_addl_block_cce_params_present	See clause 6.1.5.24.7	
	addl_cce_parameters()	See clause 6.1.5.24.8	
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 1	1	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	1	v(1)
	b_addl_packet_cce_params_present	See clause 6.1.7.5.2	
	addl_cce_parameters()	See clause 6.1.5.24.8	
	coefficient_vector()	See clause 6.1.15	

NOTE: All fields contained between `/* block encryption info start */` and `/* block encryption info end */` within the `block_header()` structure are encrypted using the bitstream encryption key with ID `bitstream_encryption_key_id`. The `coefficient_vector()` structure is encrypted using the `block_cce_key` and `addl_cce_parameters()` contained within the `packet_header()` structure.

F.1.4.3.6.4 Encrypted systematic coded_symbol

Table F.13 provides the required fields and values when `code_type` is `0` (xCD-1), the `coded_symbol` is systematic (i.e. `b_systematic_symbol` is set), and coefficient information is encrypted.

Table F.13: Field values when systematic coded_symbol is encrypted

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	0	u(4)
	b_block_cc_encrypted	TRUE	b(1)
	bitstream_encryption_key_id	See clause 6.1.4.15	
block_header()	*block_mask*: Bit 3	1	v(1)
	block_cc_encryption_algorithm	000b	v(3)
	block_cc_encryption_mode	See clause 6.1.5.24.5	
	block_cce_key_size_exp	See clause 6.1.5.24.6	
	block_cce_key	See clause 6.1.5.24.6	
	b_addl_block_cce_params_present	See clause 6.1.5.24.7	
	addl_cce_parameters()	See clause 6.1.5.24.8	
packet_header()	*b_systematic_symbol*	TRUE	b(1)
	packet_mask: Bit 0	1	v(1)
	packet_mask: Bit 1	1	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	0	v(1)
	packet_symbol_index	See clause 6.1.7.4	
	b_systematic_symbol_encrypted	TRUE	b(1)
	b_addl_packet_cce_params_present	See clause 6.1.7.5.2	
	addl_cce_parameters()	See clause 6.1.5.24.8	

NOTE: All fields contained between `/* block encryption info start */` and `/* block encryption info end */` within the `block_header()` structure are encrypted using the bitstream encryption key with ID `bitstream_encryption_key_id`. The systematic coded_symbol within the `packet()` structure is encrypted using the `block_cce_key` and `addl_cce_parameters()` contained within the `packet_header()` structure.

F.1.4.4 code_type 1 (Raptor), 5 (Reed-Solomon), and 6 (RaptorQ) required fields and values

When `code_type` `1` (Raptor), `5` (Reed-Solomon), or `6` (RaptorQ) is used to encode content, the `code_type` field in the `bitstream_header()` structure as specified in clause 6.1.4.5 and `profile_description` as specified in clause F.1.3 shall be set to the appropriate code type.

Fields used to support communication of coefficient information shall not be set. This includes bit 4 in the `block_mask` as specified in clause 6.1.5.19, and bits 3 and 4 in the `packet_mask` as specified in clause 6.1.7.2. Instead, the encoding symbol ID (ESI) produced by the relevant encoder shall be communicated using the `packet_symbol_index` field within the `packet_header()` structure as specified in clause 6.1.7.4. Furthermore, fields used to signal a `coded_symbol` is systematic (i.e. `b_systematic_symbol` as specified in clause 6.1.7.1) and coefficient information is encrypted (i.e. `b_block_cc_encrypted` as specified in clause 6.1.4.13, bit 3 in the `block_mask` as specified in clause 6.1.5.19, and bit 1 in the `packet_mask` as specified in clause 6.1.7.2) shall not be set.

NOTE: Signalling of systematic symbols by each of these code types is accomplished via the ESI (i.e. `coded_symbol` with `packet_symbol_index` `0` to `num_block_symbols` – 1 are systematic).

Table F.14 provides the required fields and values when `code_type` is `1` (Raptor), `5` (Reed-Solomon), or `6` (RaptorQ).

Table F.14: Required CMMF bitstream fields and values for code_type 1, 5, and 6

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*code_type*	1, 5, or 6	u(4)
	b_block_cc_encrypted	FALSE	b(1)
block_header()	*block_mask*: Bit 1	0	v(1)
	block_mask: Bit 3	0	v(1)
	block_mask: Bit 4	0	v(1)
packet_header()	*b_systematic_symbol*	FALSE	b(1)
	packet_mask: Bit 0	1	v(1)
	packet_mask: Bit 1	0	v(1)
	packet_mask: Bit 3	0	v(1)
	packet_mask: Bit 4	0	v(1)
	packet_symbol_index	See clause 6.1.7.4	

F.1.4.5 Block integrity required fields and values

In cases where verification that the received and decoded data in the block matches that of the original source is needed, block integrity information may be added to the CMMF bitstream. The presence of this information is independent of the code type in use or whether coefficient information is encrypted.

When block integrity information is included within the CMMF bitstream, `b_block_integrity` within the `profile_description` as specified in clause F.1.3 shall be set. Furthermore, Table F.15 provides additional required fields and values when block integrity information is included within the CMMF bitstream.

Table F.15: Required CMMF bitstream fields and values for block integrity verification

CMMF structure	CMMF field name	Value	Bit field encoding
block_header()	*block_mask*: Bit 5	1	v(1)
	fb_integrity()		
fb_integrity()	*fb_hash_type*	See Table 66	v(2)
	fb_hash_algorithm	See Table 68	v(3)
	fb_hash_size	See Table 69	v(4)
	b_fb_integrity_ext	FALSE	b(1)
	fb_hash	See clause 6.1.13.5	

The hash `fb_hash` shall be a hash of the data comprising the original source object.

F.1.4.6 Packet integrity required fields and values

In cases where verification that the received data in a packet matches the data contained in the CMMF bitstream at the time it was created is needed, packet integrity information may be added to the CMMF bitstream. This presence of this information is independent of the code type in use or whether coefficient information is encrypted.

When packet integrity information is included within the CMMF bitstream, `b_packet_integrity` within the `profile_description` as specified in clause F.1.3 shall be set. Furthermore, Table F.16 provides the required fields and values when packet integrity information is included within the CMMF bitstream.

Table F.16: Required CMMF bitstream fields and values for packet integrity verification

CMMF structure	CMMF field name	Value	Bit field encoding
packet_header()	*packet_mask*: Bit 5	1	v(1)
	packet_integrity()		
packet_integrity()	*packet_hash_algorithm*	See Table 70	v(3)
	packet_hash_size	See Table 72	v(3)
	b_packet_integrity_ext	FALSE	b(1)
	packet_hash	See clause 6.1.14.4	

The hash `packet_hash` shall be a hash of the data comprising the `coded_symbol` within the `packet()` structure at the time the CMMF bitstream was created.

F.1.5 Object-based sources providing complete objects

A CMMF Encoder may be configured to encode content from a source where the full source object or the full source object's size is available to the CMMF Encoder before it starts creating CMMF bitstreams/Transport Objects. In such cases, the required fields and values within the CMMF bitstream to indicate that this is the case are provided in Table F.17.

Table F.17: Required CMMF bitstream fields and values for sources providing complete objects

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*content_source_size*	*sizeof*(content)	u(64)
	content_source_type	000b or 001b	v(3)
block_header()	*block_size*	*sizeof*(content)	u(32)

Ingested source data is immediately partitioned into source symbols. These source symbols may be immediately encoded within a CMMF bitstream/Transport Object as systematic `coded_symbols` when `code_type` is `0` (xCD-1) or encoded symbols ESI 0 through `num_block_symbols` – 1 when `code_type` is `1` (Raptor), `5` (Reed-Solomon), or `6` (RaptorQ). Furthermore, the CMMF Encoder may add `packet()` subatoms to a CMMF bitstream/Transport Object with a `packet_symbol_index` that follows a predetermined pattern. For example, a CMMF bitstream/Transport Object may be constructed where the source symbol indexes associated with the `packet()` subatoms added to the CMMF bitstream/Transport Object are 0, 2, 4, etc.

The CMMF Encoder may also create and append either non-systematic `packet()` subatoms to the CMMF bitstream/Transport Object when `code_type` is `0` (xCD-1) or encoded symbols with ESI greater than `num_block_symbols` – 1 when `code_type` is `1` (Raptor), `5` (Reed-Solomon), or `6` (RaptorQ).

The value of `target_symbols_present_percentage` in the `profile_description` as specified in clause F.1.3.3.6 is used to determine the number of `packet()` subatoms (i.e. `block_symbols_present`) present in the CMMF bitstream/Transport Object. The appropriate fields in the block header subatom (e.g. `b_sufficient_symbols_present` and `bock_symbols_present`) shall be set according to the provided value of `target_symbols_present_percentage`.

F.1.6 Object-based live or streaming sources

A CMMF Encoder may be configured to encode content from a live or streaming source where the full source object may not be available to the CMMF Encoder before it starts creating CMMF bitstreams/Transport Objects. In such cases, the required fields and values within the CMMF bitstream to indicate that this is the case are provided in Table F.18.

Table F.18: Required CMMF bitstream fields and values for live or streaming sources

CMMF structure	CMMF field name	Value	Bit field encoding
bitstream_header()	*content_source_size*	0	u(64)
	content_source_type	011b	v(3)
block_header()	*block_size*	0	u(32)
	block_num_symbols	0	u(bns_bits)
	block_mask: Bit 0	1	v(1)
	b_sufficient_symbols_present	TRUE	b(1)

Ingested source data is immediately partitioned into source symbols with a predetermined `block_symbol_size`. These source symbols may be immediately encoded within a CMMF bitstream/Transport Object as systematic `coded_symbols` when `code_type` is `0` (xCD-1) or encoded symbols ESI 0 through `num_block_symbols` – 1 when `code_type` is `1` (Raptor), `5` (Reed-Solomon), or `6` (RaptorQ). Furthermore, the CMMF Encoder may add `packet()` subatoms to a CMMF bitstream/Transport Object with a `packet_symbol_index` that follows a predetermined pattern. For example, a CMMF bitstream/Transport Object may be constructed where the source symbol indexes associated with the `packet()` subatoms added to the CMMF bitstream/Transport Object are 0, 2, 4, etc.

Once the CMMF Encoder has obtained the complete object from the source or knows the size of the full source object, it shall create and append an updated block header subatom to the CMMF bitstream/Transport Object. This block header subatom shall contain identical values as the original block header subatom with the following exceptions:

- `block_size` shall be updated to provide the size of the block (i.e. size of the full source object) in bytes.
- `block_num_symbols` shall be updated to provide the total number of `packet()` subatoms contained in the CMMF bitstream/Transport Object. This value is calculated according to the following formula:

```
block_num_symbols = ceil(block_size / block_symbol_size)
```

The CMMF Encoder may also create and append non-systematic `packet()` subatoms to the CMMF bitstream/Transport Object when `code_type` is `0` (xCD-1) or encoded symbols with ESI greater than `num_block_symbols` – 1 when `code_type` is `1` (Raptor), `5` (Reed-Solomon), or `6` (RaptorQ). Finally, the total number of `packet()` subatoms contained within the CMMF bitstream/Transport Object shall be at least `block_num_symbols`.

The value of `target_symbols_present_percentage` in the `profile_description` as specified in clause F.1.3.3.6 for CMMF bitstreams/Transport Objects created for live or streaming sources shall be `127` (i.e. `percent_symbols_present` = `100`).

F.1.7 CMMF bitstream/Transport Object deployment

A one-to-many mapping between a media resource/source object (e.g. CMAF segment) and the CMMF bitstreams/Transport Objects created to deliver that resource should exist where a CMMF Receiver or an application provider may fully extract the media resource from:

- Any individual CMMF bitstream/Transport Object when it is obtained in its entirety from one service location if `b_sufficient_symbols_present` within the CMMF bitstreams `block_header()` subatom is set, or
- Some combination of CMMF bitstreams/Transport Objects when partial bitstreams/Transport Objects are obtained from multiple service locations.

Each individual CMMF bitstream/Transport Object constructed to deliver a media resource/source object should consist of a unique encoding (i.e. representation or variation) of the media resource/source object such that a CMMF Receiver or application provider may jointly decode multiple partially received CMMF bitstreams/Transport Objects allowing for the recovery of the media resource/source object in its entirety.

A one-to-one mapping should exist between each service location and the CMMF bitstream representation hosted at or contributed to that service location.

Configuration Information required by a CMMF Receiver as specified in annex D to configure and stream media using CMMF should be communicated to the CMMF Receiver/Encoder prior to the start of a delivery session.

History

Version	Date	Status
V1.1.1	October 2024	Publication
V1.2.1	March 2026	Publication