
# ETSI TS 131 124 V7.0.0 (2007-06)

*Technical Specification*

**Universal Mobile Telecommunications System (UMTS);
Mobile Equipment (ME) conformance test specification;
Universal Subscriber Interface Module Application Toolkit
(USAT) conformance test specification
(3GPP TS 31.124 version 7.0.0 Release 7)**



Reference
RTS/TSGC-0631124v700

Keywords
UMTS

***ETSI***

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - NAF 742 C
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° 7803/88

***Important notice***

Individual copies of the present document can be downloaded from:
http://www.etsi.org

The present document may be made available in more than one electronic version or in print. In any case of existing or perceived difference in contents between such versions, the reference version is the Portable Document Format (PDF). In case of dispute, the reference shall be the printing on ETSI printers of the PDF version kept on a specific network drive within ETSI Secretariat.

Users of the present document should be aware that the document may be subject to revision or change of status. Information on the current status of this and other ETSI documents is available at
http://portal.etsi.org/tb/status/status.asp

If you find errors in the present document, please send your comment to one of the following services:
http://portal.etsi.org/chaircor/ETSI_support.asp

***Copyright Notification***

No part may be reproduced except as authorized by written permission.
The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 2007.
All rights reserved.

**DECT**™, **PLUGTESTS**™ and **UMTS**™ are Trade Marks of ETSI registered for the benefit of its Members.
**TIPHON**™ and the **TIPHON logo** are Trade Marks currently being registered by ETSI for the benefit of its Members.
**3GPP**™ is a Trade Mark of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners.

# Intellectual Property Rights

IPRs essential or potentially essential to the present document may have been declared to ETSI. The information pertaining to these essential IPRs, if any, is publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI Web server (http://webapp.etsi.org/IPR/home.asp).

Pursuant to the ETSI IPR Policy, no investigation, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

# Foreword

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities, UMTS identities or GSM identities. These should be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between GSM, UMTS, 3GPP and ETSI identities can be found under http://webapp.etsi.org/key/queryform.asp.

# Contents

Intellectual Property Rights ..... 2
Foreword ..... 2
Foreword ..... 9
1 Scope ..... 10
2 References ..... 11
3 Definitions and abbreviations ..... 12
3.1 Mobile station definition and configurations ..... 12
3.2 Applicability ..... 12
3.2.1 Applicability of the present document ..... 12
3.2.2 Applicability of the individual tests ..... 12
3.2.3 Applicability to terminal equipment ..... 12
3.2.4 Definitions ..... 12
3.2.4.1 Format of the table of optional features ..... 12
3.2.4.2 Format of the applicability table ..... 13
3.2.4.3 Status and notations ..... 13
3.3 Table of optional features ..... 14
3.4 Applicability table ..... 18
3.5 Conventions for mathematical notations ..... 54
3.5.1 Mathematical signs ..... 54
4 Test equipment ..... 55
5 Testing methodology in general ..... 55
5.1 Testing of optional functions and procedures ..... 55
5.2 Test interfaces and facilities ..... 55
5.3 Information to be provided by the apparatus supplier ..... 55
6 Implicit testing ..... 56
7 Measurement uncertainty ..... 56
8 Format of tests ..... 56
9 Generic call set up procedures ..... 59
10 - 26 Not used ..... 59
27 Testing of the UICC/ME interface ..... 59
27.1 - 27.21 Void ..... 60
27.22 USIM Application Toolkit ..... 60
27.22.1A General Test purpose ..... 60
27.22.2A Definition of default values for USIM Application Toolkit testing ..... 60
27.22.1 Initialization of USIM Application Toolkit Enabled UICC by USIM Application Toolkit Enabled ME (Profile Download) ..... 65
27.22.1.1 Definition and applicability ..... 65
27.22.1.2 Conformance requirement ..... 65
27.22.1.3 Test purpose ..... 65
27.22.1.4 Method of test ..... 66
27.22.1.4.1 Initial conditions ..... 66
27.22.1.4.2 Procedure ..... 66
27.22.1.5 Test requirement ..... 66
27.22.2 Contents of the TERMINAL PROFILE command ..... 66
27.22.2.1 Definition and applicability ..... 66
27.22.2.2 Conformance requirement ..... 66
27.22.2.3 Test purpose ..... 67
27.22.2.4 Method of test ..... 67
27.22.2.4.1 Initial conditions ..... 67

27.22.1.4.2 Procedure ..... 67
27.22.2.5 Test requirement ..... 67
27.22.3 Servicing of proactive UICC commands ..... 67
27.22.3.1 Definition and applicability ..... 67
27.22.3.2 Conformance requirement ..... 67
27.22.3.3 Test purpose ..... 68
27.22.3.4 Method of test ..... 68
27.22.3.4.1 Initial conditions ..... 68
27.22.3.4.2 Procedure ..... 68
27.22.3.5 Test requirement ..... 68
27.22.4 Proactive UICC commands ..... 68
27.22.4.1 DISPLAY TEXT ..... 68
27.22.4.1.1 DISPLAY TEXT (Normal) ..... 68
27.22.4.1.2 DISPLAY TEXT (Support of "No response from user") ..... 69
27.22.4.1.3 DISPLAY TEXT (Display of extension text) ..... 70
27.22.4.1.4 DISPLAY TEXT (Sustained text) ..... 71
27.22.4.1.5 DISPLAY TEXT (Display of icons) ..... 73
27.22.4.1.6 DISPLAY TEXT (UCS2 display in Cyrillic) ..... 74
27.22.4.1.7 DISPLAY TEXT (Variable Time out) ..... 74
27.22.4.1.8 DISPLAY TEXT (Support of Text Attribute) ..... 75
27.22.4.1.9 DISPLAY TEXT (UCS2 display in Chinese) ..... 82
27.22.4.1.10 DISPLAY TEXT (UCS2 display in Katakana) ..... 83
27.22.4.2 GET INKEY ..... 83
27.22.4.2.1 GET INKEY(normal) ..... 83
27.22.4.2.2 GET INKEY (No response from User) ..... 84
27.22.4.2.3 GET INKEY (UCS2 display in Cyrillic) ..... 85
27.22.4.2.4 GET INKEY (UCS2 entry in Cyrillic) ..... 86
27.22.4.2.5 GET INKEY ("Yes/No" Response) ..... 87
27.22.4.2.6 GET INKEY (display of Icon) ..... 87
27.22.4.2.7 GET INKEY (Help Information) ..... 89
27.22.4.2.8 GET INKEY (Variable Time out) ..... 89
27.22.4.2.9 GET INKEY (Support of Text Attribute) ..... 90
27.22.4.2.10 GET INKEY (UCS2 display in Chinese) ..... 97
27.22.4.2.11 GET INKEY (UCS2 entry in Chinese) ..... 97
27.22.4.2.12 GET INKEY (UCS2 display in Katakana) ..... 98
27.22.4.2.13 GET INKEY (UCS2 entry in Katakana) ..... 99
27.22.4.3. GET INPUT ..... 100
27.22.4.3.1 GET INPUT (normal) ..... 100
27.22.4.3.2 GET INPUT (No response from User) ..... 101
27.22.4.3.3 GET INPUT (UCS2 display in Cyrillic) ..... 102
27.22.4.3.4 GET INPUT (UCS2 entry in Cyrillic) ..... 102
27.22.4.3.5 GET INPUT (default text) ..... 103
27.22.4.3.6 GET INPUT (display of Icon) ..... 104
27.22.4.3.7 GET INPUT (Help Information) ..... 105
27.22.4.3.8 GET INPUT (Support of Text Attribute) ..... 106
27.22.4.3.9 GET INPUT (UCS2 display in Chinese) ..... 112
27.22.4.3.10 GET INPUT (UCS2 entry in Chinese) ..... 113
27.22.4.3.11 GET INPUT (UCS2 display in Katakana) ..... 114
27.22.4.3.12 GET INPUT (UCS2 entry in Katakana) ..... 115
27.22.4.4 MORE TIME ..... 115
27.22.4.4.2 Conformance requirement ..... 115
27.22.4.4.3 Test purpose ..... 116
27.22.4.4.4 Method of test ..... 116
27.22.4.4.5 Test requirement ..... 116
27.22.4.5 PLAY TONE ..... 116
27.22.4.5.1 PLAY TONE (Normal) ..... 116
27.22.4.5.2 PLAY TONE (UCS2 display in Cyrillic) ..... 121
27.22.4.5.3 PLAY TONE (display of Icon) ..... 122
27.22.4.5.4 PLAY TONE (Support of Text Attribute) ..... 123
27.22.4.5.5 PLAY TONE (UCS2 display in Chinese) ..... 130
27.22.4.5.6 PLAY TONE (UCS2 display in Katakana) ..... 131
27.22.4.6 POLL INTERVAL ..... 131

27.22.4.6.1 Definition and applicability ..... 131
27.22.4.6.2 Conformance requirement ..... 131
27.22.4.6.3 Test purpose ..... 132
27.22.4.6.4 Method of test ..... 132
27.22.4.7 REFRESH ..... 132
27.22.4.7.1 REFRESH (normal) ..... 132
27.22.4.7.2 REFRESH (IMSI changing procedure) ..... 143
27.22.4.8 SET UP MENU and ENVELOPE MENU SELECTION ..... 146
27.22.4.8.1 SET UP MENU (normal) and ENVELOPE MENU SELECTION ..... 146
27.22.4.8.2 SET UP MENU (help request support) and ENVELOPE MENU SELECTION ..... 148
27.22.4.8.3 SET UP MENU (next action support) and ENVELOPE MENU SELECTION ..... 148
27.22.4.8.4 SET UP MENU (display of icons) and ENVELOPE MENU SELECTION ..... 149
27.22.4.8.5 SET UP MENU (soft keys support) and ENVELOPE MENU SELECTION ..... 150
27.22.4.8.6 SET UP MENU (support of Text Attribute) and ENVELOPE MENU SELECTION ..... 151
27.22.4.8.7 SET UP MENU (UCS2 display in Cyrillic) and ENVELOPE MENU SELECTION ..... 158
27.22.4.8.8 SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION ..... 159
27.22.4.8.9 SET UP MENU (UCS2 display in Katakana) and ENVELOPE MENU SELECTION ..... 160
27.22.4.9 SELECT ITEM ..... 161
27.22.4.9.1 SELECT ITEM (mandatory features for ME supporting SELECT ITEM) ..... 161
27.22.4.9.2 SELECT ITEM (next action support) ..... 162
27.22.4.9.3 SELECT ITEM (default item support) ..... 163
27.22.4.9.4 SELECT ITEM (help request support) ..... 164
27.22.4.9.5 SELECT ITEM (icons support) ..... 164
27.22.4.9.6 SELECT ITEM (presentation style) ..... 165
27.22.4.9.7 SELECT ITEM (soft keys support) ..... 166
27.22.4.9.8 SELECT ITEM (Support of "No response from user") ..... 166
27.22.4.9.9 SELECT ITEM (Support of Text Attribute) ..... 167
27.22.4.9.10 SELECT ITEM (UCS2 display in Cyrillic) ..... 173
27.22.4.9.11 SELECT ITEM (UCS2 display in Chinese) ..... 174
27.22.4.9.12 SELECT ITEM (UCS2 display in Katakana) ..... 175
27.22.4.10 SEND SHORT MESSAGE ..... 176
27.22.4.10.1 SEND SHORT MESSAGE (normal) ..... 176
27.22.4.10.2 SEND SHORT MESSAGE (UCS2 display in Cyrillic) ..... 194
27.22.4.10.3 SEND SHORT MESSAGE (icon support) ..... 199
27.22.4.10.4 SEND SHORT MESSAGE (Support of Text Attribute) ..... 204
27.22.4.10.5 SEND SHORT MESSAGE (UCS2 display in Chinese) ..... 241
27.22.4.10.6 SEND SHORT MESSAGE (UCS2 display in Katakana) ..... 246
27.22.4.11 SEND SS ..... 252
27.22.4.11.1 SEND SS (normal) ..... 252
27.22.4.11.2 SEND SS (Icon support) ..... 264
27.22.4.11.3 SEND SS (UCS2 display in Cyrillic) ..... 271
27.22.4.11.4 SEND SS (support of Text Attribute) ..... 273
27.22.4.11.5 SEND SS (UCS2 display in Chinese) ..... 309
27.22.4.11.6 SEND SS (UCS2 display in Katakana) ..... 311
27.22.4.12 SEND USSD ..... 313
27.22.4.12.1 SEND USSD (normal) ..... 313
27.22.4.12.2 SEND USSD (Icon support) ..... 324
27.22.4.12.3 SEND USSD (UCS2 display in Cyrillic) ..... 331
27.22.4.12.4 SEND USSD (support of Text Attribute) ..... 334
27.22.4.12.5 SEND USSD (UCS2 display in Chinese) ..... 370
27.22.4.12.6 SEND USSD (UCS2 display in Katakana) ..... 373
27.22.4.13 SET UP CALL ..... 375
27.22.4.13.1 SET UP CALL (normal) ..... 375
27.22.4.13.2 SET UP CALL (second alpha identifier) ..... 388
27.22.4.13.3 SET UP CALL (display of icons) ..... 390
27.22.4.13.4 SET UP CALL (support of Text Attribute) ..... 399
27.22.4.13.5 SET UP CALL (UCS2 Display in ***Cyrillic***) ..... 435
27.22.4.13.6 SET UP CALL (UCS2 Display in Chinese) ..... 438
27.22.4.13.7 SET UP CALL (UCS2 Display in Katakana) ..... 441
27.22.4.14 POLLING OFF ..... 444
27.22.4.14.1 Definition and applicability ..... 444
27.22.4.14.2 Conformance requirement ..... 444

27.22.4.14.3 Test purpose ....444
27.22.4.14.4 Method of test....444
27.22.4.14.5 Test requirement....447
27.22.4.15 PROVIDE LOCAL INFORMATION ....447
27.22.4.15.1 Definition and applicability....447
27.22.4.15.2 Conformance requirement....447
27.22.4.15.3 Test purpose ....447
27.22.4.15.4 Method of tests ....448
27.22.4.15.5 Test requirement....454
27.22.4.16 SET UP EVENT LIST....454
27.22.4.16.1 SET UP EVENT LIST (normal) ....454
27.22.4.17 PERFORM CARD APDU ....463
27.22.4.17.1 PERFORM CARD APDU (normal)....463
27.22.4.17.2 PERFORM CARD APDU (detachable card reader) ....465
27.22.4.18 POWER OFF CARD ....465
27.22.4.18.1 POWER OFF CARD (normal)....465
27.22.4.18.2 POWER OFF CARD (detachable card reader) ....466
27.22.4.19 POWER ON CARD....467
27.22.4.19.1 POWER ON CARD (normal) ....467
27.22.4.19.2 POWER ON CARD (detachable card reader)....468
27.22.4.20 GET READER STATUS....468
27.22.4.20.1 GET READER STATUS (normal) ....468
27.22.4.20.2 GET CARD READER STATUS (detachable card reader)....469
27.22.4.21 TIMER MANAGEMENT and ENVELOPE TIMER EXPIRATION ....470
27.22.4.21.1 TIMER MANAGEMENT (normal)....470
27.22.4.21.2 ENVELOPE TIMER EXPIRATION (normal) ....471
27.22.4.22 SET UP IDLE MODE TEXT....472
27.22.4.22.1 SET UP IDLE MODE TEXT (normal)....472
27.22.4.22.2 SET UP IDLE MODE TEXT (Icon support) ....477
27.22.4.22.3 SET UP IDLE MODE TEXT (UCS2 support)....479
27.22.4.22.4 SET UP IDLE MODE TEXT (support of Text Attribute) ....479
27.22.4.22.5 SET UP IDLE MODE TEXT (UCS2 display in Chinese) ....485
27.22.4.22.6 SET UP IDLE MODE TEXT (UCS2 display in Katakana) ....486
27.22.4.23 RUN AT COMMAND....487
27.22.4.23.1 RUN AT COMMAND (normal) ....487
27.22.4.23.2 RUN AT COMMAND (Icon support) ....490
27.22.4.23.3 RUN AT COMMAND (support of Text Attribute)....496
27.22.4.23.4 RUN AT COMMAND (UCS2 display in Cyrillic) ....531
27.22.4.23.5 RUN AT COMMAND (UCS2 display in Chinese) ....532
27.22.4.23.6 RUN AT COMMAND (UCS2 display in Katakana) ....532
27.22.4.24 SEND DTMF ....533
27.22.4.24.1 SEND DTMF (Normal)....533
27.22.4.24.2 SEND DTMF (Display of icons)....539
27.22.4.24.3 SEND DTMF (UCS2 display in Cyrillic) ....544
27.22.4.24.4 SEND DTMF (support of Text Attribute) ....546
27.22.4.24.5 SEND DTMF (UCS2 Display in Chinese)....589
27.22.4.24.6 SEND DTMF (UCS2 Display in Katakana)....591
27.22.4.25 LANGUAGE NOTIFICATION ....592
27.22.4.25.1 Definition and applicability....592
27.22.4.25.2 Conformance Requirement....592
27.22.4.25.3 Test purpose ....593
27.22.4.25.4 Method of Test ....593
27.22.4.25.5 Test requirement....593
27.22.4.26 LAUNCH BROWSER....593
27.22.4.26.1 LAUNCH BROWSER (No session already launched) ....593
27.22.4.26.2 LAUNCH BROWSER (Interaction with current session)....599
27.22.4.26.3 LAUNCH BROWSER (UCS2 display in Cyrillic) ....603
27.22.4.26.4 LAUNCH BROWSER (icons support) ....605
27.22.4.26.5 LAUNCH BROWSER (support of Text Attribute)....610
27.22.4.26.6 LAUNCH BROWSER (UCS2 Display in Chinese)....646
27.22.4.26.7 LAUNCH BROWSER (UCS2 Display in Katakana) ....648
27.22.4.27 OPEN CHANNEL ....650

27.22.4.27.2 Open Channel (related to GPRS) ..... 650
27.22.4.27.3 Open Channel (default bearer) ..... 663
27.22.4.27.4 Open Channel (Local Bearer) ..... 663
27.22.4.27.5 Open Channel (GPRS, support of Text Attribute) ..... 663
27.22.4.28 CLOSE CHANNEL ..... 720
27.22.4.28.1 CLOSE CHANNEL(normal) ..... 720
27.22.4.28.2 CLOSE CHANNEL (support of Text Attribute) ..... 727
27.22.4.29 RECEIVE DATA ..... 769
27.22.4.29.1 RECEIVE DATA (NORMAL) ..... 769
27.22.4.29.5 Test requirement ..... 779
27.22.4.29.2 RECEIVE DATA (support of Text Attribute) ..... 779
27.22.4.30 SEND DATA ..... 818
27.22.4.30.1 SEND DATA (normal) ..... 818
27.22.4.30.2 SEND DATA (support of Text Attribute) ..... 833
27.22.4.31 GET CHANNEL STATUS ..... 868
27.22.4.31.1 Definition and applicability ..... 868
27.22.4.31.2 Conformance requirements ..... 868
27.22.4.31.3 Test purpose ..... 868
27.22.4.31.4 Method of test ..... 868
27.22.4.31.5 Test requirement ..... 878
27.22.5 Data Download to UICC ..... 878
27.22.5.1 SMS-PP Data Download ..... 878
27.22.5.1.1 Definition and applicability ..... 878
27.22.5.1.2 Conformance requirement ..... 878
27.22.5.1.3 Test purpose ..... 878
27.22.5.1.4 Method of Test ..... 878
27.22.5.1.5 Test requirement ..... 885
27.22.5.2 Cell Broadcast Data Download ..... 885
27.22.5.2.1 Definition and applicability ..... 885
27.22.5.2.2 Conformance requirement ..... 885
27.22.5.2.3 Test purpose ..... 885
27.22.5.2.4 Method of Test ..... 885
27.22.5.2.5 Test requirement ..... 891
27.22.6 CALL CONTROL BY USIM ..... 891
27.22.6.1 Procedure for Mobile Originated calls ..... 891
27.22.6.1.1 Definition and applicability ..... 891
27.22.6.1.2 Conformance requirement ..... 891
27.22.6.1.3 Test purpose ..... 891
27.22.6.1.4 Method of tests ..... 891
27.22.6.1.5 Test requirement ..... 913
27.22.6.2 Procedure for Supplementary (SS) Services ..... 913
27.22.6.2.1 Definition and applicability ..... 913
27.22.6.2.2 Conformance requirement ..... 913
27.22.6.2.3 Test purpose ..... 913
27.22.6.2.4 Method of tests ..... 913
27.22.6.2.5 Test requirement ..... 920
27.22.6.3 Interaction with Fixed Dialling Number (FDN) ..... 921
27.22.6.3.1 Definition and applicability ..... 921
27.22.6.3.2 Conformance requirement ..... 921
27.22.6.3.3 Test purpose ..... 921
27.22.6.3.4 Method of tests ..... 921
27.22.6.3.5 Test requirement ..... 928
27.22.6.4 Support of Barred Dialling Number (BDN) service ..... 928
27.22.6.4.1 Definition and applicability ..... 928
27.22.6.4.2 Conformance requirement ..... 928
27.22.6.4.3 Test purpose ..... 929
27.22.6.4.4 Method of tests ..... 929
27.22.6.4.5 Test requirement ..... 936
27.22.6.5 Barred Dialling Number (BDN) service handling for terminals not supporting BDN ..... 936
27.22.6.5.1 Definition and applicability ..... 936
27.22.6.5.2 Conformance requirement ..... 937
27.22.6.5.3 Test purpose ..... 937

27.22.6.5.4 Method of tests ..... 937
27.22.7 EVENT DOWNLOAD ..... 938
27.22.7.1 MT Call Event ..... 938
27.22.7.1.1 MT Call Event (normal) ..... 938
27.22.7.2 Call Connected Event ..... 940
27.22.7.2.1 Call Connected Event (MT and MO call) ..... 940
27.22.7.2.2 Call Connected Event (ME supporting SET UP CALL) ..... 942
27.22.7.3 Call Disconnected Event ..... 945
27.22.7.3.1 Call Disconnected Event ..... 945
27.22.7.4 Location Status Event ..... 950
27.22.7.4.1 Location Status Event (normal) ..... 950
27.22.7.5 User Activity Event ..... 953
27.22.7.5.1 User Activity Event (normal) ..... 953
27.22.7.6 Idle screen available event ..... 954
27.22.7.6.1 Idle Screen Available (normal) ..... 954
27.22.7.7 Card reader status event ..... 954
27.22.7.7.1 Card Reader Status (normal) ..... 954
27.22.7.7.2 Card Reader Status(detachable card reader) ..... 955
27.22.7.8 Language selection event ..... 956
27.22.7.8.1 Language selection event (normal) ..... 956
27.22.7.9 Browser termination event ..... 956
27.22.7.9.1 Browser termination (normal) ..... 956
27.22.7.10 Data available event ..... 958
27.22.7.10.1 Definition and applicability ..... 958
27.22.7.10.2 Conformance requirements ..... 958
27.22.7.10.3 Test purpose ..... 958
27.22.7.10.4 Method of test ..... 959
27.22.7.11 Channel Status event ..... 963
27.22.7.11.1 Definition and applicability ..... 963
27.22.7.11.2 Conformance requirements ..... 963
27.22.7.11.3 Test purpose ..... 963
27.22.7.11.4 Method of test ..... 963
27.22.7.12 Access Technology Change event ..... 967
27.22.7.13 Local Connection event ..... 967
27.22.7.14 Network search mode change event ..... 967
27.22.7.15 Browsing status event ..... 967
27.22.8 MO SHORT MESSAGE CONTROL BY USIM ..... 968
27.22.8.1 Definition and applicability ..... 968
27.22.8.2 Conformance requirement ..... 968
27.22.8.3 Test purpose ..... 968
27.22.8.4 Method of tests ..... 968
27.22.8.4.1 Initial conditions ..... 968
27.22.8.4.2 Procedure ..... 969
27.22.8.5 Test requirement ..... 977
27.22.9 Handling of command number ..... 977
27.22.9.1 Definition and applicability ..... 977
27.22.9.2 Conformance requirement ..... 977
27.22.9.3 Test purpose ..... 977
27.22.9.4 Method of tests ..... 978
27.22.9.4.1 Initial conditions ..... 978
27.22.9.4.2 Procedure ..... 978
27.22.9.5 Test requirement ..... 978

**Annex A (normative): Details of Test-SIM (TestSIM) ..... 979**

**Annex B (normative): Details of terminal profile support ..... 981**

**Annex C (informative): Change history ..... 989**

History ..... 992

# Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

# 1 Scope

The present document describes the technical characteristics and methods of test for testing the USIM Application Toolkit implemented in 3rd Generation Mobile Equipments (ME) or Mobile Station (MS) for the 3G and 2G digital cellular communications systems within the 3GPP digital cellular telecommunications system, in compliance with the relevant requirements, and in accordance with the relevant guidance given in ISO/IEC 9646-7 [19] and ETS 300 406 [20].

The present document is valid for ME implemented according to 3GPP Release 99, or Release 4, or Release 5 or Release 6

The present document covers the minimum characteristics considered necessary in order to provide sufficient performance for mobile equipment and to prevent interference to other services or to other users, and to the PLMNs.

It does not necessarily include all the characteristics which may be required by a user or subscriber, nor does it necessarily represent the optimum performance achievable.

The present document is part of the 3GPP-series of technical specifications. The present document neither replaces any of the other 3GPP technical specifications or 3GPP related ETSs or ENs, nor is it created to provide full understanding of (or parts of) the UMTS. The present document lists the requirements, and provides the methods of test for testing the USIM Application Toolkit implemented in a ME for conformance to the 3GPP standard.

For a full description of the system, reference should be made to all the 3GPP technical specifications or 3GPP related ETSIs, ETSs or ENs. Clause 2 provides a complete list of the 3GPP technical specifications, 3GPP related ETSIs, ETSs, ENs, and ETRs, on which this conformance test specifications is based.

If there is a difference between this present conformance document, and any other 3GPP technical specification or 3GPP related ETSI, ETS, EN, or 3GPP TS, then the other 3GPP technical specification or 3GPP related ETSI, ETS, EN or 3GPP TS shall prevail.

Within the context of this document, the term "terminal" used in ETSI TS 102 223 [16] refers to the Mobile Equipment (ME).

Within the context of this document, the term "UICC" used in ETSI TS 102 223 [16] refers to the USIM card.

Within the context of this document, the term "NAA" used in ETSI TS 102 223 [16] refers to the USIM application.

# 2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the relevant Release*.
- References to 3GPP Technical Specifications and Technical Reports throughout the present document shall be interpreted according to the Release shown in the formal reference in this clause, based upon the Release of the implementation under test.

[1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".

[2] 3GPP TS 22.001: "Principles of circuit telecommunication services supported by a Public Land Mobile Network (PLMN)".

[3] 3GPP TS 22.003: "Circuit Teleservices supported by a Public Land Mobile Network (PLMN)".

[4] 3GPP TS 22.004: "General on supplementary services".

[5] ETSI TS 101 220: "ETSI numbering system for telecommunication application providers"

[6] 3GPP TS 21.904: "UE capability requirements"

[7] 3GPP TS 23.038: "Alphabets and language-specific information".

[8] 3GPP TS 23.040: "Technical realization of the Short Message Service (SMS)".

[9] 3GPP TS 23.041: "Technical realization of Cell Broadcast Service (CBS)".

[10] 3GPP TS 24.008: "Mobile radio interface layer 3 specification; Core network protocols; Stage 3" (see note 1).

[11] 3GPP TS 24.011: "Point-to-Point (PP) Short Message Service (SMS) Support on mobile radio interface".

[12] 3GPP TS 34.108: "Common test environments for User Equipment (UE) conformance testing".

[13] ETSI TS 102 221: "UICC-Terminal interface; Physical and logical characteristics".

[14] 3GPP TS 31.102: "Characteristics of the USIM application".

[15] 3GPP TS 31.111: "USIM Application Toolkit (USAT)"

[16] ETSI TS 102 223: "Smart cards; Card Application Toolkit (CAT)"

[17a] ISO/IEC 10646-1: "Information technology - Universal Multiple Octet Coded Character Set (UCS) - Part 1: Architecture and Basic Multilingual Plane".

[17b] ISO/IEC 10646-2: "Information technology - Universal Multiple Octet Coded Character Set (UCS) - Part 2: Supplementary Planes".

[18] 3GPP TS 27.007: "AT command set for 3G User Equipment (UE)".

[19] ISO/IEC 9646-7 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".

[20] ETSI ETS 300 406 (1995): "Methods for Testing and Specification (MTS); Protocol and profile conformance testing specifications; Standardization methodology".

[21] 3GPP TS 31.121: "UICC-terminal interface; USIM application test specification"

[22] 3GPP TS 22.101: "Service Aspects; Service principles"

[23] 3GPP TS 51.010-1: "Mobile Station (MS) conformance specification; Part 1: Conformance specification"

[24] Void.

[25] TIA/IS-820-A: "Removable User Identity Module (R-UIM) for TIA/EIA Spread Spectrum System".

[26] ETSI TS 102 384 "Smart cards; UICC-Terminal interface; Card Application Toolkit (CAT) conformance specification".

[27] 3GPP TS 34.123-3: "User Equipment (UE) conformance specification; Part 3: Abstract test suites (ATSs)".

[28] 3GPP TS 31.115: "Secured packet structure for (U)SIM Toolkit applications".

# 3 Definitions and abbreviations

## 3.1 Mobile station definition and configurations

The mobile station definition and configurations specified in TS 34.108 [12] shall apply, unless otherwise specified in the present clause.

## 3.2 Applicability

### 3.2.1 Applicability of the present document

The present specification applies to a terminal equipment that supports the USIM Application Toolkit optional feature.

### 3.2.2 Applicability of the individual tests

Table A.1 lists the optional features for which the supplier of the implementation states the support.

### 3.2.3 Applicability to terminal equipment

The applicability to terminal equipment specified in TS 34.108 [12] shall apply, unless otherwise specified in the present clause.

Within the context of this document, the term "USS" refers to the 'UMTS System Simulator' when accessing a UTRAN and to the 'System Simulator' when accessing a GERAN.

See table B.1.

### 3.2.4 Definitions

For the purposes of the present document, the terms and definitions given in TS 34.108 [12], , apply.

#### 3.2.4.1 Format of the table of optional features

Option: The optional feature supported or not by the implementation.

Support Answer notation: The support columns shall be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [19], are used for the support column in the tables below.

| | |
|---|---|
| Y or y | supported by the implementation |
| N or n | not supported by the implementation |
| N/A, n/a or - | no answer required (allowed only if the status is N/A, directly or after evaluation of a conditional status) |

Mnemonic column: The Mnemonic column contains mnemonic identifiers for each item.

### 3.2.4.2 Format of the applicability table

The applicability of every test in table B.1 is formally expressed by the use of Boolean expression defined in the following clause.

The columns in table B.1 have the following meaning:

- In the "Item" column a local entry number for the requirement in the table is given.
- In the "Description" column a short non-exhaustive description of the requirement is found.
- The "Release" column gives the Release applicable and onwards, for the item in the "Description" column
- The "Test Sequence(s)" column gives a reference to the test sequence number(s) detailed in the present document and required to validate the implementation of the corresponding item in the "Description" column.
- For a given Release, the corresponding "Rel X ME" column lists the tests required for a Mobile Station to be declared compliant to this Release.
- The "Support" column is blank in the proforma, and shall be completed by the manufacturer in respect of each particular requirement to indicate the choices, which have been made in the implementation.
- The "Network Dependency" column indicates if a test depends on specific network access technology or requires network connection, but the status may not have an impact on references to ETSI TS 102 384 [26].
- The "Terminal Profile" column gives a reference to the corresponding bit that needs to be present in the Terminal Profile.

### 3.2.4.3 Status and notations

"Release X ME" columns show the status of the entries as follows:

The following notations, defined in ISO/IEC 9646-7 [19], are used for the status column:

| | |
|---|---|
| M | mandatory - the capability is required to be supported. |
| O | optional - the capability may be supported or not. |
| N/A | not applicable - in the given context, it is impossible to use the capability. |
| X | prohibited (excluded) - there is a requirement not to use this capability in the given context. |
| O.i | qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is defined immediately following the table. |
| Ci | conditional - the requirement on the capability ("M", "O", "X" or "N/A") depends on the support of other optional or conditional items. "i" is an integer identifying an unique conditional status expression which is defined immediately following the table. For nested conditional expressions, the syntax "IF ... THEN (IF ... THEN ... ELSE...) ELSE ..." shall be used to avoid ambiguities. |

References to items: For each possible item answer (answer in the support column) there exists a unique reference, used, for example, in the conditional expressions. It is defined as the table identifier, followed by a solidus character "/",

followed by the item number in the table. If there is more than one support column in a table, the columns shall be discriminated by letters (a, b, etc.), respectively.

EXAMPLE: A.1/4 is the reference to the answer of item 4 in table A.1.

## 3.3 Table of optional features

Support of USIM Application Toolkit is optional for Mobile Equipment. However, if an ME states conformance with a specific 3GPP release, it is mandatory for the ME to support all functions of that release, as stated in table B.1.

The support of letter classes, which specify mainly ME hardware dependent features, is optional for the ME and may supplement the USIM Application Toolkit functionality described in the present document. If an ME states conformance to a letter class, it is mandatory to support all functions within the respective letter class.

The supplier of the implementation shall state the support of possible options in table A.1.

**Table A.1: Options**

| Item | Option | Status | Support | Mnemonic |
|---|---|---|---|---|
| 1 | Capability Configuration parameter | M | | O_Cap_Conf |
| 2 | Sustained text | M | | O_sust_text |
| 3 | UCS2 coding scheme for Entry | O | | O_Ucs2_Entry |
| 4 | Extended Text String | M | | O_Ext_Str |
| 5 | Help information | O | | O_Help |
| 6 | Icons | O | | O_Icons |
| 7 | Class A: Dual Slot | O | | O_Dual_Slot |
| 8 | Detachable reader | O | | O_Detach_Rdr |
| 9 | Class B: RUN AT | O | | O_Run_At |
| 10 | Class C: LAUNCH BROWSER | O | | O_LB |
| 11 | Class D: Soft keys | O | | O_Soft_key |
| 12 | Class E: B.I.P related to CSD | O | | O_BIP_CSD |
| 13 | Screen sizing parameters | O | | O_Scr_Siz |
| 14 | Screen Resizing | O | | O_Scr_Resiz |
| 15 | UCS2 coding scheme for Display | O | | O_Ucs2_Disp |
| 16 | Mobile supporting GPRS | O | | O_GPRS |
| 17 | Mobile supporting UDP | O | | O_UDP |
| 18 | Mobile supporting TCP | O | | O_TCP |
| 19 | Redial in Set Up Call | O | | O_Redial |
| 20 | Mobile decision to respond with "No response from user" in finite time | O | | O_D_NoResp |
| 21 | Class E: B.I.P related to GPRS | O | | O_BIP_GPRS |
| 22 | Mobile supporting Called Party Subaddress | O | | O_CP_Subaddr |
| 23 | Immediate response | O | | O_Imm_Resp |
| 24 | Variable Timeout | O | | O_Duration |
| 25 | void | | | |
| 26 | Class F: B.I.P related to local bearer | O | | O_BIP_Local |
| 27 | BlueTooth Support | O | | O_BT |
| 28 | IrDA Support | O | | O_IrDA |
| 29 | RS232 Support | O | | O_RS232 |

| | | | | |
|---|---|---|---|---|
| 30 | USB Support | O | | O_USB |
| 31 | WML Browser Support | O | | O_WML |
| 32 | XHTML Browser Support | O | | O_XHTML |
| 33 | HTML Browser Support | O | | O_HTML |
| 34 | CHTML Browser Support | O | | O_CHTML |
| 35 | Class G: Battery Data | O | | O_Batt |
| 36 | Class H: Multimedia Call Support | O | | O_Xmedia_Call |
| 37 | Class I: Frame support | O | | O_Frames |
| 38 | Class J: Multimedia Messaging Support | O | | O_MMS |
| 39 | ME requesting for user confirmation before sending the Envelope Call Control command | O | | O_UC_Before_EnvCC |
| 40 | ME requesting for user confirmation after sending the Envelope Call Control command | O | | O_UC_After_EnvCC |
| 41 | UCS2 in Cyrillic | O | | O_UCS2_Cyrillic |
| 42 | UCS2 in Chinese | O | | O_UCS2_Chinese |
| 43 | UCS2 in Katakana | O | | O_UCS2_Katakana |
| 44 | Mobile supporting **B**arred **D**ialling Numbers | O | | O_BDN |
| 45 | Mobile supporting Fixed dialling numbers | O | | O_FDN |
| 46 | Mobile supporting "+CIMI" in combination with Run AT Command | O | | O_+CIMI |
| 47 | Mobile supporting "+CGMI" in combination with Run AT Command | O | | O_+CGMI |
| 48 | Mobile supporting Open Channel (GPRS) not containing a Network Access Name TLV when no default Access Point Name is set in the terminal configuration | O | | O_Open_Channel_GPRS_without_DefaultAPN |
| 49 | Preferred buffer size supported by the terminal for Open Channel command is greater than 0 byte and less than 65535 bytes | O | | O_BUFFER_SIZE |
| 50 | Text attributes – Alignment left | O | | O_TAT_AL |
| 51 | Text attributes – Alignment center | O | | O_TAT_AC |
| 52 | Text attributes – Alignment right | O | | O_TAT_AR |
| 53 | Text attributes – Font size normal | O | | O_TAT_FSN |
| 54 | Text attributes – Font size large | O | | O_TAT_FSL |
| 55 | Text attributes – Font size small | O | | O_TAT_FSS |

| | | | | |
|---|---|---|---|---|
| 56 | Text attributes – Style normal | O | | O_TAT_SN |
| 57 | Text attributes – Style bold | O | | O_TAT_SB |
| 58 | Text attributes – Style italic | O | | O_TAT_SI |
| 59 | Text attributes – Style underlined | O | | O_TAT_SU |
| 60 | Text attributes – Style strikethrough | O | | O_TAT_SS |
| 61 | Text attributes – Style text foreground colour | O | | O_TAT_STFC |
| 62 | Text attributes – Style text background colour | O | | O_TAT_STFB |
| 63 | Terminal supports Long ForwardToNumber | O | | O_longFTN |
| 64 | Mobile supporting GERAN | O | | O_GERAN |
| 65 | Support of global phonebook | C001 | | O_Global_PB |
| 66 | HSDPA Support | O | | O_HSDPA |
| 67 | UTRAN PS with extended parameters Support | O | | O_UTRAN_PS_Ext_Param |
| 68 | Terminal executes User confirmation phase before sending PDP context activation request | O | | O_User_Confirm_Before_PDP_Context_Request |
| C001 If terminal is implemented according to Rel-6 or later then M, else O | | | | |

## 3.4 Applicability table

**Table B.1: Applicability of tests**

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| **1** | **PROFILE DOWNLOAD 27.22.1** | R99 | **1** | **M** | M | M | M | E.1/1 | No | |
| **2** | **Contents of the TERMINAL PROFILE command 27.22.2** | R99 | | M | M | M | M | E.1/1 | No | |
| **3** | **Servicing of Proactive UICC Commands 27.22.3** | R99 | | M | M | M | M | | | |
| **4** | **DISPLAY TEXT 27.22.4.1** | | | | | | | | | |
| | Unpacked | R99 | 1.1 | M | M | M | M | E.1/17 | No | |
| | Screen busy | R99 | 1.2 | M | M | M | M | E.1/17 | No | |
| | high priority | R99 | 1.3 | M | M | M | M | E.1/17 | No | |
| | Packed | R99 | 1.4 | M | M | M | M | E.1/17 | No | |
| | clear after delay | R99 | 1.5 | M | M | M | M | E.1/17 | No | |
| | long text up to 160 bytes | R99 | 1.6 | M | M | M | M | E.1/17 | No | |
| | Backwards move in USIM session | R99 | 1.7 | M | M | M | M | E.1/17 | No | |
| | Session terminated by user | R99 | 1.8 | M | M | M | M | E.1/17 | No | |
| | Command not understood by ME | R99 | 1.9 | M | M | M | M | E.1/17 | No | |
| | no response from user | R99 | 2.1 | C120 | C120 | C120 | C120 | E.1/17 | No | |
| | Extension Text | R99 | 3.1 | M | M | M | M | E.1/17 AND E.1/16 | No | |
| | sustained text | R99 | 4.1, 4.2, 4.3, 4.4 | M | M | M | M | E.1/17 AND E.1/65 | No, except seq. 4.4 | |
| | Icons | R99 | 5.1, 5.2, 5.3 | C108 | C108 | C108 | C108 | E.1/17 | No | |
| | UCS2 display in Cyrillic | R99 | 6.1 | C118 | C118 | C118 | C118 | E.1/17 AND E.1/15 | No | |
| | Variable Timeout | Rel-4 | 7.1 | C126 | C126 | C126 | C126 | E.1/17 AND E.1/137 | No | |
| | Text attribute – left alignment | Rel-5 | 8.1 | | | C153 | C153 | E.1/17 AND E.1/124 AND E.1/217 | No | |
| | **Text attribute – center alignment** | **Rel-5** | **8.2** | | | **C154** | **C154** | **E.1/17 AND E.1/124 AND E.1/218** | **No** | |
| | **Text attribute – right alignment** | Rel-5 | 8.3 | | | C155 | C155 | E.1/17 AND E.1/124 AND E.1/219 | **No** | |
| | **Text attribute – large font size** | Rel-5 | 8.4 | | | C157 AND C156 | C157 AND C156 | E.1/17 AND E.1/124 AND E.1/221 AND E.1/220 | **No** | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – small font size** | Rel-5 | 8.5 | | | C158 AND C156 | C158 AND C156 | E.1/17 AND E.1/124 AND E.1/222 AND E.1/220 | **No** | |
| | **Text attribute – bold on** | Rel-5 | 8.6 | | | C160 AND C159 | C160 AND C159 | E.1/17 AND E.1/124 AND E.1/225 AND E.1/226 | **No** | |
| | **Text attribute – italic on** | Rel-5 | 8.7 | | | C161 AND C159 | C161 AND C159 | E.1/17 AND E.1/124 AND E.1/225 AND E.1/227 | **No** | |
| | **Text attribute – underlined on** | Rel-5 | 8.8 | | | C162 AND C159 | C162 AND C159 | E.1/17 AND E.1/124 AND E.1/225 AND E.1/228 | **No** | |
| | **Text attribute – strikethrough on** | Rel-5 | 8.9 | | | C163 AND C159 | C163 AND C159 | E.1/17 AND E.1/124 AND E.1/225 AND E.1/229 | **No** | |
| | **Text attribute – foreground and background colours** | Rel-5 | 8.10 | | | C164 AND C165 | C164 AND C165 | E.1/17 AND E.1/124 AND E.1/230 AND E.1/231 | **No** | |
| | UCS2 display in Chinese | **R99** | **9.1** | | | **C143** | **C143** | **E.1/17 AND E.1/15** | **No** | |
| | UCS2 display in Katakana | **R99** | **10.1** | | | **C145** | **C145** | E.1/17 AND E.1/15 | No | |
| | Frames | Rel-6 | TBD | | | | | E.1/17 AND E.1/177 AND E.1/178 | TBD | |
| **5** | **GET INKEY 27.22.4.2** | | | | | | | | | |
| | prompt unpacked | R99 | 1.1 | M | M | M | M | E.1/18 | No | |
| | prompt packed | R99 | 1.2 | M | M | M | M | E.1/18 | No | |
| | digits only | R99 | 1.1 | M | M | M | M | E.1/18 | No | |
| | Backwards move in UICC session | R99 | 1.3 | M | M | M | M | E.1/18 | No | |
| | Session terminated by user | R99 | 1.4 | M | M | M | M | E.1/18 | No | |
| | SMS alphabet | R99 | 1.5 | M | M | M | M | E.1/18 | No | |
| | Long text up to 160 bytes | R99 | 1.6 | M | M | M | M | E.1/18 | No | |
| | no response from user | R99 | 2.1 | C120 | C120 | C120 | C120 | E.1/18 | No | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | UCS2 display in Cyrillic | R99 | 3.1 | C118 | C118 | C118 | C118 | E.1/18 AND E.1/15 | No | |
| | **UCS2 display, Long text up to 70 chars in Cyrillic** | R99 | 3.2 | C118 | C118 | C118 | C118 | E.1/18 AND E.1/15 | No | |
| | **UCS2 entry in Cyrillic** | R99 | 4.1 | C105 | C105 | C105 | C105 | E.1/18 AND E.1/14 | No | |
| | **"Yes/No" response** | R99 | 5.1 | M | M | M | M | E.1/18 AND E.1/60 | No | |
| | **Icons** | R99 | 6.1, 6.2, 6.3, 6.4 | C108 | C108 | C108 | C108 | E.1/18 | No | |
| | **Help information** | R99 | 7.1 | C107 | C107 | C107 | C107 | E.1/18 | No | |
| | **Variable Timeout** | Rel-4 | 8.1 | C126 | C126 | C126 | C126 | E.1/18 AND E.1/140 | No | |
| | **Text attribute – left alignment** | Rel-5 | 9.1 | | | C153 | C153 | E.1/18 AND E.1/124 AND E.1/217 | No | |
| | **Text attribute – center alignment** | Rel-5 | 9.2 | | | C154 | C154 | E.1/18 AND E.1/124 AND E.1/218 | No | |
| | **Text attribute – right alignment** | Rel-5 | 9.3 | | | C155 | C156 | E.1/18 AND E.1/124 AND E.1/219 | No | |
| | **Text attribute – large font size** | Rel-5 | 9.4 | | | C157 AND C156 | C157 AND C156 | E.1/18 AND E.1/124 AND E.1/221 AND E.1/220 | No | |
| | **Text attribute – small font size** | Rel-5 | 9.5 | | | C158 AND C156 | C158 AND C156 | E.1/18 AND E.1/124 AND E.1/222 AND E.1/220 | **No** | |
| | **Text attribute – bold on** | Rel-5 | 9.6 | | | C160 AND C159 | C160 AND C159 | E.1/18 AND E.1/124 E.1/221 AND E.1/220 | **No** | |
| | **Text attribute – italic on** | Rel-5 | 9.7 | | | C161 AND C159 | C161 AND C159 | E.1/18 AND E.1/124 E.1/225 AND E.1/227 | **No** | |
| | **Text attribute – underlined on** | Rel-5 | 9.8 | | | C162 AND C159 | C162 AND C159 | E.1/18 AND E.1/124 E.1/225 AND E.1/228 | **No** | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – strikethough on** | Rel-5 | 9.9 | | | C163 AND C159 | C163 AND C159 | E.1/18 AND E.1/124 E.1/225 AND E.1/229 | **No** | |
| | **Text attribute – foreground and background colours** | **Rel-5** | 9.10 | | | C164 AND C165 | C164 And C165 | E.1/18 AND E.1/124 AND E.1/230 AND E.1/231 | **No** | |
| | UCS2 display in Chinese | **R99** | **10.1** | | | **C143** | **C143** | **E.1/18 AND E.1/15** | **No** | |
| | UCS2 display in Chinese, Long text up to 70 chars | **R99** | **10.2** | | | **C143** | **C143** | **E.1/18 AND E.1/15** | **No** | |
| | UCS2 entry in Chinese | **R99** | **11.1** | | | **C142** | **C142** | **E.1/18 AND E.1/14** | **No** | |
| | UCS2 display in Katakana | **R99** | **12.1** | | | **C145** | **C145** | **E.1/18 AND E.1/15** | **No** | |
| | UCS2 display in Katakana, Long text up to 70 chars | **R99** | **12.2** | | | **C145** | **C145** | **E.1/18 AND E.1/15** | **No** | |
| | UCS2 entry in Katakana | **R99** | **13.1** | | | **C144** | **C144** | E.1/18 AND E.1/14 | No | |
| | Frames | Rel-6 | TBD | | | | | E.1/18 AND E.1/177 AND E.1/178 | TBD | |
| **6** | **GET INPUT 27.22.4.3** | | | | | | | | | |
| | input unpacked | R99 | 1.1 | M | M | M | M | E.1/19 | No | |
| | input packed | R99 | 1.2 | M | M | M | M | E.1/19 | No | |
| | digits only | R99 | 1.1 | M | M | M | M | E.1/19 | No | |
| | SMS alphabet | R99 | 1.3 | M | M | M | M | E.1/19 | No | |
| | hidden input | R99 | 1.4 | M | M | M | M | E.1/19 | No | |
| | min / max acceptable length | R99 | 1.5, 1.9 | M | M | M | M | E.1/19 | No | |
| | Backwards move in UICC session | R99 | 1.6 | M | M | M | M | E.1/19 | No | |
| | Session terminated by user | R99 | 1.7 | M | M | M | M | E.1/19 | No | |
| | Prompt text up to 160 bytes | R99 | 1.8 | M | M | M | M | E.1/19 | No | |
| | SMS default alphabet, ME to echo text, packing not required | R99 | 1.9 | M | M | M | M | E.1/19 | No | |
| | Null length for the text string | R99 | 1.10 | M | M | M | M | E.1/19 | No | |
| | no response from user | R99 | 2.1 | C120 | C120 | C120 | C120 | E.1/19 | No | |
| | UCS2 display in Cyrillic | R99 | 3.1, 3.2 | C118 | C118 | C118 | C118 | E.1/19 AND E.1/15 | No | |
| | UCS2 entry in Cyrillic | R99 | 4.1, 4.2 | C105 | C105 | C105 | C105 | E.1/19 AND E.1/14 | No | |
| | default text for the input | R99 | 5.1, 5.2 | M | M | M | M | E.1/19 | No | |
| | icons | R99 | 6.1, 6.2, 6.3, 6.4 | C108 | C108 | C108 | C108 | E.1/19 | No | |
| | help information | R99 | 7.1 | C107 | C107 | C107 | C107 | E.1/19 | No | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute– left alignment | Rel-5 | 8.1 | | | C153 | C153 | E.1/19 AND E.1/124 AND E.1/217 | No | |
| | Text attribute – center alignment | Rel-5 | 8.2 | | | C154 | C145 | E.1/19 AND E.1/124 AND E.1/218 | No | |
| | Text attribute – right alignment | Rel-5 | 8.3 | | | C155 | C155 | E.1/19 AND E.1/124 AND E.1/219 | No | |
| | Text attribute – large font size | Rel-5 | 8.4 | | | C157 AND C156 | C157 AND C156 | E.1/19 AND E.1/124 AND E.1/221 AND E.1/220 | No | |
| | Text attribute – small font size | Rel-5 | 8.5 | | | C158 AND C156 | C158 AND C156 | E.1/19 AND E.1/124 AND E.1/222 AND E.1/220 | No | |
| | Text attribute – bold on | Rel-5 | 8.6 | | | C160 AND C159 | C160 AND C159 | E.1/19 AND E.1/124 AND E.1/225 AND E.1/226 | No | |
| | Text attribute – italic on | Rel-5 | 8.7 | | | C161 AND C159 | C161 AND C159 | E.1/19 AND E.1/124 AND E.1/225 AND E.1/227 | **No** | |
| | Text attribute – underlined on | Rel-5 | 8.8 | | | C162 AND C159 | C162 AND C159 | E.1/19 AND E.1/124 AND E.1/225 AND E.1/228 | **No** | |
| | Text attribute – strikethrough on | Rel-5 | 8.9 | | | C163 AND C159 | C163 AND C159 | E.1/19 AND E.1/124 AND E.1/225 AND E.1/229 | **No** | |
| | Text attribute – foreground and background colours | Rel-5 | 8.10 | | | C164 AND C165 | C164 AND C165 | E.1/19 AND E.1/124 AND E.1/230 AND E.1/231 | **N o** | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | UCS2 display in Chinese | **R99** | **9.1, 9.2** | | | **C143** | **C143** | **E.1/19 AND E.1/15** | **No** | |
| | UCS2 entry in Chinese | **R99** | **10.1, 10.2** | | | **C142** | **C142** | **E.1/19 AND E.1/14** | **No** | |
| | UCS2 display in Katakana | **R99** | **11.1, 11.2** | | | **C145** | **C145** | **E.1/19 AND E.1/15** | **No** | |
| | UCS2 entry in Katakana | **R99** | **12.1, 12.2** | | | **C144** | **C144** | E.1/19 AND E.1/14 | No | |
| | Frames | Rel-6 | TBD | | | | | E.1/19 AND E.1/177 AND E.1/178 | TBD | |
| **7** | MORE TIME 27.22.4.4 | R99 | 1.1 | M | M | M | M | E.1/20 | No | |
| **8** | PLAY TONE 27.22.4.5 | | | | | | | | | |
| | play all tones | R99 | 1.1 | M | M | M | M | E.1/21 | Yes | |
| | display alpha | R99 | 1.1 | M | M | M | M | E.1/21 | Yes | |
| | user termination | R99 | 1.1 | M | M | M | M | E.1/21 | Yes | |
| | superimpose | R99 | 1.1 | M | M | M | M | E.1/21 | Yes | |
| | UCS2 display in Cyrillic | R99 | 2.1 | C118 | C118 | C118 | C118 | E.1/21 AND E.1/15 | No | |
| | icons | R99 | 3.1, 3.2,3.3, 3.4 | C108 | C108 | C108 | C108 | E.1/21 | No | |
| | Text attribute – left alignment | Rel-5 | 4.1 | | | C153 | C153 | E.1/21 AND E.1/124 AND E.1/217 | No | |
| | Text attribute – center alignment | Rel-5 | 4.2 | | | C154 | C154 | E.1/21 AND E.1/124 AND E.1/218 | No | |
| | Text attribute – right alignment | Rel-5 | 4.3 | | | C155 | C155 | E.1/21 AND E.1/124 AND E.1/219 | No | |
| | Text attribute – large font size | Rel-5 | 4.4 | | | C157 AND C156 | C157 AND C156 | E.1/21 AND E.1/124 AND E.1/221 AND E.1/220 | No | |
| | Text attribute – small font size | Rel-5 | 4.5 | | | C158 AND C156 | C158 AND C156 | E.1/21 AND E.1/124 AND E.1/222 AND E.1/220 | No | |
| | Text attribute – bold on | Rel-5 | 4.6 | | | C160 AND C159 | C160 AND C159 | E.1/21 AND E.1/124 AND E.1/225 AND E.1/226 | No | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – italic on | Rel-5 | 4.7 | | | C161 AND C159 | C161 AND C159 | E.1/21 AND E.1/124 AND E.1/225 AND E.1/227 | No | |
| | Text attribute – underlined on | Rel-5 | 4.8 | | | C162 AND C159 | C162 AND C159 | E.1/21 AND E.1/124 AND E.1/225 AND E.1/228 | No | |
| | Text attribute – strikethrough on | Rel-5 | 4.9 | | | C163 AND C159 | C163 AND C159 | E.1/21 AND E.1/124 AND E.1/225 AND E.1/229 | No | |
| | Text attribute– foreground and background colours | Rel-5 | 4.10 | | | C164 AND C165 | C164 AND C165 | E.1/21 AND E.1/124 AND E.1/230 AND E.1/231 | No | |
| | UCS2 display in Chinese | **R99** | **5.1** | | | **C143** | **C143** | **E.1/21 AND E.1/15** | **No** | |
| | UCS2 display in Katakana | **R99** | **6.1** | | | **C145** | **C145** | E.1/21 AND E.1/15 | No | |
| | Frames | Rel-6 | TBD | | | | | E.1/21 AND E.1/177 AND E.1/178 | TBD | |
| | Themed and Melody tones | Rel-6 | TBD | | | | | E.1/21 | TBD | |
| **9** | **POLL INTERVAL 27.22.4.6** | | | | | | | | | |
| | duration | R99 | 1.1 | M | M | M | M | E.1/22 | No | |
| **10** | **REFRESH 27.22.4.7** | | | | | | | | | |
| | **USIM initialization, enabling FDN mode** | **R99** | **1.1** | **C146** | **C146** | **C146** | **C146** | **E.1/24** | **Yes** | |
| | **file change notification of FDN file** | **R99** | **1.2** | **C146** | **C146** | **C146** | **C146** | **E.1/24** | **Yes** | |
| | USIM initialization and file change notification of ADN | R99 | 1.3 | C168 | C168 | C168 | M | E.1/24 | No | |
| | **USIM initialization and full file change notification, enabling FDN mode** | **R99** | **1.4** | **C146** | **C146** | **C146** | **C146** | **E.1/24** | **Yes** | |
| | UICC reset | R99 | 1.5 | | | | M | E.1/24 | No | |
| | **USIM Initialization after SMS-PP data download** | R99 | 1.6 | C146 | C146 | C146 | C146 | E.1/24 | Yes | |
| | **USIM Application Reset** | R99 | 1.7 | | | | C146 | E1/24 | Yes | |
| | UICC Reset for IMSI Changing procedure | R99 | 2.1 | | | | | | TBD | |
| | USIM Application Reset for IMSI Changing procedure | R99 | 2.2 | | | | M | E.1/24 | Yes | |
| | 3G Session Reset for IMSI Changing procedure | R99 | 2.3 | | | | | | TBD | |
| | reject 3G Session Reset for IMSI Changing procedure during call | R99 | 2.4 | | | | M | E 1/24 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| 11 | **SET UP MENU 27.22.4.8** | | | | | | | | | |
| | Set up, menu selection, replace and remove menu | R99 | 1.1 | M | M | M | M | E.1/30 AND E.1/4 | No | |
| | Large menu | R99 | 1.2 | M | M | M | M | E.1/30 AND E.1/4 | No | |
| | help information | R99 | 2.1 | C107 | C107 | C107 | C107 | E.1/30 AND E.1/4 | No | |
| | next action indicator | R99 | 3.1 | M | M | M | M | E.1/30 | No | |
| | Icons | R99 | 4.1, 4.2 | C108 | C108 | C108 | C108 | E.1/30 | No | |
| | soft key access | R99 | 5.1 | C112 | C112 | C112 | C112 | E.1/30 AND E.1/74 | No | |
| | Text attribute – left alignment | Rel-5 | 6.1 | | | C153 | C153 | E.1/30 AND E.1/124 AND E.1/217 | No | |
| | Text attribute – center alignment | Rel-5 | 6.2 | | | C154 | C154 | E.1/30 AND E.1/124 AND E.1/218 | No | |
| | Text attribute – right alignment | Rel-5 | 6.3 | | | C155 | C155 | E.1/30 AND E.1/124 AND E.1/219 | No | |
| | Text attribute – large font size | Rel-5 | 6.4 | | | C157 AND C156 | C157 AND C156 | E.1/30 AND E.1/124 AND E.1/221 AND E.1/220 | No | |
| | Text attribute – small font size | Rel-5 | 6.5 | | | C158 AND C156 | C158 AND C156 | E.1/30 AND E.1/124 AND E.1/222 AND E.1/220 | No | |
| | Text attribute – bold on | Rel-5 | 6.6 | | | C160 AND C159 | C160 AND C159 | E.1/30 AND E.1/124 AND E.1/225 AND E.1/226 | No | |
| | Text attribute – italic on | Rel-5 | 6.7 | | | C161 AND C159 | C161 AND C159 | E.1/30 AND E.1/124 AND E.1/225 AND E.1/227 | No | |
| | Text attribute – underlined on | Rel-5 | 6.8 | | | C162 AND C159 | C162 AND C159 | E.1/30 AND E.1/124 AND E.1/225 AND E.1/228 | No | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – strikethrough on | Rel-5 | 6.9 | | | C163 AND C159 | C163 AND C159 | E.1/30 AND E.1/124 AND E.1/225 AND E.1/229 | No | |
| | Text attribute – foreground and background colours | Rel-5 | 6.10 | | | C164 AND C165 | C164 AND C165 | E.1/30 AND E.1/124 AND E.1/230 AND E.1/231 | No | |
| | UCS2 display in Cyrillic | **R99** | **7.1** | | | **C118** | **C118** | **E.1/39 AND E.1/15** | **No** | |
| | UCS2 display in Chinese | **R99** | **8.1** | | | **C143** | **C143** | **E.1/39 AND E.1/15** | **No** | |
| | UCS2 display in Katakana | **R99** | **9.1** | | | **C145** | **C145** | E.1/39 AND E.1/15 | No | |
| **12** | **SELECT ITEM 27.22.4.9** | | | | | | | | | |
| | Mandatory features | R99 | 1.1 | M | M | M | M | E.1/25 | No | |
| | Large menu | R99 | 1.2, 1.3, 1.5,1.6 | M | M | M | M | E.1/25 | No | |
| | Backwards move | R99 | 1.4 | M | M | M | M | E.1/25 | No | |
| | user termination | R99 | 1.5 | M | M | M | M | E.1/25 | No | |
| | next action indicator | R99 | 2.1 | M | M | M | M | E.1/25 | No | |
| | default selected item | R99 | 3.1 | M | M | M | M | E.1/25 | No | |
| | help information | R99 | 4.1 | C107 | C107 | C107 | C107 | E 1/25 | No | |
| | icons | R99 | 5.1, 5.2 | C108 | C108 | C108 | C108 | E.1/25 | No | |
| | Presentation style | R99 | 6.1, 6.2 | M | M | M | M | E.1/25 | No | |
| | Soft keys | R99 | 7.1 | C112 | C112 | C112 | C112 | E.1/25 AND E.1/73 | No | |
| | No Response from user | R99 | 8.1 | C120 | C120 | C120 | C120 | E.1/25 | No | |
| | Text attribute – left alignment | Rel-5 | 9.1 | | | C153 | C153 | E.1/25 AND E.1/124 AND E.1/217 | No | |
| | Text attribute – center alignment | Rel-5 | 9.2 | | | C154 | C154 | E.1/25 AND E.1/124 AND E.1/218 | No | |
| | Text attribute – right alignment | Rel-5 | 9.3 | | | C155 | C155 | E.1/25 AND E.1/124 AND E.1/219 | No | |
| | Text attribute – large font size | Rel-5 | 9.4 | | | C157 AND C156 | C157 AND C156 | E.1/25 AND E.1/124 AND E.1/221 AND E.1/220 | No | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – small font size | Rel-5 | 9.5 | | | C158 AND C156 | C158 AND C156 | E.1/25 AND E.1/124 AND E.1/222 AND E.1/220 | No | |
| | Text attribute – bold on | Rel-5 | 9.6 | | | C160 AND C159 | C160 AND C159 | E.1/25 AND E.1/124 AND E.1/225 AND E.1/226 | No | |
| | Text attribute – italic on | Rel-5 | 9.7 | | | C161 AND C159 | C161 AND C159 | E.1/25 AND E.1/124 AND E.1/225 AND E.1/227 | No | |
| | Text attribute – underline on | Rel-5 | 9.8 | | | C162 AND C159 | C162 AND C159 | E.1/25 AND E.1/124 AND E.1/225 AND E.1/228 | No | |
| | Text attribute – strikethrough on | Rel-5 | 9.9 | | | C163 AND C159 | C163 AND C159 | E.1/25 AND E.1/124 AND E.1/225 AND E.1/229 | No | |
| | Text attribute – foreground and background colours | Rel-5 | 9.10 | | | C164 AND C165 | C164 AND C165 | E.1/25 AND E.1/124 AND E.1/230 AND E.1/231 | No | |
| | UCS2 display in Cyrillic | **R99** | **10.1, 10.2, 10.3** | | | **C118** | **C118** | **E.1/39 AND E.1/15** | **No** | |
| | UCS2 display in Chinese | **R99** | **11.1** | | | **C143** | **C143** | **E.1/25 AND E.1/15** | **No** | |
| | UCS2 display in Katakana | **R99** | **12.1, 12.2, 12.3** | | | **C145** | **C145** | E.1/25 AND E.1/15 | No | |
| | Frames | Rel-6 | TBD | | | | | E.1/25 AND E.1/177 AND E.1/178 | TBD | |
| **13** | **SEND SMS 27.22.4.10** | | | | | | | | | |
| | Packing not required | R99 | 1.1, 1.3 1.5 | M | M | M | M | E.1/26 | Yes | |
| | Packing required | R99 | 1.2, 1.4 | M | M | M | M | E.1/26 | Yes | |
| | 8 bit data | R99 | 1.1, 1.2 | M | M | M | M | E.1/26 | Yes | |
| | SMS default alphabet | R99 | 1.3, 1.4, 1.5 | M | M | M | M | E.1/26 | Yes | |
| | 160 bytes length | R99 | 1.4, 1.5 | M | M | M | M | E.1/26 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Alpha identifier | R99 | 1.6, 1.7, 1.8 | M | M | M | M | E.1/26 | Yes | |
| | UCS2 SMS in Cyrillic | R99 | 2.1 | C118 | C118 | C118 | C118 | E.1/26 AND E.1/15 | Yes | |
| | icons | R99 | 3.1, 3.2 | C108 | C108 | C108 | C108 | E.1/26 | Yes | |
| | Text attribute– left alignment | Rel-5 | 4.1 | | | C153 | C153 | E.1/26 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 4.2 | | | C154 | C154 | E.1/26 AND E.1/124 AND E.1/218 | No | |
| | **Text attribute – right alignment** | Rel-5 | 4.3 | | | C155 | C155 | E.1/26 AND E.1/124 AND E.1/219 | No | |
| | **Text attribute – large font size** | Rel-5 | 4.4 | | | C157 AND C156 | C157 AND C156 | E.1/26 AND E.1/124 AND E.1/221 AND E.1/220 | No | |
| | **Text attribute – small font size** | Rel-5 | 4.5 | | | C158 AND C156 | C158 AND C156 | E.1/26 AND E.1/124 AND E.1/222 AND E.1/220 | No | |
| | **Text attribute – bold on** | Rel-5 | 4.6 | | | C160 AND C159 | C160 AND C159 | E.1/26 AND E.1/124 AND E.1/225 AND E.1/226 | No | |
| | **Text attribute – italic on** | Rel-5 | 4.7 | | | C161 AND C159 | C161 AND C159 | E.1/26 AND E.1/124 AND E.1/225 AND E.1/227 | No | |
| | Text attribute – underline on | Rel-5 | 4.8 | | | C162 AND C159 | C162 AND C159 | E.1/26 AND E.1/124 AND E.1/225 AND E.1/228 | No | |
| | Text attribute– strikethrough on | Rel-5 | 4.9 | | | C163 AND C159 | C163 AND C159 | E.1/26 AND E.1/124 AND E.1/225 AND E.1/229 | No | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – foreground and background colours | Rel-5 | 4.10 | | | C164 AND C165 | C164 AND C165 | E.1/26 AND E.1/124 AND E.1/230 AND E.1/231 | No | |
| | UCS2 display in Chinese | **R99** | **5.1** | | | **C143** | **C143** | **E.1/26 AND E.1/15** | **Yes** | |
| | UCS2 display in Katakana | **R99** | **6.1** | | | **C145** | **C145** | E.1/26 AND E.1/15 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/26 AND E.1/177 AND E.1/178 | TBD | |
| **14** | **SEND SS 27.22.4.11** | | | | | | | | | |
| | call forward unconditional, all bearers, successful | R99 | 1.1 | C166 | C166 | C166 | C166 | E.1/27 | Yes | |
| | call forward unconditional, all bearers, Return Error | R99 | 1.2 | M | M | M | M | E.1/27 | Yes | |
| | call forward unconditional, all bearers, Reject | R99 | 1.3 | M | M | M | M | E.1/27 | Yes | |
| | call forward unconditional, all bearers, successful, SS request size limit | R99 | 1.4 | C166 | C166 | C166 | C166 | E.1/27 | Yes | |
| | interrogate CLIR status, successful, alpha identifier limits | R99 | 1.5 | M | M | M | M | E.1/27 | Yes | |
| | call forward unconditional, all bearers, successful, null data alpha identifier | R99 | 1.6 | C166 | C166 | C166 | C166 | E.1/27 | Yes | |
| | call forward unconditional, all bearers, successful, icon support | R99 | 2.1, 2.2, 2.3, 2.4 | C108 | C108 | C108 | C108 | E.1/27 | Yes | |
| | UCS2 display in Cyrillic | R99 | 3.1 | C118 | C118 | C118 | C118 | E.1/27 AND E.1/15 | Yes | |
| | Text attribute – left alignment | Rel-5 | 4.1 | | | C153 AND C166 | C153 AND C166 | E.1/27 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | **4.2** | | | **C154 AND C166** | **C154 AND C166** | **E.1/27 AND E.1/124 AND E.1/218** | **Yes** | |
| | **Text attribute – right alignment** | **Rel-5** | **4.3** | | | **C155 AND C166** | **C155 AND C166** | **E.1/27 AND E.1/124 AND E.1/219** | **Yes** | |
| | **Text attribute – large font size** | **Rel-5** | **4.4** | | | **C157 AND C156 AND C166** | **C157 AND C156 AND C166** | **E.1/27 AND E.1/124 AND E.1/221 AND E.1/220** | **Yes** | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – small font size** | **Rel-5** | **4.5** | | | **C158 AND C156 AND C166** | **C158 AND C156 AND C166** | **E.1/27 AND E.1/124 AND E.1/222 AND E.1/220** | **Yes** | |
| | **Text attribute – bold on** | **Rel-5** | **4.6** | | | **C160 AND C159 AND C166** | **C160 AND C159 AND C166** | **E.1/27 AND E.1/124 AND E.1/225 AND E.1/226** | **Yes** | |
| | **Text attribute – italic on** | **Rel-5** | **4.7** | | | **C161 AND C159 AND C166** | **C161 AND C159 AND C166** | **E.1/27 AND E.1/124 AND E.1/225 AND E.1/227** | **Yes** | |
| | Text attribute – underline on | **Rel-5** | **4.8** | | | **C162 AND C159 AND C166** | **C162 AND C159 AND C166** | **E.1/27 AND E.1/124 AND E.1/225 AND E.1/228** | **Yes** | |
| | Text attribute – strikethrough on | **Rel-5** | **4.9** | | | **C163 AND C159 AND C166** | **C163 AND C159 AND C166** | **E.1/27 AND E.1/124 AND E.1/225 AND E.1/229** | **Yes** | |
| | Text attribute – foreground and background colours | **Rel-5** | **4.10** | | | **C164 AND C165 AND C166** | **C164 AND C165 AND C166** | **E.1/27 AND E.1/124 AND E.1/230 AND E.1/231** | **Yes** | |
| | UCS2 display in Chinese | **R99** | **5.1** | | | **C143 AND C166** | **C143 AND C166** | **E.1/27 AND E.1/15** | **Yes** | |
| | UCS2 display in Katakana | **R99** | **6.1** | | | **C145 AND C166** | **C145 AND C166** | E.1/27 AND E.1/15 | Yes | |
| **15** | **SEND USSD 27.22.4.12** | | | | | | | | | |
| | 7-bit data, successful | R99 | 1.1 | M | M | M | M | E.1/28 | Yes | |
| | 8-bit data, successful | R99 | 1.2 | M | M | M | M | E.1/28 | Yes | |
| | UCS2 data, successful | R99 | 1.3 | M | M | M | M | E.1/28 | Yes | |
| | 7-bit data, unsuccessful | R99 | 1.4 | M | M | M | M | E.1/28 | Yes | |
| | 7-bit data, unsuccessful | R99 | 1.5 | M | M | M | M | E.1/28 | Yes | |
| | 256 octets, 7-bit data, successful, long alpha identifier | R99 | 1.6 | M | M | M | M | E.1/28 | Yes | |
| | 7-bit data, successful, no alpha identifier | R99 | 1.7 | M | M | M | M | E.1/28 | Yes | |
| | 7-bit data, successful, null length alpha identifier | R99 | 1.8 | M | M | M | M | E.1/28 | Yes | |
| | icons | R99 | 2.1, 2.2, 2.3, 2.4 | C108 | C108 | C108 | C108 | E.1/28 | Yes | |
| | UCS2 in Cyrillic | R99 | 3.1 | C118 | C118 | C118 | C118 | E.1/28 AND E.1/15 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – left alignment | Rel-5 | 4.1 | | | C153 | C153 | E.1/28 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 4.2 | | | C154 | C154 | E.1/28 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | Rel-5 | 4.3 | | | C155 | C155 | E.1/28 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 4.4 | | | C157 AND C156 | C157 AND C156 | E.1/28 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 4.5 | | | C158 AND C156 | C158 AND C156 | E.1/28 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |
| | **Text attribute – bold on** | Rel-5 | 4.6 | | | C160 AND C159 | C160 AND C159 | E.1/28 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | Rel-5 | 4.7 | | | C161 AND C159 | C161 AND C159 | E.1/28 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 4.8 | | | C162 AND C159 | C162 AND C159 | E.1/28 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | Text attribute – strikethrough on | Rel-5 | 4.9 | | | C163 AND C159 | C163 AND C159 | E.1/28 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |
| | Text attribute – foreground and background colours | Rel-5 | 4.10 | | | C164 AND C165 | C164 AND C165 | E.1/28 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | UCS2 in Chinese | **R99** | **5.1** | | | **C143** | **C143** | **E.1/28 AND E.1/15** | **Yes** | |
| | UCS2 in Katakana | **R99** | **6.1** | | | **C145** | **C145** | E.1/28 AND E.1/15 | Yes | |
| **16** | **SET UP CALL 27.22.4.13** | | | | | | | | | |
| | Call confirmed by the user and connected | R99 | 1.1 | M | M | M | M | E.1/29 | Yes | |
| | call rejected by the user | R99 | 1.2 | M | M | M | M | E.1/29 | Yes | |
| | void | | | | | | | E.1/29 | | |
| | putting all other calls on hold, ME busy | R99 | 1.4 | M | M | M | M | E.1/29 | Yes | |
| | disconnecting all other calls, ME busy | R99 | 1.5 | M | M | M | M | E.1/29 | Yes | |
| | only if not currently busy on another call, ME busy | R99 | 1.6 | M | M | M | M | E.1/29 | Yes | |
| | putting all other calls on hold, call hold is not allowed | R99 | 1.7 | M | M | M | M | E.1/29 | Yes | |
| | Capability configuration | R99 | 1.8 | C101 | C101 | C101 | C101 | E.1/29 | Yes | |
| | long dialling number string | R99 | 1.9 | M | M | M | M | E.1/29 | Yes | |
| | long first alpha identifier | R99 | 1.10 | M | M | M | M | E.1/29 | Yes | |
| | Called party subaddress | R99 | 1.11 | C124 | C124 | C124 | C124 | E.1/29 | Yes | |
| | maximum duration for the redial mechanism | R99 | 1.12 | C119 | C119 | C119 | C119 | E.1/29 | Yes | |
| | second alpha identifier | R99 | 2.1 | M | M | M | M | E.1/29 AND E.1/63 | Yes | |
| | icons | R99 | 3.1,3.2, 3.3, 3.4 | C108 | C108 | C108 | C108 | E.1/29 | Yes | |
| | Text attribute – left alignment | Rel-5 | 4.1 | | | C153 | C153 | E.1/29 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 4.2 | | | C154 | C154 | E.1/29 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | Rel-5 | 4.3 | | | C155 | C155 | E.1/29 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 4.4 | | | C157 AND C156 | C157 AND C156 | E.1/29 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 4.5 | | | C158 AND C156 | C158 AND C156 | E.1/29 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – bold on** | Rel-5 | 4.6 | | | C160 AND C159 | C160 AND C159 | E.1/29 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | Rel-5 | 4.7 | | | C161 AND C159 | C161 AND C159 | E.1/29 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 4.8 | | | C162 AND C159 | C162 AND C159 | E.1/29 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | Text attribute – strikethrough on | Rel-5 | 4.9 | | | C163 AND C159 | C163 AND C159 | E.1/29 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |
| | Text attribute – foreground and background colours | Rel-5 | 4.10 | | | C164 AND C165 | C164 AND C165 | E.1/29 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | UCS2 Display in Cyrillic | **R99** | **5.1, 5.2.** | | | **C118** | **C118** | **E.1/29 AND E.1/15** | **Yes** | |
| | UCS2 display in Chinese | **R99** | **6.1, 6.2** | | | **C143** | **C143** | **E.1/29 AND E.1/15** | **Yes** | |
| | UCS2 display in Katakana | **R99** | **7.1, 7.2** | | | **C145** | **C145** | E.1/29 AND E.1/15 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/29 AND E.1/177 AND E.1/178 | TBD | |
| **17** | **POLLING OFF 27.22.4.14** | R99 | 1.1 | M | M | M | M | E.1/23 | Yes | |
| **18** | **PROVIDE LOCAL INFO 27.22.4.15** | | | | | | | | | |
| | location information | R99 | 1.1 | M | M | M | M | E.1/31 | Yes | |
| | IMEI | R99 | 1.2 | M | M | M | M | E.1/31 | Yes | |
| | network measurement results and BCCH channel list | R99 | 1.3 | C167 | C167 | C167 | C167 | E.1/32 AND E.1/67 | System Simulator only | |
| | Date, time and time zone | R99 | 1.4 | M | M | M | M | E.1/59 | No | |
| | language setting | R99 | 1.5 | M | M | M | M | E.1/68 | No | |
| | Timing advance | R99 | 1.6 | C167 | C167 | C167 | C167 | E.1/69 | System Simulator only | |
| | Access Technology | Rel-4 | 1.7 | | M | M | M | E.1/72 | Yes | |
| | Void | | | | | | | | | |
| | IMEISV | Rel-6 | 1.9 | | | | M | E.1/143 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Search Mode Change | Rel-6 | 1.10 | | | | | E.1/144 | TBD | |
| | Charge State of the Battery | Rel-6 | 1.11 | | | | C139 | E.1/170 | No | |
| | UTRAN measurements | Rel-6 | 1.12 | | | | M | E.1/183 | System Simulator only | |
| **19** | **SET UP EVENT LIST 27.22.4.16** | | | | | | | | | |
| | Set up call connected event | R99 | 1.1 | M | M | M | M | E.1/33 AND E.1/35 | Yes | |
| | Replace by new event list | R99 | 1.2 | M | M | M | M | E.1/33 AND E.1/35 AND E.1/36 | Yes | |
| | Remove event | R99 | 1.3 | M | M | M | M | E.1/33 AND E.1/35 | Yes | |
| | Remove Event on ME Power Cycle | R99 | 1.4 | M | M | M | M | E.1/33 AND E.1/35 | Yes | |
| **20** | **PERFORM CARD APDU 27.22.4.17** | | | | | | | | | |
| | Additional card inserted, Select MF and Get Response | R99 | 1.1 | C109 | C109 | C109 | C109 | E.1/51 | No | |
| | Additional card inserted, Select DF GSM, Select EF PLMN , Update Binary, Read Binary on EF PLMN | R99 | 1.2 | C109 | C109 | C109 | C109 | E.1/51 | No | |
| | Additional card inserted, card powered off | R99 | 1.3 | C109 | C109 | C109 | C109 | E.1/51 | No | |
| | No card inserted, card powered off | R99 | 1.4 | C109 | C109 | C109 | C109 | E.1/51 | No | |
| | Invalid card reader identifier | R99 | 1.5 | C109 | C109 | C109 | C109 | E.1/51 | No | |
| | Detachable reader | R99 | 2.1 | C116 | C116 | C116 | C116 | E.1/51 | No | |
| **21** | **POWER OFF CARD 27.22.4.18** | | | | | | | | | |
| | Additional card inserted | R99 | 1.1 | C109 | C109 | C109 | C109 | E.1/50 | No | |
| | No card inserted | R99 | 1.2 | C109 | C109 | C109 | C109 | E.1/50 | No | |
| | Detachable reader | R99 | 2.1 | C116 | C109 | C109 | C109 | E.1/50 | No | |
| **22** | **POWER ON CARD 27.22.4.19** | | | | | | | | | |
| | Additional card inserted | R99 | 1.1 | C109 | C109 | C109 | C109 | E.1/49 | No | |
| | No ATR | R99 | 1.2 | C109 | C109 | C109 | C109 | E.1/49 | No | |
| | No card inserted | R99 | 1.3 | C109 | C109 | C109 | C109 | E.1/49 | No | |
| | Detachable reader | R99 | 2.1 | C116 | C116 | C116 | C116 | E.1/49 | No | |
| **23** | **GET READER STATUS 27.22.4.20** | | | | | | | | | |
| | Additional card inserted, card powered | R99 | 1.1 | C109 | C109 | C109 | C109 | E.1/52 | No | |
| | Additional card inserted, card not powered | R99 | 1.2 | C109 | C109 | C109 | C109 | E.1/52 | No | |
| | Additional card inserted, card not present | R99 | 1.3 | C109 | C109 | C109 | C109 | E.1/52 | No | |
| | Detachable reader | R99 | 2.1 | C116 | C116 | C116 | C116 | E.1/52 | No | |
| **24** | **TIMER MANAGEMENT 27.22.4.21.1** | | | | | | | | | |
| | Start timer 1 several times, get the current value of the timer and deactivate the timer successfully | R99 | 1.1 | M | M | M | M | E.1/57 AND E.1/58 | No | |
| | Start timer 2 several times, get the current value of the timer and deactivate the timer successfully | R99 | 1.2 | M | M | M | M | E.1/57 AND E.1/58 | No | |
| | Start timer 8 several times, get the current value of the timer and deactivate the timer successfully | R99 | 1.3 | M | M | M | M | E.1/57 AND E.1/58 | No | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Try to get the current value of a timer which is not started: action in contradiction with the current timer state | R99 | 1.4 | M | M | M | M | E.1/57 AND E.1/58 | No | |
| | Try to deactivate a timer which is not started: action in contradiction with the current timer state | R99 | 1.5 | M | M | M | M | E.1/57 AND E.1/58 | No | |
| | Start 8 timers successfully | R99 | 1.6 | M | M | M | M | E.1/57 AND E.1/58 | No | |
| **25** | **ENVELOPE TIMER EXPIRATION 27.22.4.21.2** | | | | | | | | | |
| | Pending proactive UICC command | R99 | 2.1 | M | M | M | M | E.1/6 AND E.1/57 | No | |
| | USIM application toolkit busy | R99 | 2.2 | M | M | M | M | E.1/6 AND E.1/57 AND E.1/20 | No | |
| **26** | **SET UP IDLE MODE TEXT 27.22.4.22** | | | | | | | | | |
| | Display idle mode text | R99 | 1.1 | M | M | M | M | E.1/61 AND E.1/33 AND E.1/39 | Yes | |
| | Replace idle mode text | R99 | 1.2 | M | M | M | M | E.1/61 AND E.1/33 AND E.1/39 | Yes | |
| | Remove idle mode test | R99 | 1.3 | M | M | M | M | E.1/61 AND E.1/33 AND E.1/39 | Yes | |
| | Competing information on ME display | R99 | 1.4 | M | M | M | M | E.1/61 AND E.1/33 AND E.1/39 | Yes | |
| | ME powered cycled | R99 | 1.5 | M | M | M | M | E.1/61 AND E.1/33 AND E.1/39 | Yes | |
| | Refresh with USIM initialization | R99 | 1.6 | M | M | M | M | E.1/61 AND E.1/24 AND E.1/33 AND E.1/39 | Yes | |
| | Large text string | R99 | 1.7 | M | M | M | M | E.1/61 AND E.1/33 AND E.1/39 | Yes | |
| | Icons | R99 | 2.1, 2.2, 2.3, 2.4 | C108 | C108 | C108 | C108 | E.1/61 AND E.1/39 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | UCS2 display in Cyrillic | R99 | 3.1 | C118 | C118 | C118 | C118 | E.1/61 AND E.1/15 AND E.1/39 | Yes | |
| | Text attribute – left alignment | Rel-5 | 4.1 | | | C153 | C153 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 4.2 | | | C154 | C154 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | Rel-5 | 4.3 | | | C155 | C155 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 4.4 | | | C157 AND C156 | C157 AND C156 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 4.5 | | | C158 AND C156 | C158 AND C156 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |
| | **Text attribute – bold on** | Rel-5 | 4.6 | | | C160 AND C159 | C160 AND C159 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – italic on** | Rel-5 | 4.7 | | | C161 AND C159 | C161 AND C159 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 4.8 | | | C162 AND C159 | C162 AND C159 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | **Text attribute – strikethrough on** | Rel-5 | 4.9 | | | C163 AND C159 | C163 AND C159 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |
| | Text attribute – foreground and background colours | Rel-5 | 4.10 | | | C164 AND C165 | C164 AND C165 | E.1/61 AND E.1/33 AND E.1/39 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | UCS2 display in Chinese | **R99** | **5.1** | | | **C143** | **C143** | **E.1/61 AND E.1/15 AND E.1/39** | Yes | |
| | UCS2 display in Katakana | **R99** | **6.1** | | | **C145** | **C145** | **E.1/61 AND E.1/15 AND E.1/39** | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/61 AND E.1/177 AND E.1/178 | TBD | |
| **27** | **RUN AT COMMAND 27.22.4.23** | | | | | | | | | |
| | No alpha Identifier | R99 | 1.1 | C110 | C110 | C110 | C110 | E.1/62 | No | |
| | null data alpha identifier presented | R99 | 1.2 | C110 | C110 | C110 | C110 | E.1/62 | No | |
| | alpha identifier presented | R99 | 1.3 | C110 | C110 | C110 | C110 | E.1/62 | No | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Icons | R99 | 2.1, 2.2, 2.3, 2.4, 2.5 | C114 | C114 | C114 | C114 | E.1/62 | No | |
| | Text attribute – left alignment | Rel-5 | 3.1 | | | C110 AND C153 | C110 AND C153 | E.1/62 AND E.1/124 AND E.1/217 | No | |
| | **Text attribute – center alignment** | Rel-5 | 3.2 | | | C110 AND C154 | C110 AND C154 | E.1/62 AND E.1/124 AND E.1/218 | No | |
| | **Text attribute – right alignment** | Rel-5 | 3.3 | | | C110 AND C155 | C110 AND C155 | E.1/62 AND E.1/124 AND E.1/219 | No | |
| | **Text attribute – large font size** | Rel-5 | 3.4 | | | C110 AND C157 AND C156 | C110 AND C157 AND C156 | E.1/62 AND E.1/124 AND E.1/221 AND E.1/220 | No | |
| | **Text attribute – small font size** | Rel-5 | 3.5 | | | C110 AND C158 AND C156 | C110 AND C158 AND C156 | E.1/62 AND E.1/124 AND E.1/222 AND E.1/220 | No | |
| | **Text attribute – bold on** | Rel-5 | 3.6 | | | C110 AND C160 AND C159 | C110 AND C160 AND C159 | E.1/62 AND E.1/124 AND E.1/225 AND E.1/226 | No | |
| | **Text attribute – italic on** | Rel-5 | 3.7 | | | C110 AND C161 AND C159 | C110 AND C161 AND C159 | E.1/62 AND E.1/124 AND E.1/225 AND E.1/227 | No | |
| | Text attribute – underline on | Rel-5 | 3.8 | | | C110 AND C162 AND C159 | C110 AND C162 AND C159 | E.1/62 AND E.1/124 AND E.1/225 AND E.1/228 | No | |
| | Text attribute – strikethrough on | Rel-5 | 3.9 | | | C110 AND C163 AND C159 | C110 AND C163 AND C159 | E.1/62 AND E.1/124 AND E.1/225 AND E.1/229 | No | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – foreground and background colours | Rel-5 | 3.10 | | | C110 AND C164 AND C165 | C110 AND C164 AND C165 | E.1/62 AND E.1/124 AND E.1/230 AND E.1/231 | No | |
| | UCS2 Display in Cyrillic | **R99** | **4.1** | | | **C149** | **C149** | **E.1/62 AND E.1/15** | **No** | |
| | UCS2 display in Chinese | **R99** | **5.1** | | | **C150** | **C150** | **E.1/62 AND E.1/15** | **No** | |
| | UCS2 display in Katakana | **R99** | **6.1** | | | **C151** | **C151** | E.1/62 AND E.1/15 | No | |
| | Frames | Rel-6 | TBD | | | | | E.1/62 AND E.1/177 AND E.1/178 | TBD | |
| **28** | **SEND DTMF 27.22.4.24** | | | | | | | | | |
| | Normal | R99 | 1.1 | M | M | M | M | E.1/66 | Yes | |
| | alpha identifier | R99 | 1.2, 1.3 | M | M | M | M | E.1/66 | Yes | |
| | Mobile is not in a speech call | R99 | 1.4 | M | M | M | M | E.1/66 | Yes | |
| | Icons | R99 | 2.1, 2.2, 2.3 | C108 | C108 | C108 | C108 | E.1/66 | Yes | |
| | UCS2 display in Cyrillic | R99 | 3.1 | C118 | C118 | C118 | C118 | E.1/66 AND E.1/15 | Yes | |
| | Text attribute – left alignment | Rel-5 | 4.1 | | | C153 | C153 | E.1/66 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | **Rel-5** | **4.2** | | | C154 | C154 | E.1/66 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | **Rel-5** | **4.3** | | | C155 | C155 | E.1/66 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | **Rel-5** | **4.4** | | | C157 AND C156 | C157 AND C156 | E.1/66 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | **Rel-5** | **4.5** | | | C158 AND C156 | C158 AND C156 | E.1/66 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – bold on** | **Rel-5** | **4.6** | | | C160 AND C159 | C160 AND C159 | E.1/66 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | **Rel-5** | **4.7** | | | C161 AND C159 | C161 AND C159 | E.1/66 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 4.8 | | | C162 AND C159 | C162 AND C159 | E.1/66 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | Text attribute – strikethrough on | Rel-5 | 4.9 | | | C163 AND C159 | C163 AND C159 | E.1/66 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |
| | Text attribute – foreground and background colours | Rel-5 | 4.10 | | | C164 AND C165 | C164 AND C165 | E.1/66 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | UCS2 display in Chinese | **R99** | **5.1** | | | **C143** | **C143** | **E.1/66 AND E.1/15** | **Yes** | |
| | UCS2 display in Katakana | **R99** | **6.1** | | | **C145** | **C145** | E.1/66 AND E.1/15 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/66 AND E.1/177 AND E.1/178 | TBD | |
| **29** | **LANGUAGE NOTIFICATION 27.22.4.25** | | | | | | | | | |
| | Specific language notification | R99 | 1.1 | M | M | M | M | E.1/70 | No | |
| | Non specific language notification | R99 | 1.2 | M | M | M | M | E.1/70 | No | |
| **30** | **LAUNCH BROWSER 27.22.4.26** | | | | | | | | | |
| | No session already launched: Connect to the default URL | R99 | 1.1 | C111 | C111 | C111 | C111 | E.1/71 | Yes | |
| | connect to the specified URL, alpha identifier length=0 | R99 | 1.2 | C111 | C111 | C111 | C111 | E.1/71 | Yes | |
| | Browser identity, no alpha identifier | R99 | 1.3 | C111 | C111 | C111 | C111 | E.1/71 | Yes | |
| | one bearer specified and gateway/proxy identity | R99 | 1.4 | C122 | C122 | C122 | C122 | E.1/71 AND E.1/98 | Yes | |
| | void | R99 | 1.5 | Void | void | void | void | void | | |
| | Interaction with current session | R99 | 2.1, 2.2, 2.3 | C111 | C111 | C111 | C111 | E.1/71 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | UCS2 display in Cyrillic | R99 | 3.1 | **C111 AND 118** | **C111 AND 118** | **C111 AND 118** | C111 AND 118 | E.1/71 AND E.1/15 | Yes | |
| | Icons | R99 | 4.1, 4.2 | C115 | C115 | C115 | C115 | E.1/71 | Yes | |
| | Text attribute – left alignment | Rel-5 | 5.1 | | | C111 AND C153 | C111 AND C153 | E.1/71 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 5.2 | | | C111 AND C154 | C111 AND C154 | E.1/71 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | Rel-5 | 5.3 | | | C111 AND C155 | C111 AND C155 | E.1/71 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 5.4 | | | C111 AND C157 AND C156 | C111 AND C157 AND C156 | E.1/71 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 5.5 | | | C111 AND C158 AND C156 | C111 AND C158 AND C156 | E.1/71 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |
| | **Text attribute – bold on** | Rel-5 | 5.6 | | | C111 AND C160 AND C159 | C111 AND C160 AND C159 | E.1/71 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | Rel-5 | 5.7 | | | C111 AND C161 AND C159 | C111 AND C161 AND C159 | E.1/71 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 5.8 | | | C111 AND C162 AND C159 | C111 AND C162 AND C159 | E.1/71 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | **Text attribute – strikethrough on** | Rel-5 | 5.9 | | | C111 AND C163 AND C159 | C111 AND C163 AND C159 | E.1/71 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – foreground and background colours | Rel-5 | 5.10 | | | C111 AND C164 AND C165 | C111 AND C164 AND C165 | E.1/71 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | UCS2 display in Chinese | **R99** | **6.1** | | | **C111 AND C143** | **C111 AND C143** | **E.1/71 AND E.1/15** | **Yes** | |
| | UCS2 display in Katakana | **R99** | **7.1** | | | **C111 AND C145** | **C111 AND C145** | E.1/71 AND E.1/15 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/71 AND E.1/177 AND E.1/178 | TBD | |
| **31** | **OPEN CHANNEL 27.22.4.27** | | | | | | | | | |
| | void | R99 | void | Void | void | void | void | void | | |
| | immediate link establishment, GPRS, no local address, no alpha identifier, no network access name | R99 | 2.1 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/98 | Yes | |
| | immediate link establishment GPRS, no alpha identifier, with network access name | R99 | 2.2 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/98 | Yes | |
| | immediate link establishment, GPRS, with alpha identifier | R99 | 2.3 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/98 | Yes | |
| | immediate link establishment, GPRS, with null alpha identifier | R99 | 2.4 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/98 | Yes | |
| | immediate link establishment, GPRS, command performed with modifications (buffer size) | R99 | 2.5 | C152 | C152 | C152 | C152 | E.1/89 AND E.1/98 | Yes | |
| | immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command | R99 | 2.7 | C169 | C169 | C169 | C169 | E.1/89 AND E.1/98 | Yes | |
| | void | void | 2.8 | Void | void | void | void | void | | |
| | Default bearer | R99 | TBD | | | | | E.1/89 AND E.1/98 AND C132 | TBD | |
| | Local Bearer | Rel-4 | TBD | | | | | E.1/89 AND E.1/98 AND C132 | TBD | |
| | Text attribute – center alignment | Rel-5 | 5.1 | | | C121 AND C153 | C121 AND C153 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 5.2 | | | C121 AND C154 | C121 AND C154 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/218 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – right alignment** | Rel-5 | 5.3 | | | C121 AND C155 | C121 AND C155 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 5.4 | | | C121 AND C157 AND C156 | C121 AND C157 AND C156 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 5.5 | | | C121 AND C158 AND C156 | C121 AND C158 AND C156 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |
| | **Text attribute – bold on** | Rel-5 | 5.6 | | | C121 AND C160 AND C159 | C121 AND C160 AND C159 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | Rel-5 | 5.7 | | | C121 AND C161 AND C159 | C121 AND C161 AND C159 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 5.8 | | | C121 AND C162 AND C159 | C121 AND C162 AND C159 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | Text attribute – strikethrough on | Rel-5 | 5.9 | | | C121 AND C163 AND C159 | C121 AND C163 AND C159 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – foreground and background colours | Rel-5 | 5.10 | | | C121 AND C164 AND C165 | C121 AND C164 AND C165 | E.1/89 AND E.1/98 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/89 AND E.1/98 AND E.1/177 AND E.1/178 | TBD | |
| **32** | **CLOSE CHANNEL 27.22.4.28** | | | | | | | | | |
| | successful | R99 | 1.1 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/90 | Yes | |
| | with an invalid channel identifier | R99 | 1.2 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/90 | Yes | |
| | on an already closed channel | R99 | 1.3 | C121 | C121 | C121 | C121 | E.1/90 | Yes | |
| | Text attribute – left alignment | Rel-5 | 2.1 | | | C121 AND C153 | C121 AND C153 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 2.2 | | | C121 AND C154 | C121 AND C154 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | Rel-5 | 2.3 | | | C121 AND C155 | C121 AND C155 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 2.4 | | | C121 AND C157 AND C156 | C121 AND C157 AND C156 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 2.5 | | | C121 AND C158 AND C156 | C121 AND C158 AND C156 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – bold on** | Rel-5 | 2.6 | | | C121 AND C160 AND C159 | C121 AND C160 AND C159 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | Rel-5 | 2.7 | | | C121 AND C161 AND C159 | C121 AND C161 AND C159 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | Text attribute – underline on | Rel-5 | 2.8 | | | C121 AND C162 AND C159 | C121 AND C162 AND C159 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | Text attribute – strikethrough on | Rel-5 | 2.9 | | | C121 AND C163 AND C159 | C121 AND C163 AND C159 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |
| | Text attribute – foreground and background colours | Rel-5 | 2.10 | | | C121 AND C164 AND C165 | C121 AND C164 AND C165 | E.1/89 AND E.1/90 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/89 AND E.1/98 AND E.1/177 AND E.1/178 | TBD | |
| **33** | **RECEIVE DATA 27.22.4.29** | | | | | | | | | |
| | already opened channel | R99 | 1.1 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/91 AND E.1/92 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute – center alignment | Rel-5 | 2.1 | | | C121 AND C153 | C121 AND C153 | E.1/89 AND E.1/91 AND E.1/92 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | **Rel-5** | **2.2** | | | C121 AND C154 | C121 AND C154 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/218 | Yes | |
| | **Text attribute – right alignment** | **Rel-5** | **2.3** | | | C121 AND C155 | C121 AND C155 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | **Rel-5** | **2.4** | | | C121 AND C157 AND C156 | C121 AND C157 AND C156 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | **Rel-5** | **2.5** | | | C121 AND C158 AND C156 | C121 AND C158 AND C156 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |
| | **Text attribute – bold on** | **Rel-5** | **2.6** | | | C121 AND C160 AND C159 | C121 AND C160 AND C159 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | **Rel-5** | **2.7** | | | C121 AND C161 AND C159 | C121 AND C161 AND C159 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – underline on** | **Rel-5** | **2.8** | | | C121 AND C162 AND C159 | C121 AND C162 AND C159 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | **Text attribute – strikethrough on** | **Rel-5** | **2.9** | | | C121 AND C163 AND C159 | C121 AND C163 AND C159 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |
| | Text attribute– foreground and background colours | Rel-5 | 2.10 | | | C121 AND C164 AND C165 | C121 AND C164 AND C165 | E.1/89 AND E.1/91 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/89 AND E.1/91 AND E.1/177 AND E.1/178 | TBD | |
| **34** | **SEND DATA 27.22.4.30** | | | | | | | | | |
| | immediate mode | R99 | 1.1 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/92 | Yes | |
| | Store mode | R99 | 1.2 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/92 | Yes | |
| | Store mode, Tx buffer fully used | R99 | 1.3 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/92 | Yes | |
| | 2 consecutive SEND DATA Store mode | R99 | 1.4 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/92 | Yes | |
| | immediate mode with a bad channel identifier | R99 | 1.5 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/92 | Yes | |
| | void | | | | | | | | Yes | |
| | Text attribute– left alignment | Rel-5 | 2.1 | | | C121 AND C153 | C121 AND C153 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/217 | Yes | |
| | **Text attribute – center alignment** | Rel-5 | 2.2 | | | C121 AND C154 | C121 AND C154 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/218 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | **Text attribute – right alignment** | Rel-5 | 2.3 | | | C121 AND C155 | C121 AND C155 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/219 | Yes | |
| | **Text attribute – large font size** | Rel-5 | 2.4 | | | C121 AND C157 AND C156 | C121 AND C157 AND C156 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/221 AND E.1/220 | Yes | |
| | **Text attribute – small font size** | Rel-5 | 2.5 | | | C121 AND C158 AND C156 | C121 AND C158 AND C156 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/222 AND E.1/220 | Yes | |
| | **Text attribute – bold on** | Rel-5 | 2.6 | | | C121 AND C160 AND C159 | C121 AND C160 AND C159 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/226 | Yes | |
| | **Text attribute – italic on** | Rel-5 | 2.7 | | | C121 AND C161 AND C159 | C121 AND C161 AND C159 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/227 | Yes | |
| | **Text attribute – underline on** | Rel-5 | 2.8 | | | C121 AND C162 AND C159 | C121 AND C162 AND C159 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/228 | Yes | |
| | **Text attribute – strikethrough on** | Rel-5 | 2.9 | | | C121 AND C163 AND C159 | C121 AND C163 AND C159 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/225 AND E.1/229 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Text attribute– foreground and background colours | Rel-5 | 2.10 | | | C121 AND C164 AND C165 | C121 AND C164 AND C165 | E.1/89 AND E.1/92 AND E.1/124 AND E.1/230 AND E.1/231 | Yes | |
| | Frames | Rel-6 | TBD | | | | | E.1/89 AND E.1/92 AND E.1/177 AND E.1/178 | TBD | |
| **35** | **GET CHANNEL STATUS 27.22.4.31** | | | | | | | | | |
| | without any BIP channel opened | R99 | 1.1 | C121 | C121 | C121 | C121 | E.1/93 | Yes | |
| | with a BIP channel currently opened | R99 | 1.2 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/93 | Yes | |
| | after a link dropped | R99 | 1.3 | C121 | C121 | C121 | C121 | E.1/89 AND E.1/93 | Yes | |
| **36** | **DATA DOWNLOAD TO UICC 27.22.5** | | | | | | | | | |
| **37** | **SMS-PP DATA DOWNLOAD 27.22.5.1** | | | | | | | | | |
| | void | | 1.1 | | | | | | | |
| | UICC responds with '61 XX' | R99 | 1.2 | M | M | M | M | E.1/2 | Yes | |
| | More time | R99 | 1.3 | M | M | M | M | E.1/2 | Yes | |
| | void | | 1.4 | | | | | | | |
| | Data coding / message class | R99 | 1.6 | M | M | M | M | E.1/2 | Yes | |
| | RP-ERROR Handling | R99 | 1.7 | | | | M | E 1/2 | Yes | |
| | General Data Coding UDH | R99 | 1.8 | M | M | M | M | E 1/2 | Yes | |
| **38** | **CELL BROADCAST DATA DOWNLOAD 27.22.5.2** | | | | | | | | | |
| | Cell Broadcast(GSM) - ME does not display message | R99 | 1.1 | M | M | M | M | E.1/3 | System Simulator only | |
| | void | | 1.2 | | | | | | | |
| | Cell Broadcast(GSM) - ME displays message | R99 | 1.3 | M | M | M | M | E.1/3 | System Simulator only | |
| | Cell Broadcast (UTRAN) - ME does not display message | Rel-5 | 1.4 | | | | | E.1/3 | UMTS System Simulator only | |
| | Cell Broadcast (UTRAN) -More time | Rel-5 | 1.5 | | | | | E.1/3 AND E.1/20 | UMTS System Simulator only | |
| | Cell Broadcast(UTRAN) - ME displays message | Rel-5 | 1.6 | | | | | E.1/3 | UMTS System Simulator only | |
| | Cell Broadcast(GSM) - More time (UDH) | R99 | 1.7 | M | M | M | M | E.1/3 AND E.1/20 | System Simulator only | |
| **39** | **CALL CONTROL BY USIM 27.22.6** | | | | | | | | | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | Procedure for MO calls (Cell identity in envelope call control) | R99 | 1.1, 1.2, 1.4, 1.6, 1.8 to 1.14 | M | M | M | M | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64 | Yes | |
| | Procedure for MO calls (Cell identity in envelope call control) | R99 | 1.3 A, 1.5 A, 1.7 A | C140 | C140 | C140 | C140 | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64 | Yes | |
| | Procedure for MO calls (Cell identity in envelope call control) | R99 | 1.3 B, 1.5 B, 1.7 B | C141 | C141 | C141 | C141 | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/29 AND E.1/64 | Yes | |
| | Procedure for SS (Cell identity in envelope call control) | R99 | 2.1, 2.2, 2.3, 2.4 | M | M | M | M | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 | Yes | |
| | Interaction with FDN (Cell identity in envelope call control) | R99 | 3.1, 3.2, 3.3, 3.4, 3.5 | C146 | C146 | C146 | C146 | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 | Yes | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | BDN service enabled | R99 | 4.1 | C147 | C147 | C147 | C147 | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 | Yes | |
| | BDN service enabled, interaction with emergency call codes, R99 only | R99 | 4.2A | C147 | | | | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 | Yes | |
| | BDN service enabled, interaction with emergency call codes, Rel-4+ | Rel-4 | 4.2B | | C147 | C147 | C147 | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 ND E.1/64 | Yes | |
| | FDN and BDN enabled, set up a call in EFFDN, Allowed with modifications | R99 | 4.3 | C146 AND C147 | C146 AND C147 | C146 AND C147 | C146 AND C147 | E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 AND E.1/64 | Yes | |
| | Call control on GPRS | Rel-5 | TBD | | | | | E.1/98 AND E.1/7 AND E.1/8 AND E.1/10 AND E.1/11 AND E.1/13 | TBD | |
| | BDN service enabled, ME not supporting BDN | R99 | 5.1 | | | C147 | C147 | N/A | Yes | |
| 40 | **EVENT DOWNLOAD 27.22.7** | | | | | | | | | |
| | 27.22.7.1: MT call event | R99 | 1.1 | M | M | M | M | E.1/34 AND E.1/33 | Yes | |
| | 27.22.7.2.1: call connected event | R99 | 1.1 | M | M | M | M | E.1/35 AND E.1/33 | Yes | |

| Item | Description | Re-lease | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | 27.22.7.2.2: ME supporting SET UP CALL | R99 | 2.1 | M | M | M | M | E.1/35 AND E.1/29 AND E.1/33 | Yes | |
| | 27.22.7.3: call disconnected event | R99 | 1.1 | M | M | M | M | E.1/36 AND E.1/33 | Yes | |
| | 27.22.7.4: location status event | R99 | 1.1 | M | M | M | M | E.1/37 AND E.1/33 | Yes | |
| | 27.22.7.5: user activity event | R99 | 1.1 | M | M | M | M | E.1/38 AND E.1/33 | No | |
| | 27.22.7.6: idle screen available event | R99 | 1.1 | M | M | M | M | E.1/39 AND E.1/33 | Yes | |
| | 27.22.7.7.1: Card reader status normal | R99 | 1.1 | C109 | C109 | C109 | C109 | E.1/40 AND E.1/33 | No | |
| | 27.22.7.7.2: Detachable card reader | R99 | 2.1 | C116 | C116 | C116 | C116 | E.1/40 AND E.1/33 | No | |
| | 27.22.7.8: language selection event | R99 | 1.1 | M | M | M | M | E.1/41 AND E.1/33 | No | |
| | 27.22.7.9: Browser termination event | R99 | 1.1 | C111 | C111 | C111 | C111 | E.1/42 AND E.1/33 | Yes | |
| | 27.22.7.10: Data available event | R99 | 1.1 | C121 | C121 | C121 | C121 | E.1/43 AND E.1/89 AND E.1/92 AND E.1/33 | Yes | |
| | 27.22.7.11: Channel status event | R99 | 1.1 | C121 | C121 | C121 | C121 | E.1/44 AND E.1/89 AND E.1/33 | Yes | |
| | 27.22.7.12: Access Technology change event | Rel-4 | TBD | | | | | E.1/45 AND E.1/33 | TBD | |
| | 27.22.7.13: Display parameter changed event | Rel-4 | TBD | | | | | E.1/46 AND E.1/33 | TBD | |
| | 27.22.7.14: Local connection event | Rel-4 | TBD | | | | | E.1/47 AND E.1/33 | TBD | |
| | 27.22.7.15: Network search mode change event | Rel-6 | TBD | | | | | E.1/48 AND E.1/33 | TBD | |
| | 27.22.7.16: Browsing status event | Rel-6 | TBD | | | | | E.1/193 AND E.1/33 | TBD | |
| | Frame information changed event | Rel-6 | TBD | | | | | E.1/195 AND E.1/177 AND E.1/178 | TBD | |
| **41** | **MO SMS Control by USIM** | | | | | | | | | |
| | With proactive command, Allowed , no modification | R99 | 1.1 | M | M | M | M | E1/12 AND E.1/26 | Yes | |

| Item | Description | Re-leas e | Test sequence (s) | Rel 99 ME | Rel-4 ME | Rel-5 ME | Rel-6 ME | Terminal Profile | Network Dependency | Sup-port |
|---|---|---|---|---|---|---|---|---|---|---|
| | With user SMS, Allowed , no modification | R99 | 1.2 | M | M | M | M | E1/12 | Yes | |
| | With proactive command, Not allowed | R99 | 1.3 | M | M | M | M | E1/12 AND E.1/26 | Yes | |
| | With user SMS, Not allowed | R99 | 1.4 | M | M | M | M | E1/12 | Yes | |
| | With proactive command, Allowed, with modifications | R99 | 1.5 | M | M | M | M | E1/12 AND E.1/26 | Yes | |
| | With user SMS, Allowed, with modifications | R99 | 1.6 | M | M | M | M | E1/12 | Yes | |
| | With Proactive command, the USIM responds with '90 00', Allowed, no modification | R99 | 1.7 | M | M | M | M | E1/12 AND E.1/26 | Yes | |
| | Send Short Message attempt by user, the USIM responds with '90 00', Allowed, no modification | R99 | 1.8 | M | M | M | M | E1/12 | Yes | |
| | Void | | 1.9 | | | | | | | |
| **42** | SERVICE SEARCH | Rel-4 | TBD | | | | | E.1/94 | TBD | |
| **43** | GET SERVICE INFORMATION | Rel-4 | TBD | | | | | E.1/95 | TBD | |
| **44** | DECLARE SERVICE | Rel-4 | TBD | | | | | E.1/96 | TBD | |
| **45** | RETRIEVE MULTIMEDIA MESSAGE | Rel-6 | TBD | | | | | E.1/173 | TBD | |
| **46** | SUBMIT MULTIMEDIA MESSAGE | Rel-6 | TBD | | | | | E.1/173 | TBD | |
| **47** | DISPLAY MULTIMEDIA MESSAGE | Rel-6 | TBD | | | | | E.1/173 | TBD | |
| **48** | SET FRAMES | Rel-6 | TBD | | | | | E.1/177 AND E.1/178 | TBD | |
| **49** | GET FRAME STATUS | Rel-6 | TBD | | | | | E.1/178 AND E.1/177 | TBD | |
| **50** | Handling of command number | | | | | | | | | |
| | DISPLAY TEXT normal priority | R99 | 1.1 | M | M | M | M | E.1/17 | No | |

| | | |
|---|---|---|
| C101 | IF A.1/1 THEN M ELSE N/A | -- O_Cap_Conf |
| C102 | IF A.1/16 THEN M ELSE N/A | -- O_GPRS |
| C103 | void | |
| C104 | IF A.1/2 THEN M ELSE N/A | -- O_Sust_text |
| C105 | IF A.1/3 AND A.1/41 THEN M ELSE N/A | -- O_Ucs2_Entry AND O_UCS2_Cyrillic |
| C106 | IF A.1/4 THEN M ELSE N/A | -- O_Ext_Str |
| C107 | IF A.1/5 THEN M ELSE N/A | -- O_Help |
| C108 | IF A.1/6 THEN (O.1 OR O.2) ELSE N/A | -- O_Icons |
| C109 | IF A.1/7 THEN M ELSE N/A | -- O_Dual_Slot |
| C110 | IF A.1/9 AND A.1/46 THEN M ELSE N/A | -- O_Run_At AND O_+CIMI |
| C111 | IF A.1/10 THEN M ELSE N/A | -- O_LB |
| C112 | IF A.1/11 THEN M ELSE N/A | -- O_Soft_key |
| C113 | void | |
| C114 | IF C110 AND C108 THEN M ELSE N/A | -- O_Run_At AND O_+CIMI AND O_Icons |
| C115 | IF C111 AND C108 THEN M ELSE N/A | -- O_LB AND O_Icons |
| C116 | IF A.1/7 AND A.1/8 THEN M ELSE N/A | -- O_Dual_Slot AND O_Detach_Rdr |
| C117 | void | |
| C118 | IF A.1/15 AND A.1/41 THEN M ELSE N/A | -- O_Ucs2_Disp AND O_UCS2_Cyrillic |
| C119 | IF A.1/19 THEN M ELSE N/A | -- O_Redial |
| C120 | IF A.1/20 THEN M ELSE N/A | -- O_D_NoResp |
| C121 | IF A.1/21 AND A.1/17 THEN M ELSE N/A | -- O_BIP_GPRS AND O_UDP |
| C122 | IF C111 AND A.1/16 THEN M ELSE N/A | -- O_LB AND O_GPRS |
| C123 | void | |
| C124 | IF A.1/22, test x.A M ELSE x.B M (where x is the expected sequence number value) | -- O_CP_Subaddr |
| C125 | IF A.1/23 THEN M ELSE N/A | -- O_Imm_Resp |
| C126 | IF A.1/24 THEN M ELSE N/A | -- O_Duration |
| C127 | void | |

| | | |
|---|---|---|
| C128 | void | |
| C129 | void | |
| C130 | void | |
| C131 | void | |
| C132 | IF A.1/27 THEN M ELSE N/A | -- O_BIP_Local |
| C133 | IF A.1/37 THEN M ELSE N/A | -- O_Frames |
| C134 | IF A.1/38 THEN M ELSE N/A | -- O_MMS |
| C135 | IF C110 AND C133 THEN M ELSE N/A | -- O_Run_At AND O_Frames |
| C136 | IF C111 AND C133 THEN M ELSE N/A | -- O_LB AND O_Frames |
| C137 | IF A.1/12 AND C133 THEN M ELSE N/A | -- O_BIP AND O_Frames |
| C138 | IF A.1/39 THEN M ELSE N/A | -- O_Tones |
| C139 | IF A.1/35 THEN M ELSE N/A | -- O_Batt |
| C140 | IF A.1/39 THEN M ELSE N/A | -- O_UC_Before_EnvCC |
| C141 | IF A.1/40 THEN M ELSE N/A | -- O_UC_After_EnvCC |
| C142 | IF A.1/3 AND A.1/42 THEN M ELSE N/A | -- O_UCS2_Entry AND O_UCS2_Chinese |
| C143 | IF A.1/15 AND A.1/42 THEN M ELSE N/A | -- O_UCS2_Disp AND O_UCS2_Chinese |
| C144 | IF A.1/3 AND A.1/43 THEN M ELSE N/A | -- O_UCS2_Entry AND O_UCS2_Katakana |
| C145 | IF A.1/15 AND A.1/43 THEN M ELSE N/A | -- O_UCS2_Disp AND O_UCS2_Katakana |
| C146 | IF A. 1/45 THEN M ELSE N/A | -- O_FDN |
| C147 | IF A. 1/44 THEN M ELSE N/A | -- O_BDN |
| C148 | IF (A.1/9 AND A.1/47) THEN M ELSE N/A | -- O_Run_At AND O_+CGMI |
| C149 | IF C148 AND C118 THEN M ELSE N/A | -- O_Run_At AND O_+CGMI AND O_ O_Ucs2_Disp AND O_Ucs2_ Cyrillic |
| C150 | IF C148 AND C143 THEN M ELSE N/A | -- O_Run_At AND O_+CGMI AND O_ O_Ucs2_Disp AND O_Ucs2_ Chinese |
| C151 | IF C148 AND C145 THEN M ELSE N/A | -- O_Run_At AND O_+CGMI AND O_ O_Ucs2_Disp AND O_Ucs2_ Katakana |
| C152 | IF C121 AND A.1/49 THEN M ELSE N/A | -- O_BIP_GPRS AND O_UDP AND O_BUFFER_SIZE |
| C153 | IF A.1/50 THEN M ELSE N/A | -- O_TAT_AL |
| C154 | IF A.1/51 THEN M ELSE N/A | -- O_TAT_AC |
| C155 | IF A.1/52 THEN M ELSE N/A | -- O_TAT_AR |
| C156 | IF A.1/53 THEN M ELSE N/A | -- O_TAT_FSN |
| C157 | IF A.1/54 THEN M ELSE N/A | -- O_TAT_FSL |
| C158 | IF A.1/55 THEN M ELSE N/A | -- O_TAT_FSS |
| C159 | IF A.1/56 THEN M ELSE N/A | -- O_TAT_SN |
| C160 | IF A.1/57 THEN M ELSE N/A | -- O_TAT_SB |
| C161 | IF A.1/58 THEN M ELSE N/A | -- O_TAT_SI |
| C162 | IF A.1/59 THEN M ELSE N/A | -- O_TAT_SU |
| C163 | IF A.1/60 THEN M ELSE N/A | -- O_TAT_SS |
| C164 | IF A.1/61 THEN M ELSE N/A | -- O_TAT_STFC |
| C165 | IF A.1/62 THEN M ELSE N/A | -- O_TAT_STBC |
| C166 | IF A.1/63 THEN test step option n.A M ELSE test step option n.B M | -- O_longFTN |
| C167 | IF A.1/64 THEN M ELSE N/A | -- O_GERAN |
| C168 | IF A.1/65 THEN M ELSE N/A | -- O_Global_PB |
| C169 | IF (C121 AND A.1/68 THEN test x.A M ELSE IF (C121 AND NOT A.1/68) test x.B M | -- (O_BIP_GPRS AND O_UDP AND O_User_Confirm_Before_PDP_Context_Request) OR (O_BIP_GPRS AND O_UDP AND NOT O_User_Confirm_Before_PDP_Context_Request) |
| O.1 | IF (the ME supports icons as defined in record 1 of EF(IMG), tests x.1A M ELSE tests x.1B M (where x is the expected sequence number value) | |
| O.2 | IF the ME supports icons as defined in record 2 of EF(IMG), tests x.2A M ELSE x.2B M (where x is the expected sequence number value) | |
| O.3 | void | |

## 3.5 Conventions for mathematical notations

The conventions for mathematical notations specified below shall apply.

### 3.5.1 Mathematical signs

The "plus or minus" sign is expressed by "±".

The sign "multiplied by" is expressed by "*".

The sign "divided by" is expressed by "/", or the common division bar.

The sign "greater than or equal to" is expressed by "≥".

The sign "less than or equal to" is expressed by "≤".

# 4 Test equipment

The test equipment is specified in TS 34.108 [12] clause 4.

# 5 Testing methodology in general

When possible the present document refers to ETSI TS 102 384 [26] to describe generic aspects of application toolkit tests.

## 5.1 Testing of optional functions and procedures

Any function or procedure which is optional, as indicated in the present document, may be subject to a conformance test if it is implemented in the ME.

## 5.2 Test interfaces and facilities

The UICC, and (U)SS interfaces provides the main test interfaces for the purpose of performing conformance tests.

The tests which require a network simulator shall be carried out with using a Universal System Simulator when accessing a UTRAN, and if theses tests have to be peformed additionally when accessing a GERAN a System Simulator shall be used instead.

## 5.3 Information to be provided by the apparatus supplier

The information to be provided by the apparatus supplier specified in both TS 34.108 [12] and TS 51.010-1 [23] shall apply, unless otherwise specified in the present clause.

In addition, the apparatus supplier shall provide the information with respect to the Supported Option table A.1 and to ME"s default configuration table A.2.

**Table A.2: ME"s default configuration**

| Item | Description | Value | Status |
|---|---|---|---|
| 1 | DISPLAY TEXT: No Response from user timeout interval | | C |
| 2 | GET INKEY: No response from user Timeout interval | | C |
| 3 | GET INPUT: No response from user Timeout interval | | C |
| 4 | SELECT ITEM: No response from user Timeout interval | | C |
| 5 | DISPLAY TEXT Text Attributes Alignment [Left or Center or Right] | | C |
| 6 | GET INKEY Text Attributes Alignment [Left or Center or Right] | | C |
| 7 | GET IMPUT Text Attributes Alignment [Left or Center or Right] | | C |
| 8 | PLAY TONE Text Attributes Alignment [Left or Center or Right] | | C |
| 9 | SET UP MENU Text Attributes Alignment [Left or Center or Right] | | C |
| 10 | SELECT ITEM Text Attributes Alignment [Left or Center or Right] | | C |
| 11 | SEND SHORT MESSAGE Text Attributes Alignment [Left or Center or Right] | | C |
| 12 | SEND SS Text Attributes Alignment [Left or Center or Right] | | C |
| 13 | SEND USSD Text Attributes Alignment [Left or Center or Right] | | C |
| 14 | SET UP CALL Text Attributes Alignment [Left or Center or Right] | | C |
| 15 | SET UP IDLE MODE TEXT Text Attributes Alignment [Left or Center or Right] | | C |
| 16 | RUN AT Text Attributes Alignment [Left or Center or Right] | | C |
| 17 | SEND DTMF Text Attributes Alignment [Left or Center or Right] | | C |
| 18 | LAUNCH BROWSER Text Attributes Alignment [Left or Center or Right] | | C |
| 19 | OPEN CHANNEL Text Attributes Alignment [Left or Center or Right] | | C |
| 20 | CLOSE CHANNEL Text Attributes Alignment [Left or Center or Right] | | C |
| 21 | RECEIVE DATA Text Attributes Alignment [Left or Center or Right] | | C |
| 22 | SEND DATA Text Attributes Alignment [Left or Center or Right] | | C |
| 23 | IMEI | | M |
| 24 | IMEISV | | C |
| 25 | [Reserved] | | |
| 26 | Additional Card Reader Id | | C |
| 27 | Channel Id | | C |
| 28 | Manufacturer identification as implemented according to TS 27.007, cl. 5.1 | | C |
| 29 | Preferred buffer size supported by the terminal for Open Channel command | | C |
| NOTE : Conditional values shall be provided if the corresponding option is supported in the table A.1 | | | |

# 6 Implicit testing

For some 3GPP features conformance is not verified explicitly in the present document. This does not imply that correct functioning of these features is not essential, but that these are implicitly tested to a sufficient degree in other tests.

It should be noted that for these features some aspects have to be and are explicitly tested, e.g. the ability to switch between 1.8v and 3v operation.

Some UICC features will be explicitly tested as result of other tests. These should be identified for the following reason:

- To identify the areas of overlap and thus provide a more efficient testing.

# 7 Measurement uncertainty

The measured value relating to the corresponding limit shall be used to determine whether or not a terminal equipment meets the requirement. (ETR 028, annex B).

This process is often referred to as "shared risk".

# 8 Format of tests

In general the following basic format for tests is used:

**27.22.X.X. Tested command**

#### 27.22.X.X.1 Command tested in «environment #1" (NORMAL, ICONS, UCS2 …)

##### 27.22.X.X.1.1 Definition and applicability

This clause refers back to clause 3.2.2.

##### 27.22.X.X.1.2 Conformance requirement

Only if required, this clause details the necessary core specification references.

##### 27.22.X.X.1.3 Test purpose

This clause details the purpose of the test.

##### 27.22.X.X.1.4 Method of test

###### 27.22.X.X.1.4.1 Initial conditions

If present this clause defines the initial conditions to be established before running each test sequence.

###### 27.22.X.X.1.4.2 Procedure

This clause details the test procedure. Each test sequence shall be carried out independently unless otherwise stated.

- Sequence 1.1 (further initial conditions, added here)

| |
|---|
| Command 1.1.1 |
| TERMINAL RESPONSE1.1.1A or 1.1.1B |
| Command 1.1.2 |
| TERMINAL RESPONSE1.1.2 |

PROACTIVE COMMAND 1.1.1

TERMINAL RESPONSE 1.1.1A

TERMINAL RESPONSE 1.1.1B

PROACTIVE COMMAND 1.1.2

TERMINAL RESPONSE 1.1.2

- Sequence 1.2

| |
|---|
| Command 1.2.1 |
| TERMINAL RESPONSE 1.2.1 |
| Command 1.2.2 |
| TERMINAL RESPONSE1.2.2 (same as TERMINAL RESPONSE 1.2.1) |
| Command 1.2.3 |
| TERMINAL RESPONSE 1.2.3 |

PROACTIVE COMMAND 1.2.1

PROACTIVE COMMAND 1.2.2

PROACTIVE COMMAND 1.2.3

TERMINAL RESPONSE 1.2.1

TERMINAL RESPONSE 1.2.2

TERMINAL RESPONSE 1.2.3

- Sequence 1.3

| Command 1.3.1 |
|---|
| TERMINAL RESPONSE1.3.1 |

PROACTIVE COMMAND 1.3.1

TERMINAL RESPONSE 1.3.1

**27.22.X.X.1.5 Test requirement**

This clause details the conditions to be met for successful completion of the test.

**27.22.X.X.2 Command tested in "environment #2" (NORMAL, ICONS, UCS2 …)**

**27.22.X.X. 2.1 Definition and applicability**

**27.22.X.X. 2.2 Conformance requirement**

**27.22.X.X. 2.3 Test purpose**

**27.22.X.X. 2.4 Method of test**

**27.22.X.X. 2.4.1.1 Initial conditions**

**27.22.X.X. 2.4.1.2 Procedure**

- Sequence 2.1

| Command 2.1.1 |
|---|
| TERMINAL RESPONSE2.1.1A or 2.1.1B |
| Command 2.1.2 |
| TERMINAL RESPONSE2.1.2 |

PROACTIVE COMMAND 2.1.1

TERMINAL RESPONSE 2.1.1A

TERMINAL RESPONSE 2.1.1B

PROACTIVE COMMAND 2.1.2

TERMINAL RESPONSE 2.1.2

- Sequence 2.2

| Command 2.2.1 |
|---|

| |
|---|
| TERMINAL RESPONSE 2.2.1 |
| Command 2.2.2 |
| TERMINAL RESPONSE 2.2.2 (same as TERMINAL RESPONSE 2.2.1) |
| Command 2.2.3 |
| TERMINAL RESPONSE 2.2.3 |

PROACTIVE COMMAND 2.2.1

PROACTIVE COMMAND 2.2.2

PROACTIVE COMMAND 2.2.3

Coding TERMINAL RESPONSE 2.2.1

Coding TERMINAL RESPONSE 2.2.2

Coding TERMINAL RESPONSE 2.2.3

**27.22.X.X.2.5 Test requirement**

# 9 Generic call set up procedures

The generic call set up procedure for PS and CS calls specified for GERAN and UTRAN shall apply.

For a ME accessing UTRAN the call set up procedures specified in TS 34.108 [12] subclause 7.2.3.1.3 and 7.2.3.2.3 shall apply, for session setup the ones defined in 7.2.4.1.3 and 7.2.4.2.3, unless otherwise specified in the present clause.

For a ME accessing GERAN the call set up procedures specified in TS 51.010-1 [23] subclause 26.9 shall apply, for session setup the ones defined in 45.2 and 45.4, unless otherwise specified in the present clause.

# 10 - 26 Not used

# 27 Testing of the UICC/ME interface

This clause is an addition to TS 31.121 [21] to confirm the correct interpretation of the USIM Application Toolkit commands and the correct operation of the Toolkit facilities.

The definitions, declarations and default values specified in TS 31.121 [21] clause 4.1 shall apply, unless otherwise specified in the present clause.

A USIM Simulator with the appropriate USIM Application Toolkit functionality will be required. The USIM data defined below shall be used for all test cases unless otherwise specified within the test case.

The comprehension required flags in SIMPLE-TLV objects that are included in a TERMINAL RESPONSE or an ENVELOPE shall be set as described in TS 31.111 [15]. This means that in cases where it is up to the ME to decide if this flag is used or not, the corresponding Tag coding in the TERMINAL RESPONSEs and ENVELOPEs in this document represents only one of the two valid possibilities.

TS 31.111 [15] defines that in case of the general result "Command performed successfully" some proactive commands require additional information in the command result and in which cases this is mandatory or optional. Thus when

additional information bytes are optional in the Result TLV, the additional information bytes of the Result TLVin the Terminal Responses shall be ignored.

# 27.1 - 27.21 Void

# 27.22 USIM Application Toolkit

## 27.22.1A General Test purpose

Testing of functional conformance to USIM Application Toolkit commands, including proactive UICC commands.

All facilities given by the TERMINAL PROFILE as supported, for which tests exist in the present document, shall be tested.

Many of the proactive UICC commands include an alpha identifier data object. This is intended to be a short one or two word identifier for the ME to optionally display on the screen along with any other indications, at the same time as the ME performs the UICC command.

NOTE: The sequence of USIM Application Toolkit commands are specific to the Toolkit Application being executed within the UICC, hence sequential testing of commands is not possible. The testing will therefore have to be performed on a command by command basis.

## 27.22.2A Definition of default values for USIM Application Toolkit testing

A UICC containing the following default values is used for all tests of this clause unless otherwise stated.

For each item, the logical default values and the coding within the Elementary Files (EF) of the USIM follow, as defined in:

- TS 31.121 [21], clause 4.1.
- ETSI TS 102 384 [26], clause 27.22.1B.

NOTE 1: Bx represents byte x of the coding.

NOTE 2: Unless otherwise defined, the coding values in binary.

**$EF_{UST}$ (USIM Service Table)**

Logically:

(Service 01) Local Phone Book available
(Service 02) Fixed dialling numbers available
(Service 06) Barred dialling numbers available
(Service 10) Short Message Storage available
(Service 11) Short Message Status Reports available
(Service 12) Short Message Service Parameters available
(Service 15) Cell Broadcast Message Identifier available
(Services 17, 18) The Group Identifier level 1 and level 2 not available
(Service 20) User controlled PLMN selector available
(Service 22) Image (IMG) available
(Service 27) The GSM Access available
(Service 28) Data download via SMS-PP available
(Service 29) Data download via SMS-CB available
(Service 30) Call Control by USIM not available
(Service 31) MO-SMS Control by USIM not available
(Service 32) RUN AT COMMAND available
(Service 33) (Packed Switched Domain) shall be set to '1'
(Service 34) Enabled Services Table available

| Coding: | B1 | B2 | B3 | B4 | B5 |
|---|---|---|---|---|---|
| binary | xx1x xx11 | x1xx 111x | xx1x 1x00 | 1001 11xx | xxx xx11 |

The coding of $EF_{UST}$ shall conform with the capabilities of the USIM used.

**$EF_{EST}$ (Enabled Services Table)**

Logically:

(Service 1) Fixed Dialling number deactivated
(Service 2) Barred Dialling number deactivated
(Service 3) APN Control List deactivated

| Coding: | B1 |
|---|---|
| binary | 00 |

**$EF_{IMSI}$ (International Mobile Subscriber Identity)**

Logically:

Length: 8 bytes
IMSI: 001 01 0123456789

| Coding: | '08 09 10 10 10 32 54 76 98' |
|---|---|

**$EF_{AD}$ (Administrative Data)**

Logically: Type approval operations
OFM to be deactivated by the Terminal
MNC: 2 digit

| Coding: | B1 | B2 | B3 | B4 |
|---|---|---|---|---|
| Hex | 80 | 00 | 00 | 02 |

**$EF_{LOCI}$ (Location Information)**

Logically:

LAI-MCC: 001
LAI-MNC: 01
LAI-LAC: 0001
TMSI: "FF .. FF"

| Coding: | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | FF | FF | FF | FF | 00 | F1 | 10 | 00 | 01 | FF | 00 |

**$EF_{PSLOCI}$ (Packet Switch Location Information)**

Logically:

RAI-MCC: 001
RAI-MNC: 01

RAI-LAC: 0001
RAI-RAC: 05
P-TMSI: "FF….FF"
P-TMSI signature value:"FF…FF"

| Coding: | B1 | B2 | B3 | B4 | B5 | B6 | B7 |
|---|---|---|---|---|---|---|---|
| Hex | FF | FF | FF | FF | FF | FF | FF |

| Coding: | B8 | B9 | B10 | B11 | B12 | B13 | B14 |
|---|---|---|---|---|---|---|---|
| Hex | 00 | F1 | 10 | 00 | 01 | 05 | 00 |

**$EF_{CBMI}$ (Cell Broadcast Message Identifier)**

Logically:

Cell Broadcast Message Identifier 1: '03 E7'

| Coding: | 03 | E7 | FF | .. | FF | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|

**$EF_{CBMID}$ (Cell Broadcast Message Identifier for Data Download)**

Logically:

Cell Broadcast Message Identifier 1: '10 01'

| Coding: | 10 | 01 | FF | .. | FF | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|

**$EF_{FDN}$ (Fixed Dialling Numbers)**

Logically:

Record 1:
Length of alp ha identifier: 6 characters;
Alpha identifier: "FDN111";
Length of BCD number: "03";
TON and NPI: Telephony and unknown;
Dialled number: 123;
CCI: None;
Ext2: None.

Coding for record 1:

| | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 | B12 | B13 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | 46 | 44 | 4E | 31 | 31 | 31 | 03 | 81 | 21 | F3 | FF | FF | FF |

| B14 | B15 | B16 | B17 | B18 | B19 | B20 |
|---|---|---|---|---|---|---|
| FF | FF | FF | FF | FF | FF | FF |

Record 2: Length of alpha identifier: 6 characters;
Alpha identifier: "FDN222";
Length of BCD number: "03";
TON and NPI: Telephony and Unknown;
Dialled number: 9876;
CCI: None;
Ext2: None.

Coding for record 2:

| | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 | B12 | B13 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | 46 | 44 | 4E | 32 | 32 | 32 | 03 | 81 | 89 | 67 | FF | FF | FF |

| B14 | B15 | B16 | B17 | B18 | B19 | B20 |
|---|---|---|---|---|---|---|
| FF | FF | FF | FF | FF | FF | FF |

Record 3: Length of alpha identifier: 6 characters;
Alpha identifier: "FDN333";
Length of BCD number: "0B";
TON and NPI: Telephony and International;
Dialled number: +12345678901234567890;
CCI: None;
Ext2: None.

Coding for record 3:

| | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 | B12 | B13 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | 46 | 44 | 4E | 33 | 33 | 33 | 0B | 91 | 21 | 43 | 65 | 87 | 09 |

| B14 | B15 | B16 | B17 | B18 | B19 | B20 |
|---|---|---|---|---|---|---|
| 21 | 43 | 65 | 87 | 09 | FF | FF |

**$EF_{BDN}$ (Barred Dialling Numbers)**

Logically:

Record 1: Length of alpha identifier: 6 characters;
Alpha identifier: "BDN111";
Length of BCD number: "06";
TON and NPI: Telephony and International;
Dialled number: +1357924680;
CCI: None;
Ext4: None
Comprehension method pointer: None.

Coding for record 1:

| | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 | B12 | B13 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | 42 | 44 | 4E | 31 | 31 | 31 | 06 | 91 | 31 | 75 | 29 | 64 | 08 |

| B14 | B15 | B16 | B17 | B18 | B19 | B20 | B21 |
|---|---|---|---|---|---|---|---|
| FF | FF | FF | FF | FF | FF | FF | FF |

Record 2: Length of alpha identifier: 6 characters;
Alpha identifier: "BDN222";
Length of BCD number: "03";
TON and NPI: Telephony and Unknown;
Dialled number: 122;
CCI: None;
Ext4: None
Comprehension method pointer: None.

Coding for record 2:

| | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 | B12 | B13 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | 42 | 44 | 4E | 32 | 32 | 32 | 04 | 81 | 21 | F2 | FF | FF | FF |

| B14 | B15 | B16 | B17 | B18 | B19 | B20 | B21 |
|---|---|---|---|---|---|---|---|
| FF | FF | FF | FF | FF | FF | FF | FF |

Record 3: Length of alpha identifier: 6 characters;
Alpha identifier: "BDN333";
Length of BCD number: "03";
TON and NPI: Telephony and Unknown;
Dialled number: 112;
CCI: None;
Ext4: None.
Comprehension method pointer: None

Coding for record 3:

| | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 | B9 | B10 | B11 | B12 | B13 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Hex | 42 | 44 | 4E | 33 | 33 | 33 | 03 | 81 | 11 | F2 | FF | FF | FF |

| B14 | B15 | B16 | B17 | B18 | B19 | B20 | B21 |
|---|---|---|---|---|---|---|---|
| FF | FF | FF | FF | FF | FF | FF | FF |

**$EF_{ECC}$ (Emergency Call Codes)**

Logically: Emergency call code: "122";
Emergency call code alpha identifier: "TEST";
Emergency call Service Category: RFU

| Coding: | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 |
|---|---|---|---|---|---|---|---|---|
| Hex | 21 | F2 | FF | 54 | 45 | 53 | 54 | 00 |

**$EF_{SMSS}$ (SMS Status)**

Logically: Last used TP-MR set to"00".
Memory capacity available (flag unset b1="1").

| Coding: | B1 | B2 |
|---|---|---|
| Hex | 00 | FF |

**$EF_{SMSP}$ (Short message service parameters)**

Logically:

Record 1:
Record length: 28 bytes
Parameter Indicators:
TP-Destination Address: Parameter absent
TS-Service Centre Address: Parameter present
TP-Protocol Identifier: Parameter absent
TP-Data Coding Scheme: Parameter absent
TP-Validity Period: Parameter absent
TS-Service Centre Address:
TON: International Number
NPI: "ISDN / telephone numbering plan"
Dialled number string: "112233445566778"

| Coding: | B1 | B2 | B3 | ... | B13 | B14 | B15 | B16 | B17 | B18 | B19 | B20 | B21 | B22 | B23 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Record 1: | FD | FF | FF | ... | FF | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 |

| B24 | B25 | B26 | B27 | B28 |
|---|---|---|---|---|
| FF | FF | FF | FF | FF |

For the display of icon: See ETSI TS 102 384 [26] subclause 27.22.1B.

## 27.22.1 Initialization of USIM Application Toolkit Enabled UICC by USIM Application Toolkit Enabled ME (Profile Download)

### 27.22.1.1 Definition and applicability

See clause 3.2.2.

### 27.22.1.2 Conformance requirement

The ME shall support the PROFILE DOWNLOAD command as defined in:

- TS 31.111 [15] clause 5.2.

### 27.22.1.3 Test purpose

To verify that the ME sends a TERMINAL PROFILE command in accordance with the above requirements.

#### 27.22.1.4 Method of test

##### 27.22.1.4.1 Initial conditions

The ME is connected to the USIM Simulator. All elementary files are coded as the default Toolkit personalization..

##### 27.22.1.4.2 Procedure

**Expected Sequence 1 (PROFILE DOWNLOAD)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | USER → ME | Power on ME | [UICC Activation] |
| 2 | ME → UICC | Select EF PL | |
| 3 | UICC → ME | Read EF PL | |
| 4 | ME → UICC | TERMINAL PROFILE 1.1 | PROFILE DOWNLOAD |
| 5 | UICC → ME | NORMAL ENDING OF COMMAND 1.1 | |
| 6 | ME → UICC | Select USIM Application | |

**TERMINAL PROFILE: 1.1**

Logically:

Coding:

| | | | | | |
|---|---|---|---|---|---|
| APDU: | CLA=80 | INS=10 | P1=00 | P2=00 | P3=XX |

| | | | |
|---|---|---|---|
| DATA IN: | YY | ZZ | … |

With XX representing the length of the following DATA IN depending on the USIM Toolkit commands supported by the ME, and with YY, ZZ, … representing here the bytes of the TERMINAL PROFILE data, as specified in TS 31.111 [15], clause 5.2.

**NORMAL ENDING OF COMMAND: 1.1**

Logically:

Coding:

| | |
|---|---|
| SW1=90 | SW2=00 |

#### 27.22.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.

### 27.22.2 Contents of the TERMINAL PROFILE command

#### 27.22.2.1 Definition and applicability

See table E.1 in annex B.

#### 27.22.2.2 Conformance requirement

The ME shall support the PROFILE DOWNLOAD command as defined in:

- TS 31.111 [15] clause 5.2.

#### 27.22.2.3 Test purpose

1. Verify that the TERMINAL PROFILE indicates that Profile Download facility is supported.
2. Record which USIM Application Toolkit facilities are supported by the ME, to determine which subsequent tests are required.

#### 27.22.2.4 Method of test

##### 27.22.2.4.1 Initial conditions

The ME is connected to the USIM Simulator. All elementary files are coded as the default USIM Application Toolkit personalization.

##### 27.22.1.4.2 Procedure

a) The ME is powered on.

b) After the ME sends the TERMINAL PROFILE command to the USIM Simulator, the USIM Simulator shall record the content of the TERMINAL PROFILE.

c) The USIM Simulator shall return SW1 / SW2 of '90 00'.

d) The contents of the TERMINAL PROFILE is recorded and compared to the corresponding table E.1 "status" column.

The test is terminated upon the ME sending the TERMINAL PROFILE command to the USIM Simulator.

#### 27.22.2.5 Test requirement

1) After step a) the ME shall send the TERMINAL PROFILE command to the USIM Simulator with bit 1 of the first byte set to 1 (facility supported by ME).

2) In table E.1 for the corresponding ME USIM Toolkit Release and Options, The TERMINAL PROFILE information "support" recorded must be in accordance with the "Status" column. Support of features defined only in releases later than currently tested release shall be ignored.

### 27.22.3 Servicing of proactive UICC commands

#### 27.22.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.3.2 Conformance requirement

On detection of a pending USIM Application Toolkit command from the UICC the ME shall perform the FETCH command to retrieve the proactive UICC command. The result of the executed command shall be transmitted from the ME to the UICC within a TERMINAL RESPONSE command.

The MORE TIME proactive command is used in this test. The ME shall have knowledge of this command, but may not support this USIM Application Toolkit facility.

- TS 31.111 [15] clause 6.3.

#### 27.22.3.3 Test purpose

To verify that the ME uses the FETCH command to obtain the proactive UICC command, after detection of a pending proactive UICC command. The pending proactive UICC command is indicated by the response parameters '91 xx' from the UICC.

To verify that the ME transmits the result of execution of the proactive UICC command to the UICC in the TERMINAL RESPONSE command.

#### 27.22.3.4 Method of test

##### 27.22.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as the USIM Application Toolkit default.

The USIM Simulator is configured to indicate that a proactive UICC command is pending.

The USIM Simulator is configured to monitor the UICC - ME interface.

##### 27.22.3.4.2 Procedure

a) The ME is powered on.

b) After the ME has performed the PROFILE DOWNLOAD procedure, the USIM Simulator indicates that a Proactive UICC Command is pending with SW1 / SW2 of '91 0B'.

c) After the ME sends the FETCH command to the USIM Simulator, the USIM Simulator returns Proactive UICC Command 2.1: MORE TIME.

#### 27.22.3.5 Test requirement

1) After step b) the ME shall send the FETCH command to the UICC.

2) After step c) the ME shall send the TERMINAL REPONSE command with command number "01", type of command "02" and command qualifier "00".

### 27.22.4 Proactive UICC commands

#### 27.22.4.1 DISPLAY TEXT

##### 27.22.4.1.1 DISPLAY TEXT (Normal)

###### 27.22.4.1.1.1 Definition and applicability

See clause 3.2.2.

###### 27.22.4.1.1.2 Conformance requirements

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

TS 31.111 [15], clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

###### 27.22.4.1.1.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.1.4 Method of test

##### 27.22.4.1.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.1.4.2 Procedure

**Expected Sequence 1.1 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, screen busy)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (DISPLAY TEXT, high priority, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (DISPLAY TEXT, Packed, SMS default alphabet, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (DISPLAY TEXT, Clear message after delay, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (DISPLAY TEXT, Text string with 160 bytes, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.6.

**Expected Sequence 1.7 (DISPLAY TEXT, Backward move in UICC session, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.7.

**Expected Sequence 1.8 (DISPLAY TEXT, session terminated by user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.8.

**Expected Sequence 1.9 (DISPLAY TEXT, icon and text to be displayed, no text string given, not understood by ME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.1.4.2, Expected Sequence 1.9.

#### 27.22.4.1.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.9.

### 27.22.4.1.2 DISPLAY TEXT (Support of "No response from user")

#### 27.22.4.1.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.2.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.1.2.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.2.4 Method of test

##### 27.22.4.1.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/1..

The USIM simulator shall be set to that period of time.

##### 27.22.4.1.2.4.2 Procedure

**Expected Sequence 2.1 (DISPLAY TEXT, no response from user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.2.4.2, Expected Sequence.

#### 2.1.27.22.4.1.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.1.3 DISPLAY TEXT (Display of extension text)

#### 27.22.4.1.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.3.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.15.

#### 27.22.4.1.3.3 Test purpose

To verify that the ME displays the extension text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.3.4 Method of test

##### 27.22.4.1.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.1.3.4.2 Procedure

**Expected Sequence 3.1 (DISPLAY TEXT, display of the extension text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.3.4.2, Expected Sequence 3.1.

#### 27.22.4.1.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.1.4 DISPLAY TEXT (Sustained text)

#### 27.22.4.1.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.4.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.15, clause 8.15.

#### 27.22.4.1.4.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, returns a successful result in the TERMINAL RESPONSE command send to the UICC and sustain the display beyond sending the TERMINAL response.

#### 27.22.4.1.4.4 Method of test

##### 27.22.4.1.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.4.4.2 Procedure

**Expected Sequence 4.1 (DISPLAY TEXT, sustained text, unpacked data 8 bits, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.1.

**Expected Sequence 4.2 (DISPLAY TEXT, sustained text, clear message after delay, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.2.

**Expected Sequence 4.3 (DISPLAY TEXT, sustained text, wait for user MMI to clear, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.4.4.2, Expected Sequence 4.3.

**Expected Sequence 4.4 (DISPLAY TEXT, sustained text, wait for high priority event to clear, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: DISPLAY TEXT 4.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: DISPLAY TEXT 4.4.1 | [wait for user to clear message] |
| 4 | ME → USER | Display "Toolkit Test 4" | |
| 5 | ME → UICC | TERMINAL RESPONSE: DISPLAY TEXT 4.4.1 | [Command performed successfully] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | ME → USER | Display of "Toolkit Test 4" | Text shall sustain until - a higher priority event occurs. |
| 8 | USS → ME | INCOMING MOBILE TERMINATED CALL | |

PROACTIVE COMMAND: DISPLAY TEXT 4.4.1

Logically:

Command details
- Command number: 1
- Command type: DISPLAY TEXT
- Command qualifier: normal priority, wait for user to clear message

Device identities
- Source device: UICC
- Destination device: Display

Text String
- Data coding scheme: unpacked, 8 bit data
- Text: "Toolkit Test 4"

Immediate Response

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 21 | 80 | 82 | 02 | 81 | 02 | 8D |
| | 0F | 04 | 54 | 6F | 6F | 6C | 6B | 69 | 74 | 20 | 54 | 65 |
| | 73 | 74 | 20 | 34 | AB | 00 | | | | | | |

TERMINAL RESPONSE: DISPLAY TEXT 4.4.1

Logically:

Command details
- Command number: 1
- Command type: DISPLAY TEXT
- Command qualifier: normal priority, wait for user to clear message

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 21 | 80 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.1.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.4.

### 27.22.4.1.5 DISPLAY TEXT (Display of icons)

#### 27.22.4.1.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.5.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.1.5.3 Test purpose

To verify that the ME displays the icons which are referred to in the contents of the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.5.4 Method of test

##### 27.22.4.1.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.5.4.2 Procedure

**Expected Sequence 5.1A (DISPLAY TEXT, display of basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.1A.

**Expected Sequence 5.1B (DISPLAY TEXT, display of basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.1B.

**Expected Sequence 5.2A (DISPLAY TEXT, display of colour icon, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.2A.

**Expected Sequence 5.2B (DISPLAY TEXT, display of colour icon, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.2B.

**Expected Sequence 5.3A (DISPLAY TEXT, display of basic icon, not self explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.3A.

**Expected Sequence 5.3B (DISPLAY TEXT, display of basic icon, not self explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.5.4.2, Expected Sequence 5.3B.27.22.4.1.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1A to 5.3B.

#### 27.22.4.1.6 DISPLAY TEXT (UCS2 display in Cyrillic)

##### 27.22.4.1.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.6.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Cyrillic alphabet, as defined in the following technical specification: ISO/IEC 10646 [17].

##### 27.22.4.1.6.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.1.6.4 Method of test

###### 27.22.4.1.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.1.6.4.2 Procedure

**Expected Sequence 6.1 (DISPLAY TEXT, UCS2 coded in Cyrillic)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.6.4.2, Expected Sequence 6.1.

##### 27.22.4.1.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.1.7 DISPLAY TEXT (Variable Time out)

##### 27.22.4.1.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.7.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31 and clause 8.43.

The ME shall support the variable time out for the display text.

##### 27.22.4.1.7.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.7.4 Method of test

##### 27.22.4.1.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.7.4.2 Procedure

**Expected Sequence 7.1 (DISPLAY TEXT, variable timeout of 10 seconds)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.7.4.2, Expected Sequence 7.1.

#### 27.22.4.1.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.1.8 DISPLAY TEXT (Support of Text Attribute)

#### 27.22.4.1.8.1 DISPLAY TEXT (Support of Text Attribute – Left Alignment)

##### 27.22.4.1.8.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.1.8.1.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Left Alignment for the display text.

##### 27.22.4.1.8.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.1.8.1.4 Method of test

###### 27.22.4.1.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.1.8.1.4.2 Procedure

**Expected Sequence 8.1 (DISPLAY TEXT, Text Attribute with Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.1.4.2, Expected Sequence 8.1.

#### 27.22.4.1.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

### 27.22.4.1.8.2 DISPLAY TEXT (Support of Text Attribute – Center Alignment)

#### 27.22.4.1.8.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.2.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Centre Alignment for the display text.

#### 27.22.4.1.8.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.2.4 Method of test

##### 27.22.4.1.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.2.4.2 Procedure

**Expected Sequence 8.2 (DISPLAY TEXT, Text Attribute with Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.2.4.2, Expected Sequence 8.2.

#### 27.22.4.1.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.2.

### 27.22.4.1.8.3 DISPLAY TEXT (Support of Text Attribute – Right Alignment)

#### 27.22.4.1.8.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.3.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with Right Alignment for the display text.

27.22.4.1.8.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.3.4 Method of test

27.22.4.1.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.3.4.2 Procedure

**Expected Sequence 8.3 (DISPLAY TEXT, Text Attribute with Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.3.4.2, Expected Sequence 8.3.

27.22.4.1.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.3.

27.22.4.1.8.4 DISPLAY TEXT (Support of Text Attribute – Large Font Size)

27.22.4.1.8.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.4.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with large font size for the display text.

27.22.4.1.8.4.3 Test purpose

To verify that the ME displays the text formatted according to the large size font text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.4.4 Method of test

27.22.4.1.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.4.4.2 Procedure

**Expected Sequence 8.4 (DISPLAY TEXT, Text Attribute with Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.4.4.2, Expected Sequence 8.4.

27.22.4.1.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.4.

27.22.4.1.8.5 DISPLAY TEXT (Support of Text Attribute – Small Font Size)

27.22.4.1.8.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.5.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with small font size for the display text.

27.22.4.1.8.5.3 Test purpose

To verify that the ME displays the text formatted according to the small size font text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.5.4 Method of test

27.22.4.1.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.5.4.2 Procedure

**Expected Sequence 8.5 (DISPLAY TEXT, Text Attribute with Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.5.4.2, Expected Sequence 8.5.

27.22.4.1.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.5.

27.22.4.1.8.6 DISPLAY TEXT (Support of Text Attribute – Bold On)

27.22.4.1.8.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.6.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with bold on for the display text.

#### 27.22.4.1.8.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.6.4 Method of test

##### 27.22.4.1.8.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.6.4.2 Procedure

**Expected Sequence 8.6 (DISPLAY TEXT, Text Attribute with Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.6.4.2, Expected Sequence 8.6.

#### 27.22.4.1.8.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.6.

### 27.22.4.1.8.7 DISPLAY TEXT (Support of Text Attribute – Italic On)

#### 27.22.4.1.8.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.7.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with italic on for the display text.

#### 27.22.4.1.8.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.7.4 Method of test

27.22.4.1.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.7.4.2 Procedure

**Expected Sequence 8.7 (DISPLAY TEXT, Text Attribute with Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.7.4.2, Expected Sequence 8.7.

27.22.4.1.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.7.

27.22.4.1.8.8 DISPLAY TEXT (Support of Text Attribute – Underline On)

27.22.4.1.8.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.8.8.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with underline on for the display text.

27.22.4.1.8.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.8.8.4 Method of test

27.22.4.1.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.8.8.4.2 Procedure

**Expected Sequence 8.8 (DISPLAY TEXT, Text Attribute with Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.8.4.2, Expected Sequence 8.8.

#### 27.22.4.1.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.8.

### 27.22.4.1.8.9 DISPLAY TEXT (Support of Text Attribute – Strikethrough On)

#### 27.22.4.1.8.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.9.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with underline on for the display text.

#### 27.22.4.1.8.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.9.4 Method of test

##### 27.22.4.1.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.9.4.2 Procedure

**Expected Sequence 8.9 (DISPLAY TEXT, Text Attribute with Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.9.4.2, Expected Sequence 8.9.

#### 27.22.4.1.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.9.

### 27.22.4.1.8.10 DISPLAY TEXT (Support of Text Attribute – Foreground and Background Colours)

#### 27.22.4.1.8.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.8.10.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.31, clause 8.43 and clause 8.70.

The ME shall support the text attribute with different foreground and background colours for the display text.

#### 27.22.4.1.8.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.8.10.4 Method of test

##### 27.22.4.1.8.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.1.8.10.4.2 Procedure

**Expected Sequence 8.10 (DISPLAY TEXT, Text Attribute with Foreground and Background Colours)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.8.10.4.2, Expected Sequence 8.10.

#### 27.22.4.1.8.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.10.

### 27.22.4.1.9 DISPLAY TEXT (UCS2 display in Chinese)

#### 27.22.4.1.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.1.9.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Chinese characters, as defined in the following technical specification: ISO/IEC 10646 [17].

#### 27.22.4.1.9.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.1.9.4 Method of test

##### 27.22.4.1.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.9.4.2 Procedure

**Expected Sequence 9.1 (DISPLAY TEXT, UCS2 coded – Chinese characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.9.4.2, Expected Sequence 9.1.

27.22.4.1.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

### 27.22.4.1.10 DISPLAY TEXT (UCS2 display in Katakana)

27.22.4.1.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.1.10.2 Conformance requirement

The ME shall support the DISPLAY TEXT command as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.1, clause 6.5.4, clause 6.6.1, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

The ME shall support the UCS2 alphabet for the coding of the Katakana characters, as defined in the following technical specification: ISO/IEC 10646 [17].

27.22.4.1.10.3 Test purpose

To verify that the ME displays the text contained in the DISPLAY TEXT proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.1.10.4 Method of test

27.22.4.1.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.1.10.4.2 Procedure

**Expected Sequence 10.1 (DISPLAY TEXT, UCS2 coded – Katakana characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.1.10.4.2, Expected Sequence 10.1.

27.22.4.1.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 10.1.

## 27.22.4.2 GET INKEY

### 27.22.4.2.1 GET INKEY(normal)

27.22.4.2.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.1.2 Conformance Requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.2.1.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the single character entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.1.4 Method of test

##### 27.22.4.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be set to a display other than the idle display.

##### 27.22.4.2.1.4.2 Procedure

**Expected Sequence 1.1 (GET INKEY, digits only for character, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (GET INKEY, digits only for character set, SMS default Alphabet for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (GET INKEY, backward move)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (GET INKEY, abort)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (GET INKEY, SMS default alphabet for character set, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (GET INKEY, Max length for the Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.1.4.2, Expected Sequence 1.6.

#### 27.22.4.2.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

### 27.22.4.2.2 GET INKEY (No response from User)

#### 27.22.4.2.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.2.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.2.2.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.2.2.4 Method of test

##### 27.22.4.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/2.

The USIM Simulator shall be set to that period of time.

##### 27.22.4.2.2.4.2 Procedure

**Expected Sequence 2.1 (GET INKEY, no response from the user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.2.4.2, Expected Sequence 2.1.

#### 27.22.4.2.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.2.3 GET INKEY (UCS2 display in Cyrillic)

#### 27.22.4.2.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.3.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.3.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.3.4 Method of test

##### 27.22.4.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.2.3.4.2 Procedure

**Expected Sequence 3.1 (GET INKEY, Text String coding in UCS2 Alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.3.4.2, Expected Sequence 3.1.

**Expected Sequence 3.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.3.4.2, Expected Sequence 3.2.

#### 27.22.4.2.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1 to 3.2.

### 27.22.4.2.4 GET INKEY (UCS2 entry in Cyrillic)

#### 27.22.4.2.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.4.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.4.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.4.4 Method of test

##### 27.22.4.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.4.4.2 Procedure

**Expected Sequence 4.1 (GET INKEY, characters from UCS2 alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.4.4.2, Expected Sequence 4.1.

27.22.4.2.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.2.5 GET INKEY ("Yes/No" Response)

27.22.4.2.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.5.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

27.22.4.2.5.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.5.4 Method of test

27.22.4.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.2.5.4.2 Procedure

**Expected Sequence 5.1(GET INKEY, "Yes/No" Response for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.5.4.2, Expected Sequence 5.1.

27.22.4.2.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.2.6 GET INKEY (display of Icon)

27.22.4.2.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.6.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.2.6.3 Test purpose

To verify that the ME displays the Icon contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.6.4 Method of test

##### 27.22.4.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.2.6.4.2 Procedure

**Expected Sequence 6.1A (GET INKEY, Basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.1A.

**Expected Sequence 6.1B (GET INKEY, Basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.1B.

**Expected Sequence 6.2A (GET INKEY, Basic icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.2A.

**Expected Sequence 6.2B (GET INKEY, Basic icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.2B.

**Expected Sequence 6.3A (GET INKEY, Colour icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.3A.

**Expected Sequence 6.3B (GET INKEY, Colour icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.3B.

**Expected Sequence 6.4A (GET INKEY, Colour icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.4A.

**Expected Sequence 6.4B (GET INKEY, Colour icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.6.4.2, Expected Sequence 6.4B.

#### 27.22.4.2.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1A to 6.4B.

### 27.22.4.2.7 GET INKEY (Help Information)

#### 27.22.4.2.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.7.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.2.7.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.7.4 Method of test

##### 27.22.4.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.2.7.4.2 Procedure

**Expected Sequence 7.1 (GET INKEY, help information available)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.7.4.2, Expected Sequence 7.1.

#### 27.22.4.2.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.2.8 GET INKEY (Variable Time out)

#### 27.22.4.2.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.8.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.31.

#### 27.22.4.2.8.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.8.4 Method of test

27.22.4.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.8.4.2 Procedure

**Expected Sequence 8.1 (GET INKEY, variable time out of 10 seconds)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.8.4.2, Expected Sequence 8.1.

27.22.4.2.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

## 27.22.4.2.9 GET INKEY (Support of Text Attribute)

### 27.22.4.2.9.1 GET INKEY (Support of Text Attribute – Left Alignment)

27.22.4.2.9.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.1.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

27.22.4.2.9.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.1.4 Method of test

27.22.4.2.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.1.4.2 Procedure

**Expected Sequence 9.1 (GET INKEY, Text attribute with Left Alignment )**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.1.4.2, Expected Sequence 9.1.

27.22.4.2.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

#### 27.22.4.2.9.2 GET INKEY (Support of Text Attribute – Center Alignment)

##### 27.22.4.2.9.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.2.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.2.4 Method of test

###### 27.22.4.2.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.2.9.2.4.2 Procedure

**Expected Sequence 9.2 (GET INKEY, Text attribute with Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.2.4.2, Expected Sequence 9.2.

##### 27.22.4.2.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.2.

#### 27.22.4.2.9.3 GET INKEY (Support of Text Attribute – Right Alignment)

##### 27.22.4.2.9.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.3.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.3.4 Method of test

27.22.4.2.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.3.4.2 Procedure

**Expected Sequence 9.3 (GET INKEY, Text attribute with Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.3.4.2, Expected Sequence 9.3.

27.22.4.2.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.3.

27.22.4.2.9.4 GET INKEY (Support of Text Attribute – Large Font Size)

27.22.4.2.9.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.4.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

27.22.4.2.9.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.4.4 Method of test

27.22.4.2.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.4.4.2 Procedure

**Expected Sequence 9.4 (GET INKEY, Text attribute with Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.4.4.2, Expected Sequence 9.4.

27.22.4.2.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.4.

#### 27.22.4.2.9.5 GET INKEY (Support of Text Attribute – Small Font Size)

##### 27.22.4.2.9.5.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.5.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.5.4 Method of test

###### 27.22.4.2.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.2.9.5.4.2 Procedure

**Expected Sequence 9.5 (GET INKEY, Text attribute with Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.5.4.2, Expected Sequence 9.5.

##### 27.22.4.2.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.5.

#### 27.22.4.2.9.6 GET INKEY (Support of Text Attribute – Bold On)

##### 27.22.4.2.9.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.6.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.6.4 Method of test

27.22.4.2.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.6.4.2 Procedure

**Expected Sequence 9.6 (GET INKEY, Text attribute with Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.6.4.2, Expected Sequence 9.6.

27.22.4.2.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.6.

27.22.4.2.9.7 GET INKEY (Support of Text Attribute – Italic On)

27.22.4.2.9.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.7.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

27.22.4.2.9.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.7.4 Method of test

27.22.4.2.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.7.4.2 Procedure

**Expected Sequence 9.7 (GET INKEY, Text attribute with Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.7.4.2, Expected Sequence 9.7.

27.22.4.2.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.7.

#### 27.22.4.2.9.8 GET INKEY (Support of Text Attribute – Underline On)

##### 27.22.4.2.9.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.8.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.2.9.8.4 Method of test

###### 27.22.4.2.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.2.9.8.4.2 Procedure

**Expected Sequence 9.8 (GET INKEY, Text attribute with Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.8.4.2, Expected Sequence 9.8.

##### 27.22.4.2.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.8.

#### 27.22.4.2.9.9 GET INKEY (Support of Text Attribute – Strikethrough On)

##### 27.22.4.2.9.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.2.9.9.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

##### 27.22.4.2.9.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.9.4 Method of test

27.22.4.2.9.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.9.4.2 Procedure

**Expected Sequence 9.9 (GET INKEY, Text attribute with Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.9.4.2, Expected Sequence 9.9.

27.22.4.2.9.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.9.

27.22.4.2.9.10 GET INKEY (Support of Text Attribute – Foreground and Background Colour)

27.22.4.2.9.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.2.9.10.2 Conformance requirement

The ME shall support the GET INKEY command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.5.4, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.8, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3, clause 8.31 and clause 8.70.

27.22.4.2.9.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.2.9.10.4 Method of test

27.22.4.2.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.2.9.10.4.2 Procedure

**Expected Sequence 9.10 (GET INKEY, Text attribute with Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.9.10.4.2, Expected Sequence 9.10.

27.22.4.2.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.10.

### 27.22.4.2.10 GET INKEY (UCS2 display in Chinese)

#### 27.22.4.2.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.10.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.10.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.10.4 Method of test

##### 27.22.4.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.2.10.4.2 Procedure

**Expected Sequence 10.1 (GET INKEY, Text String coding in UCS2 Alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.10.4.2, Expected Sequence 10.1.

**Expected Sequence 10.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.10.4.2, Expected Sequence 10.2.

#### 27.22.4.2.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 10.1 to 10.2.

### 27.22.4.2.11 GET INKEY (UCS2 entry in Chinese)

#### 27.22.4.2.11.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.11.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.11.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.11.4 Method of test

##### 27.22.4.2.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.2.11.4.2 Procedure

**Expected Sequence 11.1 (GET INKEY, characters from UCS2 alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.11.4.2, Expected Sequence 11.1.

#### 27.22.4.2.11.5 Test requirement

The ME shall operate in the manner defined in expected sequence 11.1

### 27.22.4.2.12 GET INKEY (UCS2 display in Katakana)

#### 27.22.4.2.12.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.2.12.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.2.12.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.2.12.4 Method of test

##### 27.22.4.2.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.2.12.4.2 Procedure

**Expected Sequence 12.1 (GET INKEY, Text String coding in UCS2 Alphabet - Katakana characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.12.4.2, Expected Sequence 12.1.

**Expected Sequence 12.2 (GET INKEY, max length for the Text String coding in UCS2 Alphabet - Katakana characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.12.4.2, Expected Sequence 12.2.

### 27.22.4.2.12.5 Test requirement

The ME shall operate in the manner defined in expected sequence 12.1 to 12.2.

## 27.22.4.2.13 GET INKEY (UCS2 entry in Katakana)

### 27.22.4.2.13.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.2.13.2 Conformance requirement

The ME shall support the GET INKEY command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.2, clause 6.6.2, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

### 27.22.4.2.13.3 Test purpose

To verify that the ME displays the text contained in the GET INKEY proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

### 27.22.4.2.13.4 Method of test

#### 27.22.4.2.13.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.2.13.4.2 Procedure

**Expected Sequence 13.1 (GET INKEY, characters from UCS2 alphabet - Katakana characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.2.13.4.2, Expected Sequence 13.1.

### 27.22.4.2.13.5 Test requirement

The ME shall operate in the manner defined in expected sequence 13.1

## 27.22.4.3. GET INPUT

### 27.22.4.3.1 GET INPUT (normal)

#### 27.22.4.3.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.1.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.3.1.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.1.4 Method of test

##### 27.22.4.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.1.4.2 Procedure

**Expected Sequence 1.1 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (GET INPUT, digits only, SMS default alphabet, ME to echo text, packing SMS Point-to-point required by ME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (GET INPUT, character set, SMS Default Alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (GET INPUT, digits only, SMS default alphabet, ME to hide text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (GET INPUT, backwards move)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.6.

**Expected Sequence 1.7 (GET INPUT, abort)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.7.

**Expected Sequence 1.8 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.8.

**Expected Sequence 1.9 (GET INPUT, digits only, SMS default alphabet, ME to echo text, ME supporting 8 bit data Message)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.9.

**Expected Sequence 1.10 (GET INPUT, null length for the text string, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.1.4.2, Expected Sequence 1.10.

#### 27.22.4.3.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.10.

### 27.22.4.3.2 GET INPUT (No response from User)

#### 27.22.4.3.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.2.2 Conformance requirement

The ME shall support the GET INPUT command as defined in the following technical specifications :

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.3.2.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns a "No response from user" result value in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.3.2.4 Method of test

##### 27.22.4.3.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

ME Manufacturers shall set the "no response from user" period of time as declared in table A.2/3.

The USIM Simulator shall be set to that period of time.

##### 27.22.4.3.2.4.2 Procedure

**Expected Sequence 2.1 (GET INPUT, no response from the user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.2.4.2, Expected Sequence 2.1.

#### 27.22.4.3.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.3.3 GET INPUT (UCS2 display in Cyrillic)

#### 27.22.4.3.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.3.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.3.3.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.3.4 Method of test

##### 27.22.4.3.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.3.4.2 Procedure

**Expected Sequence 3.1 (GET INPUT, text string coding in UCS2 in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.3.4.2, Expected Sequence 3.1.

**Expected Sequence 3.2 (GET INPUT, max length for the text string coding in UCS2 in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.3.4.2, Expected Sequence 3.2.

#### 27.22.4.3.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.2.

### 27.22.4.3.4 GET INPUT (UCS2 entry in Cyrillic)

#### 27.22.4.3.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.4.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

#### 27.22.4.3.4.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.4.4 Method of test

##### 27.22.4.3.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.4.4.2 Procedure

**Expected Sequence 4.1 (GET INPUT, character set from UCS2 alphabet in Cyrillic, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.4.4.2, Expected Sequence 4.1.

**Expected Sequence 4.2 (GET INPUT, character set from UCS2 alphabet in Cyrillic, Max length for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.4.4.2, Expected Sequence 4.2.

#### 27.22.4.3.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.2.

### 27.22.4.3.5 GET INPUT (default text)

#### 27.22.4.3.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.5.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.23.

#### 27.22.4.3.5.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.5.4 Method of test

##### 27.22.4.3.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.5.4.2 Procedure

**Expected Sequence 5.1(GET INPUT, default text for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.5.4.2, Expected Sequence 5.1.

**Expected Sequence 5.2 (GET INPUT, default text for the input with max length, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.5.4.2, Expected Sequence 5.2.

#### 27.22.4.3.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1 to 5.2.

### 27.22.4.3.6 GET INPUT (display of Icon)

#### 27.22.4.3.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.6.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.5.4, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 12.31.

#### 27.22.4.3.6.3 Test purpose

To verify that the ME displays the Icon contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.6.4 Method of test

##### 27.22.4.3.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.6.4.2 Procedure

**Expected Sequence 6.1A (GET INPUT, Basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.1A.

**Expected Sequence 6.1B (GET INPUT, Basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.1B.

**Expected Sequence 6.2A (GET INPUT, Basic icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.2A.

**Expected Sequence 6.2B (GET INPUT, Basic icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.2B.

**Expected Sequence 6.3A (GET INPUT, Colour icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.3A.

**Expected Sequence 6.3B (GET INPUT, Colour icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.3B.

**Expected Sequence 6.4A (GET INPUT, Colour icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.4A.

**Expected Sequence 6.4B (GET INPUT, Colour icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.6.4.2, Expected Sequence 6.4B.

#### 27.22.4.3.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 6.1A to 6.4B.

### 27.22.4.3.7 GET INPUT (Help Information)

#### 27.22.4.3.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.7.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

#### 27.22.4.3.7.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns a 'help information required by the user' result value in the TERMINAL RESPONSE command sent to the UICC if the user has indicated the need to get help information.

#### 27.22.4.3.7.4 Method of test

##### 27.22.4.3.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.7.4.2 Procedure

**Expected Sequence 7.1 (GET INPUT, digits only, ME to echo text, ME supporting 8 bit data Message, help information available)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.7.4.2, Expected Sequence 7.1.

27.22.4.3.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.3.8 GET INPUT (Support of Text Attribute)

#### 27.22.4.3.8.1 GET INPUT (Support of Text Attribute – Left Alignment)

27.22.4.3.8.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.1.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.1.4 Method of test

27.22.4.3.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.1.4.2 Procedure

**Expected Sequence 8.1 (GET INPUT, Text attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.1.4.2, Expected Sequence 8.1.

27.22.4.3.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

#### 27.22.4.3.8.2 GET INPUT (Support of Text Attribute – Center Alignment)

27.22.4.3.8.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.2.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.8.2.4 Method of test

##### 27.22.4.3.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.8.2.4.2 Procedure

**Expected Sequence 8.2 (GET INPUT, Text attribute – Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.2.4.2, Expected Sequence 8.2.

#### 27.22.4.3.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.2.

### 27.22.4.3.8.3 GET INPUT (Support of Text Attribute – Right Alignment)

#### 27.22.4.3.8.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.3.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.8.3.4 Method of test

##### 27.22.4.3.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.3.4.2 Procedure

**Expected Sequence 8.3 (GET INPUT, Text attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.3.4.2, Expected Sequence 8.3.

27.22.4.3.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.3.

27.22.4.3.8.4 GET INPUT (Support of Text Attribute – Large Font Size)

27.22.4.3.8.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.4.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.4.4 Method of test

27.22.4.3.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.4.4.2 Procedure

**Expected Sequence 8.4 (GET INPUT, Text attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.4.4.2, Expected Sequence 8.4.

27.22.4.3.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.4.

27.22.4.3.8.5 GET INPUT (Support of Text Attribute – Small Font Size)

27.22.4.3.8.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.5.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.8.5.4 Method of test

##### 27.22.4.3.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.8.5.4.2 Procedure

**Expected Sequence 8.5 (GET INPUT, Text attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.5.4.2, Expected Sequence 8.5.

#### 27.22.4.3.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.5.

### 27.22.4.3.8.6 GET INPUT (Support of Text Attribute – Bold On)

#### 27.22.4.3.8.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.6.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.8.6.4 Method of test

##### 27.22.4.3.8.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.8.6.4.2 Procedure

**Expected Sequence 8.6 (GET INPUT, Text attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.6.4.2, Expected Sequence 8.6.

#### 27.22.4.3.8.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.6.

### 27.22.4.3.8.7 GET INPUT (Support of Text Attribute – Italic On)

#### 27.22.4.3.8.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.7.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.8.7.4 Method of test

##### 27.22.4.3.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.3.8.7.4.2 Procedure

**Expected Sequence 8.7 (GET INPUT, Text attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.7.4.2, Expected Sequence 8.7.

#### 27.22.4.3.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.7.

### 27.22.4.3.8.8 GET INPUT (Support of Text Attribute – Underline On)

#### 27.22.4.3.8.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.8.8.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

#### 27.22.4.3.8.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.8.4 Method of test

27.22.4.3.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.8.4.2 Procedure

**Expected Sequence 8.8 (GET INPUT, Text attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.8.4.2, Expected Sequence 8.8.

27.22.4.3.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.8.

27.22.4.3.8.9 GET INPUT (Support of Text Attribute – Strikethrough On)

27.22.4.3.8.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.8.9.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

27.22.4.3.8.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.8.9.4 Method of test

27.22.4.3.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.3.8.9.4.2 Procedure

**Expected Sequence 8.9 (GET INPUT, Text attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.9.4.2, Expected Sequence 8.9.

27.22.4.3.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.9.

#### 27.22.4.3.8.10 GET INPUT (Support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.3.8.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.3.8.10.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2, clause 8.15.3 and clause 8.70.

##### 27.22.4.3.8.10.3 Test purpose

To verify that the ME displays the text formatted according to the fore- and background colour text attribute configuration contained in the GET INPUT proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.3.8.10.4 Method of test

###### 27.22.4.3.8.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.3.8.10.4.2 Procedure

**Expected Sequence 8.10 (GET INPUT, Text attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.8.10.4.2, Expected Sequence 8.10.

##### 27.22.4.3.8.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.10.

### 27.22.4.3.9 GET INPUT (UCS2 display in Chinese)

#### 27.22.4.3.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.9.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.3.9.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.9.4 Method of test

##### 27.22.4.3.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.9.4.2 Procedure

**Expected Sequence 9.1 (GET INPUT, text string coding in UCS2 - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.9.4.2, Expected Sequence 9.1.

**Expected Sequence 9.2 (GET INPUT, max length for the text string coding in UCS2 - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.9.4.2, Expected Sequence 9.2.

#### 27.22.4.3.9.5 Test requirement

The ME shall operate in the manner defined in expected sequences 9.1 to 9.2

### 27.22.4.3.10 GET INPUT (UCS2 entry in Chinese)

#### 27.22.4.3.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.10.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in ISO/IEC 10646 [17].

#### 27.22.4.3.10.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.10.4 Method of test

##### 27.22.4.3.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.10.4.2 Procedure

**Expected Sequence 10.1 (GET INPUT, character set from UCS2 alphabet - Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.10.4.2, Expected Sequence 10.1.

**Expected Sequence 10.2 (GET INPUT, character set from UCS2 alphabet - Chinese characters, Max length for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.10.4.2, Expected Sequence 10.2.

27.22.4.3.10.5 Test requirement

The ME shall operate in the manner defined in expected sequences 10.1 to 10.2

## 27.22.4.3.11 GET INPUT (UCS2 display in Katakana)

27.22.4.3.11.1 Definition and applicability

See clause 3.2.2.

27.22.4.3.11.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

27.22.4.3.11.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.3.11.4 Method of test

27.22.4.3.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.3.11.4.2 Procedure

**Expected Sequence 11.1 (GET INPUT, text string coding in UCS2 in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.11.4.2, Expected Sequence 11.1.

**Expected Sequence 11.2 (GET INPUT, max length for the text string coding in UCS2 in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.11.4.2, Expected Sequence 11.2.

#### 27.22.4.3.11.5 Test requirement

The ME shall operate in the manner defined in expected sequences 11.1 to 11.2

### 27.22.4.3.12 GET INPUT (UCS2 entry in Katakana)

#### 27.22.4.3.12.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.3.12.2 Conformance requirement

The ME shall support the GET INPUT command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.11, clause 8.15, clause 8.15.1, clause 8.15.2 and clause 8.15.3.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese character, as defined in ISO/IEC 10646 [17].

#### 27.22.4.3.12.3 Test purpose

To verify that the ME displays the text contained in the GET INPUT proactive UICC command, and returns the text string entered in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.3.12.4 Method of test

##### 27.22.4.3.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.3.12.4.2 Procedure

**Expected Sequence 12.1 (GET INPUT, character set from UCS2 alphabet in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.12.4.2, Expected Sequence 12.1.

**Expected Sequence 12.2 (GET INPUT, character set from UCS2 alphabet in Katakana, Max length for the input, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.3.12.4.2, Expected Sequence 12.2.

#### 27.22.4.3.12.5 Test requirement

The ME shall operate in the manner defined in expected sequences 12.1 to 12.2.

## 27.22.4.4 MORE TIME

### 27.22.4.4.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.4.2 Conformance requirement

The ME shall support the MORE TIME command as defined in:

- TS 31.111 [15] clause 6.4.4, clause 6.6.4, clause 5.2, clause 8.6 and clause 8.7.

#### 27.22.4.4.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the MORE TIME proactive UICC command.

#### 27.22.4.4.4 Method of test

##### 27.22.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.4.4.2 Procedure

**Expected Sequence 1.1 (MORE TIME)**

See ETSI TS 102 384 [26] in subclause 27.22.4.4.4.2, Expected Sequence 1.1.

#### 27.22.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.4.5 PLAY TONE

#### 27.22.4.5.1 PLAY TONE (Normal)

##### 27.22.4.5.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.1.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

##### 27.22.4.5.1.3 Test purpose

To verify that the ME plays an audio tone of a type and duration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece whilst not in call and shall superimpose the tone on top of the downlink audio whilst in call.

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command.

##### 27.22.4.5.1.4 Method of test

###### 27.22.4.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.1.4.2 Procedure

**Expected Sequence 1.1 (PLAY TONE)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.1 | |
| 4 | ME → USER | Display "Dial Tone"<br>Play a standard supervisory dial tone through the external ringer for a duration of 5 s | |
| 5 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.1 | [Command performed successfully] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.2 | |
| 10 | ME → USER | Display "Sub. Busy"<br>Play a standard supervisory called subscriber busy tone for a duration of 5 s | |
| 11 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.2 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.3 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.3 | |
| 16 | ME → USER | Display "Congestion"<br>Play a standard supervisory congestion tone for a duration of 5 s | |
| 17 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.3 | [Command performed successfully] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.4 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.4 | |
| 22 | ME → USER | Display "RP Ack"<br>Play a standard supervisory radio path acknowledgement tone | |
| 23 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.4 | [Command performed successfully] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 25 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.5 | |
| 26 | ME → UICC | FETCH | |
| 27 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.5 | |
| 28 | ME → USER | Display "No RP"<br>Play a standard supervisory radio path not available / call dropped tone for a duration of 5 s | |
| 29 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.5 | [Command performed successfully] |

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.6 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.6 | |
| 34 | ME → USER | Display "Spec Info"<br>Play a standard supervisory error / special information tone for a duration of 5 s | |
| 35 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.6 | [Command performed successfully] |
| 36 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.7 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.7 | |
| 40 | ME → USER | Display "Call Wait"<br>Play a standard supervisory call waiting tone for a duration of 5 s | |
| 41 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.7 | [Command performed successfully] |
| 42 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.8 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.8 | |
| 46 | ME → USER | Display "Ring Tone"<br>Play a standard supervisory ringing tone for duration of 5 s | |
| 47 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.8 | [Command performed successfully] |
| 48 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 49 | USER → ME | Set up a voice call | [ User dials 123456789 to connect to the network manually] |
| 50 | ME → USS | Establish voice call | [Voice call is established] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.9 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.9 | |
| 54 | ME → USER | Display "Dial Tone"<br>Superimpose the standard supervisory dial tone on the audio downlink for the duration of 5 s | |
| 55 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.9 | [Command performed successfully] |
| 56 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 57 | USER → ME | The user ends the call | |
| 58 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.10 | |
| 59 | ME → UICC | FETCH | |
| 60 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.10 | |

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 61 | ME → USER | Display "This command instructs the ME to play an audio tone. Upon receiving this command, the ME shall check if it is currently in, or in the process of setting up (SET-UP message sent to the network, see GSM"04.08"(8)), a speech call. - If the ME I" Play a general beep | |
| 62 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.10a<br>or<br>TERMINAL RESPONSE: PLAY TONE 1.1.10b | [Command performed successfully]<br>or<br>[Command beyond ME's capabilities] |
| 63 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.11 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.11 | |
| 67 | ME → USER | Display "Beep" Play a ME proprietary general beep | |
| 68 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.11a<br>Or<br>TERMINAL RESPONSE: PLAY TONE 1.1.11b | [Command performed successfully]<br>or<br>[Command beyond ME's capabilities] |
| 69 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 70 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.12 | |
| 71 | ME → UICC | FETCH | |
| 72 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.12 | |
| 73 | ME → USER | Display "Positive" Play a ME proprietary positive acknowledgement tone | |
| 74 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.12a<br>or<br>TERMINAL RESPONSE: PLAY TONE 1.1.12b | [Command performed successfully]<br>or<br>[Command beyond ME's capabilities] |
| 75 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 76 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.13 | |
| 77 | ME → UICC | FETCH | |
| 78 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.13 | |
| 79 | ME → USER | Display "Negative" Play a ME proprietary negative acknowledgement tone | |
| 80 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.13a<br>or<br>TERMINAL RESPONSE: PLAY TONE 1.1.13b | [Command performed successfully]<br>or<br>[Command beyond ME's capabilities] |
| 81 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 82 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.14 | |
| 83 | ME → UICC | FETCH | |
| 84 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.14 | |

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 85 | ME → USER | Display "Quick"<br>Play a ME proprietary general beep | |
| 86 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.14a<br>or<br>TERMINAL RESPONSE: PLAY TONE 1.1.14b | [Command performed successfully]<br>or<br>[Command beyond ME's capabilities] |
| 87 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 88 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.15 | |
| 89 | ME → UICC | FETCH | |
| 90 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.15 | |
| 91 | ME → USER | Display "<ABORT>"<br>Play an ME Error / Special information tone until user aborts this command (the command shall be aborted by the user within 1 minute) | |
| 92 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.15 | [Proactive UICC session terminated by the user] |
| 93 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 94 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.1.16 | |
| 95 | ME → UICC | FETCH | |
| 96 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.1.16 | [No alpha identifier, no tone tag, no duration tag] |
| 97 | ME → User | ME plays general beep, or if not supported any (defined by ME-manufacturer) other supported tone | [ME uses default duration defined by ME-manufacturer] |
| 98 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.1.16 | [Command performed successfully], [ME uses general beep, or if not supported any (defined by ME-manufacturer) other supported tone, uses default duration defined by ME-manufacturer] |
| 99 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

For coding, see ETSI TS 102 384 [26] in subclause 27.22.4.5.1.4.2, Expected Sequence 1.1.

#### 27.22.4.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.4.5.2 PLAY TONE (UCS2 display in Cyrillic)

#### 27.22.4.5.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.2.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

#### 27.22.4.5.2.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

#### 27.22.4.5.2.4 Method of test

##### 27.22.4.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.2.4.2 Procedure

**Expected Sequence 2.1 (PLAY TONE, character set from UCS2 alphabet in Russian, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.2.4.2, Expected Sequence 2.1.

#### 27.22.4.5.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.5.3 PLAY TONE (display of Icon)

#### 27.22.4.5.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.3.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8 and clause 8.31.

#### 27.22.4.5.3.3 Test purpose

To verify that the ME plays an audio tone of a type and duration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

To verify that the ME displays the icon contained in the PLAY TONE proactive UICC command.

#### 27.22.4.5.3.4 Method of test

##### 27.22.4.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.3.4.2 Procedure

**Expected Sequence 3.1A (PLAY TONE, Basic icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.1A.

**Expected Sequence 3.1B (PLAY TONE, Basic icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.1B.

**Expected Sequence 3.2A (PLAY TONE, Basic icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.2A.

**Expected Sequence 3.2B (PLAY TONE, Basic icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.2B.

**Expected Sequence 3.3A (PLAY TONE, Colour icon, self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.3A.

**Expected Sequence 3.3B (PLAY TONE, Colour icon, self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.3B.

**Expected Sequence 3.4A (PLAY TONE, Colour icon, non self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.4A.

**Expected Sequence 3.4B (PLAY TONE, Colour icon, non self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.3.4.2, Expected Sequence 3.4B.

27.22.4.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.4B.

## 27.22.4.5.4 PLAY TONE (Support of Text Attribute)

### 27.22.4.5.4.1 PLAY TONE (Support of Text Attribute – Left Alignment)

#### 27.22.4.5.4.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.1.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.1.3 Test purpose

To verify that the ME displays the text formatted according to the left alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.1.4 Method of test

27.22.4.5.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.1.4.2 Procedure

**Expected Sequence 4.1 (PLAY TONE, Text Attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.1.4.2, Expected Sequence 4.1.

27.22.4.5.4.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.1.

27.22.4.5.4.2 PLAY TONE (Support of Text Attribute – Center Alignment)

27.22.4.5.4.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.2.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

27.22.4.5.4.2.3 Test purpose

To verify that the ME displays the text formatted according to the center alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.2.4 Method of test

27.22.4.5.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.2.4.2 Procedure

**Expected Sequence 4.2 (PLAY TONE, Text Attribute – Centre Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.2.4.2, Expected Sequence 4.2.

27.22.4.5.4.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.2.

#### 27.22.4.5.4.3 PLAY TONE (Support of Text Attribute – Right Alignment)

##### 27.22.4.5.4.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.3.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.3.3 Test purpose

To verify that the ME displays the text formatted according to the right alignment text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.3.4 Method of test

###### 27.22.4.5.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.3.4.2 Procedure

**Expected Sequence 4.3 (PLAY TONE, Text Attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.3.4.2, Expected Sequence 4.3.

##### 27.22.4.5.4.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.3.

#### 27.22.4.5.4.4 PLAY TONE (Support of Text Attribute – Large Font Size)

##### 27.22.4.5.4.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.4.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.4.3 Test purpose

To verify that the ME displays the text formatted according to the large font size text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.4.4 Method of test

27.22.4.5.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.4.4.2 Procedure

**Expected Sequence 4.4 (PLAY TONE, Text Attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.4.4.2, Expected Sequence 4.4.

27.22.4.5.4.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.4.

27.22.4.5.4.5 PLAY TONE (Support of Text Attribute – Small Font Size)

27.22.4.5.4.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.5.4.5.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

27.22.4.5.4.5.3 Test purpose

To verify that the ME displays the text formatted according to the small font size text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

27.22.4.5.4.5.4 Method of test

27.22.4.5.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.5.4.5.4.2 Procedure

**Expected Sequence 4.5 (PLAY TONE, Text Attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.5.4.2, Expected Sequence 4.5.

27.22.4.5.4.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.5.

#### 27.22.4.5.4.6 PLAY TONE (Support of Text Attribute – Bold On)

##### 27.22.4.5.4.6.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.6.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.6.3 Test purpose

To verify that the ME displays the text formatted according to the bold text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.6.4 Method of test

###### 27.22.4.5.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.6.4.2 Procedure

**Expected Sequence 4.6 (PLAY TONE, Text Attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.6.4.2, Expected Sequence 4.6.

##### 27.22.4.5.4.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.6.

#### 27.22.4.5.4.7 PLAY TONE (Support of Text Attribute – Italic On)

##### 27.22.4.5.4.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.7.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.7.3 Test purpose

To verify that the ME displays the text formatted according to the italic text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.5.4.7.4 Method of test

##### 27.22.4.5.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.4.7.4.2 Procedure

**Expected Sequence 4.7 (PLAY TONE, Text Attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.7.4.2, Expected Sequence 4.7.

#### 27.22.4.5.4.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.7.

### 27.22.4.5.4.8 PLAY TONE (Support of Text Attribute – Underline On)

#### 27.22.4.5.4.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.4.8.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

#### 27.22.4.5.4.8.3 Test purpose

To verify that the ME displays the text formatted according to the underline text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.5.4.8.4 Method of test

##### 27.22.4.5.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.4.8.4.2 Procedure

**Expected Sequence 4.8 (PLAY TONE, Text Attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.8.4.2, Expected Sequence 4.8.

#### 27.22.4.5.4.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.8.

#### 27.22.4.5.4.9 PLAY TONE (Support of Text Attribute – Strikethrough On)

##### 27.22.4.5.4.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.9.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.9.3 Test purpose

To verify that the ME displays the text formatted according to the strikethrough text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

##### 27.22.4.5.4.9.4 Method of test

###### 27.22.4.5.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.5.4.9.4.2 Procedure

**Expected Sequence 4.9 (PLAY TONE, Text Attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.9.4.2, Expected Sequence 4.9.

##### 27.22.4.5.4.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.9.

#### 27.22.4.5.4.10 PLAY TONE (Support of Text Attribute – Foreground and Background Colour)

##### 27.22.4.5.4.10.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.5.4.10.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.5, clause 6.6.5, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.16, clause 8.8, clause 8.31 and clause 8.70.

##### 27.22.4.5.4.10.3 Test purpose

To verify that the ME displays the text formatted according to the foreground and background colour text attribute configuration contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.5.4.10.4 Method of test

##### 27.22.4.5.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.4.10.4.2 Procedure

**Expected Sequence 4.10 (PLAY TONE, Text Attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.4.10.4.2, Expected Sequence 4.10.

#### 27.22.4.5.4.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.10.

### 27.22.4.5.5 PLAY TONE (UCS2 display in Chinese)

#### 27.22.4.5.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.5.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.5.5.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

#### 27.22.4.5.5.4 Method of test

##### 27.22.4.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.5.4.2 Procedure

**Expected Sequence 5.1 (PLAY TONE, character set from UCS2 alphabet in Chinese, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.5.4.2, Expected Sequence 5.1.

#### 27.22.4.5.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.5.6 PLAY TONE (UCS2 display in Katakana)

#### 27.22.4.5.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.5.6.2 Conformance requirement

The ME shall support the PLAY TONE command as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.3, clause 6.6.3, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.16 and clause 8.8.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.5.6.3 Test purpose

To verify that the ME displays the text contained in the PLAY TONE proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME plays the requested audio tone through the earpiece.

#### 27.22.4.5.6.4 Method of test

##### 27.22.4.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.5.6.4.2 Procedure

**Expected Sequence 6.1 (PLAY TONE, with UCS2 in Katakana, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.5.6.4.2, Expected Sequence 6.1.

#### 27.22.4.5.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.6 POLL INTERVAL

### 27.22.4.6.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.6.2 Conformance requirement

The ME shall support the POLL INTERVAL command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.6, clause 6.6.6, clause 5.2, clause 8.6, clause 8.7 and clause 8.8.

#### 27.22.4.6.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the POLL INTERVAL proactive UICC command.

To verify that the ME gives a valid response to the polling interval requested by the UICC.

To verify that the ME sends STATUS commands to the UICC at an interval no longer than the interval negotiated by the UICC.

#### 27.22.4.6.4 Method of test

##### 27.22.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.6.4.2 Procedure

See ETSI TS 102 384 [26] in subclause 27.22.4.6.4.2, Expected Sequence 1.1.

NOTE: If the requested poll interval is not supported by the ME, the ME is allowed to use a different one as stated in TS 31.111 [15], subclause 6.4.6.

#### 27.22.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.4.7 REFRESH

#### 27.22.4.7.1 REFRESH (normal)

##### 27.22.4.7.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.7.1.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.7, clause 6.6.13, clause 5.2, clause 8.6, clause 8.7 and clause 8.18.

Consequently the ME shall support the USIM Initialization procedure as defined in:

- TS 31.102 [14] clause 5.1.1.2 and ETSI TS 102 221[13] clause 11.1.2

##### 27.22.4.7.1.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier. This shall require the ME to perform:

- the UICC and USIM initialization,
- a re-read of the contents and structure of the EFs on the UICC that have been notified as changed and are either part of initialization or used during the test,
- a restart of the card session,
- a successfull return of the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

27.22.4.7.1.4 Method of test

27.22.4.7.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table..

The elementary files are coded as Toolkit default except for expected sequence 1.3.

For expected sequence 1.3 the global phonebook shall be present.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

These values might be overwritten with values defined in the expected sequences itself.

Prior to the execution of expected sequence 1.2 the FDN service shall be enabled.

27.22.4.7.1.4.2 Procedure

**Expected Sequence 1.1 (REFRESH, USIM Initialization)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC→ ME | PROACTIVE COMMAND PENDING: REFRESH 1.1.1 | [To inform the ME that FDN becomes enabled] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.1.1 | |
| 4 | UICC | EF EST contents states FDN enabled | [New EF EST value: 01] |
| 5 | ME → UICC | USIM Initialization including send STATUS[P1='01'] | [ME performs USIM initialization in accordance with TS 31.111 [15] clause 6.4.7] |
| 6 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.1.1A<br>Or<br>TERMINAL RESPONSE: REFRESH 1.1.1B | [normal ending]<br><br>[additional EFs read] |
| 7 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 8 | USER → ME | Call setup to "321" | |
| 9 | ME → USER | Call set up not allowed | |
| 10 | USER → ME | Call setup to "123" | |
| 11 | ME → USS | Setup | Called party BCD number shall be "123" |

PROACTIVE COMMAND: REFRESH 1.1.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Initialization

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 01 | 03 | 82 | 02 | 81 | 82 | |

TERMINAL RESPONSE: REFRESH 1.1.1A

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: USIM Initialization
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 03 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

TERMINAL RESPONSE: REFRESH 1.1.1B

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: USIM Initialization
Device identities
Source device: ME
Destination device: UICC
Result
General Result: REFRESH performed with additional EFs read

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 03 | 82 | 02 | 82 | 81 | 83 | 01 | 03 |

**Expected Sequence 1.2 (REFRESH, File Change Notification)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: REFRESH 1.2.1 | [To inform the ME that EF FDN will be in an updated state, FDN service already enabled] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.2.1 | |
| 4 | UICC | Update EF FDN RECORD 1 | [EF FDN record 1 updated to contain the dialling string "0123456789"] |
| 5 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.2.1A<br>Or<br>TERMINAL RESPONSE: REFRESH 1.2.1B | [normal ending]<br><br>[additional EFs read] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | USER → ME | Call setup to "123" | |
| 8 | ME → USER | Call set up not allowed | |
| 9 | USER → ME | Call setup to "0123456789" | |
| 10 | ME → USS | Setup | Called party BCD number shall be "0123456789" |

PROACTIVE COMMAND: REFRESH 1.2.1

Logically:

Command details

Command number: 1
Command type: REFRESH
Command qualifier: File Change Notification
Device identities
Source device: UICC
Destination device: ME
File List: EF FDN

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 12 | 81 | 03 | 01 | 01 | 01 | 82 | 02 | 81 | 82 | 92 |
| | 07 | 01 | 3F | 00 | 7F | FF | 6F | 3B | | | | |

TERMINAL RESPONSE: REFRESH 1.2.1A

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: File Change Notification
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

TERMINAL RESPONSE: REFRESH 1.2.1B

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: File Change Notification
Device identities
Source device: ME
Destination device: UICC
Result
General Result: REFRESH performed with additional EFs read

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 03 |

**Expected Sequence 1.3 (REFRESH, USIM Initialization and File Change Notification)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: REFRESH 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.3.1 | |
| 4 | UICC | Update EF ADN in the global phonebook | [EF ADN entry 1 of the global phonebook to contain the the new and previously unused alpha identifier "Changed" |
| 5 | ME → UICC | USIM Initialization including sending STATUS [P1='01'] | [ME performs USIM initialization in accordance with TS 31.111 [15] clause 6.4.7] |
| 6 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.3.1A<br>Or<br>TERMINAL RESPONSE: REFRESH 1.3.1B | [normal ending]<br><br>[additional EFs read] |
| 7 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 8 | USER → ME | Use an MMI dependent procedure to display the entry with the alpha identifier "Changed" stored in record 1 of EF ADN in the global phonebook | [To ensure that EF ADN in the global phonebook has been read after issuing the Refresh command] |
| 9 | ME → USER | The ME shall display the alpha identifier "Changed" for record 1 of EF ADN in the global phonebook | |

PROACTIVE COMMAND: REFRESH 1.3.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Initialization and File Change Notification

Device identities
- Source device: UICC
- Destination device: ME
- File List: ADN in the global phonebook

Coding:

| BER-TLV: | D0 | 12 | 81 | 03 | 01 | 01 | 02 | 82 | 02 | 81 | 82 | 92 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | Note 1 | | | | | | | | | | | |

Note 1: Length and data of the file list TLV depend on the card configuration used in this test. The global phonebook shall be used. The number of changed files shall be set to '01'.

TERMINAL RESPONSE: REFRESH 1.3.1A

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Initialization and File Change Notification

Device identities
- Source device: ME
- Destination device: UICC

Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

TERMINAL RESPONSE: REFRESH 1.3.1B

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: USIM Initialization and File Change Notification
Device identities
Source device: ME
Destination device: UICC
Result
General Result: REFRESH performed with additional EFs read

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 03 |

**Expected Sequence 1.4 (REFRESH, USIM Initialization and Full File Change Notification)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: REFRESH 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.4.1 | |
| 4 | UICC | EF EST contents states FDN enabled | [New EF EST value: 01] |
| 5 | UICC | Update EF FDN | [EF FDN record 1 updated to contain the dialling string "0123456789"] |
| 6 | ME → UICC | USIM Initialization including send STATUS[P1='01'] | [ME performs USIM initialization in accordance with TS 31.111 [15] clause 6.4.7] |
| 7 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.4.1A<br>Or<br>TERMINAL RESPONSE: REFRESH 1.4.1B | [normal ending]<br><br>[additional EFs read] |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | Call setup to "321" | |
| 10 | ME → USER | Call set up not allowed | |
| 11 | USER → ME | Call setup to "0123456789" | |
| 12 | ME → USS | Setup | Called party BCD number shall be "0123456789" |

PROACTIVE COMMAND: REFRESH 1.4.1

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: USIM Initialization and Full File Change Notification

Device identities
Source device: UICC
Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 01 | 00 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: REFRESH 1.4.1A

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: USIM Initialization and Full file Change Notification
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

TERMINAL RESPONSE: REFRESH 1.4.1B

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: USIM Initialization and full File change Notification
Device identities
Source device: ME
Destination device: UICC
Result
General Result: REFRESH performed with additional EFs read

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 03 |

**Expected Sequence 1.5 (REFRESH, UICC Reset)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC→ ME | PROACTIVE COMMAND PENDING: REFRESH 1.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.5.1 | |
| 4 | ME → UICC | STATUS[P1='02'] | ME indicates to USIM that the termination procedure is starting |
| 5 | ME → UICC | ME resets the UICC, performs USIM initialisation, including send STATUS[P1='01'] and no TERMINAL RESPONSE shall be sent | |

PROACTIVE COMMAND: REFRESH 1.5.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: UICC Reset

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 01 | 04 | 82 | 02 | 81 | 82 | |

**Expected Sequence 1.6 (REFRESH, USIM Initialization after SMS-PP data download)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | ME | The ME shall be in its normal idle mode | [Start a sequence to verify that the ME returns the RP-ACK message back to the USS, if the UICC responds with '90 00'] |
| 2 | USS → ME | SMS-PP Data Download Message 1.6.1 | |
| 3 | ME → USER | The ME shall not display the message or alert the user of a short message waiting | |
| 4 | ME → USS | ENVELOPE: SMS-PP DOWNLOAD 1.6.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: REFRESH 1.1.1 | |
| 6 | ME → USS | RP-ACK | |
| 7 | ME → UICC | FETCH | |
| 8 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.1.1 | |
| 9 | UICC | EF EST contents states FDN enabled | [New EF EST value: 01] |
| 10 | ME → UICC | USIM Initialization including send STATUS[P1='01'] | [ME performs USIM initialization in accordance with TS 31.111 [15] clause 6.4.7] |
| 11 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.1.1A<br>Or<br>TERMINAL RESPONSE: REFRESH 1.1.1B | [normal ending]<br><br>[additional EFs read] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | USER → ME | Call setup to "321" | |
| 14 | ME → USER | Call set up not allowed | |
| 15 | USER → ME | Call setup to "123" | |
| 16 | ME → USS | Setup | Called party BCD number shall be "123" |

SMS-PP (Data Download) Message 1.6.1

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-DELIVER |
| TP-MMS | No more messages waiting for the MS in this SC |
| TP-RP | TP-Reply-Path is not set in this SMS-DELIVER |
| TP-UDHI | TP-UD field contains only the short message |
| TP-SRI | A status report will not be returned to the SME |
| TP-OA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "1234" |
| TP-PID | (U)SIM Data download |
| TP-DCS | |
| Coding Group | General Data Coding |
| Compression | Text is uncompressed |
| Message Class | Class 2 (U)SIM Specific Message |
| Alphabet | 8 bit data |
| TP-SCTS: | 01/01/98 00:00:00 +0 |
| TP-UDL | 13 |
| TP-UD | "Short Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 04 | 04 | 91 | 21 | 43 | 7F | 16 | 89 | 10 | 10 | 00 | 00 |
| | 00 | 00 | 0D | 53 | 68 | 6F | 72 | 74 | 20 | 4D | 65 | 73 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 73 | 61 | 67 | 65 | | | | | | | | |

ENVELOPE: SMS-PP DOWNLOAD 1.6.1

Logically:

SMS-PP Download
- Device identities
- Source device: Network
- Destination device: UICC
- Address
- TON International number
- NPI "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"
- SMS TPDU
- TP-MTI SMS-DELIVER
- TP-MMS No more messages waiting for the MS in this SC
- TP-RP TP-Reply-Path is not set in this SMS-DELIVER
- TP-UDHI TP-UD field contains only the short message
- TP-SRI A status report will not be returned to the SME
- TP-OA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "1234"
- TP-PID (U)SIM Data download
- TP-DCS
- Coding Group General Data Coding
- Compression Text is uncompressed
- Message Class Class 2 (U)SIM Specific Message
- Alphabet 8 bit data
- TP-SCTS: 01/01/98 00:00:00 +0
- TP-UDL 13
- TP-UD "Short Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D1 | 2D | 82 | 02 | 83 | 81 | 06 | 09 | 91 | 11 | 22 | 33 |
| | 44 | 55 | 66 | 77 | F8 | 8B | 1C | 04 | 04 | 91 | 21 | 43 |
| | 7F | 16 | 89 | 10 | 10 | 00 | 00 | 00 | 00 | 0D | 53 | 68 |
| | 6F | 72 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | |

**Expected Sequence 1.7 (REFRESH, USIM Application Reset)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC→ ME | PROACTIVE COMMAND PENDING: REFRESH 1.7.1 | [To inform the ME that FDN becomes enabled] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.7.1 | No UICC reset shall be performed between steps 3 and 9. |
| 4 | ME → UICC | STATUS[P1='02'] | ME indicates to USIM that the termination procedure is starting |
| 5 | ME → UICC | Select AID=USIM (P2='44') OR (P2='4C') | Application termination |
| 6 | UICC | EF EST contents states FDN enabled | [New EF EST value: 01] |
| 7 | ME → UICC | USIM Initialization, including send STATUS[P1='01'] | [ME performs USIM initialization] |
| 8 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.7.1 | [normal ending] |
| 9 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 10 | USER → ME | Call setup to "321" | |
| 11 | ME → USER | Call set up not allowed | |
| 12 | USER → ME | Call setup to "123" | |
| 13 | ME → USS | Setup | Called party BCD number shall be "123" |
| 14 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 15 | USER → ME | The user ends the call after a few seconds. | |

PROACTIVE COMMAND: REFRESH 1.7.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Application Reset

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 01 | 05 | 82 | 02 | 81 | 82 | |

TERMINAL RESPONSE: REFRESH 1.7.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Application Reset

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 05 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.7.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

### 27.22.4.7.2 REFRESH (IMSI changing procedure)

#### 27.22.4.7.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.7.2.2 Conformance requirement

The ME shall support the REFRESH command as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.7, clause 6.4.7.1, clause 6, clause 6.6.13, clause 5.2, clause 8.6, clause 8.7 and clause 8.18.

Additionally the ME shall support the USIM Initialization and USIM application closure procedure as defined in:

- TS 31.102 [14] clause 5.1.2 and Annex I.

#### 27.22.4.7.2.3 Test purpose

To verify that the ME performs the Proactive Command – REFRESH in accordance with the Command Qualifier and the IMSI changing procedure. This may require the ME to perform:

- the USIM initialization
- a re-read of the contents and structure of the IMSI on the USIM
- a restart of the card session
- a successful return of the result of the execution of the command in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.7.2.4 Method of test

##### 27.22.4.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table..

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ATT flag broadcast in the SYSTEM INFORMATION BLOCK TYPE 1 on the BCCH is set to "UEs shall apply IMSI attach and detach procedure" for Expected Sequences 2.2.

##### 27.22.4.7.2.4.2 Procedure

**Expected Sequence 2.1 (REFRESH, UICC Reset for IMSI Changing procedure)**

TBD

**Expected Sequence 2.2 (REFRESH, USIM Application Reset for IMSI Changing procedure )**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC→ ME | PROACTIVE COMMAND PENDING: REFRESH 2.2.1 | [To inform the ME that IMSI has changed] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: REFRESH 2.2.1 | |
| 4 | ME → UICC | STATUS[P1='02'] | ME indicates to USIM that the termination procedure is starting |
| 5 | ME → UICC | | Application termination |
| 6 | ME→USS | IMSI DETACH INDICATION and/or DETACH REQUEST | Indicates IMSI detach and/or GPRS detach, depending on if the ME is CS and/or PS registered according to its capabilities |
| 7 | UICC | Update EF IMSI and EF LOCI | [Update the content of EF IMSI to "001010123456786", Temporary Mobile Subscriber Identity (TMSI) in EF LOCI be set to "FF FF FF FF"] |
| 8 | ME → UICC | SELECT AID=USIM (P2='0x') | Application selection |
| 9 | ME → UICC | USIM Initialization, including send STATUS[P1='01'] | [ME performs USIM initialization] |
| 10 | ME → UICC | TERMINAL RESPONSE: REFRESH 2.2.1 | [normal ending] |
| 11 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 12 | ME → USS | LOCATION UPDATING REQUEST and/or ATTACH REQUEST | The ME will again register in CS and/or PS depending on its capabilities |
| 13 | USS → ME | LOCATION UPDATING ACCEPT and/or ATTACH ACCEPT | |
| 14 | ME → USS | TMSI REALLOCATION COMPLETE and/or ATTACH COMPLETE | |

PROACTIVE COMMAND: REFRESH 2.2.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Application Reset

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 01 | 05 | 82 | 02 | 81 | 82 |
|---|---|---|---|---|---|---|---|---|---|---|---|

TERMINAL RESPONSE: REFRESH 2.2.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Application Reset

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 05 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 2.3 (REFRESH, 3G Session Reset for IMSI Changing procedure)**

TBD

**Expected Sequence 2.4 (REFRESH, reject 3G Session Reset for IMSI Changing procedure during call)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USER → ME | MO Call setup | |
| 2 | ME → USS | Call established and maintained | |
| 3 | UICC → ME | PROACTIVE COMMAND PENDING: REFRESH 2.4.1 | |
| 4 | ME → UICC | FETCH | |
| 5 | UICC → ME | PROACTIVE COMMAND: REFRESH 2.4.1 | |
| 6 | ME → UICC | TERMINAL RESPONSE: REFRESH 2.4.1A<br>Or<br>TERMINAL RESPONSE: REFRESH 2.4.1B | ME rejects REFRESH proactive command |
| 7 | UICC → ME | PROACTIVE UICC SESSION ENDED | Note: EF IMSI and EF LOCI are not updated by the UICC, see TS 31.111[15], cl. 6.4.7.1 |
| 8 | USER → ME | The MO call is terminated | |

PROACTIVE COMMAND: REFRESH 2.4.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: 3G Session Reset

Device identities
- Source device: UICC
- Destination device: ME

File list
- Number of files: 2
- File: EF IMSI
- File: EF LOCI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 18 | 81 | 03 | 01 | 01 | 06 | 82 | 02 | 81 | 82 | 92 |
| | 0D | 02 | 3F | 00 | 7F | FF | 6F | 07 | 3F | 00 | 7F | FF |
| | 6F | 7E | | | | | | | | | | |

TERMINAL RESPONSE: REFRESH 2.4.1A

Logically:

Command details

Command number: 1
Command type: REFRESH
Command qualifier: 3G Session Reset
Device identities
Source device: ME
Destination device: UICC
Result
General Result: ME currently unable to process command
Additional information on result: ME currently busy on call

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 06 | 82 | 02 | 82 | 81 | 83 | 02 | 20 |
| | 02 | | | | | | | | | | | |

TERMINAL RESPONSE: REFRESH 2.4.1B

Logically:

Command details
Command number: 1
Command type: REFRESH
Command qualifier: 3G Session Reset
Device identities
Source device: ME
Destination device: UICC
Result
General Result: ME currently unable to process command
Additional information on result: Screen is busy

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 06 | 82 | 02 | 82 | 81 | 83 | 02 | 20 |
| | 01 | | | | | | | | | | | |

#### 27.22.4.7.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

## 27.22.4.8 SET UP MENU and ENVELOPE MENU SELECTION

### 27.22.4.8.1 SET UP MENU (normal) and ENVELOPE MENU SELECTION

#### 27.22.4.8.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.1.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.

#### 27.22.4.8.1.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

#### 27.22.4.8.1.4 Method of test

##### 27.22.4.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.1.4.2 Procedure

**Expected Sequence 1.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (SET UP MENU, Large Menu with many items or with large items or with Large Alpha Identifier)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.1.4.2, Expected Sequence 1.2.

The following table details the test requirements with relation to the tested features:

| | Proactive UICC Command Facilities | | |
|---|---|---|---|
| **Proactive UICC Command Number** | **Alpha Identifier Length** | **Number of items** | **Maximum length of item** |
| 1.1.1 | 12 | 4 | 6 |
| 1.1.2 | 12 | 2 | 3 |
| 1.1.3 | 10 | 0 | - |
| 1.2.1 | 10 | 30 | 8 |
| 1.2.2 | 10 | 7 | 37 |
| 1.2.3 | 235 | 1 | 1 |

#### 27.22.4.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1 and in expected sequence 1.2.

### 27.22.4.8.2 SET UP MENU (help request support) and ENVELOPE MENU SELECTION

#### 27.22.4.8.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- TS 31.111 [15] clause 8.21.

#### 27.22.4.8.2.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that when the help is available for the command and the user has indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.2.4 Method of test

##### 27.22.4.8.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.2.4.2 Procedure

**Expected Sequence 2.1 (SET UP MENU and MENU SELECTION, with Help Request, Replace and Remove a Toolkit Menu)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.2.4.2, Expected Sequence 2.1.

#### 27.22.4.8.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.8.3 SET UP MENU (next action support) and ENVELOPE MENU SELECTION

#### 27.22.4.8.3.1 Definition and applicability

See clause 3.2.2.

If the UICC provides an Items Next Action Indicator data object, the comprehension required flag shall be set to '0'.

#### 27.22.4.8.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- TS 31.111 [15] clause 8.24.

#### 27.22.4.8.3.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the next action indicator is supported.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.3.4 Method of test

##### 27.22.4.8.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.3.4.2 Procedure

**Expected Sequence 3.1 (SET UP MENU, next action indicator "Send SM", "Set Up Call", "Launch Browser", "Provide Local Information", successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.3.4.2, Expected Sequence 3.1.

#### 27.22.4.8.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.8.4 SET UP MENU (display of icons) and ENVELOPE MENU SELECTION

#### 27.22.4.8.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clause 6.5.4, 8.31 and 8.32.

#### 27.22.4.8.4.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that icons are displayed with the command Set Up Menu in the Alpha Identifier and Items Data Objects. To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.4.4 Method of test

##### 27.22.4.8.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.4.4.2 Procedure

**Expected Sequence 4.1A (SET UP MENU, BASIC ICON NOT SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.1A.

**Expected Sequence 4.1B (SET UP MENU, BASIC ICON NOT SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.1B.

**Expected Sequence 4.2A (SET UP MENU, BASIC ICON SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.2A.

**Expected Sequence 4.2B (SET UP MENU, BASIC ICON SELF EXPLANATORY in ALPHA ID and ITEMS DATA OBJECTS, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.4.4.2, Expected Sequence 4.2B.

27.22.4.8.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1A to 4.2B.

## 27.22.4.8.5 SET UP MENU (soft keys support) and ENVELOPE MENU SELECTION

### 27.22.4.8.5.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.8.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1.

### 27.22.4.8.5.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that if soft key preferred is indicated in the command details and soft key for SET UP MENU is supported by the ME and the number of icon items does not exceed the number of soft keys available, then the ME displays those icons as soft key.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

### 27.22.4.8.5.4 Method of test

#### 27.22.4.8.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.5.4.2 Procedure

**Expected Sequence 5.1 (SET UP MENU, SOFT KEY PREFERRED, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.5.4.2, Expected Sequence 5.1.

#### 27.22.4.8.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.8.6 SET UP MENU (support of Text Attribute) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.1 SET UP MENU (support of Text Attribute – Left Alignment) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.1.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.1.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the left alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.1.4 Method of test

#### 27.22.4.8.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.8.6.1.4.2 Procedure

**Expected Sequence 6.1 (SET UP MENU, Text Attribute – Left Alignment, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.1.4.2, Expected Sequence 6.1.

#### 27.22.4.8.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

#### 27.22.4.8.6.2 SET UP MENU (support of Text Attribute – Center Alignment) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.2.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the center alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

##### 27.22.4.8.6.2.4 Method of test

###### 27.22.4.8.6.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

###### 27.22.4.8.6.2.4.2 Procedure

**Expected Sequence 6.2 (SET UP MENU, Text Attribute – Center Alignment, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.2.4.2, Expected Sequence 6.2.

##### 27.22.4.8.6.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.2.

#### 27.22.4.8.6.3 SET UP MENU (support of Text Attribute – Right Alignment) and ENVELOPE MENU SELECTION

##### 27.22.4.8.6.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.8.6.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.8.6.3.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the right alignment text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.3.4 Method of test

##### 27.22.4.8.6.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.3.4.2 Procedure

**Expected Sequence 6.3 (SET UP MENU, Text Attribute – Right Alignment, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.3.4.2, Expected Sequence 6.3.

#### 27.22.4.8.6.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.3.

### 27.22.4.8.6.4 SET UP MENU (support of Text Attribute – Large Font Size) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.4.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the large font size text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.4.4 Method of test

##### 27.22.4.8.6.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.4.4.2 Procedure

**Expected Sequence 6.4 (SET UP MENU, Text Attribute – Large Font Size, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.4.4.2, Expected Sequence 6.4.

27.22.4.8.6.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.4.

27.22.4.8.6.5 SET UP MENU (support of Text Attribute – Small Font Size) and ENVELOPE MENU SELECTION

27.22.4.8.6.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.8.6.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.8.6.5.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the with small font size text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

27.22.4.8.6.5.4 Method of test

27.22.4.8.6.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.8.6.5.4.2 Procedure

**Expected Sequence 6.5 (SET UP MENU, Text Attribute – Small Font Size, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.5.4.2, Expected Sequence 6.5.

27.22.4.8.6.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.5.

27.22.4.8.6.6 SET UP MENU (support of Text Attribute – Bold On) and ENVELOPE MENU SELECTION

27.22.4.8.6.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.6.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.6.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.6.4 Method of test

##### 27.22.4.8.6.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.6.4.2 Procedure

**Expected Sequence 6.6 (SET UP MENU, Text Attribute – Bold On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.6.4.2, Expected Sequence 6.6.

#### 27.22.4.8.6.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.6.

### 27.22.4.8.6.7 SET UP MENU (support of Text Attribute – Italic On) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.7.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.7.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.7.4 Method of test

##### 27.22.4.8.6.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.7.4.2 Procedure

**Expected Sequence 6.7 (SET UP MENU, Text Attribute – Italic On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.7.4.2, Expected Sequence 6.7.

#### 27.22.4.8.6.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.7.

### 27.22.4.8.6.8 SET UP MENU (support of Text Attribute – Underline On) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.8.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.8.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.8.4 Method of test

##### 27.22.4.8.6.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.8.4.2 Procedure

**Expected Sequence 6.8 (SET UP MENU, Text Attribute – Underline On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.8.4.2, Expected Sequence 6.8.

#### 27.22.4.8.6.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.8.

### 27.22.4.8.6.9 SET UP MENU (support of Text Attribute – Strikethrough On) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.9.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.9.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.9.4 Method of test

##### 27.22.4.8.6.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.9.4.2 Procedure

**Expected Sequence 6.9 (SET UP MENU, Text Attribute – Strikethrough On, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.9.4.2, Expected Sequence 6.9.

#### 27.22.4.8.6.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.9.

### 27.22.4.8.6.10 SET UP MENU (support of Text Attribute – Foreground and Background Colour) and ENVELOPE MENU SELECTION

#### 27.22.4.8.6.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.6.10.2 Conformance requirement

Requirements are the same as in clause 27.22.4.8.1.1, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.8.6.10.3 Test purpose

To verify that the ME correctly integrates the menu items contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that text is displayed according to the text attribute configuration within the command Set Up Menu and the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

#### 27.22.4.8.6.10.4 Method of test

##### 27.22.4.8.6.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.6.10.4.2 Procedure

**Expected Sequence 6.10 (SET UP MENU, Text Attribute – Foreground and Background Colour, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.6.10.4.2, Expected Sequence 6.10.

#### 27.22.4.8.6.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.10.

### 27.22.4.8.7 SET UP MENU (UCS2 display in Cyrillic) and ENVELOPE MENU SELECTION

#### 27.22.4.8.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.7.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in ISO/IEC 10646 [17].

#### 27.22.4.8.7.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

#### 27.22.4.8.7.4 Method of test

##### 27.22.4.8.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.7.4.2 Procedure

**Expected Sequence 7.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 in Cyrillic Characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.7.4.2, Expected Sequence 7.1.

#### 27.22.4.8.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.8.8 SET UP MENU (UCS2 display in Chinese) and ENVELOPE MENU SELECTION

#### 27.22.4.8.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.8.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.8.8.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

#### 27.22.4.8.8.4 Method of test

##### 27.22.4.8.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.8.4.2 Procedure

**Expected Sequence 8.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 – Chinese characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.8.4.2, Expected Sequence 8.1.

#### 27.22.4.8.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

### 27.22.4.8.9 SET UP MENU (UCS2 display in Katakana) and ENVELOPE MENU SELECTION

#### 27.22.4.8.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.8.9.2 Conformance requirement

The ME shall support the SET UP MENU command as defined in:

- TS 31.111 [15] clause 5, clause 6.4.8, clause 6.6.7, clause 6.8, clause 6.11, clause 8.6, clause 8.7, clause 8.2, clause 8.9 and clause 9.4.

The ME shall support MENU SELECTION as defined in:

- TS 31.111 [15] clause 4.4, clause 5.2, clause 6.4.8, clause 6.9, clause 7.2, clause 8.7 and clause 8.10.
- Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.8.9.3 Test purpose

To verify that the ME correctly integrates the menu items in UCS2 coding contained in the SET UP MENU proactive UICC command, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME replaces the current list of menu items with the list of menu items contained in the SET UP MENU command.

To verify that the ME removes the current list of menu items following receipt of a SET UP MENU command with no items.

To verify that the ME correctly passes the identifier of the selected menu item to the UICC using the ENVELOPE (MENU SELECTION) command.

To verify that when the help is available for the command and the user gas indicated the need to get help information on one of the items, the ME informs properly the UICC about an HELP REQUEST, using the MENU SELECTION mechanism.

#### 27.22.4.8.9.4 Method of test

##### 27.22.4.8.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

The ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.4.8.9.4.2 Procedure

**Expected Sequence 9.1 (SET UP MENU and MENU SELECTION, without Help Request, Replace and Remove a Toolkit Menu, with UCS2 in Katakana Characters)**

See ETSI TS 102 384 [26] in subclause 27.22.4.8.9.4.2, Expected Sequence 9.1.

#### 27.22.4.8.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

## 27.22.4.9 SELECT ITEM

### 27.22.4.9.1 SELECT ITEM (mandatory features for ME supporting SELECT ITEM)

#### 27.22.4.9.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.1.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.

#### 27.22.4.9.1.3 Test purpose

To verify that the ME correctly presents the set of items contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

27.22.4.9.1.4 Method of test

27.22.4.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.1.4.2 Procedure

**Expected Sequence 1.1 (SELECT ITEM, mandatory features, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (SELECT ITEM, large menu, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (SELECT ITEM, call options, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (SELECT ITEM, backward move by user, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (SELECT ITEM, "Y", successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (SELECT ITEM, Large menu, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.1.4.2, Expected Sequence 1.6.

The following table details the test commands with relation to the tested features:

| | Proactive UICC Command Facilities | | |
|---|---|---|---|
| **Proactive UICC Command SELECT ITEM Number** | **Alpha Identifier Length** | **Number of items** | **Maximum length of item** |
| 1.1 | 14 | 4 | 6 |
| 1.2 | 10 | 30 | 8 |
| 1.3 | 10 | 7 | 43 |
| 1.4 | 11 | 2 | 3 |
| 1.5 | 236 | 1 | 1 |
| 1.6 | 10 | 7 | 37 |

27.22.4.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1, 1.2, 1.3, 1.4, 1.5 and 1.6 (SELECT ITEM, mandatory features).

27.22.4.9.2 SELECT ITEM (next action support)

27.22.4.9.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.2.2 Conformance Requirement

Same as clause 27.22.4.9.1.2.

#### 27.22.4.9.2.3 Test purpose

To verify that the mobile supports next action indicator mode.

#### 27.22.4.9.2.4 Method of test

##### 27.22.4.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.2.4.2 Procedure

**Expected Sequence 2.1 (SELECT ITEM, next action indicator, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.2.4.2, Expected Sequence 2.1.

#### 27.22.4.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1

### 27.22.4.9.3 SELECT ITEM (default item support)

#### 27.22.4.9.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.3.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

#### 27.22.4.9.3.3 Test purpose

To verify that the mobile supports "default item" mode.

#### 27.22.4.9.3.4 Method of test

##### 27.22.4.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.3.4.2 Procedure

**Expected Sequence 3.1 (SELECT ITEM, default item, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.3.4.2, Expected Sequence 3.1.

#### 27.22.4.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1

### 27.22.4.9.4 SELECT ITEM (help request support)

#### 27.22.4.9.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.4.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

#### 27.22.4.9.4.3 Test purpose

To verify that the mobile supports "help request" for the command Select Item.

#### 27.22.4.9.4.4 Method of test

##### 27.22.4.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.4.4.2 Procedure

**Expected Sequence 4.1 (SELECT ITEM, help request, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.4.4.2, Expected Sequence 4.1.

#### 27.22.4.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1

### 27.22.4.9.5 SELECT ITEM (icons support)

#### 27.22.4.9.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.5.2 Conformance requirement

Same as clause 27.22.4.9.1.2 and TS 31.111 [15] clause 8.31 and clause 8.32.

#### 27.22.4.9.5.3 Test purpose

To verify that the mobile displays icons with the command Select Item.

#### 27.22.4.9.5.4 Method of test

##### 27.22.4.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.5.4.2 Procedure

**Expected Sequence 5.1A (SELECT ITEM, BASIC ICON NOT SELF EXPLANATORY, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.1A.

**Expected Sequence 5.1B (SELECT ITEM, BASIC ICON NOT SELF EXPLANATORY, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.1B.

**Expected Sequence 5.2A (SELECT ITEM, BASIC ICON SELF EXPLANATORY, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.2A.

**Expected Sequence 5.2B (SELECT ITEM, BASIC ICON SELF EXPLANATORY, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.5.4.2, Expected Sequence 5.2B.

27.22.4.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1A to 5.2B.

## 27.22.4.9.6 SELECT ITEM (presentation style)

27.22.4.9.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.6.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

27.22.4.9.6.3 Test purpose

To verify that the mobile supports the "presentation style" with the command Select Item.

27.22.4.9.6.4 Method of test

27.22.4.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.6.4.2 Procedure

**Expected Sequence 6.1 (SELECT ITEM, PRESENTATION AS A CHOICE OF NAVIGATION OPTIONS, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.6.4.2, Expected Sequence 6.1.

**Expected Sequence 6.2 (SELECT ITEM, PRESENTATION AS A CHOICE OF DATA VALUES, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.6.4.2, Expected Sequence 6.2.

#### 27.22.4.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequences 6.1 and 6.2.

### 27.22.4.9.7 SELECT ITEM (soft keys support)

#### 27.22.4.9.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.7.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

#### 27.22.4.9.7.3 Test purpose

To verify that the mobile supports the "soft keys" with the command Select Item.

#### 27.22.4.9.7.4 Method of test

##### 27.22.4.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.7.4.2 Procedure

**Expected Sequence 7.1 (SELECT ITEM, SELECTING USING SOFT KEYS PREFERRED, successful, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.7.4.2, Expected Sequence 7.1.

#### 27.22.4.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.9.8 SELECT ITEM (Support of "No response from user")

#### 27.22.4.9.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.8.2 Conformance requirement

Same as clause 27.22.4.9.1.2.

#### 27.22.4.9.8.3 Test purpose

To verify that after a period of user inactivity the ME returns a "No response from user" result value in the TERMINAL RESPONSE command sent to the UICC.

#### 27.22.4.9.8.4 Method of test

##### 27.22.4.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME Manufacturer shall have defined the "no response from user" period of time as declared in table A.2/4.

The USIM Simulator shall be set to that period of time.

#### 27.22.4.9.8.4.2 Procedure

**Expected Sequence 8.1 (SELECT ITEM, no response from user)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.8.4.2, Expected Sequence 8.1.

#### 27.22.4.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 8.1.

### 27.22.4.9.9 SELECT ITEM (Support of Text Attribute)

#### 27.22.4.9.9.1 SELECT ITEM (Support of Text Attribute – Left Alignment)

#### 27.22.4.9.9.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.9.1.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.9.9.1.3 Test purpose

To verify that the ME displays text formatted according to the left alignment text attribute configuration within the command Select Item.

#### 27.22.4.9.9.1.4 Method of test

#### 27.22.4.9.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.9.1.4.2 Procedure

**Expected Sequence 9.1 (SELECT ITEM, Text Attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.1.4.2, Expected Sequence 9.1.

#### 27.22.4.9.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.1.

#### 27.22.4.9.9.2 SELECT ITEM (Support of Text Attribute – Center Alignment)

##### 27.22.4.9.9.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.2.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.2.3 Test purpose

To verify that the ME displays text formatted according to the center alignment text attribute configuration within the command Select Item.

##### 27.22.4.9.9.2.4 Method of test

###### 27.22.4.9.9.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.9.9.2.4.2 Procedure

**Expected Sequence 9.2 (SELECT ITEM, Text Attribute – Center Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.2.4.2, Expected Sequence 9.2.

##### 27.22.4.9.9.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.2.

#### 27.22.4.9.9.3 SELECT ITEM (Support of Text Attribute – Right Alignment)

##### 27.22.4.9.9.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.3.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.3.3 Test purpose

To verify that the ME displays text formatted according to the right alignment text attribute configuration within the command Select Item.

##### 27.22.4.9.9.3.4 Method of test

###### 27.22.4.9.9.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.3.4.2 Procedure

**Expected Sequence 9.3 (SELECT ITEM, Text Attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.3.4.2, Expected Sequence 9.3.

27.22.4.9.9.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.3.

27.22.4.9.9.4 SELECT ITEM (Support of Text Attribute – Large Font Size)

27.22.4.9.9.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.4.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.4.3 Test purpose

To verify that the ME displays text formatted according to the large font size text attribute configuration within the command Select Item.

27.22.4.9.9.4.4 Method of test

27.22.4.9.9.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.4.4.2 Procedure

**Expected Sequence 9.4 (SELECT ITEM, Text Attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.4.4.2, Expected Sequence 9.4.

27.22.4.9.9.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.4.

27.22.4.9.9.5 SELECT ITEM (Support of Text Attribute – Small Font Size)

27.22.4.9.9.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.5.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.9.9.5.3 Test purpose

To verify that the ME displays text formatted according to the small font size text attribute configuration within the command Select Item.

#### 27.22.4.9.9.5.4 Method of test

##### 27.22.4.9.9.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.9.5.4.2 Procedure

**Expected Sequence 9.5 (SELECT ITEM, Text Attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.5.4.2, Expected Sequence 9.5.

#### 27.22.4.9.9.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.5.

### 27.22.4.9.9.6 SELECT ITEM (Support of Text Attribute – Bold On)

#### 27.22.4.9.9.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.9.6.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.9.9.6.3 Test purpose

To verify that the ME displays text formatted according to the bold text attribute configuration within the command Select Item.

#### 27.22.4.9.9.6.4 Method of test

##### 27.22.4.9.9.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.9.6.4.2 Procedure

**Expected Sequence 9.6 (SELECT ITEM, Text Attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.6.4.2, Expected Sequence 9.6.

#### 27.22.4.9.9.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.6.

#### 27.22.4.9.9.7 SELECT ITEM (Support of Text Attribute – Italic On)

##### 27.22.4.9.9.7.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.7.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.7.3 Test purpose

To verify that the ME displays text formatted according to the italic text attribute configuration within the command Select Item.

##### 27.22.4.9.9.7.4 Method of test

###### 27.22.4.9.9.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.9.9.7.4.2 Procedure

**Expected Sequence 9.7 (SELECT ITEM, Text Attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.7.4.2, Expected Sequence 9.7.

##### 27.22.4.9.9.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.7.

#### 27.22.4.9.9.8 SELECT ITEM (Support of Text Attribute – Underline On)

##### 27.22.4.9.9.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.9.9.8.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

##### 27.22.4.9.9.8.3 Test purpose

To verify that the ME displays text formatted according to the underline text attribute configuration within the command Select Item.

##### 27.22.4.9.9.8.4 Method of test

###### 27.22.4.9.9.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.8.4.2 Procedure

**Expected Sequence 9.8 (SELECT ITEM, Text Attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.8.4.2, Expected Sequence 9.8.

27.22.4.9.9.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.8.

27.22.4.9.9.9 SELECT ITEM (Support of Text Attribute – Strikethrough On)

27.22.4.9.9.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.9.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

27.22.4.9.9.9.3 Test purpose

To verify that the ME displays text formatted according to the strikethrough text attribute configuration within the command Select Item.

27.22.4.9.9.9.4 Method of test

27.22.4.9.9.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.9.9.9.4.2 Procedure

**Expected Sequence 9.9 (SELECT ITEM, Text Attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.9.4.2, Expected Sequence 9.9.

27.22.4.9.9.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.9.

27.22.4.9.9.10 SELECT ITEM (Support of Text Attribute – Foreground and Background Colour)

27.22.4.9.9.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.9.9.10.2 Conformance requirement

Requirements are the same as in clause 27.22.4.9.1.2, with an additional one:

- 3GPP 31.111 [15] clauses 6.5.4, 8.70 and 8.71.

#### 27.22.4.9.9.10.3 Test purpose

To verify that the ME displays text formatted according to the foreground and background colour text attribute configuration within the command Select Item.

#### 27.22.4.9.9.10.4 Method of test

##### 27.22.4.9.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.9.9.10.4.2 Procedure

**Expected Sequence 9.10 (SELECT ITEM, Text Attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.9.10.4.2, Expected Sequence 9.10.

#### 27.22.4.9.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 9.10.

### 27.22.4.9.10 SELECT ITEM (UCS2 display in Cyrillic)

#### 27.22.4.9.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.10.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.9.10.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

#### 27.22.4.9.10.4 Method of test

##### 27.22.4.9.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.10.4.2 Procedure

**Expected Sequence 10.1 (SELECT ITEM with UCS2 in Cyrillic characters, 0x80 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.1.

**Expected Sequence 10.2 (SELECT ITEM with UCS2 in Cyrillic characters, 0x81 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.2.

**Expected Sequence 10.3 (SELECT ITEM with UCS2 in Cyrillic characters, 0x82 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.10.4.2, Expected Sequence 10.3.

### 27.22.4.9.10.5 Test requirement

The ME shall operate in the manner defined in expected sequences 10.1 to 10.3.

## 27.22.4.9.11 SELECT ITEM (UCS2 display in Chinese)

### 27.22.4.9.11.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.9.11.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in ISO/IEC 10646 [17].

### 27.22.4.9.11.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

### 27.22.4.9.11.4 Method of test

#### 27.22.4.9.11.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.11.4.2 Procedure

**Expected Sequence 11.1 (SELECT ITEM with UCS2 in Chinese characters, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.11.4.2, Expected Sequence 11.1.

#### 27.22.4.9.11.5 Test requirement

The ME shall operate in the manner defined in expected sequence 11.1.

### 27.22.4.9.12 SELECT ITEM (UCS2 display in Katakana)

#### 27.22.4.9.12.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.9.12.2 Conformance requirement

The ME shall support the Proactive UICC: Select Item facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 6.4.9, clause 6.6.8, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.9, clause 9.4 and clause 10.
- Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in ISO/IEC 10646 [17].

#### 27.22.4.9.12.3 Test purpose

To verify that the ME correctly presents the set of items in UCS2 coding contained in the SELECT ITEM proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC with the identifier of the item chosen.

To verify that the ME allows a SELECT ITEM proactive UICC command within the maximum 255 byte BER-TLV boundary.

To verify that the ME returns a TERMINAL RESPONSE with "Proactive UICC application session terminated by the user", if the user has indicated the need to end the proactive UICC session.

To verify that the ME returns a TERMINAL RESPONSE with "Backwards move in the proactive UICC application session requested by the user", if the user has indicated the need to go backwards in the proactive UICC application session.

#### 27.22.4.9.12.4 Method of test

#### 27.22.4.9.12.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

#### 27.22.4.9.12.4.2 Procedure

**Expected Sequence 12.1 (SELECT ITEM with UCS2 in Katakana characters, 0x80 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.1.

**Expected Sequence 12.2 (SELECT ITEM with UCS2 - Katakana characters, 0x81 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.2.

**Expected Sequence 12.3 (SELECT ITEM with UCS2 - Katakana characters, 0x82 UCS2 coding, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.9.12.4.2, Expected Sequence 12.3.

#### 27.22.4.9.12.5 Test requirement

The ME shall operate in the manner defined in expected sequences 12.1 to 12.3.

## 27.22.4.10 SEND SHORT MESSAGE

### 27.22.4.10.1 SEND SHORT MESSAGE (normal)

#### 27.22.4.10.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.1.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

#### 27.22.4.10.1.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.1.4 Method of test

##### 27.22.4.10.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.10.1.4.2 Procedure

**Expected Sequence 1.1(SEND SHORT MESSAGE, packing not required, 8-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1 | [packing not required, 8-bit data] |
| 4 | ME → USER | Display "Send SM" | [Alpha Identifier] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Send SM"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding 8-bit data
- Message class class 0
- TP-UDL 12
- TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 37 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 53 | 65 | 6E | 64 | 20 | 53 | 4D | 86 | 09 | 91 | 11 |
| | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 18 | 01 | 00 | 09 |
| | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C | 54 | 65 | 73 |
| | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.1

Logically:

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "01"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"

TP-PID Short message type 0
TP-DCS
Message coding 8-bit data
Message class class 0
TP-UDL 12
TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.2 (SEND SHORT MESSAGE, packing required, 8-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.2.1 | [packing required, 8-bit data] |
| 4 | ME → USER | Display "Send SM" | [Alpha Identifier] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.2 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.2.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.2.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send SM"
Address

| | |
|---|---|
| TON: | International number |
| NPI: | "ISDN / telephone numbering plan" |
| Dialling number string | "112233445566778" |
| SMS TPDU | |
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "00" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 8-bit data |
| Message class | class 0 |
| TP-UDL | 7 |
| TP-UD | "Send SM" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 32 | 81 | 03 | 01 | 13 | 01 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 53 | 65 | 6E | 64 | 20 | 53 | 4D | 86 | 09 | 91 | 11 |
| | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 13 | 01 | 00 | 09 |
| | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 07 | 53 | 65 | 6E |
| | 64 | 20 | 53 | 4D | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.2

Logically:

| | |
|---|---|
| SMS TPDU | |
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 7 |
| TP-UD | "Send SM" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F0 | 07 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | D3 | B2 | 9B | 0C | 9A | 36 | 01 | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.3 (SEND SHORT MESSAGE, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.3.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Short Message" | [Alpha Identifier] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.3 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Short Message"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message

| | |
|---|---|
| TP-SRR | A status report is not requested |
| TP-MR | "00" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 13 |
| TP-UD | "Short Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 3D | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0D | 53 | 68 | 6F | 72 | 74 | 20 | 4D | 65 | 73 | 73 | 61 |
| | 67 | 65 | 86 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 |
| | F8 | 8B | 18 | 01 | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 |
| | 40 | F0 | 0D | 53 | F4 | 5B | 4E | 07 | 35 | CB | F3 | 79 |
| | F8 | 5C | 06 | | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.3

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 13 |
| TP-UD | "Short Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F0 | 0D |
| | 53 | F4 | 5B | 4E | 07 | 35 | CB | F3 | 79 | F8 | 5C | 06 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.4 (SEND SHORT MESSAGE, packing required, 8 bit data, message of 160 characters user data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.4. 1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.4.1 | [packing required, 8 bit data] |
| 4 | ME → USER | Display "The address data object holds the RP_Destination_Address " | [Alpha Identifier] |
| 5 | ME → USS | Send SMS-PP(SEND SHORT MESSAGE) Message 1.4 | [message of 140 bytes user data] |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.4.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "The address data object holds the RP_Destination_Address"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"

| | |
|---|---|
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 8 bit data |
| Message class | class 0 |
| TP-UDL | 160 |
| TP-UD | "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | FD | 81 | 03 | 01 | 13 | 01 | 82 | 02 | 81 | 83 |
| | 85 | 38 | 54 | 68 | 65 | 20 | 61 | 64 | 64 | 72 | 65 | 73 |
| | 73 | 20 | 64 | 61 | 74 | 61 | 20 | 6F | 62 | 6A | 65 | 63 |
| | 74 | 20 | 68 | 6F | 6C | 64 | 73 | 20 | 74 | 68 | 65 | 20 |
| | 52 | 50 | 11 | 44 | 65 | 73 | 74 | 69 | 6E | 61 | 74 | 69 |
| | 6F | 6E | 11 | 41 | 64 | 64 | 72 | 65 | 73 | 73 | 86 | 09 |
| | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 81 | AC |
| | 01 | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | A0 |
| | 54 | 77 | 6F | 20 | 74 | 79 | 70 | 65 | 73 | 20 | 61 | 72 |
| | 65 | 20 | 64 | 65 | 66 | 69 | 6E | 65 | 64 | 3A | 20 | 2D |
| | 20 | 41 | 20 | 73 | 68 | 6F | 72 | 74 | 20 | 6D | 65 | 73 |
| | 73 | 61 | 67 | 65 | 20 | 74 | 6F | 20 | 62 | 65 | 20 | 73 |
| | 65 | 6E | 74 | 20 | 74 | 6F | 20 | 74 | 68 | 65 | 20 | 6E |
| | 65 | 74 | 77 | 6F | 72 | 6B | 20 | 69 | 6E | 20 | 61 | 6E |
| | 20 | 53 | 4D | 53 | 2D | 53 | 55 | 42 | 4D | 49 | 54 | 20 |
| | 6D | 65 | 73 | 73 | 61 | 67 | 65 | 2C | 20 | 6F | 72 | 20 |
| | 61 | 6E | 20 | 53 | 4D | 53 | 2D | 43 | 4F | 4D | 4D | 41 |
| | 4E | 44 | 20 | 6D | 65 | 73 | 73 | 61 | 67 | 65 | 2C | 20 |
| | 77 | 68 | 65 | 72 | 65 | 20 | 74 | 68 | 65 | 20 | 75 | 73 |
| | 65 | 72 | 20 | 64 | 61 | 74 | 61 | 20 | 63 | 61 | 6E | 20 |
| | 62 | 65 | 20 | 70 | 61 | 73 | 73 | 65 | 64 | 20 | 74 | 72 |
| | 61 | 6E | 73 | 70 | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.4

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |

| | |
|---|---|
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 160 |
| TP-UD | "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp" |

Coding:

| Coding | | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F0 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | A0 | D4 | FB | 1B | 44 | CF | C3 | CB | 73 | 50 | 58 | 5E |
| | 06 | 91 | CB | E6 | B4 | BB | 4C | D6 | 81 | 5A | A0 | 20 |
| | 68 | 8E | 7E | CB | E9 | A0 | 76 | 79 | 3E | 0F | 9F | CB |
| | 20 | FA | 1B | 24 | 2E | 83 | E6 | 65 | 37 | 1D | 44 | 7F |
| | 83 | E8 | E8 | 32 | C8 | 5D | A6 | DF | DF | F2 | 35 | 28 |
| | ED | 06 | 85 | DD | A0 | 69 | 73 | DA | 9A | 56 | 85 | CD |
| | 24 | 15 | D4 | 2E | CF | E7 | E1 | 73 | 99 | 05 | 7A | CB |
| | 41 | 61 | 37 | 68 | DA | 9C | B6 | 86 | CF | 66 | 33 | E8 |
| | 24 | 82 | DA | E5 | F9 | 3C | 7C | 2E | B3 | 40 | 77 | 74 |
| | 59 | 5E | 06 | D1 | D1 | 65 | 50 | 7D | 5E | 96 | 83 | C8 |
| | 61 | 7A | 18 | 34 | 0E | BB | 41 | E2 | 32 | 08 | 1E | 9E |
| | CF | CB | 64 | 10 | 5D | 1E | 76 | CF | E1 | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| BER-TLV: | 81 | 03 | 01 | 13 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|

**Expected Sequence 1.5 (SEND SHORT MESSAGE, packing not required, SMS default alphabet, message of 160 characters user data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.5.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "The address data object holds the RP Destination Address " | [Alpha Identifier] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.5 | [message of 140 bytes user data] |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "The address data object holds the RP Destination Address"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding SMS default alphabet
- Message class class 0
- TP-UDL 160
- TP-UD "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | E9 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 |
| | 85 | 38 | 54 | 68 | 65 | 20 | 61 | 64 | 64 | 72 | 65 | 73 |
| | 73 | 20 | 64 | 61 | 74 | 61 | 20 | 6F | 62 | 6A | 65 | 63 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 74 | 20 | 68 | 6F | 6C | 64 | 73 | 20 | 74 | 68 | 65 | 20 |
| 52 | 50 | 20 | 44 | 65 | 73 | 74 | 69 | 6E | 61 | 74 | 69 |
| 6F | 6E | 20 | 41 | 64 | 64 | 72 | 65 | 73 | 73 | 86 | 09 |
| 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 81 | 98 |
| 01 | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F0 | A0 |
| D4 | FB | 1B | 44 | CF | C3 | CB | 73 | 50 | 58 | 5E | 06 |
| 91 | CB | E6 | B4 | BB | 4C | D6 | 81 | 5A | A0 | 20 | 68 |
| 8E | 7E | CB | E9 | A0 | 76 | 79 | 3E | 0F | 9F | CB | 20 |
| FA | 1B | 24 | 2E | 83 | E6 | 65 | 37 | 1D | 44 | 7F | 83 |
| E8 | E8 | 32 | C8 | 5D | A6 | DF | DF | F2 | 35 | 28 | ED |
| 06 | 85 | DD | A0 | 69 | 73 | DA | 9A | 56 | 85 | CD | 24 |
| 15 | D4 | 2E | CF | E7 | E1 | 73 | 99 | 05 | 7A | CB | 41 |
| 61 | 37 | 68 | DA | 9C | B6 | 86 | CF | 66 | 33 | E8 | 24 |
| 82 | DA | E5 | F9 | 3C | 7C | 2E | B3 | 40 | 77 | 74 | 59 |
| 5E | 06 | D1 | D1 | 65 | 50 | 7D | 5E | 96 | 83 | C8 | 61 |
| 7A | 18 | 34 | 0E | BB | 41 | E2 | 32 | 08 | 1E | 9E | CF |
| CB | 64 | 10 | 5D | 1E | 76 | CF | E1 | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.5

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 160 |
| TP-UD | "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transp" |

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F0 | A0 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| D4 | FB | 1B | 44 | CF | C3 | CB | 73 | 50 | 58 | 5E | 06 |
| 91 | CB | E6 | B4 | BB | 4C | D6 | 81 | 5A | A0 | 20 | 68 |
| 8E | 7E | CB | E9 | A0 | 76 | 79 | 3E | 0F | 9F | CB | 20 |
| FA | 1B | 24 | 2E | 83 | E6 | 65 | 37 | 1D | 44 | 7F | 83 |
| E8 | E8 | 32 | C8 | 5D | A6 | DF | DF | F2 | 35 | 28 | ED |
| 06 | 85 | DD | A0 | 69 | 73 | DA | 9A | 56 | 85 | CD | 24 |
| 15 | D4 | 2E | CF | E7 | E1 | 73 | 99 | 05 | 7A | CB | 41 |
| 61 | 37 | 68 | DA | 9C | B6 | 86 | CF | 66 | 33 | E8 | 24 |
| 82 | DA | E5 | F9 | 3C | 7C | 2E | B3 | 40 | 77 | 74 | 59 |
| 5E | 06 | D1 | D1 | 65 | 50 | 7D | 5E | 96 | 83 | C8 | 61 |
| 7A | 18 | 34 | 0E | BB | 41 | E2 | 32 | 08 | 1E | 9E | CF |
| CB | 64 | 10 | 5D | 1E | 76 | CF | E1 | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.6 (SEND SHORT MESSAGE, alpha identifier 160 bytes long, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.6.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transparently; - A short message to be sent to the network in an SMS-SUBMIT " | [Alpha Identifier of 160 bytes] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.6 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.6.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Two types are defined: - A short message to be sent to the network in an SMS-SUBMIT message, or an SMS-COMMAND message, where the user data can be passed transparently; - A short message to be sent to the network in an SMS-SUBMIT"

SMS TPDU
- TP-MTI: SMS-SUBMIT
- TP-RD: Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF: TP-VP field not present
- TP-RP: TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI: The TP-UD field contains only the short message
- TP-SRR: A status report is not requested
- TP-MR: "00"
- TP-DA
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "01"
- TP-PID: Short message type 0
- TP-DCS
  - Message coding: SMS default alphabet
  - Message class: class 0
- TP-UDL: 1
- TP-UD: " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | FD | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 |
| | 85 | 81 | E6 | 54 | 77 | 6F | 20 | 74 | 79 | 70 | 65 | 73 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 20 | 61 | 72 | 65 | 20 | 64 | 65 | 66 | 69 | 6E | 65 | 64 |
| 3A | 20 | 2D | 20 | 41 | 20 | 73 | 68 | 6F | 72 | 74 | 20 |
| 6D | 65 | 73 | 73 | 61 | 67 | 65 | 20 | 74 | 6F | 20 | 62 |
| 65 | 20 | 73 | 65 | 6E | 74 | 20 | 74 | 6F | 20 | 74 | 68 |
| 65 | 20 | 6E | 65 | 74 | 77 | 6F | 72 | 6B | 20 | 69 | 6E |
| 20 | 61 | 6E | 20 | 53 | 4D | 53 | 2D | 53 | 55 | 42 | 4D |
| 49 | 54 | 20 | 6D | 65 | 73 | 73 | 61 | 67 | 65 | 2C | 20 |
| 6F | 72 | 20 | 61 | 6E | 20 | 53 | 4D | 53 | 2D | 43 | 4F |
| 4D | 4D | 41 | 4E | 44 | 20 | 6D | 65 | 73 | 73 | 61 | 67 |
| 65 | 2C | 20 | 77 | 68 | 65 | 72 | 65 | 20 | 74 | 68 | 65 |
| 20 | 75 | 73 | 65 | 72 | 20 | 64 | 61 | 74 | 61 | 20 | 63 |
| 61 | $6^E$ | 20 | 62 | 65 | 20 | 70 | 61 | 73 | 73 | 65 | 64 |
| 20 | 74 | 72 | 61 | 6E | 73 | 70 | 61 | 72 | 65 | 6E | 74 |
| 6C | 79 | 3B | 20 | 2D | 20 | 41 | 20 | 73 | 68 | 6F | 72 |
| 74 | 20 | 6D | 65 | 73 | 73 | 61 | 67 | 65 | 20 | 74 | 6F |
| 20 | 62 | 65 | 20 | 73 | 65 | 6E | 74 | 20 | 74 | 6F | 20 |
| 74 | 68 | 65 | 20 | 6E | 65 | 74 | 77 | 6F | 72 | 6B | 20 |
| 69 | 6E | 20 | 61 | 6E | 20 | 53 | 4D | 53 | 2D | 53 | 55 |
| 42 | 4D | 49 | 54 | 20 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| 40 | F0 | 01 | 20 | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.6

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "01" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 1 |
| TP-UD | " " |

Coding:

| | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 02 | 91 | 10 | 40 | F0 | 01 | 20 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.7(SEND SHORT MESSAGE, alpha identifier length '00', packing not required, 8-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.7.1 | [packing not required, 8-bit data] |
| 4 | ME | No information to user | [Alpha identifier length '00'] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.7 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.7.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier:

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT

| | |
|---|---|
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "00" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 8-bit data |
| Message class | class 0 |
| TP-UDL | 12 |
| TP-UD | "Test Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 30 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 00 | 86 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 |
| | 8B | 18 | 01 | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 |
| | F4 | 0C | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 |
| | 67 | 65 | | | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.7

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 8-bit data |
| Message class | class 0 |
| TP-UDL | 12 |
| TP-UD | "Test Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.8 (SEND SHORT MESSAGE, packing not required, 8-bit data, no alpha identifier, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.8.1 | [packing not required, 8-bit data] |
| 4 | ME → USER | May give information to user concerning what is happening | [No Alpha Identifier] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 1.8 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.8.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"

| | |
|---|---|
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 8-bit data |
| Message class | class 0 |
| TP-UDL | 12 |
| TP-UD | "Test Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2E | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 86 |
| | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 18 |
| | 01 | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

SMS-PP (SEND SHORT MESSAGE) Message 1.8

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 8-bit data |
| Message class | class 0 |
| TP-UDL | 12 |
| TP-UD | "Test Message" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.8.1

Logically:

Command details

| | |
|---|---|
| Command number: | 1 |
| Command type: | SEND SHORT MESSAGE |
| Command qualifier: | packing not required |

Device identities

| | |
|---|---|
| Source device: | ME |
| Destination device: | UICC |

Result

| | |
|---|---|
| General Result: | Command performed successfully |

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.8.

### 27.22.4.10.2 SEND SHORT MESSAGE (UCS2 display in Cyrillic)

#### 27.22.4.10.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.2.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.10.2.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.2.4 Method of test

##### 27.22.4.10.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.2.4.2 Procedure

**Expected Sequence 2.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data in Cyrillic))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 2.1.1 | [packing not required, 16-bit data] |
| 4 | ME → USER | Display "ЗДРАВСТВУЙТЕ" | [Alpha Identifier] "Hello" in Russian, 0x80 coding of UCS2 format |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 2.1 | Cyrillic |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 2.1.2 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND SEND SHORT MESSAGE 2.1.2 | |
| 12 | ME → USER | Display "ЗДРАВСТВУЙТЕ" | [Alpha Identifier] "Hello" in Russian, 0x81 coding of UCS2 format |
| 13 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 2.1 | |
| 14 | USS → ME | SMS RP-ACK | |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 17 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 2.1.3 | |
| 18 | ME → UICC | FETCH | |
| 19 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 2.1.3 | [UCS2 alphabet] |
| 20 | ME → USER | Display "ЗДРАВСТВУЙТЕ" | [Alpha Identifier] "Hello" in Russian, 0x82 coding of UCS2 format |
| 21 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 2.1 | |
| 22 | USS → ME | SMS RP-ACK | |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1 | [Command performed successfully] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"
Address
TON: International number
NPI: "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 16-bit data
Message class class 0
TP-UDL 24
TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 55 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 19 | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 |
| | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 |
| | 04 | 15 | 86 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 |
| | F8 | 8B | 24 | 01 | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 |
| | 40 | 08 | 18 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 |
| | 12 | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 |
| | 22 | 04 | 15 | | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 2.1

Logically:

SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "01"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding UCS2 (16-bit data)
Message class class 0

TP-UDL 24
TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 18 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 | 04 | 21 |
| | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 | 04 | 15 |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "ЗДРАВСТВУЙТЕ"
Address
TON: International number
NPI: "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 16-bit data
Message class class 0
TP-UDL 24
TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

| BER-TLV: | D0 | 4B | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0F | 81 | 0C | 08 | 97 | 94 | A0 | 90 | 92 | A1 | A2 | 92 |
| | A3 | 99 | A2 | 95 | 86 | 09 | 91 | 11 | 22 | 33 | 44 | 55 |
| | 66 | 77 | F8 | 8B | 24 | 01 | 00 | 09 | 91 | 10 | 32 | 54 |
| | 76 | F8 | 40 | 08 | 18 | 04 | 17 | 04 | 14 | 04 | 20 | 04 |
| | 10 | 04 | 12 | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 |
| | 19 | 04 | 22 | 04 | 15 | | | | | | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 2.1.3

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding 16-bit data
- Message class class 0
- TP-UDL 24
- TP-UD "ЗДРАВСТВУЙТЕ"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 82 | 0C | 04 | 10 | 87 | 84 | 90 | 80 | 82 | 91 | 92 |
| | 82 | 93 | 89 | 92 | 85 | 86 | 09 | 91 | 11 | 22 | 33 | 44 |
| | 55 | 66 | 77 | F8 | 8B | 24 | 01 | 00 | 09 | 91 | 10 | 32 |
| | 54 | 76 | F8 | 40 | 08 | 18 | 04 | 17 | 04 | 14 | 04 | 20 |
| | 04 | 10 | 04 | 12 | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 |
| | 04 | 19 | 04 | 22 | 04 | 15 | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

27.22.4.10.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.10.3 SEND SHORT MESSAGE (icon support)

### 27.22.4.10.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.10.3.2 Conformance requirement

### 27.22.4.10.3.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

### 27.22.4.10.3.4 Method of test

#### 27.22.4.10.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as Toolkit default.

The ME screen shall be in its normal stand-by display.

#### 27.22.4.10.3.4.2 Procedure

**Expected Sequence 3.1A (SEND SHORT MESSAGE, basic icon self-explanatory, packing not required, 8-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1 | [packing not required, 8-bit data] |
| 4 | ME → USER | Displays the icon and not the alpha identifier | [basic icon self-explanatory] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 3.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1A | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "NO ICON"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding 8bit-data
- Message class class 0
- TP-UDL 12
- TP-UD "Test Message"

Icon Identifier
- Icon Qualifier self-explanatory
- Icon Identifier 1 (number of record in EF IMG)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 3B | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 4E | 4F | 20 | 49 | 43 | 4F | 4E | 86 | 09 | 91 | 11 |
| | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 18 | 01 | 00 | 09 |
| | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C | 54 | 65 | 73 |
| | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | 9E | 02 | 00 |
| | 01 | | | | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 3.1

Logically:

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "01"

TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 8-bit data
Message class class 0
TP-UDL 12
TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1A

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 3.1B (SEND SHORT MESSAGE, basic icon self-explanatory, packing not required, 8-bit data, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 3.1.1 | [packing not required, 8-bit data, basic icon self-explanatory]] |
| 4 | ME → USER | Displays the alpha identifier without the icon | |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 3.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1B | [Command performed successfully, but requested icon could not be displayed] |

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.1.1B

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully, but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

**Expected Sequence 3.2A (SEND SHORT MESSAGE, basic icon non-self-explanatory, packing not required, 8-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1 | [packing not required, 8-bit data] |
| 4 | ME → USER | display the icon and "Send SM" | [basic icon non-self-explanatory] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 3.2 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1A | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha Identifier "Send SM"
Address
TON: International number
NPI: "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 8bit-data
Message class class 0
TP-UDL 12

TP-UD "Test Message"
Icon Identifier
Icon Qualifier non-self-explanatory
Icon Identifier 1 (number of record in EF IMG)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 3B | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 53 | 65 | 6E | 64 | 20 | 53 | 4D | 86 | 09 | 91 | 11 |
| | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 18 | 01 | 00 | 09 |
| | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C | 54 | 65 | 73 |
| | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | 1E | 02 | 01 |
| | 01 | | | | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 3.2

Logically:

SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "01"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 8-bit data
Message class class 0
TP-UDL 12
TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1A

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result

General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 3.2B (SEND SHORT MESSAGE, basic icon non-self-explanatory, packing not required, 8-bit data, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 3.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 3.2.1 | [packing not required, 8-bit data, basic icon non-self-explanatory ] |
| 4 | ME → USER | display "Send SM" without the icon | |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 3.2 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1B | [Command performed successfully, but requested icon could not be displayed] |

TERMINAL RESPONSE: SEND SHORT MESSAGE 3.2.1B

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed;

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

#### 27.22.4.10.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.2B.

### 27.22.4.10.4 SEND SHORT MESSAGE (Support of Text Attribute)

#### 27.22.4.10.4.1 SEND SHORT MESSAGE (Support of Text Attribute – Left Alignment)

##### 27.22.4.10.4.1.1 Definition and applicability

See clause 3.2.2.

27.22.4.10.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

27.22.4.10.4.1.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the left alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

27.22.4.10.4.1.4 Method of test

27.22.4.10.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.1.4.2 Procedure

**Expected Sequence 4.1 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Left Alignment, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with left alignment] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.1.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.1

Logically:

Command details
Command number: 1

Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.1.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA

| | |
|---|---|
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "01" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 1 |
| TP-UD | " " |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 4.1

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "01" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | SMS default alphabet |
| Message class | class 0 |
| TP-UDL | 1 |
| TP-UD | " " |

Coding:

| | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 02 | 91 | 10 | 40 | F0 | 01 | 20 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.1.1

Logically:

Command details

| | |
|---|---|
| Command number: | 1 |
| Command type: | SEND SHORT MESSAGE |
| Command qualifier: | packing not required |

Device identities

| | |
|---|---|
| Source device: | ME |
| Destination device: | UICC |

Result

| | |
|---|---|
| General Result: | Command performed successfully |

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.10.4.2 SEND SHORT MESSAGE (Support of Text Attribute – Center Alignment)

#### 27.22.4.10.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.2.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the center alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.2.4 Method of test

##### 27.22.4.10.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.2.4.2 Procedure

**Expected Sequence 4.2 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Center Alignment, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with center alignment] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.2.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU
- TP-MTI: SMS-SUBMIT
- TP-RD: Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF: TP-VP field not present
- TP-RP: TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI: The TP-UD field contains only the short message
- TP-SRR: A status report is not requested
- TP-MR: "00"
- TP-DA
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "01"
- TP-PID: Short message type 0
- TP-DCS
  - Message coding: SMS default alphabet
  - Message class: class 0
- TP-UDL: 1

TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 01 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.2.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.2.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

### 27.22.4.10.4.3 SEND SHORT MESSAGE (Support of Text Attribute – Right Alignment)

#### 27.22.4.10.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.3.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the right alignment text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.3.4 Method of test

##### 27.22.4.10.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.3.4.2 Procedure

**Expected Sequence 4.3 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Right Alignment, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with right alignment] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.3.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/11, no alignment change will take place] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU
- TP-MTI: SMS-SUBMIT
- TP-RD: Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF: TP-VP field not present
- TP-RP: TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI: The TP-UD field contains only the short message
- TP-SRR: A status report is not requested
- TP-MR: "00"
- TP-DA
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "01"
- TP-PID: Short message type 0
- TP-DCS
  - Message coding: SMS default alphabet
  - Message class: class 0
- TP-UDL: 1

TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 02 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.3.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.3.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

### 27.22.4.10.4.4 SEND SHORT MESSAGE (Support of Text Attribute – Large Font Size)

#### 27.22.4.10.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.4.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the large font size text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.4.4 Method of test

##### 27.22.4.10.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.4.4.2 Procedure

**Expected Sequence 4.4 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Large Font Size, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with large font size] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with normal font size] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1 | [packing not required, SMS default alphabet] |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with large font size] |
| 19 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 20 | USS → ME | SMS RP-ACK | |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1 | [Command performed successfully] |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.4.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.3 | [packing not required, SMS default alphabet] |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with normal font size] |
| 26 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 27 | USS → ME | SMS RP-ACK | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 04 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number

NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.4.3

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 75 | 74 | 65 | 20 | 33 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

### 27.22.4.10.4.5 SEND SHORT MESSAGE (Support of Text Attribute – Small Font Size)

#### 27.22.4.10.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.5.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the small font size text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.5.4 Method of test

##### 27.22.4.10.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.5.4.2 Procedure

**Expected Sequence 4.5 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Small Font Size, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with small font size] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with normal font size] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1 | [packing not required, SMS default alphabet] |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with small font size] |
| 19 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 20 | USS → ME | SMS RP-ACK | |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1 | [Command performed successfully] |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.5.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.3 | [packing not required, SMS default alphabet] |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with normal font size] |
| 26 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 27 | USS → ME | SMS RP-ACK | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 08 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number

NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.5.3

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 75 | 74 | 65 | 20 | 33 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

### 27.22.4.10.4.6 SEND SHORT MESSAGE (Support of Text Attribute – Bold On)

#### 27.22.4.10.4.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.6.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the bold text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.6.4 Method of test

##### 27.22.4.10.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.6.4.2 Procedure

**Expected Sequence 4.6 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Bold On, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with bold on] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with bold off] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1 | [packing not required, SMS default alphabet] |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with bold on] |
| 19 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 20 | USS → ME | SMS RP-ACK | |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1 | [Command performed successfully] |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.6.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.3 | [packing not required, SMS default alphabet] |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with bold off] |
| 26 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 27 | USS → ME | SMS RP-ACK | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC

Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 10 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0

TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.6.3

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.6.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

### 27.22.4.10.4.7 SEND SHORT MESSAGE (Support of Text Attribute – Italic On)

#### 27.22.4.10.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.7.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the italic text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.7.4 Method of test

##### 27.22.4.10.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.7.4.2 Procedure

**Expected Sequence 4.7 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Italic On, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with italic on] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with italic off] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1 | [packing not required, SMS default alphabet] |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with italic on] |
| 19 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 20 | USS → ME | SMS RP-ACK | |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1 | [Command performed successfully] |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.7.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.3 | [packing not required, SMS default alphabet] |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with italic off] |
| 26 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 27 | USS → ME | SMS RP-ACK | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC

Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 20 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0

TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.7.3

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.7.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

### 27.22.4.10.4.8 SEND SHORT MESSAGE (Support of Text Attribute – Underline On)

#### 27.22.4.10.4.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.8.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the underline text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.8.4 Method of test

##### 27.22.4.10.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.8.4.2 Procedure

**Expected Sequence 4.8 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Underline On, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with underline on] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with underline off] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1 | [packing not required, SMS default alphabet] |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with underline on] |
| 19 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 20 | USS → ME | SMS RP-ACK | |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1 | [Command performed successfully] |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.8.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.3 | [packing not required, SMS default alphabet] |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with underline off] |
| 26 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 27 | USS → ME | SMS RP-ACK | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 40 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number

NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.8.3

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 75 | 74 | 65 | 20 | 33 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

### 27.22.4.10.4.9 SEND SHORT MESSAGE (Support of Text Attribute – Strikethrough On)

#### 27.22.4.10.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.9.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the strikethrough text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.9.4 Method of test

##### 27.22.4.10.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.9.4.2 Procedure

**Expected Sequence 4.9 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Strikethrough On, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with strikethrough on] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with strikethrough off] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1 | [packing not required, SMS default alphabet] |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with strikethrough on] |
| 19 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 20 | USS → ME | SMS RP-ACK | |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1 | [Command performed successfully] |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.9.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.3 | [packing not required, SMS default alphabet] |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with strikethrough off] |
| 26 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 27 | USS → ME | SMS RP-ACK | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE

Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 80 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number

NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.9.3

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 75 | 74 | 65 | 20 | 33 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.9.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

### 27.22.4.10.4.10 SEND SHORT MESSAGE (Support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.10.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- ETSI TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31, 8.67 and clause 5.2.

#### 27.22.4.10.4.10.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) and display the alpha identifier according to the foreground and background colour text attribute configuration as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.4.10.4 Method of test

##### 27.22.4.10.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.4.10.4.2 Procedure

**Expected Sequence 4.10 (SEND SHORT MESSAGE, alpha identifier with Text attribute – Foreground and Background Colour, packing not required, SMS default alphabet, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.1 | [packing not required, SMS default alphabet] |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with foreground and background colour according to text attribute configuration] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 4.10.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.2 | [packing not required, SMS default alphabet] |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with ME"s default foreground and background colour] |
| 12 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 4.1 | |
| 13 | USS → ME | SMS RP-ACK | |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SMS TPDU
- TP-MTI: SMS-SUBMIT
- TP-RD: Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF: TP-VP field not present
- TP-RP: TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI: The TP-UD field contains only the short message
- TP-SRR: A status report is not requested
- TP-MR: "00"
- TP-DA
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "01"
- TP-PID: Short message type 0
- TP-DCS
  - Message coding: SMS default alphabet
  - Message class: class 0
- TP-UDL: 1
- TP-UD: " "

Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 4.10.2

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "01"
TP-PID Short message type 0
TP-DCS
Message coding SMS default alphabet
Message class class 0
TP-UDL 1
TP-UD " "

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8B | 09 | 01 | 00 | 02 | 91 | 10 |
| | 40 | F0 | 01 | 20 | | | | | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 4.10.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.10.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

### 27.22.4.10.5 SEND SHORT MESSAGE (UCS2 display in Chinese)

#### 27.22.4.10.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.10.5.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.5.4 Method of test

##### 27.22.4.10.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.5.4.2 Procedure

**Expected Sequence 5.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data in Chinese))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 5.1.1 | [packing not required, 16-bit data] |
| 4 | ME → USER | Display "中一" | [Alpha Identifier]<br>"Middle 1" in Chinese, 0x80 coding of UCS2 format |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 5.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.2 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND SEND SHORT MESSAGE 5.1.2 | |
| 12 | ME → USER | Display "中一" | [Alpha Identifier]<br>"Middle 1" in Chinese, 0x81 coding of UCS2 format |
| 13 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 5.1 | |
| 14 | USS → ME | SMS RP-ACK | |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 17 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 5.1.3 | |
| 18 | ME → UICC | FETCH | |
| 19 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 5.1.3 | [UCS2 alphabet] |
| 20 | ME → USER | Display "中一" | [Alpha Identifier]<br>"Middle 1" in Chinese, 0x82 coding of UCS2 format |
| 21 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 5.1 | |
| 22 | USS → ME | SMS RP-ACK | |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1 | [Command performed successfully] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "中—"
Address
TON: International number
NPI: "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 16-bit data
Message class class 0
TP-UDL 24
TP-UD "中—"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 4E | 2D | 4E | 00 | 86 | 09 | 91 | 11 | 22 | 33 |
| | 44 | 55 | 66 | 77 | F8 | 8B | 10 | 01 | 00 | 09 | 91 | 10 |
| | 32 | 54 | 76 | F8 | 40 | 08 | 04 | 4E | 2D | 4E | 00 | |

SMS-PP (SEND SHORT MESSAGE) Message 5.1

Logically:

SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "01"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding UCS2 (16-bit data)
Message class class 0
TP-UDL 24
TP-UD "中—"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 04 |
| | 4E | 2D | 4E | 00 | | | | | | | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.2

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "中—"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding 16-bit data
- Message class class 0
- TP-UDL 24
- TP-UD "中—"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 81 | 02 | 9C | AD | 80 | 86 | 09 | 91 | 11 | 22 | 33 |
| | 44 | 55 | 66 | 77 | F8 | 8B | 10 | 01 | 00 | 09 | 91 | 10 |
| | 32 | 54 | 76 | F8 | 40 | 08 | 04 | 4E | 2D | 4E | 00 | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 5.1.3

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "中—"
Address
TON: International number
NPI: "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-SUBMIT
TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
TP-VPF TP-VP field not present
TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
TP-UDHI The TP-UD field contains only the short message
TP-SRR A status report is not requested
TP-MR "00"
TP-DA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"
TP-PID Short message type 0
TP-DCS
Message coding 16-bit data
Message class class 0
TP-UDL 24
TP-UD "中—"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2E | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 06 | 82 | 02 | 4E | 00 | AD | 80 | 86 | 09 | 91 | 11 | 22 |
| | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 10 | 01 | 00 | 09 | 91 |
| | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 04 | 4E | 2D | 4E | 00 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 5.1.1

Logically:

Command details
Command number: 1
Command type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

### 27.22.4.10.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.10.6 SEND SHORT MESSAGE (UCS2 display in Katakana)

#### 27.22.4.10.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.10.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.10, clause 6.6.9, clause 8.1, clause 8.2, clause 8.6, clause 8.7, clause 8.13, clause 8.31 and clause 5.2.

Additionally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in the following technical specifications: ISO/IEC 10646 [17].

#### 27.22.4.10.6.3 Test purpose

To verify that the ME correctly formats and sends a short message to the network (USS) as indicated in the SEND SHORT MESSAGE proactive UICC command, and returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the Short Message.

#### 27.22.4.10.6.4 Method of test

##### 27.22.4.10.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.10.6.4.2 Procedure

**Expected Sequence 6.1 (SEND SHORT MESSAGE, packing not required, UCS2 (16-bit data, in Katakana))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.1 | [packing not required, 16-bit data] |
| 4 | ME → USER | Display "80ルの" | [Characters in katakana] |
| 5 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 6.1 | |
| 6 | USS → ME | SMS RP-ACK | |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.2 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.2 | [packing not required, 16-bit data] |
| 12 | ME → USER | Display "81ルの" | [Characters in katakana] |
| 13 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 6.2 | |
| 14 | USS → ME | SMS RP-ACK | |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 17 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 6.1.3 | |
| 18 | ME → UICC | FETCH | |
| 19 | UICC → ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 6.1.3 | [packing not required, 16-bit data] |
| 20 | ME → USER | Display "82ルの" | [Characters in katakana] |
| 21 | ME → USS | Send SMS-PP (SEND SHORT MESSAGE) Message 6.3 | |
| 22 | USS → ME | SMS RP-ACK | |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1 | [Command performed successfully] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "80ルの"

Address
- TON: International number

| | |
|---|---|
| NPI: | "ISDN / telephone numbering plan" |
| Dialling number string | "112233445566778" |

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept a SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "00" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 16-bit data |
| Message class | class 0 |
| TP-UDL | 10 |
| TP-UD | "80ルー1" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 35 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 09 | 80 | 00 | 38 | 00 | 30 | 30 | EB | 00 | 30 | 86 | 09 |
| | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 14 | 01 |
| | 00 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 08 | 00 |
| | 38 | 00 | 30 | 30 | EB | 00 | 31 | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 6.1

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | UCS2 (16-bit data) |
| Message class | class 0 |
| TP-UDL | 10 |
| TP-UD | "80ルー1" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 08 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 38 | 00 | 30 | 30 | EB | 00 | 31 | | | | |

TERMINAL RESPONSE: SEND SHORT MESSAGE 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.2

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "81儿1"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept a SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding 16-bit data
- Message class class 0
- TP-UDL 10
- TP-UD "80儿2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 81 | 04 | 61 | 38 | 31 | EB | 31 | 86 | 09 | 91 | 11 |
| | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 14 | 01 | 00 | 09 |
| | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 08 | 00 | 38 | 00 |
| | 30 | 30 | EB | 00 | 32 | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 6.2

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | UCS2 (16-bit data) |
| Message class | class 0 |
| TP-UDL | 10 |
| TP-UD | "80ルク2" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 08 |
| | 00 | 38 | 00 | 30 | 30 | EB | 00 | 32 | | | | |

PROACTIVE COMMAND: SEND SHORT MESSAGE: 6.1.3

Logically:

Command details

| | |
|---|---|
| Command number: | 1 |
| Command type: | SEND SHORT MESSAGE |
| Command qualifier: | packing not required |

Device identities

| | |
|---|---|
| Source device: | UICC |
| Destination device: | Network |

Alpha identifier: "82ルク2"

Address

| | |
|---|---|
| TON: | International number |
| NPI: | "ISDN / telephone numbering plan" |
| Dialling number string | "112233445566778" |

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept a SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |

| | |
|---|---|
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "00" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | 16-bit data |
| Message class | class 0 |
| TP-UDL | 10 |
| TP-UD | "80ルЗ" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 34 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 08 | 82 | 04 | 30 | A0 | 38 | 32 | CB | 32 | 86 | 09 | 91 |
| | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 14 | 01 | 00 |
| | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 08 | 00 | 38 |
| | 00 | 30 | 30 | EB | 00 | 33 | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 6.3

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-SUBMIT |
| TP-RD | Instruct the SC to accept an SMS-SUBMIT for a SM |
| TP-VPF | TP-VP field not present |
| TP-RP | TP-Reply-Path is not set in this SMS-SUBMIT |
| TP-UDHI | The TP-UD field contains only the short message |
| TP-SRR | A status report is not requested |
| TP-MR | "01" |
| TP-DA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "012345678" |
| TP-PID | Short message type 0 |
| TP-DCS | |
| Message coding | UCS2 (16-bit data) |
| Message class | class 0 |
| TP-UDL | 10 |
| TP-UD | "80ルЗ" |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | 08 | 08 |
| | 00 | 38 | 00 | 30 | 30 | EB | 00 | 33 | | | | |

#### 27.22.4.10.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.11 SEND SS

### 27.22.4.11.1 SEND SS (normal)

#### 27.22.4.11.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.1.3 Test purpose

To verify that the ME correctly translates and sends the supplementary service request indicated in the SEND SS proactive UICC command to the USS.

To verify that the ME returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the SS and any contents of the SS result as additional data.

#### 27.22.4.11.1.4 Method of test

##### 27.22.4.11.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.11.1.4.2 Procedure

**Expected Sequence 1.1A (SEND SS, call forward unconditional, all bearers, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.1.1 | |
| 4 | ME → USER | Display "Call Forward" | |
| 5 | ME → USS | REGISTER 1.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.1.1A | |

**Expected Sequence 1.1B (SEND SS, call forward unconditional, all bearers, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.1.1 | |
| 4 | ME → USER | Display "Call Forward" | |
| 5 | ME → USS | REGISTER 1.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.1.1B | |

PROACTIVE COMMAND: SEND SS 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Call Forward"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*012345678901234567 89*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 29 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0C | 43 | 61 | 6C | 6C | 20 | 46 | 6F | 72 | 77 | 61 | 72 |
| | 64 | 89 | 10 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 |
| | 21 | 43 | 65 | 87 | A9 | 01 | FB | | | | | |

REGISTER 1.1A

Logically (only SS argument):

REGISTER SS ARGUMENT
- SS-Code:
- Call Forwarding Unconditional
- TeleserviceCode
- All Tele Services
- ForwardedToNumber
- nature of address ind.: international
- numbering plan ind.: ISDN/Telephony (E.164)
- TBCD String: 01234567890123456789
- longFTN-Supported

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 15 | 04 | 01 | 21 | 83 | 01 | 00 | 84 | 0B | 91 | 10 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 32 | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | 89 | 00 | |

REGISTER 1.1B

Logically (only SS argument):

REGISTER SS ARGUMENT
SS-Code:
- Call Forwarding Unconditional
TeleserviceCode
- All Tele Services
ForwardedToNumber
- nature of address ind.: international
- numbering plan ind.: ISDN/Telephony (E.164)
- TBCD String: 01234567890123456789

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 13 | 04 | 01 | 21 | 83 | 01 | 00 | 84 | 0B | 91 | 10 |
| | 32 | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | | | |

RELEASE COMPLETE (SS RETURN RESULT) 1.1A

Logically (only from operation code):

REGISTER SS RETURN RESULT
ForwardingInfo
SS-Code
- Call Forwarding Unconditional
ForwardFeatureList
ForwardingFeature
TeleserviceCode
- All Tele Services
SS-Status
- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: active
longForwardedToNumber
- nature of address ind.: international
- numbering plan ind.: ISDN/Telephony (E.164)
- TBCD String: 01234567890123456789

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 0A | A0 | 1A | 04 | 01 | 21 | 30 | 15 | 30 | 13 | 83 | 01 |
| | 00 | 84 | 01 | 07 | 89 | 0B | 91 | 10 | 32 | 54 | 76 | 98 |
| | 10 | 32 | 54 | 76 | 98 | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 1.1B

Logically (only from operation code):

REGISTER SS RETURN RESULT
ForwardingInfo
SS-Code

- Call Forwarding Unconditional
ForwardFeatureList
ForwardingFeature
TeleserviceCode
- All Tele Services
SS-Status
- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: active

Coding:

| Coding | 0A | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 | 83 | 01 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 84 | 01 | 07 | | | | | | | | |

TERMINAL RESPONSE: SEND SS 1.1.1A

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Additional information: Operation Code and SS Parameters

Coding:

| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 1E |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 0A | A0 | 1A | 04 | 01 | 21 | 30 | 15 | 30 | 13 |
| | 83 | 01 | 00 | 84 | 01 | 07 | 89 | 0B | 91 | 10 | 32 |
| | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | | | |

TERMINAL RESPONSE: SEND SS 1.1.1B

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Additional information: Operation Code and SS Parameters

Coding:

| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 11 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 0A | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 |
| | 83 | 01 | 00 | 84 | 01 | 07 | | | | | |

**Expected Sequence 1.2 (SEND SS, call forward unconditional, all bearers, Return Error)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.1.1 | |
| 4 | ME → USER | Display "Call Forward" | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN ERROR) 1.1 | [Return Error] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.2.1 | |

RELEASE COMPLETE (SS RETURN ERROR) 1.1

Logically (only from error code):

Error Code: Facility not supported

Coding:

| | | | |
|---|---|---|---|
| Coding | 02 | 01 | 15 |

TERMINAL RESPONSE: SEND SS 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: SS Return Error
- Additional information: Error Code

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 02 |
| | 34 | 15 | | | | | | | | | |

**Expected Sequence 1.3 (SEND SS, call forward unconditional, all bearers, Reject)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.1.1 | |
| 4 | ME → USER | Display "Call Forward" | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS REJECT) 1.1. | [Reject] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.3.1 | |

RELEASE COMPLETE (SS REJECT) 1.1

Logically (only from problem code):

Problem Code:
- General problem
- Unrecognized component

Coding:

| Coding | 80 | 01 | 00 |
|---|---|---|---|

TERMINAL RESPONSE: SEND SS 1.3.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: SS Return Error
Additional information: No specific cause can be given

Coding:

| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 02 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 34 | 00 | | | | | | | | | |

**Expected Sequence 1.4A (SEND SS, call forward unconditional, all bearers, successful, SS request size limit)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.4.1 | |
| 4 | ME → USER | Display "Call Forward" | |
| 5 | ME → USS | REGISTER 1.2A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.2A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.4.1A | |

**Expected Sequence 1.4B (SEND SS, call forward unconditional, all bearers, successful, SS request size limit)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.4.1 | |
| 4 | ME → USER | Display "Call Forward" | |
| 5 | ME → USS | REGISTER 1.2B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.2B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.4.1B | |

PROACTIVE COMMAND: SEND SS 1.4.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Call Forward"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*012345678901234567890123456 7*11#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0C | 43 | 61 | 6C | 6C | 20 | 46 | 6F | 72 | 77 | 61 | 72 |
| | 64 | 89 | 14 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 |
| | 21 | 43 | 65 | 87 | 09 | 21 | 43 | 65 | A7 | 11 | FB | |

REGISTER 1.2A

Logically (only SS argument):

REGISTER SS ARGUMENT
RegisterSSArg
SS-Code
Call Forwarding Unconditional
TeleserviceCode
See Note 1
ForwardedToNumber
nature of address ind.: international
numbering plan ind.: ISDN/Telephony (E.164)
TBCD String: 012345678901234567890123456 7
longFTN-Supported

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 19 | 04 | 01 | 21 | 83 | 01 | Note 1 | 84 | 0F | 91 | 10 |
| | 32 | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | 10 | 32 | 54 |
| | 76 | 89 | 00 | | | | | | | | | |

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

REGISTER 1.2B

Logically (only SS argument):

REGISTER SS ARGUMENT
RegisterSSArg
SS-Code
Call Forwarding Unconditional
TeleserviceCode
See Note 1
ForwardedToNumber

nature of address ind.: international
numbering plan ind.: ISDN/Telephony (E.164)
TBCD String: 01234567890123456789012345 67

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 17 | 04 | 01 | 21 | 83 | 01 | Note 1 | 84 | 0F | 91 | 10 |
| | 32 | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | 10 | 32 | 54 |
| | 76 | | | | | | | | | | | |

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

Logically (only from operation code):

REGISTER SS RETURN RESULT
ForwardingInfo
SS-Code
- Call Forwarding Unconditional
ForwardFeatureList
ForwardingFeature
TeleserviceCode
- See Note 1
SS-Status
- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: active
longForwardedToNumber
- nature of address ind.: international
- numbering plan ind.: ISDN/Telephony (E.164)
- TBCD String: 01234567890123456789012345 67

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 0A | A0 | 1E | 04 | 01 | 21 | 30 | 19 | 30 | 17 | 83 | 01 |
| | Note 1 | 84 | 01 | 07 | 89 | 0F | 91 | 10 | 32 | 54 | 76 | 98 |
| | 10 | 32 | 54 | 76 | 98 | 10 | 32 | 54 | 76 | | | |

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

RELEASE COMPLETE (SS RETURN RESULT) 1.2B

Logically (only from operation code):

REGISTER SS RETURN RESULT
ForwardingInfo
SS-Code
- Call Forwarding Unconditional
ForwardFeatureList
ForwardingFeature
TeleserviceCode
- See Note 1
SS-Status
- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: active

Coding:

| Coding | 0A | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 | 83 | 01 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | Note 1 | 84 | 01 | 07 | | | | | | | | |

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

TERMINAL RESPONSE: SEND SS 1.4.1A

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Additional information: Operation Code and SS Parameters

Coding:

| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 22 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 0A | A0 | 1E | 04 | 01 | 21 | 30 | 19 | 30 | 17 |
| | 83 | 01 | Note 1 | 84 | 01 | 07 | 89 | 0F | 91 | 10 | 32 |
| | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | 10 | 32 | 54 |
| | 76 | | | | | | | | | | |

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

TERMINAL RESPONSE: SEND SS 1.4.1B

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Additional information: Operation Code and SS Parameters

Coding:

| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 11 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 0A | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 |
| | 83 | 01 | Note 1 | 84 | 01 | 07 | | | | | |

Note 1: TeleserviceCode is '11' for "Telephony" or is '10' for "allSpeechTransmissionServices"

**Expected Sequence 1.5 (SEND SS, interrogate CLIR status, successful, alpha identifier limits)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.5.1 | |
| 4 | ME → USER | Display "Even if the Fixed Dialling Number service is enabled, the supplementary service control string included in the SEND SS proactive command shall not be checked against those of the FDN list. Upon receiving this command, the ME shall deci" | |
| 5 | ME → USS | REGISTER 1.3 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.3 | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.5.1 | |

PROACTIVE COMMAND: SEND SS 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Even if the Fixed Dialling Number service is enabled, the supplementary service control string included in the SEND SS proactive command shall not be checked against those of the FDN list. Upon receiving this command, the ME shall deci"

SS String
- TON: Undefined
- NPI: Undefined
- SS string: "*#31#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | FD | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 |
| | 85 | 81 | EB | 45 | 76 | 65 | 6E | 20 | 69 | 66 | 20 | 74 |
| | 68 | 65 | 20 | 46 | 69 | 78 | 65 | 64 | 20 | 44 | 69 | 61 |
| | 6C | 6C | 69 | 6E | 67 | 20 | 4E | 75 | 6D | 62 | 65 | 72 |
| | 20 | 73 | 65 | 72 | 76 | 69 | 63 | 65 | 20 | 69 | 73 | 20 |
| | 65 | 6E | 61 | 62 | 6C | 65 | 64 | 2C | 20 | 74 | 68 | 65 |
| | 20 | 73 | 75 | 70 | 70 | 6C | 65 | 6D | 65 | 6E | 74 | 61 |
| | 72 | 79 | 20 | 73 | 65 | 72 | 76 | 69 | 63 | 65 | 20 | 63 |
| | 6F | 6E | 74 | 72 | 6F | 6C | 20 | 73 | 74 | 72 | 69 | 6E |
| | 67 | 20 | 69 | 6E | 63 | 6C | 75 | 64 | 65 | 64 | 20 | 69 |
| | 6E | 20 | 74 | 68 | 65 | 20 | 53 | 45 | 4E | 44 | 20 | 53 |
| | 53 | 20 | 70 | 72 | 6F | 61 | 63 | 74 | 69 | 76 | 65 | 20 |
| | 63 | 6F | 6D | 6D | 61 | 6E | 64 | 20 | 73 | 68 | 61 | 6C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 6C | 20 | 6E | 6F | 74 | 20 | 62 | 65 | 20 | 63 | 68 | 65 |
| 63 | 6B | 65 | 64 | 20 | 61 | 67 | 61 | 69 | 6E | 73 | 74 |
| 20 | 74 | 68 | 6F | 73 | 65 | 20 | 6F | 66 | 20 | 74 | 68 |
| 65 | 20 | 46 | 44 | 4E | 20 | 6C | 69 | 73 | 74 | 2E | 20 |
| 55 | 70 | 6F | 6E | 20 | 72 | 65 | 63 | 65 | 69 | 76 | 69 |
| 6E | 67 | 20 | 74 | 68 | 69 | 73 | 20 | 63 | 6F | 6D | 6D |
| 61 | 6E | 64 | 2C | 20 | 74 | 68 | 65 | 20 | 4D | 45 | 20 |
| 73 | 68 | 61 | 6C | 6C | 20 | 64 | 65 | 63 | 69 | 89 | 04 |
| FF | BA | 13 | FB | | | | | | | | |

REGISTER 1.3

Logically (only SS argument):

INTERROGATE SS ARGUMENT
SS-Code
- Calling Line Id Restriction

Coding:

| | | | | | |
|---|---|---|---|---|---|
| BER-TLV | 30 | 03 | 04 | 01 | 12 |

RELEASE COMPLETE (SS RETURN RESULT) 1.3

Logically (only from operation code):

INTERROGATE SS RESULT
CliRestrictionInfo
SS-Status
- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: not active
CliRestrictionOption
- Temporary Def Allowed

Coding:

| | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|
| Coding | 0E | A4 | 06 | 04 | 01 | 06 | 0A | 01 | 02 |

TERMINAL RESPONSE: SEND SS 1.5.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC

Result
General Result: Command performed successfully
Additional information
Operation Code: SS Code
Parameters: SS Return Result

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 0A |
| | 00 | 0E | A4 | 06 | 04 | 01 | 06 | 0A | 01 | 02 | |

**Expected Sequence 1.6A (SEND SS, call forward unconditional, all bearers, successful, null data alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.6.1 | |
| 4 | ME | Should not give any information to the user on the fact that the ME is sending an SS request | |
| 5 | ME → USS | REGISTER 1.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.1.1A | |

**Expected Sequence 1.6B (SEND SS, call forward unconditional, all bearers, successful, null data alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 1.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 1.6.1 | |
| 4 | ME | Should not give any information to the user on the fact that the ME is sending an SS request | |
| 5 | ME → USS | REGISTER 1.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.1.1B | |

PROACTIVE COMMAND: SEND SS 1.6.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: null data object
SS String
TON: International
NPI: "ISDN / telephone numbering plan"

SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 00 | 89 | 10 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 |
| | 21 | 43 | 65 | 87 | A9 | 01 | FB | | | | | |

27.22.4.11.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1 to 1.6.

## 27.22.4.11.2 SEND SS (Icon support)

### 27.22.4.11.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.11.2.2 Conformance requirement

### 27.22.4.11.2.3 Test purpose

To verify that the ME displays the text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

### 27.22.4.11.2.4 Method of test

#### 27.22.4.11.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

The elementary files are coded as Toolkit default.

27.22.4.11.2.4.2 Procedure

**Expected Sequence 2.1A (SEND SS, call forward unconditional, all bearers, successful, basic icon self explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.1.1 | [BASIC-ICON, self-explanatory] |
| 4 | ME → USER | Display the basic icon without the alpha identifier | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or<br>RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.1.1AA or<br>TERMINAL RESPONSE: SEND SS 2.1.1AB | [Command performed successfully]<br>Option AA applies if A.1/63 is supported,<br>Option AB applies if A.1/63 is not supported |

PROACTIVE COMMAND: SEND SS 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Basic Icon"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Icon Identifier:
- Icon qualifier: icon is self-explanatory
- Icon Identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2B | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | 89 |
| | 10 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 | 21 | 43 |
| | 65 | 87 | A9 | 01 | FB | 9E | 02 | 00 | 01 | | | |

TERMINAL RESPONSE: SEND SS 2.1.1AA

Logically:

Command details
- Command number: 1

Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Additional information: Operation Code and SS Parameters

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 1E |
| | 00 | 0A | A0 | 1A | 04 | 01 | 21 | 30 | 15 | 30 | 13 |
| | 83 | 01 | 00 | 84 | 01 | 07 | 89 | 0B | 91 | 10 | 32 |
| | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | | | |

TERMINAL RESPONSE: SEND SS 2.1.1AB

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Additional information: Operation Code and SS Parameters

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 11 |
| | 00 | 0A | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 |
| | 83 | 01 | 00 | 84 | 01 | 07 | | | | | |

**Expected Sequence 2.1B (SEND SS, call forward unconditional, all bearers, successful, basic icon self explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.1.1 | [BASIC-ICON, self-explanatory] |
| 4 | ME → USER | Display "Basic Icon" without the icon | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or<br>RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.1.1BA or<br>TERMINAL RESPONSE: SEND SS 2.1.1BB | [Command performed successfully, but requested icon could not be displayed]<br>Option BA applies if A.1/63 is supported,<br>Option BB applies if A.1/63 is not supported |

TERMINAL RESPONSE: SEND SS 2.1.1BA

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed
- Additional information: Operation Code and SS Parameters

Coding:

BER-TLV:

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 1E |
| 04 | 0A | A0 | 1A | 04 | 01 | 21 | 30 | 15 | 30 | 13 |
| 83 | 01 | 00 | 84 | 01 | 07 | 89 | 0B | 91 | 10 | 32 |
| 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 | | | |

TERMINAL RESPONSE: SEND SS 2.1.1BB

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed
- Additional information: Operation Code and SS Parameters

Coding:

| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 03 | 11 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 04 | 0A | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 |
| | 83 | 01 | 00 | 84 | 01 | 07 | | | | | |

**Expected Sequence 2.2A (SEND SS, call forward unconditional, all bearers, successful, colour icon self explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.2.1 | [COLOUR-ICON, self-explanatory] |
| 4 | ME → USER | Display the colour icon without thealpha identifier | |
| 5 | ME → USS | REGISTER 1.1A Or REGISTER 1.1B | Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful] Option A applies if A.1/63 is supported, Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.1.1AA or TERMINAL RESPONSE: SEND SS 2.1.1AB | [Command performed successfully] Option AA applies if A.1/63 is supported, Option AB applies if A.1/63 is not supported |

PROACTIVE COMMAND: SEND SS 2.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Colour Icon"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Icon Identifier:
- Icon qualifier: icon is self-explanatory
- Icon Identifier: record 2 in $EF_{(IMG)}$

Coding:

| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0B | 43 | 6F | 6C | 6F | 75 | 72 | 20 | 49 | 63 | 6F | 6E |
| | 89 | 10 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 | 21 |
| | 43 | 65 | 87 | A9 | 01 | FB | 9E | 02 | 00 | 02 | | |

**Expected Sequence 2.2B (SEND SS, call forward unconditional, all bearers, successful, colour icon self explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.2.1 | [COLOUR-ICON, self-explanatory] |
| 4 | ME → USER | Display "Colour Icon" without the icon | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or<br>RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.1.1BA or<br>TERMINAL RESPONSE: SEND SS 2.1.1BB | [Command performed but requested icon could not be displayed]<br>Option BA applies if A.1/63 is supported,<br>Option BB applies if A.1/63 is not supported |

**Expected Sequence 2.3A (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.3.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → USER | Display "Basic Icon" and the basic icon | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or<br>RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.1.1AA or<br>TERMINAL RESPONSE: SEND SS 2.1.1AB | [Command performed successfully]<br>Option AA applies if A.1/63 is supported,<br>Option AB applies if A.1/63 is not supported |

PROACTIVE COMMAND: SEND SS 2.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Text: "Basic Icon"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Icon Identifier

Icon qualifier: icon is non self-explanatory
Icon Identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2B | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | 89 |
| | 10 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 | 21 | 43 |
| | 65 | 87 | A9 | 01 | FB | 9E | 02 | 01 | 01 | | | |

**Expected Sequence 2.3B (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.3.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → USER | Display "Basic Icon" without the icon | |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or<br>RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.1.1BA or<br>TERMINAL RESPONSE: SEND SS 2.1.1BB | [Command performed but requested icon could not be displayed]<br>Option BA applies if A.1/63 is supported,<br>Option BB applies if A.1/63 is not supported |

**Expected Sequence 2.4 (SEND SS, call forward unconditional, all bearers, successful, basic icon non self-explanatory, no alpha identifier presented)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 2.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 2.4.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → UICC | TERMINAL RESPONSE: SEND SS 2.4.1 | [Command data not understood by ME] |

PROACTIVE COMMAND: SEND SS 2.4.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
SS String

TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789#"
Icon Identifier
Icon qualifier: icon is non self-explanatory
Icon Identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 89 |
| | 0E | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 | 09 | 21 | 43 |
| | 65 | 87 | B9 | 9E | 02 | 01 | 01 | | | | | |

TERMINAL RESPONSE: SEND SS 2.4.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command data not understood by ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 32 |

#### 27.22.4.11.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1A to 2.4.

### 27.22.4.11.3 SEND SS (UCS2 display in Cyrillic)

#### 27.22.4.11.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.3.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionnally, the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.11.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.11.3.4 Method of test

27.22.4.11.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.3.4.2 Procedure

**Expected Sequence 3.1 (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Cyrillic)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 3.1.1 | |
| 4 | ME → USER | Display "ЗДРАВСТВУЙТЕ" | ["Hello" in Russian] |
| 5 | ME → USS | REGISTER 1.1A<br>Or<br>REGISTER 1.1B | Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1A or<br>RELEASE COMPLETE (SS RETURN RESULT) 1.1B | [Successful]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 1.1.1A or<br>TERMINAL RESPONSE: SEND SS 1.1.1B | [Command performed successfully]<br>Option A applies if A.1/63 is supported,<br>Option B applies if A.1/63 is not supported |

PROACTIVE COMMAND: SEND SS 3.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha Identifier
- Data coding scheme: UCS2 (16bit)
- Text: "ЗДРАВСТВУЙТЕ"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 36 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 19 | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 |
| | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 |
| | 04 | 15 | 89 | 10 | 91 | AA | 12 | 0A | 21 | 43 | 65 | 87 |
| | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | | | | |

#### 27.22.4.11.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.11.4 SEND SS (support of Text Attribute)

#### 27.22.4.11.4.1 SEND SS (support of Text Attribute – Left Alignment)

##### 27.22.4.11.4.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.11.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

##### 27.22.4.11.4.1.3 Test purpose

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.11.4.1.4 Method of test

###### 27.22.4.11.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.1.4.2 Procedure

**Expected Sequence 4.1A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.1.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with left alignment] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.1.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.1.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.1B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.1.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with left alignment] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.1.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.1.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"

SS string: "**21*01234567890123456789*10#"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.1.2

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

REGISTER 4.1A

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

REGISTER 4.1B

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

RELEASE COMPLETE (SS RETURN RESULT) 4.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

RELEASE COMPLETE (SS RETURN RESULT) 4.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

TERMINAL RESPONSE: SEND SS 4.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

TERMINAL RESPONSE: SEND SS 4.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

#### 27.22.4.11.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.11.4.2 SEND SS (support of Text Attribute – Center Alignment)

#### 27.22.4.11.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.2.3 Test purpose

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.2.4 Method of test

##### 27.22.4.11.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.2.4.2 Procedure

**Expected Sequence 4.2A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.2.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with center alignment] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.2.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.2.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.2B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.2.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with center alignment] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.2.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.2.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 01 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.2.2

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

### 27.22.4.11.4.3 SEND SS (support of Text Attribute – Right Alignment)

#### 27.22.4.11.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.3.3 Test purpose

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.3.4 Method of test

##### 27.22.4.11.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.3.4.2 Procedure

**Expected Sequence 4.3A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.3.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with right alignment] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.3.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.3.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.3B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.3.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with right alignment] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.3.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.3.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/12, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 02 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.3.2

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 2"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Coding:

| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

### 27.22.4.11.4.4 SEND SS (support of Text Attribute – Large Font Size)

#### 27.22.4.11.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.4.3 Test purpose

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.4.4 Method of test

##### 27.22.4.11.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.4.4.2 Procedure

**Expected Sequence 4.4A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with large font size] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with normal font size] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with large font size] |
| 19 | ME → USS | REGISTER 4.1A | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with normal font size] |
| 26 | ME → USS | REGISTER 4.1A | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.4B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with large font size] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with normal font size] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with large font size] |
| 19 | ME → USS | REGISTER 4.1B | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.4.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.4.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with normal font size] |
| 26 | ME → USS | REGISTER 4.1B | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 04 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.4.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.4.3

Logically:

Command details
Command number: 1

Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

### 27.22.4.11.4.5 SEND SS (support of Text Attribute – Small Font Size)

#### 27.22.4.11.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.5.3 Test purpose

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.5.4 Method of test

##### 27.22.4.11.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.5.4.2 Procedure

**Expected Sequence 4.5A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with small font size] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with normal font size] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with small font size] |
| 19 | ME → USS | REGISTER 4.1A | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with normal font size] |
| 26 | ME → USS | REGISTER 4.1A | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.5B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with small font size] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with normal font size] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with small font size] |
| 19 | ME → USS | REGISTER 4.1B | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.5.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.5.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with normal font size] |
| 26 | ME → USS | REGISTER 4.1B | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 08 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.5.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.5.3

Logically:

Command details
Command number: 1

Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

### 27.22.4.11.4.6 SEND SS (support of Text Attribute – Bold On)

#### 27.22.4.11.4.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.6.3 Test purpose

To verify that the ME displays the alpha identifier according to the bold text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.6.4 Method of test

##### 27.22.4.11.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.6.4.2 Procedure

**Expected Sequence 4.6A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with bold on] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with bold off] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with bold on] |
| 19 | ME → USS | REGISTER 4.1A | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with bold off] |
| 26 | ME → USS | REGISTER 4.1A | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.6B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with bold on] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with bold off] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with bold on] |
| 19 | ME → USS | REGISTER 4.1B | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.6.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.6.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with bold off] |
| 26 | ME → USS | REGISTER 4.1B | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*0123456789012345678 9*10#"

Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 10 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.6.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.6.3

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

### 27.22.4.11.4.7 SEND SS (support of Text Attribute – Italic On)

#### 27.22.4.11.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.7.3 Test purpose

To verify that the ME displays the alpha identifier according to the italic text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.7.4 Method of test

##### 27.22.4.11.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.7.4.2 Procedure

**Expected Sequence 4.7A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with italic on] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with italic off] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with italic on] |
| 19 | ME → USS | REGISTER 4.1A | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with italic off] |
| 26 | ME → USS | REGISTER 4.1A | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.7B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with italic on] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with italic off] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with italic on] |
| 19 | ME → USS | REGISTER 4.1B | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.7.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.7.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with italic off] |
| 26 | ME → USS | REGISTER 4.1B | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 20 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.7.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.7.3

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities

Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

### 27.22.4.11.4.8 SEND SS (support of Text Attribute – Underline On)

#### 27.22.4.11.4.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.8.3 Test purpose

To verify that the ME displays the alpha identifier according to the underline text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.8.4 Method of test

##### 27.22.4.11.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.8.4.2 Procedure

**Expected Sequence 4.8A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with underline on] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with underline off] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with underline on] |
| 19 | ME → USS | REGISTER 4.1A | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with underline off] |
| 26 | ME → USS | REGISTER 4.1A | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.8B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with underline on] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with underline off] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with underline on] |
| 19 | ME → USS | REGISTER 4.1B | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.8.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.8.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with underline off] |
| 26 | ME → USS | REGISTER 4.1B | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 40 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.8.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.8.3

Logically:

Command details
Command number: 1

Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

### 27.22.4.11.4.9 SEND SS (support of Text Attribute – Strikethrough On)

#### 27.22.4.11.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.9.3 Test purpose

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.9.4 Method of test

##### 27.22.4.11.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.9.4.2 Procedure

**Expected Sequence 4.9A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with strikethrough on] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with strikethrough off] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with strikethrough on] |
| 19 | ME → USS | REGISTER 4.1A | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with strikethrough off] |
| 26 | ME → USS | REGISTER 4.1A | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.9B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with strikethrough on] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with strikethrough off] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with strikethrough on] |
| 19 | ME → USS | REGISTER 4.1B | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.9.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.9.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Message shall be formatted with strikethrough off] |
| 26 | ME → USS | REGISTER 4.1B | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.9.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

SS String

TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 80 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.9.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.9.3

Logically:

Command details

Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

### 27.22.4.11.4.10 SEND SS (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.11.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Send SS facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5.

#### 27.22.4.11.4.10.3 Test purpose

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.4.10.4 Method of test

##### 27.22.4.11.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.11.4.10.4.2 Procedure

**Expected Sequence 4.10A (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.10.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with foreground and background colour according to text attribute configuration] |
| 5 | ME → USS | REGISTER 4.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.10.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.10.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with ME"s default foreground and background colour] |
| 12 | ME → USS | REGISTER 4.1A | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1A | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1A | |

**Expected Sequence 4.10B (SEND SS, call forward unconditional, all bearers, successful, alpha identifier with Text attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.10.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with foreground and background colour according to text attribute configuration] |
| 5 | ME → USS | REGISTER 4.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 4.10.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND SS 4.10.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with ME"s default foreground and background colour] |
| 12 | ME → USS | REGISTER 4.1B | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1B | [Successful] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND SS 4.1.1B | |

PROACTIVE COMMAND: SEND SS 4.10.1

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 33 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | D0 |
| | 04 | 00 | 10 | 00 | B4 | | | | | | | |

PROACTIVE COMMAND: SEND SS 4.10.2

Logically:

Command details
Command number: 1
Command type: SEND SS
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
SS String
TON: International
NPI: "ISDN / telephone numbering plan"
SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 89 | 10 | 91 | AA | 12 | 0A | 21 |
| | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | |

#### 27.22.4.11.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

### 27.22.4.11.5 SEND SS (UCS2 display in Chinese)

#### 27.22.4.11.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.5.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionnally, the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.11.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.5.4 Method of test

##### 27.22.4.11.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.11.5.4.2 Procedure

**Expected Sequence 5.1A (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Chinese)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 5.1.1 | |
| 4 | ME → USER | Display "你好" | ["Hello" in Chinese] |
| 5 | ME → USS | REGISTER 5.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 5.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 5.1.1A | [Command performed successfully] |

**Expected Sequence 5.1B (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Chinese)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 5.1.1 | |
| 4 | ME → USER | Display "你好" | ["Hello" in Chinese] |
| 5 | ME → USS | REGISTER 5.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 5.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 5.1.1B | [Command performed successfully] |

PROACTIVE COMMAND: SEND SS 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Data coding scheme: UCS2 (16bit)
- Text: "你好"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 4F | 60 | 59 | 7D | 89 | 10 | 91 | AA | 12 | 0A |
| | 21 | 43 | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB |

REGISTER 5.1A

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

REGISTER 5.1B

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

RELEASE COMPLETE (SS RETURN RESULT) 5.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

RELEASE COMPLETE (SS RETURN RESULT) 5.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

TERMINAL RESPONSE: SEND SS 5.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

TERMINAL RESPONSE: SEND SS 5.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

#### 27.22.4.11.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.11.6 SEND SS (UCS2 display in Katakana)

#### 27.22.4.11.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.11.6.2 Conformance requirement

The ME shall support the Proactive UICC: SEND SHORT MESSAGE facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.11, clause 6.6.10, clause 8.12.1 , clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.14, clause 8.31 and clause 6.5

Additionnally, the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.11.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND SS proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.11.6.4 Method of test

##### 27.22.4.11.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.11.6.4.2 Procedure

**Expected Sequence 6.1A (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Katakana)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 6.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 6.1.1 | |
| 4 | ME → USER | Display "ル" | [Character in Katakana] |
| 5 | ME → USS | REGISTER 6.1A | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 6.1A | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 6.1.1A | [Command performed successfully] |

**Expected Sequence 6.1B (SEND SS, call forward unconditional, all bearers, successful, UCS2 text in Katakana)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND SS 6.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND SS 6.1.1 | |
| 4 | ME → USER | Display "ル" | [Character in Katakana] |
| 5 | ME → USS | REGISTER 6.1B | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 6.1B | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND SS 6.1.1B | [Command performed successfully] |

PROACTIVE COMMAND: SEND SS 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SS
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Data coding scheme: UCS2 (16bit)
- Text: "ル"

SS String
- TON: International
- NPI: "ISDN / telephone numbering plan"
- SS string: "**21*01234567890123456789*10#"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 11 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 03 | 80 | 30 | EB | 89 | 10 | 91 | AA | 12 | 0A | 21 | 43 |
| | 65 | 87 | 09 | 21 | 43 | 65 | 87 | A9 | 01 | FB | | |

REGISTER 6.1A

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1A

REGISTER 6.1B

Same as cl 27.22.4.11.1.4.2 REGISTER 1.1B

RELEASE COMPLETE (SS RETURN RESULT) 6.1A

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1A

RELEASE COMPLETE (SS RETURN RESULT) 6.1B

Same as cl 27.22.4.11.1.4.2 RELEASE COMPLETE (SS RETURN RESULT) 1.1B

TERMINAL RESPONSE: SEND SS 6.1.1A

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1A

TERMINAL RESPONSE: SEND SS 6.1.1B

Same as cl 27.22.4.11.1.4.2 TERMINAL RESPONSE: SEND SS 1.1.1B

#### 27.22.4.11.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.12 SEND USSD

### 27.22.4.12.1 SEND USSD (normal)

#### 27.22.4.12.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.12.1.3 Test purpose

To verify that the ME correctly translates and sends the unstructured supplementary service request indicated in the SEND USSD proactive UICC command to the USS.

To verify that the ME returns a TERMINAL RESPONSE command to the UICC indicating the status of the transmission of the USSD request and including a USSD result as a text string in the TERMINAL RESPONSE.

#### 27.22.4.12.1.4 Method of test

##### 27.22.4.12.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.1.4.2 Procedure

**Expected Sequence 1.1 (SEND USSD, 7-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.1.1 | |
| 4 | ME → USER | Display "7-bit USSD" | |
| 5 | ME → USS | REGISTER 1.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.1.1 | |

PROACTIVE COMMAND: SEND USSD 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "7-bit USSD"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 50 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 37 | 2D | 62 | 69 | 74 | 20 | 55 | 53 | 53 | 44 | 8A |
| | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 | E5 | 92 |
| | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E | B1 | 59 |
| | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD | 5E | B3 |
| | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B | 3E | AF |
| | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 | | |

REGISTER 1.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT
- USSD-DataCodingScheme:
- 7-bit default, no message class
- USSD string:
- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 3D | 04 | 01 | F0 | 04 | 38 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |
| | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| | C3 | E5 | 60 | | | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 1.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD string:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 1E | 04 | 01 | F0 | 04 | 19 | D5 | E9 | 94 | 08 | 9A |
| | D3 | E5 | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 |
| | 0C | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

TERMINAL RESPONSE: SEND USSD 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

**Expected Sequence 1.2 (SEND USSD, 8-bit data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.2.1 | |
| 4 | ME → USER | Display "8-bit USSD" | |
| 5 | ME → USS | REGISTER 1.2 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.2 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.2.1 | |

PROACTIVE COMMAND: SEND USSD 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "8-bit USSD"

USSD String
- Data coding scheme: Uncompressed, no message class meaning, 8-bit data
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 58 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 38 | 2D | 62 | 69 | 74 | 20 | 55 | 53 | 53 | 44 | 8A |
| | 41 | 44 | 41 | 42 | 43 | 44 | 45 | 46 | 47 | 48 | 49 | 4A |
| | 4B | 4C | 4D | 4E | 4F | 50 | 51 | 52 | 53 | 54 | 55 | 56 |
| | 57 | 58 | 59 | 5A | 2D | 61 | 62 | 63 | 64 | 65 | 66 | 67 |
| | 68 | 69 | 6A | 6B | 6C | 6D | 6E | 6F | 70 | 71 | 72 | 73 |
| | 74 | 75 | 76 | 77 | 78 | 79 | 7A | 2D | 31 | 32 | 33 | 34 |
| | 35 | 36 | 37 | 38 | 39 | 30 | | | | | | |

REGISTER 1.2

Logically (only USSD argument):

ProcessUnstructuredSS-Request ARGUMENT
- USSD-DataCodingScheme:
- Uncompressed, no message class meaning, 8-bit data
- USSD string:
- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 45 | 04 | 01 | 44 | 04 | 40 | 41 | 42 | 43 | 44 | 45 |
| | 46 | 47 | 48 | 49 | 4A | 4B | 4C | 4D | 4E | 4F | 50 | 51 |
| | 52 | 53 | 54 | 55 | 56 | 57 | 58 | 59 | 5A | 2D | 61 | 62 |
| | 63 | 64 | 65 | 66 | 67 | 68 | 69 | 6A | 6B | 6C | 6D | 6E |
| | 6F | 70 | 71 | 72 | 73 | 74 | 75 | 76 | 77 | 78 | 79 | 7A |
| | 2D | 31 | 32 | 33 | 34 | 35 | 36 | 37 | 38 | 39 | 30 | |

RELEASE COMPLETE (SS RETURN RESULT) 1.2

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- Uncompressed, no message class meaning, 8-bit data
USSD string:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 21 | 04 | 01 | 44 | 04 | 1C | 55 | 53 | 53 | 44 | 20 |
| | 73 | 74 | 72 | 69 | 6E | 67 | 20 | 72 | 65 | 63 | 65 | 69 |
| | 76 | 65 | 64 | 20 | 66 | 72 | 6F | 6D | 20 | 53 | 53 | |

TERMINAL RESPONSE: SEND USSD 1.2.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: Uncompressed, no message class meaning, 8-bit data
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1D | 04 | 55 | 53 | 53 | 44 | 20 | 73 | 74 |
| | 72 | 69 | 6E | 67 | 20 | 72 | 65 | 63 | 65 | 69 | 76 |
| | 65 | 64 | 20 | 66 | 72 | 6F | 6D | 20 | 53 | 53 | |

**Expected Sequence 1.3 (SEND USSD, UCS2 data, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.3.1 | |
| 4 | ME → USER | Display "UCS2 USSD" | |
| 5 | ME → USS | REGISTER 1.3 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.3 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.3.1 | |

PROACTIVE COMMAND: SEND USSD 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "UCS2 USSD"

USSD String
- Data coding scheme: Uncompressed, no message class meaning, UCS2 (16 bit)
- USSD string: "ЗДРАВСТВУЙТЕ" ("Hello" in Russian)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2F | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 09 | 55 | 43 | 53 | 32 | 20 | 55 | 53 | 53 | 44 | 8A | 19 |
| | 48 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 | 04 |
| | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 | 04 |
| | 15 | | | | | | | | | | | |

REGISTER 1.3

Logically (only USSD argument):

ProcessUnstructuredSS-Request ARGUMENT
- USSD-DataCodingScheme:
- Uncompressed, no message class meaning, UCS2 (16 bit)
- USSD string:
- "ЗДРАВСТВУЙТЕ" ("Hello" in Russian)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 1D | 04 | 01 | 48 | 04 | 18 | 04 | 17 | 04 | 14 | 04 |
| | 20 | 04 | 10 | 04 | 12 | 04 | 21 | 04 | 22 | 04 | 12 | 04 |
| | 23 | 04 | 19 | 04 | 22 | 04 | 15 | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 1.3

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- Uncompressed, no message class meaning, UCS2 (16 bit)
USSD string:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 3D | 04 | 01 | 48 | 04 | 38 | 00 | 55 | 00 | 53 | 00 |
| | 53 | 00 | 44 | 00 | 20 | 00 | 73 | 00 | 74 | 00 | 72 | 00 |
| | 69 | 00 | 6E | 00 | 67 | 00 | 20 | 00 | 72 | 00 | 65 | 00 |
| | 63 | 00 | 65 | 00 | 69 | 00 | 76 | 00 | 65 | 00 | 64 | 00 |
| | 20 | 00 | 66 | 00 | 72 | 00 | 6F | 00 | 6D | 00 | 20 | 00 |
| | 53 | 00 | 53 | | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 1.3.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: Uncompressed, no message class meaning, UCS2 (16 bit)
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 39 | 08 | 00 | 55 | 00 | 53 | 00 | 53 | 00 |
| | 44 | 00 | 20 | 00 | 73 | 00 | 74 | 00 | 72 | 00 | 69 |
| | 00 | 6E | 00 | 67 | 00 | 20 | 00 | 72 | 00 | 65 | 00 |
| | 63 | 00 | 65 | 00 | 69 | 00 | 76 | 00 | 65 | 00 | 64 |
| | 00 | 20 | 00 | 66 | 00 | 72 | 00 | 6F | 00 | 6D | 00 |
| | 20 | 00 | 53 | 00 | 53 | | | | | | |

**Expected Sequence 1.4 (SEND USSD, 7-bit data, unsuccessful (Return Error))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.1.1 | |
| 4 | ME → USER | Display "7-bit USSD" | |
| 5 | ME → USS | REGISTER 1.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN ERROR) 1.1 | Return Error |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.4.1 | |

RELEASE COMPLETE (SS RETURN ERROR) 1.1

Logically (only from Return Error code):

ProcessUnstructuredSS-Request RETURN ERROR
Return Error code:
- Unknown alphabet

Coding:

| | | | |
|---|---|---|---|
| Coding | 02 | 01 | 47 |

TERMINAL RESPONSE: SEND USSD 1.4.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: USSD Return Error
Additional information: "Unknown alphabet"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 02 |
| | 37 | 47 | | | | | | | | | |

**Expected Sequence 1.5 (SEND USSD, 7-bit data, unsuccessful (Reject))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.1.1 | |
| 4 | ME → USER | Display "7-bit USSD" | |
| 5 | ME → USS | REGISTER 1.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS REJECT) 1.1 | Reject |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.5.1 | |

RELEASE COMPLETE (SS REJECT) 1.1

Logically (only from Problem code):

ProcessUnstructuredSS-Request REJECT
Invoke Problem code:
- Mistyped parameter

Coding:

| Coding | 81 | 01 | 02 |
|---|---|---|---|

TERMINAL RESPONSE: SEND USSD 1.5.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: USSD Return Error
Additional information: "No specific cause can be given"

Coding:

| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 02 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 37 | 00 | | | | | | | | | |

**Expected Sequence 1.6 (SEND USSD, 256 octets, 7-bit data, successful, long alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.6.1 | |
| 4 | ME → USER | Display "once a RELEASE COMPLETE message containing the USSD Return Result message not containing an error has been received from the network, the ME shall inform the UICC that the command has" | |
| 5 | ME → USS | REGISTER 1.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.1.1 | |

PROACTIVE COMMAND: SEND USSD 1.6.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "once a RELEASE COMPLETE message containing the USSD Return Result message not containing an error has been received from the network, the ME shall inform the UICC that the command has"

USSD String

Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | FD | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 |
| | 85 | 81 | B6 | 6F | 6E | 63 | 65 | 20 | 61 | 20 | 52 | 45 |
| | 4C | 45 | 41 | 53 | 45 | 20 | 43 | 4F | 4D | 50 | 4C | 45 |
| | 54 | 45 | 20 | 6D | 65 | 73 | 73 | 61 | 67 | 65 | 20 | 63 |
| | 6F | 6E | 74 | 61 | 69 | 6E | 69 | 6E | 67 | 20 | 74 | 68 |
| | 65 | 20 | 55 | 53 | 53 | 44 | 20 | 52 | 65 | 74 | 75 | 72 |
| | 6E | 20 | 52 | 65 | 73 | 75 | 6C | 74 | 20 | 6D | 65 | 73 |
| | 73 | 61 | 67 | 65 | 20 | 6E | 6F | 74 | 20 | 63 | 6F | 6E |
| | 74 | 61 | 69 | 6E | 69 | 6E | 67 | 20 | 61 | 6E | 20 | 65 |
| | 72 | 72 | 6F | 72 | 20 | 68 | 61 | 73 | 20 | 62 | 65 | 65 |
| | 6E | 20 | 72 | 65 | 63 | 65 | 69 | 76 | 65 | 64 | 20 | 66 |
| | 72 | 6F | 6D | 20 | 74 | 68 | 65 | 20 | 6E | 65 | 74 | 77 |
| | 6F | 72 | 6B | 2C | 20 | 74 | 68 | 65 | 20 | 4D | 45 | 20 |
| | 73 | 68 | 61 | 6C | 6C | 20 | 69 | 6E | 66 | 6F | 72 | 6D |
| | 20 | 74 | 68 | 65 | 20 | 53 | 49 | 4D | 20 | 74 | 68 | 61 |
| | 74 | 20 | 74 | 68 | 65 | 20 | 63 | 6F | 6D | 6D | 61 | 6E |
| | 64 | 20 | 68 | 61 | 73 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

**Expected Sequence 1.7 (SEND USSD, 7-bit data, successful, no alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.7.1 | |
| 4 | ME → USER | Optionally display an informative message | |
| 5 | ME → USS | REGISTER 1.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.1.1 | |

PROACTIVE COMMAND: SEND USSD 1.7.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 44 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 8A |
| | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 | E5 | 92 |
| | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E | B1 | 59 |
| | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD | 5E | B3 |
| | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B | 3E | AF |
| | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 | | |

**Expected Sequence 1.8 (SEND USSD, 7-bit data, successful, null length alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 1.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 1.8.1 | |
| 4 | ME → USER | the ME should not give any information to the user on the fact that the ME is sending a USSD request | |
| 5 | ME → USS | REGISTER 1.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 1.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 1.1.1 | |

PROACTIVE COMMAND: SEND USSD 1.8.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: ""
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 46 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 00 | 8A | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 |
| | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E |
| | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD |
| | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B |
| | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 |

#### 27.22.4.12.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 - 1.8.

### 27.22.4.12.2 SEND USSD (Icon support)

#### 27.22.4.12.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.2.2 Conformance requirement

#### 27.22.4.12.2.3 Test purpose

To verify that the ME displays the text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

#### 27.22.4.12.2.4 Method of test

##### 27.22.4.12.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS

The elementary files are coded as Toolkit default.

##### 27.22.4.12.2.4.2 Procedure

**Expected Sequence 2.1A (SEND USSD, 7-bit data, successful, basic icon self explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 2.1.1 | [BASIC-ICON, self-explanatory] |
| 4 | ME → USER | Display BASIC ICON | |
| 5 | ME → USS | REGISTER 2.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 2.1.1A | [Command performed successfully] |

PROACTIVE COMMAND: SEND USSD 2.1.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Basic Icon"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Icon Identifier:
Icon qualifier: icon is self-explanatory
Icon Identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 54 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | 8A |
| | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 | E5 | 92 |
| | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E | B1 | 59 |
| | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD | 5E | B3 |
| | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B | 3E | AF |
| | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 | 9E | 02 |
| | 00 | 01 | | | | | | | | | | |

REGISTER 2.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD string:
- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 3D | 04 | 01 | F0 | 04 | 38 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |
| | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| | C3 | E5 | 60 | | | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 2.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD string:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 1E | 04 | 01 | F0 | 04 | 19 | D5 | E9 | 94 | 08 | 9A |
| | D3 | E5 | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 |
| | 0C | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

TERMINAL RESPONSE: SEND USSD 2.1.1A

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

**Expected Sequence 2.1B (SEND USSD, 7-bit data, successful, basic icon self explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 2.1.1 | [BASIC-ICON, self-explanatory] |
| 4 | ME → USER | Display "Basic Icon" without the icon | |
| 5 | ME → USS | REGISTER 2.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 2.1.1B | [Command performed but requested icon could not be displayed] |

TERMINAL RESPONSE: SEND USSD 2.1.1B

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 04 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

**Expected Sequence 2.2 (SEND USSD, 7-bit data, successful, colour icon self explanatory)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 2.2.1 | [COLOUR-ICON, self-explanatory] |
| 4 | ME → USER | Display COLOUR-ICON<br>or<br>May give information to user concerning what is happening | |
| 5 | ME → USS | REGISTER 2.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 2.1.1A<br>or<br>TERMINAL RESPONSE: SEND USSD 2.1.1B | [Command performed successfully]<br>or<br>[Command performed but requested icon could not be displayed] |

PROACTIVE COMMAND: SEND USSD 2.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Color Icon"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Icon Identifier:
- Icon qualifier: icon is self-explanatory
- Icon Identifier: record 2 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 54 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 43 | 6F | 6C | 6F | 72 | 20 | 49 | 63 | 6F | 6E | 8A |
| | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 | E5 | 92 |
| | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E | B1 | 59 |
| | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD | 5E | B3 |
| | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B | 3E | AF |
| | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 | 9E | 02 |
| | 00 | 02 | | | | | | | | | | |

**Expected Sequence 2.3A (SEND USSD, 7-bit data, successful, basic icon non self-explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 2.3.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → USER | Display "Basic Icon" and BASIC-ICON | |
| 5 | ME → USS | REGISTER 2.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 2.1.1A | [Command performed successfully] |

PROACTIVE COMMAND: SEND USSD 2.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Basic Icon"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Icon Identifier
- Icon qualifier: icon is non self-explanatory
- Icon Identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 54 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | 8A |
| | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 | E5 | 92 |
| | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E | B1 | 59 |
| | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD | 5E | B3 |
| | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B | 3E | AF |
| | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 | 9E | 02 |
| | 01 | 01 | | | | | | | | | | |

**Expected Sequence 2.3B (SEND USSD, 7-bit data, successful, basic icon non self-explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 2.3.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → USER | Display "Basic Icon" without the icon | |
| 5 | ME → USS | REGISTER 2.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 2.1.1B | [Command performed but requested icon could not be displayed] |

**Expected Sequence 2.4 (SEND USSD, 7-bit data, basic icon non self-explanatory, no alpha identifier presented)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 2.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 2.4.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → UICC | TERMINAL RESPONSE: SEND USSD 2.4.1 | [Command data not understood by ME] |

PROACTIVE COMMAND: SEND USSD 2.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

Icon Identifier
- Icon qualifier: icon is non self-explanatory
- Icon Identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 48 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 8A |
| | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 | 49 | E5 | 92 |
| | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 | 5E | B1 | 59 |
| | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A | AD | 5E | B3 |
| | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 | 3B | 3E | AF |
| | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 | 60 | 9E | 02 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 2.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command data not understood by ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 32 |

#### 27.22.4.12.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 - 2.4.

### 27.22.4.12.3 SEND USSD (UCS2 display in Cyrillic)

#### 27.22.4.12.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.12.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.3.4 Method of test

##### 27.22.4.12.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.3.4.2 Procedure

**Expected Sequence 3.1 (SEND USSD, 7-bit data, successful, UCS2 text in Cyrillic)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 3.1.1 | |
| 4 | ME → USER | Display "ЗДРАВСТВУЙТЕ" | ["Hello" in Russian] |
| 5 | ME → USS | REGISTER 3.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 3.1 | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 3.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND USSD 3.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Data coding scheme: UCS2 (16bit)
- Text: "ЗДРАВСТВУЙТЕ"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD String: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5F | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 19 | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 |
| | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 |
| | 04 | 15 | 8A | 39 | F0 | 41 | E1 | 90 | 58 | 34 | 1E | 91 |
| | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 | 5A | B5 |
| | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 | 33 | 3A |
| | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 | EB | F6 |
| | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 | C3 | E5 |
| | 60 | | | | | | | | | | | |

REGISTER 3.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT
- USSD-DataCodingScheme:
- 7-bit default, no message class
- USSD String:
- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 3D | 04 | 01 | F0 | 04 | 38 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |
| | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| | C3 | E5 | 60 | | | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 3.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD String:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 1E | 04 | 01 | F0 | 04 | 19 | D5 | E9 | 94 | 08 | 9A |
| | D3 | E5 | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 |
| | 0C | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

TERMINAL RESPONSE: SEND USSD 3.1.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.12.4 SEND USSD (support of Text Attribute)

#### 27.22.4.12.4.1 SEND USSD (support of Text Attribute – Left Alignment)

##### 27.22.4.12.4.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.12.4.1.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

##### 27.22.4.12.4.1.3 Test purpose

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.12.4.1.4 Method of test

###### 27.22.4.12.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.1.4.2 Procedure

**Expected Sequence 4.1 (SEND USSD, 7-bit data, successful, with Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.1.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with left alignment] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.1.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.1.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.1.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/13, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.1.1 | |

PROACTIVE COMMAND: SEND USSD 4.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.1.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

REGISTER 4.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD string:
- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 30 | 3D | 04 | 01 | F0 | 04 | 40 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| C3 | E5 | 60 | | | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 4.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD string:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 30 | 1E | 04 | 01 | F0 | 04 | 19 | D5 | E9 | 94 | 08 | 9A |
| | D3 | E5 | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 |
| | 0C | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

TERMINAL RESPONSE: SEND USSD 4.1.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

27.22.4.12.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

27.22.4.12.4.2 SEND USSD (support of Text Attribute – Center Alignment)

27.22.4.12.4.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.2.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

27.22.4.12.4.2.3 Test purpose

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.2.4 Method of test

27.22.4.12.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.2.4.2 Procedure

**Expected Sequence 4.2 (SEND USSD, 7-bit data, successful, with Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.2.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with center alignment] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.2.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.2.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.2.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/13, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.2.1 | |

PROACTIVE COMMAND: SEND USSD 4.2.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 1"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 01 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.2.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

### 27.22.4.12.4.3 SEND USSD (support of Text Attribute – Right Alignment)

#### 27.22.4.12.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.4.3.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

27.22.4.12.4.3.3 Test purpose

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.3.4 Method of test

27.22.4.12.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.3.4.2 Procedure

**Expected Sequence 4.3 (SEND USSD, 7-bit data, successful, with Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.3.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with right alignment] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.3.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.3.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.3.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/13, no alignment change will take place] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.3.1 | |

PROACTIVE COMMAND: SEND USSD 4.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
- Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute

Formatting position: 0
Formatting length: 16
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 02 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.3.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

### 27.22.4.12.4.4 SEND USSD (support of Text Attribute – Large Font Size)

#### 27.22.4.12.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.4.4.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.4.3 Test purpose

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.4.4 Method of test

##### 27.22.4.12.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.4.4.2 Procedure

**Expected Sequence 4.4 (SEND USSD, 7-bit data, successful, with Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.4.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with large font size] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.4.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.4.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.4.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed with normal font size] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.4.1 | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.4.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.4.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with large font size] |
| 19 | ME → USS | REGISTER 4.1 | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.4.1 | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.4.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.4.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Alpha identifier is displayed with normal font size] |
| 26 | ME → USS | REGISTER 4.1 | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.4.1 | |

PROACTIVE COMMAND: SEND USSD 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 04 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.4.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.4.3

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 3"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

### 27.22.4.12.4.5 SEND USSD (support of Text Attribute – Small Font Size)

#### 27.22.4.12.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.4.5.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.5.3 Test purpose

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.5.4 Method of test

##### 27.22.4.12.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.5.4.2 Procedure

**Expected Sequence 4.5 (SEND USSD, 7-bit data, successful, with Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.5.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with small font size] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.5.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.5.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.5.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed with normal font size] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.5.1 | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.5.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.5.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with small font size] |
| 19 | ME → USS | REGISTER 4.1 | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.5.1 | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.5.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.5.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Alpha identifier is displayed with normal font size] |
| 26 | ME → USS | REGISTER 4.1 | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.5.1 | |

PROACTIVE COMMAND: SEND USSD 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 08 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.5.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.5.3

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 3"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

### 27.22.4.12.4.6 SEND USSD (support of Text Attribute – Bold On)

#### 27.22.4.12.4.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.4.6.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.6.3 Test purpose

To verify that the ME displays the alpha identifier according to the bold text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.6.4 Method of test

##### 27.22.4.12.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.6.4.2 Procedure

**Expected Sequence 4.6 (SEND USSD, 7-bit data, successful, with Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.6.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with bold on] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.6.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.6.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.6.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed with bold off] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.6.1 | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.6.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.6.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with bold on] |
| 19 | ME → USS | REGISTER 4.1 | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.6.1 | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.6.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.6.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Alpha identifier is displayed with bold off] |
| 26 | ME → USS | REGISTER 4.1 | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.6.1 | |

PROACTIVE COMMAND: SEND USSD 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
- Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute

Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 10 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.6.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute

Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.6.3

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 3"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

### 27.22.4.12.4.7 SEND USSD (support of Text Attribute – Italic On)

#### 27.22.4.12.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.4.7.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.7.3 Test purpose

To verify that the ME displays the alpha identifier according to the italic text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.7.4 Method of test

##### 27.22.4.12.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.7.4.2 Procedure

**Expected Sequence 4.7 (SEND USSD, 7-bit data, successful, with Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.7.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with italic on] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.7.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.7.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.7.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed with italic off] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.7.1 | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.7.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.7.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with italic on] |
| 19 | ME → USS | REGISTER 4.1 | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.7.1 | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.7.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.7.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Alpha identifier is displayed with italic off] |
| 26 | ME → USS | REGISTER 4.1 | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.7.1 | |

PROACTIVE COMMAND: SEND USSD 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
- Data coding scheme: 7-bit default, no message class

USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute

Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 20 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.7.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute

Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.7.3

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 3"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

27.22.4.12.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

27.22.4.12.4.8 SEND USSD (support of Text Attribute – Underline On)

27.22.4.12.4.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.8.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

27.22.4.12.4.8.3 Test purpose

To verify that the ME displays the alpha identifier according to the underline text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.8.4 Method of test

27.22.4.12.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.8.4.2 Procedure

**Expected Sequence 4.8 (SEND USSD, 7-bit data, successful, with Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.8.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with underline on] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.8.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.8.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.8.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed with underline off] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.8.1 | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.8.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.8.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with underline on] |
| 19 | ME → USS | REGISTER 4.1 | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.8.1 | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.8.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.8.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Alpha identifier is displayed with underline off] |
| 26 | ME → USS | REGISTER 4.1 | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.8.1 | |

PROACTIVE COMMAND: SEND USSD 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 40 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.8.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.8.3

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 3"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

### 27.22.4.12.4.9 SEND USSD (support of Text Attribute – Strikethrough On)

#### 27.22.4.12.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.4.9.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

#### 27.22.4.12.4.9.3 Test purpose

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.4.9.4 Method of test

##### 27.22.4.12.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.9.4.2 Procedure

**Expected Sequence 4.9 (SEND USSD, 7-bit data, successful, with Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.9.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with strikethrough on] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.9.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.9.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.9.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Alpha identifier is displayed with strikethrough off] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.9.1 | |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.9.1 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.9.1 | |
| 18 | ME → USER | Display "Text Attribute 1" | [Alpha identifier is displayed with strikethrough on] |
| 19 | ME → USS | REGISTER 4.1 | |
| 20 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 21 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.9.1 | |
| 22 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.9.3 | |
| 23 | ME → UICC | FETCH | |
| 24 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.9.3 | |
| 25 | ME → USER | Display "Text Attribute 3" | [Alpha identifier is displayed with strikethrough off] |
| 26 | ME → USS | REGISTER 4.1 | |
| 27 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.9.1 | |

PROACTIVE COMMAND: SEND USSD 4.9.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 80 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.9.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.9.3

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 3"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 33 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.9.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

27.22.4.12.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.12.4.10 SEND USSD (support of Text Attribute – Foreground and Background Colour)

27.22.4.12.4.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.12.4.10.2 Conformance requirement

The terminal shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

27.22.4.12.4.10.3 Test purpose

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.12.4.10.4 Method of test

27.22.4.12.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.

The elementary files are coded as UICC default. Prior to this test the terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.4.10.4.2 Procedure

**Expected Sequence 4.10 (SEND USSD, 7-bit data, successful, with Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.10.1 | |
| 4 | ME → USER | Display "Text Attribute 1" | [Message shall be formatted with foreground and background colour according to text attribute configuration] |
| 5 | ME → USS | REGISTER 4.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.10.1 | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 4.10.2 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND USSD 4.10.2 | |
| 11 | ME → USER | Display "Text Attribute 2" | [Message shall be formatted with ME"s default foreground and background colour] |
| 12 | ME → USS | REGISTER 4.1 | |
| 13 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 4.1 | ["USSD string received from SS"] |
| 14 | ME → UICC | TERMINAL RESPONSE: SEND USSD 4.10.1 | |

PROACTIVE COMMAND: SEND USSD 4.10.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Text Attribute 1"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 5C | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 31 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| 76 | C3 | E5 | 60 | D0 | 04 | 00 | 10 | 00 | B4 | | |

PROACTIVE COMMAND: SEND USSD 4.10.2

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Text Attribute 2"
USSD String
Data coding scheme: 7-bit default, no message class
USSD string: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 56 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 10 | 54 | 65 | 78 | 74 | 20 | 41 | 74 | 74 | 72 | 69 | 62 |
| | 75 | 74 | 65 | 20 | 32 | 8A | 39 | F0 | 41 | E1 | 90 | 58 |
| | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 |
| | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB |
| | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F |
| | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD |
| | 76 | C3 | E5 | 60 | | | | | | | | |

TERMINAL RESPONSE: SEND USSD 4.10.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

### 27.22.4.12.5 SEND USSD (UCS2 display in Chinese)

#### 27.22.4.12.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.

- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.12.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.5.4 Method of test

##### 27.22.4.12.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.12.5.4.2 Procedure

**Expected Sequence 5.1 (SEND USSD, 7-bit data, successful, UCS2 text in Chinese)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 5.1.1 | |
| 4 | ME → USER | Display "你好" | ["Hello" in Chinese] |
| 5 | ME → USS | REGISTER 5.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 5.1 | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND USSD 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Data coding scheme: UCS2 (16bit)
- Text: "你好"

USSD String
- Data coding scheme: 7-bit default, no message class
- USSD String: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4B | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 4F | 60 | 59 | 7D | 8A | 39 | F0 | 41 | E1 | 90 |
| | 58 | 34 | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 |
| | E9 | 94 | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 |
| | CB | E6 | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E |
| | 9F | D3 | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A |
| | CD | 76 | C3 | E5 | 60 | | | | | | | |

REGISTER 5.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT
- USSD-DataCodingScheme:
  - 7-bit default, no message class
- USSD String:
  - "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 30 | 3D | 04 | 01 | F0 | 04 | 38 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |
| | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| | C3 | E5 | 60 | | | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 5.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- 7-bit default, no message class

USSD String:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 30 | 1E | 04 | 01 | 00 | 04 | 19 | D5 | E9 | 94 | 08 | 9A |
| | D3 | E5 | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 |
| | 0C | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

TERMINAL RESPONSE: SEND USSD 5.1.1

Logically:

Command details
Command number: 1
Command type: SEND USSD
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Text String
Data coding scheme: 7-bit default, no message class
String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.12.6 SEND USSD (UCS2 display in Katakana)

#### 27.22.4.12.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.12.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send USSD facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.12, clause 6.6.11, clause 8.12.7, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.17, clause 8.31 and clause 6.5.
- ETSI TS 23.038 [7] clause 5

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in: ISO/IEC 10646 [17].

#### 27.22.4.12.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND USSD proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.12.6.4 Method of test

##### 27.22.4.12.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default. Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.12.6.4.2 Procedure

**Expected Sequence 6.1 (SEND USSD, 7-bit data, successful, UCS2 text in Katakana)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND USSD 6.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND USSD 6.1.1 | |
| 4 | ME → USER | Display "ﾉﾚ" | [Character " in Katakana] |
| 5 | ME → USS | REGISTER 6.1 | |
| 6 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 6.1 | [Successful] |
| 7 | ME → UICC | TERMINAL RESPONSE: SEND USSD 6.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND USSD 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
Data coding scheme: UCS2 (16bit)
Text: "ル"
USSD String
Data coding scheme: 7-bit default, no message class
USSD String: "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 49 | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 03 | 80 | 30 | EB | 8A | 39 | F0 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |
| | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| | C3 | E5 | 60 | | | | | | | | | |

REGISTER 6.1

Logically (only USSD argument)

ProcessUnstructuredSS-Request ARGUMENT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD String:
- "ABCDEFGHIJKLMNOPQRSTUVWXYZ-abcdefghijklmnopqrstuvwxyz-1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 30 | 3D | 04 | 01 | F0 | 04 | 38 | 41 | E1 | 90 | 58 | 34 |
| | 1E | 91 | 49 | E5 | 92 | D9 | 74 | 3E | A1 | 51 | E9 | 94 |
| | 5A | B5 | 5E | B1 | 59 | 6D | 2B | 2C | 1E | 93 | CB | E6 |
| | 33 | 3A | AD | 5E | B3 | DB | EE | 37 | 3C | 2E | 9F | D3 |
| | EB | F6 | 3B | 3E | AF | 6F | C5 | 64 | 33 | 5A | CD | 76 |
| | C3 | E5 | 60 | | | | | | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 6.1

Logically (only from USSD result):

ProcessUnstructuredSS-Request RETURN RESULT
USSD-DataCodingScheme:
- 7-bit default, no message class
USSD String:
- "USSD string received from SS"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 30 | 1E | 04 | 01 | 00 | 04 | 19 | D5 | E9 | 94 | 08 | 9A |
| | D3 | E5 | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 |
| | 0C | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

TERMINAL RESPONSE: SEND USSD 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND USSD
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Text String
- Data coding scheme: 7-bit default, no message class
- String: "USSD string received from SS"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 12 | 00 | 82 | 02 | 82 | 81 | 83 | 01 |
| | 00 | 8D | 1A | 00 | D5 | E9 | 94 | 08 | 9A | D3 | E5 |
| | 69 | F7 | 19 | 24 | 2F | 8F | CB | 69 | 7B | 99 | 0C |
| | 32 | CB | DF | 6D | D0 | 74 | 0A | | | | |

#### 27.22.4.12.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.13 SET UP CALL

### 27.22.4.13.1 SET UP CALL (normal)

#### 27.22.4.13.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

#### 27.22.4.13.1.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.1.4 Method of test

27.22.4.13.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.1.4.2 Procedure

**Expected Sequence 1.1 (SET UP CALL, call confirmed by the user and connected)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.1.1 | |
| 4 | ME → USER | ME displays "Not busy" during user confirmation phase. | |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 1.1.1<br>The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s.<br>The ME returns to idle mode. | |

PROACTIVE COMMAND: SET UP CALL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Not busy"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1E | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 08 | 4E | 6F | 74 | 20 | 62 | 75 | 73 | 79 | 86 | 09 | 91 |
| | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | | | | |

TERMINAL RESPONSE: SET UP CALL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.2 (SET UP CALL, call rejected by the user)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.1.1 | |
| 4 | ME → USER | ME displays "Not busy" during the user confirmation phase | |
| 5 | USER → ME | The user rejects the set up call | [user rejects the call] |
| 6 | ME → UICC | TERMINAL RESPONSE 1.2.1 | [User did not accept call set-up request] |
| 7 | ME → USER | The ME returns in idle mode. | |

TERMINAL RESPONSE: SET UP CALL 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: User did not accept the proactive command

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 22 |

Expected Sequence 1.3void

**Expected Sequence 1.4 (SET UP CALL, putting all other calls on hold, ME busy)**

ME is busy on a call

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.4.1 | [putting all other calls on hold] |
| 4 | ME → USER | ME displays "On hold" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirms the call] |
| 6 | ME → USS | The active call is put on hold | |
| 7 | ME→USS | The ME attempts to set up a call to "+012340123456" | |
| 8 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 9 | ME → UICC | TERMINAL RESPONSE 1.4.1 | [Command performed successfully] |
| 10 | USER → ME | The user ends the call after 10 s. The ME retrieves the previous call automatically or on request of the user. | |

PROACTIVE COMMAND: SET UP CALL 1.4.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: putting all other calls on hold

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "On hold"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 10 | 02 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 4F | 6E | 20 | 68 | 6F | 6C | 64 | 86 | 09 | 91 | 10 |
| | 32 | 04 | 21 | 43 | 65 | 1C | 2C | | | | | |

TERMINAL RESPONSE: SET UP CALL 1.4.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: putting all other calls on hold

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

### Expected Sequence 1.5 (SET UP CALL, disconnecting all other calls, ME busy)

ME is busy on a call

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.5.1 | [disconnecting all other calls] |
| 4 | ME → USER | ME displays "Disconnect" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirms the call] |
| 6 | ME → USS | The ME disconnects the active call | |
| 7 | ME→USS | The ME attempts to set up a call to "+012340123456" | |
| 8 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 9 | ME → UICC | TERMINAL RESPONSE 1.5.1 | [Command performed successfully] |
| 10 | USER → ME | The user ends the call after 10 s. | |

PROACTIVE COMMAND: SET UP CALL 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: disconnecting all other calls

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Disconnect"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 10 | 04 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 44 | 69 | 73 | 63 | 6F | 6E | 6E | 65 | 63 | 74 | 86 |
| | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | | |

TERMINAL RESPONSE: SET UP CALL 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: putting all other calls on hold

Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 04 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

### Expected Sequence 1.6 (SET UP CALL, only if not currently busy on another call, ME busy)

ME is busy on a call

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.1.1 | [only if not currently busy on another call] |
| 4 | ME → UICC | TERMINAL RESPONSE 1.6.1 | [ME currently unable to process command] |

TERMINAL RESPONSE: SET UP CALL 1.6.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: ME currently unable to process command
Additional Information: ME currently busy on call

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 20 |
| | 02 | | | | | | | | | | | |

### Expected Sequence 1.7 (SET UP CALL, putting all other calls on hold, call hold is not allowed)

ME is busy on a call. The USS shall be configured to not allow Call Hold.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.4.1 | [putting all other calls on hold] |
| 4 | ME → USER | ME displays "On hold" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirms the call] |
| 6 | ME → USS | The ME attempts to put the active call on hold. | |
| 7 | USS->ME | The ME receives the HOLD REJECT message from the USS. | [USS sends 'Facility Rejected' as cause value] |
| 8 | ME → UICC | TERMINAL RESPONSE 1.7.1A OR TERMINAL RESPONSE 1.7.1B | [Network currently unable to process command] |

TERMINAL RESPONSE: SET UP CALL 1.7.1A

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: putting all other calls on hold

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Network currently unable to process command
- Additional Information: No specific cause can be given

Coding:

| BER-TLV: | 81 | 03 | 01 | 10 | 02 | 82 | 02 | 82 | 81 | 83 | 02 | 21 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | | | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 1.7.1B

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: putting all other calls on hold

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Network currently unable to process command
- Additional Information: Facility Rejected

Coding:

| BER-TLV: | 81 | 03 | 01 | 10 | 02 | 82 | 02 | 82 | 81 | 83 | 02 | 21 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 9D | | | | | | | | | | | |

**Expected Sequence 1.8 (SET UP CALL, Capability configuration)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.8.1 | [Capability configuration parameters: full rate support] |
| 4 | ME → USER | ME displays "Capability config" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" using the capability configuration parameters supplied by UICC | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 1.8.1 | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 1.8.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: if not busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Capability config"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Capability configuration parameters
- Information transfer cap: full rate support only MS

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2B | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 11 | 43 | 61 | 70 | 61 | 62 | 69 | 6C | 69 | 74 | 79 | 20 |
| | 63 | 6F | 6E | 66 | 69 | 67 | 86 | 09 | 91 | 10 | 32 | 04 |
| | 21 | 43 | 65 | 1C | 2C | 87 | 02 | 01 | A0 | | | |

TERMINAL RESPONSE: SET UP CALL 1.8.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: if not busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.9 (SET UP CALL, max dialling number string, no alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND SET UP CALL 1.9.1 | [dialling number string, no alpha identifier] |
| 4 | USER → ME | The user confirms the set up call | [user confirmation] |
| 5 | ME→USS | The ME attempts to set up a call to "012345678901234567890123456 78901" | |
| 6 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 7 | ME → UICC | TERMINAL RESPONSE 1.9.1 | [Command performed successfully] |
| 8 | USER → ME | The user ends the call<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 1.9.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call with redial
Device identities
Source device: UICC
Destination device: Network
Address
TON: International
NPI: ISDN / telephone numbering plan
Dialling number string: "012345678901234567890123456789012345678901"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 10 | 01 | 82 | 02 | 81 | 83 | 86 |
| | 11 | 91 | 10 | 32 | 54 | 76 | 98 | 10 | 32 | 54 | 76 | 98 |
| | 10 | 32 | 54 | 76 | 98 | 10 | | | | | | |

TERMINAL RESPONSE: SET UP CALL 1.9.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call with redial
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.10 (SET UP CALL,256 octets length, long first alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.10.1 | [ alpha identifier] |
| 4 | ME → USER | ME displays "Three types are defined: - set up a call, but only if not currently busy on another call; - set up a call, putting all other calls (if any) on hold; - set up a call, disconnecting all other calls (if any) first. For each of these types, " during the user confirmation phase. | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+01" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 1.10.1 | [Command performed successfully] |
| 9 | USER → ME | The user ends the call<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 1.10.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call with redial

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Three types are defined: - set up a call, but only if not currently busy on another call; - set up a call, putting all other calls (if any) on hold; - set up a call, disconnecting all other calls (if any) first. For each of these types, "

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string: "01"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | FD | 81 | 03 | 01 | 10 | 01 | 82 | 02 | 81 | 83 |
| | 85 | 81 | ED | 54 | 68 | 72 | 65 | 65 | 20 | 74 | 79 | 70 |
| | 65 | 73 | 20 | 61 | 72 | 65 | 20 | 64 | 65 | 66 | 69 | 6E |
| | 65 | 64 | 3A | 20 | 2D | 20 | 73 | 65 | 74 | 20 | 75 | 70 |
| | 20 | 61 | 20 | 63 | 61 | 6C | 6C | 2C | 20 | 62 | 75 | 74 |
| | 20 | 6F | 6E | 6C | 79 | 20 | 69 | 66 | 20 | 6E | 6F | 74 |
| | 20 | 63 | 75 | 72 | 72 | 65 | 6E | 74 | 6C | 79 | 20 | 62 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 75 | 73 | 79 | 20 | 6F | 6E | 20 | 61 | 6E | 6F | 74 | 68 |
| 65 | 72 | 20 | 63 | 61 | 6C | 6C | 3B | 20 | 2D | 20 | 73 |
| 65 | 74 | 20 | 75 | 70 | 20 | 61 | 20 | 63 | 61 | 6C | 6C |
| 2C | 20 | 70 | 75 | 74 | 74 | 69 | 6E | 67 | 20 | 61 | 6C |
| 6C | 20 | 6F | 74 | 68 | 65 | 72 | 20 | 63 | 61 | 6C | 6C |
| 73 | 20 | 28 | 69 | 66 | 20 | 61 | 6E | 79 | 29 | 20 | 6F |
| 6E | 20 | 68 | 6F | 6C | 64 | 3B | 20 | 2D | 20 | 73 | 65 |
| 74 | 20 | 75 | 70 | 20 | 61 | 20 | 63 | 61 | 6C | 6C | 2C |
| 20 | 64 | 69 | 73 | 63 | 6F | 6E | 6E | 65 | 63 | 74 | 69 |
| 6E | 67 | 20 | 61 | 6C | 6C | 20 | 6F | 74 | 68 | 65 | 72 |
| 20 | 63 | 61 | 6C | 6C | 73 | 20 | 28 | 69 | 66 | 20 | 61 |
| 6E | 79 | 29 | 20 | 66 | 69 | 72 | 73 | 74 | 2E | 20 | 46 |
| 6F | 72 | 20 | 65 | 61 | 63 | 68 | 20 | 6F | 66 | 20 | 74 |
| 68 | 65 | 73 | 65 | 20 | 74 | 79 | 70 | 65 | 73 | 2C | 20 |
| 86 | 02 | 91 | 10 | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 1.10.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call with redial

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.11A (SET UP CALL, Called party subaddress, command performed successfully)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.11.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.11.1 | [set up a call with called party subaddress] |
| 4 | ME → USER | ME displays "Called party" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+012340123456" with the called party subaddress information | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 1.11.1A | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s The ME returns in idle mode. | |

**Expected Sequence 1.11B (SET UP CALL, Called party subaddress, ME not supporting the called party subaddress)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.11.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.11.1 | [set up a call with called party subaddress] |
| 4 | ME → UICC | TERMINAL RESPONSE 1.11.1B | [beyond ME's capabilities] |

PROACTIVE COMMAND: SET UP CALL 1.11.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: if not busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Called party"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string: "012340123456p1p2"

Called party subaddress
- Type of subaddress: NSAP (X.213 / ISO 8348 AD2)
- Odd / even indicator: even number of address signals
- Subaddress information: AFI, 95, 95, 95, 95, 95

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2B | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0C | 43 | 61 | 6C | 6C | 65 | 64 | 20 | 70 | 61 | 72 | 74 |
| | 79 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 88 | 07 | 80 | 50 | 95 | 95 | 95 | 95 | 95 | | | |

TERMINAL RESPONSE: SET UP CALL 1.11.1A

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: if not busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

TERMINAL RESPONSE: SET UP CALL 1.11.1B

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: if not busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Beyond ME's capabilities

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 30 |

### Expected Sequence 1.12 (SET UP CALL, maximum duration for the redial mechanism)

The USS shall be configured such that call set up requests will be rejected with cause "User Busy".

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 1.12.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.12.1 | [only if not currently busy on another call with redial] |
| 4 | ME → USER | ME displays "Duration" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirms the call] |
| 6 | ME → USS | ME attempts to set up a call to "+012340123456" . It stops its attempts after 10 seconds. | [redial mechanism with maximum duration of 10 seconds]] |
| 7 | ME → UICC | TERMINAL RESPONSE 1.12.1 | [network currently unable to process command] |
| 8 | ME → USER | The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 1.12.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call with redial

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Duration"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string: "012340123456p1p2"

Duration
- Unit: Seconds
- Interval: 10

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 10 | 01 | 82 | 02 | 81 | 83 | 85 |
| | 08 | 44 | 75 | 72 | 61 | 74 | 69 | 6F | 6E | 86 | 09 | 91 |
| | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | 84 | 02 | 01 | 0A |

TERMINAL RESPONSE: SET UP CALL 1.12.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call with redial

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: network currently unable to process command
- Additional Information: User Busy

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 01 | 82 | 02 | 82 | 81 | 83 | 02 | 21 |
| | 91 | | | | | | | | | | | |

#### 27.22.4.13.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.12.

### 27.22.4.13.2 SET UP CALL (second alpha identifier)

#### 27.22.4.13.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.13.2.2 Conformance requirement

Same as clause 27.22.4.13.2.1.

27.22.4.13.2.3 Test purpose

To verify that the ME accepts a Proactive Command - Set Up Call, displays the alpha identifiers to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

27.22.4.13.2.4 Method of test

27.22.4.13.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and is in updated idle mode on the USS.

27.22.4.13.2.4.2 Procedure

**Expected Sequence 2.1 (SET UP CALL, two alpha identifiers)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 2.1.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL" | [second alpha identifier] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 2.1.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 28 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0C | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C |
| | 85 | 04 | 43 | 41 | 4C | 4C | | | | | | |

TERMINAL RESPONSE: SET UP CALL 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.13.3 SET UP CALL (display of icons)

#### 27.22.4.13.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.3.2 Conformance requirement

#### 27.22.4.13.3.3 Test purpose

To verify that the ME accepts a Proactive Set Up Call , displays the message or icon to the user ,attempts to set up a call to the address, returns the result in the TERMINAL response.

#### 27.22.4.13.3.4 Method of test

##### 27.22.4.13.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and is in updated idle mode on the USS.

27.22.4.13.3.4.2 Procedure

**Expected Sequence 3.1A (SET UP CALL, display of basic icon during confirmation phase, not self-explanatory, successful )**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.1.1 | Including icon identifier, icon shall be displayed in addition of the first alpha identifier |
| 4 | ME → USER | ME displays "Set up call Icon 3.1.1" and the basic icon during a user confirmation phase. | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.1.1A | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 3.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Set up call Icon 3.1.1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Icon identifier
- Icon qualifier: icon is not self-explanatory
- Icon identifier: <record 1 in EF IMG>

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 30 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 16 | 53 | 65 | 74 | 20 | 75 | 70 | 20 | 63 | 61 | 6C | 6C |
| | 20 | 49 | 63 | 6F | 6E | 20 | 33 | 2E | 31 | 2E | 31 | 86 |
| | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | 9E | 02 |
| | 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 3.1.1A

Logically:

Command details

Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 3.1B (SET UP CALL, display of basic icon during confirmation phase, not self-explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.1.1 | Including icon identifier, icon shall be displayed in addition of the first alpha identifier |
| 4 | ME → USER | ME displays "Set up call Icon 3.1.1" without the basic icon during a user confirmation phase. | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.1.1B | [Command performed successfully, but requested icon could not be displayed]. |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

TERMINAL RESPONSE: SET UP CALL 3.1.1B

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully, but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

**Expected Sequence 3.2A (SET UP CALL, display of basic icon during confirmation phase, self-explanatory, successful )**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.2.1 | Including icon identifier, icon shall be displayed instead of the first alpha identifier |
| 4 | ME → USER | ME displays the basic icon during a user confirmation phase. | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.2.1A | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 3.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Set up call Icon 3.2.1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Icon identifier
- Icon qualifier: icon is self-explanatory
- Icon identifier: <record 1 in EF IMG>

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 30 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 16 | 53 | 65 | 74 | 20 | 75 | 70 | 20 | 63 | 61 | 6C | 6C |
| | 20 | 49 | 63 | 6F | 6E | 20 | 33 | 2E | 32 | 2E | 31 | 86 |
| | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | 9E | 02 |
| | 00 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 3.2.1A

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 3.2B (SET UP CALL, display of basic icon during confirmation phase, self-explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.2.1 | Including icon identifier, icon shall be displayed instead of the first alpha identifier |
| 4 | ME → USER | ME display "Set up call Icon 3.2.1" without the icon | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.2.1B | [Command performed successfully, but requested icon could not be displayed]. |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

TERMINAL RESPONSE: SET UP CALL 3.2.1B

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully, but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

**Expected Sequence 3.3A (SET UP CALL, display of colour icon during confirmation phase, not self-explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.3.1 | Including icon identifier, icon shall be displayed in addition of the first alpha identifier |
| 4 | ME → USER | ME displays "Set up call Icon 3.3.1" and the colour icon during a user confirmation phase. | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.3.1A | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 3.3.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Set up call Icon 3.3.1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Icon identifier
- Icon qualifier: icon is not self-explanatory
- Icon identifier: <record 2 in EF IMG>

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 30 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 16 | 53 | 65 | 74 | 20 | 75 | 70 | 20 | 63 | 61 | 6C | 6C |
| | 20 | 49 | 63 | 6F | 6E | 20 | 33 | 2E | 33 | 2E | 31 | 86 |
| | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | 9E | 02 |
| | 01 | 02 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 3.3.1A

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 3.3B (SET UP CALL, display of colour icon during confirmation phase, not self-explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.3.1 | Including icon identifier, icon shall be displayed in addition of the first alpha identifier |
| 4 | ME → USER | ME only display alpha string: " Set up call Icon 3.3.1" | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.3.1B | [Command performed successfully, but requested icon could not be displayed]. |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

TERMINAL RESPONSE: SET UP CALL 3.3.1B

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully, but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

**Expected Sequence 3.4A (SET UP CALL, display of self explanatory basic icon during set up call, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.4.1 | Including a second alpha identifier and two icons |
| 4 | ME → USER | ME displays the basic icon during a user confirmation phase. | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME→USS | The ME attempts to set up a call to "+012340123456". The ME displays the basic icon without the text during the set up call. | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.4.1A | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 3.4.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Set up call Icon 3.4.1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"

Icon identifier
- Icon qualifier: icon is self-explanatory
- Icon identifier: <record 1 in EF IMG>

Alpha identifier: "Set up call Icon 3.4.2"

Icon identifier
- Icon qualifier: icon is self-explanatory
- Icon identifier: <record 1 in EF IMG>

Coding:

| BER-TLV: | D0 | 4C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 16 | 53 | 65 | 74 | 20 | 75 | 70 | 20 | 63 | 61 | 6C | 6C |
| | 20 | 49 | 63 | 6F | 6E | 20 | 33 | 2E | 34 | 2E | 31 | 86 |
| | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | 1C | 2C | 9E | 02 |
| | 00 | 01 | 85 | 16 | 53 | 65 | 74 | 20 | 75 | 70 | 20 | 63 |
| | 61 | 6C | 6C | 20 | 49 | 63 | 6F | 6E | 20 | 33 | 2E | 34 |
| | 2E | 32 | 9E | 02 | 00 | 01 | | | | | | |

TERMINAL RESPONSE: SET UP CALL 3.4.1A

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 3.4B (SET UP CALL, display of self explanatory basic icon during set up call, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 3.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 3.4.1 | Including a second alpha identifier and two icons |
| 4 | ME → USER | ME displays "Set up call Icon 3.4.1" without the icon | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "Set up call Icon 3.4.2" without the icon during the set up call. | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 3.4.1B | [Command performed successfully, but requested icon could not be displayed]. |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

TERMINAL RESPONSE: SET UP CALL 3.4.1B

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

#### 27.22.4.13.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1A to 3.4B.

### 27.22.4.13.4 SET UP CALL (support of Text Attribute)

#### 27.22.4.13.4.1 SET UP CALL (support of Text Attribute – Left Alignment)

##### 27.22.4.13.4.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.13.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

##### 27.22.4.13.4.1.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the left alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

##### 27.22.4.13.4.1.4 Method of test

###### 27.22.4.13.4.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.1.4.2 Procedure

**Expected Sequence 4.1 (SET UP CALL, Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.1.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with left alignment] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with left alignment] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.1.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.1.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.1.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [User confirmation shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [Second alpha identifier shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.1.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 18 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International

NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase): "CALL 1"
Text Attribute (user confirmation phase)
Formatting position: 0
Formatting length: 14
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background
Text Attribute (call set up phase)
Formatting position: 0
Formatting length: 6
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.1.2

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "CONFIRMATION 2"
Address
TON: International
NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase):"CALL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | | |

TERMINAL RESPONSE: SET UP CALL 4.1.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.13.4.2 SET UP CALL (support of Text Attribute – Center Alignment)

#### 27.22.4.13.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.2.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the center alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.2.4 Method of test

##### 27.22.4.13.4.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.2.4.2 Procedure

**Expected Sequence 4.2 (SET UP CALL, Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.2.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with center alignment] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with center alignment] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.2.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.2.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.2.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [User confirmation shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [Second alpha identifier shall be formatted without centert alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.2.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International

NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase): "CALL 1"
Text Attribute (user confirmation phase)
Formatting position: 0
Formatting length: 14
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background
Text Attribute (call set up phase)
Formatting position: 0
Formatting length: 6
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 01 | B4 | D0 | 04 | 00 | 06 | 01 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.2.2

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "CONFIRMATION 2"
Address
TON: International
NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase):"CALL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | | |

TERMINAL RESPONSE: SET UP CALL 4.2.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

### 27.22.4.13.4.3 SET UP CALL (support of Text Attribute – Right Alignment)

#### 27.22.4.13.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.3.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the right alignment text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.3.4 Method of test

##### 27.22.4.13.4.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.3.4.2 Procedure

**Expected Sequence 4.3 (SET UP CALL, Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.3.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with right alignment] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with right alignment] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.3.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.3.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.3.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [User confirmation shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [Second alpha identifier shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/14, no alignment change will take place] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.3.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.3.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International

NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase): "CALL 1"
Text Attribute (user confirmation phase)
Formatting position: 0
Formatting length: 14
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background
Text Attribute (call set up phase)
Formatting position: 0
Formatting length: 6
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 02 | B4 | D0 | 04 | 00 | 06 | 02 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.3.2

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "CONFIRMATION 2"
Address
TON: International
NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase):"CALL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | | |

TERMINAL RESPONSE: SET UP CALL 4.3.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

### 27.22.4.13.4.4 SET UP CALL (support of Text Attribute – Large Font Size)

#### 27.22.4.13.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.4.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the large font size text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.4.4 Method of test

##### 27.22.4.13.4.4.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.4.4.2 Procedure

**Expected Sequence 4.4 (SET UP CALL, Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.4.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with large font size] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with large font size] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.4.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.4.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with normal font size] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with normal font size] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.4.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.4.1 | |
| 22 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 23 | USER → ME | The user confirms the set up call | [user confirmation is displayed with large font size] |
| 24 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with large font size] |
| 25 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 26 | ME → UICC | TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 27 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.4.3 | |
| 29 | ME → UICC | FETCH | |

| | | | |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.4.3 | |
| 31 | ME → USER | ME displays "CONFIRMATION 3" during the user confirmation phase | |
| 32 | USER → ME | The user confirms the set up call | [user confirmation is displayed with normal font size] |
| 33 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3" | [second alpha identifier is displayed with normal font size] |
| 34 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 35 | ME → UICC | TERMINAL RESPONSE 4.4.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 36 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 04 | B4 | D0 | 04 | 00 | 06 | 04 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.4.2

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 2"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.4.3

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 3"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase):"CALL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 33 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 33 | | |

TERMINAL RESPONSE: SET UP CALL 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

### 27.22.4.13.4.5 SET UP CALL (support of Text Attribute – Small Font Size)

#### 27.22.4.13.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.5.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the small font size text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.4.5 Method of test

#### 27.22.4.13.4.4.5.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.4.5.2 Procedure

**Expected Sequence 4.5 (SET UP CALL, Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.5.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with small font size] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with small font size] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.5.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.5.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with normal font size] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with normal font size] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.5.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.5.1 | |
| 22 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 23 | USER → ME | The user confirms the set up call | [user confirmation is displayed with small font size] |
| 24 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with small font size] |
| 25 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 26 | ME → UICC | TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 27 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.5.3 | |
| 29 | ME → UICC | FETCH | |

| | | | |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.5.3 | |
| 31 | ME → USER | ME displays "CONFIRMATION 3" during the user confirmation phase | |
| 32 | USER → ME | The user confirms the set up call | [user confirmation is displayed with normal font size] |
| 33 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3" | [second alpha identifier is displayed with normal font size] |
| 34 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 35 | ME → UICC | TERMINAL RESPONSE 4.5.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 36 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 08 | B4 | D0 | 04 | 00 | 06 | 08 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.5.2

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 2"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.5.3

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 3"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 33 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 33 | | |

TERMINAL RESPONSE: SET UP CALL 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

### 27.22.4.13.4.6 SET UP CALL (support of Text Attribute – Bold On)

#### 27.22.4.13.4.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.6.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the bold text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.6.4 Method of test

##### 27.22.4.13.4.6.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.6.4.2 Procedure

**Expected Sequence 4.6 (SET UP CALL, Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.6.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with bold on] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with bold on] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.6.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.6.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with bold off] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with bold off] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.6.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.6.1 | |
| 22 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 23 | USER → ME | The user confirms the set up call | [user confirmation is displayed with bold on] |
| 24 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with bold on] |
| 25 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 26 | ME → UICC | TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 27 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.6.3 | |
| 29 | ME → UICC | FETCH | |

| | | | |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.6.3 | |
| 31 | ME → USER | ME displays "CONFIRMATION 3" during the user confirmation phase | |
| 32 | USER → ME | The user confirms the set up call | [user confirmation is displayed with bold off] |
| 33 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3" | [second alpha identifier is displayed with bold off] |
| 34 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 35 | ME → UICC | TERMINAL RESPONSE 4.6.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 36 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 10 | B4 | D0 | 04 | 00 | 06 | 10 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.6.2

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 2"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.6.3

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 3"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 33 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 33 | | |

TERMINAL RESPONSE: SET UP CALL 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

### 27.22.4.13.4.7 SET UP CALL (support of Text Attribute – Italic On)

#### 27.22.4.13.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.7.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the italic text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.7.4 Method of test

##### 27.22.4.13.4.7.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.7.4.2 Procedure

**Expected Sequence 4.7 (SET UP CALL, Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.7.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with italic on] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with italic on] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.7.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.7.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with italic off] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with italic off] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.7.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.7.1 | |
| 22 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 23 | USER → ME | The user confirms the set up call | [user confirmation is displayed with italic on] |
| 24 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with italic on] |
| 25 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 26 | ME → UICC | TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 27 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.7.3 | |
| 29 | ME → UICC | FETCH | |

| | | | |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.7.3 | |
| 31 | ME → USER | ME displays "CONFIRMATION 3" during the user confirmation phase | |
| 32 | USER → ME | The user confirms the set up call | [user confirmation is displayed with italic off] |
| 33 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3" | [second alpha identifier is displayed with italic off] |
| 34 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 35 | ME → UICC | TERMINAL RESPONSE 4.7.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 36 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 20 | B4 | D0 | 04 | 00 | 06 | 20 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.7.2

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 2"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.7.3

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 3"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 33 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 33 | | |

TERMINAL RESPONSE: SET UP CALL 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

### 27.22.4.13.4.8 SET UP CALL (support of Text Attribute – Underline On)

#### 27.22.4.13.4.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.8.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the underline text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.8.4 Method of test

##### 27.22.4.13.4.8.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.8.4.2 Procedure

**Expected Sequence 4.8 (SET UP CALL, Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.8.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with underline on] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with underline on] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.8.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.8.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with underline off] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with underline off] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.8.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.8.1 | |
| 22 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 23 | USER → ME | The user confirms the set up call | [user confirmation is displayed with underline on] |
| 24 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with underline on] |
| 25 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 26 | ME → UICC | TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 27 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.8.3 | |
| 29 | ME → UICC | FETCH | |

| | | | |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.8.3 | |
| 31 | ME → USER | ME displays "CONFIRMATION 3" during the user confirmation phase | |
| 32 | USER → ME | The user confirms the set up call | [user confirmation is displayed with underline off] |
| 33 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3" | [second alpha identifier is displayed with Undeline off] |
| 34 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 35 | ME → UICC | TERMINAL RESPONSE 4.8.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 36 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 40 | B4 | D0 | 04 | 00 | 06 | 40 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.8.2

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 2"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.8.3

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 3"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 33 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 33 | | |

TERMINAL RESPONSE: SET UP CALL 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

### 27.22.4.13.4.9 SET UP CALL (support of Text Attribute – Strikethrough On)

#### 27.22.4.13.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.9.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the strikethrough text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.9.4 Method of test

##### 27.22.4.13.4.9.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.9.4.2 Procedure

**Expected Sequence 4.9 (SET UP CALL, Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.9.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with strikethrough on] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with strikethrough on] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.9.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.9.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with strikethrough off] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with strikethrough off] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.9.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.9.1 | |
| 22 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 23 | USER → ME | The user confirms the set up call | [user confirmation is displayed with strikethrough on] |
| 24 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with strikethrough on] |
| 25 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 26 | ME → UICC | TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 27 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.9.3 | |
| 29 | ME → UICC | FETCH | |

| | | | |
|---|---|---|---|
| 30 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.9.3 | |
| 31 | ME → USER | ME displays "CONFIRMATION 3" during the user confirmation phase | |
| 32 | USER → ME | The user confirms the set up call | [user confirmation is displayed with strikethrough off] |
| 33 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 3" | [second alpha identifier is displayed with strikethrough off] |
| 34 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 35 | ME → UICC | TERMINAL RESPONSE 4.9.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 36 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.9.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 80 | B4 | D0 | 04 | 00 | 06 | 80 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.9.2

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 2"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 2"

Text Attribute (user confirmation phase)
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Text Attribute (call set up phase)
- Formatting position: 0
- Formatting length: 6
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | B4 | | |

PROACTIVE COMMAND: SET UP CALL 4.9.3

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 3"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 33 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 33 | | |

TERMINAL RESPONSE: SET UP CALL 4.9.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

### 27.22.4.13.4.10 SET UP CALL (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.13.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3, clause 8.70 and clause 5.2.

#### 27.22.4.13.4.10.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier according to the foreground and background colour text attribute configuration to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.4.10.4 Method of test

##### 27.22.4.13.4.10.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and in the updated idle mode on the USS.

27.22.4.13.4.10.4.2 Procedure

**Expected Sequence 4.10 (SET UP CALL, Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.10.1 | |
| 4 | ME → USER | ME displays "CONFIRMATION 1" during the user confirmation phase | |
| 5 | USER → ME | The user confirms the set up call | [user confirmation is displayed with foreground and background colour according to Text Attribute configuration] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 1" | [second alpha identifier is displayed with foreground and background colour according to Text Attribute configuration] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 8 | ME → UICC | TERMINAL RESPONSE 4.10.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 4.10.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 4.10.2 | |
| 13 | ME → USER | ME displays "CONFIRMATION 2" during the user confirmation phase | |
| 14 | USER → ME | The user confirms the set up call | [user confirmation is displayed with ME"s default foreground and background colour] |
| 15 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "CALL 2" | [second alpha identifier is displayed with ME"s default foreground and background colour] |
| 16 | USS → ME | The ME receives the CONNECT message from the USS. | [The USS also has to handle the START DTMF and STOP DTMF messages sent by the ME in an appropriate way] |
| 17 | ME → UICC | TERMINAL RESPONSE 4.10.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 18 | USER → ME | The user ends the call after 10 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 4.10.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "CONFIRMATION 1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456p1p2"
- Alpha Identifier (call set up phase): "CALL 1"

Text Attribute (user confirmation phase)
Formatting position: 0
Formatting length: 14
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background
Text Attribute (call set up phase)
Formatting position: 0
Formatting length: 6
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Bright Yellow Foreground, Dark Green Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 38 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 31 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 31 | D0 | 04 |
| | 00 | 0E | 00 | B4 | D0 | 04 | 00 | 06 | 00 | 4B | | |

PROACTIVE COMMAND: SET UP CALL 4.10.2

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "CONFIRMATION 2"
Address
TON: International
NPI: ISDN / telephone numbering plan
Dialling number string "012340123456p1p2"
Alpha Identifier (call set up phase): "CALL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0E | 43 | 4F | 4E | 46 | 49 | 52 | 4D | 41 | 54 | 49 | 4F |
| | 4E | 20 | 32 | 86 | 09 | 91 | 10 | 32 | 04 | 21 | 43 | 65 |
| | 1C | 2C | 85 | 06 | 43 | 41 | 4C | 4C | 20 | 32 | | |

TERMINAL RESPONSE: SET UP CALL 4.10.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL

Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

### 27.22.4.13.5 SET UP CALL (UCS2 Display in ***Cyrillic***)

#### 27.22.4.13.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.5.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.13.5.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.5.4 Method of test

##### 27.22.4.13.5.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.5.4.2 Procedure

**Expected Sequence 5.1 (SET UP CALL with UCS2 – Cyrillic Characters, call confirmed by the user and connected)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 5.1.1 | |
| 4 | ME → USER | ME displays "ЗДРАВСТВУЙТЕ" during user confirmation phase. | ["ЗДРАВСТВУЙТЕ": 'Hello' in Russian] |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 5.1.1<br>The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 5 s.<br>The ME returns to idle mode. | |

PROACTIVE COMMAND: SET UP CALL 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "ЗДРАВСТВУЙТЕ"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2D | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 19 | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 |
| | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 |
| | 04 | 15 | 86 | 07 | 91 | 10 | 32 | 04 | 21 | 43 | 65 | |

TERMINAL RESPONSE: SET UP CALL 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 5.2 (SET UP CALL, two alpha identifiers coded in UCS2 – Cyrillic Characters)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 5.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 5.2.1 | |
| 4 | ME → USER | ME displays "ЗДРАВСТВУЙТЕ1" during the user confirmation phase | ['ЗДРАВСТВУЙТЕ1' : 'Hello1' in Russian] |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "ЗДРАВСТВУЙТЕ2" | [second alpha identifier] ['ЗДРАВСТВУЙТЕ2' : 'Hello2' in Russian] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 5.2.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 5 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 5.2.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: " ЗДРАВСТВУЙТЕ1"
Address
TON: International
NPI: ISDN / telephone numbering plan
Dialling number string "012340123456"
Alpha Identifier (call set up phase): " ЗДРАВСТВУЙТЕ2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4C | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 1B | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 |
| | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 |
| | 04 | 15 | 00 | 31 | 86 | 07 | 91 | 10 | 32 | 04 | 21 | 43 |
| | 65 | 85 | 1B | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 04 | 12 | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 |
| 04 | 22 | 04 | 15 | 00 | 32 | | | | | | |

TERMINAL RESPONSE: SET UP CALL 5.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.5.5 Test requirement

The ME shall operate in the manner defined in expected sequences 5.1 to 5.2.

### 27.22.4.13.6 SET UP CALL (UCS2 Display in Chinese)

#### 27.22.4.13.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.6.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.13.6.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.6.4 Method of test

##### 27.22.4.13.6.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.6.4.2 Procedure

**Expected Sequence 6.1 (SET UP CALL with UCS2 – Chinese characters, call confirmed by the user and connected)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 6.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 6.1.1 | |
| 4 | ME → USER | ME displays "不忙" during user confirmation phase. | ['不忙' : 'Not Busy' in Chinese] |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 6.1.1<br>The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 5 s.<br>The ME returns to idle mode. | |

PROACTIVE COMMAND: SET UP CALL 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "不忙"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 19 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 4E | 0D | 5F | D9 | 86 | 07 | 91 | 10 | 32 | 04 |
| | 21 | 43 | 65 | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 6.2 (SET UP CALL, two alpha identifiers coded in UCS2 – Chinese characters)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 6.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 6.2.1 | |
| 4 | ME → USER | ME displays "确定" during the user confirmation phase | ['确定' : 'Confirmation' in Chinese] |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456".<br>The ME displays "打电话" | [second alpha identifier]<br>['打电话' : 'CALL' in Chinese] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 6.2.1<br>The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 5 s.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 6.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "确定"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456"

Alpha Identifier (call set up phase): "打电话"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 78 | 6E | 5B | 9A | 86 | 07 | 91 | 10 | 32 | 04 |
| | 21 | 43 | 65 | 85 | 07 | 80 | 62 | 53 | 75 | 35 | 8B | DD |

TERMINAL RESPONSE: SET UP CALL 6.2.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.6.5 Test requirement

The ME shall operate in the manner defined in expected sequences 6.1 to 6.2.

### 27.22.4.13.7 SET UP CALL (UCS2 Display in Katakana)

#### 27.22.4.13.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.13.7.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Call facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.13, clause 6.6.12, clause 8.6, clause 8.7, clause 8.12, clause 8.12.3 and clause 5.2.

The ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.13.7.3 Test purpose

To verify that the ME accepts the Proactive Command - Set Up Call, displays the alpha identifier with UCS2 coding to the user, attempts to set up a call to the address and returns the result in the TERMINAL RESPONSE.

#### 27.22.4.13.7.4 Method of test

##### 27.22.4.13.7.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.13.7.4.2 Procedure

**Expected Sequence 7.1 (SET UP CALL with UCS2 – Katakana characters, call confirmed by the user and connected)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 7.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 7.1.1 | |
| 4 | ME → USER | ME displays "ル" during user confirmation phase. | [Character in Katakana] |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456" | |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 7.1.1<br>The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 5 s.<br>The ME returns to idle mode. | |

PROACTIVE COMMAND: SET UP CALL 7.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "ル"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 17 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 03 | 80 | 30 | EB | 86 | 07 | 91 | 10 | 32 | 04 | 21 | 43 |
| | 65 | | | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 7.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 7.2 (SET UP CALL, two alpha identifiers coded in UCS2 – Katakana characters)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 7.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 7.2.1 | |
| 4 | ME → USER | ME displays "ル1" during the user confirmation phase | [Character in Katakana] |
| 5 | USER → ME | The user confirms the set up call | [user confirmation] |
| 6 | ME → USS | The ME attempts to set up a call to "+012340123456". The ME displays "ル2". | [second alpha identifier] [Character in Katakana] |
| 7 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 8 | ME → UICC | TERMINAL RESPONSE 7.2.1 The ME shall not update EF LND with the called party address. | [Command performed successfully] |
| 9 | USER → ME | The user ends the call after 5 s. The ME returns in idle mode. | |

PROACTIVE COMMAND: SET UP CALL 7.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "ル1"

Address
- TON: International
- NPI: ISDN / telephone numbering plan
- Dialling number string "012340123456"

Alpha Identifier (call set up phase): "ル2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 30 | EB | 00 | 31 | 86 | 07 | 91 | 10 | 32 | 04 |
| | 21 | 43 | 65 | 85 | 05 | 80 | 30 | EB | 00 | 32 | | |

TERMINAL RESPONSE: SET UP CALL 7.2.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.13.7.5 Test requirement

The ME shall operate in the manner defined in expected sequences 7.1 to 7.2.

## 27.22.4.14 POLLING OFF

### 27.22.4.14.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.14.2 Conformance requirement

The ME shall support the POLLING OFF as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.14, clause 6.6.14, clause 6.8, clause 6.11, clause 8.6 and clause 8.7.

### 27.22.4.14.3 Test purpose

To verify that the ME cancels the effect of any previous POLL INTERVAL commands and does not effect UICC presence detection.

### 27.22.4.14.4 Method of test

#### 27.22.4.14.4.1 Initial conditions

The ME is connected to the USIM Simulator and to the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.14.4.2 Procedure

**Expected Sequence 1.1 (POLLING OFF)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: POLL INTERVAL 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: POLL INTERVAL 1.1.1 | Interval = 1 min |
| 4 | ME → UICC | TERMINAL RESPONSE: POLL INTERVAL 1.1.1 A or TERMINAL RESPONSE: POLL INTERVAL 1.1.1B | [command performed successfully, duration depends on the ME"s capabilities] |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: POLLING OFF 1.1.2 | |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: POLLING OFF 1.1.2 | |
| 8 | ME → UICC | TERMINAL RESPONSE: POLLING OFF 1.1.2 | [command performed successfully] |
| 9 | USER → ME | Call to be set up | |
| 10 | ME → UICC | Periods of inactivity on the UICC-ME interfaceshall not exceed 30 seconds | |
| 11 | USER → ME | Call to be terminated 3 minutes after call setup | |

PROACTIVE COMMAND: POLL INTERVAL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: POLL INTERVAL
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Duration
- Time unit: Minutes
- Time interval: 1

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0D | 81 | 03 | 01 | 03 | 00 | 82 | 02 | 81 | 82 | 84 |
| | 02 | 00 | 01 | | | | | | | | | |

TERMINAL RESPONSE: POLL INTERVAL 1.1.1A

Logically:

Command details
- Command number: 1
- Command type: POLL INTERVAL
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Duration

Time unit: Minutes

Time interval: 1

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 03 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 84 | 02 | 00 | 01 | | | | | | | | |

TERMINAL RESPONSE: POLL INTERVAL 1.1.1B

Logically:

Command details

Command number: 1

Command type: POLL INTERVAL

Command qualifier: "00"

Device identities

Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Duration

Time unit: Seconds

Time interval: 60

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 03 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 84 | 02 | 01 | 3C | | | | | | | | |

NOTE: If the requested poll interval is not supported by the ME, the ME is allowed to use a different one as stated in TS 31.111 [15], subclause 6.4.6.

PROACTIVE COMMAND: POLLING OFF 1.1.2

Logically:

Command details

Command number: 1

Command type: POLLING OFF

Command qualifier: "00"

Device identities

Source device: UICC

Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 04 | 00 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: POLLING OFF 1.1.2

Logically:

Command details
Command number: 1
Command type: POLLING OFF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 04 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.14.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.4.15 PROVIDE LOCAL INFORMATION

#### 27.22.4.15.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.15.2 Conformance requirement

The ME shall support the PROVIDE LOCAL INFORMATION facility as defined in:

- TS 31.111 [15] clause 6.4.15.

#### 27.22.4.15.3 Test purpose

To verify that the ME returns the following requested local information within a TERMINAL RESPONSE:

- location information:
  - Mobile Country Code (MCC);
  - Mobile Network Code (MNC);
  - Location Area Code (LAC); and
  - cell ID of the current serving cell;
- the IMEI of the ME;
- the Network Measurement Results and the BCCH channel list;
- the current date, time and time zone;
- the current ME language setting;
- the Timing Advance;
- the Access Technology;
- the IMEISV
- the Search Mode change
- the Battery charge State

- the UTRAN measurements.

if the local information is stored in the ME; otherwise, sends the correct error code to the UICC in the TERMINAL RESPONSE.

### 27.22.4.15.4 Method of tests

#### 27.22.4.15.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME is connected to the USS and has performed the location update procedure.

The UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The GERAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;
- Timing advance = 0;
- Neighbour allocations = 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;
- Timing advance = 0;
- Neighbour allocations = 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585.

The elementary files are coded as the USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Expected sequence 1.3 and 1.6 shall be used on a USS setting up only a GERAN or PCS 1900 cell and expected sequence 1.12 shall be used on a USS setting up only a UTRAN cell.

27.22.4.15.4.2 Procedure

**Expected Sequence 1.1 (PROVIDE LOCAL INFORMATION, Local Info (MCC, MNC, LAC & Cell ID))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1A<br>or<br>TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1B | [Command performed successfully, MCC MNC LAC and Cell Identity as USS, option A shall apply for 3GPP parameters]<br>[Command performed successfully, MCC MNC LAC and Cell Identity as USS, option B shall apply for PCS1900 parameters] |

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.1.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 26 | 00 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1A

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Location Information
- MCC & MNC: MCC = 001, MNC = 01
- Location Area Code: 0001
- Cell Identity Value: 0001
- Extended Cell Identity Value: RNC-id value (for Rel-4 onwards), see also Note 2

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 26 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 93 | Note 1 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 2 | | |

Note 1: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 2: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.1.1B

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "00" Location information (MCC MNC LAC and Cell Identity)

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Location Information
- MCC & MNC: MCC = 001, MNC = 011
- Location Area Code: 0001
- Cell Identity Value: 0001

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 26 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 93 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | | | |

**Expected Sequence 1.2 (PROVIDE LOCAL INFORMATION, IMEI of the ME)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | Identity request | [Identity type = IMEI] |
| 2 | ME → USS | Identity response | [Mobile identity = IMEI] |
| 3 | UICC → ME | PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.2.1 | |
| 4 | ME → UICC | FETCH | |
| 5 | UICC → ME | PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.2.1 | |
| 6 | ME → UICC | TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.2.1 | [Command performed successfully, IMEI as USS, but spare digit shall be zero when transmitted by the ME] |

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.2.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "01" IMEI of the ME

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 26 | 01 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.2.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "01" IMEI of the ME

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

IMEI
- IMEI of the ME: The IMEI of the ME

The result coding depends on the Mobile IMEI value as declared in table A.2/23.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 26 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 94 | 08 | XX | XX | XX | XX | XX | XX | XX | XX | | |

As an example, if the IMEI of the mobile is "123456789012345" then XX XX XX XX XX XX XX XX = 1A 32 54 76 98 10 32 04. For further details see also TS 24.008 [10], clause 10.5.1.

**Expected Sequence 1.3 (PROVIDE LOCAL INFORMATION, Network Measurement Results (NMR))**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.3.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.3.1 | [Command performed successfully, NMR as USS ] |

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.3.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "02" Network Measurement Results

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 26 | 02 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.3.1

The actual values of the measurements are not tested.

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "02" Network Measurement Results

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Network Measurement Results: RXLEV-FULL-SERVING-CELL=52, BA not used, DTX not used, as an example in the BER-TLV)
- BCCH channel list: 561, 565, 568, 569, 573, 575, 577, 581, 582 and 585

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 26 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 96 | 10 | 34 | 34 | 00 | 00 | 00 | 00 | 00 | 00 | 00 | 00 |
| | 00 | 00 | 00 | 00 | 00 | 00 | 9D | 0D | 8C | 63 | 58 | E2 |
| | 39 | 8F | 63 | F9 | 06 | 45 | 91 | A4 | 90 | | | |

### Expected Sequence 1.4 (PROVIDE LOCAL INFORMATION, Date, Time, Time Zone)

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.4.

### Expected Sequence 1.5 (PROVIDE LOCAL INFORMATION, Language setting)

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.5.

### Expected Sequence 1.6 (PROVIDE LOCAL INFORMATION, Timing advance)

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.6.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.6.1 | [Command performed successfully] |

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.6.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "05" Timing Advance

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 26 | 05 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.6.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "05" Timing Advance

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Timing Advance 2 bytes
- ME status: "00" ME is in idle state
- Timing Advance: 0

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 26 | 05 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | AE | 02 | 00 | 00 | | | | | | | | |

### Expected Sequence 1.7 (PROVIDE LOCAL INFORMATION, Access Technology

TBD

### Expected Sequence 1.8 (Void)

### Expected Sequence 1.9 (PROVIDE LOCAL INFORMATION, IMEISV of the terminal)

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | Identity request | [Identity type = IMEISV] |
| 2 | ME → USS | Identity response | [Mobile identity = IMEISV] |
| 3 | UICC → ME | PROACTIVE COMMAND PENDING PROVIDE LOCAL INFORMATION 1.9.1 | |
| 4 | ME → UICC | FETCH | |
| 5 | UICC → ME | PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.9.1 | |
| 6 | ME → UICC | TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.9.1 | [Command performed successfully, IMEISV] as USS |

PROACTIVE COMMAND: PROVIDE LOCAL INFORMATION 1.9.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "08" IMEISV of the ME

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 26 | 08 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: PROVIDE LOCAL INFORMATION 1.9.1

Logically:

Command details
- Command number: 1
- Command type: PROVIDE LOCAL INFORMATION
- Qualifier: "08" IMEISV of the ME

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

IMEISV
- IMEISV of the ME: The IMEISV of the ME

The result coding depends on the ME IMEISV value as declared in table A.2/24.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 26 | 08 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | E2 | 09 | XX | XX | XX | XX | XX | XX | XX | XX | XX | |

As an example, if the IMEISV of the ME is "1234567890123456" then XX XX XX XX XX XX XX XX XX= 13 32 54 76 98 10 32 54 F6. For further details see also ETSI TS 124.008 [7].

**Expected Sequence 1.10 (PROVIDE LOCAL INFORMATION, Search Mode Change)**

TBD

**Expected Sequence 1.11 (PROVIDE LOCAL INFORMATION, charge state of the battery)**

See ETSI TS 102 384 [26] in subclause 27.22.4.15.4.2, Expected Sequence 1.11.

**Expected Sequence 1.12 (PROVIDE LOCAL INFORMATION, UTRAN Measurements)**

TBD

### 27.22.4.15.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.12.

## 27.22.4.16 SET UP EVENT LIST

### 27.22.4.16.1 SET UP EVENT LIST (normal)

#### 27.22.4.16.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.16.1.2 Conformance requirement

The ME shall support the Proactive UICC: Set Up Event List facility as defined in:

- TS 31.111 [15] clause 6.4.16 and clause 6.6.16.

Additionally the ME shall support the Event Download: Call Connect and the Event Download: Call Disconnected mechanism as defined in:

- TS 31.111 [15] clause 11.2, clause 11.2.1, clause 11.2.2, clause 11.3, clause 11.3.1 and clause 11.3.2.

#### 27.22.4.16.1.3 Test purpose

To verify that the ME accepts a list of events that it shall monitor the current list of events supplied by the UICC, is able to have this current list of events replaced and is able to have the list of events removed.

To verify that when the ME has successfully accepted or removed the list of events, it shall send TERMINAL RESPONSE (OK) to the UICC and when the ME is not able to successfully accept or remove the list of events, it shall send TERMINAL RESPONSE (Command beyond ME's capabilities).

#### 27.22.4.16.1.4 Method of test

##### 27.22.4.16.1.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.16.1.4.2 Procedure

**Expected Sequence 1.1 (SET UP EVENT LIST, Set Up Call Connect Event)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 6 | USS → ME | SETUP 1.1.1 | [Incoming call alert] |
| 7 | USER → ME | User shall accept the incoming call | |
| 8 | ME → USS | CONNECT 1.1.1 | |
| 9 | ME → UICC | ENVELOPE: EVENT DOWNLOAD CALL CONNECTED 1.1.1 | [Call Connected Event] |
| 10 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Call Connected

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
| | 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

SET UP 1.1.1

Logically:

Transaction identifier
- Ti value: 0 (bit 5-7)

Address
- TON: "Unknown"
- NPI: "ISDN/ telephone numbering plan"
- Dialling number string: "9876"

CONNECT 1.1.1

Logically:

Transaction identifier
- Ti value: 0 (bit 5-7)
- Ti flag: 1 (bit 8)

ENVELOPE: EVENT DOWNLOAD CALL CONNECTED 1.1.1

Logically

Event list
- Event 1: Call Connected

Device identities
- Source device: ME
- Destination device: UICC

Transaction identifier
- Ti value: 0 (bit 5-7)
- Ti flag: 1 (bit 8)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 99 | 01 | 01 | 82 | 02 | 82 | 81 | 9C | 01 | 80 |

**Expected Sequence 1.2 (SET UP EVENT LIST, Replace Event)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.2.1 | [Call Connected and Call Disconnected Events] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.2.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.2.2 | |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.2.2 | [Call Disconnected Event] |
| 8 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.2.2 | |
| 9 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 10 | USS → ME | SETUP 1.2.2 | [Incoming call alert] |
| 11 | USER → ME | User shall accept the incoming call | |
| 12 | ME → USS | CONNECT 1.2.2 | |
| 13 | USS → ME | DISCONNECT 1.2.2 | |
| 14 | ME → UICC | ENVELOPE: EVENT DOWNLOAD CALL DISCONNECT 1.2.2A or ENVELOPE: EVENT DOWNLOAD CALL DISCONNECT 1.2.2B | [Call Disconnect Event] |
| 15 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Call Connected
- Event 2: Call Disconnected

Coding:

| BER-TLV: | D0 | 0D | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 02 | 01 | 02 | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

PROACTIVE COMMAND: SET UP EVENT LIST 1.2.2

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: UICC
Destination device: ME
Event list
Event 1: Call Disconnected

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
| | 01 | 02 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.2.2

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

SET UP 1.2.2

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Address
TON: "Unknown"
NPI: "ISDN/ telephone numbering plan"
Dialling number string: "9876"

CONNECT 1.2.2

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

DISCONNECT 1.2.2

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause
Value: Normal call clearing

ENVELOPE: EVENT DOWNLOAD CALL DISCONNECTED 1.2.2A

Logically:

Event list
Event 1: Call Disconnected
Device identities
Source device: Network
Destination device: UICC
Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause
Value: Normal call clearing

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 99 | 01 | 02 | 82 | 02 | 83 | 81 | 9C | 01 | 00 |
| | 9A | 02 | 60 | 90 | | | | | | | | |

ENVELOPE: EVENT DOWNLOAD CALL DISCONNECTED 1.2.2B

Logically:

Event list
Event 1: Call Disconnected
Device identities
Source device: Network
Destination device: UICC
Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause
Value: Normal call clearing

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 99 | 01 | 02 | 82 | 02 | 83 | 81 | 9C | 01 | 00 |
| | 9A | 02 | E0 | 90 | | | | | | | | |

**Expected Sequence 1.3 (SET UP EVENT LIST, Remove Event)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.3.1 | [Call Connected Event] |
| | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.3.1 | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.3.2 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.3.2 | [Remove Event] |
| 7 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.3.2 | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 10 | USS → ME | SETUP 1.3.2 | [Incoming call alert] |
| 11 | USER → ME | User shall accept the incoming call | |
| 12 | ME → USS | CONNECT 1.3.2 | |
| 13 | ME → UICC | No ENVELOPE: EVENT DOWNLOAD (call connected) sent | |
| 14 | USS → ME | DISCONNECT 1.3.2 | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Call Connected

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

PROACTIVE COMMAND: SET UP EVENT LIST 1.3.2

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME
- Event list: Empty

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0B | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
| | 00 | | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.3.2

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

SET UP 1.3.2

Logically:

Transaction identifier
- Ti value: 0 (bit 5-7)
- Ti flag: 0 (bit 8)

Address
- TON: "Unknown"
- NPI: "ISDN/ telephone numbering plan"
- Dialling number string: "9876"

CONNECT 1.3.2

Logically:

Transaction identifier
- Ti value: 0 (bit 5-7)
- Ti flag: 1 (bit 8)

DISCONNECT 1.3.2

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause
Value: Normal call clearing

**Expected Sequence 1.4 (SET UP EVENT LIST, Remove Event on ME Power Cycle)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.4.1 | [Call Connected Event] |
| | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.4.1 | |
| 4 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 5 | User → ME | Power off ME | |
| 6 | User → ME | Power on ME | |
| 7 | USS → ME | SETUP 1.4.1 | [Incoming call alert] |
| 8 | USER → ME | User shall accept the incoming call | |
| 9 | ME → USS | CONNECT 1.4.1 | |
| 10 | ME → UICC | No ENVELOPE: EVENT DOWNLOAD (call connected) sent | |
| 11 | USS → ME | DISCONNECT 1.4.1 | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.4.1

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: UICC
Destination device: ME
Event list
Event 1: Call Connected

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.4.1

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: ME

Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

SET UP 1.4.1

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Address
TON: "Unknown"
NPI: "ISDN/ telephone numbering plan"
Dialling number string: "9876"

CONNECT 1.4.1

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

DISCONNECT 1.4.1

Logically:

Transaction identifier
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause
Value: Normal call clearing

#### 27.22.4.16.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4.

## 27.22.4.17 PERFORM CARD APDU

### 27.22.4.17.1 PERFORM CARD APDU (normal)

#### 27.22.4.17.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.17.1.2 Conformance requirement

The ME shall support the Proactive UICC: Perform Card APDU facility as defined in:

- TS 31.111 [15] clause 6.1, clause 5.2, clause 6.4.17, clause 6.6.17, clause 6.8, clause 8.6, clause 8.7, clause 8.35, clause 8.36 and clause 8.12.9.

Additionally the ME shall support multiple card operation as defined in:

- TS 31.111 [15] clause 6.4.19, clause 6.6.19, clause 6.4.18 and clause 6.6.18.

#### 27.22.4.17.1.3 Test purpose

To verify that the ME sends an APDU command to the additional card identified in the PERFORM CARD APDU proactive UICC command, and successfully returns the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

In this particular case a special Test-SIM (TestSIM) with T=0 protocol is chosen as additional card for the additional ME card reader (for coding of the TestSIM see annex A).

#### 27.22.4.17.1.4 Method of test

##### 27.22.4.17.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The TestSIM is inserted in the additional ME card reader.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

The elementary files of the TestSIM are coded as defined in annex A. Another card with different parameters may be used as TestSIM to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

##### 27.22.4.17.1.4.2 Procedure

**Expected Sequence 1.1 (PERFORM CARD APDU, card reader 1, additional card inserted, Select MF and Get Response)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (PERFORM CARD APDU, card reader 1, additional card inserted, Select DF GSM, Select EF PLMN , Update Binary, Read Binary on EF PLMN)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (PERFORM CARD APDU, card reader 1, card inserted, card powered off)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.3.

**Expected Sequence 1.4 (PERFORM CARD APDU, card reader 1, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.4.

**Expected Sequence 1.5 (PERFORM CARD APDU, card reader 7 (which is not the valid card reader identifier of the additional ME card reader))**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.1.4.2, Expected Sequence 1.5.

#### 27.22.4.17.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.5.

#### 27.22.4.17.2 PERFORM CARD APDU (detachable card reader)

##### 27.22.4.17.2.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.17.2.2 Conformance requirement

##### 27.22.4.17.2.3 Test purpose

To verify that the ME sends an APDU command to the additional card identified in the PERFORM CARD APDU proactive UICC command, and successfully returns the result of the execution of the command in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.17.2.4 Method of test

###### 27.22.4.17.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The card reader shall be detached from the ME.

###### 27.22.4.17.2.4.2 Procedure

**Expected Sequence 2.1 (PERFORM CARD APDU, card reader 1, card reader detached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.17.2.4.2, Expected Sequence 2.1.

##### 27.22.4.17.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

### 27.22.4.18 POWER OFF CARD

#### 27.22.4.18.1 POWER OFF CARD (normal)

##### 27.22.4.18.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.18.1.2 Conformance requirement

The ME shall support the Proactive UICC: Power Off Card facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.18, clause 6.6.18, clause 8.6, clause 8.7, clause 8.12, clause 8.12.9, clause 5.2 and annex H.

##### 27.22.4.18.1.3 Test purpose

To verify that the ME closes a session with the additional card identified in the POWER OFF CARD proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

#### 27.22.4.18.1.4 Method of test

##### 27.22.4.18.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to aSIM Simulator (SIM2). Instead of a SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

##### 27.22.4.18.1.4.2 Procedure

**Expected Sequence 1.1 (POWER OFF CARD, card reader 1)**

See ETSI TS 102 384 [26] in subclause 27.22.4.18.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (POWER OFF CARD, card reader 1, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.4.18.1.4.2, Expected Sequence 1.2.

#### 27.22.4.18.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.2.

### 27.22.4.18.2 POWER OFF CARD (detachable card reader)

#### 27.22.4.18.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.18.2.2 Conformance requirement

Void.

#### 27.22.4.18.2.3 Test purpose

To verify that the ME closes a session with the additional card identified in the POWER OFF CARD proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.18.2.4 Method of test

##### 27.22.4.18.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2).

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

The card reader shall be detached from the ME.

#### 27.22.4.18.2.4.2 Procedure

**Expected Sequence 2.1 (POWER OFF CARD, card reader 1, no card reader attached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.18.2.4.2, Expected Sequence 2.1.

#### 27.22.4.18.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.19 POWER ON CARD

### 27.22.4.19.1 POWER ON CARD (normal)

#### 27.22.4.19.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.19.1.2 Conformance requirement

The ME shall support the Proactive UICC: Power On Card facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.19, clause 6.6.19, clause 8.6, clause 8.7, clause 8.12, clause 8.12.9, clause 8.34, clause 5.2 and annex H.

#### 27.22.4.19.1.3 Test purpose

To verify that the ME starts a session with the additional card identified in the POWER ON CARD proactive UICC command, and successfully returns the Answer To Reset within the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

#### 27.22.4.19.1.4 Method of test

##### 27.22.4.19.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2). Instead of the SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

##### 27.22.4.19.1.4.2 Procedure

**Expected Sequence 1.1 (POWER ON CARD, card reader 1)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (POWER ON CARD, card reader 1, no ATR)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (POWER ON CARD, card reader 1, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.1.4.2, Expected Sequence 1.3.

#### 27.22.4.19.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

### 27.22.4.19.2 POWER ON CARD (detachable card reader)

#### 27.22.4.19.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.19.2.2 Conformance requirement

#### 27.22.4.19.2.3 Test purpose

To verify that the ME starts a session with the additional card identified in the POWER ON CARD proactive UICC command, and successfully returns the Answer To Reset within the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.19.2.4 Method of test

##### 27.22.4.19.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The card reader shall be detached from the ME.

##### 27.22.4.19.2.4.2 Procedure

**Expected Sequence 2.1 (POWER ON CARD, card reader 1, no card reader attached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.19.2.4.2, Expected Sequence 2.1.

#### 27.22.4.19.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.20 GET READER STATUS

### 27.22.4.20.1 GET READER STATUS (normal)

#### 27.22.4.20.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.20.1.2 Conformance requirement

The ME shall support the Proactive UICC: Get Card Reader Status facility as defined in:

- TS 31.111 [15] clause 6.1, clause 5.2, clause 6.4.20, clause 6.6.20, clause 6.8, clause 8.6, clause 8.7, clause 8.33, clause 8.57 and annex H.

Additionally the ME shall support multiple card operation as defined in:

- TS 31.111 [15] clause 6.4.19, clause 6.6.19, clause 6.4.18 and clause 6.6.18.

#### 27.22.4.20.1.3 Test purpose

To verify that the ME sends starts a session with the additional card identified in the GET CARD READER STATUS proactive UICC command, and successfully returns information about all interfaces to additional card reader(s) in the TERMINAL RESPONSE command send to the UICC.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

In this test case the SIM-Simulator (SIM2) shall response with the ATR "3B 00".

#### 27.22.4.20.1.4 Method of test

##### 27.22.4.20.1.4.1 Initial conditions

The ME shall support the Proactive UICC: Get Card Reader Status (Card Reader Status) facility. The ME is connected to the USIM Simulator.

The ME card reader is connected to a SIM Simulator (SIM2). Instead of the SIM Simulator a card with different parameters may be used as SIM2 to execute these tests. In this case the USIM Simulator shall take into account the corresponding response data.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

If the ME supports a detachable card reader, the card reader shall be attached to the ME.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

##### 27.22.4.20.1.4.2 Procedure

**Expected Sequence 1.1 (GET CARD READER STATUS, card reader 1, card inserted, card powered)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (GET CARD READER STATUS, card reader 1, card inserted, card not powered)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (GET CARD READER STATUS, card reader 1, card not present)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.1.4.2, Expected Sequence 1.3.

#### 27.22.4.20.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

### 27.22.4.20.2 GET CARD READER STATUS (detachable card reader)

#### 27.22.4.20.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.20.2.2 Conformance requirement

Void.

#### 27.22.4.20.2.3 Test purpose

To verify that the ME closes a session with the additional card identified in the GET CARD READER STATUS proactive UICC command, and successfully returns result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.20.2.4 Method of test

##### 27.22.4.20.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to this test the ME shall have powered on the SIM Simulator (SIM2).

The card reader shall be detached from the ME.

##### 27.22.4.20.2.4.2 Procedure

**Expected Sequence 2.1 (GET CARD READER STATUS, no card reader attached)**

See ETSI TS 102 384 [26] in subclause 27.22.4.20.2.4.2, Expected Sequence 2.1.

#### 27.22.4.20.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 2.1.

## 27.22.4.21 TIMER MANAGEMENT and ENVELOPE TIMER EXPIRATION

### 27.22.4.21.1 TIMER MANAGEMENT (normal)

#### 27.22.4.21.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.21.1.2 Conformance Requirement

The ME shall support the TIMER MANAGEMENT as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.21, clause 6.8, clause 8.6, clause 8.7, clause 8.37 and clause 8.38.

#### 27.22.4.21.1.3 Test purpose

To verify that the ME manages correctly its internal timers, start a timer, deactivate a timer or return the current value of a timer according to the Timer Identifier defined in the TIMER MANAGEMENT proactive UICC command.

#### 27.22.4.21.1.4 Method of Test

##### 27.22.4.21.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

27.22.4.21.1.4.2 Procedure

**Expected Sequence 1.1 (TIMER MANAGEMENT, start timer 1 several times, get the current value of the timer and deactivate the timer successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (TIMER MANAGEMENT, start timer 2 several times, get the current value of the timer and deactivate the timer successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.2.

**Expected Sequence 1.3 (TIMER MANAGEMENT, start timer 8 several times, get the current value of the timer and deactivate the timer successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.3.

**Expected Sequence1.4 (TIMER MANAGEMENT, try to get the current value of a timer which is not started: action in contradiction with the current timer state)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.4.

**Expected Sequence1.5 (TIMER MANAGEMENT, try to deactivate a timer which is not started: action in contradiction with the current timer state)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.5.

**Expected Sequence 1.6 (TIMER MANAGEMENT, start 8 timers successfully)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.1.4.2, Expected Sequence 1.6.

27.22.4.21.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.6.

## 27.22.4.21.2 ENVELOPE TIMER EXPIRATION (normal)

### 27.22.4.21.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.21.2.2 Conformance requirement

The ME shall support the ENVELOPE (TIMER EXPIRATION) command as defined in the following technical specifications:

- TS 31.111 [15] clause 4.10, clause 7.4.1 and clause 7.4.2.

The ME shall support the TIMER MANAGEMENT as defined in the following technical specifications:

- TS 31.111 [15] clause 5.2, clause 6.4.21, clause 6.8, clause 8.6, clause 8.7, clause 8.37 and clause 8.38.

### 27.22.4.21.2.3 Test purpose

To verify that the ME shall pass the identifier of the timer that has expired and its value using the ENVELOPE (TIMER EXPIRATION) command, when a timer previously started in a TIMER MANAGEMENT proactive command expires.

### 27.22.4.21.2.4 Method of test

#### 27.22.4.21.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default with the following exceptions.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The timer 1 is not started.

When the UICC is busy when the envelope TIMER EXPIRATION is sent, either the ME retries periodically to send the envelope or it waits for a status not indicating busy.

#### 27.22.4.21.2.4.2 Procedure

**Expected Sequence 2.1 (TIMER EXPIRATION, pending proactive UICC command)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.2.4.2, Expected Sequence 2.1.

**Expected Sequence 2.2 (TIMER EXPIRATION, UICC application toolkit busy)**

See ETSI TS 102 384 [26] in subclause 27.22.4.21.2.4.2, Expected Sequence 2.2.

#### 27.22.4.21.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.2.

## 27.22.4.22 SET UP IDLE MODE TEXT

### 27.22.4.22.1 SET UP IDLE MODE TEXT (normal)

#### 27.22.4.22.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.1.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 6.4.7 and clause 6.6.13.

Additionally the ME shall support the REFRESH proactive UICC facility as defined in:

- TS 31.111 [15] clause 5.2, clause 6.1, clause 6.4.7, clause 6.6.13, clause 6.11, clause 8.6, clause 8.7, clause 8.12, clause 9.4 and clause 10.

#### 27.22.4.22.1.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text.

#### 27.22.4.22.1.4 Method of test

#### 27.22.4.22.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.22.1.4.2 Procedure

**Expected Sequence 1.1 (SET UP IDLE MODE TEXT, display idle mode text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.1.

### Expected Sequence 1.2 (SET UP IDLE MODE TEXT, replace idle mode text)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.2.

### Expected Sequence 1.3 (SET UP IDLE MODE TEXT, remove idle mode text)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.3.

### Expected Sequence 1.4 (SET UP IDLE MODE TEXT, competing information on ME display)

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP IDLE MODE TEXT 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP IDLE MODE TEXT 1.1.1 | ["Idle Mode Text"] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP IDLE MODE TEXT 1.1.1 | [Command performed successfully] |
| 5 | USER → ME | Select idle screen | Only if idle screen not already available |
| 6 | ME → USER | Display "Idle Mode Text" | |
| 7 | USS → ME | SMS PP 1.4.1 | [Display immediate SMS] |
| 8 | ME → USER | Display "Test Message" | |
| 9 | USER → ME | Clear display and select idle screen | |
| 10 | ME → USER | Display "Idle Mode Text" | |
| 11 | UICC → ME | PROACTIVE COMMAND PENDING: DISPLAY TEXT 1.4.1 | |
| 12 | ME → UICC | FETCH | |
| 13 | UICC → ME | PROACTIVE COMMAND: DISPLAY TEXT 1.4.1 | [Normal priority, wait for user to clear message, unpacked, 8 bit data] |
| 14 | ME → USER | Display "Toolkit Test 1" | |
| 15 | USER → ME | Clear Message | |
| 16 | ME → UICC | TERMINAL RESPONSE: DISPLAY TEXT 1.4.1 | [Command performed successfully] |
| 17 | ME → USER | Display "Idle Mode Text" | |
| 18 | UICC → ME | PROACTIVE COMMAND PENDING: PLAY TONE 1.4.1 | |
| 19 | ME → UICC | FETCH | |
| 20 | UICC → ME | PROACTIVE COMMAND: PLAY TONE 1.4.1 | |
| 21 | ME → USER | Display "Dial Tone"<br>Play a standard supervisory dial tone through the external ringer for a duration of 5 s | |
| 22 | ME → UICC | TERMINAL RESPONSE: PLAY TONE 1.4.1 | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 24 | ME → USER | Display "Idle Mode Text" | |

SMS-PP 1.4.1

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-DELIVER |
| TP-MMS | No more messages waiting for the MS in this SC |
| TP-RP | TP-Reply-Path is not set in this SMS-DELIVER |
| TP-UDHI | TP-UD field contains only the short message |
| TP-SRI | A status report will not be returned to the ME |
| TP-OA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "1234" |

TP-PID "00"
TP-DCS
Coding Group General Data Coding
Compression Text is uncompressed
Message Class Class 0
Alphabet GSM 7 bit default alphabet
TP-SCTS: 01/01/98 00:00:00 +0
TP-UDL 12
TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 04 | 04 | 91 | 21 | 43 | 00 | 10 | 89 | 10 | 10 | 00 | 00 |
| | 00 | 00 | 0C | D4 | F2 | 9C | 0E | 6A | 96 | E7 | F3 | F0 |
| | B9 | 0C | | | | | | | | | | |

PROACTIVE COMMAND: DISPLAY TEXT 1.4.1

Logically:

Command details
Command number: 1
Command type: DISPLAY TEXT
Command qualifier: normal priority, wait for user to clear message
Device identities
Source device: UICC
Destination device: Display
Text String
Data coding scheme: unpacked, 8 bit data
Text: "Toolkit Test 1"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 21 | 80 | 82 | 02 | 81 | 02 | 8D |
| | 0F | 04 | 54 | 6F | 6F | 6C | 6B | 69 | 74 | 20 | 54 | 65 |
| | 73 | 74 | 20 | 31 | | | | | | | | |

TERMINAL RESPONSE: DISPLAY TEXT 1.4.1

Logically:

Command details
Command number: 1
Command type: DISPLAY TEXT
Command qualifier: normal priority, wait for user to clear message
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 21 | 80 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

PROACTIVE COMMAND: PLAY TONE 1.4.1

Logically:

Command details
- Command number: 1
- Command type: PLAY TONE
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Earpiece
- Alpha identifier: "Dial Tone"
- TONe: Standard supervisory tones: dial tone

Duration
- Time unit: Seconds
- Time interval: 5

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 20 | 00 | 82 | 02 | 81 | 03 | 85 |
| | 09 | 44 | 69 | 61 | 6C | 20 | 54 | 6F | 6E | 65 | 8E | 01 |
| | 01 | 84 | 02 | 01 | 05 | | | | | | | |

TERMINAL RESPONSE: PLAY TONE 1.4.1

Logically:

Command details
- Command number: 1
- Command type: PLAY TONE
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 20 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.5 (SET UP IDLE MODE TEXT, ME power cycled)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP IDLE MODE TEXT 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP IDLE MODE TEXT 1.1.1 | ["Idle Mode Text"] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP IDLE MODE TEXT 1.1.1 | [command performed successfully] |
| 5 | USER → ME | Select idle screen | Only if idle screen not already available |
| 6 | ME → USER | Display "Idle Mode Text" | |
| 7 | USER → ME | Power off ME | |
| 8 | ME ⇔ UICC | 3G Session TERMINATION PROCEDURE | |
| 9 | USER → ME | Power on ME | |
| 10 | ME ⇔ UICC | 3G Session ACTIVATION PROCEDURE | |
| 11 | ME ⇔ UICC | USIM INITIALIZATION | |
| 12 | USER → ME | Select idle screen | Only if idle screen not already available |
| 13 | ME → USER | Display idle screen / "Idle Mode Text" not to be displayed | |

**Expected Sequence 1.6 (SET UP IDLE MODE TEXT, REFRESH with USIM Initialization)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP IDLE MODE TEXT 1.1.1 | [Idle Mode Text] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP IDLE MODE TEXT 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP IDLE MODE TEXT 1.1.1 | |
| 5 | USER → ME | Select idle screen | Only if idle screen not already available |
| 6 | ME → USER | Display "Idle Mode Text" | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: REFRESH 1.6.1 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: REFRESH 1.6.1 | [USIM Initialization] |
| 10 | ME ⇔ UICC | USIM INITIALIZATION | |
| 11 | USER → ME | Select idle screen | Only if idle screen not already available |
| 12 | ME → USER | Display idle screen / "Idle Mode Text" not to be displayed | |
| 13 | ME → UICC | TERMINAL RESPONSE: REFRESH 1.6.1A<br>or<br>TERMINAL RESPONSE: REFRESH 1.6.1B | [Command performed successfully]<br>[Command performed successfully with additional files read] |
| 14 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: REFRESH 1.6.1

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Initialization

Device identities
- Source device: UICC

Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 01 | 03 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: REFRESH 1.6.1A

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Initialization

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 03 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

TERMINAL RESPONSE: REFRESH 1.6.1B

Logically:

Command details
- Command number: 1
- Command type: REFRESH
- Command qualifier: USIM Initialization

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: REFRESH performed with additional EFs read

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 01 | 03 | 82 | 02 | 82 | 81 | 83 | 01 | 03 |

**Expected Sequence 1.7 (SET UP IDLE MODE TEXT, large text string)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.1.4.2, Expected Sequence 1.7.

#### 27.22.4.22.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

### 27.22.4.22.2 SET UP IDLE MODE TEXT (Icon support)

#### 27.22.4.22.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.2.2 Conformance requirement

27.22.4.22.2.3 Test purpose

To verify that the ME text and / or icon passed to the ME is displayed by the ME as an idle mode text.

To verify that the icon identifier provided with the text string can replace the text string or accompany it.

To verify that if both an alpha identifier or text string, and an icon are provided with a proactive command, and both are requested to be displayed, but the ME is not able to display both together on the screen, then the alpha identifier or text string takes precedence over the icon.

To verify that if the UICC provides an icon identifier with a proactive command, then the ME shall inform the UICC if the icon could not be displayed by sending the general result "Command performed successfully, but requested icon could not be displayed".

To verify that if the ME receives an icon identifier with a proactive command, and either an empty, or no alpha identifier / text string is given by the UICC, than the ME shall reject the command with general result "Command data not understood by ME".

27.22.4.22.2.4 Method of test

27.22.4.22.2.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in update idle mode on the System Simulator.

27.22.4.22.2.4.2 Procedure

**Expected Sequence 2.1A (SET UP IDLE MODE TEXT, Icon is self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.1A.

**Expected Sequence 2.1B (SET UP IDLE MODE TEXT, Icon is self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.1B.

**Expected Sequence 2.2A (SET UP IDLE MODE TEXT, Icon is not self-explanatory, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.2A.

**Expected Sequence 2.2B (SET UP IDLE MODE TEXT, Icon is not self-explanatory, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.2B.

**Expected Sequence 2.3A (SET UP IDLE MODE TEXT, Icon is self-explanatory, colour icon, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.3A.

**Expected Sequence 2.3B (SET UP IDLE MODE TEXT, Icon is self-explanatory, colour icon, requested icon could not be displayed)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.3B.

**Expected Sequence 2.4 (SET UP IDLE MODE TEXT, Icon is not self-explanatory, empty text string)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.2.4.2, Expected Sequence 2.4.

#### 27.22.4.22.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1A to 2.4.

### 27.22.4.22.3 SET UP IDLE MODE TEXT (UCS2 support)

#### 27.22.4.22.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.3.2 Conformance requirement

The ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.22.3.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

#### 27.22.4.22.3.4 Method of test

##### 27.22.4.22.3.4.1 Initial conditions

The ME is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in update idle mode on the System Simulator..

##### 27.22.4.22.3.4.2 Procedure

**Expected Sequence 3.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.3.4.2, Expected Sequence 3.1.

#### 27.22.4.22.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.22.4 SET UP IDLE MODE TEXT (support of Text Attribute)

#### 27.22.4.22.4.1 SET UP IDLE MODE TEXT (support of Text Attribute – Left Alignment)

##### 27.22.4.22.4.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.1.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.1.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the left alignment text attribute configuration.

#### 27.22.4.22.4.1.4 Method of test

##### 27.22.4.22.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.22.4.1.4.2 Procedure

**Expected Sequence 4.1 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Left Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.1.4.2, Expected Sequence 4.1.

#### 27.22.4.22.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.22.4.2 SET UP IDLE MODE TEXT (support of Text Attribute – Center Alignment)

#### 27.22.4.22.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.4.2.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

#### 27.22.4.22.4.2.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the center alignment text attribute configuration.

#### 27.22.4.22.4.2.4 Method of test

##### 27.22.4.22.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.22.4.2.4.2 Procedure

Expected Sequence 4.2 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Center Alignment)

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.2.4.2, Expected Sequence 4.2.

#### 27.22.4.22.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

27.22.4.22.4.3 SET UP IDLE MODE TEXT (support of Text Attribute – Right Alignment)

27.22.4.22.4.3.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.4.3.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

27.22.4.22.4.3.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the right alignment text attribute configuration.

27.22.4.22.4.3.4 Method of test

27.22.4.22.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.3.4.2 Procedure

**Expected Sequence 4.3 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Right Alignment)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.3.4.2, Expected Sequence 4.3.

27.22.4.22.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

27.22.4.22.4.4 SET UP IDLE MODE TEXT (support of Text Attribute – Large Font Size)

27.22.4.22.4.4.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.4.4.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

27.22.4.22.4.4.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the large font size text attribute configuration.

27.22.4.22.4.4.4 Method of test

27.22.4.22.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.4.4.2 Procedure

**Expected Sequence 4.4 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Large Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.4.4.2, Expected Sequence 4.4.

27.22.4.22.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

27.22.4.22.4.5 SET UP IDLE MODE TEXT (support of Text Attribute – Small Font Size)

27.22.4.22.4.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.4.5.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

27.22.4.22.4.5.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the small font size text attribute configuration.

27.22.4.22.4.5.4 Method of test

27.22.4.22.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.5.4.2 Procedure

**Expected Sequence 4.5 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Small Font Size)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.5.4.2, Expected Sequence 4.5.

27.22.4.22.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

27.22.4.22.4.6 SET UP IDLE MODE TEXT (support of Text Attribute – Bold On)

27.22.4.22.4.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.4.6.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

27.22.4.22.4.6.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the bold text attribute configuration.

27.22.4.22.4.6.4 Method of test

27.22.4.22.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.6.4.2 Procedure

**Expected Sequence 4.6 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Bold On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.6.4.2, Expected Sequence 4.6.

27.22.4.22.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

27.22.4.22.4.7 SET UP IDLE MODE TEXT (support of Text Attribute – Italic On)

27.22.4.22.4.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.4.7.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

27.22.4.22.4.7.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the italic text attribute configuration.

27.22.4.22.4.7.4 Method of test

27.22.4.22.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.7.4.2 Procedure

**Expected Sequence 4.7 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Italic On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.7.4.2, Expected Sequence 4.7.

27.22.4.22.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

#### 27.22.4.22.4.8 SET UP IDLE MODE TEXT (support of Text Attribute – Underline On)

##### 27.22.4.22.4.8.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.8.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

##### 27.22.4.22.4.8.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the underline text attribute configuration.

##### 27.22.4.22.4.8.4 Method of test

###### 27.22.4.22.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

###### 27.22.4.22.4.8.4.2 Procedure

**Expected Sequence 4.8 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Underline On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.8.4.2, Expected Sequence 4.8.

##### 27.22.4.22.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

#### 27.22.4.22.4.9 SET UP IDLE MODE TEXT (support of Text Attribute – Strikethrough On)

##### 27.22.4.22.4.9.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.22.4.9.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

##### 27.22.4.22.4.9.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the strikethrough text attribute configuration.

##### 27.22.4.22.4.9.4 Method of test

###### 27.22.4.22.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.9.4.2 Procedure

**Expected Sequence 4.9 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Strikethrough On)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.9.4.2, Expected Sequence 4.9.

27.22.4.22.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

27.22.4.22.4.10 SET UP IDLE MODE TEXT (support of Text Attribute – Foreground and Background Colour)

27.22.4.22.4.10.1 Definition and applicability

See clause 3.2.2.

27.22.4.22.4.10.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

27.22.4.22.4.10.3 Test purpose

To verify that the text passed to the ME is displayed as idle mode text according to the foreground and background colour text attribute configuration.

27.22.4.22.4.10.4 Method of test

27.22.4.22.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.4.22.4.10.4.2 Procedure

**Expected Sequence 4.10 (SET UP IDLE MODE TEXT, display idle mode text, Text Attribute – Foreground and Background Colour)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.4.10.4.2, Expected Sequence 4.10.

27.22.4.22.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

27.22.4.22.5 SET UP IDLE MODE TEXT (UCS2 display in Chinese)

27.22.4.22.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.5.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

The Terminal shall additionally support the UCS2 facility for the coding of the Chinese character, as defined in:

ISO/IEC 10646 [17a/17b].

#### 27.22.4.22.5.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

#### 27.22.4.22.5.4 Method of test

##### 27.22.4.22.5.4.1 Initial conditions

The Terminal is connected to both the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the Terminal shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.22.5.4.2 Procedure

**Expected Sequence 5.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text in Chinese)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.5.4.2, Expected Sequence 5.1.

#### 27.22.4.22.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.22.6 SET UP IDLE MODE TEXT (UCS2 display in Katakana)

#### 27.22.4.22.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.22.6.2 Conformance requirement

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.22, clause 6.6.22, clause 6.4.16, clause 6.6.16, clause 7.5.6, clause 6.8, clause 7.5, clause 7.5.1, clause 8.25, clause 8.70, clause 6.4.7 and clause 6.6.13.

The ME shall additionally support the UCS2 facility for the coding of the Katakana character, as defined in:

ISO/IEC 10646 [17a/17b].

#### 27.22.4.22.6.3 Test purpose

To verify that the UCS2 coded text string is displayed by the ME as an idle mode text.

#### 27.22.4.22.6.4 Method of test

##### 27.22.4.22.6.4.1 Initial conditions

The ME is connected to both the UICC Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

#### 27.22.4.22.6.4.2 Procedure

**Expected Sequence 6.1 (SET UP IDLE MODE TEXT, UCS2 alphabet text in Katakana)**

See ETSI TS 102 384 [26] in subclause 27.22.4.22.6.4.2, Expected Sequence 6.1.

#### 27.22.4.22.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.23 RUN AT COMMAND

### 27.22.4.23.1 RUN AT COMMAND (normal)

#### 27.22.4.23.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.1.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31 and clause 8.41.
- TS 27.007 [18].

#### 27.22.4.23.1.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.1.4 Method of test

##### 27.22.4.23.1.4.1 Initial conditions

The ME is connected to the USIM Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.1.4.2 Procedure

**Expected Sequence 1.1(RUN AT COMMAND, no alpha identifier presented, request IMSI)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 1.1.1 | [no alpha identifier, request IMSI] |
| 4 | ME (→ User) | The ME may give information to the user concerning what is happening | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 1.1.1 | [Command performed successfully, AT Response containing IMSI] |

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.1.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

AT Command
- AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 12 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | A8 |
| | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 1.1.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

AT Response
- AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

**Expected Sequence 1.2 (RUN AT COMMAND, null data alpha identifier presented, request IMSI)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 1.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 1.2.1 | [null data alpha identifier, request IMSI] |
| 4 | ME | The ME should not give any information to user on the fact that the ME is performing an AT command | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 1.1.1 | [Command performed successfully, AT Response containing IMSI] |

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.2.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier: null data object

AT Command
- AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 14 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 00 | A8 | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | | |

**Expected Sequence 1.3 (RUN AT COMMAND, alpha identifier presented, request IMSI)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 1.3.1 | [alpha identifier, request IMSI] |
| 4 | ME → USER | Display "Run AT Command" | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 1.1.1 | [Command performed successfully, AT Response containing IMSI] |

PROACTIVE UICC COMMAND: RUN AT COMMAND 1.3.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 0E | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | A8 | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 |

#### 27.22.4.23.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

### 27.22.4.23.2 RUN AT COMMAND (Icon support)

#### 27.22.4.23.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.2.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31 and clause 8.41.
- TS 27.007 [18].

#### 27.22.4.23.2.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

In addition to verify that if an icon is provided by the UICC, the icon indicated in the command may be used by the ME to inform the user, in addition to, or instead of the alpha identifier, as indicated with the icon qualifier.

#### 27.22.4.23.2.4 Method of test

##### 27.22.4.23.2.4.1 Initial conditions

The ME is connected to the USIM Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

The ME screen shall be in its normal stand-by display.

27.22.4.23.2.4.2 Procedure

**Expected Sequence 2.1A (RUN AT COMMAND, basic icon self explanatory, request IMSI, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.1.1 | [BASIC-ICON, self-explanatory, request IMSI] |
| 4 | ME → USER | Display BASIC ICON without the alpha identifier | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A | [Command performed successfully, AT response containing IMSI] |

PROACTIVE COMMAND: RUN AT COMMAND 2.1.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
- Alpha identifier: "Basic Icon"

AT Command
- AT Command string: "AT+CIMI"

Icon identifier:
- Icon qualifier: icon is self-explanatory
- Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | A8 |
| | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | 9E | 02 | 00 | 01 |

TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

AT Response
- AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

**Expected Sequence 2.1B (RUN AT COMMAND, basic icon self explanatory, request IMSI, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.1.1 | [BASIC-ICON, self-explanatory, request IMSI] |
| 4 | ME → USER | Display 'Basic Icon' without the BASIC-ICON | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B | [Command performed but requested icon could not be displayed, AT response containing IMSI] |

TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed

AT Response
- AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

**Expected Sequence 2.2A (RUN AT COMMAND, colour icon self explanatory, request IMSI, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.2.1 | [COLOUR-ICON, self-explanatory, request IMSI] |
| 4 | ME → USER | Display COLOUR-ICON without the alpha identifier | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A | [Command performed successfully, AT response containing IMSI] |

PROACTIVE COMMAND: RUN AT COMMAND 2.2.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
- Alpha identifier: "Colour Icon"

AT Command
- AT Command string: "AT+CIMI"

Icon identifier:
- Icon qualifier: icon is self-explanatory
- Icon identifier: record 2 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | A8 |
| | 0B | 43 | 6F | 6C | 6F | 75 | 72 | 20 | 49 | 63 | 6F | 6E |
| | A8 | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | 9E | 02 | 00 |
| | 02 | | | | | | | | | | | |

**Expected Sequence 2.2B (RUN AT COMMAND, colour icon self explanatory, request IMSI, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.2.1 | [COLOUR-ICON, self-explanatory, request IMSI] |
| 4 | ME → USER | Display 'Colour Icon' without the COLOUR-ICON | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B | [Command performed but requested icon could not be displayed, AT response containing IMSI] |

**Expected Sequence 2.3A (RUN AT COMMAND, basic icon non self-explanatory, request IMSI, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.3.1 | [BASIC-ICON, non self-explanatory, request IMSI] |
| 4 | ME → USER | Display "Basic Icon" and BASIC-ICON | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A | [Command performed successfully, AT response containing IMSI] |

PROACTIVE COMMAND: RUN AT COMMAND 2.3.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
- Alpha identifier: "Basic Icon"

AT Command
- AT Command string: "AT+CIMI"

Icon identifier
- Icon qualifier: icon is non self-explanatory
- Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | A8 |
| | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | 9E | 02 | 01 | 01 |

**Expected Sequence 2.3B (RUN AT COMMAND, basic icon non self-explanatory, request IMSI, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.3.1 | [BASIC-ICON, non self-explanatory, request IMSI] |
| 4 | ME → USER | Display "Basic Icon" without BASIC-ICON | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B | [Command performed but requested icon could not be displayed, AT response containing IMSI] |

**Expected Sequence 2.4A (RUN AT COMMAND, colour icon non self-explanatory, request IMSI, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.4.1 | [COLOUR-ICON, non self-explanatory, request IMSI] |
| 4 | ME → USER | Display "Colour Icon" and COLOUR-ICON | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1A | [Command performed successfully, AT response containing IMSI] |

PROACTIVE COMMAND: RUN AT COMMAND 2.4.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha identifier: "Colour Icon"
AT Command
AT Command string: "AT+CIMI"
Icon identifier:
Icon qualifier: icon is self-explanatory
Icon identifier: record 2 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 0B | 43 | 6F | 6C | 6F | 75 | 72 | 20 | 49 | 63 | 6F | 6E |
| | A8 | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | 9E | 02 | 01 |
| | 02 | | | | | | | | | | | |

**Expected Sequence 2.4B (RUN AT COMMAND, colour icon non self-explanatory, request IMSI, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.4.1 | [COLOUR-ICON, non self-explanatory, request IMSI] |
| 4 | ME → USER | Display "Colour Icon" without COLOUR-ICON | |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.1.1B | [Command performed but requested icon could not be displayed, AT response containing IMSI] |

**Expected Sequence 2.5 (RUN AT COMMAND, basic icon non self-explanatory, no alpha identifier presented)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 2.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 2.5.1 | [BASIC-ICON, non self-explanatory] |
| 4 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 2.5.1 | [Command data not understood by ME] |

PROACTIVE COMMAND: RUN AT COMMAND 2.5.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
AT Command
AT Command string: "AT+CIMI"
Icon identifier
Icon qualifier: icon is non self-explanatory
Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 16 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | A8 |
| | 07 | 41 | 54 | 2B | 43 | 49 | 4D | 49 | 9E | 02 | 01 | 01 |

TERMINAL RESPONSE: RUN AT COMMAND 2.5.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Result
General Result: Command data not understood by ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 32 |

#### 27.22.4.23.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.5.

### 27.22.4.23.3 RUN AT COMMAND (support of Text Attribute)

#### 27.22.4.23.3.1 RUN AT COMMAND (support of Text Attribute – Left Alignment)

##### 27.22.4.23.3.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.1.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

27.22.4.23.3.1.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with left alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

27.22.4.23.3.1.4 Method of test

27.22.4.23.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.1.4.2 Procedure

**Expected Sequence 3.1(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.1.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with left alignment, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.1.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.1.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.1.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [Message shall be formatted without left alignment, request IMSI. Remark: If left alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.1.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.1.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC

Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.1.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.1.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result

General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.23.3.2 RUN AT COMMAND (support of Text Attribute – Center Alignment)

#### 27.22.4.23.3.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.3.2.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.2.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with center alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.2.4 Method of test

##### 27.22.4.23.3.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.2.4.2 Procedure

**Expected Sequence 3.2(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.2.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with center alignment, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.2.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.2.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.2.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [Message shall be formatted without center alignment, request IMSI. Remark: If center alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.2.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.2.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
- Alpha Identifier "Run AT Command 1"

AT Command
- AT Command string: "AT+CIMI"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 4D | 49 | D0 | 04 | 00 | 10 | 01 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.2.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.2.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

### 27.22.4.23.3.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.2.

#### 27.22.4.23.3.3 RUN AT COMMAND (support of Text Attribute – Right Alignment)

##### 27.22.4.23.3.3.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.3.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

##### 27.22.4.23.3.3.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with right alignment text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

##### 27.22.4.23.3.3.4 Method of test

###### 27.22.4.23.3.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.3.4.2 Procedure

**Expected Sequence 3.3(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.3.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with right alignment, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.3.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.3.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.3.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [Message shall be formatted without right alignment, request IMSI. Remark: If right alignment is the ME"s default alignment as declared in table A.2/16, no alignment change will take place] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.3.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.3.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
- Alpha Identifier "Run AT Command 1"

AT Command
- AT Command string: "AT+CIMI"

Text Attribute
- Formatting position: 0
- Formatting length: 16
- Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
- Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 4D | 49 | D0 | 04 | 00 | 10 | 02 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.3.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.3.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

### 27.22.4.23.3.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.3.

#### 27.22.4.23.3.4 RUN AT COMMAND (support of Text Attribute – Large Font Size)

##### 27.22.4.23.3.4.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.23.3.4.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

##### 27.22.4.23.3.4.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with large font size as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

##### 27.22.4.23.3.4.4 Method of test

###### 27.22.4.23.3.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.4.4.2 Procedure

**Expected Sequence 3.4(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.4.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with large font size, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.4.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.4.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with normal font size, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.4.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.4.1 | |
| 16 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with large font size, request IMSI] |
| 17 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.4.1 | [Command performed successfully, AT Response containing IMSI] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.4.3 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.4.3 | |
| 22 | ME (→ USER) | Display "Run AT Command 3" | [alpha identifier is displayed with normal font size, request IMSI] |
| 23 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.4.1 | [Command performed successfully, AT Response containing IMSI] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 04 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.4.3

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 3"
AT Command
AT Command string: "AT+CIMI"

Coding:

| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 33 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.4.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.4.

### 27.22.4.23.3.5 RUN AT COMMAND (support of Text Attribute – Small Font Size)

#### 27.22.4.23.3.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.3.5.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.5.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with small font size as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.5.4 Method of test

##### 27.22.4.23.3.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.5.4.2 Procedure

**Expected Sequence 3.5(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.5.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with small font size, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.5.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.5.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with normal font size, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.5.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.5.1 | |
| 16 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with small font size, request IMSI] |
| 17 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.5.1 | [Command performed successfully, AT Response containing IMSI] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.5.3 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.5.3 | |
| 22 | ME (→ USER) | Display "Run AT Command 3" | [alpha identifier is displayed with normal font size, request IMSI] |
| 23 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.5.1 | [Command performed successfully, AT Response containing IMSI] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 08 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.5.3

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 3"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 33 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.5.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.5.

### 27.22.4.23.3.6 RUN AT COMMAND (support of Text Attribute – Bold On)

#### 27.22.4.23.3.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.3.6.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.6.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with bold text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.6.4 Method of test

##### 27.22.4.23.3.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.6.4.2 Procedure

**Expected Sequence 3.6(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.6.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with bold on, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.6.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.6.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with bold off, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.6.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.6.1 | |
| 16 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with bold on, request IMSI] |
| 17 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.6.1 | [Command performed successfully, AT Response containing IMSI] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.6.3 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.6.3 | |
| 22 | ME (→ USER) | Display "Run AT Command 3" | [alpha identifier is displayed with bold off, request IMSI] |
| 23 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.6.1 | [Command performed successfully, AT Response containing IMSI] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 10 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.6.3

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 3"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 33 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.6.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.6.

### 27.22.4.23.3.7 RUN AT COMMAND (support of Text Attribute – Italic On)

#### 27.22.4.23.3.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.3.7.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.7.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with italic text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.7.4 Method of test

##### 27.22.4.23.3.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.7.4.2 Procedure

**Expected Sequence 3.7(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.7.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with italic on, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.7.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.7.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with italic off, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.7.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.7.1 | |
| 16 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with italic on, request IMSI] |
| 17 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.7.1 | [Command performed successfully, AT Response containing IMSI] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.7.3 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.7.3 | |
| 22 | ME (→ USER) | Display "Run AT Command 3" | [alpha identifier is displayed with italic off, request IMSI] |
| 23 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.7.1 | [Command performed successfully, AT Response containing IMSI] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 20 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.7.3

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 3"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 33 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.7.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.7.

### 27.22.4.23.3.8 RUN AT COMMAND (support of Text Attribute – Underline On)

#### 27.22.4.23.3.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.3.8.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.8.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with underline text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.8.4 Method of test

##### 27.22.4.23.3.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.8.4.2 Procedure

**Expected Sequence 3.8(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.8.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with underline on, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.8.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.8.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with underline off, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.8.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.8.1 | |
| 16 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with underline on, request IMSI] |
| 17 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.8.1 | [Command performed successfully, AT Response containing IMSI] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.8.3 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.8.3 | |
| 22 | ME (→ USER) | Display "Run AT Command 3" | [alpha identifier is displayed with underline off, request IMSI] |
| 23 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.8.1 | [Command performed successfully, AT Response containing IMSI] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 40 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.8.3

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 3"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 33 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.8.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

### 27.22.4.23.3.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.8.

### 27.22.4.23.3.9 RUN AT COMMAND (support of Text Attribute – Strikethrough On)

### 27.22.4.23.3.9.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.23.3.9.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.9.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with strikethrough text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.9.4 Method of test

##### 27.22.4.23.3.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

27.22.4.23.3.9.4.2 Procedure

**Expected Sequence 3.9(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.9.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with strikethrough on, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.9.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.9.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with strikethrough off, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.9.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.9.1 | |
| 16 | ME (→ USER) | Display " Run AT Command 1" | [alpha identifier is displayed with strikethrough on, request IMSI] |
| 17 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.9.1 | [Command performed successfully, AT Response containing IMSI] |
| 18 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.9.3 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.9.3 | |
| 22 | ME (→ USER) | Display "Run AT Command 3" | [alpha identifier is displayed with strikethrough off, request IMSI] |
| 23 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.9.1 | [Command performed successfully, AT Response containing IMSI] |
| 24 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 80 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.9.3

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND

Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 3"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 33 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.9.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.9.

### 27.22.4.23.3.10 RUN AT COMMAND (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.23.3.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.3.10.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.3.10.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with foreground and background colour text attribute as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.3.10.4 Method of test

##### 27.22.4.23.3.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

##### 27.22.4.23.3.10.4.2 Procedure

**Expected Sequence 3.10(RUN AT COMMAND, with alpha identifier presented, request IMSI, Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.10.1 | |
| 4 | ME (→ USER) | Display "Run AT Command 1" | [alpha identifier is displayed with foreground and background colour according to the text attribute configuration, request IMSI] |
| 5 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.10.1 | [Command performed successfully, AT Response containing IMSI] |
| 6 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: RUN AT COMMAND 3.10.2 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: RUN AT COMMAND 3.10.2 | |
| 10 | ME (→ USER) | Display "Run AT Command 2" | [alpha identifier is displayed with ME"s default foreground and background colour, request IMSI] |
| 11 | ME → UICC | TERMINAL RESPONSE: RUN AT COMMAND 3.10.1 | [Command performed successfully, AT Response containing IMSI] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.10.1

Logically:

Command details
- Command number: 1
- Command type: RUN AT COMMAND
- Command qualifier: "00"

Device identities

Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 1"
AT Command
AT Command string: "AT+CIMI"
Text Attribute
Formatting position: 0
Formatting length: 16
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 2A | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 31 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | D0 | 04 | 00 | 10 | 00 | B4 | | | | |

PROACTIVE UICC COMMAND: RUN AT COMMAND 3.10.2

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier
Alpha Identifier "Run AT Command 2"
AT Command
AT Command string: "AT+CIMI"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 24 | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 81 | 82 | 85 |
| | 10 | 52 | 75 | 6E | 20 | 41 | 54 | 20 | 43 | 6F | 6D | 6D |
| | 61 | 6E | 64 | 20 | 32 | A8 | 07 | 41 | 54 | 2B | 43 | 49 |
| | 4D | 49 | | | | | | | | | | |

TERMINAL RESPONSE: RUN AT COMMAND 3.10.1

Logically:

Command details
Command number: 1
Command type: RUN AT COMMAND
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC

Result
General Result: Command performed successfully
AT Response
AT Response string: IMSI

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 34 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | A9 | 08 | 09 | 10 | 10 | 10 | 32 | 54 | 76 | 98 | | |

#### 27.22.4.23.3.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.10.

### 27.22.4.23.4 RUN AT COMMAND (UCS2 display in Cyrillic)

#### 27.22.4.23.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.4.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.4.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.4.4 Method of test

##### 27.22.4.23.4.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

##### 27.22.4.23.4.4.2 Procedure

**Expected Sequence 4.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Cyrillic, request ME Manufacturer ID)**

See ETSI TS 102 384 [26] in subclause 27.22.4.23.4.4.2, Expected Sequence 4.1.

#### 27.22.4.23.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.23.5 RUN AT COMMAND (UCS2 display in Chinese)

#### 27.22.4.23.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.5.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.
- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.5.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.5.4 Method of test

##### 27.22.4.23.5.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

##### 27.22.4.23.5.4.2 Procedure

**Expected Sequence 5.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Chinese, request ME Manufacturer ID)**

See ETSI TS 102 384 [26] in subclause 27.22.4.23.5.4.2, Expected Sequence 5.1.

#### 27.22.4.23.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.23.6 RUN AT COMMAND (UCS2 display in Katakana)

#### 27.22.4.23.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.23.6.2 Conformance requirement

The ME shall support the Proactive UICC: RUN AT COMMAND facility as defined in:

- TS 31.111 [15] clause 6.4.23, clause 6.6.23, clause 5.2, clause 6.8, clause 8.6, clause 8.7, clause 8.2, clause 8.40, clause 8.31, clause 8.41 and clause 8.70.

- TS 27.007 [18].

The terminal shall support the text attribute.

#### 27.22.4.23.6.3 Test purpose

To verify that the ME responds to an AT Command contained within a RUN AT COMMAND with UCS2 alpha identifier as though it were initiated by an attached TE, and returns an AT Response within a TERMINAL RESPONSE to the UICC.

#### 27.22.4.23.6.4 Method of test

##### 27.22.4.23.6.4.1 Initial conditions

The ME is connected to the UICC Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

Prior to the test the ME shall be connected to the TE.

The TA-TE interface is set to 8-bit operation.

##### 27.22.4.23.6.4.2 Procedure

**Expected Sequence 6.1(RUN AT COMMAND, alpha identifier presented coded with UCS2 in Katakana, request ME Manufacturer ID)**

See ETSI TS 102 384 [26] in subclause 27.22.4.23.6.4.2, Expected Sequence 6.1.

#### 27.22.4.23.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.24 SEND DTMF

### 27.22.4.24.1 SEND DTMF (Normal)

#### 27.22.4.24.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

#### 27.22.4.24.1.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that if an alpha identifier is provided by the UICC and is a null data object the ME does not give any information to the user on the fact that the ME is performing a SEND DTMF command.

### 27.22.4.24.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

### 27.22.4.24.1.4. 2 Procedure

**Expected Sequence 1.1 (SEND DTMF, normal)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 1.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 1.1.1 | |
| 7 | ME → USER | May give information to the user concerning what is happening. Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 1.1.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- DTMF String: "1" pause "2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | AC |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 02 | C1 | F2 | | | | | | | | | |

Start DTMF 1.1

Logically:

DTMF String: "1"

Start DTMF 1.2

Logically:

DTMF String: "2"

TERMINAL RESPONSE: SEND DTMF 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.2 (SEND DTMF, containing alpha identifier)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 1.2.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 1.2.1 | |
| 7 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | Alpha identifier |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 1.1.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Send DTMF"
- DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 09 | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | AC | 05 |
| | 21 | 43 | 65 | 87 | 09 | | | | | | | |

Start DTMF 1.3

Logically:

DTMF String: "3"

Start DTMF 1.4

Logically:

DTMF String: "4"

Start DTMF 1.5

Logically:

DTMF String: "5"

Start DTMF 1.6

Logically:

DTMF String: "6"

Start DTMF 1.7

Logically:

DTMF String: "7"

Start DTMF 1.8

Logically:

DTMF String: "8"

Start DTMF 1.9

Logically:

DTMF String: "9"

Start DTMF 1.10

Logically:

DTMF String: "0"

**Expected Sequence 1.3 (SEND DTMF, containing alpha identifier with null data object)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 1.3.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 1.3.1 | Alpha identifier with null data object |
| 7 | ME → USER | Do not give any information to the user on the fact that the ME is performing a SEND DTMF command. Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 30 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 1.1.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "" (null data object)
- DTMF String: "1" pause pause pause pause pause pause pause pause pause pause "2"

Coding:

| BER-TLV: | D0 | 13 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | AC | 06 | C1 | CC | CC | CC | CC | 2C | | | |

**Expected Sequence 1.4 (SEND DTMF, mobile is not in a speech call)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 1.1.1 | [Mobile is not in a speech call] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 1.4.1 | [ME currently unable to process command, not in speech call] |
| 5 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

TERMINAL RESPONSE: SEND DTMF 1.4.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: ME currently unable to process command
Additional information: Not in speech call

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 20 |
| | 07 | | | | | | | | | | | |

#### 27.22.4.24.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4.

### 27.22.4.24.2 SEND DTMF (Display of icons)

#### 27.22.4.24.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44, clause 8.31 and clause 6.5.4.

#### 27.22.4.24.2.3 Test purpose

To verify that after a call has been successfully established the ME send the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME do not locally generate audible DTMF tones and play them to the user.

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the icons which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.2.4 Method of test

##### 27.22.4.24.2.4.1 Initial conditions

The ME is connected to the SIM Simulator and only connected to the System Simulator if the System Simulator is mentioned in the sequence table.Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

The elementary files are coded as Toolkit default.

27.22.4.24.2.4.2 Procedure

**Expected Sequence 2.1A (SEND DTMF, BASIC ICON self explanatory, successful)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 2.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 2.1.1 | [BASIC-ICON, self-explanatory] |
| 7 | ME → USER | Display the BASIC-ICON<br>Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 2.1.1A | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Basic Icon"
- DTMF String: "1" pause "2"

Icon identifier
- Icon qualifier: icon is self-explanatory
- Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0A | 42 | 61 | 73 | 69 | 63 | 20 | 49 | 63 | 6F | 6E | AC |
| | 02 | C1 | F2 | 9E | 02 | 00 | 01 | | | | | |

DTMF Request 2.1.1

Logically:

DTMF String: $DTMF_2.1$ = "C1 F2" (given as example)

TERMINAL RESPONSE: SEND DTMF 2.1.1A

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 2.1B (SEND DTMF, BASIC ICON self explanatory, requested icon could not be displayed)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 2.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 2.1.1 | [BASIC-ICON, self-explanatory] |
| 7 | ME → USER | Display "Basic Icon" without the icon<br>Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20 % |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 2.1.1B | [Command performed successfully, but requested icon could not be displayed] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

TERMINAL RESPONSE: SEND DTMF 2.1.1B

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully, but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

### Expected Sequence 2.2A (SEND DTMF, COLOUR-ICON self explanatory, successful)

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 2.2.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 2.2.1 | [COLOUR-ICON] |
| 7 | ME → USER | Display the COLOUR-ICON<br>Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 2.1.1A | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 2.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Colour Icon"
- DTMF String: "1" pause "2"

Icon identifier:
- Icon qualifier: icon is self-explanatory
- Icon identifier: record 2 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1E | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 43 | 6F | 6C | 6F | 75 | 72 | 20 | 49 | 63 | 6F | 6E |
| | AC | 02 | C1 | F2 | 9E | 02 | 00 | 02 | | | | |

### Expected Sequence 2.2B (SEND DTMF, COLOUR-ICON self explanatory, requested icon could not be displayed)

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 2.2.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 2.2.1 | [COLOUR-ICON] |
| 7 | ME → USER | Display "Colour Icon" without the icon<br>Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 2.1.1B | [Command performed successfully, but requested icon could not be displayed] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

### Expected Sequence 2.3A (SEND DTMF, Alpha identifier & BASIC-ICON, not self-explanatory, successful)

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 2.3.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 2.3.1 | [Alpha identifier & BASIC-ICON, not self-explanatory] |
| 7 | ME → USER | Display 'Send DTMF' and the BASIC-ICON<br>Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20 % |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 2.1.1A | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 2.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF"
DTMF String: "1" pause "2"
Icon identifier:
Icon qualifier: icon is not self-explanatory
Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 09 | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | AC | 02 |
| | C1 | F2 | 9E | 02 | 01 | 01 | | | | | | |

**Expected Sequence 2.3B (SEND DTMF, Alpha identifier & BASIC-ICON, not self-explanatory, requested icon could not be displayed)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 2.3.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 2.3.1 | [Alpha identifier & BASIC-ICON, not self-explanatory] |
| 7 | ME → USER | Display "Send DTMF" without the icon<br>Do not locally generate audible DTMF tones and play them to the user. | |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 2.1.1B | [Command performed successfully, but requested icon could not be displayed] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

27.22.4.24.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

## 27.22.4.24.3 SEND DTMF (UCS2 display in Cyrillic)

### 27.22.4.24.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.24.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646. [17].

#### 27.22.4.24.3.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.24.3.4 Method of test

##### 27.22.4.24.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.24.3.4.2 Procedure

**Expected Sequence 3.1 (SEND DTMF, successful, UCS2 text in Cyrillic)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 3.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 3.1.1 | |
| 7 | ME → USER | Display "ЗДРАВСТВУЙТЕ" | ["Hello" in Russian] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 3.1.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 3.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Text: "ЗДРАВСТВУЙТЕ"
- DTMF String: "1" pause "2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 28 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 19 | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 | 04 | 12 |
| | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 | 04 | 22 |
| | 04 | 15 | AC | 02 | C1 | F2 | | | | | | |

TERMINAL RESPONSE: SEND DTMF 3.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successful

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.12.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.24.4 SEND DTMF (support of Text Attribute)

#### 27.22.4.24.4.1 SEND DTMF (support of Text Attribute – Left Alignment)

##### 27.22.4.24.4.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.24.4.1.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

##### 27.22.4.24.4.1.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the left alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.1.4 Method of test

##### 27.22.4.24.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.1.4.2 Procedure

**Expected Sequence 4.1 (SEND DTMF, with text attribute – Left Alignment)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.1.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with left alignment] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.1.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.1.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.1.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/17, no alignment change will take place] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.1.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.1.1

Logically:

Command details

Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"
DTMF String: "1234567890"
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.1.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.1.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.1.

### 27.22.4.24.4.2 SEND DTMF (support of Text Attribute – Center Alignment)

#### 27.22.4.24.4.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.2.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.2.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the center alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.2.4 Method of test

##### 27.22.4.24.4.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.2.4.2 Procedure

**Expected Sequence 4.2 (SEND DTMF, with text attribute – Center Alignment)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.2.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.2.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with center alignment] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.2.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.2.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.2.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/17, no alignment change will take place] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.2.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.2.1

Logically:

Command details

Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"
DTMF String: "1234567890"
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 01 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.2.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.2.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.2.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.2.

### 27.22.4.24.4.3 SEND DTMF (support of Text Attribute – Right Alignment)

#### 27.22.4.24.4.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.3.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.3.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the right alignment text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.3.4 Method of test

##### 27.22.4.24.4.3.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.3.4.2 Procedure

**Expected Sequence 4.3 (SEND DTMF, with text attribute – Right Alignment)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.3.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.3.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with right alignment] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.3.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.3.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.3.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/17, no alignment change will take place] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.3.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.3.1

Logically:

Command details

Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"
DTMF String: "1234567890"
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | B0 | 02 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.3.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.3.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.3.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.3.

### 27.22.4.24.4.4 SEND DTMF (support of Text Attribute – Large Font Size)

#### 27.22.4.24.4.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.4.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.4.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the large font size text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.4.4 Method of test

##### 27.22.4.24.4.4.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.4.4.2 Procedure

**Expected Sequence 4.4 (SEND DTMF, with text attribute – Large Font Size)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.4.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.4.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with large font size] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.4.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.4.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.4.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with normal font size] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.4.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |
| 41 | User → ME | Set up a call to "+0123456789" | |
| 42 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 43 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 44 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.4.1 | |

| | | | |
|---|---|---|---|
| 45 | ME → UICC | FETCH | |
| 46 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.4.1 | |
| 47 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with large font size] |
| 48 | ME → USS | Start DTMF 1.1 | ["1"] |
| 49 | ME → USS | Start DTMF 1.2 | ["2"] |
| 50 | ME → USS | Start DTMF 1.3 | ["3"] |
| 51 | ME → USS | Start DTMF 1.4 | ["4"] |
| 52 | ME → USS | Start DTMF 1.5 | ["5"] |
| 53 | ME → USS | Start DTMF 1.6 | ["6"] |
| 54 | ME → USS | Start DTMF 1.7 | ["7"] |
| 55 | ME → USS | Start DTMF 1.8 | ["8"] |
| 56 | ME → USS | Start DTMF 1.9 | ["9"] |
| 57 | ME → USS | Start DTMF 1.10 | ["0"] |
| 58 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.4.1 | [Command performed successfully] |
| 59 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 60 | User → ME | End the call | |
| 61 | User → ME | Set up a call to "+0123456789" | |
| 62 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 63 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.4.3 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.4.3 | |
| 67 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with normal font size] |
| 68 | ME → USS | Start DTMF 1.1 | ["1"] |
| 69 | ME → USS | Start DTMF 1.2 | ["2"] |
| 70 | ME → USS | Start DTMF 1.3 | ["3"] |
| 71 | ME → USS | Start DTMF 1.4 | ["4"] |
| 72 | ME → USS | Start DTMF 1.5 | ["5"] |
| 73 | ME → USS | Start DTMF 1.6 | ["6"] |
| 74 | ME → USS | Start DTMF 1.7 | ["7"] |
| 75 | ME → USS | Start DTMF 1.8 | ["8"] |
| 76 | ME → USS | Start DTMF 1.9 | ["9"] |
| 77 | ME → USS | Start DTMF 1.10 | ["0"] |
| 78 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.4.1 | [Command performed successfully] |
| 79 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 80 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 04 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.4.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"
Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.4.3

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 33 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.4.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.4.

### 27.22.4.24.4.5 SEND DTMF (support of Text Attribute – Small Font Size)

#### 27.22.4.24.4.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.5.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the small font size text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.5.4 Method of test

##### 27.22.4.24.4.5.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.5.4.2 Procedure

**Expected Sequence 4.5 (SEND DTMF, with text attribute – Small Font Size)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.5.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.5.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with small font size] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.5.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.5.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.5.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with normal font size] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.5.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |
| 41 | User → ME | Set up a call to "+0123456789" | |
| 42 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 43 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 44 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.5.1 | |

| | | | |
|---|---|---|---|
| 45 | ME → UICC | FETCH | |
| 46 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.5.1 | |
| 47 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with small font size] |
| 48 | ME → USS | Start DTMF 1.1 | ["1"] |
| 49 | ME → USS | Start DTMF 1.2 | ["2"] |
| 50 | ME → USS | Start DTMF 1.3 | ["3"] |
| 51 | ME → USS | Start DTMF 1.4 | ["4"] |
| 52 | ME → USS | Start DTMF 1.5 | ["5"] |
| 53 | ME → USS | Start DTMF 1.6 | ["6"] |
| 54 | ME → USS | Start DTMF 1.7 | ["7"] |
| 55 | ME → USS | Start DTMF 1.8 | ["8"] |
| 56 | ME → USS | Start DTMF 1.9 | ["9"] |
| 57 | ME → USS | Start DTMF 1.10 | ["0"] |
| 58 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.5.1 | [Command performed successfully] |
| 59 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 60 | User → ME | End the call | |
| 61 | User → ME | Set up a call to "+0123456789" | |
| 62 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 63 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.5.3 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.5.3 | |
| 67 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with normal font size] |
| 68 | ME → USS | Start DTMF 1.1 | ["1"] |
| 69 | ME → USS | Start DTMF 1.2 | ["2"] |
| 70 | ME → USS | Start DTMF 1.3 | ["3"] |
| 71 | ME → USS | Start DTMF 1.4 | ["4"] |
| 72 | ME → USS | Start DTMF 1.5 | ["5"] |
| 73 | ME → USS | Start DTMF 1.6 | ["6"] |
| 74 | ME → USS | Start DTMF 1.7 | ["7"] |
| 75 | ME → USS | Start DTMF 1.8 | ["8"] |
| 76 | ME → USS | Start DTMF 1.9 | ["9"] |
| 77 | ME → USS | Start DTMF 1.10 | ["0"] |
| 78 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.5.1 | [Command performed successfully] |
| 79 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 80 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 08 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.5.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.5.3

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 33 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.5.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.5.

### 27.22.4.24.4.6 SEND DTMF (support of Text Attribute – Bold On)

#### 27.22.4.24.4.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.6.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the bold text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.6.4 Method of test

27.22.4.24.4.6.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.6.4.2 Procedure

**Expected Sequence 4.6 (SEND DTMF, with text attribute – Bold On)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.6.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.6.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with bold on] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.6.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.6.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.6.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with bold off] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.6.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |
| 41 | User → ME | Set up a call to "+0123456789" | |
| 42 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 43 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 44 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.6.1 | |

| | | | |
|---|---|---|---|
| 45 | ME → UICC | FETCH | |
| 46 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.6.1 | |
| 47 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with bold on] |
| 48 | ME → USS | Start DTMF 1.1 | ["1"] |
| 49 | ME → USS | Start DTMF 1.2 | ["2"] |
| 50 | ME → USS | Start DTMF 1.3 | ["3"] |
| 51 | ME → USS | Start DTMF 1.4 | ["4"] |
| 52 | ME → USS | Start DTMF 1.5 | ["5"] |
| 53 | ME → USS | Start DTMF 1.6 | ["6"] |
| 54 | ME → USS | Start DTMF 1.7 | ["7"] |
| 55 | ME → USS | Start DTMF 1.8 | ["8"] |
| 56 | ME → USS | Start DTMF 1.9 | ["9"] |
| 57 | ME → USS | Start DTMF 1.10 | ["0"] |
| 58 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.6.1 | [Command performed successfully] |
| 59 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 60 | User → ME | End the call | |
| 61 | User → ME | Set up a call to "+0123456789" | |
| 62 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 63 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.6.3 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.6.3 | |
| 67 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with bold off] |
| 68 | ME → USS | Start DTMF 1.1 | ["1"] |
| 69 | ME → USS | Start DTMF 1.2 | ["2"] |
| 70 | ME → USS | Start DTMF 1.3 | ["3"] |
| 71 | ME → USS | Start DTMF 1.4 | ["4"] |
| 72 | ME → USS | Start DTMF 1.5 | ["5"] |
| 73 | ME → USS | Start DTMF 1.6 | ["6"] |
| 74 | ME → USS | Start DTMF 1.7 | ["7"] |
| 75 | ME → USS | Start DTMF 1.8 | ["8"] |
| 76 | ME → USS | Start DTMF 1.9 | ["9"] |
| 77 | ME → USS | Start DTMF 1.10 | ["0"] |
| 78 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.6.1 | [Command performed successfully] |
| 79 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 80 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 10 |
| | B4 | 00 | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.6.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.6.3

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 33 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.6.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.6.

### 27.22.4.24.4.7 SEND DTMF (support of Text Attribute – Italic On)

#### 27.22.4.24.4.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.7.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.7.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the italic text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.7.4 Method of test

27.22.4.24.4.7.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.7.4.2 Procedure

**Expected Sequence 4.7 (SEND DTMF, with text attribute – Italic On)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.7.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.7.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with italic on] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.7.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.7.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.7.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with italic off] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.7.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |
| 41 | User → ME | Set up a call to "+0123456789" | |
| 42 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 43 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 44 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.7.1 | |

| | | | |
|---|---|---|---|
| 45 | ME → UICC | FETCH | |
| 46 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.7.1 | |
| 47 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with italic on] |
| 48 | ME → USS | Start DTMF 1.1 | ["1"] |
| 49 | ME → USS | Start DTMF 1.2 | ["2"] |
| 50 | ME → USS | Start DTMF 1.3 | ["3"] |
| 51 | ME → USS | Start DTMF 1.4 | ["4"] |
| 52 | ME → USS | Start DTMF 1.5 | ["5"] |
| 53 | ME → USS | Start DTMF 1.6 | ["6"] |
| 54 | ME → USS | Start DTMF 1.7 | ["7"] |
| 55 | ME → USS | Start DTMF 1.8 | ["8"] |
| 56 | ME → USS | Start DTMF 1.9 | ["9"] |
| 57 | ME → USS | Start DTMF 1.10 | ["0"] |
| 58 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.7.1 | [Command performed successfully] |
| 59 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 60 | User → ME | End the call | |
| 61 | User → ME | Set up a call to "+0123456789" | |
| 62 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 63 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.7.3 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.7.3 | |
| 67 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with italic off] |
| 68 | ME → USS | Start DTMF 1.1 | ["1"] |
| 69 | ME → USS | Start DTMF 1.2 | ["2"] |
| 70 | ME → USS | Start DTMF 1.3 | ["3"] |
| 71 | ME → USS | Start DTMF 1.4 | ["4"] |
| 72 | ME → USS | Start DTMF 1.5 | ["5"] |
| 73 | ME → USS | Start DTMF 1.6 | ["6"] |
| 74 | ME → USS | Start DTMF 1.7 | ["7"] |
| 75 | ME → USS | Start DTMF 1.8 | ["8"] |
| 76 | ME → USS | Start DTMF 1.9 | ["9"] |
| 77 | ME → USS | Start DTMF 1.10 | ["0"] |
| 78 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.7.1 | [Command performed successfully] |
| 79 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 80 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 20 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.7.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"
Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.7.3

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 33 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.7.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.7.

### 27.22.4.24.4.8 SEND DTMF (support of Text Attribute – Underline On)

#### 27.22.4.24.4.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.8.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.8.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the underline text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.8.4 Method of test

27.22.4.24.4.8.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.8.4.2 Procedure

**Expected Sequence 4.8 (SEND DTMF, with text attribute – Underline On)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.8.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.8.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with underline on] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.8.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.8.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.8.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with underline off] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.8.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |
| 41 | User → ME | Set up a call to "+0123456789" | |
| 42 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 43 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 44 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.8.1 | |

| | | | |
|---|---|---|---|
| 45 | ME → UICC | FETCH | |
| 46 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.8.1 | |
| 47 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with underline on] |
| 48 | ME → USS | Start DTMF 1.1 | ["1"] |
| 49 | ME → USS | Start DTMF 1.2 | ["2"] |
| 50 | ME → USS | Start DTMF 1.3 | ["3"] |
| 51 | ME → USS | Start DTMF 1.4 | ["4"] |
| 52 | ME → USS | Start DTMF 1.5 | ["5"] |
| 53 | ME → USS | Start DTMF 1.6 | ["6"] |
| 54 | ME → USS | Start DTMF 1.7 | ["7"] |
| 55 | ME → USS | Start DTMF 1.8 | ["8"] |
| 56 | ME → USS | Start DTMF 1.9 | ["9"] |
| 57 | ME → USS | Start DTMF 1.10 | ["0"] |
| 58 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.8.1 | [Command performed successfully] |
| 59 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 60 | User → ME | End the call | |
| 61 | User → ME | Set up a call to "+0123456789" | |
| 62 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 63 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.8.3 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.8.3 | |
| 67 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with underline off] |
| 68 | ME → USS | Start DTMF 1.1 | ["1"] |
| 69 | ME → USS | Start DTMF 1.2 | ["2"] |
| 70 | ME → USS | Start DTMF 1.3 | ["3"] |
| 71 | ME → USS | Start DTMF 1.4 | ["4"] |
| 72 | ME → USS | Start DTMF 1.5 | ["5"] |
| 73 | ME → USS | Start DTMF 1.6 | ["6"] |
| 74 | ME → USS | Start DTMF 1.7 | ["7"] |
| 75 | ME → USS | Start DTMF 1.8 | ["8"] |
| 76 | ME → USS | Start DTMF 1.9 | ["9"] |
| 77 | ME → USS | Start DTMF 1.10 | ["0"] |
| 78 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.8.1 | [Command performed successfully] |
| 79 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 80 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 40 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.8.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"
Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.8.3

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 33 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.8.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.8.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.8.

### 27.22.4.24.4.9 SEND DTMF (support of Text Attribute – Strikethrough On)

#### 27.22.4.24.4.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.9.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.9.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the strikethrough text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

#### 27.22.4.24.4.9.4 Method of test

##### 27.22.4.24.4.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.4.24.4.9.4.2 Procedure

**Expected Sequence 4.9 (SEND DTMF, with text attribute – Strikethrough On)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.9.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.9.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with strikethrough on] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.9.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.9.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.9.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with strikethrough off] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.9.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |
| 41 | User → ME | Set up a call to "+0123456789" | |
| 42 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 43 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 44 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.9.1 | |

| | | | |
|---|---|---|---|
| 45 | ME → UICC | FETCH | |
| 46 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.9.1 | |
| 47 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with strikethrough on] |
| 48 | ME → USS | Start DTMF 1.1 | ["1"] |
| 49 | ME → USS | Start DTMF 1.2 | ["2"] |
| 50 | ME → USS | Start DTMF 1.3 | ["3"] |
| 51 | ME → USS | Start DTMF 1.4 | ["4"] |
| 52 | ME → USS | Start DTMF 1.5 | ["5"] |
| 53 | ME → USS | Start DTMF 1.6 | ["6"] |
| 54 | ME → USS | Start DTMF 1.7 | ["7"] |
| 55 | ME → USS | Start DTMF 1.8 | ["8"] |
| 56 | ME → USS | Start DTMF 1.9 | ["9"] |
| 57 | ME → USS | Start DTMF 1.10 | ["0"] |
| 58 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.9.1 | [Command performed successfully] |
| 59 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 60 | User → ME | End the call | |
| 61 | User → ME | Set up a call to "+0123456789" | |
| 62 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 63 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 64 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.9.3 | |
| 65 | ME → UICC | FETCH | |
| 66 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.9.3 | |
| 67 | ME → USER | Display "Send DTMF"<br>Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with strikethrough off] |
| 68 | ME → USS | Start DTMF 1.1 | ["1"] |
| 69 | ME → USS | Start DTMF 1.2 | ["2"] |
| 70 | ME → USS | Start DTMF 1.3 | ["3"] |
| 71 | ME → USS | Start DTMF 1.4 | ["4"] |
| 72 | ME → USS | Start DTMF 1.5 | ["5"] |
| 73 | ME → USS | Start DTMF 1.6 | ["6"] |
| 74 | ME → USS | Start DTMF 1.7 | ["7"] |
| 75 | ME → USS | Start DTMF 1.8 | ["8"] |
| 76 | ME → USS | Start DTMF 1.9 | ["9"] |
| 77 | ME → USS | Start DTMF 1.10 | ["0"] |
| 78 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.9.1 | [Command performed successfully] |
| 79 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 80 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.9.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "Send DTMF 1"

DTMF String: "1234567890"

Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 80B |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.9.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"
Text Attribute

Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.9.3

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 3"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 33 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.9.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.9.

### 27.22.4.24.4.10 SEND DTMF (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.24.4.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.4.10.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2, clause 8.44 and clause 8.70.

#### 27.22.4.24.4.10.3 Test purpose

To verify that after a call has been successfully established the ME sends the DTMF string contained in the SEND DTMF proactive UICC command to the network, and returns a successful response in the TERMINAL RESPONSE command sent to the UICC.

To verify that the ME does not locally generate audible DTMF tones and play them to the user.

To verify that if the ME is in idle mode it informs the UICC using TERMINAL RESPONSE '20' with the additional information "Not in speech call".

To verify that the ME displays the text contained in the SEND DTMF proactive UICC command.

To verify that the ME displays the alpha identifier according to the foreground and background colour text attribute configuration which are referred to in the contents of the SEND DTMF proactive UICC command.

27.22.4.24.4.10.4 Method of test

27.22.4.24.4.10.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on, performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

27.22.4.24.4.10.4.2 Procedure

**Expected Sequence 4.10 (SEND DTMF, with text attribute – Foreground and Background Colour)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.10.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.10.1 | |
| 7 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with foreground and background colour according to the text attribute configuration] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME → USS | Start DTMF 1.2 | ["2"] |
| 10 | ME → USS | Start DTMF 1.3 | ["3"] |
| 11 | ME → USS | Start DTMF 1.4 | ["4"] |
| 12 | ME → USS | Start DTMF 1.5 | ["5"] |
| 13 | ME → USS | Start DTMF 1.6 | ["6"] |
| 14 | ME → USS | Start DTMF 1.7 | ["7"] |
| 15 | ME → USS | Start DTMF 1.8 | ["8"] |
| 16 | ME → USS | Start DTMF 1.9 | ["9"] |
| 17 | ME → USS | Start DTMF 1.10 | ["0"] |
| 18 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.10.1 | [Command performed successfully] |
| 19 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 20 | User → ME | End the call | |
| 21 | User → ME | Set up a call to "+0123456789" | |
| 22 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 23 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 4.10.2 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 4.10.2 | |
| 27 | ME → USER | Display "Send DTMF" Do not locally generate audible DTMF tones and play them to the user. | [Alpha identifier is displayed with ME"s default foreground and background colour] |
| 28 | ME → USS | Start DTMF 1.1 | ["1"] |
| 29 | ME → USS | Start DTMF 1.2 | ["2"] |
| 30 | ME → USS | Start DTMF 1.3 | ["3"] |
| 31 | ME → USS | Start DTMF 1.4 | ["4"] |
| 32 | ME → USS | Start DTMF 1.5 | ["5"] |
| 33 | ME → USS | Start DTMF 1.6 | ["6"] |
| 34 | ME → USS | Start DTMF 1.7 | ["7"] |
| 35 | ME → USS | Start DTMF 1.8 | ["8"] |
| 36 | ME → USS | Start DTMF 1.9 | ["9"] |
| 37 | ME → USS | Start DTMF 1.10 | ["0"] |
| 38 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 4.10.1 | [Command performed successfully] |
| 39 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 40 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 4.10.1

Logically:

Command details

Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 1"
DTMF String: "1234567890"
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 23 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 31 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | D0 | 04 | 00 | 0B | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: SEND DTMF 4.10.2

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "Send DTMF 2"
DTMF String: "1234567890"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 54 | 4D | 46 | 20 | 32 |
| | AC | 05 | 21 | 43 | 65 | 87 | 09 | | | | | |

TERMINAL RESPONSE: SEND DTMF 4.10.1

Logically:

Command details
Command number: 1
Command type: SEND DTMF
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.4.10.5 Test requirement

The ME shall operate in the manner defined in expected sequence 4.10.

### 27.22.4.24.5 SEND DTMF (UCS2 Display in Chinese)

#### 27.22.4.24.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.5.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters , as defined in:

- ISO/IEC 10646. [17].

#### 27.22.4.24.5.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.24.5.4 Method of test

##### 27.22.4.24.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.24.5.4.2 Procedure

**Expected Sequence 5.1 (SEND DTMF, successful, UCS2 text in Chinese)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 5.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 5.1.1 | |
| 7 | ME → USER | Display "你好" | ["Hello" in Chinese] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 5.1.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Text: "你好"
- DTMF String: "1" pause "2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 14 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 05 | 80 | 4F | 60 | 59 | 7D | AC | 02 | C1 | F2 | | |

TERMINAL RESPONSE: SEND DTMF 5.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successful

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.5.5 Test requirement

The ME shall operate in the manner defined in expected sequence 5.1.

### 27.22.4.24.6 SEND DTMF (UCS2 Display in Katakana)

#### 27.22.4.24.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.24.6.2 Conformance requirement

The ME shall support the Proactive UICC: Send DTMF facility as defined in:

- TS 31.111 [15] clause 6.1, clause 6.4.24, clause 6.6.24, clause 8.12.2, clause 5.2, clause 8.6, clause 8.7, clause 8.2 and clause 8.44.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters , as defined in:

- ISO/IEC 10646. [17].

#### 27.22.4.24.6.3 Test purpose

To verify that the ME displays the UCS2 text contained in the SEND DTMF proactive UICC command, and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.24.6.4 Method of test

##### 27.22.4.24.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table. The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.24.6.4.2 Procedure

**Expected Sequence 6.1 (SEND DTMF, successful, UCS2 text)**

Some details of the DTMF protocol have been left out for clarity.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+0123456789" | |
| 2 | ME → USS | The ME attempts to set up a call to "+0123456789" | |
| 3 | USS → ME | The ME receives the CONNECT message from the USS. | |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DTMF 6.1.1 | |
| 5 | ME → UICC | FETCH | |
| 6 | UICC → ME | PROACTIVE COMMAND: SEND DTMF 6.1.1 | |
| 7 | ME → USER | Display "ル" | [Character in Katakana] |
| 8 | ME → USS | Start DTMF 1.1 | ["1"] |
| 9 | ME | | No DTMF sending for 3 seconds ±20% |
| 10 | ME → USS | Start DTMF 1.2 | ["2"] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DTMF 6.1.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 13 | User → ME | End the call | |

PROACTIVE COMMAND: SEND DTMF 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: Network

Alpha Identifier
- Text: "ル"
- DTMF String: "1" pause "2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 12 | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 03 | 80 | 30 | EB | AC | 02 | C1 | F2 | | | | |

TERMINAL RESPONSE: SEND DTMF 6.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DTMF
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successful

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 14 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.24.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 6.1.

## 27.22.4.25 LANGUAGE NOTIFICATION

### 27.22.4.25.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.25.2 Conformance Requirement

The ME shall conclude the command by sending TERMINAL RESPONSE (OK) to the UICC, as soon as possible after receiving the LANGUAGE NOTIFICATION proactive UICC command.

- TS 31.111 [15] clause 6.4.25 and clause 6.6.25.

#### 27.22.4.25.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (OK) to the UICC after the ME receives the LANGUAGE NOTIFICATION proactive UICC command.

#### 27.22.4.25.4 Method of Test

##### 27.22.4.25.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

##### 27.22.4.25.4.2 Procedure

**Expected Sequence 1.1 (LANGUAGE NOTIFICATION)**

See ETSI TS 102 384 [26] in subclause 27.22.4.25.4.2, Expected Sequence 1.1.

**Expected Sequence 1.2 (LANGUAGE NOTIFICATION)**

See ETSI TS 102 384 [26] in subclause 27.22.4.25.4.2, Expected Sequence 1.2.

#### 27.22.4.25.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 and 1.2.

### 27.22.4.26 LAUNCH BROWSER

#### 27.22.4.26.1 LAUNCH BROWSER (No session already launched)

##### 27.22.4.26.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.26.1.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15 and clause 8.31.

##### 27.22.4.26.1.3 Test purpose

To verify that when the ME is in idle state, it launches properly the browser session required in LAUNCH BROWSER, and returns a successful result in the TERMINAL RESPONSE command.

##### 27.22.4.26.1.4 Method of test

###### 27.22.4.26.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is in idle mode.

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.26.1.4.2 Procedure

**Expected Sequence 1.1 (LAUNCH BROWSER, connect to the default URL)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 1.1.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id.] |
| 4 | ME → USER | ME displays the alpha identifier | |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 1.1.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default browser parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default browser session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 1.1.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities

Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 18 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0B | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | | | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 1.1.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.2 (LAUNCH BROWSER, connect to the specified URL, alpha identifier length=0)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 1.2.1 | [connect to defined URL, "launch browser, if not already launched, alpha identifier length=0] |
| 4 | ME → USER | No information should be displayed. | |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 1.2.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to connect the URL specified in the LAUNCH BROWSER command. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the URL is properly connected. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 1.2.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: http://xxx.yyy.zzz (note: this URL shall be different from the default URL, but it can be reached from the gateway defined by default in the browser parameters of the mobile)

Alpha Identifier: empty

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1F | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 12 | 68 | 74 | 74 | 70 | 3A | 2F | 2F | 78 | 78 | 78 | 2E |
| | 79 | 79 | 79 | 2E | 7A | 7A | 7A | 05 | 00 | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 1.2.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.3 (LAUNCH BROWSER, Browser identity, no alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 1.3.1 | [connect to the default URL, "launch browser, if not already launched, browser identity] |
| 4 | ME → USER | ME may display a default message of its own. | |
| 5 | USER → ME | The user may confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 1.3.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default browser session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 1.3.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- Browser Identity default
- URL empty

Coding::

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0E | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 30 |
| | 01 | 00 | 31 | 00 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 1.3.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.4 (LAUNCH BROWSER, only GPRS bearer specified and gateway/proxy identity, GPRS supported by USS)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode], GPRS supported by USS, GPRS supported by the ME and activated] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 1.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 1.4.1 | [connect to the default URL, "launch browser, if not already launched, 1 bearer specified, gateway/proxy id specified] |
| 4 | ME → USER | ME may display a default message | |
| 5 | USER → ME | The user may confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 1.4.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to connect the default URL using the requested bearer and proxy identity | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the browser session is properly established with the required bearer. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 1.4.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty
- Bearer: GPRS

Gateway/Proxy id
- DCSunpacked, 8 bits data
- Text string: abc.def.ghi (different from the default IP address)

Coding::

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 32 | 01 | 03 | 0D | 0C | 04 | 61 | 62 | 63 | 2E | 64 |
| | 65 | 66 | 2E | 67 | 68 | 69 | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 1.4.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

Expected Sequence 1.5 Void

#### 27.22.4.26.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.4

### 27.22.4.26.2 LAUNCH BROWSER (Interaction with current session)

#### 27.22.4.26.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.2.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 82.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

#### 27.22.4.26.2.3 Test purpose

To verify that when the ME is already busy in a browser session, it launches properly the browser session required in LAUNCH BROWSER, and returns a successful result in the TERMINAL RESPONSE.

#### 27.22.4.26.2.4 Method of test

##### 27.22.4.26.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to a Wap gateway is required. The default browser parameters (IP address, gateway/proxy identity, called number…) of the tested mobile shall be properly filled to access that gateway.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in browser parameters.

27.22.4.26.2.4.2 Procedure

**Expected Sequence 2.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | The user is navigating in a browser session (not default URL). | [Browser is in use, the current session is not secured] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 2.1.1 | [connect to the default URL, "use the existing browser", no null alpha id.] |
| 4 | ME → USER | ME displays the alpha identifier | |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 2.1.1 | [Command performed successfully] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

PROACTIVE COMMAND: LAUNCH BROWSER 2.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Default URL"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 18 | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0B | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | | | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 2.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 2.2 (LAUNCH BROWSER, close the existing browser session and launch new browser session, connect to the default URL)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | The user is navigating in a browser session (not default URL).. | [Browser is in use, the current session is not secured] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 2.2.1 | [connect to the default URL, "close the existing browser session and launch new browser session", no null alpha id.] |
| 4 | ME → USER | ME displays the alpha identifier | |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 2.2.1 | [Command performed successfully] |
| 7 | ME→USS | The ME closes the existing session and attempts to launch the session with the default browser parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL cannot be retrieved (to verify the previous session has been closed). Then he/she does not end the navigation. | |

PROACTIVE COMMAND: LAUNCH BROWSER 2.2.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: close the existing browser session and launch new browser sessionDevice identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Default URL"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 18 | 81 | 03 | 01 | 15 | 03 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0B | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | | | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 2.2.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: close the existing browser session and launch new browser session
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 03 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 2.3 (LAUNCH BROWSER, if not already launched)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | The user is navigating in a browser session (not default URL).. | [Browser is in use, the current session is not secured] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 2.3.1 | [connect to the default URL, "launch browser, if not already launched] |
| 4 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 2.3.1 | [ME unable to process command - browser unavailable] |
| 5 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 6 | USER → ME | The user verifies that the default URL has not been connected. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 2.3.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0B | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | | | | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 2.3.1

Logically:

Command details

Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Launch browser generic error code
Additional data Browser unavailable

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 26 |
| | 02 | | | | | | | | | | | |

27.22.4.26.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.3.

## 27.22.4.26.3 LAUNCH BROWSER (UCS2 display in Cyrillic)

### 27.22.4.26.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.26.3.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Cyrillic alphabet, as defined in:

- ISO/IEC 10646 [17].

### 27.22.4.26.3.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

### 27.22.4.26.3.4 Method of test

#### 27.22.4.26.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in Wap parameters.

27.22.4.26.3.4.2 Procedure

**Expected Sequence 3.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Cyrillic)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | The user is navigating in a browser session (not default URL).. | [Browser is in use, the current session is not secured]] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 3.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 3.1.1 | [connect to the default URL, "use the existing browser", alpha id. In UCS2] |
| 4 | ME → USER | ME displays the alpha identifier "ЗДРАВСТВУЙТЕ" | ["Hello" in Russian] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 3.1.1 | [Command performed successfully] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

PROACTIVE COMMAND: LAUNCH BROWSER 3.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier
- Data coding scheme: UCS2 (16 bits)
- Text: "ЗДРАВСТВУЙТЕ"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 19 | 80 | 04 | 17 | 04 | 14 | 04 | 20 | 04 | 10 |
| | 04 | 12 | 04 | 21 | 04 | 22 | 04 | 12 | 04 | 23 | 04 | 19 |
| | 04 | 22 | 04 | 15 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 3.1.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: use the existing browser
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequence 3.1.

### 27.22.4.26.4 LAUNCH BROWSER (icons support)

#### 27.22.4.26.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.4.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

#### 27.22.4.26.4.3 Test purpose

To verify that the ME performs a proper user confirmation with an icon identifier, launches the browser session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.4.4 Method of test

##### 27.22.4.26.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default browser parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default browser parameters.

The mobile is busy in a browser session, the user navigates in pages different from the URL defined by default in browser parameters.

27.22.4.26.4.4.2 Procedure

**Expected Sequence 4.1A (LAUNCH BROWSER, use the existing browser, icon not self explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.1.1 | [Browser is in use, the current session is not secured]] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1 | [connect to the default URL, "use the existing browser", no null alpha id.] |
| 4 | ME → USER | ME displays the alpha identifier and the icon | ["Not self explan."] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 A | [Command performed successfully] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Not self explan."

Icon identifier:
- Icon qualifier: not self-explanatory
- Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 21 | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 10 | 4E | 6F | 74 | 20 | 73 | 65 | 6C | 66 | 20 |
| | 65 | 78 | 70 | 6C | 61 | 6E | 2E | 1E | 02 | 01 | 01 | |

TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 A

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 4.1B (LAUNCH BROWSER, use the existing browser, icon not self explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.1.1 | [Browser is in use, the current session is not secured]] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 4.1.1 | [connect to the default URL, "use the existing browser", no null alpha id.] |
| 4 | ME → USER | ME displays the alpha identifier Without the icon | ["Not self explan."] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 B | [Command performed successfully but requested icon could not be displayed] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

TERMINAL RESPONSE: LAUNCH BROWSER 4.1.1 B

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: use the existing browser
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

**Expected Sequence 4.2A (LAUNCH BROWSER, use the existing browser, icon self explanatory, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.2.1 | [Browser is in use, the current session is not secured]] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1 | [connect to the default URL, "use the existing browser", alpha id. In UCS2] |
| 4 | ME → USER | ME displays only the icon | ["Self explan."] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 A | [Command performed successfully] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier: "Self explan."

Icon identifier:
- Icon qualifier: self-explanatory
- Icon identifier: record 1 in $EF_{(IMG)}$

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1D | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0C | 53 | 65 | 6C | 66 | 20 | 65 | 78 | 70 | 6C |
| | 61 | 6E | 2E | 1E | 02 | 00 | 01 | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 A

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 4.2B (LAUNCH BROWSER, use the existing browser, icon self explanatory, requested icon could not be displayed)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 4.2.1 | [Browser is in use, the current session is not secured]] |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 4.2.1 | [connect to the default URL, "use the existing browser", alpha id. In UCS2] |
| 4 | ME → USER | ME displays only the alpha identifier | ["Self explan."] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 B | [Command performed successfully]<br>[Command performed successfully but requested icon could not be displayed] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

TERMINAL RESPONSE: LAUNCH BROWSER 4.2.1 B

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully but requested icon could not be displayed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 04 |

27.22.4.26.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 4.1A to 4.2B.

### 27.22.4.26.5 LAUNCH BROWSER (support of Text Attribute)

#### 27.22.4.26.5.1 LAUNCH BROWSER (support of Text Attribute – Left Alignment)

##### 27.22.4.26.5.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.26.5.1.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111[15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

##### 27.22.4.26.5.1.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the left alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

##### 27.22.4.26.5.1.4 Method of test

###### 27.22.4.26.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.1.4.2 Procedure

**Expected Sequence 5.1 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.1.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with left alignment] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.1.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.1.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/18, no alignment change will take place] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Default URL 1"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.1.2

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.1.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.1.

### 27.22.4.26.5.2 LAUNCH BROWSER (support of Text Attribute – Center Alignment)

#### 27.22.4.26.5.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.2.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.2.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the center alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.2.4 Method of test

##### 27.22.4.26.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.2.4.2 Procedure

**Expected Sequence 5.2 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.2.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with center alignment] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.2.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.2.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/18, no alignment change will take place] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.2.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Default URL 1"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 01 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.2.2

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.2.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.2.

### 27.22.4.26.5.3 LAUNCH BROWSER (support of Text Attribute – Right Alignment)

#### 27.22.4.26.5.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.3.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.3.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the right alignment text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.3.4 Method of test

##### 27.22.4.26.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.3.4.2 Procedure

**Expected Sequence 5.3 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.3.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with right alignment] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.3.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.3.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/18, no alignment change will take place] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.3.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Default URL 1"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 02 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.3.2

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.3.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.3.

### 27.22.4.26.5.4 LAUNCH BROWSER (support of Text Attribute – Large Font Size)

#### 27.22.4.26.5.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.4.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.&&& [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.4.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the large font size text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.4.4 Method of test

##### 27.22.4.26.5.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.4.4.2 Procedure

**Expected Sequence 5.4 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with large font size] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.4.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with normal font size] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 22 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with large font size] |
| 23 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 24 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1 | [Command performed successfully] |
| 25 | ME USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 26 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

| | | | |
|---|---|---|---|
| 27 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.4.3 | |
| 29 | ME → UICC | FETCH | |
| 30 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.4.3 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 31 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with normal font size] |
| 32 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 33 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1 | [Command performed successfully] |
| 34 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 35 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 36 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.4.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute
- Formatting position: 0
- Formatting length: 13
- Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 04 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.4.2

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.4.3

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 33 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.4.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.4.

### 27.22.4.26.5.5 LAUNCH BROWSER (support of Text Attribute – Small Font Size)

#### 27.22.4.26.5.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.5.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.5.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the small font size text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.5.4 Method of test

##### 27.22.4.26.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.5.4.2 Procedure

**Expected Sequence 5.5 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with small font size] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.5.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with normal font size] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 22 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with small font size] |
| 23 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 24 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1 | [Command performed successfully] |
| 25 | ME USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 26 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

| | | | |
|---|---|---|---|
| 27 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.5.3 | |
| 29 | ME → UICC | FETCH | |
| 30 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.5.3 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 31 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with normal font size] |
| 32 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 33 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1 | [Command performed successfully] |
| 34 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 35 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 36 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.5.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute
- Formatting position: 0
- Formatting length: 13
- Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 08 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.5.2

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.5.3

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 33 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.5.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.5.

### 27.22.4.26.5.6 LAUNCH BROWSER (support of Text Attribute – Bold on)

#### 27.22.4.26.5.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.6.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.6.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the bold text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.6.4 Method of test

##### 27.22.4.26.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.6.4.2 Procedure

**Expected Sequence 5.6 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with bold on] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.6.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with bold off] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 22 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with bold on] |
| 23 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 24 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1 | [Command performed successfully] |
| 25 | ME USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 26 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

| | | | |
|---|---|---|---|
| 27 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.6.3 | |
| 29 | ME → UICC | FETCH | |
| 30 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.6.3 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 31 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with bold off] |
| 32 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 33 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1 | [Command performed successfully] |
| 34 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 35 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 36 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.6.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute
- Formatting position: 0
- Formatting length: 13
- Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 10 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.6.2

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.6.3

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 33 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.6.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.6.

### 27.22.4.26.5.7 LAUNCH BROWSER (support of Text Attribute – Italic On)

#### 27.22.4.26.5.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.7.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.7.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the italic text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.7.4 Method of test

##### 27.22.4.26.5.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.7.4.2 Procedure

**Expected Sequence 5.7 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with italic on] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.7.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with italic off] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 22 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with italic on] |
| 23 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 24 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1 | [Command performed successfully] |
| 25 | ME USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 26 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

| | | | |
|---|---|---|---|
| 27 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.7.3 | |
| 29 | ME → UICC | FETCH | |
| 30 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.7.3 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 31 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with italic off] |
| 32 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 33 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1 | [Command performed successfully] |
| 34 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 35 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 36 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.7.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute
- Formatting position: 0
- Formatting length: 13
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 20 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.7.2

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.7.3

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 33 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.7.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.7.

### 27.22.4.26.5.8 LAUNCH BROWSER (support of Text Attribute – Underline On)

#### 27.22.4.26.5.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.8.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.8.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the underline text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.8.4 Method of test

##### 27.22.4.26.5.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.8.4.2 Procedure

**Expected Sequence 5.8 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with underline on] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.8.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with underline off] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 22 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with underline on] |
| 23 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 24 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1 | [Command performed successfully] |
| 25 | ME USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 26 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

| | | | |
|---|---|---|---|
| 27 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.8.3 | |
| 29 | ME → UICC | FETCH | |
| 30 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.8.3 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 31 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with underline off] |
| 32 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 33 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1 | [Command performed successfully] |
| 34 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 35 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 36 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.8.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute
- Formatting position: 0
- Formatting length: 13
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 40 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.8.2

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.8.3

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 33 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.8.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.8.

### 27.22.4.26.5.9 LAUNCH BROWSER (support of Text Attribute – Strikethrough On)

#### 27.22.4.26.5.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.9.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.9.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the strikethrough text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.9.4 Method of test

##### 27.22.4.26.5.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.9.4.2 Procedure

**Expected Sequence 5.9 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with strikethrough on] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.9.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with strikethrough off] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 22 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with strikethrough on] |
| 23 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 24 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1 | [Command performed successfully] |
| 25 | ME USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 26 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

| | | | |
|---|---|---|---|
| 27 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |
| 28 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.9.3 | |
| 29 | ME → UICC | FETCH | |
| 30 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.9.3 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 31 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with strikethrough off] |
| 32 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 33 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1 | [Command performed successfully] |
| 34 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 35 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 36 | USER → ME | The user verifies that the default Wap session is properly established.<br>Then he/she ends the navigation.<br>The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.9.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL: empty

Alpha Identifier "Default URL 1"

Text Attribute
- Formatting position: 0
- Formatting length: 13
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 80 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.9.2

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER

Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"
Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.9.3

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 3"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 33 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.9.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.5.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.9.

### 27.22.4.26.5.10 LAUNCH BROWSER (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.26.5.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.5.10.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, clause 8.49, clause 8.50, clause 8.15, clause 8.31 and clause 8.70.

#### 27.22.4.26.5.10.3 Test purpose

To verify that the ME performs a proper user confirmation with an alpha identifier according to the foreground and background colour text attribute configuration, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.5.10.4 Method of test

##### 27.22.4.26.5.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway")

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The ME is in idle mode.

27.22.4.26.5.10.4.2 Procedure

**Expected Sequence 5.10 (LAUNCH BROWSER, connect to the default URL with Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | | [the ME is in idle mode] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.10.1 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 4 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with foreground and background colour according to the text attribute configuration] |
| 5 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1 | [Command performed successfully] |
| 7 | ME→USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |
| 10 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 5.10.2 | |
| 11 | ME → UICC | FETCH | |
| 12 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 5.10.2 | [connect to the default URL, "launch browser, if not already launched", no null alpha id] |
| 13 | ME → USER | ME displays the alpha identifier | [alpha identifier is displayed with ME"s default foreground and background colour] |
| 14 | USER → ME | The user may have to confirm the launch browser. | [option: user confirmation] |
| 15 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1 | [Command performed successfully] |
| 16 | ME → USS | The ME attempts to launch the session with the default Wap parameters and the default URL. | |
| 17 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 18 | USER → ME | The user verifies that the default Wap session is properly established. Then he/she ends the navigation. The ME returns in idle mode. | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.10.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: launch browser, if not already launched

Device identities
- Source device: UICC
- Destination device: ME
- URL empty

Alpha Identifier "Default URL 1"

Text Attribute
Formatting position: 0
Formatting length: 13
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 31 | D0 | 04 | 00 | 0D | 00 | B4 | | |

PROACTIVE COMMAND: LAUNCH BROWSER 5.10.2

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: UICC
Destination device: ME
URL empty
Alpha Identifier "Default URL 2"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1A | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 0D | 44 | 65 | 66 | 61 | 75 | 6C | 74 | 20 | 55 |
| | 52 | 4C | 20 | 32 | | | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 5.10.1

Logically:

Command details
Command number: 1
Command type: LAUNCH BROWSER
Command qualifier: launch browser, if not already launched
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

### 27.22.4.26.5.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.10.

### 27.22.4.26.6 LAUNCH BROWSER (UCS2 Display in Chinese)

#### 27.22.4.26.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.6.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Chinese characters, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.26.6.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.6.4 Method of test

##### 27.22.4.26.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

  With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The mobile is busy in a Wap session, the user navigates in pages different from the URL defined by default in Wap parameters.

27.22.4.26.6.4.2 Procedure

**Expected Sequence 6.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Chinese)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | The user is navigating in a Wap session (not default URL). | [Browser is in use, the current session is not secured]] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 6.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 6.1.1 | [connect to the default URL, "use the existing browser", alpha id. In UCS2] |
| 4 | ME → USER | ME displays the alpha identifier "你好" | ["Hello" in Chinese] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 6.1.1 | [Command performed successfully] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

PROACTIVE COMMAND: LAUNCH BROWSER 6.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: UICC
- Destination device: ME

URL: empty

Alpha Identifier
- Data coding scheme: UCS2 (16 bits)
- Text: "你好"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 12 | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 05 | 80 | 4F | 60 | 59 | 7D | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 6.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.6.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

### 27.22.4.26.7 LAUNCH BROWSER (UCS2 Display in Katakana)

#### 27.22.4.26.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.26.7.2 Conformance requirements

The ME shall support the LAUNCH BROWSER Proactive UICC Command as defined in:

- TS 31.111 [15] clause 5.2, clauses 6.4.26 and 6.6.26, clause 8.6, clause 8.7, clause 8.48, clause 9.2, clause 8.2, clause 8.47, optional clause 8.49, optional clause 8.50, clause 8.15 and clause 8.31.

Additionally the ME shall support the UCS2 facility for the coding of the Katakana characters, as defined in:

- ISO/IEC 10646 [17].

#### 27.22.4.26.7.3 Test purpose

To verify that the ME performs a proper user confirmation with an USC2 alpha identifier, launches the Wap session required in LAUNCH BROWSER and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.26.7.4 Method of test

##### 27.22.4.26.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

A valid access to 2 different Wap gateways is required:

- the default Wap parameters (IP address, gateway/proxy identity, called number, URL …) of the tested mobile shall be properly filled to access one of the gateways ("default gateway").

With that default gateway we shall be able to access to an URL different from the default one.

- another gateway with an IP address different from the one defined in default Wap parameters.

The mobile is busy in a Wap session, the user navigates in pages different from the URL defined by default in Wap parameters.

27.22.4.26.7.4.2 Procedure

**Expected Sequence 7.1 (LAUNCH BROWSER, use the existing browser, connect to the default URL, UCS2 in Katakana)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 0 | ME | The user is navigating in a Wap session (not default URL). | [Browser is in use, the current session is not secured]] |
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: LAUNCH BROWSER 7.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: LAUNCH BROWSER 7.1.1 | [connect to the default URL, "use the existing browser", alpha id. In UCS2] |
| 4 | ME → USER | ME displays the alpha identifier "ル" | [Character in Katakana] |
| 5 | USER → ME | The user confirms the launch browser. | [user confirmation] |
| 6 | ME → UICC | TERMINAL RESPONSE: LAUNCH BROWSER 7.1.1 | [Command performed successfully] |
| 7 | ME→USS | The ME does not close the existing session and attempts to connect the default URL. | |
| 8 | UICC → ME | PROACTIVE UICC SESSION ENDED | |
| 9 | USER → ME | The user verifies that the default URL is connected; and the previous URL can be retrieved. Then he/she ends the navigation with the default URL. | |

PROACTIVE COMMAND: LAUNCH BROWSER 7.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities
- Source device: UICC
- Destination device: ME

URL empty

Alpha Identifier
- Data coding scheme: UCS2 (16 bits)
- Text: "ル"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 10 | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 81 | 82 | 31 |
| | 00 | 05 | 03 | 80 | 30 | EB | | | | | | |

TERMINAL RESPONSE: LAUNCH BROWSER 7.1.1

Logically:

Command details
- Command number: 1
- Command type: LAUNCH BROWSER
- Command qualifier: use the existing browser

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 15 | 02 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.26.7.5 Test requirement

The ME shall operate in the manner defined in expected sequence 7.1.

## 27.22.4.27 OPEN CHANNEL

#### 27.22.4.27.1 Void

### 27.22.4.27.2 Open Channel (related to GPRS)

#### 27.22.4.27.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111[15] clause 5.2, clauses 6.4.27 and 6.6.27, clause 8.6, clause 8.7, clause 9.2, clause 8.2, clause 8.15, clause 8.31 and clause 8.70..

#### 27.22.4.27.2.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (OK); or
- TERMINAL RESPONSE (Command performed with modification); or
- TERMINAL RESPONSE (User did not accept the proactive command);
- TERMINAL RESPONSE (ME currently unable to process command);

to the UICC after the ME receives the OPEN CHANNEL proactive command. The TERMINAL RESPONSE sent back to the UICC is the result of the ME and the network capabilities against requested parameters by the UICC.

#### 27.22.4.27.2.4 Method of test

##### 27.22.4.27.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The following Bearer Parameters used are those defined in the default Test PDP ContextDch, as specified in TS 34.123-3 [27], clause 8.10 for test cases using packet services:

Bearer Parameters

| | |
|---|---|
| Precedence Class: | 03 |
| Delay Class: | 04 |
| Reliability Class: | 03 |
| Peak throughput class: | 04 |
| Mean throughput class: | 31 |
| Packet data protocol: | 02 (IP) |

GPRS Parameters

| | |
|---|---|
| Network access name: | TestGp.rs |
| User login: | UserLog |
| User password: | UserPwd |

UICC/ME interface transport level

| | |
|---|---|
| Transport format: | UDP |
| Port number: | 44444 |
| Data destination address | 01.01.01.01 |

Prior to test case execution the apparatus supplier shall have provided the "Preferred buffer size supported by the terminal for Open Channel command" as requested in table A.2/29.

Pre-condition for successful execution of expected sequence 2.1:

If the terminal does not support the execution of an Open Channel (GPRS) command when no Network Access Name TLV is present in the proactive command and when no default Access Point Name is set in the terminal configuration (s.a. table A.1/48), then "TestGp.rs" shall be set and activated as default Access Point Name in the terminal configuration prior to execution of the proactive command in expected sequence 2.1.

27.22.4.27.2.4.2 Procedure

**Expected Sequence 2.1 (OPEN CHANNEL, immediate link establishment, GPRS, no local address, no alpha identifier, no network access name)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USER → ME | Set and activate APN "TestGp.rs" in the terminal configuration if required | [see initial conditions] |
| 2 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.1.1 | |
| 3 | ME → UICC | FETCH | |
| 4 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 2.1.1 | |
| 5 | ME → user | The ME may display channel opening information | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 2.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 2.1.1

Logically:

Command details

| | |
|---|---|
| Command number: | 1 |
| Command type: | OPEN CHANNEL |
| Command qualifier: | immediate link establishment |

Device identities
Source device: UICC
Destination device: ME
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 36 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

**Expected Sequence 2.2 (OPEN CHANNEL, immediate link establishment GPRS, no alpha identifier, with network access name)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 2.2.1 | |
| 4 | ME → user | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 2.2.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 2.2.1B | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 2.2.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 |
| | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 2.2.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment
- Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated

Bearer Description:
- Bearer Type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03

Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 2.2.1B

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer Description:
Bearer Type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

**Expected Sequence 2.3 (OPEN CHANNEL, immediate link establishment, GPRS, with alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 2.3.1 | |
| 4 | ME → user | Confirmation phase with alpha ID | 'Open ID' |
| 5 | user → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 2.3.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier: Open ID

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address: 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4B | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 07 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 35 | 07 | 02 | 03 |
| | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 | 0A | 06 |
| | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 | 55 | 73 |
| | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C | 3E | 05 |
| | 21 | 01 | 01 | 01 | 01 | | | | | | | |

**Expected Sequence 2.4 (OPEN CHANNEL, immediate link establishment, GPRS, with null alpha identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 2.4.1 | |
| 4 | ME → user | Confirmation phase | [The ME should not give any information] |
| 5 | user → ME | The user confirms | [Only if the ME asks for user confirmation] |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 2.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 2.1.1B | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 2.4.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Alpha Identifier Null

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Other Address
- Length: 00

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 46 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 |
| | 05 | 78 | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 |
| | 72 | 73 | 3E | 00 | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 6F | 67 | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 |
| 3C | 03 | 01 | AD | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 |

**Expected Sequence 2.5 (OPEN CHANNEL, immediate link establishment, GPRS, command performed with modifications (buffer size) )**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 2.5.1 | |
| 4 | ME → user | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 2.5.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 2.5.1B | [Command performed with modification] |

PROACTIVE COMMAND: OPEN CHANNEL 2.5.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 65535

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | FF | FF |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 2.5.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed with modifications (07)

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 07 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | Note 1 | | | | | | | | | | |

Note1: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

TERMINAL RESPONSE: OPEN CHANNEL 2.5.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed with modifications (07)

Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 07 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | Note 1 | | | | | | | | | | |

Note1: The buffer size TLV shall be attached and contain the value stated in table A.2/29 "Preferred buffer size supported by the terminal for Open Channel command".

### Expected Sequence 2.6 Void

### Expected Sequence 2.7A (OPEN CHANNEL, immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command)

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 2.7.1 | |
| 4 | ME → user | Confirmation phase with alpha ID | [The ME shall display 'Open ID'] |
| 5 | user → ME | The user rejects | |
| 6 | ME → USS | No PDP context activation request is sent to the USS | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 2.7.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 2.7.1B | [User did not accept the proactive command] |

**Expected Sequence 2.7B (OPEN CHANNEL, immediate link establishment, GPRS, open command with alpha identifier, User did not accept the proactive command)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 2.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 2.7.1 | |
| 4 | ME → USS | PDP context activation request | |
| 5 | USS → ME | PDP context activation accept | |
| 6 | ME → user | Confirmation phase with alpha ID | [The ME shall display 'Open ID'] |
| 7 | user → ME | The user rejects | |
| 8 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 2.7.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 2.7.1B | [User did not accept the proactive command] |

PROACTIVE COMMAND: OPEN CHANNEL 2.7.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4B | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 07 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 35 | 07 | 02 | 03 |
| | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 | 0A | 06 |
| | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D | 08 | F4 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 | 55 | 73 |
| 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C | 3E | 05 |
| 21 | 01 | 01 | 01 | 01 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 2.7.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: User did not accept the proactive command

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: Because the value depends in this case on the terminal's implementation, it shall be ignored.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 22 |
| | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | Note 1 | | |

Note1: The buffer size TLV shall be present and because the value depends in this case on the terminal's implementation, the value shall be ignored.

TERMINAL RESPONSE: OPEN CHANNEL 2.7.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: User did not accept the proactive command

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04

Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer

Buffer size: Because the value depends in this case on the terminal's implementation, it shall be ignored.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 22 |
| | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F | 02 | Note 1 | | |

Note1: The buffer size TLV shall be present and because the value depends in this case on the terminal's implementation, the value shall be ignored.

**Expected Sequence 2.8 Void**

27.22.4.27.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.8.

## 27.22.4.27.3 Open Channel (default bearer)

TBD

## 27.22.4.27.4 Open Channel (Local Bearer)

TBD

## 27.22.4.27.5 Open Channel (GPRS, support of Text Attribute)

### 27.22.4.27.5.1 Open Channel (GPRS, support of Text Attribute – Left Alignment)

#### 27.22.4.27.5.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.27.5.1.3 Test purpose

To verify that the ME displays an alpha identifier according to the left alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.1.4 Method of test

##### 27.22.4.27.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

| | |
|---|---|
| Precedence Class: | 03 |
| Delay Class: | 04 |
| Reliability Class: | 03 |
| Peak throughput class: | 04 |
| Mean throughput class: | 31 |
| Packet data protocol: | 02 (IP) |

GPRS Parameters

| | |
|---|---|
| Network access name: | TestGp.rs |
| User login: | UserLog |
| User password: | UserPwd |

UICC/ME interface transport level

| | |
|---|---|
| Transport format: | UDP |
| Port number: | 44444 |
| Data destination address | 01.01.01.01 |

27.22.4.27.5.1.4.2 Procedure

**Expected Sequence 5.1 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.1.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with left alignment] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.1.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.1.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.1.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities

Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 1"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.1.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03

Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel
Alpha Identifier "Close ID"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 14 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 08 | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | |

TERMINAL RESPONSE: OPEN CHANNEL 5.1.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME

Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.1.1B

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 5.1.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.27.5.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.1.

### 27.22.4.27.5.2 Open Channel (GPRS, support of Text Attribute – Center Alignment)

#### 27.22.4.27.5.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.27.5.2.3 Test purpose

To verify that the ME displays an alpha identifier according to the center alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.2.4 Method of test

##### 27.22.4.27.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.2.4.2 Procedure

**Expected Sequence 5.2 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.2.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.2.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with center alignment] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.2.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.2.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.2.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.2.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.2.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.2.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.2.1

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 1"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 01 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.2.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities

Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.2.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.2.1B

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

### 27.22.4.27.5.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.2.

### 27.22.4.27.5.3 Open Channel (GPRS, support of Text Attribute – Right Alignment)

#### 27.22.4.27.5.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.27.5.3.3 Test purpose

To verify that the ME displays an alpha identifier according to the right alignment text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.3.4 Method of test

##### 27.22.4.27.5.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

| | |
|---|---|
| Precedence Class: | 03 |
| Delay Class: | 04 |
| Reliability Class: | 03 |
| Peak throughput class: | 04 |
| Mean throughput class: | 31 |
| Packet data protocol: | 02 (IP) |

GPRS Parameters

| | |
|---|---|
| Network access name: | TestGp.rs |
| User login: | UserLog |
| User password: | UserPwd |

UICC/ME interface transport level

| | |
|---|---|
| Transport format: | UDP |
| Port number: | 44444 |
| Data destination address | 01.01.01.01 |

27.22.4.27.5.3.4.2 Procedure

**Expected Sequence 5.3 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.3.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.3.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with right alignment] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.3.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.3.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.3.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.3.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/19, no alignment change will take place] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.3.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.3.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.3.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities

Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 1"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 02 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.3.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03

Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.3.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.3.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

### 27.22.4.27.5.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.3.

## 27.22.4.27.5.4 Open Channel (GPRS, support of Text Attribute – Large Font Size)

### 27.22.4.27.5.4.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.27.5.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

### 27.22.4.27.5.4.3 Test purpose

To verify that the ME displays an alpha identifier according to the large font size text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.4.4 Method of test

27.22.4.27.5.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

| | |
|---|---|
| Precedence Class: | 03 |
| Delay Class: | 04 |
| Reliability Class: | 03 |
| Peak throughput class: | 04 |
| Mean throughput class: | 31 |
| Packet data protocol: | 02 (IP) |

GPRS Parameters

| | |
|---|---|
| Network access name: | TestGp.rs |
| User login: | UserLog |
| User password: | UserPwd |

UICC/ME interface transport level

| | |
|---|---|
| Transport format: | UDP |
| Port number: | 44444 |
| Data destination address | 01.01.01.01 |

27.22.4.27.5.4.4.2 Procedure

**Expected Sequence 5.4 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.4.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.4.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with large font size] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.4.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.4.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with normal font size] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.4.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.4.1 | |
| 32 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with large font size] |
| 33 | USER → ME | The user confirms | |
| 34 | ME → USS | PDP context activation request | |
| 35 | USS → ME | PDP context activation accept | |
| 36 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 40 | ME → USS | PDP context deactivation request | |
| 41 | USS → ME | PDP context deactivation accept | |
| 42 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.4.3 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.4.3 | |
| 46 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with normal font size] |
| 47 | USER → ME | The user confirms | |
| 48 | ME → USS | PDP context activation request | |
| 49 | USS → ME | PDP context activation accept | |
| 50 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.4.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.4.1B | [Command performed successfully] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 54 | ME → USS | PDP context deactivation request | |
| 55 | USS → ME | PDP context deactivation accept | |
| 56 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.4.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 1"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 04 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.4.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.4.3

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 3"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 33 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.4.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.4.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

27.22.4.27.5.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.4.

27.22.4.27.5.5 Open Channel (GPRS, support of Text Attribute – Small Font Size)

27.22.4.27.5.5.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.5.3 Test purpose

To verify that the ME displays an alpha identifier according to the small font size text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.5.4 Method of test

27.22.4.27.5.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.5.4.2 Procedure

**Expected Sequence 5.5 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.5.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.5.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with small font size] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.5.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.5.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with normal font size] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.5.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.5.1 | |
| 32 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with small font size] |
| 33 | USER → ME | The user confirms | |
| 34 | ME → USS | PDP context activation request | |
| 35 | USS → ME | PDP context activation accept | |
| 36 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 40 | ME → USS | PDP context deactivation request | |
| 41 | USS → ME | PDP context deactivation accept | |
| 42 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.5.3 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.5.3 | |
| 46 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with normal font size] |
| 47 | USER → ME | The user confirms | |
| 48 | ME → USS | PDP context activation request | |
| 49 | USS → ME | PDP context activation accept | |
| 50 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.5.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.5.1B | [Command performed successfully] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 54 | ME → USS | PDP context deactivation request | |
| 55 | USS → ME | PDP context deactivation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.5.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 1"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 08 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.5.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.5.3

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 3"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 33 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.5.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.5.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

27.22.4.27.5.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.5.

27.22.4.27.5.6 Open Channel (GPRS, support of Text Attribute – Bold On)

27.22.4.27.5.6.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.6.3 Test purpose

To verify that the ME displays an alpha identifier according to the bold text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.6.4 Method of test

27.22.4.27.5.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.6.4.2 Procedure

**Expected Sequence 5.6 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.6.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.6.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with bold on] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.6.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.6.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with bold off] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.6.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.6.1 | |
| 32 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with bold on] |
| 33 | USER → ME | The user confirms | |
| 34 | ME → USS | PDP context activation request | |
| 35 | USS → ME | PDP context activation accept | |
| 36 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 40 | ME → USS | PDP context deactivation request | |
| 41 | USS → ME | PDP context deactivation accept | |
| 42 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.6.3 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.6.3 | |
| 46 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with bold off] |
| 47 | USER → ME | The user confirms | |
| 48 | ME → USS | PDP context activation request | |
| 49 | USS → ME | PDP context activation accept | |
| 50 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.6.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.6.1B | [Command performed successfully] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 54 | ME → USS | PDP context deactivation request | |
| 55 | USS → ME | PDP context deactivation accept | |
| 56 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.6.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 1"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 10 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.6.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.6.3

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 3"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 33 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.6.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.6.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

27.22.4.27.5.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.6.

27.22.4.27.5.7 Open Channel (GPRS, support of Text Attribute – Italic On)

27.22.4.27.5.7.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.7.3 Test purpose

To verify that the ME displays an alpha identifier according to the italic text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.7.4 Method of test

27.22.4.27.5.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.7.4.2 Procedure

**Expected Sequence 5.7 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.7.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.7.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with italic on] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.7.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.7.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with italic off] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.7.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.7.1 | |
| 32 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with italic on] |
| 33 | USER → ME | The user confirms | |
| 34 | ME → USS | PDP context activation request | |
| 35 | USS → ME | PDP context activation accept | |
| 36 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 40 | ME → USS | PDP context deactivation request | |
| 41 | USS → ME | PDP context deactivation accept | |
| 42 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.7.3 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.7.3 | |
| 46 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with italic off] |
| 47 | USER → ME | The user confirms | |
| 48 | ME → USS | PDP context activation request | |
| 49 | USS → ME | PDP context activation accept | |
| 50 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.7.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.7.1B | [Command performed successfully] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 54 | ME → USS | PDP context deactivation request | |
| 55 | USS → ME | PDP context deactivation accept | |
| 56 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.7.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 1"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 20 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.7.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.7.3

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 3"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 33 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.7.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.7.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result

General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

27.22.4.27.5.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.7.

27.22.4.27.5.8 Open Channel (GPRS, support of Text Attribute – Underline On)

27.22.4.27.5.8.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.8.3 Test purpose

To verify that the ME displays an alpha identifier according to the underline text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.8.4 Method of test

27.22.4.27.5.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.8.4.2 Procedure

**Expected Sequence 5.8 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.8.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.8.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with underline on] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.8.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.8.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.8.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with underline off] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 5.8.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 5.8.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.8.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.8.1 | |
| 32 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with underline on] |
| 33 | USER → ME | The user confirms | |
| 34 | ME → USS | PDP context activation request | |
| 35 | USS → ME | PDP context activation accept | |
| 36 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.8.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 40 | ME → USS | PDP context deactivation request | |
| 41 | USS → ME | PDP context deactivation accept | |
| 42 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.8.3 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.8.3 | |
| 46 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with underline off] |
| 47 | USER → ME | The user confirms | |
| 48 | ME → USS | PDP context activation request | |
| 49 | USS → ME | PDP context activation accept | |
| 50 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.8.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.8.1B | [Command performed successfully] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 54 | ME → USS | PDP context deactivation request | |
| 55 | USS → ME | PDP context deactivation accept | |
| 56 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.8.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 1"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 40 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.8.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.8.3

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 3"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 33 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.8.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.8.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

27.22.4.27.5.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.8.

27.22.4.27.5.9 Open Channel (GPRS, support of Text Attribute – Strikethrough On)

27.22.4.27.5.9.1 Definition and applicability

See clause 3.2.2.

27.22.4.27.5.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.27.5.9.3 Test purpose

To verify that the ME displays an alpha identifier according to the strikethrough text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

27.22.4.27.5.9.4 Method of test

27.22.4.27.5.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444

| | |
|---|---|
| Data destination address | 01.01.01.01 |

27.22.4.27.5.9.4.2 Procedure

**Expected Sequence 5.9 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.9.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.9.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with strikethrough on] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.9.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.9.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with strikethrough off] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.9.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.9.1 | |
| 32 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with strikethrough on] |
| 33 | USER → ME | The user confirms | |
| 34 | ME → USS | PDP context activation request | |
| 35 | USS → ME | PDP context activation accept | |
| 36 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 40 | ME → USS | PDP context deactivation request | |
| 41 | USS → ME | PDP context deactivation accept | |
| 42 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 43 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.9.3 | |
| 44 | ME → UICC | FETCH | |
| 45 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.9.3 | |
| 46 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with strikethrough off] |
| 47 | USER → ME | The user confirms | |
| 48 | ME → USS | PDP context activation request | |
| 49 | USS → ME | PDP context activation accept | |
| 50 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.9.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.9.1B | [Command performed successfully] |
| 51 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 52 | ME → UICC | FETCH | |
| 53 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 54 | ME → USS | PDP context deactivation request | |
| 55 | USS → ME | PDP context deactivation accept | |
| 56 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.9.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 1"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Text Attribute

Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 80 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.9.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.9.3

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Alpha Identifier "Open ID 3"

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 33 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.9.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.9.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer

Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

### 27.22.4.27.5.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.9.

### 27.22.4.27.5.10 Open Channel (GPRS, support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.27.5.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.27.5.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.27.5.10.3 Test purpose

To verify that the ME displays an alpha identifier according to the foreground and background colour text attribute configuration in OPEN CHANNEL and returns a successful result in the TERMINAL RESPONSE command send to the UICC.

#### 27.22.4.27.5.10.4 Method of test

##### 27.22.4.27.5.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.27.5.10.4.2 Procedure

**Expected Sequence 5.10 (OPEN CHANNEL, immediate link establishment, GPRS, Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING : OPEN CHANNEL 5.10.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.10.1 | |
| 4 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with foreground and background colour according to the text attribute] |
| 5 | USER → ME | The user confirms | |
| 6 | ME → USS | PDP context activation request | |
| 7 | USS → ME | PDP context activation accept | |
| 8 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.10.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.10.1B | [Command performed successfully] |
| 9 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 10 | ME → UICC | FETCH | |
| 11 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 12 | ME → USS | PDP context deactivation request | |
| 13 | USS → ME | PDP context deactivation accept | |
| 14 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |
| 15 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 5.10.2 | |
| 16 | ME → UICC | FETCH | |
| 17 | UICC → ME | PROACTIVE COMMAND : OPEN CHANNEL 5.10.2 | |
| 18 | ME → USER | Confirmation phase with alpha ID | [alpha identifier is displayed with ME''s default foreground and background colour] |
| 19 | USER → ME | The user confirms | |
| 20 | ME → USS | PDP context activation request | |
| 21 | USS → ME | PDP context activation accept | |
| 22 | ME → UICC | TERMINAL RESPONSE : OPEN CHANNEL 5.10.1A<br>or<br>TERMINAL RESPONSE : OPEN CHANNEL 5.10.1B | [Command performed successfully] |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 5.1.1 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 5.1.1 | |
| 26 | ME → USS | PDP context deactivation request | |
| 27 | USS → ME | PDP context deactivation accept | |
| 28 | ME → UICC | TERMINAL RESPONSE : CLOSE CHANNEL 5.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 5.10.1

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL

Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 1"
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01
Text Attribute
Formatting position: 0
Formatting length: 9
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 53 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 31 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | D0 | 04 | 00 | 09 | 00 |
| | B4 | | | | | | | | | | | |

PROACTIVE COMMAND: OPEN CHANNEL 5.10.2

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Alpha Identifier "Open ID 2"
Bearer
Bearer type: GPRS

Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 4D | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 05 |
| | 09 | 4F | 70 | 65 | 6E | 20 | 49 | 44 | 20 | 32 | 35 | 07 |
| | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 05 | 78 | 47 |
| | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 | 0D |
| | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 | F4 |
| | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD | 9C |
| | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.10.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 5.10.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 00
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1400

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 05 | 78 | | | | | | | |

#### 27.22.4.27.5.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 5.10.

## 27.22.4.28 CLOSE CHANNEL

### 27.22.4.28.1 CLOSE CHANNEL(normal)

#### 27.22.4.28.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);

to the UICC after the ME receives the CLOSE CHANNEL proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

#### 27.22.4.28.1.4 Method of Test

##### 27.22.4.28.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.1.4.2 Procedure

**Expected sequence 1.1 (CLOSE CHANNEL, successful)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.1.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1 | |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 1.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 03 | E8 |
| | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |

TERMINAL RESPONSE: CLOSE CHANNEL 1.1.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected sequence 1.2 (CLOSE CHANNEL, with an invalid channel identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.2.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 1.2.1 | |
| 11 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 1.2.1 | [Invalid channel number] |

PROACTIVE COMMAND: CLOSE CHANNEL 1.2.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 2

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 22 |

TERMINAL RESPONSE: CLOSE CHANNEL 1.2.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Bearer Independent Protocol error
- Additional Result: Channel identifier not valid

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 3A |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 03 | | | | | | | | | | | |

**Expected sequence 1.3 (CLOSE CHANNEL, on an already closed channel)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.1.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 1.1.1 | |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 1.1.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 1.3.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 1.3.1 | |
| 17 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 1.3.1A<br>or<br>TERMINAL RESPONSE CLOSE CHANNEL 1.3.1B | [Channel closed]<br><br>[Channel identifier invalid] |

PROACTIVE COMMAND: CLOSE CHANNEL 1.3.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |

TERMINAL RESPONSE: CLOSE CHANNEL 1.3.1A

Logically:

Command details

Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Bearer Independent Protocol error
Additional Result: Channel closed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 3A |
| | 02 | | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 1.3.1B

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Bearer Independent Protocol error
Additional Result: Channel identifier invalid

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 3A |
| | 03 | | | | | | | | | | | |

#### 27.22.4.28.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

### 27.22.4.28.2 CLOSE CHANNEL (support of Text Attribute)

#### 27.22.4.28.2.1 CLOSE CHANNEL (support of Text Attribute – Left Alignment)

##### 27.22.4.28.2.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.4.28.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.1.4 Method of Test

##### 27.22.4.28.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.1.4.2 Procedure

**Expected sequence 2.1 (CLOSE CHANNEL, with Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1 | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.1.1 | [alpha identifier is displayed with left alignment] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.1.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.1.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.1.2 | [Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/20, no alignment change will take place] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.1.1

Logically:

Command details
Command number: 1

Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 1"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.1.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.1.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

### 27.22.4.28.2.2 CLOSE CHANNEL (support of Text Attribute – Center Alignment)

#### 27.22.4.28.2.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.2.4 Method of Test

##### 27.22.4.28.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.2.4.2 Procedure

**Expected sequence 2.2 (CLOSE CHANNEL, with Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.2.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.2.1 | [alpha identifier is displayed with center alignment] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.2.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.2.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.2.2 | [Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/20, no alignment change will take place] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.2.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.2.1

Logically:

Command details
Command number: 1

Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 1"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 01 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.2.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.2.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

### 27.22.4.28.2.3 CLOSE CHANNEL (support of Text Attribute – Right Alignment)

#### 27.22.4.28.2.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.3.4 Method of Test

##### 27.22.4.28.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.3.4.2 Procedure

**Expected sequence 2.3 (CLOSE CHANNEL, with Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.3.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.3.1 | [alpha identifier is displayed with right alignment] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.3.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.3.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.3.2 | [Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/20, no alignment change will take place] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.3.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.3.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device:Channel 1

Alpha Identifier "Close ID 1"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 02 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.3.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.3.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

### 27.22.4.28.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

### 27.22.4.28.2.4 CLOSE CHANNEL (support of Text Attribute – Large Font Size)

#### 27.22.4.28.2.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.4.4 Method of Test

##### 27.22.4.28.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.4.4.2 Procedure

**Expected sequence 2.4 (CLOSE CHANNEL, with Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1 | [alpha identifier is displayed with large font size] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.4.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context deactivation request | |
| 19 | USS → ME | PDP context deactivation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2 | [alpha identifier is displayed with normal font size] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.4.1 | [Command performed successfully] |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 30 | ME → USER | The ME may display channel opening information | |
| 31 | ME → USS | PDP context activation request | |
| 32 | USS → ME | PDP context activation accept | |
| 33 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 34 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.1 | |
| 35 | ME → UICC | FETCH | |
| 36 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1 | [alpha identifier is displayed with large font size] |
| 37 | ME → USS | PDP context deactivation request | |
| 38 | USS → ME | PDP context deactivation accept | |
| 39 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.4.1 | [Command performed successfully] |
| 40 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 41 | ME → UICC | FETCH | |
| 42 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 43 | ME → USER | The ME may display channel opening information | |
| 44 | ME → USS | PDP context activation request | |
| 45 | USS → ME | PDP context activation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 47 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.4.3 | |
| 48 | ME → UICC | FETCH | |
| 49 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.4.3 | [alpha identifier is displayed with normal font size] |
| 50 | ME → USS | PDP context deactivation request | |
| 51 | USS → ME | PDP context deactivation accept | |
| 52 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.4.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.4.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute
- Formatting position: 0
- Formatting length: 10
- Formatting mode: Left Alignment, Large Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 04 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.4.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.4.3

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 3"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 33 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.4.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

### 27.22.4.28.2.5 CLOSE CHANNEL (support of Text Attribute – Small Font Size)

#### 27.22.4.28.2.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to the small font size text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.5.4 Method of Test

##### 27.22.4.28.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.5.4.2 Procedure

**Expected sequence 2.5 (CLOSE CHANNEL, with Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1 | [alpha identifier is displayed with small font size] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.5.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.5.2 | [alpha identifier is displayed with normal font size] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.5.1 | [Command performed successfully] |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 30 | ME → USER | The ME may display channel opening information | |
| 31 | ME → USS | PDP context activation request | |
| 32 | USS → ME | PDP context activation accept | |
| 33 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 34 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.1 | |
| 35 | ME → UICC | FETCH | |
| 36 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1 | [alpha identifier is displayed with small font size] |
| 37 | ME → USS | PDP context deactivation request | |
| 38 | USS → ME | PDP context deactivation accept | |
| 39 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.5.1 | [Command performed successfully] |
| 40 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 41 | ME → UICC | FETCH | |
| 42 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 43 | ME → USER | The ME may display channel opening information | |
| 44 | ME → USS | PDP context activation request | |
| 45 | USS → ME | PDP context activation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 47 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.5.3 | |
| 48 | ME → UICC | FETCH | |
| 49 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.5.3 | [alpha identifier is displayed with normal font size] |
| 50 | ME → USS | PDP context deactivation request | |
| 51 | USS → ME | PDP context deactivation accept | |
| 52 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.5.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.5.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute
- Formatting position: 0
- Formatting length: 10
- Formatting mode: Left Alignment, Small Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 08 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.5.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.5.3

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 3"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 33 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.5.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

### 27.22.4.28.2.6 CLOSE CHANNEL (support of Text Attribute – Bold On)

#### 27.22.4.28.2.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.6.4 Method of Test

##### 27.22.4.28.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.6.4.2 Procedure

**Expected sequence 2.6 (CLOSE CHANNEL, with Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1 | [alpha identifier is displayed with bold on] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.6.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.6.2 | [alpha identifier is displayed with bold off] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.6.1 | [Command performed successfully] |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 30 | ME → USER | The ME may display channel opening information | |
| 31 | ME → USS | PDP context activation request | |
| 32 | USS → ME | PDP context activation accept | |
| 33 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 34 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.1 | |
| 35 | ME → UICC | FETCH | |
| 36 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1 | [alpha identifier is displayed with bold on] |
| 37 | ME → USS | PDP context deactivation request | |
| 38 | USS → ME | PDP context deactivation accept | |
| 39 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.6.1 | [Command performed successfully] |
| 40 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 41 | ME → UICC | FETCH | |
| 42 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 43 | ME → USER | The ME may display channel opening information | |
| 44 | ME → USS | PDP context activation request | |
| 45 | USS → ME | PDP context activation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 47 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.3 | |
| 48 | ME → UICC | FETCH | |
| 49 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.6.3 | [alpha identifier is displayed with bold off] |
| 50 | ME → USS | PDP context deactivation request | |
| 51 | USS → ME | PDP context deactivation accept | |
| 52 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.6.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.6.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute
- Formatting position: 0
- Formatting length: 10
- Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 10 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.6.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.6.3

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 3"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 33 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.6.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

### 27.22.4.28.2.7 CLOSE CHANNEL (support of Text Attribute – Italic On)

#### 27.22.4.28.2.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.7.4 Method of Test

##### 27.22.4.28.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.7.4.2 Procedure

**Expected sequence 2.7 (CLOSE CHANNEL, with Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1 | [alpha identifier is displayed with bold on] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.7.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.6.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.7.2 | [alpha identifier is displayed with bold off] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.7.1 | [Command performed successfully] |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 30 | ME → USER | The ME may display channel opening information | |
| 31 | ME → USS | PDP context activation request | |
| 32 | USS → ME | PDP context activation accept | |
| 33 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 34 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.1 | |
| 35 | ME → UICC | FETCH | |
| 36 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1 | [alpha identifier is displayed with bold on] |
| 37 | ME → USS | PDP context deactivation request | |
| 38 | USS → ME | PDP context deactivation accept | |
| 39 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.7.1 | [Command performed successfully] |
| 40 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 41 | ME → UICC | FETCH | |
| 42 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 43 | ME → USER | The ME may display channel opening information | |
| 44 | ME → USS | PDP context activation request | |
| 45 | USS → ME | PDP context activation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 47 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.7.3 | |
| 48 | ME → UICC | FETCH | |
| 49 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.7.3 | [alpha identifier is displayed with bold off] |
| 50 | ME → USS | PDP context deactivation request | |
| 51 | USS → ME | PDP context deactivation accept | |
| 52 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.7.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.7.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute
- Formatting position: 0
- Formatting length: 10
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 20 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.7.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.7.3

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 3"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 33 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.7.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

### 27.22.4.28.2.8 CLOSE CHANNEL (support of Text Attribute – Underline On)

#### 27.22.4.28.2.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.8.4 Method of Test

##### 27.22.4.28.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.8.4.2 Procedure

**Expected sequence 2.8 (CLOSE CHANNEL, with Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1 | [alpha identifier is displayed with underline on] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.8.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.8.2 | [alpha identifier is displayed with underline off] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.8.1 | [Command performed successfully] |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 30 | ME → USER | The ME may display channel opening information | |
| 31 | ME → USS | PDP context activation request | |
| 32 | USS → ME | PDP context activation accept | |

| | | | |
|---|---|---|---|
| 33 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 34 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.1 | |
| 35 | ME → UICC | FETCH | |
| 36 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1 | [alpha identifier is displayed with underline on] |
| 37 | ME → USS | PDP context deactivation request | |
| 38 | USS → ME | PDP context deactivation accept | |
| 39 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.8.1 | [Command performed successfully] |
| 40 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 41 | ME → UICC | FETCH | |
| 42 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 43 | ME → USER | The ME may display channel opening information | |
| 44 | ME → USS | PDP context activation request | |
| 45 | USS → ME | PDP context activation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 47 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.8.3 | |
| 48 | ME → UICC | FETCH | |
| 49 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.8.3 | [alpha identifier is displayed with underline off] |
| 50 | ME → USS | PDP context deactivation request | |
| 51 | USS → ME | PDP context deactivation accept | |
| 52 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.8.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.8.1

Logically:

Command details
- Command number: 1
- Command type: CLOSE CHANNEL
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Close ID 1"

Text Attribute
- Formatting position: 0
- Formatting length: 10
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 40 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.8.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.8.3

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 3"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 33 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.8.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL

Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

### 27.22.4.28.2.9 CLOSE CHANNEL (support of Text Attribute – Strikethrough On)

#### 27.22.4.28.2.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.9.4 Method of Test

##### 27.22.4.28.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.9.4.2 Procedure

**Expected sequence 2.9 (CLOSE CHANNEL, with Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1 | [alpha identifier is displayed with strikethrough on] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.9.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.9.2 | [alpha identifier is displayed with strikethrough off] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.9.1 | [Command performed successfully] |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 30 | ME → USER | The ME may display channel opening information | |
| 31 | ME → USS | PDP context activation request | |
| 32 | USS → ME | PDP context activation accept | |
| 33 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 34 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.1 | |
| 35 | ME → UICC | FETCH | |
| 36 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1 | [alpha identifier is displayed with strikethrough on] |
| 37 | ME → USS | PDP context deactivation request | |
| 38 | USS → ME | PDP context deactivation accept | |
| 39 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.9.1 | [Command performed successfully] |
| 40 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 41 | ME → UICC | FETCH | |
| 42 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 43 | ME → USER | The ME may display channel opening information | |
| 44 | ME → USS | PDP context activation request | |
| 45 | USS → ME | PDP context activation accept | |
| 46 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 47 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.9.3 | |
| 48 | ME → UICC | FETCH | |
| 49 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.9.3 | [alpha identifier is displayed with strikethrough off] |
| 50 | ME → USS | PDP context deactivation request | |
| 51 | USS → ME | PDP context deactivation accept | |
| 52 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.9.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.9.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 1"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 80 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.9.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.9.3

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 3"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 33 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.9.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

### 27.22.4.28.2.10 CLOSE CHANNEL (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.28.2.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.28.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.28.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the CLOSE CHANNEL proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.28.2.10.4 Method of Test

##### 27.22.4.28.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP

Port number: 44444
Data destination address 01.01.01.01

27.22.4.28.2.10.4.2 Procedure

**Expected sequence 2.10 (CLOSE CHANNEL, with Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.10.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.10.1 | [alpha identifier is displayed with foreground and background colour according to the text attribute configuration] |
| 11 | ME → USS | PDP context deactivation request | |
| 12 | USS → ME | PDP context deactivation accept | |
| 13 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.10.1 | [Command performed successfully] |
| 14 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | |
| 15 | ME → UICC | FETCH | |
| 16 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 17 | ME → USER | The ME may display channel opening information | |
| 18 | ME → USS | PDP context activation request | |
| 19 | USS → ME | PDP context activation accept | |
| 20 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 21 | UICC → ME | PROACTIVE COMMAND PENDING: CLOSE CHANNEL 2.10.2 | |
| 22 | ME → UICC | FETCH | |
| 23 | UICC → ME | PROACTIVE COMMAND: CLOSE CHANNEL 2.10.2 | [alpha identifier is displayed with ME"s default foreground and background colour] |
| 24 | ME → USS | PDP context deactivation request | |
| 25 | USS → ME | PDP context deactivation accept | |
| 26 | ME → UICC | TERMINAL RESPONSE CLOSE CHANNEL 2.10.1 | [Command performed successfully] |

PROACTIVE COMMAND: CLOSE CHANNEL 2.10.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL

Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 1"
Text Attribute
Formatting position: 0
Formatting length: 10
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1B | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 31 | D0 | 04 | 00 | 0A | 00 | B4 | | | | |

PROACTIVE COMMAND: CLOSE CHANNEL 2.10.2

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Close ID 2"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 15 | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 81 | 21 |
| | 85 | 0A | 43 | 6C | 6F | 73 | 65 | 20 | 49 | 44 | 20 |
| | 32 | | | | | | | | | | |

TERMINAL RESPONSE: CLOSE CHANNEL 2.10.1

Logically:

Command details
Command number: 1
Command type: CLOSE CHANNEL
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 41 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.4.28.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

## 27.22.4.29 RECEIVE DATA

### 27.22.4.29.1 RECEIVE DATA (NORMAL)

#### 27.22.4.29.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (ME currently unable to process command); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);

to the UICC after the ME receives the RECEIVE DATA proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

#### 27.22.4.29.1.4 Method of test

##### 27.22.4.29.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 51.010-1 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.1.4.2 Procedure

**Expected sequence 1.1 (RECEIVE DATA, already opened channel)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 1000 Bytes of data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1 | (1000 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 1.1.1 | 200 Bytes |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 1.1.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 1.1.2 | 200 Bytes |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 1.1.2 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.3 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 1.1.3 | 200 Bytes |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 1.1.3 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.4 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 1.1.4 | 200 Bytes |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 1.1.4 | |
| 35 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 1.1.5 | |
| 36 | ME → UICC | FETCH | |
| 37 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 1.1.5 | 200 Bytes |
| 38 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 1.1.5 | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: ME

Event list: Data available

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | 09 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: RFU

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 03 | E8 |
| | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 13 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | B6 |
| | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | | |

TERMINAL RESPONSE: SEND DATA 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1

Logically:

Event list
Event: Data available
Device identities
Source device: ME
Destination device: UICC
Channel status
Channel status: Channel 1 open, link established
Channel Data Length
Channel data length: FF (more than 255 bytes are available)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 99 | 01 | 09 | 82 | 02 | 82 | 81 | B8 | 02 | 81 |
| | 00 | B7 | 01 | FF | | | | | | | | |

PROACTIVE COMMAND: RECEIVE DATA 1.1.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | B7 |
| | 01 | C8 | | | | | | | | | | |

PROACTIVE COMMAND: RECEIVE DATA 1.1.2

Logically:

Command details
Command number: 2
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 02 | 42 | 00 | 82 | 02 | 81 | 21 | B7 |
| | 01 | C8 | | | | | | | | | | |

PROACTIVE COMMAND: RECEIVE DATA 1.1.3

Logically:

Command details
- Command number: 3
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Channel Data Length
- Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 03 | 42 | 00 | 82 | 02 | 81 | 21 | B7 |
| | 01 | C8 | | | | | | | | | | |

PROACTIVE COMMAND: RECEIVE DATA 1.1.4

Logically:

Command details
- Command number: 4
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Channel Data Length
- Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 04 | 42 | 00 | 82 | 02 | 81 | 21 | B7 |
| | 01 | C8 | | | | | | | | | | |

PROACTIVE COMMAND: RECEIVE DATA 1.1.5

Logically:

Command details
- Command number: 5
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Channel Data Length

Channel Data Length: 200

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 05 | 42 | 00 | 82 | 02 | 81 | 21 | B7 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | C8 | | | | | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 1.1.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

TERMINAL RESPONSE: RECEIVE DATA 1.1.2

Logically:

Command details
- Command number: 2
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel Data : C8 C9 CA .. FF 00 01 .. 8F (200 Bytes of data)
Channel data length: FF

Coding:

| BER-TLV: | 81 | 03 | 02 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B6 | 81 | C8 | C8 | C9 | CA | .. | FF | 00 | 01 | 02 | .. |
| | 8F | B7 | 01 | FF | | | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 1.1.3

Logically:

Command details

Command number: 3
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 90 91 .. FF 00 01 – 57 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 03 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 90 | 91 | 92 | .. | FF | 00 | 01 | 02 | .. |
| | 57 | B7 | 01 | FF | | | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 1.1.4

Logically:

Command details
Command number: 4
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 58 59 .. FF 00 01 .. 1F (200 Bytes of data)
Channel data length: C8

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 04 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 58 | 59 | 5A | .. | FF | 00 | 01 | 02 | .. |
| | 1F | B7 | 01 | C8 | | | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 1.1.5

Logically:

Command details
Command number: 5
Command type: RECEIVE DATA
Command qualifier: RFUDevice identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data: 20 21 .. E7 (200 Bytes of data)
Channel data length: 00

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 05 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 20 | 21 | 22 | .. | E7 | B7 | 01 | 00 | |

### 27.22.4.29.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.4.29.2 RECEIVE DATA (support of Text Attribute)

### 27.22.4.29.2.1 RECEIVE DATA (support of Text Attribute – Left Alignment)

#### 27.22.4.29.2.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.1.4 Method of test

##### 27.22.4.29.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog

User password: UserPwd

UICC/ME interface transport level

Transport format:UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.1.4.2 Procedure

**Expected sequence 2.1 (RECEIVE DATA, with Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1ENVELOPE (Data Available) | (400 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.1.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.1.1 | 200 Bytes with alpha identifier is displayed with left alignment |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.1.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.1.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.1.2 | 200 Bytes with alpha identifier shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/21, no alignment change will take place |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.1.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Logically:

Event list
Event: Data available
Device identities
Source device: ME
Destination device: UICC
Channel status
Channel status: Channel 1 open, link established
Channel Data Length
Channel data length: FF (more than 255 bytes are available)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 99 | 01 | 09 | 82 | 02 | 82 | 81 | B8 | 02 | 81 |
| | 00 | B7 | 01 | FF | | | | | | | | |

PROACTIVE COMMAND: RECEIVE DATA 2.1.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"
Channel Data Length
Channel Data Length: 200
Text Attribute
Formatting position: 0
Formatting length: 14
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.1.2

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.1.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

### 27.22.4.29.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

## 27.22.4.29.2.2 RECEIVE DATA (support of Text Attribute – Center Alignment)

### 27.22.4.29.2.2.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.29.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.2.4 Method of test

##### 27.22.4.29.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.2.4.2 Procedure

**Expected sequence 2.2 (RECEIVE DATA, with Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (400 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.2.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.2.1 | 200 Bytes with alpha identifier is displayed with center alignment |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.2.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.2.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.2.2 | 200 Bytes with alpha identifier shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/21, no alignment change will take place |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.2.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.2.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Center Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 01 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.2.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.2.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

### 27.22.4.29.2.3 RECEIVE DATA (support of Text Attribute – Right Alignment)

#### 27.22.4.29.2.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.3.4 Method of test

##### 27.22.4.29.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.3.4.2 Procedure

**Expected sequence 2.3 (RECEIVE DATA, with Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (400 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.3.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.3.1 | 200 Bytes with alpha identifier is displayed with right alignment |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.3.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.3.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.3.2 | 200 Bytes with alpha identifier shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/21, no alignment change will take place |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.3.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.3.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Right Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 02 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.3.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.3.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

### 27.22.4.29.2.4 RECEIVE DATA (support of Text Attribute – Large Font Size)

#### 27.22.4.29.2.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.4.4 Method of test

##### 27.22.4.29.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.4.4.2 Procedure

**Expected sequence 2.4 (RECEIVE DATA, with Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (800 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.4.1 | 200 Bytes with alpha identifier is displayed with large font size |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.4.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.4.2 | 200 Bytes with alpha identifier is displayed with normal font size |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.4.1 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.4.1 | 200 Bytes with alpha identifier is displayed with large font size |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.4.1 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.4.3 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.4.3 | 200 Bytes with alpha identifier is displayed with normal font size |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.4.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.4.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Large Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 04 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.4.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.4.3

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 33 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.4.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

### 27.22.4.29.2.5 RECEIVE DATA (support of Text Attribute – Small Font Size)

#### 27.22.4.29.2.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to small font size the text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.5.4 Method of test

##### 27.22.4.29.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.5.4.2 Procedure

**Expected sequence 2.5 (RECEIVE DATA, with Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (800 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.5.1 | 200 Bytes with alpha identifier is displayed with small font size |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.5.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.5.2 | 200 Bytes with alpha identifier is displayed with normal font size |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.5.1 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.5.1 | 200 Bytes with alpha identifier is displayed with small font size |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.5.1 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.5.3 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.5.3 | 200 Bytes with alpha identifier is displayed with normal font size |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.5.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.5.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Small Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 08 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.5.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.5.3

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 33 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.5.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

### 27.22.4.29.2.6 RECEIVE DATA (support of Text Attribute – Bold On)

#### 27.22.4.29.2.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.6.4 Method of test

##### 27.22.4.29.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.6.4.2 Procedure

**Expected sequence 2.6 (RECEIVE DATA, with Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (800 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.6.1 | 200 Bytes with alpha identifier is displayed with bold on |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.6.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.6.2 | 200 Bytes with alpha identifier is displayed with bold off |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.6.1 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.6.1 | 200 Bytes with alpha identifier is displayed with bold on |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.6.1 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.6.3 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.6.3 | 200 Bytes with alpha identifier is displayed with bold off |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.6.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.6.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold On, Italic Off, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 10 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.6.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.6.3

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 33 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.6.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

### 27.22.4.29.2.7 RECEIVE DATA (support of Text Attribute – Italic On)

#### 27.22.4.29.2.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.7.4 Method of test

##### 27.22.4.29.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.7.4.2 Procedure

**Expected sequence 2.7 (RECEIVE DATA, with Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1ENVELOPE | (800 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.7.1 | 200 Bytes with alpha identifier is displayed with italic on |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.7.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.7.2 | 200 Bytes with alpha identifier is displayed with italic off |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.7.1 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.7.1 | 200 Bytes with alpha identifier is displayed with italic on |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.7.1 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.7.3 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.7.3 | 200 Bytes with alpha identifier is displayed with italic off |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.7.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.7.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 20 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.7.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.7.3

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 33 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.7.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

### 27.22.4.29.2.8 RECEIVE DATA (support of Text Attribute – Underline On)

#### 27.22.4.29.2.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.8.4 Method of test

##### 27.22.4.29.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.8.4.2 Procedure

**Expected sequence 2.8 (RECEIVE DATA, with Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (800 kBytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.8.1 | 200 Bytes with alpha identifier is displayed with underline on |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.8.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.8.2 | 200 Bytes with alpha identifier is displayed with underline off |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.8.1 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.8.1 | 200 Bytes with alpha identifier is displayed with underline on |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.8.1 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.8.3 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.8.3 | 200 Bytes with alpha identifier is displayed with underline off |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.8.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.8.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 40 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.8.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.8.3

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 33 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.8.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

### 27.22.4.29.2.9 RECEIVE DATA (support of Text Attribute – Strikethrough On)

#### 27.22.4.29.2.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.9.4 Method of test

##### 27.22.4.29.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.9.4.2 Procedure

**Expected sequence 2.9 (RECEIVE DATA, with Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 800 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (800 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.9.1 | 200 Bytes with alpha identifier is displayed with strikethrough on |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.9.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.9.2 | 200 Bytes with alpha identifier is displayed with strikethrough off |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.9.1 | |
| 27 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.1 | |
| 28 | ME → UICC | FETCH | |
| 29 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.9.1 | 200 Bytes with alpha identifier is displayed with strikethrough on |
| 30 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.9.1 | |
| 31 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.9.3 | |
| 32 | ME → UICC | FETCH | |
| 33 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.9.3 | 200 Bytes with alpha identifier is displayed with strikethrough off |
| 34 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.9.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.9.1

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 1"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14
- Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 80 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.9.2

Logically:

Command details
- Command number: 1
- Command type: RECEIVE DATA
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier: "Receive Data 2"

Channel Data Length
- Channel Data Length: 200

Text Attribute
- Formatting position: 0
- Formatting length: 14

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.9.3

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 3"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 33 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.9.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

### 27.22.4.29.2.10 RECEIVE DATA (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.29.2.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.29.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.29.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the RECEIVE DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.29.2.10.4 Method of test

##### 27.22.4.29.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.29.2.10.4.2 Procedure

**Expected sequence 2.10 (RECEIVE DATA, with Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 15 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 16 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 17 | USS → ME | Transfer of 400 Bytes data to the ME through channel 1 using the ME's port number, which was retrieved in step 15 | |
| 18 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1 | (400 Bytes of data in the ME buffer) |
| 19 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.10.1 | |
| 20 | ME → UICC | FETCH | |
| 21 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.10.1 | 200 Bytes with alpha identifier is displayed with foreground and background colour |
| 22 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.10.1 | |
| 23 | UICC → ME | PROACTIVE COMMAND PENDING: RECEIVE DATA 2.10.2 | |
| 24 | ME → UICC | FETCH | |
| 25 | UICC → ME | PROACTIVE COMMAND: RECEIVE DATA 2.10.2 | 200 Bytes with alpha identifier is displayed with ME"s default foreground and background colour |
| 26 | ME → UICC | TERMINAL RESPONSE: RECEIVE DATA 2.10.1 | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Same as PROACTIVE COMMAND: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

TERMINAL RESPONSE: SEND DATA 1.1.1

Same as TERMINAL RESPONSE: SEND DATA 1.1.1 in clause 27.22.4.29.1.4.2.

ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1

Same as cl. 27.22.4.29.2.1.4.2, ENVELOPE: EVENT DOWNLOAD - Data available 2.1.1.

PROACTIVE COMMAND: RECEIVE DATA 2.10.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 1"
Channel Data Length
Channel Data Length: 200
Text Attribute
Formatting position: 0
Formatting length: 14
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 22 | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 31 | B7 | 01 | C8 | D0 | 04 | 00 | 0E | 00 | B4 |

PROACTIVE COMMAND: RECEIVE DATA 2.10.2

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Receive Data 2"
Channel Data Length
Channel Data Length: 200

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 1C | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 81 | 21 | 85 |
| | 0E | 52 | 65 | 63 | 65 | 69 | 76 | 65 | 20 | 44 | 61 | 74 |
| | 61 | 20 | 32 | B7 | 01 | C8 | | | | | | |

TERMINAL RESPONSE: RECEIVE DATA 2.10.1

Logically:

Command details
Command number: 1
Command type: RECEIVE DATA
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel Data : 00 01 02 .. C7 (200 Bytes of data)
Channel data length: FF

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 42 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B6 | 81 | C8 | 00 | 01 | 02 | .. | C7 | B7 | 01 | FF | |

#### 27.22.4.29.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

## 27.22.4.30 SEND DATA

### 27.22.4.30.1 SEND DATA (normal)

#### 27.22.4.30.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.1.3 Test purpose

To verify that the ME shall send a:

- TERMINAL RESPONSE (Command Performed Successfully); or
- TERMINAL RESPONSE (ME currently unable to process command); or
- TERMINAL RESPONSE (Bearer Independent Protocol Error);
- TERMINAL RESPONSE (Proactive USIM session terminated by the user);

to the UICC after the ME receives the SEND DATA proactive command. The TERMINAL RESPONSE sent back to the UICC is the result of the ME and the network capabilities against requested parameters by the UICC.

#### 27.22.4.30.1.4 Method of test

##### 27.22.4.30.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The Channel identifier value used for these tests is set to 1 as an example.

This channel identifier is dependent on the ME"s default channel identifier as declared in table A.2/27

The following Bearer Parameters used are those defined in the default Test PDP context for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.1.4.2 Procedure

**Expected sequence 1.1 (SEND DATA, immediate mode)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 11 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | |
| 12 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details

Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

BER-TLV

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 03 | E8 |
| 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

Buffer
Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 13 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | B6 |
| | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | | |

TERMINAL RESPONSE: SEND DATA 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

**Expected sequence 1.2 (SEND DATA, Store mode)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.2.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.2.1 | Send 500 Bytes of data (200 + 200 + 100) |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.2.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.2.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.2.2 | [200 Bytes] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.2.2 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.2.3 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA (Immediate mode) 1.2.3 | [100 Bytes] |
| 19 | ME → USS | Transfer of 500 Bytes of data to the USS through channel 1 | |
| 20 | ME → UICC | TERMINAL RESPONSE: SEND DATA (Immediate mode) 1.2.3 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 1.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Store mode

Device identities
- Source device: UICC
- Destination device: Channel 1

Channel Data
- Channel Data : 00 01 .. C7 (200 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 81 | 21 |
| | B6 | 81 | C8 | 00 | 01 | .. | C7 | | | | | |

TERMINAL RESPONSE: SEND DATA 1.2.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| BER-TLV: | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B7 | 01 | FF | | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.2.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data : C8 C9 .. FF 00 01 .. 8F (200 Bytes of data)

Coding:

| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 81 | 21 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B6 | 81 | C8 | C8 | C9 | .. | FF | 00 | 01 | .. | 8F | |

TERMINAL RESPONSE: SEND DATA 1.2.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| BER-TLV: | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B7 | 01 | FF | | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.2.3

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Immediate mode

Device identities
- Source device: UICC
- Destination device: Channel 1

Channel Data
- Channel Data : 90 91 .. F3 (100 Bytes of data)

Coding:

| BER-TLV: | D0 | 6F | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | B6 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 64 | 90 | 91 | .. | F3 | | | | | | | |

TERMINAL RESPONSE: SEND DATA 1.2.3

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Immediate mode

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B7 | 01 | FF | | | | | | | | | |

**Expected sequence 1.3 (SEND DATA, Store mode, Tx buffer fully used)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.1 | Send 1000 Bytes of data by packet of 200 Bytes |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2 | [200 Bytes] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.3 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3 | [200 Bytes] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.4 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.4 | [200 Bytes] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4 | [Command performed successfully] |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.5 | |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5 | [200 Bytes] |
| 27 | ME → USS | Transfer of 1000 Bytes of data to the USS through channel 1 | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Store mode

Device identities
- Source device: UICC
- Destination device: Channel 1

Channel Data
Channel Data : 00 01 02 .. C7 (200 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 81 | 21 |
| | B6 | 81 | C8 | 00 | 01 | 02 | ... | C7 | | | | |

TERMINAL RESPONSE: SEND DATA 1.3.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.3.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data : C8 C9 CA .. FF 00 01 .. 8F (200 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 81 | 21 |
| | B6 | 81 | C8 | C8 | C9 | CA | ... | FF | 00 | 02 | .. | 8F |

TERMINAL RESPONSE: SEND DATA 1.3.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| BER-TLV: | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B7 | 01 | FF | | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.3.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data : 90 91 .. FF 00 01 .. 57 (200 Bytes of data)

Coding:

| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 81 | 21 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B6 | 81 | C8 | 90 | 91 | .. | FF | 00 | 01 | .. | 57 | |

TERMINAL RESPONSE: SEND DATA 1.3.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| BER-TLV: | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B7 | 01 | FF | | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.3.4

Logically:

Command details
Command number: 1

Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data : 58 59 .. FF 00 01 .. 1F (200 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 81 | 21 |
| | B6 | 81 | C8 | 58 | 59 | .. | FF | 00 | 01 | .. | 1F | |

TERMINAL RESPONSE: SEND DATA 1.3.4

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Store mode
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: 200 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | C8 | | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.3.5

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data: 20 21 .. E7 (200 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 81 | D4 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 |
| | B6 | 81 | C8 | 20 | 21 | .. | E7 | | | | | |

TERMINAL RESPONSE: SEND DATA 1.3.5

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

**Expected sequence 1.4 (SEND DATA, 2 consecutive SEND DATA Store mode)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.1 | Send 1000 Bytes of data by packet of 200 Bytes |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2 | [200 Bytes] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.3 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3 | [200 Bytes] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.4 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.4 | [200 Bytes] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4 | [Command performed successfully] |
| 24 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.5 | … |
| 25 | ME → UICC | FETCH | |
| 26 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5 | [200 Bytes] |
| 27 | ME → USS | Transfer of 1000 Bytes of data to the USS through channel 1 | |
| 28 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5 | [Command performed successfully] |
| 29 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.1 | |
| 30 | ME → UICC | FETCH | |
| 31 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.1 | Send 1000 Bytes of data by packet of 200 Bytes |
| 32 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.1 | [Command performed successfully] |
| 33 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.2 | |
| 34 | ME → UICC | FETCH | |
| 35 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.2 | [200 Bytes] |
| 36 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.2 | [Command performed successfully] |

| | | | |
|---|---|---|---|
| 37 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.3 | |
| 38 | ME → UICC | FETCH | |
| 39 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.3 | [200 Bytes] |
| 40 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.3 | [Command performed successfully] |
| 41 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.4 | |
| 42 | ME → UICC | FETCH | |
| 43 | UICC → ME | PROACTIVE COMMAND: SEND DATA (store mode) 1.3.4 | [200 Bytes] |
| 44 | ME → UICC | TERMINAL RESPONSE: SEND DATA (store mode) 1.3.4 | [Command performed successfully] |
| 45 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.3.5 | … |
| 46 | ME → UICC | FETCH | |
| 47 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.3.5 | [200 Bytes] |
| 48 | ME → USS | Transfer of 1000 Bytes of data to the USS through channel 1 | |
| 49 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.3.5 | [Command performed successfully] |

**Expected sequence 1.5 (SEND DATA, immediate mode with a bad channel identifier)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.5.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.5.1 | |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.5.1 | [Invalid channel number] |

PROACTIVE COMMAND: SEND DATA 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 2

Channel Data
- Channel Data : 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 13 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 22 | B6 |
| | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | | |

TERMINAL RESPONSE: SEND DATA 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Bearer Independent Protocol error (3A)
- Additional Result: Channel identifier not valid (03)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 02 | 3A |
| | 03 | | | | | | | | | | | |

**Expected sequence 1.6 Void**

27.22.4.30.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.5.

## 27.22.4.30.2 SEND DATA (support of Text Attribute)

### 27.22.4.30.2.1 SEND DATA (support of Text Attribute – Left Alignment)

#### 27.22.4.30.2.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.1.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.1.3 Test purpose

To verify that the ME shall display the alpha identifier according to the left alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.1.4 Method of test

##### 27.22.4.30.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.1.4.2 Procedure

**Expected sequence 2.1 (SEND DATA with Text Attribute – Left Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.1.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.1.1 | [alpha identifier shall be displayed with left alignment] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.1.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.1.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.1.2 | [Message shall be formatted without left alignment. Remark: If left alignment is the ME"s default alignment as declared in table A.2/22, no alignment change will take place] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.1.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold On, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.1.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately

Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

27.22.4.30.2.1.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.1.

27.22.4.30.2.2 SEND DATA (support of Text Attribute – Center Alignment)

27.22.4.30.2.2.1 Definition and applicability

See clause 3.2.2.

27.22.4.30.2.2.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

27.22.4.30.2.2.3 Test purpose

To verify that the ME shall display the alpha identifier according to the center alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

27.22.4.30.2.2.4 Method of test

27.22.4.30.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format:UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.2.4.2 Procedure

**Expected sequence 2.2 (SEND DATA with Text Attribute – Center Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.2.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.2.1 | [alpha identifier shall be displayed with center alignment] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.2.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.2.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.2.2 | [Message shall be formatted without center alignment. Remark: If center alignment is the ME"s default alignment as declared in table A.2/22, no alignment change will take place] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.2.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.2.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Center Alignment, Normal Font, Bold On, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 01 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.2.2

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 2"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.2.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

### 27.22.4.30.2.2.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.2.

### 27.22.4.30.2.3 SEND DATA (support of Text Attribute – Right Alignment)

#### 27.22.4.30.2.3.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.3.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.3.3 Test purpose

To verify that the ME shall display the alpha identifier according to the right alignment text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.3.4 Method of test

##### 27.22.4.30.2.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.3.4.2 Procedure

**Expected sequence 2.3 (SEND DATA with Text Attribute – Right Alignment)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.3.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.3.1 | [alpha identifier shall be displayed with right alignment] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.3.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.3.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.3.2 | [Message shall be formatted without right alignment. Remark: If right alignment is the ME"s default alignment as declared in table A.2/22, no alignment change will take place] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.3.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11
- Formatting mode: Right Alignment, Normal Font, Bold On, Italic On, Underline Off, Strikethrough Off

Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| 00 | 0B | 02 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.3.2

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 2"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.3.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

### 27.22.4.30.2.3.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.3.

### 27.22.4.30.2.4 SEND DATA (support of Text Attribute – Large Font Size)

#### 27.22.4.30.2.4.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.4.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.4.3 Test purpose

To verify that the ME shall display the alpha identifier according to the large font size text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.4.4 Method of test

##### 27.22.4.30.2.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.4.4.2 Procedure

**Expected sequence 2.4 (SEND DATA with Text Attribute – Large Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.4.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.4.1 | [alpha identifier shall be displayed with large font size] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.4.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.4.2 | [alpha identifier shall be displayed with normal font size] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.4.1 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.4.1 | [alpha identifier shall be displayed with large font size] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.4.3 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.4.3 | [alpha identifier shall be displayed with normal font size] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.4.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11

Formatting mode: Left Alignment, Large Font, Bold On, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 04 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.4.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.4.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 33 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.4.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

#### 27.22.4.30.2.4.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.4.

### 27.22.4.30.2.5 SEND DATA (support of Text Attribute – Small Font Size)

#### 27.22.4.30.2.5.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.5.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.5.3 Test purpose

To verify that the ME shall display the alpha identifier according to the small font size text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.5.4 Method of test

##### 27.22.4.30.2.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.5.4.2 Procedure

**Expected sequence 2.5 (SEND DATA with Text Attribute – Small Font Size)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.5.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.5.1 | [alpha identifier shall be displayed with small font size] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.5.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.5.2 | [alpha identifier shall be displayed with normal font size] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.5.1 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.5.1 | [alpha identifier shall be displayed with small font size] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.5.3 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.5.3 | [alpha identifier shall be displayed with normal font size] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.5.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11

Formatting mode: Left Alignment, Small Font, Bold On, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 08 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.5.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.5.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 33 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.5.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

#### 27.22.4.30.2.5.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.5.

### 27.22.4.30.2.6 SEND DATA (support of Text Attribute – Bold On)

#### 27.22.4.30.2.6.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.6.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.6.3 Test purpose

To verify that the ME shall display the alpha identifier according to the bold text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.6.4 Method of test

##### 27.22.4.30.2.6.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.6.4.2 Procedure

**Expected sequence 2.6 (SEND DATA with Text Attribute – Bold On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.6.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.6.1 | [alpha identifier shall be displayed with Bold on] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.6.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.6.2 | [alpha identifier shall be displayed with bold off] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.6.1 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.6.1 | [alpha identifier shall be displayed with bold on] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.6.3 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.6.3 | [alpha identifier shall be displayed with bold off] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.6.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold On , Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 10 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.6.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.6.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 33 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.6.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

#### 27.22.4.30.2.6.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.6.

### 27.22.4.30.2.7 SEND DATA (support of Text Attribute – Italic On)

#### 27.22.4.30.2.7.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.7.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.7.3 Test purpose

To verify that the ME shall display the alpha identifier according to the italic text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.7.4 Method of test

##### 27.22.4.30.2.7.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.7.4.2 Procedure

**Expected sequence 2.7 (SEND DATA with Text Attribute – Italic On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.7.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.7.1 | [alpha identifier shall be displayed with Italic on] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.7.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.7.2 | [alpha identifier shall be displayed with italic off] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.7.1 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.7.1 | [alpha identifier shall be displayed with italic on] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.7.3 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.7.3 | [alpha identifier shall be displayed with italic off] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.7.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic On, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 20 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.7.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.7.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 33 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.7.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

#### 27.22.4.30.2.7.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.7.

### 27.22.4.30.2.8 SEND DATA (support of Text Attribute – Underline On)

#### 27.22.4.30.2.8.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.8.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.8.3 Test purpose

To verify that the ME shall display the alpha identifier according to the underline text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.8.4 Method of test

##### 27.22.4.30.2.8.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The

corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.8.4.2 Procedure

**Expected sequence 2.8 (SEND DATA with Text Attribute – Underline On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.8.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.8.1 | [alpha identifier shall be displayed with underline on] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.8.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.8.2 | [alpha identifier shall be displayed with underline off] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.8.1 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.8.1 | [alpha identifier shall be displayed with underline on] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.8.3 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.8.3 | [alpha identifier shall be displayed with underline off] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.8.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline On, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 40 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.8.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.8.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 33 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.8.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

#### 27.22.4.30.2.8.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.8.

### 27.22.4.30.2.9 SEND DATA (support of Text Attribute – Strikethrough On)

#### 27.22.4.30.2.9.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.9.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.9.3 Test purpose

To verify that the ME shall display the alpha identifier according to the strikethrough text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.9.4 Method of test

##### 27.22.4.30.2.9.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.9.4.2 Procedure

**Expected sequence 2.9 (SEND DATA with Text Attribute – Strikethrough On)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.9.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.9.1 | [alpha identifier shall be displayed with strikethrough on] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.9.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.9.2 | [alpha identifier shall be displayed with strikethrough off] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1 | [Command performed successfully] |
| 16 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.9.1 | |
| 17 | ME → UICC | FETCH | |
| 18 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.9.1 | [alpha identifier shall be displayed with strikethrough on] |
| 19 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1 | [Command performed successfully] |
| 20 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.9.3 | |
| 21 | ME → UICC | FETCH | |
| 22 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.9.3 | [alpha identifier shall be displayed with strikethrough off] |
| 23 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.9.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.9.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: UICC
- Destination device: Channel 1

Alpha Identifier "Send Data 1"

Channel Data
- Channel Data: 00 01 .. 07 (8 Bytes of data)

Text Attribute
- Formatting position: 0
- Formatting length: 11

Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough On
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 80 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.9.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.9.3

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 3"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 33 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.9.1

Logically:

Command details
- Command number: 1
- Command type: SEND DATA
- Command qualifier: Send Immediately

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully
- Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

#### 27.22.4.30.2.9.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.9.

### 27.22.4.30.2.10 SEND DATA (support of Text Attribute – Foreground and Background Colour)

#### 27.22.4.30.2.10.1 Definition and applicability

See clause 3.2.2.

#### 27.22.4.30.2.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

#### 27.22.4.30.2.10.3 Test purpose

To verify that the ME shall display the alpha identifier according to the foreground and background colour text attribute configuration in the SEND DATA proactive command and send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC.

#### 27.22.4.30.2.10.4 Method of test

##### 27.22.4.30.2.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, as specified in TS 34.108 [12], for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.30.2.10.4.2 Procedure

**Expected sequence 2.10 (SEND DATA with Text Attribute – Foreground and Background Colour)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.10.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.10.1 | [alpha identifier shall be displayed with foreground and background colour according to the text attribute configuration] |
| 11 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.10.1 | [Command performed successfully] |
| 12 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 2.10.2 | |
| 13 | ME → UICC | FETCH | |
| 14 | UICC → ME | PROACTIVE COMMAND: SEND DATA 2.10.2 | [alpha identifier shall be displayed with ME"s default foreground and background colour] |
| 15 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 2.10.1 | [Command performed successfully] |

PROACTIVE COMMAND: SEND DATA 2.10.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 1"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)
Text Attribute
Formatting position: 0
Formatting length: 11
Formatting mode: Left Alignment, Normal Font, Bold Off, Italic Off, Underline Off, Strikethrough Off
Colour: Dark Green Foreground, Bright Yellow Background

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 26 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 31 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | D0 | 04 |
| | 00 | 0B | 00 | B4 | | | | | | | | |

PROACTIVE COMMAND: SEND DATA 2.10.2

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Alpha Identifier "Send Data 2"
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 20 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | 85 |
| | 0B | 53 | 65 | 6E | 64 | 20 | 44 | 61 | 74 | 61 | 20 | 32 |
| | B6 | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | |

TERMINAL RESPONSE: SEND DATA 2.10.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: ME

Destination device: UICC

Result

General Result: Command performed successfully

Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B7 | 01 | FF | | | | | | | | | |

27.22.4.30.2.10.5 Test Requirement

The ME shall operate in the manner defined in expected sequences 2.10.

## 27.22.4.31 GET CHANNEL STATUS

### 27.22.4.31.1 Definition and applicability

See clause 3.2.2.

### 27.22.4.31.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

### 27.22.4.31.3 Test purpose

To verify that the ME shall send a TERMINAL RESPONSE (Command Performed Successfully) to the UICC after the ME receives the GET STATUS proactive command. The TERMINAL RESPONSE sent back to the UICC is function of the ME and the network capabilities against asked parameters by the UICC.

### 27.22.4.31.4 Method of test

#### 27.22.4.31.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs

User login: UserLog
User password: UserPwd
UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.4.31.4.2 Procedure

**Expected sequence 1.1 (GET STATUS, without any BIP channel opened)**

For that test, no channel has been opened.

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: GET CHANNEL STATUS 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: GET STATUS 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE GET STATUS 1.1.1 A<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.1.1B<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.1.1C | [Command performed successfully] |

PROACTIVE COMMAND: GET STATUS 1.1.1

Logically:

Command details
Command number: 1
Command type: GET STATUS
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: ME

Coding:

| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 81 | 82 |
|---|---|---|---|---|---|---|---|---|---|---|---|

TERMINAL RESPONSE: GET STATUS 1.1.1A

Logically:

Command details
Command number: 1
Command type: GET STATUS
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | | | | | | | | | | | | |

TERMINAL RESPONSE: GET STATUS 1.1.1B

Logically:

Command details
- Command number: 1
- Command type: GET STATUS
- Command qualifier: RFU

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status
- Channel status: No Channel available, link not established or PDP context not activated

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | B8 | 02 | 00 | 00 | | | | | | | | |

TERMINAL RESPONSE: GET STATUS 1.1.1C

Logically:

Command details
- Command number: 1
- Command type: GET STATUS
- Command qualifier: RFU

Device identities
- Source device: ME
- Destination device: SIM

Result
- General Result: Command performed successfully

Channel status
- Channel 1 status: Channel identifier 1, Link not established or PDP context not activated
- Channel 2 status: Channel identifier 2, Link not established or PDP context not activated
- .
- .
- Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | Note1 | | | | | | | | | | | |

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. Each channel status TLV coding shall indicate the corresponding channel identifier and shall state "Link not established or PDP context not activated". As an example, if the mobile supports two channels then the corresponding channel status data objects coding would be : 'B8 02 01 00 B8 02 02 00'.

**Expected sequence 1.2 (GET STATUS, with a BIP channel currently opened)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 4 | ME → USS | PDP context activation request | |
| 5 | USS → ME | PDP context activation accept | |
| 6 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 7 | UICC → ME | PROACTIVE COMMAND PENDING: GET CHANNEL STATUS 1.2.1 | |
| 8 | ME → UICC | FETCH | |
| 9 | UICC → ME | PROACTIVE COMMAND: GET STATUS 1.2.1 | |
| 10 | ME → UICC | TERMINAL RESPONSE GET STATUS 1.2.1 A<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.2.1B | [Command performed successfully] |

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Bearer
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 03 | E8 |
| | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS

Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

PROACTIVE COMMAND: GET STATUS 1.2.1

Logically:

Command details
Command number: 1
Command type: GET STATUS
Command qualifier: RFU
Device identities
Source device: UICC
Destination device: ME

Coding:

| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 81 | 82 |
|---|---|---|---|---|---|---|---|---|---|---|---|

TERMINAL RESPONSE: GET STATUS 1.2.1A

Logically:

Command details
Command number: 1
Command type: GET STATUS
Command qualifier: RFU
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status
Channel status: Channel 1 open, link established or PDP context activated

Coding:

| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B8 | 02 | 81 | 00 | | | | | | | | |

TERMINAL RESPONSE: GET STATUS 1.2.1B

Logically:

Command details
Command number: 1
Command type: GET STATUS
Command qualifier: RFU
Device identities
Source device: ME
Destination device: SIM
Result
General Result: Command performed successfully
Channel status
Channel 1 status: Channel identifier 1 open, Link established or PDP context activated

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

.

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | Note1 | | | | | | | | | | | |

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. The channel status TLV coding of the opened channel shall state "Link established or PDP context activated". Each other channel status TLV coding shall indicate the corresponding channel identifier and shall state "Link is not established or PDP context not activated". As an example, if the mobile supports two channels and channel 1 is opened then the corresponding channel status data objects coding would be : 'B8 02 81 00 B8 02 02 00'.

**Expected sequence 1.3 (GET STATUS, after a link dropped)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | [Command performed successfully] |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USS | PDP context activation request | |
| 9 | USS → ME | PDP context activation accept | |
| 10 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 11 | USS → ME | DROP LINK | |
| 12 | ME → UICC | ENVELOPE EVENT DOWNLOAD: CHANNEL STATUS 1.3.1 | [Link dropped] |
| 13 | UICC → ME | PROACTIVE COMMAND PENDING: GET STATUS 1.3.1 | |
| 14 | ME → UICC | FETCH | |
| 15 | UICC → ME | PROACTIVE COMMAND: GET STATUS 1.3.1 | |
| 16 | ME → UICC | TERMINAL RESPONSE: GET STATUS 1.3.1A<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.3.1B<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.3.1C<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.3.1D<br>Or<br>TERMINAL RESPONSE: GET STATUS 1.3.1E | [Command performed successfully] |

TERMINAL RESPONSE: GET STATUS 1.3.1A

Same as TERMINAL RESPONSE: GET STATUS 1.1.1A

TERMINAL RESPONSE: GET STATUS 1.3.1B

Same as TERMINAL RESPONSE: GET STATUS 1.1.1B

TERMINAL RESPONSE: GET STATUS 1.3.1C

Same as TERMINAL RESPONSE: GET STATUS 1.1.1C

TERMINAL RESPONSE: GET STATUS 1.3.1D

Logically:

Command details
- Command number: 1
- Command type: GET STATUS
- Command qualifier: RFU

Device identities

Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel status
Channel status: Channel 1, link dropped

Coding:

| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B8 | 02 | 01 | 05 | | | | | | | | |

TERMINAL RESPONSE: GET STATUS 1.3.1E

Logically:

Command details
Command number: 1
Command type: GET STATUS
Command qualifier: RFU
Device identities
Source device: ME
Destination device: SIM
Result
General Result: Command performed successfully
Channel status
Channel 1 status: Channel identifier 1, link dropped

Channel 2 status: Channel identifier 2, Link not established or PDP context not activated

.

.

Channel n status: Channel identifier n, Link not established or PDP context not activated

The number of channel status data objects shall be same as the number of channels(n) supported by the ME

Coding:

| BER-TLV: | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B8 | 02 | 01 | 05 | Note1 | | | | | | | |

Note1: The Terminal Response shall contain as many channel status TLVs as channels are supported by the ME. Each channel status TLV coding except that one for which the link was dropped by the SS shall indicate the corresponding channel identifier and shall state "Link not established or PDP context not activated". As an example, if the mobile supports two channels then the corresponding channel status data objects coding would be : 'B8 02 01 05 B8 02 02 00'.

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: UICC
Destination device: ME
Event list

Event 1: Channel Status

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 99 | 01 | 0A | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|

ENVELOPE EVENT DOWNLOAD: CHANNEL STATUS 1.3.1

Logically:

Event list
- Event list: Channel Status

Device identities
- Source device: ME
- Destination device: UICC

Channel status
- Channel status: Channel 1, link dropped

Coding:

| BER-TLV: | D6 | 0B | 99 | 01 | 0A | 82 | 02 | 82 | 81 | B8 | 02 | 01 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 05 | | | | | | | | | | | |

PROACTIVE COMMAND: GET STATUS 1.3.1

Logically:

Command details
- Command number: 1
- Command type: GET STATUS
- Command qualifier: RFU

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 44 | 00 | 82 | 02 | 81 | 82 |

#### 27.22.4.31.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.3.

## 27.22.5 Data Download to UICC

### 27.22.5.1 SMS-PP Data Download

#### 27.22.5.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.5.1.2 Conformance requirement

The ME shall support the Proactive UICC: SMS-PP Data Download facility as defined in the following technical specifications:

- TS 31.111 [15] clause 5, clause 7.1, clause 8.1, clause 8.7, clause 8.13 and clause 11.
- TS 31.115 [28] clause 4.
- TS 23.038 [7] clause 4..

#### 27.22.5.1.3 Test purpose

To verify that the ME transparently passes the "data download via SMS Point-to-point" messages to the UICC.

To verify that the ME returns the RP-ACK message back to the USS, if the UICC responds with '90 00' or '91 XX'.

To verify that the ME returns the RP-ERROR message back to the system Simulator, if the UICC responds with '62 XX' or '63 XX'.

To verify that the ME returns the response data from the UICC back to the USS in the TP-User-Data element of the RP-ACK message, if the UICC returns response data'.

#### 27.22.5.1.4 Method of Test

##### 27.22.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The "data download via SMS-PP" service is available in the USIM Service Table.

27.22.5.1.4.2 Procedure

**Expected Sequence 1.1 (void)**

**Expected Sequence 1.2 (SMS-PP Data Download, General Data Coding, Acknowledgement)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | SMS-PP Data Download Message 1.2.1 | |
| 2 | ME → USER | The ME shall not display the message or alert the user of a short message waiting. | |
| 3 | ME → UICC | ENVELOPE: SMS-PP DOWNLOAD 1.2.2 | |
| 4 | UICC → ME | SMS-PP Data Download UICC Acknowledgement 1.2.4 | [SW1 / SW2 of '90 00' |
| 5 | ME → USS | SMS-PP Data Download UICC Acknowledgement 1.2.4 in the TP-User-Data element of the RP-ACK message. The values of protocol identifier and data coding scheme in RP-ACK shall be as in the original message. | |

**Expected Sequence 1.3 (SMS-PP Data Download, General Data Coding, FETCH, MORE TIME)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | SMS-PP Data Download Message 1.3.1 | |
| 2 | ME → USER | The ME shall not display the message or alert the user of a short message waiting | |
| 3 | ME → UICC | ENVELOPE: SMS-PP DOWNLOAD 1.3.2 | [SW1 / SW2 of '91 0B'] |
| 4 | UICC → ME | PROACTIVE COMMAND PENDING: MORE TIME 1.3.4 | |
| 5 | ME → USS | RP-ACK | |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: MORE TIME 1.3.4 | |
| 8 | ME → UICC | TERMINAL RESPONSE: MORE TIME 1.3.5 | |
| 9 | UICC → ME | PROACTIVE UICC SESSION ENDED | |

PROACTIVE COMMAND: MORE TIME 1.3.4

Logically:

Command details
- Command number: 1
- Command type: MORE TIME
- Command qualifier: "00"

Device identities
- Source device: UICC
- Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 02 | 00 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: MORE TIME 1.3.5

Logically:

Command details
- Command number: 1
- Command type: MORE TIME
- Command qualifier: "00"

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 02 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.4 (void)**

SMS-PP (Data Download) Message 1.2.1 / 1.3.1

Logically:

SMS TPDU
- TP-MTI: SMS-DELIVER
- TP-MMS: No more messages waiting for the MS in this SC
- TP-RP: TP-Reply-Path is not set in this SMS-DELIVER
- TP-UDHI: TP-UD field contains only the short message
- TP-SRI: A status report will not be returned to the SME
- TP-OA
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "1234"
- TP-PID: (U)SIM Data download
- TP-DCS
  - Coding Group: General Data Coding
  - Compression: Text is uncompressed
  - Message Class: Class 2 (U)SIM Specific Message
  - Alphabet: 8 bit data
- TP-SCTS: 01/01/98 00:00:00 +0
- TP-UDL: 13
- TP-UD: "Short Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 04 | 04 | 91 | 21 | 43 | 7F | 16 | 89 | 10 | 10 | 00 | 00 |
| | 00 | 00 | 0D | 53 | 68 | 6F | 72 | 74 | 20 | 4D | 65 | 73 |
| | 73 | 61 | 67 | 65 | | | | | | | | |

ENVELOPE: SMS-PP DOWNLOAD 1.2.2 / 1.3.2

Logically:

SMS-PP Download
- Device identities
  - Source device: Network
  - Destination device: UICC

Address
TON International number
NPI "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-DELIVER
TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains only the short message
TP-SRI A status report will not be returned to the SME
TP-OA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "1234"
TP-PID (U)SIM Data download
TP-DCS
Coding Group General Data Coding
Compression Text is uncompressed
Message Class Class 2 (U)SIM Specific Message
Alphabet 8 bit data
TP-SCTS: 01/01/98 00:00:00 +0
TP-UDL 13
TP-UD "Short Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D1 | 2D | 82 | 02 | 83 | 81 | 06 | 09 | 91 | 11 | 22 | 33 |
| | 44 | 55 | 66 | 77 | F8 | 8B | 1C | 04 | 04 | 91 | 21 | 43 |
| | 7F | 16 | 89 | 10 | 10 | 00 | 00 | 00 | 00 | 0D | 53 | 68 |
| | 6F | 72 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | |

**Expected Sequence 1.5 (void)**

**Expected Sequence 1.6 (SMS-PP Data Download, with Data Coding / Message Class)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | SMS-PP Data Download Message 1.6.1 | |
| 2 | ME | The ME shall not display the message or alert the user of a short message waiting | |
| 3 | ME → UICC | ENVELOPE: SMS-PP DOWNLOAD 1.6.2 | |
| 4 | UICC → ME | SW1 / SW2 of '90 00' | |
| 5 | ME → USS | RP-ACK | |

SMS-PP (Data Download) Message 1.6.1

Logically:

SMS TPDU
TP-MTI SMS-DELIVER
TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains only the short message
TP-SRI A status report will not be returned to the SME
TP-OA
TON International number

NPI "ISDN / telephone numbering plan"
Address value "1234"
TP-PID (U)SIM Data download
TP-DCS
Coding Group Data Coding / Message Class
Message Coding 8 bit data
Message Class Class 2 (U)SIM Specific Message
TP-SCTS: 01/01/98 00:00:00 +0
TP-UDL 13
TP-UD "Short Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 04 | 04 | 91 | 21 | 43 | 7F | F6 | 89 | 10 | 10 | 00 | 00 |
| | 00 | 00 | 0D | 53 | 68 | 6F | 72 | 74 | 20 | 4D | 65 | 73 |
| | 73 | 61 | 67 | 65 | | | | | | | | |

ENVELOPE: SMS-PP DOWNLOAD 1.6.2

Logically:

SMS-PP Download
Device identities
Source device: Network
Destination device: UICC
Address
TON International number
NPI "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-DELIVER
TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains only the short message
TP-SRI A status report will not be returned to the SME
TP-OA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "1234"
TP-PID (U)SIM Data download
TP-DCS
Coding Group Data Coding / Message Class
Message Coding 8 bit data
Message Class Class 2 (U)SIM Specific Message
TP-SCTS: 01/01/98 00:00:00 +0
TP-UDL 13
TP-UD "Short Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D1 | 2D | 82 | 02 | 83 | 81 | 06 | 09 | 91 | 11 | 22 | 33 |
| | 44 | 55 | 66 | 77 | F8 | 8B | 1C | 04 | 04 | 91 | 21 | 43 |
| | 7F | F6 | 89 | 10 | 10 | 00 | 00 | 00 | 00 | 0D | 53 | 68 |
| | 6F | 72 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | |

**Expected Sequence 1.7 (SMS-PP Data Download error)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | SMS-PP Data Download Message 1.2.1 | |
| 2 | ME → USER | The ME shall not display the message or alert the user of a short message waiting. | |
| 3 | ME → UICC | ENVELOPE: SMS-PP DOWNLOAD 1.2.2 | [SW1 / SW2 of '62 xx" or "63 xx"] |
| 4 | UICC → ME | SMS-PP Data Download UICC Acknowledgement 1.2.4 | |
| 5 | ME → UICC | Retrieve RP-Error information provided by the USIM | |
| 6 | ME → USS | SMS-PP Data Download UICC Acknowledgement 1.2.4 in the TP-User-Data element of the RP-ERROR message. The values of protocol identifier and data coding scheme in RP-ERROR shall be as in the original message. | |

SMS-PP Data Download UICC Acknowledgement 1.2.4

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 50 | 68 | 69 | 6C | 20 | 48 | 6F | 6F | 6B | 65 | 72 |

**Expected Sequence 1.8 (SMS-PP Data Download, General Data Coding, User Data Header payload)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | SMS-PP Data Download Message 1.8.1 | |
| 2 | ME | The ME shall not display the message or alert the user of a short message waiting | |
| 3 | ME → UICC | ENVELOPE: SMS-PP DOWNLOAD 1.8.2 | |
| 4 | UICC → ME | SW1 / SW2 of '90 00' | |
| 5 | ME → USS | RP-ACK | |

SMS-PP (Data Download) Message 1.8.1

Logically:

SMS TPDU

| | |
|---|---|
| TP-MTI | SMS-DELIVER |
| TP-MMS | No more messages waiting for the MS in this SC |
| TP-RP | TP-Reply-Path is not set in this SMS-DELIVER |
| TP-UDHI | TP-UD field contains user data header and a short message |
| TP-SRI | A status report will not be returned to the SME |
| TP-OA | |
| TON | International number |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "1234" |
| TP-PID | (U)SIM Data download |
| TP-DCS | |
| Coding Group | Data Coding / Message Class |
| Message Coding | 8 bit data |
| Message Class | Class 2 (U)SIM Specific Message |
| TP-SCTS: | 01/01/98 00:00:00 +0 |

TP-UDL 30
TP-UD
TP-UDHL 2
IEI (U)SIM Toolkit Security Headers
IEIL 0
SM (8 bit data)
Command Packet Length: 25
Command Header Identifier: 0
Command Header Length: 13
Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity
Ciphering Key Identifier: Algorithm known implicitly by both entities
Key Identifier: Algorithm known implicitly by both entities
Toolkit Application Reference: Proprietary Toolkit Application
Counter: 1
Padding Counter: 0 (no padding is necessary)
Secure Data: 10 octets set to 'DC' (dummy data)

Coding:

| Coding | 44 | 04 | 91 | 21 | 43 | 7F | F6 | 89 | 10 | 10 | 00 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 00 | 1E | 02 | 70 | 00 | 00 | 19 | 00 | 0D | 00 | 00 |
| | 00 | 00 | BF | FF | 00 | 00 | 00 | 00 | 00 | 01 | 00 | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | | | |

ENVELOPE: SMS-PP DOWNLOAD 1.8.2

Logically:

SMS-PP Download
Device identities
Source device: Network
Destination device: UICC
Address
TON International number
NPI "ISDN / telephone numbering plan"
Dialling number string "112233445566778"
SMS TPDU
TP-MTI SMS-DELIVER
TP-MMS No more messages waiting for the MS in this SC
TP-RP TP-Reply-Path is not set in this SMS-DELIVER
TP-UDHI TP-UD field contains user data header and a short message
TP-SRI A status report will not be returned to the SME
TP-OA
TON International number
NPI "ISDN / telephone numbering plan"
Address value "1234"
TP-PID (U)SIM Data download
TP-DCS
Coding Group Data Coding / Message Class
Message Coding 8 bit data
Message Class Class 2 (U)SIM Specific Message
TP-SCTS: 01/01/98 00:00:00 +0
TP-UDL 30
TP-UD
TP-UDHL 2
IEI (U)SIM Toolkit Security Headers
IEIL 0

SM (8 bit data)
Command Packet Length: 25
Command Header Identifier: 0
Command Header Length: 13
Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity
Ciphering Key Identifier: Algorithm known implicitly by both entities
Key Identifier: Algorithm known implicitly by both entities
Toolkit Application Reference: Proprietary Toolkit Application
Counter: 1
Padding Counter: 0 (no padding is necessary)
Secure Data: 10 octets set to 'DC' (dummy data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D1 | 3E | 82 | 02 | 83 | 81 | 06 | 09 | 91 | 11 | 22 | 33 |
| | 44 | 55 | 66 | 77 | F8 | 8B | 2D | 44 | 04 | 91 | 21 | 43 |
| | 7F | F6 | 89 | 10 | 10 | 00 | 00 | 00 | 00 | 1E | 02 | 70 |
| | 00 | 00 | 19 | 00 | 0D | 00 | 00 | 00 | 00 | BF | FF | 00 |
| | 00 | 00 | 00 | 00 | 01 | 00 | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | | | | | | | | |

#### 27.22.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.2 to 1.8.

### 27.22.5.2 Cell Broadcast Data Download

#### 27.22.5.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.5.2.2 Conformance requirement

The ME shall support the Proactive UICC: Cell Broadcast Data Download facility as defined in:

- TS 31.111 [15] clause 5, clause 7.1.2, clause 8.5, clause 8.7 and clause 11.
- TS 31.115 [28] clause 5.
- TS 23.038 [7] clause 5.

#### 27.22.5.2.3 Test purpose

To verify that the ME transparently passes the "data download via Cell Broadcast" messages to the UICC, which contain a message identifier found in $EF_{CBMID}$.

#### 27.22.5.2.4 Method of Test

##### 27.22.5.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.The elementary files are coded as Toolkit default with the following exeception:

EF PL shall contain an entry indicating "English".

A USS setting up only a GERAN or PCS 1900 cell shall be used for Expected sequence 1.1, 1.7 and 1.3.

A USS setting up only a UTRAN cell shall be used on and expected sequence 1.4, 1.5 and 1.6.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

27.22.5.2.4.2 Procedure

**Expected Sequence 1.1 (Cell Broadcast Data Download (GSM), ENVELOPE(CELL BROADCAST DOWNLOAD), ME does not display message)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | CELL BROADCAST 1.1 | Message identifier '10 01' |
| 2 | ME → UICC | ENVELOPE (CELL BROADCAST DOWNLOAD) 1.1 | |
| 3 | UICC → ME | SW1, SW2 '90 00' | |

Cell Broadcast Message 1.1

Logically:

Message Content
- Serial Number
- Geographical scope: Cell wide, normal display mode
- Message code: 1
- Update number: 1
- Message Identifier: "1001"
- Data coding Scheme
- Message Coding: English, language using the GSM 7 bit default alphabet
- Page Parameter
- Total number of pages: 1
- Page number: 1
- Content of message: "Cell Broadcast "..

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | C0 | 11 | 10 | 01 | 01 | 11 | C3 | 32 | 9B | 0D | 12 | CA |
| | DF | 61 | F2 | 38 | 3C | A7 | 83 | 40 | 20 | 10 | 08 | 04 |
| | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 |
| | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 |
| | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 |
| | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 |
| | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 |
| | 10 | 08 | 04 | 02 | | | | | | | | |

ENVELOPE: CELL BROADCAST DOWNLOAD 1.1

Logically:

Cell Broadcast Download
- Device identities
- Source device: Network
- Destination device: UICC

Cell Broadcast page
- Serial Number

Geographical scope: Cell wide, normal display mode
Message code: 1
Update number: 1
Message Identifier: "1001"
Data coding Scheme
Message Coding: English, language using the GSM 7 bit default alphabet
Page Parameter
Number of pages: 1
Page number: 1
Content of message: "Cell Broadcast "..

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D2 | 5E | 82 | 02 | 83 | 81 | 8C | 58 | C0 | 11 | 10 | 01 |
| | 01 | 11 | C3 | 32 | 9B | 0D | 12 | CA | DF | 61 | F2 | 38 |
| | 3C | A7 | 83 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 |
| | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 |
| | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 |
| | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 |
| | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 |
| | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 |

**Expected Sequence 1.2 (void)**

**Expected Sequence 1.3 (Cell Broadcast (GSM), ME may display the message)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | CELL BROADCAST 1.2 | Message identifier '03 E7' |
| 2a | ME → USER | ME may display the message | |
| 2b | ME → UICC | ME shall not download the CB message to the UICC using ENVELOPE (CELL BROADCAST DOWNLOAD) | |
| 3 | USER → ME | The user shall use a MMI dependent procedure to initiate the display of the received CB message | [only if message has not been displayed in step 2a] |
| 4 | ME → USER | ME displays the message | [only if message has not been displayed in step 2a] |

Cell Broadcast Message 1.2

Logically:

Message Content
Serial Number
Geographical scope: Cell wide, normal display mode
Message code: 1
Update number: 1
Message Identifier: "03E7"
Data coding Scheme
Message Coding: English, language using the GSM 7 bit default alphabet
Page Parameter
Total number of pages: 1
Page number: 1
Content of message: "Cell Broadcast".

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | C0 | 11 | 03 | E7 | 01 | 11 | C3 | 32 | 9B | 0D | 12 | CA |
| | DF | 61 | F2 | 38 | 3C | A7 | 83 | 40 | 20 | 10 | 08 | 04 |
| | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 |
| | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 |
| | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 |
| | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 | 10 | 08 |
| | 04 | 02 | 81 | 40 | 20 | 10 | 08 | 04 | 02 | 81 | 40 | 20 |
| | 10 | 08 | 04 | 02 | | | | | | | | |

### Expected Sequence 1.4 ( Cell Broadcast (UMTS), ENVELOPE (CELL BROADCAST DOWNLOAD), ME does not display message)

TBD

### Expected Sequence 1.5 ( Cell Broadcast (UMTS), ENVELOPE (CELL BROADCAST DOWNLOAD), FETCH, MORE TIME, ME does not display message)

TBD

### Expected Sequence 1.6 (Cell Broadcast (UMTS), ME displays message)

TBD

### Expected Sequence 1.7 (Cell Broadcast (GSM),, ENVELOPE(CELL BROADCAST DATA DOWNLOAD), FETCH, MORE TIME, ME does not display message, User Data Header Payload)

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | USS → ME | CELL BROADCAST Message 1.7 | Message identifier '10 01' |
| 2 | ME → UICC | ENVELOPE (CELL BROADCAST DOWNLOAD) 1.7 | |
| 3 | UICC → ME | PROACTIVE COMMAND PENDING: MORE TIME 1.2 | SW1/SW2 '61 0B' |
| 4 | ME → UICC | FETCH 1.2 | |
| 5 | UICC → ME | PROACTIVE COMMAND:MORE TIME 1.2 | |
| 6 | ME → UICC | TERMINAL RESPONSE: MORE TIME 1.2 | |
| 7 | UICC → ME | SW1/SW2 '90 00' | UICC session ended |

CELL BROADCAST Message 1.7

Logically:

Message Content
- Serial Number
- Geographical scope: Cell wide, normal display mode
- Message code: 1
- Update number: 1
- Message Identifier: "1001"
- Data coding Scheme

Message Coding: 8 bit data
Message class: Class 2 (U)SIM specific message
Page Parameter
Total number of pages: 1
Page number: 1

Secured User Header (Content of message)

TP-UDHL 2
IEI (U)SIM Toolkit Security Headers
IEIL 0
Command Packet Length: 77
Command Header Identifier: 0
Command Header Length: 13
Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity
Ciphering Key Identifier: Algorithm known implicitly by both entities
Key Identifier: Algorithm known implicitly by both entities
Toolkit Application Reference: Proprietary Toolkit Application
Counter: 1
Padding Counter: 0 (no padding is necessary)
Secure Data: 62 octets set to "DC" (dummy data)

Coding:

| Coding | C0 | 11 | 10 | 01 | 96 | 11 | 02 | 70 | 00 | 00 | 4D | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0D | 00 | 00 | 00 | 00 | BF | FF | 00 | 00 | 00 | 00 | 00 |
| | 01 | 00 | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | | | | | | | | |

ENVELOPE: CELL BROADCAST DOWNLOAD 1.7

Logically:

Cell Broadcast Download
Device identities
Source device: Network
Destination device: UICC
Cell Broadcast page
Serial Number
Geographical scope: Cell wide, normal display mode
Message code: 1
Update number: 1
Message Identifier: "1001"
Data coding Scheme
Message Coding: 8 bit data (Message with User Data Header (UDH) structure)
Message class: Class 2 (U)SIM specific message
Page Parameter
Number of pages: 1
Page number: 1

Secured User Header (Content of message)

TP-UDHL 2
IEI (U)SIM Toolkit Security Headers
IEIL 0

Command Packet Length: 77
Command Header Identifier: 0
Command Header Length: 13
Security Parameter Indicator: No RC, CC or DS and No PoR reply to the Sending Entity
Ciphering Key Identifier: Algorithm known implicitly by both entities
Key Identifier: Algorithm known implicitly by both entities
Toolkit Application Reference: Proprietary Toolkit Application
Counter: 1
Padding Counter: 0 (no padding is necessary)
Secure Data: 62 octets set to "DC" (dummy data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D2 | 5E | 82 | 02 | 83 | 81 | 8C | 58 | C0 | 11 | 10 | 01 |
| | 96 | 11 | 02 | 70 | 00 | 00 | 4D | 00 | 0D | 00 | 00 | 00 |
| | 00 | BF | FF | 00 | 00 | 00 | 00 | 00 | 01 | 00 | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |
| | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC | DC |

PROACTIVE COMMAND: MORE TIME 1.2

Logically:

Command details
Command number: 1
Command type: MORE TIME
Command qualifier: "00"
Device identities
Source device: UICC
Destination device: ME

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 09 | 81 | 03 | 01 | 02 | 00 | 82 | 02 | 81 | 82 |

TERMINAL RESPONSE: MORE TIME 1.2

Logically:

Command details
Command number: 1
Command type: MORE TIME
Command qualifier: "00"
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 02 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

#### 27.22.5.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.7.

## 27.22.6 CALL CONTROL BY USIM

### 27.22.6.1 Procedure for Mobile Originated calls

#### 27.22.6.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.6.1.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in:

- TS 31.111 [15] clause 7.3

#### 27.22.6.1.3 Test purpose

To verify that for all call set-up attempts , even those resulting from a SET UP CALL proactive UICC command, the ME shall first pass the call set-up details (dialled digits and associated parameters) to the UICC, using the ENVELOPE (CALL CONTROL).

To verify that if the UICC responds with '90 00', the ME shall set up the call with the dialled digits and other parameters as sent to the UICC.

To verify that if the UICC returns response data, the ME shall use the response data appropriately to set up the call as proposed, not set up the call, or set up a call using the data supplied by the UICC.

To verify that, in the case where the initial call set-up request results from a proactive SET UP CALL, if the call control result is "not allowed" or "allowed with modifications", the ME shall inform the UICC using TERMINAL RESPONSE "interaction with call control by UICC or MO short message control by UICC, action not allowed".

To verify that it is possible for the UICC to request the ME to set up an emergency call by supplying the number "112" as the response data.

#### 27.22.6.1.4 Method of tests

##### 27.22.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and USS and has performed the location update procedure.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;

- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as USIM Application Toolkit default with the following exception:

The call control service is available in the USIM Service Table.

27.22.6.1.4.2 Procedure

**Expected Sequence 1.1 (CALL CONTROL BY USIM , set up call attempt by user, the USIM responds with '90 00')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.1.1A<br>Or<br>ENVELOPE CALL CONTROL 1.1.1B | [Option A shall apply for 3GPP parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | 90 00 | |
| 4 | ME → USS | The ME sets up the call without modification | [Set up call to "+01234567890123456789" |

ENVELOPE CALL CONTROL 1.1.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "01234567890123456789"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC the mobile country and network code (00F110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)
- Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | Note 5 | 07 | 00 |
| | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | |

ENVELOPE CALL CONTROL 1.1.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "01234567890123456789"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | 07 | 00 |
| | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | | | | | |

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

**Expected Sequence 1.2 (CALL CONTROL BY USIM , set up call attempt by user, allowed without modification)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.2.1 A<br>or<br>ENVELOPE CALL CONTROL 1.2.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.2.1 | [Call control result: "Allowed, no modification"] |
| 4 | ME → USS | The ME sets up the call without modification | [Set up call to "+01234567890123456789"] |

ENVELOPE CALL CONTROL 1.2.1A

Logically:

Device identities
Source device: ME
Destination device: UICC

Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "01234567890123456789"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | Note 5 | 00 |
| | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | |

ENVELOPE CALL CONTROL 1.2.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "01234567890123456789"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | 07 | 00 |
| | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | | | | | |

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

CALL CONTROL RESULT 1.2.1

Logically:

Call control result : '00' = Allowed, no modification

Coding:

| | | |
|---|---|---|
| BER-TLV: | 00 | 00 |

**Expected Sequence 1.3A (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, allowed without modification)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.3.1 PENDING | [This test applies to MEs asking for user confirmation before sending the ENVELOPE CALL CONTROL command] |
| 2 | ME→UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.3.1 | [Set up call to "+012340123456"] |
| 4 | ME → USER | ME displays "+012340123456" during user confirmation phase. | |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 1.3.1A<br>or<br>ENVELOPE CALL CONTROL 1.3.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 7 | UICC → ME | CALL CONTROL RESULT 1.3.1 | [Call control result: "Allowed, no modification"] |
| 8 | ME → USS | The ME sets up the call without modification | [Set up call to "+012340123456"] |
| 9 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 1.3.1 | [command performed successfully] |

**Expected Sequence 1.3 B (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, allowed without modification)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.3.1 PENDING | [This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command] |
| 2 | ME→UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.3.1 | [Set up call to "+012340123456"] |
| 4 | ME → UICC | ENVELOPE CALL CONTROL 1.3.1A<br>or<br>ENVELOPE CALL CONTROL 1.3.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 5 | UICC → ME | CALL CONTROL RESULT 1.3.1 | [Call control result: "Allowed, no modification"] |
| 6 | ME → USER | ME displays "+012340123456" during user confirmation phase. | |
| 7 | USER → ME | The user confirms the call set up | [user confirmation] |
| 8 | ME → USS | The ME sets up the call without modification | [Set up call to "+012340123456"] |
| 9 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 1.3.1 | [command performed successfully] |

PROACTIVE COMMAND: SET UP CALL 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: Only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "+012340123456"

Address
- TON: International
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "012340123456"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 21 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 |
| | 05 | 0D | 2B | 30 | 31 | 32 | 33 | 34 | 30 | 31 | 32 |
| | 33 | 34 | 35 | 36 | 86 | 07 | 91 | 10 | 32 | 04 | 21 |
| | 43 | 65 | | | | | | | | | |

ENVELOPE CALL CONTROL 1.3.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "012340123456"

Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 02 | 02 | 82 | 81 | 06 | 07 | 91 | 10 | 32 |
| | 04 | 21 | 43 | 65 | Note 2 | Note 3 | 13 | Note 5 | 00 | F1 | 10 |
| | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | | |

ENVELOPE CALL CONTROL 1.3.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "012340123456"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 02 | 02 | 82 | 81 | 06 | 07 | 91 | 10 | 32 |
| | 04 | 21 | 43 | 65 | Note 2 | Note 3 | 13 | 07 | 00 | 11 | 10 |
| | 00 | 01 | 00 | 01 | Note 4 | | | | | | |

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

CALL CONTROL RESULT 1.3.1

Logically:

Call control result : '00' = Allowed, no modification

Coding:

| | | |
|---|---|---|
| BER-TLV: | 00 | 00 |

TERMINAL RESPONSE: SET UP CALL 1.3.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: Only if not currently busy on another call

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.4 (CALL CONTROL BY USIM , set up call attempt by user, not allowed)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.4.1 A<br>or<br>ENVELOPE CALL CONTROL 1.4.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.4.1 | [Call control result: "not Allowed"] |
| 4 | ME → USS | The ME does not set up the call | |

ENVELOPE CALL CONTROL 1.4.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "+01234567890123456789"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | Note 5 | 00 |
| | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | |

ENVELOPE CALL CONTROL 1.4.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "+01234567890123456789"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | 07 | 00 |
| | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | | | | | |

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

CALL CONTROL RESULT 1.4.1

Logically:

Call control result: '01' = not Allowed

Coding:

| | | |
|---|---|---|
| BER-TLV: | 01 | 00 |

**Expected Sequence 1.5A (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, not allowed)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.5.1 PENDING | [This test applies to MEs asking for user confirmation before sending the ENVELOPE CALL CONTROL command] |
| 2 | ME→UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.5.1 | [Set up call to "+012340123456" |
| 4 | ME → USER | ME displays "+012340123456" during user confirmation phase. | |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 1.5.1A<br>or<br>ENVELOPE CALL CONTROL 1.5.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 7 | UICC → ME | CALL CONTROL RESULT 1.5.1 | [Call control result: "Not Allowed"] |
| 8 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 1.5.1 | [Permanent Problem - Interaction with Call Control by USIM] |
| 9 | ME → USS | The ME does not set up the call | |

**Expected Sequence 1.5 B (CALL CONTROL BY USIM , set up call attempt resulting from a set up call proactive command, not allowed)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.5.1 PENDING | [This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command] |
| 2 | ME→UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.5.1 | [Set up call to "+012340123456" |
| 4 | ME → UICC | ENVELOPE CALL CONTROL 1.5.1A<br>or<br>ENVELOPE CALL CONTROL 1.5.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 5 | UICC → ME | CALL CONTROL RESULT 1.5.1 | [Call control result: "Not Allowed"]<br>[No user confirmation phase because Call Control has disallowed the request] |
| 6 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 1.5.1 | [Permanent Problem - Interaction with Call Control by USIM] |
| 7 | ME → USS | The ME does not set up the call | |

PROACTIVE COMMAND: SET UP CALL 1.5.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: Only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: "+012340123456"
Address
TON: International
NPI: "ISDN / telephone numbering plan"
Dialling number string "012340123456"

Coding:

| BER-TLV: | D0 | 21 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 05 | 0D | 2B | 30 | 31 | 32 | 33 | 34 | 30 | 31 | 32 |
| | 33 | 34 | 35 | 36 | 86 | 07 | 91 | 10 | 32 | 04 | 21 |
| | 43 | 65 | | | | | | | | | |

ENVELOPE CALL CONTROL 1.5.1A

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "012340123456"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| BER-TLV: | D4 | Note 1 | 02 | 02 | 82 | 81 | 06 | 07 | 91 | 10 | 32 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 04 | 21 | 43 | 65 | Note 2 | Note 3 | 13 | Note 5 | 00 | F1 | 10 |
| | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | | |

ENVELOPE CALL CONTROL 1.5.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "012340123456"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.

Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 02 | 02 | 82 | 81 | 06 | 07 | 91 | 10 | 32 |
| | 04 | 21 | 43 | 65 | Note 2 | Note 3 | 13 | 07 | 00 | 11 | 10 |
| | 00 | 01 | 00 | 01 | Note 4 | | | | | | |

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

CALL CONTROL RESULT 1.5.1

Logically:

Call control result: '01' = not Allowed

Coding:

| | | |
|---|---|---|
| BER-TLV: | 01 | 00 |

TERMINAL RESPONSE: SET UP CALL 1.5.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: Only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Interaction with call control by USIM or MO short message control by USIM, permanent problem
Additional information: Action not allowed

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 39 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | | | | | | | | | | | |

**Expected Sequence 1.6 (CALL CONTROL BY USIM , set up call attempt by user, allowed with modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.6.1 A<br>or<br>ENVELOPE CALL CONTROL 1.6.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.6.1 | [Call control result: "Allowed with modifications", ] |
| 4 | ME → USS | The ME sets up the call to "+010203" | |

ENVELOPE CALL CONTROL 1.6.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "01234567890123456789"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC the mobile country and network code (00F110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)
- Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | Note 5 | 00 |
| | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | |

ENVELOPE CALL CONTROL 1.6.1B

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "01234567890123456789"

Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | 07 | 00 |
| | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | | | | | |

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 1.6.1

Logically:

Call control result: '02' = Allowed with modifications
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "010203"

Coding:

| | | | | | | | | |
|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 06 | 86 | 04 | 91 | 10 | 20 | 30 |

**Expected Sequence 1.7A (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed with modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.7.1 PENDING | [This test applies to MEs asking for user confirmation before sending the ENVELOPE CALL CONTROL command] |
| 2 | ME→UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.7.1 | [Set up call to "+012340123456"] |
| 4 | ME → USER | ME displays "+012340123456" during user confirmation phase. | |
| 5 | USER → ME | The user confirms the call set up | [user confirmation] |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 1.7.1A<br>or<br>ENVELOPE CALL CONTROL 1.7.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 7 | UICC → ME | CALL CONTROL RESULT 1.7.1 | [Call control result: "Allowed with modifications"] |
| 8 | ME → USS | The ME sets up the call to "+011111111111" | |
| 9 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 1.7.1 | [command performed successfully] |

**Expected Sequence 1.7 B (CALL CONTROL BY USIM, set up call attempt resulting from a set up call proactive command, allowed with modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.7.1 PENDING | [This test applies to MEs asking for user confirmation after sending the ENVELOPE CALL CONTROL command] |
| 2 | ME→UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 1.7.1 | [Set up call to "+012340123456"] |
| 4 | ME → UICC | ENVELOPE CALL CONTROL 1.7.1A<br>or<br>ENVELOPE CALL CONTROL 1.7.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 5 | UICC → ME | CALL CONTROL RESULT 1.7.1 | [Call control result: "Allowed with modifications"] |
| 6 | ME → USER | ME displays "+012340123456" during user confirmation phase. | |
| 7 | USER → ME | The user confirms the call set up | [user confirmation] |
| 8 | ME → USS | The ME sets up the call to "+011111111111" | [call is set up to modified address] |
| 9 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 1.7.1 | [command performed successfully] |

PROACTIVE COMMAND: SET UP CALL 1.7.1

Logically:

Command details
- Command number: 1
- Command type: SET UP CALL
- Command qualifier: Only if not currently busy on another call

Device identities
- Source device: UICC
- Destination device: Network

Alpha identifier: '+012340123456"

Address
- TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "012340123456"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 21 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 |
| | 05 | 0D | 2B | 30 | 31 | 32 | 33 | 34 | 30 | 31 | 32 |
| | 33 | 34 | 35 | 36 | 86 | 07 | 91 | 10 | 32 | 04 | 21 |
| | 43 | 65 | | | | | | | | | |

ENVELOPE CALL CONTROL 1.7.1A

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "012340123456"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 02 | 02 | 82 | 81 | 06 | 07 | 91 | 10 | 32 |
| | 04 | 21 | 43 | 65 | Note 2 | Note 3 | 13 | Note 5 | 00 | F1 | 10 |
| | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | | |

ENVELOPE CALL CONTROL 1.7.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "012340123456"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information

MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 02 | 02 | 82 | 81 | 06 | 07 | 91 | 10 | 32 |
| | 04 | 21 | 43 | 65 | Note 2 | Note 3 | 13 | 07 | 00 | 11 | 10 |
| | 00 | 01 | 00 | 01 | Note 4 | | | | | | |

Note 1: Length of BER-TLV is '16' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 1.7.1

Logically:

Call control result: '02' = Allowed with modifications
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "011111111111"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 09 | 86 | 07 | 91 | 10 | 11 | 11 | 11 | 11 | 11 |

TERMINAL RESPONSE: SET UP CALL 1.7.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: Only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.8 (CALL CONTROL BY USIM , set up call attempt by user, allowed with modifications: emergency call)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.8.1A or ENVELOPE CALL CONTROL 1.8.1B | [Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters |
| 3 | UICC → ME | CALL CONTROL RESULT 1.8.1 | [Call control result: "Allowed with modifications"] |
| 4 | ME → USS | The ME sets up an emergency call; | |

ENVELOPE CALL CONTROL 1.8.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "01234567890123456789"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC the mobile country and network code (00F110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)
- Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | Note 5 | 00 |
| | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | |

ENVELOPE CALL CONTROL 1.8.1B

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string "01234567890123456789"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information

MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | 07 | 00 |
| | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | | | | | |

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 1.8.1

Logically:

Call control result Allowed, with modification
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Address value "112"

Coding:

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 05 | 86 | 03 | 81 | 11 | F2 |

**Expected Sequence 1.9 (CALL CONTROL BY USIM , set up call attempt by user, allowed with modifications: number in $EF_{ECC}$)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.9.1A or ENVELOPE CALL CONTROL 1.9.1B | [Option A shall apply for GERAN/UTRAN parameters] [Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.9.1 | [Call control result: "Allowed with modifications"] |
| 4 | ME → USS | The ME sets up call with the dialled digits "1020". The ME does not set up an emergency call, but stes up a normal call | |

ENVELOPE CALL CONTROL 1.9.1A

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "01234567890123456789"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | Note 5 | 00 |
| | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 | | | | |

ENVELOPE CALL CONTROL 1.9.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string "01234567890123456789"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 0B | 91 | 10 | 32 | 54 |
| | 76 | 98 | 10 | 32 | 54 | 76 | 98 | Note 2 | Note 3 | 13 | 07 | 00 |
| | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | | | | | |

Note 1: Length of BER-TLV is '1A' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 1.9.1

Logically:

| | |
|---|---|
| Call control result | Allowed, with modification |
| Address | |
| TON | Unknown |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "1020" |

Coding:

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 05 | 86 | 03 | 81 | 01 | 02 |

**Expected Sequence 1.10 (CALL CONTROL BY USIM , set up call attempt by user to an emergency call)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "112" | |
| 2 | ME → UICC | The ME does not send any ENVELOPE CALL CONTROL | |
| 3 | ME → USS | The ME sets up an emergency call | |

**Expected Sequence 1.11 (CALL CONTROL BY USIM , set up call through call register, the USIM responds with '90 00')**

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed by call control in its register.

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.1.1A<br>or<br>ENVELOPE CALL CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | 90 00 | |
| 4 | ME → USS | The ME sets up the call without modification | [Set up call to "+01234567890123456789"] |
| 5 | USER → ME | End Call. | |
| 6 | USER → ME | Recall the last dialled number | |
| 7 | ME → UICC | ENVELOPE CALL CONTROL 1.1.1A<br>or<br>ENVELOPE CALL CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 8 | UICC → ME | 90 00 | |
| 9 | ME → USS | The ME sets up the call without modification | [Set up call to "+01234567890123456789"] |
| 10 | USER → ME | End Call. | |

### Expected Sequence 1.12 (CALL CONTROL BY USIM , set up call through call register, allowed without modification)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed by call control in its register.

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.2.1A<br>or<br>ENVELOPE CALL CONTROL 1.2.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.2.1 | [Call control result: "Allowed, no modification"] |
| 4 | ME → USS | The ME sets up the call without modification | [Set up call to "+0123456789012345678 9"] |
| 5 | User → ME | End the call then call the last dialled number | |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 1.2.1A<br>or<br>ENVELOPE CALL CONTROL 1.2.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 7 | UICC → ME | CALL CONTROL RESULT 1.2.1 | |
| 8 | ME → USS | The ME sets up the call without modification | [Set up call to "+0123456789012345678 9"] |

### Expected Sequence 1.13 (CALL CONTROL BY USIM , set up call through call register, not allowed)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers not allowed by call control in its register.

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.4.1A<br>or<br>ENVELOPE CALL CONTROL 1.4.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.4.1 | [Call control result: "not Allowed"] |
| 4 | ME → USS | The ME does not set up the call | |
| 5 | User → ME | The user calls the last dialled number | |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 1.4.1A<br>or<br>ENVELOPE CALL CONTROL 1.4.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 7 | UICC → ME | CALL CONTROL RESULT 1.4.1 | [Call control result: "not Allowed"] |
| 8 | ME → USS | The ME does not set up the call | |

### Expected Sequence 1.14 (CALL CONTROL BY USIM , set up call through call register, allowed with modifications)

Pre-condition: the ME has a mean to register the last dialled number(s), and the ME will store dialled numbers allowed with modification by call control in its register.

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | Set up a call to "+01234567890123456789" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 1.6.1A<br>or<br>ENVELOPE CALL CONTROL 1.6.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 1.6.1 | [Call control result: "Allowed with modifications"] |
| 4 | ME → USS | The ME sets up the call to "+010203" | |
| 5 | User → ME | End call and then set up a call to "+01234567890123456789" | |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 1.6.1A<br>or<br>ENVELOPE CALL CONTROL 1.6.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 7 | UICC → ME | CALL CONTROL RESULT 1.6.1 | [Call control result: "Allowed with modifications"] |
| 8 | ME → USS | The ME sets up the call to "+010203" | |

#### 27.22.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.14.

### 27.22.6.2 Procedure for Supplementary (SS) Services

#### 27.22.6.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.6.2.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in the following technical specifications:

- TS 31.111 [15] clause 7.3.1.2.

#### 27.22.6.2.3 Test purpose

To verify that the ME first pass the supplementary service control string corresponding to the supplementary service operation to the USIM, using the ENVELOPE (CALL CONTROL) command.

To verify that, if the UICC responds with '90 00', the ME shall send the supplementary service operation with the information as sent to the UICC.

To verify that, if the UICC returns response data, the ME shall use the response data appropriately to send the supplementary service operation as proposed, not send the SS operation, or instead send the USS operation using the data supplied by the UICC.

#### 27.22.6.2.4 Method of tests

##### 27.22.6.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as USIM Application Toolkit default with the following exception:

The call control service is available in the USIM Service Table.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

27.22.6.2.4.2 Procedure

**Expected Sequence 2.1 (CALL CONTROL BY USIM , send SS, the USIM responds with '90 00')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator). | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 2.1.1A<br>or<br>ENVELOPE CALL CONTROL 2.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | 90 00 | |
| 4 | ME → USS | REGISTER 2.1 | [The ME sends the supplementary service operation with the information as sent to the UICC] |
| 5 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | |

ENVELOPE CALL CONTROL 2.1.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

SS String
- TON/NPI: "FF"
- Dialling number string "*21**10#"

Location Information
- MCC & MNC the mobile country and network code (00F110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)
- Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

| BER-TLV: | D4 | Note1 | 82 | 02 | 82 | 81 | 89 | 05 | FF | 2A | A1 | 1A |
|---|---|---|---|---|---|---|---|---|---|---|---|---|

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B0 | 13 | Note 2 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 3 | |

Note 1: Length of BER-TLV is '14' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 2.1.1B

Logically:

Device identities
- Source device: ME
- Destination device: UICC

SS String
- TON/NPI: "FF"
- Dialling number string "*21**10#"

Location Information
- MCC & MNC the mobile country and network code (001110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | 14 | 82 | 02 | 82 | 81 | 89 | 05 | FF | 2A | A1 | 1A |
| | B0 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | | |

REGISTER 2.1

Logically (only SS argument):

ACTIVATE SS ARGUMENT
- SS-Code:
- Call Forwarding Unconditional
- TeleserviceCode
  - All Tele Services

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 30 | 06 | 04 | 01 | 21 | 83 | 01 | 00 | | | | |

RELEASE COMPLETE (SS RETURN RESULT) 2.1

Logically (only from operation code):

ACTIVATE SS RETURN RESULT
- ForwardingInfo
- SS-Code
- Call Forwarding Unconditional
- ForwardFeatureList
- ForwardingFeature
- TeleserviceCode
- All Tele Services
- SS-Status
- state ind.: operative
- provision ind.: provisioned

- registration ind.: registered
- activation ind.: active

Coding:

| Coding | 0C | A0 | 0D | 04 | 01 | 21 | 30 | 08 | 30 | 06 | 83 | 01 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 00 | 84 | 01 | 07 | | | | | | | | |

**Expected Sequence 2.2 (CALL CONTROL BY USIM , send SS, allowed without modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator). | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 2.2.1A<br>or<br>ENVELOPE CALL CONTROL 2.2.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 2.2.1 | [Call control result: "Allowed without modifications"] |
| 4 | ME → USS | REGISTER 2.1 | The ME sends the supplementary service operation with the information as sent to the UICC |
| 5 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.1 | |

ENVELOPE CALL CONTROL 2.2.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

SS String
- TON/NPI: "FF"
- Dialling number string "*21**10#"

Location Information
- MCC & MNC the mobile country and network code (00F110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)
- Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 89 | 05 | FF | 2A | A1 | 1A |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B0 | 13 | Note 2 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 3 | |

Note 1: Length of BER-TLV is '14' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 2.2.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
SS String
TON/NPI: "FF"
Dialling number string "*21**10#"
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | 14 | 82 | 02 | 82 | 81 | 89 | 05 | FF | 2A | A1 | 1A |
| | B0 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | | |

CALL CONTROL RESULT 2.2.1

Logically:

Call control result Allowed, no modifications

Coding:

| | | |
|---|---|---|
| BER-TLV: | 00 | 00 |

**Expected Sequence 2.3 (CALL CONTROL BY USIM , send SS, not allowed)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator). | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 2.3.1A<br>or<br>ENVELOPE CALL CONTROL 2.3.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 2.3.1 | [Call control result: "Not Allowed"] |
| 4 | ME → USS | The ME does not send the supplementary service operation | |

ENVELOPE CALL CONTROL 2.3.1A

Logically:

Device identities
Source device: ME
Destination device: UICC
SS String
TON/NPI: "FF"
Dialling number string "*21#"
Location Information
MCC & MNC the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 89 | 03 | FF | 2A | B1 | 13 |
| | Note 2 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 3 | | | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 2.3.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
SS String
TON/NPI: "FF"
Dialling number string "*21#"
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | 12 | 82 | 02 | 82 | 81 | 89 | 03 | FF | 2A | B1 | 13 |
| | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | | | | |

CALL CONTROL RESULT 2.3.1

Logically:

Call control result Not Allowed

Coding:

| | | |
|---|---|---|
| BER-TLV: | 01 | 00 |

**Expected Sequence 2.4 (CALL CONTROL BY USIM , send SS, allowed with modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user selects the facility of the ME which requires an unconditional call forward supplementary service operation to be sent to the network (System Simulator). | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 2.4.1A<br>or<br>ENVELOPE CALL CONTROL 2.4.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 2.4.1 | [Call control result: "Allowed with modifications"] |
| 4 | ME → USS | REGISTER 2.4 | [The ME sends the supplementary service operation with the information as sent by the UICC] |
| 5 | USS → ME | RELEASE COMPLETE (SS RETURN RESULT) 2.4 | |

ENVELOPE CALL CONTROL 2.4.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

SS String
- TON/NPI: "FF"
- Dialling number string "*21#"

Location Information
- MCC & MNC the mobile country and network code (00F110)
- LAC the location Area Code (0001)
- Cell ID Cell Identity Value (0001)
- Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 89 | 03 | FF | 2A | B1 | 13 |
| | Note 2 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 3 | | | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 2.4.1B

Logically:

Device identities
- Source device: ME
- Destination device: UICC

SS String
- TON/NPI: "FF"
- Dialling number string "*21#"

Location Information
- MCC & MNC the mobile country and network code (001110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | 12 | 82 | 02 | 82 | 81 | 89 | 03 | FF | 2A | B1 | 13 |
| | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | | | | |

CALL CONTROL RESULT 2.4.1

Logically:

Call control result Allowed, with modifications
SS String
TON/NPI "FF"
SS String "*#21#"

Coding:

| | | | | | | | | |
|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 06 | 89 | 04 | FF | BA | 12 | FB |

REGISTER 2.4

Logically (only SS argument):

INTERROGATE SS ARGUMENT
SS-Code
- Call Forwarding Unconditional

Coding:

| | | | | | |
|---|---|---|---|---|---|
| BER-TLV | 30 | 03 | 04 | 01 | 21 |

RELEASE COMPLETE (SS RETURN RESULT) 2.4

Logically (only from operation code):

INTERROGATE SS RESULT
Call Forwarding Unconditional
SS-Status
- state ind.: operative
- provision ind.: provisioned
- registration ind.: registered
- activation ind.: not active

Coding:

| | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | 80 | 01 | 06 | | | | | | |

## 27.22.6.2.5 Test requirement

The ME shall operate in the manner defined in expected sequences 2.1 to 2.4.

## 27.22.6.3 Interaction with Fixed Dialling Number (FDN)

### 27.22.6.3.1 Definition and applicability

See clause 3.2.2.

### 27.22.6.3.2 Conformance requirement

The ME shall support the CALL CONTROL facility as defined in:

- TS 31.111 [15] clause 7.3.1.4.

### 27.22.6.3.3 Test purpose

To verify that the ME checks that the number entered through the MMI is on the FDN list.

To verify that, if the MMI input does not pass the FDN check, the call shall not be set up.

To verify that, if the MMI input does pass the FDN check, the ME shall pass the dialled digits and other parameters to the UICC, using the ENVELOPE (CALL CONTROL) command.

To verify that, if the UICC responds with "allowed, no modification", the ME shall set up the call as proposed.

To verify that, if the UICC responds with "not allowed", the ME shall not set up the call.

To verify that, if the UICC responds with "allowed with modifications", the ME shall set up the call in accordance with the response from the UICC. If the modifications involve changing the dialled digits, the ME shall not re-check this modified number against the FDN list.

### 27.22.6.3.4 Method of tests

#### 27.22.6.3.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The elementary files are coded as SIM Application Toolkit default with the following exceptions:

The call control service is available in the USIM Service Table.

Fixed Dialling Number service is enabled.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

27.22.6.3.4.2 Procedure

**Expected Sequence 3.1 (CALL CONTROL BY USIM , set up a call not in $EF_{FDN}$)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "4321" | |
| 2 | ME → UICC | The ME does not send the ENVELOPE (CALL CONTROL) command to the USIM. | |
| 3 | ME → USS | The ME does not set up the call. | |

**Expected Sequence 3.2 (CALL CONTROL BY USIM , set up a call in $EF_{FDN}$ , the USIM responds with '90 00')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "123" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 3.2.1A<br>or<br>ENVELOPE CALL CONTROL 3.2.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | 90 00 | |
| 4 | ME → USS | The ME sets up the call without modification | [Set up call to "123"] |

ENVELOPE CALL CONTROL 3.2.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"
- Dialling number string: "123"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC: the mobile country and network code (00F110)
- LAC: the location Area Code (0001)
- Cell ID: Cell Identity Value (0001)

Extended Cell ID: RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 21 | F3 | Note 2 |
| | Note 3 | 13 | Note 5 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 |

ENVELOPE CALL CONTROL 3.2.1B

Logically:

Device identities
- Source device: ME

Destination device: UICC
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Dialling number string "123"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 21 | F3 | Note 2 |
| | Note 3 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

**Expected Sequence 3.3 (CALL CONTROL BY USIM , set up a call in $EF_{FDN}$, Allowed without modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "9876" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 3.3.1A<br>or<br>ENVELOPE CALL CONTROL 3.3.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 3.3.1 | [Call control result: "Allowed without modifications"] |
| 4 | ME → USS | The ME sets up the call without modification | [Set up call to "9876"] |

ENVELOPE CALL CONTROL 3.3.1A

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Dialling number string "9876"

Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 6
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 89 | 67 | Note 2 |
| | Note 3 | 13 | Note 5 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 |

ENVELOPE CALL CONTROL 3.3.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Dialling number string "9876"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 89 | 67 | Note 2 |
| | Note 3 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 3.3.1

Logically:

Call control result Allowed, no modifications

Coding:

| | | |
|---|---|---|
| BER-TLV: | 00 | 00 |

**Expected Sequence 3.4 (CALL CONTROL BY USIM , set up a call in $EF_{FDN}$ , Not Allowed)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "9876" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 3.4.1A<br>or<br>ENVELOPE CALL CONTROL 3.4.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 3.4.1 | [Call control result: "Not Allowed"] |
| 4 | ME → USS | The ME does not set up the call | |

ENVELOPE CALL CONTROL 3.4.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"
- Dialling number string: "9876"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC: the mobile country and network code (00F110)
- LAC: the location Area Code (0001)
- Cell ID: Cell Identity Value (0001)
- Extended Cell ID: RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 89 | 67 | Note 2 |
| | Note 3 | 13 | Note 5 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 |

ENVELOPE CALL CONTROL 3.4.1B

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address

TON Unknown
NPI "ISDN / telephone numbering plan"
Dialling number string "9876"

Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.

Subaddress
This parameter is optional. If present, the contents shall not be checked.

Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 89 | 67 | Note 2 |
| | Note 3 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 3.4.1

Logically:

Call control result Not Allowed

Coding:

| | | |
|---|---|---|
| BER-TLV: | 01 | 00 |

**Expected Sequence 3.5 (CALL CONTROL BY USIM , set up a call in $EF_{FDN}$ , Allowed with modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "9876" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 3.5.1A<br>or<br>ENVELOPE CALL CONTROL 3.5.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | CALL CONTROL RESULT 3.5.1 | [Call control result: "Allowed with modifications"] |
| 4 | ME → USS | The ME sets up the call with data sent by the UICC | [Set up call to "3333"] |

ENVELOPE CALL CONTROL 3.5.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"
- Dialling number string: "9876"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC: the mobile country and network code (00F110)
- LAC: the location Area Code (0001)
- Cell ID: Cell Identity Value (0001)
- Extended Cell ID: RNC-id value (for Rel-4 onwards), see also Note 6

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 89 | 67 | Note 2 |
| | Note3 | 13 | Note 5 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 6 | Note 4 |

ENVELOPE CALL CONTROL 3.5.1B

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"
- Dialling number string: "9876"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Subaddress
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC: the mobile country and network code (001110)
- LAC: the location Area Code (0001)
- Cell ID: Cell Identity Value (0001)

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 89 | 67 | Note 2 |
| | Note3 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 | 01 | Note 4 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Subaddress may be present at this place. If present, it may take up several octets.

Note 4: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 5: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 6: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 3.5.1

Logically:

| | |
|---|---|
| Call control result | Allowed with modifications |
| Address | |
| TON | Unknown |
| NPI | "ISDN / telephone numbering plan" |
| Address value | "3333" |

Coding:

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 05 | 86 | 03 | 81 | 33 | 33 |

#### 27.22.6.3.5 Test requirement

The ME shall operate in the manner defined in expected sequences 3.1 to 3.5.

### 27.22.6.4 Support of Barred Dialling Number (BDN) service

#### 27.22.6.4.1 Definition and applicability

Barred Dialling Numbers (BDN) is a service defined for the USIM. An enabled BDN service results in call restrictions for the ME. The call restrictions are controlled by the Terminal. To ascertain the type of USIM and state of BDN the ME runs the BDN capability request procedure during UICC-Terminal initialisation. At the time an emergency call is setup using the emergency call code read from the $EF_{ECC}$, the Rel-4+ ME shall use the category of the emergency service indicated.

#### 27.22.6.4.2 Conformance requirement

1) Recognising the state of the USIM (BDN enabled) the ME shall perform the UICC initialisation procedure as specified.

2) The ME shall prevent call set-up to any number stored in $EF_{BDN}$ if BDN service is enabled.

3) The ME shall allow call set-up to any number stored in $EF_{BDN}$ if BDN service is disabled.

4) Any change to the $EF_{BDN}$ or $EF_{EST}$ does request PIN2.

5) The ME allows call set-up of an emergency call, even if this number is stored in the USIM.

References:

- R99: TS 22.101[22], clause 8 and A.19;
- Rel-4: TS 22.101[22], clause 9 and A.20;
- Rel-5+: TS 22.101[22], clause 10 and A.21;
- TS 31.102[14], subclauses 4.2.44, 4.4.2.3, 5.1.1 and 5.3.2;
- TS 24.008[10], subclause 10.5.4.33;

- TS 31.111[15], subclause 7.3.1.5

### 27.22.6.4.3 Test purpose

1) To verify that the Terminal rejects call set-up to any number that has an entry in $EF_{BDN}$ if BDN service is enabled.

2) To verify that the Terminal allows call set-up to any number not stored in $EF_{BDN}$.

3) To verify that the Terminal allows emergency call set-up even if the number is stored in $EF_{BDN}$.

4) To verify that the Rel-4+ Terminal reads correctly the emergency service category stored in $EF_{ECC.}$

5) To verify that, if the UICC responds with "not allowed", the ME does not set up the call.

6) To verify that, if the UICC responds with "allowed, no modification", the ME shall set up the call (or the supplementary service operation) as proposed.

7) To verify that, if the UICC responds with "allowed with modifications", the ME sets up the call in accordance with the response from the UICC. If the modifications involve changing the dialled number the ME does not re-check this modified number against the FDN list when FDN is enabled.

8) To verify that updating EF BDN or changing the status of BDN service shall be performed by the use of second application PIN only.

9) To verify that the ME allows call set up to a BDN number if BDN service is disabled.

### 27.22.6.4.4 Method of tests

#### 27.22.6.4.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The call control service is available in the USIM Service Table.

The elementary files are coded as USIM Application Toolkit default with the following exceptions:

Barred Dialling Number service is enabled.

Fixed Dialling Number service is disabled.

Only prior to the execution of expected sequence 4.3 the FDN service shall be enabled.

The Second Application PIN (key reference 81) shall be enabled, but not verified.

Only in expected sequence 4.2B $EF_{ECC}$ shall be used with the following values:

$EF_{ECC}$ (Emergency Call Codes)

| | | |
|---|---|---|
| Logically: | Emergency call code: | "122"; |
| | Emergency call code alpha identifier: | "TEST"; |
| | Emergency call Service Category: | "Mountain Rescue". |

| Coding: | B1 | B2 | B3 | B4 | B5 | B6 | B7 | B8 |
|---|---|---|---|---|---|---|---|---|
| Hex | 21 | F2 | FF | 54 | 45 | 53 | 54 | 10 |

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;

- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

The PCS 1900 parameters of the system simulator are:

Mobile Country Code (MCC) = 001;

- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

27.22.6.4.4.2 Procedure

**Expected Sequence 4.1 (CALL CONTROL BY USIM, BDN service enabled)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "+1357924680" | [Number as stored in record 1 of EF BDN] |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 4.1.1 | |
| 3 | UICC → ME | CALL CONTROL RESULT 4.1.1 | [Call control result: "Not Allowed"] |
| 4 | ME → USS | The ME does not set up the call | |
| 5 | User → ME | The user sets up a call to the number stored in record 1 of EF ADN | |
| 6 | ME → UICC | ENVELOPE CALL CONTROL 4.1.2 | |
| 7 | UICC → ME | CALL CONTROL RESULT 4.1.2 | [Call control result: "Allowed without modifications"] |
| 8 | ME → USS | The ME sets up the call without modification | |
| 9 | User → ME | The user sets up a call to '123456' | |
| 10 | ME → UICC | ENVELOPE CALL CONTROL 4.1.3 | |
| 11 | UICC → ME | CALL CONTROL RESULT 4.1.2 | [Call control result: "Allowed without modifications"] |
| 12 | ME → USS | The ME sets up the call without modification | |
| 13 | User → ME | The user sets up a call to "1111" | |
| 14 | ME → UICC | ENVELOPE CALL CONTROL 4.1.4 | |
| 15 | UICC → ME | CALL CONTROL RESULT 4.1.3 | [Call control result: "Allowed with modifications"] |
| 16 | ME → USS | The ME sets up the call with data sent by the UICC | [Set up call to "2222"] |
| 17 | User → ME | The user shall use a MMI dependent procedure to initiate the disabling of the BDN service | |
| 18 | ME → User | Ask for second application PIN verification | |
| 19 | User → ME | The user shall enter the second application PIN | |
| 20 | ME → UICC | Update EF EST to disable BDN service | |
| 21 | UICC → ME | UICC responds with SW = '90 00' | |
| 22 | ME → User | Indicate that the BDN service was disabled successfully | |
| 23 | User → ME | The user uses the MMI to store the directory number "+876543210" in $EF_{BDN}$ as barred dialling number 1 (record 1). | [The alpha identifier is not changed.] |
| 24 | ME → UICC | Update EF BDN | |
| 25 | UICC → ME | UICC responds with SW = '90 00' | |
| 26 | ME → User | The user attempts to set up a call to '+876543210'. | |
| 27a | ME → UICC | No Envelope call control is sent | |
| 27b | ME → USS | The ME sets up the call without modification | |

ENVELOPE CALL CONTROL 4.1.1

Logically:

Device identities
Source device: ME
Destination device: UICC
Address

TON International
NPI "ISDN / telephone numbering plan"
Dialling number string "1357924680"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 06 | 91 | 31 | 75 | 29 |
| | 64 | 08 | Note 2 | 13 | Note 4 | 00 | F1 | 10 | 00 | 01 | 00 | 01 |
| | Note5 | Note 3 | | | | | | | | | | |

Note 1: Length of BER-TLV is '15' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 4.1.2

Logically:

Device identities
Source device: ME
Destination device: UICC
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Dialling number string "123"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 21 | F3 | Note 2 |
| | 13 | Note 4 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 5 | Note 3 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 4.1.3

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"
- Dialling number string: "123456"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC: the mobile country and network code (00F110)
- LAC: the location Area Code (0001)
- Cell ID: Cell Identity Value (0001)

Extended Cell ID: RNC-id value (for Rel-4 onwards), see also Note 5

Capability configuration parameters 2
- This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 04 | 81 | 21 | 43 | 65 |
| | Note 2 | 13 | Note 4 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 5 | Note 3 |

Note 1: Length of BER-TLV is '13' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'.

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE CALL CONTROL 4.1.4

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"
- Dialling number string: "1111"

Capability configuration parameters 1
- This parameter is optional. If present, the contents shall not be checked.

Location Information
- MCC & MNC: the mobile country and network code (00F110)

LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 11 | 11 | Note 2 |
| | 13 | Note 4 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 5 | Note 3 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 4.1.1

Logically:

Call control result Not Allowed

Coding:

| | | |
|---|---|---|
| BER-TLV: | 01 | 00 |

CALL CONTROL RESULT 4.1.2

Logically:

Call control result Allowed, no modifications

Coding:

| | | |
|---|---|---|
| BER-TLV: | 00 | 00 |

CALL CONTROL RESULT 4.1.3

Logically:

Call control result Allowed with modifications
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Address value "2222"

Coding:

| | | | | | | | |
|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 05 | 86 | 03 | 81 | 22 | 22 |

**Expected Sequence 4.2A (CALL CONTROL BY USIM, BDN service enabled, interaction with emergency call codes, R99 only)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up an emergency call to an emergency number stored in the terminal. | The used emergency number shall be one of the emergency call codes, which are available when a SIM/USIM is present, according to TS 22.101[22], subclause 8 is used (i.e. "112", or "911"). |
| 2a | ME → UICC | No Envelope call control is sent | |
| 2b | ME → USS | The ME shall allow an emergency call by indicating the call setup as "Emergency Call'. | |
| 3 | User → ME | End the emergency call. | |

**Expected Sequence 4.2B (CALL CONTROL BY USIM, BDN service enabled, interaction with emergency call codes, Rel-4+)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up an emergency call to an emergency number stored in the terminal. | The used emergency number shall be one of the emergency call codes, which are available when a SIM/USIM is present, according to TS 22.101[22], subclause 9 (Rel-4) or 10 (Rel-5+) is used (i.e. "112", or "911"). |
| 2a | ME → UICC | No Envelope call control is sent | |
| 2b | ME → USS | The ME shall allow an emergency call by indicating the call setup as "Emergency Call'. | |
| 3 | User → ME | End the emergency call. | |
| 4 | User → ME | The user sets up an emergency call to an emergency number stored in the USIM. | |
| 5a | ME → UICC | No Envelope call control is sent | |
| 5b | ME → USS | The ME shall allow an emergency call by sending the emergency service category correctly as 'Mountain Rescue'. | |
| 6 | User → ME | End the emergency call. | |

**Expected Sequence 4.3 (CALL CONTROL BY USIM , FDN and BDN enabled, set up a call in $EF_{FDN}$, Allowed with modifications)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "123" | |
| 2 | ME → UICC | ENVELOPE CALL CONTROL 4.3.1 | |
| 3 | UICC → ME | CALL CONTROL RESULT 4.3.1 | [Call control result: "Allowed with modifications"] |
| 4 | ME → USS | The ME sets up the call with data sent by the UICC | [Set up call to "24680"the ME does not re-check this modified number against the FDN list] |

ENVELOPE CALL CONTROL 4.3.1

Logically:

Device identities
- Source device: ME
- Destination device: UICC

Address
- TON: Unknown
- NPI: "ISDN / telephone numbering plan"

Dialling number string "123"
Capability configuration parameters 1
This parameter is optional. If present, the contents shall not be checked.
Subaddress
This parameter is optional. If present, the contents shall not be checked.
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 5
Capability configuration parameters 2
This parameter is optional. If present, the contents shall not be checked.

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D4 | Note 1 | 82 | 02 | 82 | 81 | 86 | 03 | 81 | 21 | F3 | Note 2 |
| | 13 | Note 4 | 00 | F1 | 10 | 00 | 01 | 00 | 01 | Note 5 | Note 3 | |

Note 1: Length of BER-TLV is '12' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Capability configuration parameters 1 may be present at this place. If present, it may take up several octets.

Note 3: Capability configuration parameters 2 may be present at this place. If present, it may take up several octets.

Note 4: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 5: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

CALL CONTROL RESULT 4.3.1

Logically:

Call control result Allowed with modifications
Address
TON Unknown
NPI "ISDN / telephone numbering plan"
Address value "24680"

Coding:

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 02 | 06 | 86 | 04 | 81 | 42 | 86 | F0 | | |

### 27.22.6.4.5 Test requirement

The ME shall operate in the manner defined in expected sequences 4.1 to 4.3.

## 27.22.6.5 Barred Dialling Number (BDN) service handling for terminals not supporting BDN

### 27.22.6.5.1 Definition and applicability

Barred Dialling Numbers (BDN) is a service defined for the USIM. An enabled BDN service results in call restrictions for the ME. The call restrictions are controlled by the Terminal. If BDN is enabled, an ME which does not support Call Control shall allow emergency calls but shall not allow MO-CS calls.

### 27.22.6.5.2 Conformance requirement

1) Recognising the state of the USIM (BDN enabled) the ME shall perform the UICC initialisation procedure as specified.

2) The ME shall prevent MO-CS call set-up to any number except to emergency call numbers if the BDN service is enabled.

References:

- Rel-5+: TS 22.101[22], clause 10 and A.21;

  TS 31.102[14], subclauses 4.2.44, 4.4.2.3, 5.1.1.2 and 5.3.2;

  TS 31.111[15], subclause 7.3.1.5

### 27.22.6.5.3 Test purpose

1) To verify that the Terminal rejects MO-CS call set-up to any number except to emergency call numbers if BDN service is enabled.

2) To verify that the Terminal allows emergency call set-up even if the BDN service is enabled.

### 27.22.6.5.4 Method of tests

#### 27.22.6.5.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The call control service is available in the USIM Service Table.

The elementary files are coded as USIM Application Toolkit default with the following exceptions:

Barred Dialling Number service is enabled.

#### 27.22.6.5.4.2 Procedure

**Expected Sequence 5.1 (CALL CONTROL BY USIM, BDN service enabled, ME not supporting BDN)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user sets up a call to "+1357924680" | [Number as stored in record 1 of EF BDN] |
| 2a | ME → UICC | No ENVELOPE CALL CONTROL is sent | |
| 2b | ME → USS | The ME does not set up the call | |
| 3 | User → ME | The user sets up a call to the number stored in record 1 of EF ADN | |
| 4a | ME → UICC | No ENVELOPE CALL CONTROL is sent | |
| 4b | ME → USS | The ME does not set up the call | |
| 5 | User → ME | The user sets up an emergency call to "112" | |
| 6a | ME → UICC | No ENVELOPE CALL CONTROL is sent | |
| 6b | ME → USS | The ME sets up the emergency call to "112" | |
| 7 | User → ME | The user shall terminate the emergency call after 5 seconds. The ME returns to idle mode. | |

# 27.22.7 EVENT DOWNLOAD

## 27.22.7.1 MT Call Event

### 27.22.7.1.1 MT Call Event (normal)

#### 27.22.7.1.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.1.1.2 Conformance requirement

The ME shall support the EVENT: MT Call event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

#### 27.22.7.1.1.3 Test purpose

To verify that the ME informs the UICC that an Event: MT Call has occurred using the ENVELOPE (EVENT DOWNLOAD - MT Call) command.

#### 27.22.7.1.1.4 Method of test

##### 27.22.7.1.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

##### 27.22.7.1.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -MT Call event)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | USS → ME | CALL SET UP without CLI | [MT Call Set Up Without CLI] |
| 6 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - MT Call 1.1.1 | |
| 7 | USS → ME | CALL DISCONNECT | |
| 8 | USS → ME | CALL SET UP with CLI | [MT Call Set Up With CLI] |
| 9 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - MT Call 1.1.2 | |
| 10 | USS → ME | CALL DISCONNECT | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC

Destination device: ME
Event list
Event 1: MT call

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
| | 01 | 00 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

EVENT DOWNLOAD - MT CALL 1.1.1

Logically:

Event list: MT call event
Device identities
Source device: Network
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 00 | 82 | 02 | 83 | 81 | 1C | 01 | 00 |

EVENT DOWNLOAD - MT CALL 1.1.2

Logically:

Event list: MT call event
Device identities
Source device: Network
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Address:
TON Unknown
NPI "ISDN / telephone numbering plan"

Dialling number string "9876"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0F | 19 | 01 | 00 | 82 | 02 | 83 | 81 | 1C | 01 | 00 |
| | 86 | 03 | 81 | 89 | 67 | | | | | | | |

#### 27.22.7.1.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.2 Call Connected Event

### 27.22.7.2.1 Call Connected Event (MT and MO call)

#### 27.22.7.2.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.2.1.2 Conformance requirement

The ME shall support the EVENT: Call Connected event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

#### 27.22.7.2.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Connected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Connected) command.

#### 27.22.7.2.1.4 Method of test

##### 27.22.7.2.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

27.22.7.2.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -CALL CONNECTED)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | [EVENT: Call Connected active] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | USS → ME | SETUP | [MT Call] Ti = 0 |
| 6 | USER → ME | Accept Call Set Up | |
| 7 | ME→USS | CONNECT | |
| 8 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Call Connected 1.1.1 | |
| 9 | USS → ME | DISCONNECT | |
| 10 | USER → ME | Initiate Call to "123" | |
| 11 | ME → USS | SETUP | [MO Call] Ti = 0 |
| 12 | USS → ME | CONNECT | |
| 13 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Call Connected 1.1.2 | |
| 14 | USER → ME | End Call | |
| 15 | ME → USS | DISCONNECT | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Call Connected

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
| | 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

EVENT DOWNLOAD - CALL CONNECTED 1.1.1

Logically:

Event list: Call connected
Device identities
Source device: ME
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 01 | 82 | 02 | 82 | 81 | 1C | 01 | 80 |

EVENT DOWNLOAD - CALL CONNECTED 1.1.2

Logically:

Event list: Call connected
Device identities
Source device: Network
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 01 | 82 | 02 | 83 | 81 | 1C | 01 | 80 |

#### 27.22.7.2.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

### 27.22.7.2.2 Call Connected Event (ME supporting SET UP CALL)

#### 27.22.7.2.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.2.2.2 Conformance requirement

Additionally the ME shall support the SET UP CALL Proactive UICC Command as defined in:

- TS 31.111 [15] clause 7.5, clause 6.4.13 and clause 6.6.12.

#### 27.22.7.2.2.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Connected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Connected) command.

27.22.7.2.2.4 Method of test

27.22.7.2.2.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

27.22.7.2.2.4.2 Procedure

**Expected Sequence 2.1 (EVENT DOWNLOAD -CALL CONNECTED, ME supporting SET UP CALL)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 2.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 2.1.1 | [EVENT: Call Connected active] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 2.1.1 | |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP CALL 2.1.1 | |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: SET UP CALL 2.1.1 | [SAT Call] |
| 8 | ME → USER | ME displays "+012340123456" during the user confirmation phase. | ME BEHAVIOUR: SET UP CALL |
| 9 | USER → ME | Confirm call set up | |
| 10 | ME → USS | SETUP | Ti=0 |
| 11 | USS → ME | CONNECT | |
| 12 | ME → UICC | TERMINAL RESPONSE: SET UP CALL 2.1.1 | |
| 13 | ME → UICC | ENVELOPE: CALL CONNECTED 2.1.1 | |

PROACTIVE COMMAND: SET UP EVENT LIST 2.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Call Connected

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | 01 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 2.1.1

Logically:

Command details

Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

PROACTIVE COMMAND: SET UP CALL 2.1.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: Only if not currently busy on another call
Device identities
Source device: UICC
Destination device: Network
Alpha identifier: "+012340123456"
Address
TON: International
NPI: "ISDN / telephone numbering plan"
Dialling number string "012340123456"

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 21 | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 81 | 83 |
| | 05 | 0D | 2B | 30 | 31 | 32 | 33 | 34 | 30 | 31 | 32 |
| | 33 | 34 | 35 | 36 | 86 | 07 | 91 | 10 | 32 | 04 | 21 |
| | 43 | 65 | | | | | | | | | |

TERMINAL RESPONSE: SET UP CALL 2.1.1

Logically:

Command details
Command number: 1
Command type: SET UP CALL
Command qualifier: Only if not currently busy on another call
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 10 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

EVENT DOWNLOAD - CALL CONNECTED 2.1.1

Logically:

| | |
|---|---|
| Event list: | Call connected |
| Device identities | |
| Source device: | Network |
| Destination device: | UICC |
| Transaction identifier: | |
| Ti value: | 0 (bit 5-7) |
| Ti flag: | 1 (bit 8) |

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 01 | 82 | 02 | 83 | 81 | 1C | 01 | 80 |

#### 27.22.7.2.2.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 2.1'.

### 27.22.7.3 Call Disconnected Event

#### 27.22.7.3.1 Call Disconnected Event

##### 27.22.7.3.1.1 Definition and applicability

See clause 3.2.2.

##### 27.22.7.3.1.2 Conformance requirement

The ME shall support the EVENT: Call Disconnected event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

##### 27.22.7.3.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Call Disconnected has occurred using the ENVELOPE (EVENT DOWNLOAD -Call Disconnected) command.

##### 27.22.7.3.1.4 Method of test

###### 27.22.7.3.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

27.22.7.3.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -CALL DISCONNECTED)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | [EVENT: Call Disconnected active] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | USS → ME | SETUP | [ incoming call ] Ti=0 |
| 6 | USER → ME | Accept Call Set Up | |
| 7 | USS → ME | RELEASE | [MT RELEASE] |
| 8 | ME→ UICC | ENVELOPE: CALL DISCONNECTED 1.1.1 | |
| 9 | USS → ME | SETUP | [ incoming call ] Ti=0 |
| 10 | USER → ME | Accept Call Set Up | |
| 11 | USS → ME | RELEASE COMPLETE | [MT RELEASE COMPLETE] |
| 12 | ME→ UICC | ENVELOPE: CALL DISCONNECTED 1.1.1 | |
| 13 | USS → ME | SETUP | [ incoming call ] Ti=0 |
| 14 | USER → ME | Accept Call Set Up | |
| 15 | USER → ME | End Call | |
| 16 | ME → USS | DISCONNECT | [MO DISCONNECT] |
| 17 | ME → UICC | ENVELOPE: CALL DISCONNECTED 1.1.2A or ENVELOPE: CALL DISCONNECTED 1.1.2B or ENVELOPE: CALL DISCONNECTED 1.1.2C | |
| 18 | USS → ME | SETUP | [ incoming call ] Ti=0 |
| 19 | USER → ME | Accept Call Set Up | |
| 20 | USS → ME | DISCONNECT | [MT DISCONNECT + CAUSE: normal call clearing ] |
| 21 | ME→ UICC | ENVELOPE: CALL DISCONNECTED 1.1.3A or ENVELOPE: CALL DISCONNECTED 1.1.3B | |
| 22 | USS → ME | SETUP | Ti=0 |
| 23 | USER → ME | Accept Call Set Up | |
| 24 | USS | TX POWER to XX | [RADIO LINK FAILURE] |
| 25 | ME→ UICC | ENVELOPE: CALL DISCONNECTED 1.1.4A or 1.1.4B | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Call Disconnected

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
| | 01 | 02 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.1

Logically:

Event list: Call Disconnected

Device identities
- Source device: Network
- Destination device: UICC

Transaction identifier:
- Ti value: 0 (bit 5-7)
- Ti flag: 0 (bit 8)

Cause:

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 02 | 82 | 02 | 83 | 81 | 1C | 01 | 00 |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2A

Logically:

Event list: Call Disconnected

Device identities
- Source device: ME
- Destination device: UICC

Transaction identifier:
- Ti value: 0 (bit 5-7)
- Ti flag: 1 (bit 8)

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 02 | 82 | 02 | 82 | 81 | 1C | 01 | 80 |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2B

Logically:

Event list: Call Disconnected
Device identities
Source device: ME
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)
Cause: normal call clearing

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 19 | 01 | 02 | 82 | 02 | 82 | 81 | 1C | 01 | 80 |
| | 9A | 02 | 60 | 90 | | | | | | | | |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.2C

Logically:

Event list: Call Disconnected
Device identities
Source device: ME
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)
Cause: normal call clearing

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 19 | 01 | 02 | 82 | 02 | 82 | 81 | 1C | 01 | 80 |
| | 9A | 02 | E0 | 90 | | | | | | | | |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.3A

Logically:

Event list: Call Disconnected
Device identities
Source device: Network
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause: normal call clearing

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 19 | 01 | 02 | 82 | 02 | 83 | 81 | 1C | 01 | 00 |
| | 9A | 02 | 60 | 90 | | | | | | | | |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.3B

Logically:

Event list: Call Disconnected
Device identities
Source device: Network
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause: normal call clearing

Coding:

| BER-TLV: | D6 | 0E | 19 | 01 | 02 | 82 | 02 | 83 | 81 | 1C | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 9A | 02 | E0 | 90 | | | | | | | | |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.4A

Logically:

Event list: Call Disconnected
Device identities
Source device: ME
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 1 (bit 8)
Cause: radio link failure

Coding:

| BER-TLV: | D6 | 0C | 19 | 01 | 02 | 82 | 02 | 82 | 81 | 1C | 01 | 80 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 9A | 00 | | | | | | | | | | |

EVENT DOWNLOAD - CALL DISCONNECTED 1.1.4B

Logically:

Event list: Call Disconnected
Device identities
Source device: ME
Destination device: UICC
Transaction identifier:
Ti value: 0 (bit 5-7)
Ti flag: 0 (bit 8)
Cause: radio link failure

Coding:

| BER-TLV: | D6 | 0C | 19 | 01 | 02 | 82 | 02 | 82 | 81 | 1C | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 9A | 00 | | | | | | | | | | |

### 27.22.7.3.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.4 Location Status Event

### 27.22.7.4.1 Location Status Event (normal)

#### 27.22.7.4.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.4.1.2 Conformance requirement

The ME shall support the EVENT: Location Status event as defined in:

- TS 31.111 [15] clause 7.5 and clause 6.4.16.

#### 27.22.7.4.1.3 Test purpose

To verify that the ME informs the UICC that an Event: MM_IDLE state has occurred using the ENVELOPE (EVENT DOWNLOAD - Location Status) command.

#### 27.22.7.4.1.4 Method of test

##### 27.22.7.4.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01 ;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001.

Two cells are defined. Cell 1 has location area code 1 and cell 2 has location area code 2.

MS is in service on Cell 1.

27.22.7.4.1.4.2 Procedure

**Expected Sequence 1.1(EVENT DOWNLOAD -LOCATION STATUS)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | |
| 5 | USS | Cell 1 is switched off | |
| 6 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.1 | |
| 7 | USS | Cell 2 is switched on after Location Status 'No service' has been received in step 6 | |
| 8 | ME | ME performs cell reselection to cell 2 | |
| 9 | ME → USS | LOCATION UPDATING REQUEST or ROUTING AREA UPDATE REQUEST | The ME is CS and/or PS registered depending on its capabilities |
| 10 | USS → ME | LOCATION UPDATING ACCEPT or ROUTING AREA UPDATE ACCEPT | |
| 11 | ME → USS | TMSI REALLOCATION COMPLETE or ROUTING AREA UPDATE COMPLETE | |
| 12 | ME → UICC | ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.2A<br>or<br>ENVELOPE: EVENT DOWNLOAD - Location Status 1.1.2B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters]<br>[NOTE: The inclusion of the location information is optional: (If location status indicates normal status) |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Location status

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 | 99 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 01 | 03 | | | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1

Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

EVENT DOWNLOAD - LOCATION STATUS 1.1.1

Logically:

Event list: Location status
Device identities
Source device: ME
Destination device: UICC
Location status: No service

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 19 | 01 | 03 | 82 | 02 | 82 | 81 | 1B | 01 | 02 |

EVENT DOWNLOAD - LOCATION STATUS 1.1.2A

Logically:

Event list: Location status
Device identities
Source device: ME
Destination device: UICC
Location status: normal service
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0002)
Cell ID Cell Identity Value (0002)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | Note 1 | 19 | 01 | 03 | 82 | 02 | 82 | 81 | 1B | 01 | 00 |
| | 13 | Note 2 | 00 | F1 | 10 | 00 | 02 | 00 | 02 | Note 3 | | |

Note 1: Depending on the presence of the Extended Cell Identity Value the length is '13' or '15'

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified

EVENT DOWNLOAD - LOCATION STATUS 1.1.2B

Logically:

Event list: Location status
Device identities

Source device: ME
Destination device: UICC
Location status: normal service
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0002)
Cell ID Cell Identity Value (0002)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 13 | 19 | 01 | 03 | 82 | 02 | 82 | 81 | 1B | 01 | 00 |
| | 13 | 07 | 00 | 11 | 10 | 00 | 02 | 00 | 02 | | | |

#### 27.22.7.4.1.5 Test requirement

The behaviour of the test is as defined in 'Expected Sequence 1.1'.

## 27.22.7.5 User Activity Event

### 27.22.7.5.1 User Activity Event (normal)

#### 27.22.7.5.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.5.1.2 Conformance Requirement

The ME shall support the EVENT DOWNLOAD -USER ACTIVITY as defined in:

- TS 31.111 [15] clause 5.2, clause 6.4.16, clause 6.8, clause 6.6.16, clause 6.11, clause 7.5, clause 8.6 and clause 8.25.

#### 27.22.7.5.1.3 Test purpose

To verify that the ME performed correctly the procedure of USER ACTIVITY EVENT.

#### 27.22.7.5.1.4 Method of Test

##### 27.22.7.5.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

##### 27.22.7.5.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD -USER ACTIVITY)**

See ETSI TS 102 384 [26] in subclause 27.22.7.5.1.4.2, Expected Sequence 1.1.

27.22.7.5.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.6 Idle screen available event

### 27.22.7.6.1 Idle Screen Available (normal)

#### 27.22.7.6.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.6.1.2 Conformance requirement

The ME shall support the EVENT: IDLE SCREEN AVAILABLE event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

#### 27.22.7.6.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Idle Screen Available has occurred using the ENVELOPE (EVENT DOWNLOAD - IDLE SCREEN AVAILABLE) command.

#### 27.22.7.6.1.4 Method of test

##### 27.22.7.6.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure and be in updated idle mode on the USS.

##### 27.22.7.6.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD - IDLE SCREEN AVAILABLE)**

See ETSI TS 102 384 [26] in subclause 27.22.7.6.1.4.2, Expected Sequence 1.1.

27.22.7.6.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.7 Card reader status event

### 27.22.7.7.1 Card Reader Status (normal)

#### 27.22.7.7.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.7.1.2 Conformance requirement

The ME shall support the EVENT: Call Card Reader Status event as defined in:

- TS 31.111 [15] clause 4.7, clause 4.9, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, clause 8.25, clause 8.33, annex F, annex G, clause 8.25 and clause 8.7.

#### 27.22.7.7.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Card Reader Status has changed using the ENVELOPE (EVENT DOWNLOAD - Card Reader Status) command.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen.

#### 27.22.7.7.1.4 Method of test

##### 27.22.7.7.1.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

##### 27.22.7.7.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD, Card reader status, Card reader 1, card reader attached, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.7.7.1.4.2, Expected Sequence 1.1.

27.22.7.7.1.5 Test requirement

The behaviour of the test is as defined in expected Sequence 1.1.

### 27.22.7.7.2 Card Reader Status(detachable card reader)

#### 27.22.7.7.2.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.7.2.2 Conformance requirement

The ME shall support the EVENT: Call Card Reader Status event as defined in:

- TS 31.111 [15] clause 4.7, clause 4.9, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, clause 8.25, clause 8.33, annex F, annex G, clause 8.25 and clause 8.7.

#### 27.22.7.7.2.3 Test purpose

To verify that the ME informs the UICC that an Event: Card Reader Status has changed using the ENVELOPE (EVENT DOWNLOAD - Card Reader Status) command.

The ME-Manufacturer can assign the card reader identifier from 0 to 7.

This test applies for MEs with only one additional card reader.

In this particular case the card reader identifier 1 is chosen as an example.

#### 27.22.7.7.2.4 Method of test

##### 27.22.7.7.2.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

##### 27.22.7.7.2.4.2 Procedure

**Expected Sequence 2.1 (EVENT DOWNLOAD, Detachable reader, Card reader 1, detachable card reader not attached, no card inserted)**

See ETSI TS 102 384 [26] in subclause 27.22.7.7.2.4.2, Expected Sequence 2.1.

27.22.7.7.2.5 Test requirement

The behaviour of the test is as defined in expected Sequence 2.1.

## 27.22.7.8 Language selection event

### 27.22.7.8.1 Language selection event (normal)

#### 27.22.7.8.1.1 Definition and applicability

See clause 3.2.2.

#### 27.22.7.8.1.2 Conformance requirement

The ME shall support the EVENT: LANGUAGE SELECTION event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, and clause 8.25.

#### 27.22.7.8.1.3 Test purpose

To verify that the ME informs the UICC that an Event: Language selection has occurred using the ENVELOPE (EVENT DOWNLOAD - LANGUAGE SELECTION ) command.

#### 27.22.7.8.1.4 Method of test

##### 27.22.7.8.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The elementary files are coded as USIM Application Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The current language shall have been set to English. Another language has to be supported, German is an example.

##### 27.22.7.8.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD - LANGUAGE SELECTION)**

See ETSI TS 102 384 [26] in subclause 27.22.7.8.1.4.2, Expected Sequence 1.1.

27.22.7.8.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.9 Browser termination event

### 27.22.7.9.1 Browser termination (normal)

#### 27.22.7.9.1.1 Definition and applicability

This test is only applicable to ME's that support the EVENT: browser termination event driven information.

#### 27.22.7.9.1.2 Conformance requirement

The ME shall support the EVENT: Browser termination event as defined in:

- TS 31.111 [15] clause 4.7, clause 5.2, clause 6.4.16, clause 6.8, clause 7.5, , clause 8.25, clause 8.51, annex F and clause 8.7.

27.22.7.9.1.3 Test purpose

To verify that the ME informs the UICC of an Event: Browser termination using the ENVELOPE (EVENT DOWNLOAD - Browser Termination) command.

This test applies for MEs which have a browser.

27.22.7.9.1.4 Method of test

27.22.7.9.1.4.1 Initial conditions

The ME is connected to the USIM Simulator and the USS.

The ME shall be powered on and perform the PROFILE DOWNLOAD procedure.

A valid access to a Wap gateway is required. The default browser parameters (IP address, gateway/proxy identity, called number…) of the tested mobile shall be properly filled to access that gateway.

27.22.7.9.1.4.2 Procedure

**Expected Sequence 1.1 (EVENT DOWNLOAD - Browser termination)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 PENDING | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | [EVENT: Browser termination Status] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | [Successfully] |
| 5 | User→ME | Launch the browser with the URL selected by the user | |
| 6 | ME→USS | The ME attempts to launch the session with the default browser parameters and the URL selected by the user. | |
| 7 | User→ME | Stop the session and the browser. | |
| 8 | ME→ UICC | ENVELOPE: BROWSER TERMINATION 1.1.1 | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC
- Destination device: ME

Event list
- Event 1: Browser termination

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 |
| | 99 | 01 | 08 | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

ENVELOPE: EVENT DOWNLOAD BROWSER TERMINATION 1.1.1

Logically:

Event list
- Event 1: Browser termination

Device identities
- Source device: ME
- Destination device: UICC

Browser termination cause: User termination

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0A | 99 | 01 | 08 | 82 | 02 | 82 | 81 | B4 | 01 | 00 |

#### 27.22.7.9.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.10 Data available event

### 27.22.7.10.1 Definition and applicability

See clause 3.2.2.

### 27.22.7.10.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

Additionally the ME shall support ENVELOPE (EVENT DOWNLOAD - Data available).

### 27.22.7.10.3 Test purpose

To verify that the ME shall send an ENVELOPE (EVENT DOWNLOAD - Data available) to the UICC after the ME receives a packet of data from the server by the BIP channel previously opened.

### 27.22.7.10.4 Method of test

#### 27.22.7.10.4.1 Initial conditions

The ME is connected to the USIM Simulator and only connected to the USS if the USS is mentioned in the sequence table.. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure. The UICC must have sent the SET UP EVENT LIST to the ME to supply a set of events (event Data available).

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The PROACTIVE COMMAND: SEND DATA 1.1.1 shall be performed successfully to detect the ME's port number, which has to be addressed by the network simulator when data has to be transmitted to the card. The corresponding Terminal Response shall be TERMINAL RESPONSE: SEND DATA 1.1.1.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

Bearer Parameters

Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)

GPRS Parameters

Network access name: TestGp.rs
User login: UserLog
User password: UserPwd

UICC/ME interface transport level

Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

27.22.7.10.4.2 Procedure

**Expected sequence 1.1 (EVENT DOWNLOAD - Data available)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | [Command performed successfully] |
| 4 | ME → USER | The ME may display channel opening information | |
| 5 | ME → USS | PDP context activation request | |
| 6 | USS → ME | PDP context activation accept | |
| 7 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | |
| 8 | UICC → ME | PROACTIVE COMMAND PENDING: SEND DATA 1.1.1 | |
| 9 | ME → UICC | FETCH | |
| 10 | UICC → ME | PROACTIVE COMMAND: SEND DATA (immediate) 1.1.1 | |
| 11 | ME → USS | Transfer of 8 Bytes of data to the USS through channel 1 | [To retrieve ME's port number] |
| 12 | ME → UICC | TERMINAL RESPONSE: SEND DATA (immediate) 1.1.1 | [Command performed successfully] |
| 13 | USS → ME | Data sent through the BIP channel using the ME's port number, which was retrieved in step 11 | |
| 14 | ME → UICC | ENVELOPE 1.1.1 (Event-Data Available) | |

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: UICC
- Destination device: ME

Bearer
- Bearer type: GPRS
- Bearer parameter:
  - Precedence Class: 03
  - Delay Class: 04
  - Reliability Class: 03
  - Peak throughput class: 04
  - Mean throughput class: 31
  - Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Network access name: TestGp.rs

Text String: UserLog (User login)

Text String: UserPwd (User password)

UICC/ME interface transport level
- Transport format: UDP
- Port number: 44444

Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 03 | E8 |
| | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
  - Precedence Class: 03
  - Delay Class: 04
  - Reliability Class: 03
  - Peak throughput class: 04
  - Mean throughput class: 31
  - Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status Channel identifier 1 and link established or PDP context activated
Bearer description
Bearer type: GPRS
Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

PROACTIVE COMMAND: SEND DATA 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: UICC
Destination device: Channel 1
Channel Data
Channel Data: 00 01 .. 07 (8 Bytes of data)

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 13 | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 81 | 21 | B6 |
| | 08 | 00 | 01 | 02 | 03 | 04 | 05 | 06 | 07 | | | |

TERMINAL RESPONSE: SEND DATA 1.1.1

Logically:

Command details
Command number: 1
Command type: SEND DATA
Command qualifier: Send Immediately
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully
Channel data length: More than 255 bytes of space available in the Tx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 43 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | B7 | 01 | FF | | | | | | | | | |

ENVELOPE: EVENT DOWNLOAD - Data available 1.1.1

Logically:

Event list
Event: Data available
Device identities
Source device: ME
Destination device: UICC
Channel status
Channel status: Channel 1 open, link established
Channel Data Length
Channel data length: 8 Bytes available in Rx buffer

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D6 | 0E | 99 | 01 | 09 | 82 | 02 | 82 | 81 | B8 | 02 | 81 |
| | 00 | B7 | 01 | 08 | | | | | | | | |

#### 27.22.7.10.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

## 27.22.7.11 Channel Status event

### 27.22.7.11.1 Definition and applicability

See clause 3.2.2.

### 27.22.7.11.2 Conformance requirements

The ME shall support the class "e" commands as defined in:

- TS 31.111 [15].

Additionally the ME shall support ENVELOPE (EVENT DOWNLOAD - Channel Status).

### 27.22.7.11.3 Test purpose

To verify that the ME shall send an ENVELOPE (EVENT DOWNLOAD - Channel Status) to the UICC after the link dropped between the NETWORK and the ME.

### 27.22.7.11.4 Method of test

#### 27.22.7.11.4.1 Initial conditions

The ME is connected to the USIM Simulator and the System Simulator. The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

For MEs supporting BIP related to GPRS in UDP (i.e condition C121 in table B.1), The PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 shall be executed to open a channel successfully at the beginning of the test. The corresponding Terminal Response shall be TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A or TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B.

The following Bearer Parameters used are those defined in the default Test PDP context3, for test cases using packet services:

Bearer Parameters

| | |
|---|---|
| Precedence Class: | 03 |
| Delay Class: | 04 |
| Reliability Class: | 03 |
| Peak throughput class: | 04 |
| Mean throughput class: | 31 |
| Packet data protocol: | 02 (IP) |

GPRS Parameters

| | |
|---|---|
| Network access name: | TestGp.rs |
| User login: | UserLog |
| User password: | UserPwd |

UICC/ME interface transport level

| | |
|---|---|
| Transport format: | UDP |
| Port number: | 44444 |
| Data destination address | 01.01.01.01 |

27.22.7.11.4.2 Procedure

**Expected sequence 1.1 (EVENT DOWNLOAD - Channel Status on a link dropped)**

| Step | Direction | MESSAGE / Action | Comments |
|---|---|---|---|
| 1 | UICC → ME | PROACTIVE COMMAND PENDING: SET UP EVENT LIST 1.1.1 | |
| 2 | ME → UICC | FETCH | |
| 3 | UICC → ME | PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1 | [EVENT: channel status] |
| 4 | ME → UICC | TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1 | [command performed successfully] |
| 5 | UICC → ME | PROACTIVE COMMAND PENDING: OPEN CHANNEL 1.1.1 | See initial conditions |
| 6 | ME → UICC | FETCH | |
| 7 | UICC → ME | PROACTIVE COMMAND: OPEN CHANNEL 1.1.1 | |
| 8 | ME → USER | The ME may display channel opening information | |
| 9 | ME → USS | PDP context activation request | |
| 10 | USS → ME | PDP context activation accept | |
| 11 | ME → UICC | TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A<br>or<br>TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B | [Command performed successfully] |
| 12 | USS → ME | Link dropped | |
| 13 | ME → UICC | ENVELOPE 1.1.1 (Event-Channel Status) | |

PROACTIVE COMMAND: SET UP EVENT LIST 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SET UP EVENT LIST
- Command qualifier: '00'

Device identities
- Source device: UICC

Destination device: ME
Event list
Event 1: Channel Status

Coding:

| BER-TLV: | D0 | 0C | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 81 | 82 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 99 | 01 | 0A | | | | | | | | |

TERMINAL RESPONSE: SET UP EVENT LIST 1.1.1

Logically:

Command details
Command number: 1
Command type: SET UP EVENT LIST
Command qualifier: '00'
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Command performed successfully

Coding:

| BER-TLV: | 81 | 03 | 01 | 05 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|

PROACTIVE COMMAND: OPEN CHANNEL 1.1.1

Logically:

Command details
Command number: 1
Command type: OPEN CHANNEL
Command qualifier: immediate link establishment
Device identities
Source device: UICC
Destination device: ME
Bearer
Bearer type: GPRS
Bearer parameter:
Precedence Class: 03
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000
Network access name: TestGp.rs
Text String: UserLog (User login)
Text String: UserPwd (User password)
UICC/ME interface transport level
Transport format: UDP
Port number: 44444
Data destination address 01.01.01.01

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV | D0 | 42 | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 81 | 82 | 35 |
| | 07 | 02 | 03 | 04 | 03 | 04 | 1F | 02 | 39 | 02 | 03 | E8 |
| | 47 | 0A | 06 | 54 | 65 | 73 | 74 | 47 | 70 | 02 | 72 | 73 |
| | 0D | 08 | F4 | 55 | 73 | 65 | 72 | 4C | 6F | 67 | 0D | 08 |
| | F4 | 55 | 73 | 65 | 72 | 50 | 77 | 64 | 3C | 03 | 01 | AD |
| | 9C | 3E | 05 | 21 | 01 | 01 | 01 | 01 | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1A

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS
- Bearer parameter:
- Precedence Class: 03
- Delay Class: 04
- Reliability Class: 03
- Peak throughput class: 04
- Mean throughput class: 31
- Packet data protocol: 02 (IP)

Buffer
- Buffer size: 1000

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 03 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

TERMINAL RESPONSE: OPEN CHANNEL 1.1.1B

Logically:

Command details
- Command number: 1
- Command type: OPEN CHANNEL
- Command qualifier: immediate link establishment

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Channel status: Channel identifier 1 and link established or PDP context activated

Bearer description
- Bearer type: GPRS

Bearer parameter:
Precedence Class: 00
Delay Class: 04
Reliability Class: 03
Peak throughput class: 04
Mean throughput class: 31
Packet data protocol: 02 (IP)
Buffer
Buffer size: 1000

Coding:

| BER-TLV: | 81 | 03 | 01 | 40 | 01 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 38 | 02 | 81 | 00 | 35 | 07 | 02 | 00 | 04 | 03 | 04 | 1F |
| | 02 | 39 | 02 | 03 | E8 | | | | | | | |

ENVELOPE: EVENT DOWNLOAD - Channel Status 1.1.1

Logically:

Event list
Event: Channel Status
Device identities
Source device: ME
Destination device: UICC
Channel status
Channel status: Channel 1, link dropped

Coding:

| BER-TLV: | D6 | 0B | 99 | 01 | 0A | 82 | 02 | 82 | 81 | B8 | 02 | 01 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 05 | | | | | | | | | | | |

#### 27.22.7.11.1.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1.

### 27.22.7.12 Access Technology Change event

TBD

### 27.22.7.13 Local Connection event

TBD

### 27.22.7.14 Network search mode change event

TBD

### 27.22.7.15 Browsing status event

TBD

# 27.22.8 MO SHORT MESSAGE CONTROL BY USIM

## 27.22.8.1 Definition and applicability

See clause 3.2.2.

## 27.22.8.2 Conformance requirement

The ME shall support the MO SEND SHORT MESSAGE CONTROL facility as defined in:

- TS 31.111 [15] clause 7.3.2.

The ME shall also support the SEND SMS facitily as specified in

- TS 31.111 [15] clause 6.4.10

## 27.22.8.3 Test purpose

To verify that for all SMS sending attempts, even those resulting from a SEND SHORT MESSAGE proactive UICC command, the ME shall first pass the RP_destination_address of the service center and the TP_Destination_Address to the UICC, using the ENVELOPE (MO Short Message CONTROL).

To verify that if the UICC responds with '90 00', the ME shall send the SMS with the address unchanged.

To verify that if the UICC responds with '93 00', the ME shall not send the SMS and may retry the command.

To verify that if the UICC returns response data, the ME shall use the response data appropriately to send the SM as proposed, not send the SM, or send the SM using the data supplied by the UICC.

To verify that, in the case where the initial SM request results from a proactive SEND SHORT MESSAGE, if the MO SMS CONTROL result is "not allowed" or "allowed with modifications", the ME shall inform the UICC using TERMINAL RESPONSE "interaction with call control by UICC or MO short message control by USIM, action not allowed".

## 27.22.8.4 Method of tests

### 27.22.8.4.1 Initial conditions

The ME is connected to the System Simulator and the USIM Simulator.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The MO SMS control service is available in the USIM Service Table.

The SMS service center address in the ME shall be set to '+112233445566778' prior to the execution of the tests.

The GERAN/UTRAN parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 01;
- Location Area Code (LAC) = 0001;
- Cell Identity value = 0001;

The PCS 1900 parameters of the system simulator are:

- Mobile Country Code (MCC) = 001;
- Mobile Network Code (MNC) = 011;
- Location Area Code (LAC) = 0001;

- Cell Identity value = 0001.

### 27.22.8.4.2 Procedure

**Expected Sequence 1.1 (MO SM CONTROL BY USIM , with Proactive command, Allowed, no modification')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC -> ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1 | |
| 2 | ME -> UICC | FETCH | |
| 3 | UICC -> ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1 | |
| 4 | ME -> USER | Display "Send SM" | [Alpha Identifier] |
| 5 | ME -> UICC | ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A<br>Or<br>ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 6 | UICC -> ME | MO SMS CONTROL RESULT 1.1.1 | [ 'Allowed, no modification'] |
| 7 | ME -> USS | Send SMS-PP Message 1.1 | [The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.1 without modification] |
| 8 | USS -> ME | SMS RP-ACK | |
| 9 | ME -> UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1 | |

PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: UICC
- Destination device: Network
- Alpha identifier: "Send SM"

Address
- TON: International number
- NPI: "ISDN / telephone numbering plan"
- Dialling number string "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "00"
- TP-DA
- TON International number
- NPI "ISDN / telephone numbering plan"
- Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
- Message coding 8-bit data
- Message class class 0
- TP-UDL 12
- TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | D0 | 37 | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 81 | 83 | 85 |
| | 07 | 53 | 65 | 6E | 64 | 20 | 53 | 4D | 86 | 09 | 91 | 11 |
| | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 8B | 18 | 01 | 00 | 09 |
| | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C | 54 | 65 | 73 |
| | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.1

Logically:

SMS RPDU
- RP-Originator Address not used
- RP-Destination SMSC Address
  - TON International number
  - NPI "ISDN / telephone numbering plan"
  - Address value "112233445566778"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "01"
- TP-DA
  - TON International number
  - NPI "ISDN / telephone numbering plan"
  - Address value "012345678"
- TP-PID Short message type 0
- TP-DCS
  - Message coding 8-bit data
  - Message class class 0
- TP-UDL 12
- TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 00 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | 18 |
| | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

ENVELOPE MO SHORT MESSAGE CONTROL 1.1.1A

Logically:

Device identities
- Source device: ME
- Destination device: UICC

RP Destination Address
- TON: International
- NPI: "ISDN / telephone numbering plan" or "unknown"
- Dialling number string '112233445566778'

TP Destination Address
- TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string '012345678'
Location Information
MCC & MNC the mobile country and network code (00F110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)
Extended Cell ID RNC-id value (for Rel-4 onwards), see also Note 3

Coding:

| Coding | D5 | Note 1 | 02 | 02 | 82 | 81 | 06 | 09 | 91 | 11 | 22 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 33 | 44 | 55 | 66 | 77 | F8 | 06 | 06 | 91 | 10 | 32 |
| | 54 | 76 | F8 | 13 | Note 2 | 00 | F1 | 10 | 00 | 01 | 00 |
| | 01 | Note 3 | | | | | | | | | |

Note 1: Length of BER-TLV is '20' plus the actual length of all the present optional SIMPLE-TLV data objects.

Note 2: Depending on the presence of the Extended Cell Identity Value the length is '07' or '09'

Note 3: The Extended Cell Identity Value is present in Rel-4 and onwards implementations, the values of the two bytes shall not be verified.

ENVELOPE MO SHORT MESSAGE CONTROL 1.1.1B

Logically:

Device identities
Source device: ME
Destination device: UICC
RP Destination Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string '112233445566778'
TP Destination Address
TON: International
NPI: "ISDN / telephone numbering plan" or "unknown"
Dialling number string '012345678'
Location Information
MCC & MNC the mobile country and network code (001110)
LAC the location Area Code (0001)
Cell ID Cell Identity Value (0001)

Coding:

| BER-TLV: | D5 | 20 | 02 | 02 | 82 | 81 | 06 | 09 | 91 | 11 | 22 |
|---|---|---|---|---|---|---|---|---|---|---|---|
| | 33 | 44 | 55 | 66 | 77 | F8 | 06 | 06 | 91 | 10 | 32 |
| | 54 | 76 | F8 | 13 | 07 | 00 | 11 | 10 | 00 | 01 | 00 |
| | 01 | | | | | | | | | | |

MO SHORT MESSAGE CONTROL RESULT 1.1.1

Logically:

MO Short Message control result : '00' = Allowed, no modification

Coding:

| | | |
|---|---|---|
| BER-TLV: | 00 | 00 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1

Logically:

Command details
- Command number: 1
- Command type: SEND SHORT MESSAGE
- Command qualifier: packing not required

Device identities
- Source device: ME
- Destination device: UICC

Result
- General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.2 (MO SM CONTROL BY USIM , with user SMS, Allowed, no modification')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | USER -> ME | The user makes a SMS with the user data 'Test Message' and sends it to +012345678. | [The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2. |
| 2 | ME -> UICC | ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A<br>or<br>ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC -> ME | MO SHORT MESSAGE CONTROL RESULT 1.1.1 | [ 'Allowed, no modification'] |
| 4 | ME -> USS | Send SMS-PP Message 1.2 | [The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.2 without modification] |
| 5 | USS -> ME | SMS RP-ACK | |

SMS-PP (SEND SHORT MESSAGE) Message 1.2

Logically:

SMS RPDU
- RP-Originator Address not used
- RP-Destination SMSC Address
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "112233445566778"

SMS TPDU
- TP-MTI: SMS-SUBMIT
- TP-RD: value shall not be verified
- TP-VPF: value shall not be verified
- TP-RP: value shall not be verified
- TP-UDHI: value shall not be verified
- TP-SRR: value shall not be verified
- TP-MR: "01"
- TP-DA

TON International number
NPI "ISDN / telephone numbering plan"
Address value "012345678"

Coding:

| Coding | 00 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F8 | Note 1 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | Note 2 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F8 | Note 3 | | |
| | | | | | | | | | | | | |

NOTE 1: Octet shall not be verified

NOTE 2: Only the TP-MTI bits shall be verified

NOTE 3: The remaining octets shall not be verified

**Expected Sequence 1.3 (MO SM CONTROL BY USIM , with Proactive command, Not allowed')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC -> ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1 | |
| 2 | ME -> UICC | FETCH | |
| 3 | UICC -> ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1 | |
| 4 | ME -> USER | Display "Send SM" | [Alpha Identifier] |
| 5 | ME -> UICC | ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1A<br>or<br>ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 6 | UICC -> ME | MO SHORT MESSAGE CONTROL RESULT 1.3.1 | [ 'not Allowed'] |
| 7 | ME -> UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1 | [ Permanent Problem - Interaction with Call Control or MO short message control by USIM ] |
| 8 | ME→ USS | The ME does not send the Short Message | |

MO SHORT MESSAGE CONTROL RESULT 1.3.1

Logically:

MO Short Message control result : '01' = Not Allowed

Coding:

| BER-TLV: | 01 | 00 |
|---|---|---|

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.3.1

Logically:

Command details
Command number: 01
Command Type: SEND SHORT MESSAGE
Command qualifier: packing not required
Device identities
Source device: ME
Destination device: UICC
Result
General Result: Interaction with call control or MO-SM by USIM permanent problem
Additional information: Action not allowed

Coding:

| | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 02 | 39 |
| | 01 | | | | | | | | | | | |

**Expected Sequence 1.4 (MO SM CONTROL BY USIM , with user SMS, Not allowed ')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | USER -> ME | The user makes a SMS with the user data 'Test Message' and sends it to +012345678. | [The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2. |
| 2 | ME -> UICC | ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1A<br>or<br>ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC -> ME | MO SM CONTROL RESULT 1.3.1 | [ 'Not allowed'] |
| 4 | ME → USS | The ME does not send the Short Message | |

**Expected Sequence 1.5 (MO SM CONTROL BY USIM , with Proactive command, Allowed with modifications')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC -> ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1 | |
| 2 | ME -> UICC | FETCH | |
| 3 | UICC -> ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1 | Send SMS to '+012345678' |
| 4 | ME -> USER | Display "Send SM" | [Alpha Identifier] |
| 5 | ME -> UICC | ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A<br>or<br>ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 6 | UICC -> ME | MO SM CONTROL RESULT 1.5.1 | ['Allowed with modifications'] |
| 7 | ME -> USS | Send SMS-PP Message 1.5 | [The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.5 with the data provided by the UICC to the changed Service Center Address '+112233445566779' ] |
| 8 | USS -> ME | SMS RP-ACK | |
| 9 | ME -> UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1 | |

MO SHORT MESSAGE CONTROL RESULT 1.5.1

Logically:

MO Short Message control result : '02' = Allowed with modifications

RP Destination_Address of the Service Center

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string: '112233445566779'

TP Destination Address

TON: International

NPI: "ISDN / telephone numbering plan" or "unknown"

Dialling number string: '012345679'

Coding:

| | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|
| 02 | 13 | 86 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 |
| 77 | F9 | 86 | 06 | 91 | 10 | 32 | 54 | 76 | F9 | |
| | | | | | | | | | | |

SMS-PP (SEND SHORT MESSAGE) Message 1.5

Logically:

SMS RPDU
- RP-Originator Address not used
- RP-Destination SMSC Address
  - TON International number
  - NPI "ISDN / telephone numbering plan"
  - Address value "112233445566779"

SMS TPDU
- TP-MTI SMS-SUBMIT
- TP-RD Instruct the SC to accept an SMS-SUBMIT for a SM
- TP-VPF TP-VP field not present
- TP-RP TP-Reply-Path is not set in this SMS-SUBMIT
- TP-UDHI The TP-UD field contains only the short message
- TP-SRR A status report is not requested
- TP-MR "01"
- TP-DA
  - TON International number
  - NPI "ISDN / telephone numbering plan"
  - Address value "012345679"
- TP-PID Short message type 0
- TP-DCS
  - Message coding 8-bit data
  - Message class class 0
- TP-UDL 12
- TP-UD "Test Message"

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| Coding | 00 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F9 | 18 |
| | 01 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F9 | 40 | F4 | 0C |
| | 54 | 65 | 73 | 74 | 20 | 4D | 65 | 73 | 73 | 61 | 67 | 65 |

TERMINAL RESPONSE: SEND SHORT MESSAGE 1.5.1

Logically:
- Command details
  - Command number: 01
  - Command Type: SEND SHORT MESSAGE
  - Command qualifier: packing not required
- Device identities
  - Source device: ME
  - Destination device: UICC
- Result
  - General Result: Command performed successfully

Coding:

| | | | | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| BER-TLV: | 81 | 03 | 01 | 13 | 00 | 82 | 02 | 82 | 81 | 83 | 01 | 00 |

**Expected Sequence 1.6 (MO SM CONTROL BY USIM , with user SMS, Allowed with modifications')**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | USER -> ME | The user makes a SMS with the user data 'Test Message' and sends it to +012345678. | [The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2. |
| 2 | ME -> UICC | ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1A<br>or<br>ENVELOPE: MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC -> ME | MO SM CONTROL RESULT 1.5.1 | [ 'Allowed with modifications'] |
| 4 | ME-> USS | Send SMS-PP Message 1.6 | [The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1. 6 with the data provided by the UICC to the changed Service Center Address '+112233445566779'] |
| 5 | USS -> ME | SMS RP-ACK | |

SMS-PP (SEND SHORT MESSAGE) Message 1.6

Logically:

SMS RPDU
- RP-Originator Address not used
- RP-Destination SMSC Address
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "112233445566779"

SMS TPDU
- TP-MTI: SMS-SUBMIT
- TP-RD: value shall not be verified
- TP-VPF: value shall not be verified
- TP-RP: value shall not be verified
- TP-UDHI: value shall not be verified
- TP-SRR: value shall not be verified
- TP-MR: "01"
- TP-DA
  - TON: International number
  - NPI: "ISDN / telephone numbering plan"
  - Address value: "012345679"

Coding:

| Coding | 00 | 09 | 91 | 11 | 22 | 33 | 44 | 55 | 66 | 77 | F9 | Note 1 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | Note 2 | 01 | 09 | 91 | 10 | 32 | 54 | 76 | F9 | Note 3 | | |
| | | | | | | | | | | | | |

NOTE 1: Octet shall not be verified.

NOTE 2: Only the TP-MTI bits shall be verified.

NOTE 3: The remaining octets shall not be verified.

**Expected Sequence 1.7 (MO SM CONTROL BY USIM , with Proactive command, the USIM responds with '90 00', Allowed, no modification)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | UICC -> ME | PROACTIVE COMMAND PENDING: SEND SHORT MESSAGE 1.1.1 | |
| 2 | ME -> UICC | FETCH | |
| 3 | UICC -> ME | PROACTIVE COMMAND: SEND SHORT MESSAGE 1.1.1 | Send SMS to '+012345678' |
| 4 | ME -> USER | Display "Send SM" | [Alpha Identifier] |
| 5 | ME -> UICC | ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1A<br>or<br>ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 6 | UICC -> ME | 90 00 | |
| 7 | ME ->USS | Send SMS-PP | [The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.1 without modification] |
| 8 | USS -> ME | SMS RP-ACK | |
| 9 | ME -> UICC | TERMINAL RESPONSE: SEND SHORT MESSAGE 1.1.1 | |

**Expected Sequence 1.8 (MO SM CONTROL BY USIM , Send Short Message attempt by user, the USIM responds with '90 00', Allowed, no modification)**

| Step | Direction | Message / Action | Comments |
|---|---|---|---|
| 1 | User → ME | The user makes a SMS with the user data 'Test Message' and sends it to +012345678. | [The data entered and the ME settings shall lead to the same SMS-TPDU as defined in SMS-PP (SEND SHORT MESSAGE) Message 1.2. |
| 2 | ME → UICC | ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1 A<br>or<br>ENVELOPE : MO SHORT MESSAGE CONTROL 1.1.1B | [Option A shall apply for GERAN/UTRAN parameters]<br>[Option B shall apply for PCS1900 parameters] |
| 3 | UICC → ME | 90 00 | |
| 4 | ME → USS | Send SMS-PP | [The ME sends the SM containing SMS-PP (SEND SHORT MESSAGE) Message 1.2 without modification] |
| 5 | USS -> ME | SMS RP-ACK | |

Expected Sequence 1.9void

### 27.22.8.5 Test requirement

The ME shall operate in the manner defined in expected sequences 1.1 to 1.9.

## 27.22.9 Handling of command number

### 27.22.9.1 Definition and applicability

See clause 3.2.2.

### 27.22.9.2 Conformance requirement

The ME shall support the facility as defined in ETSI TS 102 223 [16] clause 6.5.1, clause 6.8 and clause 8.6

### 27.22.9.3 Test purpose

To verify that the ME sends a Terminal Response with the Command number equivalent to the value in the corresponding proactive command.

## 27.22.9.4 Method of tests

### 27.22.9.4.1 Initial conditions

The ME is connected to the USIM Simulator.

The elementary files are coded as Toolkit default.

Prior to this test the ME shall have been powered on and performed the PROFILE DOWNLOAD procedure.

The ME screen shall be in its normal stand-by display.

The ME shall support the DISPLAY TEXT command.

### 27.22.9.4.2 Procedure

**Expected Sequence 1.1 (DISPLAY TEXT normal priority, Unpacked 8 bit data for Text String, successful)**

See ETSI TS 102 384 [26] in subclause 27.22.9.4.2, Expected Sequence 1.1.

## 27.22.9.5 Test requirement

The ME shall operate in the manner defined in expected sequence 1.1

# Annex A (normative): Details of Test-SIM (TestSIM)

The TestSIM shall be able to present the following data:

ANSWER TO RESET

Logically:

| | |
|---|---|
| TS (Initial character): | '3B' |
| T0 (Format character): | '86' (Following interface characters: TD(1), number of historical characters: 6) |
| TD1: | '00' (Following interface characters: none, Transfer protocol: T=0) |
| T1: | 91 |
| T2: | 99 |
| T3: | 00 |
| T4: | 12 |
| T5: | C1 |
| T6: | 00 |

Coding:

| | | | | | | | | | |
|---|---|---|---|---|---|---|---|---|---|
| Coding: | 3B | 86 | 00 | 91 | 99 | 00 | 12 | C1 | 00 |

1. For a successful outcome of the command "Select MasterFile" the TestSIM shall send SW1/SW2 "9F 1B".

2. For a successful outcome of the command "Get Response with Length 1B" on the MasterFile the TestSIM shall respond:

| | |
|---|---|
| RFU: | '00 00' |
| Not allocated memory: | '653 bytes' |
| File ID: | Master File |
| Type of file: | MF |
| RFU: | 00 00 22 FF 01' |
| Length of following data: | 14 bytes' |
| File characteristics: | |
| Clock Stop: | Not allowed |
| Min. frequency for GSM algorithm: | 13/8 MHz |
| Technology identification: | 3V Technology SIM |
| CHV1: | disabled |
| DFs in current directory: | 2 |
| EFs in current directory: | 8 |
| Number of CHV and admin. Codes: | 3 |
| RFU byte 18: | 00 |
| CHV1 status: | |
| False representations remaining: | 3 |
| RFU-bits 7-5: | 000 |
| Secret code: | Initialized |
| Unlock CHV1 status: | |
| False representations remaining: | 10 |
| RFU-bits 7-5: | 000 |
| Secret code: | Initialized |
| CHV2 status: | |
| False representations remaining: | 3 |
| RFU-bits 7-5: | 000 |
| Secret code: | Initialized |
| Unlock CHV2 status: | |
| False representations remaining: | 10 |
| RFU-bits 7-5: | 000 |
| Secret code: | Initialized |

RFU bytes 23: 00
Reserved for admin. management: 00 83 00 FF
Status Words
SW1 / SW2: Normal ending of command

Coding:

| Coding | 00 | 00 | 02 | 8D | 3F | 00 | 01 | 00 | 00 | 22 | FF | 01 |
|---|---|---|---|---|---|---|---|---|---|---|---|---|
| | 0E | 9B | 02 | 08 | 03 | 00 | 83 | 8A | 83 | 8A | 00 | 00 |
| | 83 | 00 | FF | 90 | 00 | | | | | | | |

1. For a successful outcome of the command "Select GSM" the TestSIM shall send SW1/SW2 "9F 1B".
2. For a successful outcome of the command "Select PLMN" the TestSIM shall send SW1/SW2 "9F 0F".
3. $EF_{PLMN}$ Information:

RFU-Bytes 1-2: 00 00
File size: 102 bytes
File ID: 6F30
Type of File: Elementary file
Byte 8
RFU: 00
Access Condition:
UPDATE: CHV1
READ/SEEK: CHV1
RFU-bits 4-1: 1111
INCREASE: NEVER
INVALIDATE: NEVER
REHABILITATE: NEVER
File Status:
Invalidation status: File not invalidated
Readable/updateable: Not readable/updatable when invalidated
RFU-bits 8-4, 2: 0000 0
Length of following data: 2 bytes
Structure: Transparent
Length of record: 00

The initial coding of the $EF_{PLMN}$ shall be FF FF ... FF (logically: Empty).

# Annex B (normative): Details of terminal profile support

**Table E.1: TERMINAL PROFILE support**

| Item | Byte.bit | Terminal Profile | Ref. | Release | Status | Support | Mnemonic |
|---|---|---|---|---|---|---|---|
| 1 | 1.1 | Profile Download | TS 31.111 §5.2 | R99 | M | | PD_Pro_Dvnl |
| 2 | 1.2 | SMS-PP data download | TS 31.111 §5.2 | R99 | M | | PD_SMS_PP |
| 3 | 1.3 | Cell Broadcast data download | TS 31.111 §5.2 | R99 | M | | PD_CB |
| 4 | 1.4 | Menu selection | TS 31.111 §5.2 | R99 | M | | PD_Menu_sel |
| 5 | 1.5 | Bit =1 if SMS-PP data Download supported | TS 31.111 §5.2 | R99 | M | | PD_SMS_PP |
| 6 | 1.6 | Timer expiration | TS 31.111 §5. | R99 | M | | PD_TExpir |
| 7 | 1.7 | Bit=1 if Call control supported | TS 31.111 §5.2. | R99 | M | | PD_CC |
| 8 | 1.8 | Bit=1 if Call control supported | TS 31.111 §5.2 | R99 | M | | PD_CC |
| 9 | 2.1 | Command result | TS 31.111 §5.2 | R99 | M | | PD_Cmd_Res |
| 10 | 2.2 | Call Control by USIM | TS 31.111 §5.2 | R99 | M | | PD_CC |
| 11 | 2.3 | Bit=1 if Call control supported | TS 31.111 §5.2 | R99 | M | | PD_CC |
| 12 | 2.4 | MO short message control by USIM | TS 31.111 §5.2 | R99 | M | | PD_MO_SMS_CC |
| 13 | 2.5 | Bit=1 if Call control supported | TS 31.111 §5.2 | R99 | M | | PD_CC |
| 14 | 2.6 | UCS2 Entry supported | TS 31.111 §5.2 | R99 | C203 | | PD_UCS2_entry |
| 15 | 2.7 | UCS2 Display supported | TS 31.111 §5.2 | R99 | C204 | | PD_UCS2_Display |
| 16 | 2.8 | Bit=1 if Display Text supported | TS 31.111 §5.2 | R99 | M | | PD_Display_Text |
| 17 | 3.1 | DISPLAY TEXT | TS 31.111 §5.2 | R99 | M | | PD_Display_Text |
| 18 | 3.2 | GET INKEY | TS 31.111 §5.2 | R99 | M | | PD_Get_Inkey |
| 19 | 3.3 | GET INPUT | TS 31.111 §5.2 | R99 | M | | PD_Get_Input |
| 20 | 3.4 | MORE TIME | TS 31.111 §5.2 | R99 | M | | PD_More_Time |
| 21 | 3.5 | PLAY TONE | TS 31.111 §5.2 TS 11.14, 5 | R99 | M | | PD_Play_Tone |
| 22 | 3.6 | POLL INTERVAL | TS 31.111 §5.2 TS 11.14, 5 | R99 | M | | PD_Poll_interval |
| 23 | 3.7 | POLLING OFF | TS 31.111 §5.2 | R99 | M | | PD_Polling_Off |
| 24 | 3.8 | REFRESH | TS 31.111 §5.2 | R99 | M | | PD_Refresh |
| 25 | 4.1 | SELECT ITEM | TS 31.111 §5.2 | R99 | M | | PD_Select_Item |
| 26 | 4.2 | SEND SHORT MESSAGE | TS 31.111 §5.2 | R99 | M | | PD_Send_SMS |
| 27 | 4.3 | SEND SS | TS 31.111 §5.2 | R99 | M | | PD_Send_SS |
| 28 | 4.4 | SEND USSD | TS 31.111 §5.2 | R99 | M | | PD_Send_USSD |
| 29 | 4.5 | SET UP CALL | TS 31.111 §5.2 | R99 | M | | PD_SetUp_Call |
| 30 | 4.6 | SET UP MENU | TS 31.111 §5.2 | R99 | M | | PD_SetUp_Menu |
| 31 | 4.7 | PROVIDE LOCAL INFORMATION (LOCI & IMEI) | TS 31.111 §5.2 | R99 | M | | PD_Provide_Local |
| 32 | 4.8 | PROVIDE LOCAL INFORMATION (NMR) | TS 31.111 §5.2 | R99 | M | | PD_Provide_Local_NMR |
| 33 | 5.1 | SET UP EVENT LIST | TS 31.111 §5.2 | R99 | M | | PD_Setup_Evt_List |
| 34 | 5.2 | Event: MT call | TS 31.111 §5.2 | R99 | M | | PD_MT_Call |
| 35 | 5.3 | Event: Call connected | TS 31.111 §5.2 | R99 | M | | PD_Call_Conn |
| 36 | 5.4 | Event: Call disconnected | TS 31.111 §5.2 | R99 | M | | PD_Call_Disc |
| 37 | 5.5 | Event: Location status | TS 31.111 §5.2 | R99 | M | | PD_Loc_Status |
| 38 | 5.6 | Event: User activity | TS 31.111 §5.2 | R99 | M | | PD_User_Act |
| 39 | 5.7 | Event: Idle screen available | TS 31.111 §5.2 | R99 | M | | PD_Idle_Scr_Avail |
| 40 | 5.8 | Event: Card reader status | TS 31.111 §5.2 | R99 | C206 | | PD_Evt_Rdr_Status |
| 41 | 6.1 | Event: Language selection | TS 31.111 §5.2 | R99 | M | | PD_Lang_Select |

| Item | Byte.bit | Terminal Profile | Ref. | Release | Status | Support | Mnemonic |
|---|---|---|---|---|---|---|---|
| 42 | 6.2 | Event: Browser Termination | TS 31.111 §5.2 | R99 | C212 | | PD_Browser_Term |
| 43 | 6.3 | Event: Data available | TS 31.111 §5.2 | R99 | C223 | | PD_Data_Avail |
| 44 | 6.4 | Event: Channel status | TS 31.111 §5.2 | R99 | C223 | | PD_Evt_Ch_Status |
| 45 | 6.5 | Event:Access Technology Change | TS 31.111 §5.2 | Rel-4 | M | | PD_Evt_ATC |
| 46 | 6.6 | Event: Display Parameters Changed | TS 31.111 §5.2 | Rel-4 | C218 | | PD_Disp_Resiz |
| 47 | 6.7 | Event: Local Connection | TS 31.111 §5.2 | Rel-4 | M | | PD_Evt_LC |
| 48 | 6.8 | Event: Network Search Mode Change | TS 31.111 §5.2 | Rel-6 | M | | PD_Evt_NSMC |
| 49 | 7.1 | POWER ON CARD | TS 31.111 §5.2 | R99 | C206 | | PD_C_On |
| 50 | 7.2 | POWER OFF CARD | TS 31.111 §5.2 | R99 | C206 | | PD_C_Off |
| 51 | 7.3 | PERFORM CARD APDU | TS 31.111 §5.2 | R99 | C206 | | PD_C_APDU |
| 52 | 7.4 | GET READER STATUS (Card reader status) | TS 31.111 §5.2 | R99 | C206 | | PD_Get_Rdr_Status |
| 53 | 7.5 | GET READER STATUS (Card reader identifier) | TS 31.111 §5.2 | R99 | C208 | | PD_Get_Rdr_Id |
| 54 | 7.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_54 |
| 55 | 7.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_55 |
| 56 | 7.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_56 |
| 57 | 8.1 | TIMER MANAGEMENT (start, stop) | TS 31.111 §5.2 | R99 | M | | PD_Timer_Mgt_Start_Stop |
| 58 | 8.2 | TIMER MANAGEMENT (get current value) | TS 31.111 §5.2 | R99 | M | | PD_Timer_Val |
| 59 | 8.3 | PROVIDE LOCAL INFORMATION (date, time and time zone) | TS 31.111 §5.2 | R99 | M | | PD_Provide_Local_D_Time |
| 60 | 8.4 | Bit=1 if Get Inkey | TS 31.111 §5.2 | R99 | M | | PD_Get_Inkey |
| 61 | 8.5 | SET UP IDLE MODE TEXT | TS 31.111 §5.2 | R99 | M | | PD_Stup_Id_Mod_Txt |
| 62 | 8.6 | RUN AT COMMAND (i.e. class "b" is supported) | TS 31.111 §5.2 | R99 | C209 | | PD_Run_AT |
| 63 | 8.7 | Bit=1 if Set UpCall | TS 31.111 §5.2 | R99 | M | | PD_SetUp_Call |
| 64 | 8.8 | Bit=1 if Call Control | TS 31.111 §5.2 | R99 | M | | PD_CC |
| 65 | 9.1 | Bit=1 if Display Text | TS 31.111 §5.2 | R99 | M | | PD_Display_Text |
| 66 | 9.2 | SEND DTMF command | TS 31.111 §5.2 | R99 | M | | PD_Send_DTMF |
| 67 | 9.3 | Bit = 1 if Provide Local Information (NMR) supported | TS 31.111 §5.2 | R99 | M | | PD_Provide_Local |
| 68 | 9.4 | PROVIDE LOCAL INFORMATION (language) | TS 31.111 §5.2 | R99 | M | | PD_Provide_Local_LS |
| 69 | 9.5 | PROVIDE LOCAL INFORMATION (Timing Advance) | TS 31.111 §5.2 | R99 | M | | PD_Provide_Local_TA |
| 70 | 9.6 | LANGUAGE NOTIFICATION | TS 31.111 §5.2 | R99 | M | | PD_Lang_Notif |
| 71 | 9.7 | LAUNCH BROWSER | TS 31.111 §5.2 | R99 | C212 | | PD_Launch_Brws |
| 72 | 9.8 | PROVIDE LOCAL INFORMATION (Access Technology) | TS 31.111 §5.2 | Rel-4 | M | | PD_Provide_Local_AT |
| 73 | 10.1 | Soft keys support for SELECT ITEM | TS 31.111 §5.2 | R99 | C213 | | PD_Softkey_Select_Item |
| 74 | 10.2 | Soft Keys support for SET UP MENU | TS 31.111 §5.2 | R99 | C213 | | PD_Softkey_SetUp_Menu |
| 75 | 10.3 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_75 |
| 76 | 10.4 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_76 |
| 77 | 10.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_77 |
| 78 | 10.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_78 |
| 79 | 10.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_79 |
| 80 | 10.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_80 |
| 81 | 11.1 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |

| Item | Byte.bit | Terminal Profile | Ref. | Release | Status | Support | Mnemonic |
|---|---|---|---|---|---|---|---|
| 82 | 11.2 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 83 | 11.3 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 84 | 11.4 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 85 | 11.5 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 86 | 11.6 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 87 | 11.7 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 88 | 11.8 | Maximum number of soft keys available ('FF' = RFU) | TS 31.111 §5.2 | R99 | C214 | | PD_Max_SoftKey |
| 89 | 12.1 | OPEN CHANNEL | TS 31.111 §5.2 | R99 | C223 | | PD_Open_Ch |
| 90 | 12.2 | CLOSE CHANNEL | TS 31.111 §5.2 | R99 | C223 | | PD_Close_Ch |
| 91 | 12.3 | RECEIVE DATA | TS 31.111 §5.2 | R99 | C223 | | PD_Rx_Data |
| 92 | 12.4 | SEND DATA | TS 31.111 §5.2 | R99 | C223 | | PD_Send_Data |
| 93 | 12.5 | GET CHANNEL STATUS | TS 31.111 §5.2 | R99 | C223 | | PD_Get_Ch_Status |
| 94 | 12.6 | SERVICE SEARCH | TS 31.111 §5.2 | Rel-4 | C224 | | PD_Serv_Search |
| 95 | 12.7 | GET SERVICE INFORMATION | TS 31.111 §5.2 | Rel-4 | C224 | | PD_Get_Serv_Info |
| 96 | 12.8 | DECLARE SERVICE | TS 31.111 §5.2 | Rel-4 | C224 | | PD_Declare_Serv |
| 97 | 13.1 | CSD supported by ME | TS 31.111 §5.2 | R99 | C207 | | PD_CSD |
| 98 | 13.2 | GPRS supported by ME | TS 31.111 §5.2 | R99 | C222 | | PD_GPRS |
| 99 | 13.3 | Bluetooth supported by terminal | TS 31.111 §5.2 | Rel-4 | C225 | | PD_BT |
| 100 | 13.4 | IrDA Supported by terminal | TS 31.111 §5.2 | Rel-4 | C226 | | PD_IrDA |
| 101 | 13.5 | RS232 Supported by terminal | TS 31.111 §5.2 | Rel-4 | C227 | | PD_RS232 |
| 102 | 13.6 | Number of channels supported by ME | TS 31.111 §5.2 | R99 | C257 | | PD_Nb_Channel |
| 103 | 13.7 | Number of channels supported by ME | TS 31.111 §5.2 | R99 | C257 | | PD_Nb_Channel |
| 104 | 13.8 | Number of channels supported by ME | TS 31.111 §5.2 | R99 | C257 | | PD_Nb_Channel |
| 105 | 14.1 | Number of characters supported down the ME | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char |
| 106 | 14.2 | Number of characters supported down the ME | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char |
| 107 | 14.3 | Number of characters supported down the ME | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char |
| 108 | 14.4 | Number of characters supported down the ME | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char |
| 109 | 14.5 | Number of characters supported down the ME | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char |
| 110 | 14.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_110 |
| 111 | 14.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_111 |
| 112 | 14.8 | Screen Sizing Parameters | TS 31.111 §5.2 | R99 | C216 | | PD_Screen_Siz |
| 113 | 15.1 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |
| 114 | 15.2 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |
| 115 | 15.3 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |
| 116 | 15.4 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |
| 117 | 15.5 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |

| Item | Byte.bit | Terminal Profile | Ref. | Release | Status | Support | Mnemonic |
|---|---|---|---|---|---|---|---|
| 118 | 15.6 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |
| 119 | 15.7 | Number of characters supported across the ME display | TS 31.111 §5.2 | R99 | C217 | | PD_Nb_Char_Disp |
| 120 | 15.8 | Variable size fonts Supported | TS 31.111 §5.2 | R99 | C217 | | PD_Var_Font |
| 121 | 16.1 | Display can be resized | TS 31.111 §5.2 | R99 | C218 | | PD_Disp_Resiz |
| 122 | 16.2 | Text Wrapping supported | TS 31.111 §5.2 | R99 | C218 | | PD_Txt_Wrap |
| 123 | 16.3 | Text Scrolling supported | TS 31.111 §5.2 | R99 | C218 | | PD_Txt_Scroll |
| 124 | 16.4 | Text attributes supported | TS 31.111 §5.2 | Rel-5 | C228 | | PD_Text_Attrib |
| 125 | 16.5 | RFU | TS 11.14, 5 | R96 | X | | PD_RFU_125 |
| 126 | 16.6 | Width reduction when in a menu | TS 31.111 §5.2 | R99 | C217 | | PD_Width_Reduc |
| 127 | 16.7 | Width reduction when in a menu | TS 31.111 §5.2 | R99 | C217 | | PD_Width_Reduc |
| 128 | 16.8 | Width reduction when in a menu | TS 31.111 §5.2 | R99 | C217 | | PD_Width_Reduc |
| 129 | 17.1 | TCP | TS 31.111 §5.2 | R99 | C220 | | PD_TCP |
| 130 | 17.2 | UDP | TS 31.111 §5.2 | R99 | C221 | | PD_UDP |
| 131 | 17.3 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_131 |
| 132 | 17.4 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_132 |
| 133 | 17.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_133 |
| 134 | 17.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_134 |
| 135 | 17.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_135 |
| 136 | 17.8 | HSDPA supported by ME | TS 31.111 §5.2 | Rel-6 | C258 | | PD_ HSDPA |
| 137 | 18.1 | DISPLAY TEXT (Variable time out) | TS 31.111 §5.2 | Rel-4 | C229 | | |
| 138 | 18.2 | GET INKEY (help is supported while waiting for immediate response or variable time out) | TS 31.111 §5.2 | Rel-4 | C231 | | |
| 139 | 18.3 | USB supported by ME | TS 31.111 §5.2 | Rel-4 | C232 | | |
| 140 | 18.4 | GET INKEY (Variable time out) | TS 31.111 §5.2 | Rel-4 | C229 | | |
| 141 | 18.5 | PROVIDE LOCAL INFORMATION (ESN) | See 3GPP2 | R99 | X | | Reserved |
| 142 | 18.6 | CALL CONTROL on GPRS | TS 31.111 §5.2 | Rel-5 | C242 | | PD_CC_GPRS |
| 143 | 18.7 | PROVIDE LOCAL INFORMATION (IMEISV) | TS 31.111 §5.2 | Rel-6 | M | | PD_Provide_Local_SV |
| 144 | 18.8 | PROVIDE LOCAL INFORMATION (search mode change) | TS 31.111 §5.2 | Rel-6 | M | | PD_Provide_Local_SMC |
| 145 | 19.1 | Protocol Version | TS 31.111 §5.2 | R99 | X | | Reserved |
| 146 | 19.2 | Protocol Version | TS 31.111 §5.2 | R99 | X | | Reserved |
| 147 | 19.3 | Protocol Version | TS 31.111 §5.2 | R99 | X | | Reserved |
| 148 | 19.4 | Protocol Version | TS 31.111 §5.2 | R99 | X | | Reserved |
| 149 | 19.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_149 |
| 150 | 19.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_150 |
| 151 | 19.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_151 |
| 152 | 19.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_152 |
| 153 | 20.1 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 154 | 20.2 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 155 | 20.3 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 156 | 20.4 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 157 | 20.5 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |

| Item | Byte.bit | Terminal Profile | Ref. | Release | Status | Support | Mnemonic |
|---|---|---|---|---|---|---|---|
| 158 | 20.6 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 159 | 20.7 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 160 | 20.8 | Reserved by TIA/EIA/IS-820 [25] | TS 31.111 §5.2 | R99 | X | | Reserved |
| 161 | 21.1 | WML browser supported | TS 31.111 §5.2 | Rel-6 | C233 | | PD_WML |
| 162 | 21.2 | XHTML browser supported | TS 31.111 §5.2 | Rel-6 | C234 | | PD_XHTML |
| 163 | 21.3 | HTML browser supported | TS 31.111 §5.2 | Rel-6 | C235 | | PD_HTML |
| 164 | 21.4 | CHTML browser supported | TS 31.111 §5.2 | Rel-6 | C236 | | PD_CHTML |
| 165 | 21.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_165_ |
| 166 | 21.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_166 |
| 167 | 21.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_167 |
| 168 | 21.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_168 |
| 169 | 22.1 | Support of UTRAN PS with extended parameters | TS 31.111 §5.2 | Rel-6 | C259 | | PD_UTRAN_PS_Ext_Param |
| 170 | 22.2 | PROVIDE LOCAL INFORMATION (Battery state) if class 'g' supported | TS 31.111 §5.2 | Rel-6 | C239 | | PD_Provide_Local_Batt |
| 171 | 22.3 | PLAY TONE (Melody tones & themed tones supported) | TS 31.111 §5.2 | Rel-6 | C241 | | PD_Tones |
| 172 | 22.4 | Multi-media in SET UP CALL supported (if class 'h' supported) | TS 31.111 §5.2 | Rel-6 | C240 | | PD_Xmedia_Call |
| 173 | 22.5 | MMS Management (class 'j' supported) | TS 31.111 §5.2 | Rel-6 | C238 | | PD_MMS |
| 174 | 22.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_174 |
| 175 | 22.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_175 |
| 176 | 22.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_176 |
| 177 | 23.1 | SET FRAMES supported (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C237 | | PD_Set_Frames |
| 178 | 23.2 | GET FRAMES STATUS supported (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C237 | | PD_Get_Frames_Stat |
| 179 | 23.3 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_179 |
| 180 | 23.4 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_180 |
| 181 | 23.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_181 |
| 182 | 23.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_182 |
| 183 | 23.7 | PROVIDE LOCAL INFORMATION (UTRAN NMR) | TS 31.111 §5.2 | Rel-6 | M | | PD_Provide_Local_NMR |
| 184 | 23.8 | USSD Data Download and application mode | TS 31.111 §5.2 | Rel-6 | M | | PD_USSD_DD |
| 185 | 24.1 | Maximum number of frames supported (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C256 | | PD_Max_Frames |
| 186 | 24.2 | Maximum number of frames supported (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C256 | | PD_Max_Frames |
| 187 | 24.3 | Maximum number of frames supported (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C256 | | PD_Max_Frames |
| 188 | 24.4 | Maximum number of frames supported (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C256 | | PD_Max_Frames |
| 189 | 24.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_189 |
| 190 | 24.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_190 |
| 191 | 24.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_191 |
| 192 | 24.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_192 |
| 193 | 25.1 | Event: browsing status | TS 31.111 §5.2 | Rel-6 | M | | PD_Browser_Stat |
| 194 | 25.2 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_194 |
| 195 | 25.3 | Event Frame parameters changed (if class 'i' supported) | TS 31.111 §5.2 | Rel-6 | C237 | | PD_Event_Frames |

| Item | Byte.bit | Terminal Profile | Ref. | Release | Status | Support | Mnemonic |
|---|---|---|---|---|---|---|---|
| 196 | 25.4 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_196 |
| 197 | 25.5 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_197 |
| 198 | 25.6 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_198 |
| 199 | 25.7 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_199 |
| 200 | 25.8 | RFU | TS 31.111 §5.2 | R99 | X | | PD_RFU_200 |
| 201 | 26.1 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_201 |
| 202 | 26.2 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_202 |
| 203 | 26.3 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_203 |
| 204 | 26.4 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_204 |
| 205 | 26.5 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_205 |
| 206 | 26.6 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_206 |
| 207 | 26.7 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_207 |
| 208 | 26.8 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_208 |
| 209 | 27.1 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_209 |
| 210 | 27.2 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_210 |
| 211 | 27.3 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_211 |
| 212 | 27.4 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_212 |
| 213 | 27.5 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_213 |
| 214 | 27.6 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_214 |
| 215 | 27.7 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_215 |
| 216 | 27.8 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_216 |
| 217 | 28.1 | Alignment left supported | TS 31.111 §5.2 | Rel-5 | C243 | | PD_Text_Attrib_Left |
| 218 | 28.2 | Alignment center supported | TS 31.111 §5.2 | Rel-5 | C244 | | PD_Text_Attrib_Center |
| 219 | 28.3 | Alignment right supported | TS 31.111 §5.2 | Rel-5 | C245 | | PD_Text_Attrib_Right |
| 220 | 28.4 | Font size normal supported | TS 31.111 §5.2 | Rel-5 | C246 | | PD_Text_Attrib_Normal |
| 221 | 28.5 | Font size large supported | TS 31.111 §5.2 | Rel-5 | C247 | | PD_Text_Attrib_Large |
| 222 | 28.6 | Font size small supported | TS 31.111 §5.2 | Rel-5 | C248 | | PD_Text_Attrib_Small |
| 223 | 28.7 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_223 |
| 224 | 28.8 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_224 |
| 225 | 29.1 | Style normal supported | TS 31.111 §5.2 | Rel-5 | C249 | | PD_Text_Attrib_Styl_Norm |
| 226 | 29.2 | Style bold supported | TS 31.111 §5.2 | Rel-5 | C250 | | PD_Text_Attrib_Styl_Bold |
| 227 | 29.3 | Style italic supported | TS 31.111 §5.2 | Rel-5 | C251 | | PD_Text_Attrib_Styl_Italic |
| 228 | 29.4 | Style underlined supported | TS 31.111 §5.2 | Rel-5 | C252 | | PD_Text_Attrib_Styl_Underl |
| 229 | 29.5 | Style strikethrough supported | TS 31.111 §5.2 | Rel-5 | C253 | | PD_Text_Attrib_Styl_Strik |
| 230 | 29.6 | Style text foreground colour supported | TS 31.111 §5.2 | Rel-5 | C254 | | PD_Text_Attrib_Styl_Text_Fore |
| 231 | 29.7 | Style text background colour supported | TS 31.111 §5.2 | Rel-5 | C255 | | PD_Text_Attrib_Styl_Text_Back |
| 232 | 29.8 | RFU | TS 31.111 §5.2 | Rel-6 | X | | PD_RFU_224 |

| | | |
|---|---|---|
| C201 | [void] | -- [void] |
| C202 | [void] | -- [void] |

| | | |
|---|---|---|
| C203 | IF A.1/3 THEN M | -- O_Ucs2_Entry |
| C204 | IF A.1/15 THEN M | -- O_Ucs2_Disp |
| C205 | [void] | -- [void] |
| C206 | IF A.1/7 THEN M | -- O_Dual_Slot |
| C207 | IF A.1/12 THEN M | -- O_BIP_CSD |
| C208 | IF (A.1/7 AND A.1/8) THEN M | -- O_Dual_Slot AND O_Detach_Rdr |
| C209 | IF A.1/9 THEN M | -- O_Run_At |
| C210 | [void] | -- [void] |
| C211 | [void] | -- [void] |
| C212 | IF A.1/10 THEN M | -- O_LB |
| C213 | IF A.1/11 THEN M for at least one of the bits 1 - 2 of byte 10 | -- O_Softkey |
| C214 | IF C213 THEN M for at least one, but not for all of the bits 1 - 8 of byte 11 | -- O_Softkey (parameters) |
| C215 | Void | -- Void |
| C216 | IF A.1/13 THEN M | -- O_Scr_Siz |
| C217 | IF C216 THEN bit values "0" / "1" allowed | -- O_Scr_Siz (parameters) |
| C218 | IF A.1/14 THEN M | -- O_Scr_Resiz |
| C219 | IF C218 THEN bit values "0" / "1" allowed | -- O_Scr_Resiz (parameters) |
| C220 | IF A.1/18 THEN M | -- O_TCP |
| C221 | IF A.1/17 THEN M | -- O_UDP |
| C222 | IF A.1/21 THEN M | -- O_BIP_GPRS |
| C223 | IF (C207 OR C222 OR C224) THEN M | -- O_BIP_CSD OR O_BIP_GPRS OR (O_BIP_Local AND (BIP_BT OR BIP_IrDA OR BIP_RS232 OR BIP_USB)) |
| C224 | IF (A1.26 AND (A.1/27 OR A.1/28 OR A.1/29 OR A.1/30)) THEN M | -- O_BIP_Local AND (BIP_BT OR BIP_IrDA OR BIP_RS232 OR BIP_USB)) |
| C225 | IF (A.1/26 AND A1.27) THEN M | -- O_BIP_Local AND O_BIP_BT |
| C226 | IF (A.1/26 AND A1.28) THEN M | -- O_BIP_Local AND O_BIP_IrDA |
| C227 | IF (A.1/26 AND A1.29) THEN M | -- O_BIP_Local AND O_BIP_RS232 |
| C228 | IF (A1./50 OR A.1/51 OR A.1/52 OR A.1/53 OR A.1/54 OR A.1/55 OR A.1/56 OR A.1/57 OR A.1/58 OR A.1/59 OR A.1/60 OR A.1/61 OR A.1/62) THEN M | -- O_TAT_AL OR O_TAT_AC OR O_TAT_AR OR O_TAT_FSN OR O_TAT_FSL OR O_TAT_FSS OR O_TAT_SN OR O_TAT_SB OR O_TAT_SI OR O_TAT_SU OR O_TAT_SS OR O_TAT_STFC OR O_TAT_STFB |
| C229 | IF A.1/24 THEN M | -- O_Duration |
| C230 | IF A.1/23 THEN M | -- O_Imm_Resp |
| C231 | IF (C229 OR C230) AND A1.5 THEN M | -- O_Help AND (O_Duration OR O_Imm_Resp) |
| C232 | IF (A.1/26 AND A.1/30) THEN M | -- O_BIP_Local AND O_USB |
| C233 | IF A.1/31 THEN M | -- O_WML |
| C234 | IF A.1/32 THEN M | -- O_XHTML |
| C235 | IF A.1/33 THEN M | -- O_HTML |
| C236 | IF A.1/34 THEN M | -- O_CHTML |
| C237 | IF A.1/37 THEN M | -- O_Frames |
| C238 | IF A.1/38 THEN M | -- O_MMS |
| C239 | IF A.1/35 THEN M | -- O_Batt |
| C240 | IF A.1/36 THEN M | -- O_Xmedia Call |
| C241 | IF A.1/29 THEN M | -- O_Tones |
| C242 | IF A.1/16 THEN M | -- O_CC_GPRS |
| C243 | IF A.1/50 THEN M | -- O_TAT_AL |
| C244 | IF A.1/51 THEN M | -- O_TAT_AC |
| C245 | IF A.1/52 THEN M | -- O_TAT_AR |
| C246 | IF A.1/53 THEN M | -- O_TAT_FSN |
| C247 | IF A.1/54 THEN M | -- O_TAT_FSL |
| C248 | IF A.1/55 THEN M | -- O_TAT_FSS |
| C249 | IF A.1/56 THEN M | -- O_TAT_SN |
| C250 | IF A.1/57 THEN M | -- O_TAT_SB |
| C251 | IF A.1/58 THEN M | -- O_TAT_SI |
| C252 | IF A.1/59 THEN M | -- O_TAT_SU |
| C253 | IF A.1/60 THEN M | -- O_TAT_SS |
| C254 | IF A.1/61 THEN M | -- O_TAT_STFC |
| C255 | IF A.1/62 THEN M | -- OR O_TAT_STFB |
| C256 | IF C237 THEN M for at least one of the bits 1 - 4 of byte 24 | -- O_Frames |
| C257 | IF (C207 OR C222 OR C224) THEN M for at least one of the bits 6 - 8 of byte 13 | -- O_BIP_CSD OR O_BIP_GPRS OR (O_BIP_Local AND (BIP_BT OR BIP_IrDA OR BIP_RS232 OR BIP_USB)) |

# Annex C (informative): Change history

| CP-doc | CR | REV | Meeting | SUBJECT | CAT | NEW_VERS |
|---|---|---|---|---|---|---|
| TP-050016 | - | - | 2.0.0 | Approved TP-27, March 2005 | | 6.0.0 |
| CP-050144 | 0001 | - | CT-28 | Correction of coding in MT Call Event | F | 6.1.0 |
| CP-050144 | 0002 | - | CT-28 | Correction of applicability table | F | 6.1.0 |
| CP-050144 | 0003 | - | CT-28 | Essential Corrections | F | 6.1.0 |
| CP-050144 | 0004 | - | CT-28 | Correction of coding in MT Call Event | F | 6.1.0 |
| CP-050144 | 0005 | - | CT-28 | Removal of GET RESPONSE references | F | 6.1.0 |
| CP-050447 | 0006 | - | CT-29 | Rel-6: Correction of release dependent EF values | F | 6.2.0 |
| CP-050447 | 0007 | - | CT-29 | Correction of applicability and terminal profile support tables | F | 6.2.0 |
| CP-050447 | 0008 | - | CT-29 | Correction of EF_BDN coding | F | 6.2.0 |
| CP-050447 | 0009 | - | CT-29 | Incorrect Dialling Number string in clause 27.22.4.13.1 SEQ 1.9 for PCS 1900 | F | 6.2.0 |
| CP-050447 | 0010 | - | CT-29 | Essential corrections in display icons Setup Menu and Select Item | f | 6.2.0 |
| CP-050447 | 0011 | - | CT-29 | Incorrect Ti Flag value for SET UP 1.4.1 in clause 27.22.4.16.1 | F | 6.2.0 |
| CP-050447 | 0012 | - | CT-29 | Correction of TP-MR (TP Message Reference) of the SMS SUBMIT TPDU submitted to the USS (Network) | F | 6.2.0 |
| CP-050447 | 0013 | - | CT-29 | Corrections in the Logical description and BER encoding in clause 27.22.6.2 and 27.22.4.11 | F | 6.2.0 |
| CP-050447 | 0014 | - | CT-29 | Incorrect DCS in SMS-CB data download tests | F | 6.2.0 |
| CP-050447 | 0015 | - | CT-29 | Essential Corrections in clause 27.22.8 MO SHORT MESSAGE CONTROL BY USIM | F | 6.2.0 |
| CP-050447 | 0016 | - | CT-29 | Introduction of BDN tests for terminals not supporting BDN | B | 6.2.0 |
| CP-050447 | 0017 | - | CT-29 | Essential Corrections | F | 6.2.0 |
| CP-050447 | 0018 | - | CT-29 | Incorrect SMS-PP 1.4.1 TPDU in clause 27.22.4.22.1 | F | 6.2.0 |
| CP-050447 | 0019 | - | CT-29 | Missing interactions in Bearer Independent Protocol test cases | F | 6.2.0 |
| CP-050447 | 0020 | - | CT-29 | Correction of Refresh tests | F | 6.2.0 |
| CP-050447 | 0022 | - | CT-29 | Applicability of TC 27.22.4.7.1 and TCs related to FDN and BDN | F | 6.2.0 |
| CP-050447 | 0023 | - | CT-29 | Essential correction to Terminal Profile table E.1 | F | 6.2.0 |
| CP-050447 | 0024 | - | CT-29 | Correction of CB message identifier | F | 6.2.0 |
| CP-050447 | 0025 | - | CT-29 | Rel-6: Addition of new UCS2 Tests | B | 6.2.0 |
| CP-050447 | 0027 | - | CT-29 | Incorrect Coding of SMS-PP (Data download) Message in clause 27.22.4.7.1 and 27.22.5.1 | F | 6.2.0 |
| - | - | - | - | 2005-10: Editorial corrections due to the CRs approved at CP-29 | - | 6.2.1 |
| CP-050495 | 0028 | - | CT-30 | Correction of Send SS (UCS2) tests | F | 6.3.0 |
| CP-050495 | 0029 | - | CT-30 | Essential Corrections in clause 27.22.4.11 | F | 6.3.0 |
| CP-050495 | 0030 | - | CT-30 | Corrections to Select Item (icons support) | F | 6.3.0 |
| CP-050495 | 0031 | - | CT-30 | 27.22.7.4.1 Location Status Event (normal) | F | 6.3.0 |
| CP-050495 | 0032 | - | CT-30 | Essential Corrections of Set Up Menu test | F | 6.3.0 |
| CP-050495 | 0033 | - | CT-30 | Correction of applicability table and related addition of missing test sequences | F | 6.3.0 |
| CP-050495 | 0034 | - | CT-30 | Correction in SMS-PP 1.4.1 TPDU of clause 27.22.4.22.1 | F | 6.3.0 |
| CP-050495 | 0035 | - | CT-30 | Essential Corrections of SMS-PP download message in Refresh test case | F | 6.3.0 |
| CP-050495 | 0036 | - | CT-30 | Essential Correction in MO SHORT MESSAGE CONTROL BY USIM Deletion of sequence 1.9 | F | 6.3.0 |
| CP-050495 | 0037 | - | CT-30 | Deletion of SEQ 1.3 in clause 27.22.4.13.1 | F | 6.3.0 |
| CP-060013 | 0041 | - | CT-31 | Deletion of Send Data test sequence | F | 6.4.0 |
| CP-060013 | 0042 | - | CT-31 | Essential correction of Provide Local Information (IMEI) test | F | 6.4.0 |
| CP-060013 | 0044 | - | CT-31 | Essential Correction in SEQ 1.8 of clause 27.22.8 | F | 6.4.0 |
| CP-060013 | 0045 | - | CT-31 | Essential correction on 27.22.7.3.1 Call Disconnected Event | F | 6.4.0 |
| CP-060013 | 0050 | - | CT-31 | Essential correction of Channel Data length in clause 27.22.4.30 | F | 6.4.0 |
| CP-060014 | 0048 | - | CT-31 | Essential Corrections in clause 27.22.4.11 | F | 6.4.0 |
| CP-060014 | 0052 | - | CT-31 | Essential Corrections in clause 27.22.8 MO SHORT MESSAGE CONTROL BY SIM | F | 6.4.0 |
| CP-060014 | 0049 | - | CT-31 | Essential correction in SEQ 1.4 of clause 27.22.4.11.1 SEND SS (normal) | F | 6.4.0 |
| CP-060014 | 0047 | - | CT-31 | Essential corrections of Run AT Command tests | F | 6.4.0 |
| CP-060014 | 0053 | - | CT-31 | Essential corrections to SET UP CALL test sequences | F | 6.4.0 |
| CP-060015 | 0055 | - | CT-31 | Essential Correction in TERMINAL RESPONSE coding of clause 27.22.4.31 | F | 6.4.0 |
| CP-060015 | 0056 | - | CT-31 | Essential corrections to Timer Expiration tests | F | 6.4.0 |
| CP-060015 | 0054 | - | CT-31 | BER-TLV suppressions | F | 6.4.0 |
| CP-060157 | 0059 | - | CT-31 | Add SMS PP Data Download RP-ERROR Test Case | B | 6.4.0 |
| CP-060022 | 0043 | - | CT-31 | Essential Correction in SEQ 1.7 of clause 27.22.4.13.1 | F | 6.4.0 |
| CP-060022 | 0046 | - | CT-31 | Essential correction of Refresh test | F | 6.4.0 |
| CP-060022 | 0051 | - | CT-31 | Essential correction of Channel Data length in Result TLV of clause | F | 6.4.0 |

| CP-doc | CR | REV | Meeting | SUBJECT | CAT | NEW_VERS |
|---|---|---|---|---|---|---|
| | | | | 27.22.4.30 | | |
| CP-060022 | 0060 | - | CT-31 | CR 31.124 Rel-6: Insertion of missing REFRESH (IMSI changing procedure) test cases | F | 6.4.0 |
| CP-060022 | 0057 | - | CT-31 | Essential corrections of references | F | 6.4.0 |
| CP-060241 | 0061 | - | CT-32 | Proposal to the TS 31.124 Split by referencing the relevant USAT Test procedures to TS 102 384 | | 6.5.0 |
| CP-060241 | 0062 | - | CT-32 | Essential corrections on test cases 27.22.6.3 and 27.22.6.4 using record 2 in EF FDN | | 6.5.0 |
| CP-060241 | 0063 | - | CT-32 | Essential corrections on TC 27.22.6.4 sequence 4.1 | | 6.5.0 |
| CP-060241 | 0064 | - | CT-32 | Essential corrections on SEND SHORT MESSAGE test cases | | 6.5.0 |
| CP-060241 | 0065 | - | CT-32 | Essential correction of text attributes tests | | 6.5.0 |
| CP-060241 | 0066 | - | CT-32 | Definition of appropriate QoS in BIP test cases related to GPRS for 3G | | 6.5.0 |
| CP-060241 | 0071 | - | CT-32 | Essential correction of Refresh test in 27.22.7.4.2, seq. 2.4 | | 6.5.0 |
| CP-060241 | 0074 | - | CT-32 | Essential corrections of RUN AT Command tests | | 6.5.0 |
| CP-060241 | 0067 | - | CT-32 | Essential correction of tables B.1 and E.1 | | 6.5.0 |
| CP-060242 | 0068 | - | CT-32 | Essential Correction in REGISTER 1.2B message coding of clause 27.22.4.11.1 SEND SS (normal) | F | 6.5.0 |
| CP-060242 | 0069 | - | CT-32 | Essential correction of 27.22.4.13.1 SET UP CALL, seq 1.4 | F | 6.5.0 |
| CP-060242 | 0070 | - | CT-32 | Essential correction of second card reader test applicability | F | 6.5.0 |
| CP-060242 | 0072 | - | CT-32 | Correction of TON/NPI coding for Call Control Test case | F | 6.5.0 |
| CP-060242 | 0073 | - | CT-32 | Essential corrections on 27.22.4.11.1 sequence. 1.2 | F | 6.5.0 |
| CP-060242 | 0075 | - | CT-32 | Essential correction of BIP tests | F | 6.5.0 |
| CP-060389 | 0082 | 1 | CT-33 | Wrong reference inside test requirement of TC 27.22.7.2.2 | F | 6.6.0 |
| CP-060389 | 0087 | 1 | CT-33 | Essential corrections of applicability table | F | 6.6.0 |
| CP-060389 | 0088 | 1 | CT-33 | Essential correction of IMEISV coding for Provide Local Information | F | 6.6.0 |
| CP-060389 | 0089 | 1 | CT-33 | Essential corrections of text attribute tests for Send USSD and Close channel | F | 6.6.0 |
| CP-060389 | 0090 | 1 | CT-33 | Proposal to the TS 31.124 Split by referencing the relevant USAT Test procedures to TS 102 384 | F | 6.6.0 |
| CP-060389 | 0091 | 1 | CT-33 | Correction to the UCS2 coding in Setup Call test | F | 6.6.0 |
| CP-060389 | 0092 | 1 | CT-33 | Essential correction of RUN AT Command for text attribute tests | F | 6.6.0 |
| CP-060389 | 0095 | 1 | CT-33 | Correction of RECEIVE DATA tests | F | 6.6.0 |
| CP-060389 | 0096 | 1 | CT-33 | Correction of terminology for USIM Service Table | F | 6.6.0 |
| CP-060389 | 0097 | 1 | CT-33 | Correction of 2nd alpha identifier usages in SET UP CALL tests | F | 6.6.0 |
| CP-060389 | 0098 | 1 | CT-33 | Correction of various typographical errors | F | 6.6.0 |
| CP-060389 | 0101 | 1 | CT-33 | Essential corrections to OPEN CHANNEL text attribute test sequences | F | 6.6.0 |
| CP-060389 | 0078 | 1 | CT-33 | Correction of "Precedence class" values in Bearer Independent Protocol test cases | F | 6.6.0 |
| CP-060389 | 0076 | 1 | CT-33 | Essential corrections on PROVIDE LOCAL INFORMATION test sequences | F | 6.6.0 |
| CP-060389 | 0080 | 2 | CT-33 | Essential corrections on test sequences using the TLV data object Location Information | F | 6.6.0 |
| CP-060389 | 0100 | 2 | CT-33 | Essential corrections to SET UP CALL (UCS2 Display) test sequences | F | 6.6.0 |
| CP-060389 | 0081 | 3 | CT-33 | Essential corrections to REFRESH(normal) test sequence | F | 6.6.0 |
| CP-060389 | 0102 | 1 | CT-33 | Essential corrections to SEND SS display tests concerning longForwardedToNumber | F | 6.6.0 |
| CP-060475 | 0086 | 1 | CT-33 | Essential corrections of MMI entries in table E.1 | F | 6.6.0 |
| CP-060475 | 0077 | 2 | CT-33 | Corrections to SET UP CALL test case 27.22.4.13.1 | F | 6.6.0 |
| CP-060475 | 0099 | 1 | CT-33 | Essential corrections to SEND SS concerning longForwardedToNumber | F | 6.6.0 |
| CP-060475 | 0094 | 2 | CT-33 | Corrections to MO SHORT MESSAGE CONTROL BY USIM tests | F | 6.6.0 |
| CP-060517 | 0084 | 1 | CT-33 | Essential corrections Set Up Call, seq. 1.9 | F | 6.6.0 |
| CP-060540 | 0103 | - | CT-34 | Correction of APN Coding in Open Channel test case | F | 6.7.0 |
| CP-060540 | 0085 | 2 | CT-34 | Essential corrections of BIP entries in table E.1 | F | 6.7.0 |
| CP-060540 | 0110 | 2 | CT-34 | Essential correction of Result TLV handling | F | 6.7.0 |
| CP-060540 | 0111 | - | CT-34 | Essential correction of expected sequence in OPEN CHANNEL test case | F | 6.7.0 |
| CP-060727 | 0105 | - | CT-34 | Some of the Applicability table content is missing when printed or in Print Layout mode | F | 6.7.0 |
| CP-060727 | 0106 | 1 | CT-34 | Correction to SET UP CALL | F | 6.7.0 |
| CP-060727 | 0107 | - | CT-34 | Correction to SEND SS | F | 6.7.0 |
| CP-060727 | 0058 | 1 | CT-34 | Addition of REFRESH USIM Application Reset | B | 6.7.0 |
| CP-060727 | 0108 | - | CT-34 | Essential corrections on SEND SS (UCS2 display) test cases | F | 6.7.0 |
| CP-060727 | 0109 | - | CT-34 | Essential corrections on REFRESH TC 27.22.4.7.1 | F | 6.7.0 |
| CP-060727 | 0104 | 1 | CT-34 | Corrections in the interpretation of Katakana Character | F | 6.7.0 |
| CP-070063 | 0115 | - | CT-35 | Essential correction of 27.22.5.2 | F | 6.8.0 |
| CP-070063 | 0113 | 1 | CT-35 | Essential correction of Terminal Profile Support table | F | 6.8.0 |
| CP-070063 | 0112 | 1 | CT-35 | Essential correction of 27.22.4.13.1 Expected Sequence 1.7 | F | 6.8.0 |
| CP-070065 | 0116 | - | CT-35 | Essential correction of 27.22.4.7, seq. 1.7 | F | 6.8.0 |
| CP-070065 | 0119 | - | CT-35 | Essential correction of TC 27.22.7.4.1 | F | 6.8.0 |
| CP-070065 | 0120 | - | CT-35 | CR implementation error correction for 27.22.6.2 SEQ 2.2 | F | 6.8.0 |
| CP-070065 | 0121 | - | CT-35 | CR implementation error correction for 27.22.4.11.1 SEQ 1.4A | F | 6.8.0 |
| CP-070065 | 0117 | 1 | CT-35 | Essential clarification of Network Simulator selection | F | 6.8.0 |
| CP-070065 | 0122 | 1 | CT-35 | Essential correction of 27.22.4.7.2 SEQ 2.2 | F | 6.8.0 |

| CP-doc | CR | REV | Meeting | SUBJECT | CAT | NEW_VERS |
|---|---|---|---|---|---|---|
| CP-070065 | 0124 | 2 | CT-35 | Addition of new expected sequence to the SMS-PP Data Download test case | C | 6.8.0 |
| CP-070065 | 0125 | 2 | CT-35 | Addition of a new expected sequence to the SMS-CB Data Download test case | F | 6.8.0 |
| CP-070297 | 0127 | 2 | CT-36 | Essential correction of test case applicability | F | 6.9.0 |
| CP-070297 | 0128 | - | CT-36 | Correction of 27.22.4.2 applicability | F | 6.9.0 |
| CP-070297 | 0129 | 1 | CT-36 | Essential correction of test case applicability for 27.22.6.1 | A | 6.9.0 |
| CP-070297 | 0130 | 1 | CT-36 | Essential correction on 27.22.8 | A | 6.9.0 |
| CP-070297 | 0131 | - | CT-36 | Essential correction on 27.22.5.1 | F | 6.9.0 |
| CP-070297 | 0132 | - | CT-36 | Essential correction on 27.22.4.11.1 sequence. 1.4 B | F | 6.9.0 |
| CP-070297 | 0133 | - | CT-36 | Correction of reference to ISO/IEC 7816-3 | A | 6.9.0 |
| - | - | - | 2007-06 | Update to Rel-7 version (MCC) | - | 7.0.0 |

# History

| Document history | | |
|---|---|---|
| V7.0.0 | June 2007 | Publication |
| | | |
| | | |
| | | |
| | | |