ETSI TS 129 388 V17.1.0 (2026-08)



TECHNICAL SPECIFICATION

LTE;
V2X Control Function to Home Subscriber Server (HSS) aspects (V4);
Stage 3
(3GPP TS 29.388 version 17.1.0 Release 17)

Reference
RTS/TSGC-0429388vh10

Keywords
LTE

ETSI

650 Route des Lucioles
F-06921 Sophia Antipolis Cedex - FRANCE

Tel.: +33 4 92 94 42 00 Fax: +33 4 93 65 47 16

Siret N° 348 623 562 00017 - APE 7112B
Association à but non lucratif enregistrée à la
Sous-Préfecture de Grasse (06) N° w061004871

Important notice

The present document can be downloaded from the
ETSI Search & Browse Standards application.

The present document may be made available in electronic versions and/or in print. The content of any electronic and/or print versions of the present document shall not be modified without the prior written authorization of ETSI. In case of any existing or perceived difference in contents between such versions and/or in print, the prevailing version of an ETSI deliverable is the one made publicly available in PDF format on ETSI deliver repository.

Users should be aware that the present document may be revised or have its status changed, this information is available in the Milestones listing.

If you find errors in the present document, please send your comments to the relevant service listed under Committee Support Staff.

If you find a security vulnerability in the present document, please report it through our Coordinated Vulnerability Disclosure (CVD) program.

Notice of disclaimer & limitation of liability

The information provided in the present deliverable is directed solely to professionals who have the appropriate degree of experience to understand and interpret its content in accordance with generally accepted engineering or other professional standard and applicable regulations.
No recommendation as to products and services or vendors is made or should be implied.
No representation or warranty is made that this deliverable is technically accurate or sufficient or conforms to any law and/or governmental rule and/or regulation and further, no representation or warranty is made of merchantability or fitness for any particular purpose or against infringement of intellectual property rights.
In no event shall ETSI be held liable for loss of profits or any other incidental or consequential damages.

Any software contained in this deliverable is provided "AS IS" with no warranties, express or implied, including but not limited to, the warranties of merchantability, fitness for a particular purpose and non-infringement of intellectual property rights and ETSI shall not be held liable in any event for any damages whatsoever (including, without limitation, damages for loss of profits, business interruption, loss of information, or any other pecuniary loss) arising out of or related to the use of or inability to use the software.

Copyright Notification

No part of this document may be reproduced in any form, by any means and in any media, without the prior written authorization of ETSI and except as expressly permitted below.
By way of exception and when the document is a normative deliverable (European Standard (EN), Technical Specification (TS), Group Specification (GS) or ETSI Standard (ES)), ETSI authorizes to reproduce and incorporate into products, services and technical documentation only those extracts (e.g. templates) that are strictly necessary for the technical implementation of the normative deliverable, to ensure compliance with the latter.
Nothing in this notice shall be construed as limiting any mandatory exceptions to copyright provided by applicable law.

© ETSI 2026.
All rights reserved.

Intellectual Property Rights

Essential patents

IPRs essential or potentially essential to normative deliverables (European Standard (EN), Technical Specification (TS), Group Specification (GS) or ETSI Standard (ES)) may have been declared to ETSI. The declarations pertaining to these essential IPRs, if any, are publicly available for **ETSI members and non-members**, and can be found in ETSI SR 000 314: *"Intellectual Property Rights (IPRs); Essential, or potentially Essential, IPRs notified to ETSI in respect of ETSI standards"*, which is available from the ETSI Secretariat. Latest updates are available on the ETSI IPR online database.

Pursuant to the ETSI Directives including the ETSI IPR Policy, no investigation regarding the essentiality of IPRs, including IPR searches, has been carried out by ETSI. No guarantee can be given as to the existence of other IPRs not referenced in ETSI SR 000 314 (or the updates on the ETSI Web server) which are, or may be, or may become, essential to the present document.

Trademarks

The present document may include trademarks and/or tradenames which are asserted and/or registered by their owners. ETSI claims no ownership of these except for any which are indicated as being the property of ETSI, and conveys no right to use or reproduce any trademark and/or tradename. Mention of those trademarks in the present document does not constitute an endorsement by ETSI of products, services or organizations associated with those trademarks.

DECT™, **PLUGTESTS™**, **UMTS™** and the ETSI logo are trademarks of ETSI registered for the benefit of its Members. **3GPP™**, **LTE™** and **5G™** logo are trademarks of ETSI registered for the benefit of its Members and of the 3GPP Organizational Partners. **oneM2M™** logo is a trademark of ETSI registered for the benefit of its Members and of the oneM2M Partners. **GSM**® and the GSM logo are trademarks registered and owned by the GSM Association.

Legal Notice

This Technical Specification (TS) has been produced by ETSI 3rd Generation Partnership Project (3GPP).

The present document may refer to technical specifications or reports using their 3GPP identities. These shall be interpreted as being references to the corresponding ETSI deliverables.

The cross reference between 3GPP and ETSI identities can be found at 3GPP to ETSI numbering cross-referencing.

Modal verbs terminology

In the present document "**shall**", "**shall not**", "**should**", "**should not**", "**may**", "**need not**", "**will**", "**will not**", "**can**" and "**cannot**" are to be interpreted as described in clause 3.2 of the ETSI Drafting Rules (Verbal forms for the expression of provisions).

"**must**" and "**must not**" are **NOT** allowed in ETSI deliverables except when used in direct citation.

Contents

Intellectual Property Rights 2
Legal Notice 2
Modal verbs terminology 2
Foreword 5
1 Scope 6
2 References 6
3 Definitions and abbreviations 7
3.1 Definitions 7
3.2 Abbreviations 7
4 General Description 7
4.1 Introduction 7
5 Procedure Description 7
5.1 Introduction 7
5.2 V2X Subscriber Information Retrieval 8
5.2.1 General 8
5.2.2 Detailed Behaviour of the V2X Control Function 8
5.2.3 Detailed Behaviour of the HSS 9
5.3 Update V2X Subscriber Data 9
5.3.1 General 9
5.3.2 Detailed behaviour of the V2X Control Function 10
5.3.3 Detailed behaviour of the HSS 11
5.4 Notification Procedure 11
5.4.1 General 11
5.4.2 Detailed Behaviour of the V2X Control Function 12
5.4.3 Detailed Behaviour of the HSS 12
5.5 Reset 13
5.5.1 General 13
5.5.2 Detailed behaviour of the V2X Control Function 13
5.5.3 Detailed behaviour of the HSS 14
6 Protocol Specification and Implementations 14
6.1 Introduction 14
6.1.1 Use of Diameter base protocol 14
6.1.2 Securing Diameter Messages 14
6.1.3 Accounting Functionality 14
6.1.4 Use of Sessions 14
6.1.5 Transport Protocol 14
6.1.6 Routing Considerations 14
6.1.7 Advertising Application Support 15
6.1.8 Diameter Application Identifier 15
6.1.9 Use of the Supported-Features AVP 15
6.2 Commands 15
6.2.1 Introduction 15
6.2.2 Command-Code Values 16
6.2.3 ProSe-Subscriber-Information-Request (PIR) Command 16
6.2.4 ProSe-Subscriber-Information-Answer (PIA) Command 17
6.2.5 Update-ProSe-Subscriber-Data-Request (UPR) Command 17
6.2.6 Update-ProSe-Subscriber-Data-Answer (UPA) Command 17
6.2.7 ProSe-Notify-Request (PNR) Command 18
6.2.8 ProSe-Notify-Answer (PNA) Command 18
6.2.9 Reset-Request (RSR) Command 19
6.2.10 Reset-Answer (RSA) Command 19
6.3 AVPs 19

6.3.1 General 19
6.3.2 V2X-Subscription-Data 20
6.3.3 V2X-PC5-Allowed-PLMN 21
6.3.4 V2X-Update-Flags 21
6.3.5 V2X-Notify-Flags 21
6.3.6 OC-Supported-Features 22
6.3.7 OC-OLR 22
6.3.8 DRMP 22
6.3.9 Load 22
6.3.10 PLMN-Allowed-PC5-RATs 22
6.3.11 PC5-RAT-Type 22
6.4 Result-Code AVP and Experimental-Result AVP Values 22
6.4.1 General 22
6.4.2 Success 23
6.4.3 Permanent Failures 23
6.4.3.1 General 23
6.4.3.2 DIAMETER_ERROR_USER_UNKNOWN (5001) 23
6.4.3.3 DIAMETER_ERROR_UNKNOWN_V2X_SUBSCRIPTION (5690) 23
6.4.3.4 DIAMETER_ERROR_V2X_NOT_ALLOWED (5691) 23

Annex A (normative): Diameter overload control mechanism 24

A.1 General 24

A.2 HSS behaviour 24

A.3 V2X Control Function behaviour 24

Annex B (Informative): Diameter overload node behaviour 25

B.1 Message prioritization 25

Annex C (normative): Diameter message priority mechanism 26

C.1 General 26

C.2 V4 interface 26
C.2.1 General 26
C.2.2 HSS and V2X Control Function behaviour 26

D.1 General 26

D.2 HSS behaviour 26

D.3 V2X Control Function behaviour 27

Annex E (informative): Change history 28

History 29

Foreword

This Technical Specification has been produced by the 3rd Generation Partnership Project (3GPP).

The contents of the present document are subject to continuing work within the TSG and may change following formal TSG approval. Should the TSG modify the contents of the present document, it will be re-released by the TSG with an identifying change of release date and an increase in version number as follows:

Version x.y.z

where:

- x the first digit:
  - 1 presented to TSG for information;
  - 2 presented to TSG for approval;
  - 3 or greater indicates TSG approved document under change control.
- y the second digit is incremented for all changes of substance, i.e. technical enhancements, corrections, updates, etc.
- z the third digit is incremented when editorial only changes have been incorporated in the document.

In the present document, modal verbs have the following meanings:

shall indicates a mandatory requirement to do something

shall not indicates an interdiction (prohibition) to do something

The constructions "shall" and "shall not" are confined to the context of normative provisions, and do not appear in Technical Reports.

The constructions "must" and "must not" are not used as substitutes for "shall" and "shall not". Their use is avoided insofar as possible, and they are not used in a normative context except in a direct citation from an external, referenced, non-3GPP document, or so as to maintain continuity of style when extending or modifying the provisions of such a referenced document.

should indicates a recommendation to do something

should not indicates a recommendation not to do something

may indicates permission to do something

need not indicates permission not to do something

The construction "may not" is ambiguous and is not used in normative elements. The unambiguous constructions "might not" or "shall not" are used instead, depending upon the meaning intended.

can indicates that something is possible

cannot indicates that something is impossible

The constructions "can" and "cannot" are not substitutes for "may" and "need not".

will indicates that something is certain or expected to happen as a result of action taken by an agency the behaviour of which is outside the scope of the present document

will not indicates that something is certain or expected not to happen as a result of action taken by an agency the behaviour of which is outside the scope of the present document

might indicates a likelihood that something will happen as a result of action taken by some agency the behaviour of which is outside the scope of the present document

might not indicates a likelihood that something will not happen as a result of action taken by some agency the behaviour of which is outside the scope of the present document

In addition:

is (or any other verb in the indicative mood) indicates a statement of fact

is not (or any other negative verb in the indicative mood) indicates a statement of fact

The constructions "is" and "is not" do not indicate requirements.

1 Scope

The present document describes the Diameter-based V4 interface between the V2X Control Function and the Home Subscriber Server (HSS) defined for V2X services.

This specification defines the Diameter application for V4 reference point between the V2X Control Function and the HSS. The interactions between the V2X Control Function and the HSS are specified.

The stage 2 description for V2X service features in EPS is specified in TS 23.285 [2].

2 References

The following documents contain provisions which, through reference in this text, constitute provisions of the present document.

- References are either specific (identified by date of publication, edition number, version number, etc.) or non-specific.
- For a specific reference, subsequent revisions do not apply.
- For a non-specific reference, the latest version applies. In the case of a reference to a 3GPP document (including a GSM document), a non-specific reference implicitly refers to the latest version of that document *in the same Release as the present document.*

[1] 3GPP TR 21.905: "Vocabulary for 3GPP Specifications".

[2] 3GPP TS 23.285: "Architecture enhancements for V2X services; Stage 2".

[3] IETF RFC 6733: "Diameter Base Protocol".

[4] 3GPP TS 33.210: "3G Security; Network Domain Security; IP Network Layer Security".

[5] IETF RFC 4960: "Stream Control Transmission Protocol".

[6] 3GPP TS 29.229: "Cx and Dx interfaces based on the Diameter protocol".

[7] IETF RFC 5234: "Augmented BNF for Syntax Specifications: ABNF".

[8] 3GPP TS 23.003: "Numbering, addressing and identification".

[9] 3GPP TS 29.228: "IP multimedia (IM) Subsystem Cx and Dx Interfaces; Signalling flows and Message Elements".

[10] 3GPP TS 29.272: "Evolved Packet System; MME and SGSN Related Interfaces Based on Diameter Protocol".

[11] 3GPP TS 29.329: "Sh Interface based on the Diameter protocol".

[12] IETF RFC 7683: "Diameter Overload Indication Conveyance".

[13] IETF RFC 7944: "Diameter Routing Message Priority".

[14] 3GPP TS 23.007: "Restoration procedures".

[15] 3GPP TS 29.344: "Proximity-services (ProSe) Function to Home Subscriber Server (HSS) aspects".

[16] IETF RFC 8583: "Diameter Load Information Conveyance".

3 Definitions and abbreviations

3.1 Definitions

For the purposes of the present document, the terms and definitions given in TR 21.905 [1] and the following apply. A term defined in the present document takes precedence over the definition of the same term, if any, in TR 21.905 [1].

example: text used to clarify abstract rules by applying them literally.

3.2 Abbreviations

For the purposes of the present document, the abbreviations given in TR 21.905 [1] and the following apply. An abbreviation defined in the present document takes precedence over the definition of the same abbreviation, if any, in TR 21.905 [1].

ProSe	Proximity-based Services
V2X	Vehicle-to-Everything

4 General Description

4.1 Introduction

The V4 reference point between the V2X Control Function and the HSS is defined in the TS 23.285 [2].

This document describes the V4 interface related procedures, message parameters and protocol specifications.

The V4 interface allows the V2X Control Function to retrieve V2X related subscription data in order to authorise access from the UE for V2X services.

5 Procedure Description

5.1 Introduction

This clause describes the Diameter-based V4 interface related procedures and information elements exchanged between the V2X Control Function and the HSS.

In the tables that describe the Information Elements transported by each Diameter command, each Information Element is marked as (M) Mandatory, (C) Conditional or (O) Optional in the "Cat." column. For the correct handling of the Information Element according to the category type, see the description detailed in clause 6 of the TS 29.228 [9].

5.2 V2X Subscriber Information Retrieval

5.2.1 General

This procedure shall be used between the V2X Control Function and the HSS for authorization of the UE for V2X services. The procedure shall be invoked by the V2X Control Function and is used:

- to request V2X related subscription data.

This procedure is mapped to the commands ProSe-Subscriber-Information-Request/Answer (PIR/PIA) in the Diameter application specified in clause 6. Table 5.2.1-1 and table 5.2.1-2 detail the involved information elements.

Table 5.2.1-1: V2X Subscriber Information Retrieval Request

Information Element Name	Mapping to Diameter AVP	Cat.	Description
IMSI	User-Name (See IETF RFC 6733 [3])	M	This information element shall contain the user IMSI, formatted according to TS 23.003 [8], clause 2.2.
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.

Table 5.2.1-2: V2X Subscriber Information Retrieval Answer

Information Element Name	Mapping to Diameter AVP	Cat.	Description
Result (See 6)	Result-Code / Experimental-Result	M	This IE shall contain the result of the operation. The Result-Code AVP shall be used to indicate success / errors as defined in the Diameter base protocol. The Experimental-Result AVP shall be used for V4 errors. This is a grouped AVP which shall contain the 3GPP Vendor ID in the Vendor-Id AVP, and the error code in the Experimental-Result-Code AVP. The following errors are applicable: - User Unknown - Unknown V2X Subscription - V2X Not Allowed
V2X Subscription Data (See 6.3.2)	V2X-Subscription-Data	C	This information element shall contain the V2X Subscription Data that gives the user permission to use V2X.
MSISDN (See TS 29.329 [11])	MSISDN	C	This information element shall contain the user MSISDN, formatted according to TS 29.329 [11]. It shall be present if available.
Visited PLMN Id (See TS 29.272 [10])	Visited-PLMN-Id	C	This IE shall contain the MCC and the MNC of the PLMN where the UE is registered, see TS 23.003 [8]. It shall be present if the UE is roaming in a PLMN different from the Home PLMN.
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
Reset-IDs (See TS 29.272 [10])	Reset-ID	O	The Reset-ID uniquely identifies a fallible resource in the HSS's realm on which the user (IMSI) depends. In the event of a restart of the fallible resource a Reset message containing the Reset-ID will exactly identify the impacted subscribers.

5.2.2 Detailed Behaviour of the V2X Control Function

The V2X Control Function shall make use of this procedure to request V2X related subscription data.

If the V2X Control Function retrieved the V2X related subscription data, the V2X Control Function shall perform the authorisation for V2X as described in the TS 23.285 [2].

5.2.3 Detailed Behaviour of the HSS

When receiving a V2X Subscriber Information Retrieval Request the HSS shall check if the IMSI for whom data is requested exists in the HSS. If not, an Experimental-Result of DIAMETER_ERROR_USER_UNKNOWN shall be returned.

If the IMSI exists but there is not any V2X subscription data for the IMSI, the HSS shall return an Experimental-Result of DIAMETER_ERROR_UNKNOWN_V2X_SUBSCRIPTION.

If the UE is not allowed to use V2X in the visited PLMN, the HSS shall return an Experimental-Result of DIAMETER_ERROR_V2X_NOT_ALLOWED. Otherwise, the HSS shall return a Result-Code of DIAMETER_SUCCESS and shall store V2X Control Function identity (the V2X Control Function identity is received within the Origin-Host AVP) and download the V2X subscription data to the V2X Control Function. The HSS shall provide the Visited PLMN ID of where the UE is registered if the UE is roaming in a PLMN different from the Home PLMN.

5.3 Update V2X Subscriber Data

5.3.1 General

The Update V2X Subscriber Data procedure shall be used between the V2X Control Function and the HSS to update the subscriber related data downloaded by means of the V2X Subscriber Information Retrieval operation (see clause 5.2) and stored in the V2X Control Function.

It shall be used to update subscriber related data in the V2X Control Function due to administrative changes of the user data in the HSS, i.e. if the user was given a subscription and the subscription has changed. It shall be used at least to perform the following:

- update of all of V2X subscription data of the subscriber,
- update of a subset of the V2X subscription data of the subscriber,
- deletion of the V2X subscription data of the subscriber.

The procedure will also be triggered when the VPLMN has changed.

This procedure is mapped to the commands Update-ProSe-Subscriber-Data-Request/Answer (UPR/UPA) in the Diameter application specified in clause 6.

Table 5.3.1-1 specifies the involved information elements for the request.

Table 5.3.1-2 specifies the involved information elements for the answer.

Table 5.3.1-1: Update V2X Subscriber Data Request

Information element name	Mapping to Diameter AVP	Cat.	Description
IMSI	User-Name (See IETF RFC 6733 [3])	M	This information element shall contain the user IMSI, formatted according to TS 23.003 [8], clause 2.2.
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
V2X Subscription Data (See 6.3.2)	V2X-Subscription-Data	C	This information element shall contain the V2X Subscription Data that gives the user permission to use V2X service.
Visited PLMN Id (See TS 29.272 [10])	Visited-PLMN-Id	C	This IE shall contain the MCC and the MNC of the PLMN where the UE is registered, see TS 23.003 [8]. It shall be present if the UE is roaming in a PLMN different from the Home PLMN.
V2X Update Flags (See 6.3.4)	V2X-Update-Flags	M	This Information Element shall contain a bit mask. See clause 6.3.6 for the meaning of the bits.
Reset-IDs (See TS 29.272 [10])	Reset-ID	O	The Reset-ID uniquely identifies a fallible resource in the HSS's realm on which the user (IMSI) depends. In the event of a restart of the fallible resource a Reset message containing the Reset-ID will exactly identify the impacted subscribers.

Table 5.3.1-2: Update V2X Subscriber Data Answer

Information element name	Mapping to Diameter AVP	Cat.	Description
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
Result (See 6.4)	Result-Code / Experimental-Result	M	This IE shall contain the result of the operation. The Result-Code AVP shall be used to indicate success / errors as defined in the Diameter base protocol. The Experimental-Result AVP shall be used for V4 errors. This is a grouped AVP which shall contain the 3GPP Vendor ID in the Vendor-Id AVP, and the error code in the Experimental-Result-Code AVP. The following errors are applicable in this case: - User Unknown - Unknown V2X Subscription

5.3.2 Detailed behaviour of the V2X Control Function

When receiving an Update V2X Subscriber Data request, the V2X Control Function shall check whether the IMSI is known.

If it is not known, a result code of DIAMETER_ERROR_USER_UNKNOWN shall be returned.

If it is known, the V2X Control Function shall update the corresponding data according to the indication as sent in the request, and acknowledge the Update V2X Subscriber Data message by returning an Update V2X Subscriber Data Answer. If the V2X-Update-Flags indicates that the V2X subscription data is to be deleted, the V2X Control Function shall delete the associated V2X UE context if it has been stored before.

If the update of the subscription data succeeds in the V2X Control Function, the Result-Code shall be set to DIAMETER_SUCCESS.

If the V2X Control Function cannot fulfil the received request for other reasons, e.g. due to a database error, it shall set the Result-Code to DIAMETER_UNABLE_TO_COMPLY. In this case, the V2X Control Function shall mark the subscription record "Subscriber data to be restored in the HSS".

5.3.3 Detailed behaviour of the HSS

The HSS shall make use of this procedure to update the relevant subscriber related data in the V2X Control Function to replace a specific part of the user data stored in the V2X Control Function with the data sent.

If the V2X related subscription data is updated or revoked, the HSS sends the updated V2X subscription data to the V2X Control Function. The HSS shall include the V2X-Update-Flags to indicate which part of the data is updated. If all of the V2X subscription data is to be removed, the HSS shall set the "Removal of all V2X Subscription Data" bit of the V2X-Update-Flags, and the HSS shall delete the V2X Control Function Identity if it is stored for this subscriber.

5.4 Notification Procedure

5.4.1 General

This procedure shall be used between the V2X Control Function and the HSS when the HSS needs to be notified about:

- revocation of authorization for V2X service on one PLMN.
- removal of the subscription data from the V2X Control Function either by an MMI interaction or automatically.

This procedure is mapped to the commands ProSe-Notify-Request/Answer (PNR/PNA) in the Diameter application specified in clause 6. Table 5.4.1-1 and table 5.4.1-2 detail the involved information elements.

Table 5.4.1-1: V2X Notify Request

Information Element Name	Mapping to Diameter AVP	Cat.	Description
IMSI	User-Name (See IETF RFC 6733 [3])	C	This information element shall contain the user IMSI, formatted according to TS 23.003 [8], clause 2.2. It shall be present if the revocation is for a specific UE.
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
PLMN ID (see TS 29.272 [10])	Visited-PLMN-Id	C	This information element shall contain the MCC and the MNC of the PLMN where the UE's authorization for V2X service is revoked, see TS 23.285 [2]. It shall be present if the V2X Control Function revokes the authorization for V2X service in a specific PLMN.
V2X Notify Flags (see 6.3.5)	V2X-Notify-Flags	C	This Information Element shall contain a bit mask. See 6.3.7 for the meaning of the bits.

Table 5.4.1-2: V2X Notify Answer

Information Element Name	Mapping to Diameter AVP	Cat.	Description
Result (See 6)	Result-Code / Experimental-Result	M	This IE shall contain the result of the operation. The Result-Code AVP shall be used to indicate success / errors as defined in the Diameter base protocol. The Experimental-Result AVP shall be used for V4 errors. This is a grouped AVP which shall contain the 3GPP Vendor ID in the Vendor-Id AVP, and the error code in the Experimental-Result-Code AVP. The following errors are applicable: - User Unknown - Unknown V2X Subscription
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.

5.4.2 Detailed Behaviour of the V2X Control Function

The V2X Control Function shall make use of this procedure to revoke authorization for V2X service.

The V2X Control Function shall make use of this procedure to inform the HSS when the subscription data is deleted from the V2X Function database due to MMI interaction or automatically.

The V2X Control Function shall send the updated V2X Permission and the PLMN ID for which the V2X Permission is to be updated. If the revocation is for a single UE in the indicated PLMN, the V2X Function shall include IMSI in the request.

5.4.3 Detailed Behaviour of the HSS

When receiving a V2X Notify Request the HSS shall check if the IMSI, if present in the message, exists in the HSS. If not, an Experimental-Result of DIAMETER_ERROR_USER_UNKNOWN shall be returned.

If the IMSI exists but there is not any V2X subscription data for the IMSI and the PLMN ID as indicated by the Visited-PLMN-Id AVP in the request, the HSS shall return an Experimental-Result of DIAMETER_ERROR_UNKNOWN_V2X_SUBSCRIPTION.

If the V2X-Notify-Flags indicates revocation of authorization for V2X service, and

- if the IMSI exists and there is V2X subscription data for the IMSI and the PLMN ID as indicated by the Visited-PLMN-Id AVP in the request, the HSS shall revoke V2X service as indicated by the VNR Flags received in the request on that PLMN for the user and update the V2X Subscription data accordingly. The HSS shall set the result code to DIAMETER_SUCCESS.

- if IMSI is not present in the message, the HSS shall check if there are any users subscribed to V2X subscription for the PLMN as indicated by the Visited-PLMN-Id AVP in the request, and if yes, revoke V2X service as indicated by the VNR Flags received in the request on that PLMN for all the impacted users and update their V2X Subscription data accordingly. The HSS shall set the result code to DIAMETER_SUCCESS.

If the VNR Flags indicates the subscription data is deleted from the V2X Control Function, the HSS shall remove the V2X Function Identity for the subscriber and set the result code to DIAMETER_SUCCESS.

For any other reasons if the HSS cannot fulfil the received request, e.g. due to a database error, it shall set the result code to DIAMETER_UNABLE_TO_COMPLY.

5.5 Reset

5.5.1 General

The Reset Procedure shall be used by the HSS, after a restart, to indicate to the V2X Control Function that a failure has occurred.

The Reset Procedure may also be used by the HSS as part of operation and maintenance actions e.g. to allow planned HSS outage without service interruption.

This procedure is mapped to the commands Reset-Request/Answer (RSR/RSA) in the Diameter application specified in clause 6.

Table 5.5.1-1 specifies the involved information elements for the request.

Table 5.5.1-2 specifies the involved information elements for the answer.

Table 5.5.1-1: Reset Request

Information element name	Mapping to Diameter AVP	Cat.	Description
User Id List (See TS 29.272 [10])	User-Id	O	This IE shall contain a list of V2X User-Ids where an V2X User-Id comprises the leading digits of an IMSI (i.e. MCC, MNC, leading digits of MSIN) and it shall identify the set of subscribers whose IMSIs begin with the User-Id. The HSS may include this information element if the occurred failure is limited to subscribers identified by one or more User-Ids.
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
Reset-IDs (See TS 29.272 [10])	Reset-ID	O	If present, this information element identifies together with the HSS's realm the set of impacted subscribers.

Table 5.5.1-2: Reset Answer

Information element name	Mapping to Diameter AVP	Cat.	Description
Supported Features (See TS 29.229 [6])	Supported-Features	O	If present, this information element shall contain the list of features supported by the origin host.
Result (See 6.4)	Result-Code / Experimental-Result	M	This IE shall contain the result of the operation. The Result-Code AVP shall be used to indicate success / errors as defined in the Diameter Base Protocol. The Experimental-Result AVP shall be used for V4 errors. This is a grouped AVP which shall contain the 3GPP Vendor ID in the Vendor-Id AVP, and the error code in the Experimental-Result-Code AVP. There are no Experimental-Result codes applicable for this command.

5.5.2 Detailed behaviour of the V2X Control Function

When receiving a Reset message the V2X Control Function shall mark all impacted subscriber records "Subscriber Data Confirmed in HSS" as "Not Confirmed", as defined in TS 23.007 [14]. If the Reset-IDs IE is supported and received, the V2X Control Function shall make use of the Reset-IDs (together with the HSS's realm) in order to determine which subscriber records are impacted (i.e. check whether at least one received Reset-ID is associated with the subscriber, and the HSS's realm identity received in the Origin-Realm AVP matches the value stored after successful V2X-Subscriber-Information retrieval); otherwise the V2X Control Function shall make use of the HSS Identity received in the Origin-Host AVP (by comparing it with the value stored after successful V2X-Subscriber-Information retrieval) and may make use of the received User-Id-List (if any) in order to determine which subscriber records are impacted.

5.5.3 Detailed behaviour of the HSS

The HSS shall make use of this procedure in order to indicate to all relevant V2X Control Functions that the HSS has restarted and may have lost the current V2X Control Function Identity of some of its subscribers who may be currently roaming in the V2X Control Function Area and that the HSS, therefore, cannot send an Update V2X Subscriber Data messages when needed.

If the Reset-ID feature is not supported by the V2X Control Function and the HSS, the HSS may include a list of User Ids identifying a subset of subscribers served by the HSS, if the occurred failure is limited to those subscribers.

If the Reset-ID feature is supported by the V2X Control Function, the HSS optionally may include one (or several) Reset-ID AVPs identifying e.g. failed hardware components if the occured failure is limited to those subscribers associated with e.g. the identified failed hardware components.

6 Protocol Specification and Implementations

6.1 Introduction

6.1.1 Use of Diameter base protocol

The Diameter Base Protocol as specified in IETF RFC 6733 [3] shall apply except as modified by the defined support of the methods and the defined support of the commands and AVPs, result and error codes as specified in this specification. Unless otherwise specified, the procedures (including error handling and unrecognised information handling) shall be used unmodified as specified in IETF RFC 6733 [3].

6.1.2 Securing Diameter Messages

For secure transport of Diameter messages, see TS 33.210 [4].

6.1.3 Accounting Functionality

Accounting functionality (Accounting Session State Machine, related command codes and AVPs) shall not be used on the V4 interface.

6.1.4 Use of Sessions

Between the V2X Control Function and the HSS, Diameter sessions shall be implicitly terminated. An implicitly terminated session is one for which the server does not maintain state information. The client shall not send any re-authorization or session termination requests to the server.

The Diameter base protocol includes the Auth-Session-State AVP as the mechanism for the implementation of implicitly terminated sessions.

The client (server) shall include in its requests (responses) the Auth-Session-State AVP set to the value NO_STATE_MAINTAINED (1), as described in IETF RFC 6733 [3]. As a consequence, the server shall not maintain any state information about this session and the client shall not send any session termination request. Neither the Authorization-Lifetime AVP nor the Session-Timeout AVP shall be present in requests or responses.

6.1.5 Transport Protocol

Diameter messages over the V4 interface shall make use of SCTP, see IETF RFC 4960 [5].

6.1.6 Routing Considerations

This clause specifies the use of the Diameter routing AVPs Destination-Realm and Destination-Host.

The V4 reference point is defined as an intra-operator interface, and both the V2X Control Function and the HSS are located in the home PLMN of the UE that requests V2X. If the V2X Control Function knows the address/name of the HSS for a certain user, both the Destination-Realm and Destination-Host AVPs shall be present in the request. Otherwise, the Destination-Realm AVP shall be present and the command shall be routed to the next Diameter node. Consequently, the Destination-Host AVP is declared as optional in the ABNF for all requests initiated by the V2X Control Function.

The HSS obtains the Destination-Host AVP to use in requests towards the V2X Control Function, from the Origin-Host AVP received in previous requests from the V2X Control Function. Consequently, the Destination-Host AVP is declared as mandatory in the ABNF for all requests initiated by the HSS.

If the Vendor-Specific-Application-ID AVP is received in any of the commands defined in this specification, it shall be ignored by the receiving node, and it shall not be used for routing purposes.

6.1.7 Advertising Application Support

The V2X Control Function and the HSS shall advertise support of the Diameter V4 Application by including the value of the application identifier in the Auth-Application-Id AVP within the Vendor-Specific-Application-Id grouped AVP of the Capabilities-Exchange-Request and Capabilities-Exchange-Answer commands.

The vendor identifier value of 3GPP (10415) shall be included in the Supported-Vendor-Id AVP of the Capabilities-Exchange-Request and Capabilities-Exchange-Answer commands, and in the Vendor-Id AVP within the Vendor-Specific-Application-Id grouped AVP of the Capabilities-Exchange-Request and Capabilities-Exchange-Answer commands.

The Vendor-Id AVP included in Capabilities-Exchange-Request and Capabilities-Exchange-Answer commands that is not included in the Vendor-Specific-Application-Id AVPs as described above shall indicate the manufacturer of the Diameter node as per IETF RFC 6733 [3].

6.1.8 Diameter Application Identifier

The V4 interface protocol shall be defined as an IETF vendor specific Diameter application, where the vendor is 3GPP. The vendor identifier assigned by IANA to 3GPP (http://www.iana.org/assignments/enterprise-numbers) is 10415.

The Diameter application identifier assigned to the V4 interface application is 16777355 (allocated by IANA).

6.1.9 Use of the Supported-Features AVP

When new functionality is introduced on the V4 interface, it should be defined as optional. If backwards incompatible changes cannot be avoided, the new functionality shall be introduced as a new feature and support advertised with the Supported-Features AVP. The usage of the Supported-Features AVP on the V4 interface is consistent with the procedures for the dynamic discovery of supported features as defined in clause 7.2 of TS 29.229 [6].

When extending the application by adding new AVPs for a feature, the new AVPs shall have the M bit cleared and the AVP shall not be defined mandatory in the command ABNF.

As defined in TS 29.229 [6], the Supported-Features AVP is of type grouped and contains the Vendor-Id, Feature-List-ID and Feature-List AVPs. On the all reference points as specified in this specification, the Supported-Features AVP is used to identify features that have been defined by 3GPP and hence, for features defined in this document, the Vendor-Id AVP shall contain the vendor ID of 3GPP (10415). If there are multiple feature lists defined for the reference point, the Feature-List-ID AVP shall differentiate those lists from one another.

6.2 Commands

6.2.1 Introduction

This clause defines the Command code values and related ABNF for each command described in this specification.

6.2.2 Command-Code Values

This clause defines Command-Code values for the V4 interface application as allocated by IANA.

Every command is defined by means of the ABNF syntax IETF RFC 5234 [7], according to the rules in IETF RFC 6733 [3]. In the case, the definition and use of an AVP is not specified in this document, the guidelines in IETF RFC 6733 [3] shall apply.

The Vendor-Specific-Application-Id AVP shall not be included in any command sent by Diameter nodes supporting applications defined in this specification. If the Vendor-Specific-Application-Id AVP is received in any of the commands defined in this specification, it shall be ignored by the receiving node.

NOTE: The Vendor-Specific-Application-Id is included as an optional AVP in all Command Code Format specifications defined in this specification in order to overcome potential interoperability issues with intermediate Diameter agents non-compliant with the IETF RFC 6733 [3].

The following Command Codes are defined in this specification:

Table 6.2.2-1: Command-Code values for V4

Command-Name	Abbreviation	Code	Clause
ProSe-Subscriber-Information-Request	PIR	8388664	6.2.3
ProSe-Subscriber-Information-Answer	PIA	8388664	6.2.4
Update-ProSe-Subscriber-Data-Request	UPR	8388665	6.2.5
Update-ProSe-Subscriber-Data-Answer	UPA	8388665	6.2.6
ProSe-Notify-Request	PNR	8388666	6.2.7
ProSe-Notify-Answer	PNA	8388666	6.2.8
Reset-Request	RSR	322	6.2.9
Reset-Answer	RSA	322	6.2.10

For these commands, the Application-ID field shall be set to 16777355 (application identifier of the V4 interface application, allocated by IANA).

6.2.3 ProSe-Subscriber-Information-Request (PIR) Command

The ProSe-Subscriber-Information-Request (PIR) command, indicated by the Command-Code field set to 8388664 and the "R" bit set in the Command Flags field, is sent from the V2X Control Function to the HSS. The ProSe-Subscriber-Information-Request (PIR) is originally defined in TS 29.344 [15].

Message Format when used over the V4 application:

```
< ProSe-Subscriber-Information-Request > ::=    < Diameter Header: 8388664, REQ, PXY, 16777355 >
                                                < Session-Id >
                                                [ DRMP ]
                                                [ Vendor-Specific-Application-Id ]
                                                { Auth-Session-State }
                                                { Origin-Host }
                                                { Origin-Realm }
                                                [ Destination-Host ]
                                                { Destination-Realm }
                                                { User-Name }
                                                *[ Supported-Features ]
                                                [ OC-Supported-Features ]
                                                *[ Proxy-Info ]
                                                *[ Route-Record ]
                                                *[ AVP ]
```

6.2.4 ProSe-Subscriber-Information-Answer (PIA) Command

The ProSe-Subscriber-Information-Answer (PIA) command, indicated by the Command-Code field set to 8388664 and the "R" bit cleared in the Command Flags field, is sent from the HSS to the V2X Control Function. The ProSe-Subscriber-Information-Answer (PIA) is originally defined in TS 29.344 [15].

Message Format when used over the V4 application:

```
< ProSe-Subscriber-Information-Answer > ::=     < Diameter Header: 8388664, PXY, 16777355 >
                                                < Session-Id >
                                                [ DRMP ]
                                                [ Vendor-Specific-Application-Id ]
                                                [ Result-Code ]
                                                [ Experimental-Result ]
                                                { Auth-Session-State }
                                                { Origin-Host }
                                                { Origin-Realm }
                                                [ V2X-Subscription-Data ]
                                                [ MSISDN ]
                                                [ Visited-PLMN-Id ]
                                                *[ Supported-Features ]
                                                [ OC-Supported-Features ]
                                                [ OC-OLR ]
                                                *[ Load ]
                                                *[ Reset-ID ]
                                                *[ AVP ]
                                                [ Failed-AVP ]
                                                *[ Proxy-Info ]
                                                *[ Route-Record ]
```

6.2.5 Update-ProSe-Subscriber-Data-Request (UPR) Command

The Update-ProSe-Subscriber-Data-Request (UPR) command, indicated by the Command-Code field set to 8388665 and the 'R' bit set in the Command Flags field, is sent from the HSS to the V2X Control Function. The Update-ProSe-Subscriber-Data-Request (UPR) is originally defined in TS 29.344 [15].

Message Format when used over the V4 application:

```
< Update-ProSe-Subscriber-Data-Request > ::=    < Diameter Header: 8388665, REQ, PXY, 16777355 >
                                                < Session-Id >
                                                [ DRMP ]
                                                [ Vendor-Specific-Application-Id ]
                                                { Auth-Session-State }
                                                { Origin-Host }
                                                { Origin-Realm }
                                                { Destination-Host }
                                                { Destination-Realm }
                                                { User-Name }
                                                *[ Supported-Features ]
                                                [ V2X-Subscription-Data ]
                                                [ Visited-PLMN-Id ]
                                                { V2X-Update-Flags }
                                                *[ Reset-ID ]
                                                *[ AVP ]
                                                *[ Proxy-Info ]
                                                *[ Route-Record ]
```

6.2.6 Update-ProSe-Subscriber-Data-Answer (UPA) Command

The Update-ProSe-Subscriber-Data-Answer (UPA) command, indicated by the Command-Code field set to 8388665 and the 'R' bit cleared in the Command Flags field, is sent from the V2X Control Function to the HSS. The Update-ProSe-Subscriber-Data-Answer (UPA) is originally defined in TS 29.344 [15].

Message Format when used over the V4 application:

```
< Update-ProSe-Subscriber-Data-Answer> ::=  < Diameter Header: 8388665, PXY, 16777355 >
                                            < Session-Id >
                                            [ DRMP ]
                                            [ Vendor-Specific-Application-Id ]
                                            *[ Supported-Features ]
                                            [ Result-Code ]
                                            [ Experimental-Result ]
                                            { Auth-Session-State }
                                            { Origin-Host }
                                            { Origin-Realm }
                                            *[ AVP ]
                                            [ Failed-AVP ]
                                            *[ Proxy-Info ]
                                            *[ Route-Record ]
```

6.2.7 ProSe-Notify-Request (PNR) Command

The ProSe-Notify-Request (VNR) command, indicated by the Command-Code field set to 8388666 and the "R" bit set in the Command Flags field, is sent from the V2X Control Function to the HSS. The ProSe-Nofity-Request (PNR) is originally defined in TS 29.344 [15].

Message Format when used over the V4 application:

```
< ProSe-Notify-Request > ::=  < Diameter Header: 8388666, REQ, PXY, 16777355 >
                              < Session-Id >
                              [ DRMP ]
                              [ Vendor-Specific-Application-Id ]
                              { Auth-Session-State }
                              { Origin-Host }
                              { Origin-Realm }
                              [ Destination-Host ]
                              { Destination-Realm }
                              [ User-Name ]
                              [ Visited-PLMN-Id ]
                              [ V2X-Notify-Flags ]
                              *[ Supported-Features ]
                              [ OC-Supported-Features ]
                              *[ AVP ]
                              *[ Proxy-Info ]
                              *[ Route-Record ]
```

6.2.8 ProSe-Notify-Answer (PNA) Command

The ProSe-Notify-Answer (VNA) command, indicated by the Command-Code field set to 8388666 and the "R" bit cleared in the Command Flags field, is sent from the HSS to the V2X Control Function. The ProSe-Nofity-Answer (PNA) is originally defined in TS 29.344 [15].

Message Format when used over the V4 application:

```
< ProSe-Notify-Answer > ::=  < Diameter Header: 8388666, PXY, 16777355 >
                             < Session-Id >
                             [ DRMP ]
                             [ Vendor-Specific-Application-Id ]
                             [ Result-Code ]
                             [ Experimental-Result ]
                             { Auth-Session-State }
                             { Origin-Host }
                             { Origin-Realm }
                             *[ Supported-Features ]
                             [ OC-Supported-Features ]
```

[OC-OLR]
*[Load]
*[AVP]
[Failed-AVP]
*[Proxy-Info]
*[Route-Record]

6.2.9 Reset-Request (RSR) Command

The Reset-Request (RSR) command, indicated by the Command-Code field set to 322 and the 'R' bit set in the Command Flags field, is sent from HSS to the V2X Control Function.

Message Format when used over the V4 application:

< Reset-Request> ::=< Diameter Header: 322, REQ, PXY, 16777355 >
< Session-Id >
[DRMP]
[Vendor-Specific-Application-Id]
{ Origin-Host }
{ Origin-Realm }
{ Destination-Host }
{ Destination-Realm }
*[Supported-Features]
*[User-Id]
*[Reset-ID]
*[AVP]
*[Proxy-Info]
*[Route-Record]

6.2.10 Reset-Answer (RSA) Command

The Reset-Answer (RSA) command, indicated by the Command-Code field set to 322 and the 'R' bit cleared in the Command Flags field, is sent from V2X Control Function to HSS.

Message Format when used over the V4 application:

< Reset-Answer> ::=< Diameter Header: 322, PXY, 16777355 >
< Session-Id >
[DRMP]
[Vendor-Specific-Application-Id]
*[Supported-Features]
[Result-Code]
[Experimental-Result]
{ Auth-Session-State }
{ Origin-Host }
{ Origin-Realm }
*[AVP]
[Failed-AVP]
*[Proxy-Info]
*[Route-Record]

6.3 AVPs

6.3.1 General

The following table specifies the Diameter AVPs defined for the V4 interface protocol, their AVP Code values, types, possible flag values and whether or not the AVP may be encrypted. The Vendor-ID header of all AVPs defined in this specification shall be set to 3GPP (10415).

Table 6.3.1-1: V4 specific Diameter AVPs

				AVP Flag rules				
Attribute Name	**AVP Code**	**Clause defined**	**Value Type**	**Must**	**May**	**Should not**	**Must not**	**May Encr.**
V2X-PC5-Allowed-PLMN	4600	6.3.3	Grouped	M,V				No
V2X-Update-Flags	4601	6.3.4	Unsigned32	M,V				No
V2X-Notify-Flags	4602	6.3.5	Unsigned32	M,V				No
PLMN-Allowed-PC5-RATs	4603	6.3.10	Grouped	V			M	No
PC5-RAT-Type	4604	6.3.11	Enumerated	V			M	No
NOTE 1: The AVP header bit denoted as "M", indicates whether support of the AVP is required. The AVP header bit denoted as "V", indicates whether the optional Vendor-ID field is present in the AVP header. For further details, see IETF RFC 6733 [3]. NOTE 2: If the M-bit is set for an AVP and the receiver does not understand the AVP, it shall return a rejection. If the M-bit is not set for an AVP, the receiver shall not return a rejection, whether or not it understands the AVP. If the receiver understands the AVP but the M-bit value does not match with the definition in this table, the receiver shall ignore the M-bit.								

The following table specifies the Diameter AVPs re-used by the V4 interface protocol from existing Diameter Applications, including a reference to their respective specifications and when needed, a short description of their use within V4.

Any other AVPs from existing Diameter Applications, except for the AVPs from the Diameter base protocol, do not need to be supported. The AVPs from the Diameter base protocol are not included in table 6.3.1-2, but they may be re-used for the V4 protocol.

Table 6.3.1-2: V4 re-used Diameter AVPs

Attribute Name	Reference	Comments	M-bit
V2X-Subscription-Data	TS 29.272 [10]	See clause 6.3.2.	
Visited-PLMN-Id	TS 29.272 [10]		
User-Name	IETF RFC 6733 [3]		
User-Id	TS 29.272 [10]		
Reset-ID	TS 29.272 [10]		
MSISDN	TS 29.329 [11]		
Supported-Features	TS 29.229 [6]		
Feature-List-ID	TS 29.229 [6]		
Feature-List	TS 29.229 [6]		
OC-Supported-Features	IETF RFC 7683 [12]	See clause 6.3.6	Must set
OC-OLR	IETF RFC 7683 [12]	See clause 6.3.7	Must set
DRMP	IETF RFC 7944 [13]	See clause 6.3.8	Must not set
Load	IETF RFC 8583 [16]	See clause 6.3.9	Must not set
NOTE 1: The M-bit settings for re-used AVPs override those of the defining specifications that are referenced. Values include: "Must set", "Must not set". If the M-bit setting is blank, then the defining specification applies. NOTE 2: If the M-bit is set for an AVP and the receiver does not understand the AVP, it shall return a rejection. If the M-bit is not set for an AVP, the receiver shall not return a rejection, whether or not it understands the AVP. If the receiver understands the AVP but the M-bit value does not match with the definition in this table, the receiver shall ignore the M-bit.			

6.3.2 V2X-Subscription-Data

The V2X-Subscription-Data AVP is of type Group. It shall contain the V2X related subscription data. The V2X-Subscription-Data is originally defined in TS 29.272 [10].

AVP format when used over V4 interface:

V2X-Subscription-Data ::= <AVP header: 1688 10415>

[V2X-PC5-Allowed-PLMN]

*[AVP]

6.3.3 V2X-PC5-Allowed-PLMN

The V2X-PC5-Allowed-PLMN AVP is of type Grouped. It shall contain the PLMN where the UE is authorised to use V2X communication over PC5, and for each indicated PLMN, the RAT(s) over which the UE is authorized to perform V2X communication over PC5 reference point.

AVP format

V2X-PC5-Allowed-PLMN ::= <AVP header: 4600 10415>

*[Visited-PLMN-Id]

*[PLMN-Allowed-PC5-RATs]

*[AVP]

If the Visited-PLMN-Id AVP is absent, the PLMN-Allowed-PC5-RATs AVP shall be absent.

6.3.4 V2X-Update-Flags

The V2X-Update-Flags AVP is of type Unsigned32 and it shall contain a bit mask. The meaning of the bits is defined in table 6.3.4-1:

Table 6.3.4-1: V2X-Update-Flags

Bit	Name	Description
0	Update	This bit, when set, indicates that the V2X subscriber related data are updated.
1	Removal	This bit, when set, indicates that all of the V2X subscriber related data are removed.
2	Reset-ID Update	This bit, when set, indicates that the complete list on Reset-IDs is updated.
3	Reset-ID Removal	This bit, when set, indicates that the complete list on Reset-IDs is removed.
NOTE: Bits not defined in this table shall be cleared by the sending HSS and discarded by the receiving V2X Control Function.		

6.3.5 V2X-Notify-Flags

The V2X-Notify-Flags AVP is of type Unsigned32 and it shall contain a bit mask. The meaning of the bits shall be as defined in table 6.3.5-1:

Table 6.3.5-1: V2X-Notify-Flags

bit	name	Description
0	V2X communication over PC5 Revoked	This bit, when set, shall indicate to the HSS that the authorization for V2X communication over PC5 is to be revoked on the indicated PLMN.
1	Purged UE	This bit, when set, shall indicate to the HSS that the subscriber's data has been deleted from the V2X Control Function.
NOTE 1: Bits not defined in this table shall be cleared by the sending V2X Control Function and discarded by the receiving HSS. NOTE 2: If Purged UE bit is set, all other bits in this table shall be cleared by the sending V2X Control Function and discarded by the receiving HSS.		

6.3.6 OC-Supported-Features

The OC-Supported-Features AVP is of type Grouped and it is defined in IETF RFC 7683 [12]. This AVP is used to support Diameter overload control mechanism, see Annex A for more information.

6.3.7 OC-OLR

The OC-OLR AVP is of type Grouped and it is defined in IETF RFC 7683 [12]. This AVP is used to support Diameter overload control mechanism, see Annex A for more information.

6.3.8 DRMP

The DRMP AVP is of type Enumerated and it is defined in IETF RFC 7944 [13]. This AVP allows the HSS and the V2X Control Function to indicate the relative priority of Diameter messages over the V4 interface.

6.3.9 Load

The Load AVP is of type Grouped and it is defined in IETF RFC 8583 [16]. This AVP is used to support Diameter load control mechanism, see Annex D for more information.

6.3.10 PLMN-Allowed-PC5-RATs

The PLMN-Allowed-PC5-RATs AVP is of type Grouped. It shall contain the RAT(s) over the indicated PLMN where the UE is authorized to perform V2X communication over PC5 reference point.

AVP format

V2X-PC5-Allowed-PLMN ::= <AVP header: 4603 10415>

{ Visited-PLMN-Id }

1*{ PC5-RAT-Type }

*[AVP]

6.3.11 PC5-RAT-Type

The PC5-RAT-Type AVP (AVP code 4604) is of type Enumerated, it is used to identify the PC5 radio technology to perform V2X communication over PC5 reference point.

The following values are defined:

LTE (0)

This value shall be used to indicate that the RAT is PC5 LTE.

NR (1)

This value shall be used to indicate that the RAT is PC5 NR.

6.4 Result-Code AVP and Experimental-Result AVP Values

6.4.1 General

This clause defines result code values that shall be supported by all Diameter implementations that conform to this specification.

6.4.2 Success

Result codes that fall within the Success category shall be used to inform a peer that a request has been successfully completed. The Result-Code AVP values defined in the Diameter base protocol IETF RFC 6733 [3] shall be applied.

6.4.3 Permanent Failures

6.4.3.1 General

Errors that fall within the Permanent Failures category shall be used to inform the peer that the request has failed, and should not be attempted again. The Result-Code AVP values defined in the Diameter base protocol IETF RFC 6733 [3] shall be applied. When one of the result codes defined here is included in a response, it shall be inside an Experimental-Result AVP and the Result-Code AVP shall be absent.

6.4.3.2 DIAMETER_ERROR_USER_UNKNOWN (5001)

This result code shall be sent by the HSS to indicate that the user identified by the IMSI is unknown. This error code is defined in TS 29.229 [6].

6.4.3.3 DIAMETER_ERROR_UNKNOWN_V2X_SUBSCRIPTION (5690)

This result code shall be sent by the HSS to indicate that no V2X subscription is associated with the IMSI.

6.4.3.4 DIAMETER_ERROR_V2X_NOT_ALLOWED (5691)

This result code shall be sent by the HSS to indicate that V2X is not allowed to be used in the specific PLMN where the UE is registered.

Annex A (normative): Diameter overload control mechanism

A.1 General

Diameter overload control mechanism is an optional feature.

IETF RFC 7683 [12] specifies a Diameter overload control mechanism which includes the definition and the transfer of related AVPs between Diameter nodes.

It is recommended to make use of IETF RFC 7683 [12] on the V4 interface where, when applied, the V2X Control Function shall behave as reacting nodes and the HSS as a reporting node.

A.2 HSS behaviour

The HSS requests traffic reduction from the V2X Control Function when it is in an overload situation, including OC-OLR AVP in answer commands as described in IETF RFC 7683 [12].

The HSS identifies that it is in an overload situation by implementation specific means. For example, the HSS may take into account the traffic over the V4 interface or other interfaces, the level of usage of internal resources (CPU, memory), the access to external resources, etc.

The HSS determines the specific contents of OC-OLR AVP in overload reports and the HSS decides when to send OC-OLR AVPs by implementation specific means.

A.3 V2X Control Function behaviour

The V2X Control Function applies required traffic reduction received in answer commands to subsequent applicable requests, as per IETF RFC 7683 [12].

The V2X Control Function achieves requested traffic reduction by implementation specific means. For example, the V2X Control Function may implement message throttling with prioritization or a message retaining mechanism for operations that can be postponed.

Annex B (Informative): Diameter overload node behaviour

B.1 Message prioritization

This clause describes possible behaviours of the V2X Control Function regarding message prioritisation in an informative purpose.

The V2X Control Function may take the following into account when making throttling decisions:

- Identification of the procedures that can be deferred, so to avoid to drop non deferrable procedures;
- Prioritisation of certain types of request (e.g. between V2X-Subscriber-Information-Request (PIR) and V2X-Notify-Request (PNR)) according to the context of their use, in particular:
  - Higher prioritisation for commands that are related to a registered user for a service, so to avoid the interruption of the registered service for the user.

Annex C (normative): Diameter message priority mechanism

C.1 General

IETF RFC 7944 [13] specifies a Diameter routing message priority mechanism that allows Diameter nodes to indicate the relative priority of Diameter messages. With this information, other Diameter nodes may leverage the relative priority of Diameter messages into routing, resource allocation and also abatement decisions when overload control is applied.

C.2 V4 interface

C.2.1 General

The Diameter message priority mechanism is an optional feature.

It is recommended to make use of IETF RFC 7944 [13] over the V4 interface of an operator network when the overload control defined in Annex A is applied on this V4 interface.

C.2.2 HSS and V2X Control Function behaviour

When the HSS and the V2X Control Function support the Diameter message priority mechanism over the V4 interface, the HSS and the V2X Control Function shall comply with IETF RFC 7944 [13]. In particular, when priority is required, the HSS and the V2X Control Function shall include the DRMP AVP indicating a priority level in the requests it sends, and prioritise received requests according to the priority level received within the DRMP AVP. They shall prioritise received answers according to the priority level received within the DRMP AVP if present, otherwise according to the priority level of the corresponding request. They shall include the DRMP AVP in the answer to a received request if the required priority of the answer is different from the one of the request. The HSS and the V2X Control Function decisions for a required priority and for the priority level value are implementation specific.

Diameter requests related to high priority traffic should contain a DRMP AVP with a high priority of which the level value is operator dependent.

D.1 General

Diameter load control mechanism is an optional feature.

IETF RFC 8583 [16] specifies a Diameter load control mechanism which includes the definition and the transfer of related AVPs between Diameter nodes.

It is recommended to make use of IETF RFC 8583 [16] on the V4 interface where, when applied, the V2X Control Function shall behave as reacting node and the HSS as a reporting node.

D.2 HSS behaviour

The HSS may report its current load by including a Load AVP of type HOST in answer commands as described in IETF RFC 8583 [16].

The HSS calculates its current load by implementation specific means. For example, the HSS may take into account the traffic over the V4 interface or other interfaces, the level of usage of internal resources (e.g. CPU, memory), the access to external resources, etc.

The HSS determines when to send Load AVPs of type HOST by implementation specific means.

D.3 V2X Control Function behaviour

When performing next hop Diameter Agent selection for requests that are routed based on realm, the V2X Control Function may take into account load values from Load AVPs of type PEER received from candidate next hop Diameter nodes, as per IETF RFC 8583 [16].

Annex E (informative): Change history

Change history							
Date	**Meeting**	**TDoc**	**CR**	**Rev**	**Cat**	**Subject/Comment**	**New version**
2016-10	CT4#74bis					Skeleton, Implementation of C4-165230, C4-165231	0.1.0
2016-10	CT4#74bis					Editorial correction to the numbering of clauses	0.1.1
2016-11	CT4#75					Implementation of C4-166239, C4-166242	0.2.0
2017-02	CT4#76					Implementation of C4-171299, C4-171301, C4-171303, C4-171305.	0.3.0
2017-03	CT#75	CP-170014				Presented for information and approval	1.0.0
2017-03	CT#75					TS approved in CT#75	14.0.0
2017-06	CT#76	CP-171032	0001	1		Load Control	14.1.0
2018-06	CT#80	-	-	-		Update to Rel-15 version (MCC)	15.0.0
2019-09	CT#85	CP-192094	0002	1		draft-ietf-dime-load published as RFC 8583	15.1.0
2020-06	CT#88e	CP-201049	0004	-		Authorized PLMNs and RATs for V2X	16.0.0
2022-04	-	-	-	-	-	Update to Rel-17 version (MCC)	17.0.0
2026-06	CT#112	CP-261038	0008	1	A	Implementation error of CR#0002	17.1.0

History

Version	Date	Status
V17.0.0	April 2022	Publication
V17.1.0	August 2026	Publication