EUROPEAN TELECOMMUNICATION STANDARD

ETS 300 476-2

August 1996

Source: ETSI TC-RES

Reference: DE/RES-03042-2

ICS: 33.020, 33.060.50

Key words: DECT, CI, PICS

Radio Equipment and Systems (RES); Digital Enhanced Cordless Telecommunications (DECT); Common Interface (CI); Protocol Implementation Conformance Statement (PICS) proforma; Part 2: Data Link Control (DLC) layer - Portable radio Termination (PT)

ETSI

European Telecommunications Standards Institute

ETSI Secretariat

Postal address: F-06921 Sophia Antipolis CEDEX - FRANCE
Office address: 650 Route des Lucioles - Sophia Antipolis - Valbonne - FRANCE
X.400: c=fr, a=atlas, p=etsi, s=secretariat - **Internet:** secretariat@etsi.fr

Tel.: +33 92 94 42 00 - Fax: +33 93 65 47 16

Copyright Notification: No part may be reproduced except as authorized by written permission. The copyright and the foregoing restriction extend to reproduction in all media.

© European Telecommunications Standards Institute 1996. All rights reserved.

Whilst every care has been taken in the preparation and publication of this document, errors in content, typographical or otherwise, may occur. If you have comments concerning its accuracy, please write to "ETSI Editing and Committee Support Dept." at the address shown on the title page.

Contents

Foreword 9

1 Scope 11

2 Normative references 11

3 Definitions, symbols and abbreviations 12
3.1 Definitions 12
3.2 Abbreviations 12

4 Conformance requirement to this PICS proforma specification 12

Annex A (normative): PICS Proforma for DECT DLC PT 13

A.1 Introduction for completing the PICS proforma 13
A.1.1 Purposes and structure 13
A.1.2 Guidances for completing the PICS 15

A.2 Identification of the implementation 16
A.2.1 Date of statement 16
A.2.2 Implementation Under Test (IUT) identification 16
A.2.3 System Under Test (SUT) identification 16
A.2.4 Product supplier 16
A.2.5 Client identification 17
A.2.6 Contact person 17

A.3 Identification of the protocol 17

A.4 Global statement of conformance 18

A.5 Capabilities 18
A.5.1 Major capabilities 18
A.5.1.1 Services 18
A.5.1.2 Procedures 19
A.5.1.2.1 Generic signalling procedures 19
A.5.1.2.2 Class U procedures 19
A.5.1.2.3 Class A procedures 19
A.5.1.2.4 Class B procedures 20
A.5.1.2.5 Broadcast procedures 20
A.5.1.2.6 LU1 procedures 20
A.5.1.2.7 LU2 procedures 21
A.5.1.2.8 LU5 protected data procedures 21
A.5.1.2.9 LU5 unprotected data procedures 22
A.5.1.2.10 LU7 procedures 22
A.5.1.2.11 Management procedures 23
A.5.2 Protocol parameters 24
A.5.2.1 C-plane timers 24
A.5.2.2 U-plane timers 24
A.5.2.3 Class A parameters 25
A.5.2.4 Class B parameters 25
A.5.2.5 LU1 parameters 25
A.5.2.6 LU2 parameters 25
A.5.2.7 LU5 parameters 26
A.5.2.8 LU7 parameters 27
A.5.3 Protocol PDUs 27
A.5.3.1 C-plane PDUs 27

A.5.3.1.1 C-plane frame structure 27
A.5.3.1.2 C-plane messages 28
A.5.3.1.2.1 Message support 28
A.5.3.1.2.2 Class A I-command 29
A.5.3.1.2.3 Class A RR command/response 31
A.5.3.1.2.4 Class B I-command 32
A.5.3.1.2.5 Class B RR command/response 33
A.5.3.1.2.6 Class B RNR command/response 34
A.5.3.1.2.7 Class B REJ command/response 35
A.5.3.1.2.8 Class B SABM command 37
A.5.3.1.2.9 Class B DM response 38
A.5.3.1.2.10 Class B DISC command 39
A.5.3.1.2.11 Class B UA response 40
A.5.3.1.2.12 Class U UI command 41
A.5.3.2 U-plane PDUs 43
A.5.3.2.1 FU1 frame structure 43
A.5.3.2.2 FU4 frame structure 44
A.5.3.2.3 FU5 frame structure 45
A.5.3.2.4 FU6a frame structure 47
A.5.3.2.5 FU6b frame structure 48
A.5.3.2.6 FU7 frame structure 49
A.5.4 Protocol error handling 51
A.5.4.1 General error handling 51
A.5.4.2 Class A error handling and recovery 51
A.5.4.3 Class B error handling and recovery 51

History 52

Questions

Table A.1 Date of Statement 16
Table A.2 IUT identification 16
Table A.3 SUT identification 16
Table A.4 Product supplier 16
Table A.5 Client 17
Table A.6 Contact person 17
Table A.7 Identification of protocol 17
Table A.8 Global statement of conformance 18
Table A.9 Data link services 18
Table A.10 C-plane services 18
Table A.11 U-plane services 18
Table A.12 Management services 19
Table A.13 Generic signalling procedures 19
Table A.14 Class U procedures 19
Table A.15 Class A procedures 19
Table A.16 Class B procedures 20
Table A.17 Broadcast procedures 20
Table A.18 LU1 procedures 20
Table A.19 FU1 options 20
Table A.20 LU2 procedures 21
Table A.21 FU4 options 21
Table A.22 FU5 options 21
Table A.23 FU6 options 21
Table A.24 LU5 protected data procedures 21
Table A.25 LU5 unprotected data procedures 22
Table A.26 LU7 procedures 22
Table A.27 LU7 establishment and synchronisation procedures 22
Table A.28 LU7 active phase procedures 22
Table A.29 LU7 exceptional procedures 23

Table A.30 Management procedures....23
Table A.31 MAC connection management procedures....23
Table A.32 DLC C-plane management procedures....23
Table A.33 DLC U-plane management procedures....24
Table A.34 Connection ciphering management procedures....24
Table A.35 C-plane timers....24
Table A.36 U-plane timers....24
Table A.37 Class A parameter values....25
Table A.38 Class B parameter values....25
Table A.39 LU1 Frame types....25
Table A.40 LU1 Connection types....25
Table A.41 LU2 Frame types....25
Table A.42 LU2 Connection types....26
Table A.43 LU2 Transmission classes....26
Table A.44 LU5 Frame types....26
Table A.45 LU5 Connection types....26
Table A.46 LU5 Transmission classes....27
Table A.47 LU7 Frame types....27
Table A.48 LU7 Connection types....27
Table A.49 LU7 Transmission classes....27
Table A.50 Frame structures (Sending P to F)....27
Table A.51 Frame structures (Receipt F to P)....27
Table A.52 Frame format type FA (Sending P to F)....28
Table A.53 Frame format type FA (Receipt F to P)....28
Table A.54 Broadcast service frame structure (Receipt F to P)....28
Table A.55 Class A messages support (Sending P to F)....28
Table A.56 Class A messages support (Receipt F to P)....28
Table A.57 Class B messages support (Sending P to F)....29
Table A.58 Class B messages support (Receipt F to P)....29
Table A.59 Class U messages support (Sending P to F)....29
Table A.60 Class U messages support (Receipt F to P)....29
Table A.61 Class A I-command (Numbered Information) (Sending P to F)....29
Table A.62 Class A I-command (Numbered Information) (Receipt F to P)....30
Table A.63 Class A I-command Control field (Sending P to F)....30
Table A.64 Class A I-command Control field (Receipt F to P)....30
Table A.65 Class A I-command Address field (Sending P to F)....30
Table A.66. Class A I-command Address field (Receipt F to P)....30
Table A.67 Class A RR-command/response (Receive ready) (Sending P to F)....31
Table A.68 Class A RR-command/response (Receive ready) (Receipt F to P)....31
Table A.69 Class A RR Control field (Sending P to F)....31
Table A.70 Class A RR Control field (Receipt F to P)....31
Table A.71 Class A RR Address field (Sending P to F)....31
Table A.72 Class A RR Address field (Receipt F to P)....32
Table A.73 Class B I-command (Numbered Information) (Sending P to F)....32
Table A.74 Class B I-command (Numbered Information) (Receipt F to P)....32
Table A.75 Class B I-command Control field (Sending P to F)....32
Table A.76 Class B I-command Control field (Receipt F to P)....32
Table A.77 Class B I-command Address field (Sending P to F)....33
Table A.78 Class B I-command Address field (Receipt F to P)....33
Table A.79 Class B RR-command/response (Receive ready) (Sending P to F)....33
Table A.80 Class B RR-command/response (Receive ready) (Receipt F to P)....33
Table A.81 Class B RR Control field (Sending P to F)....33
Table A.82 Class B RR Control field (Receipt F to P)....34
Table A.83 Class B RR Address field (Sending P to F)....34
Table A.84 Class B RR Address field (Receipt F to P)....34
Table A.85 Class B RNR command/response (Receive Not Ready) (Sending P to F)....34
Table A.86 Class B RNR command/response (Receive Not Ready) (Receipt F to P)....34
Table A.87 Class B RNR Control field (Sending P to F)....35
Table A.88 Class B RNR Control field (Receipt F to P)....35
Table A.89 Class B RNR Address field (Sending P to F)....35
Table A.90 Class B RNR Address field (Receipt F to P)....35
Table A.91 Class B REJ command/response (Reject) (Sending P to F)....35
Table A.92 Class B REJ command/response (Reject) (Receipt F to P)....36

Table A.93 Class B REJ Control field (Sending P to F) 36
Table A.94 Class B REJ Control field (Receipt F to P) 36
Table A.95 Class B REJ Address field (Sending P to F) 36
Table A.96 Class B REJ Address field (Receipt F to P) 36
Table A.97 Class B SABM command (Sending P to F) 37
Table A.98 Class B SABM command (Receipt F to P) 37
Table A.99 Class B SABM Control field (Sending P to F) 37
Table A.100 Class B SABM Control field (Receipt F to P) 37
Table A.101 Class B SABM Address field (Sending P to F) 37
Table A.102 Class B SABM Address field (Receipt F to P) 38
Table A.103 Class B DM-response (Disconnect Mode) (Sending P to F) 38
Table A.104 Class B DM-response (Disconnect Mode) (Receipt F to P) 38
Table A.105 Class B DM Control field (Sending P to F) 38
Table A.106 Class B DM Control field (Receipt F to P) 38
Table A.107 Class B DM Address field (Sending P to F) 39
Table A.108 Class B DM Address field (Receipt F to P) 39
Table A.109 Class B DISC command (Disconnect) (Sending P to F) 39
Table A.110 Class B DISC command (Disconnect) (Receipt F to P) 39
Table A.111 Class B DISC Control field (Sending P to F) 39
Table A.112 Class B DISC Control field (Receipt F to P) 40
Table A.113 Class B DISC Address field (Sending P to F) 40
Table A.114 Class B DISC Address field (Receipt F to P) 40
Table A.115 Class B UA-response (Unnumbered ACK) (Sending P to F) 40
Table A.116 Class B UA-response (Unnumbered ACK) (Receipt F to P) 40
Table A.117 Class B UA Control field (Sending P to F) 41
Table A.118 Class B UA Control field (Receipt F to P) 41
Table A.119 Class B UA Address field (Sending P to F) 41
Table A.120 Class B UA Address field (Receipt F to P) 41
Table A.121 Class U UI command (Unnumbered Information) (Sending P to F) 41
Table A.122 Class U UI command (Unnumbered Information) (Receipt F to P) 42
Table A.123 Class U UI Control field (Sending P to F) 42
Table A.124 Class U UI Control field (Receipt F to P) 42
Table A.125 Class U UI Address field (Sending P to F) 42
Table A.126 Class U UI Address field (Receipt F to P) 42
Table A.127 U-plane frames (Sending P to F) 43
Table A.128 U-plane frames (Receipt F to P) 43
Table A.129 FU1 frame structure (Sending P to F) 43
Table A.130 FU1 frame structure (Receipt F to P) 43
Table A.131 FU4 frame structure (Sending P to F) 44
Table A.132 FU4 frame structure (Receipt F to P) 44
Table A.133 FU4 Length indicator field (Sending P to F) 44
Table A.134 FU4 Length indicator field (Receipt F to P) 44
Table A.135 FU4 Send sequence number (Sending P to F) 44
Table A.136 FU4 Send sequence number (Receipt F to P) 44
Table A.137 FU4 Receive sequence number (Sending P to F) 45
Table A.138 FU4 Receive sequence number (Receipt F to P) 45
Table A.139 FU5 frame structure (Sending P to F) 45
Table A.140 FU5 frame structure (Receipt F to P) 45
Table A.141 FU5 Address field (Sending P to F) 45
Table A.142 FU5 Address field (Receipt F to P) 46
Table A.143 FU5 Length indicator field (Sending P to F) 46
Table A.144 FU5 Length indicator field (Receipt F to P) 46
Table A.145 FU5 Send sequence number (Sending P to F) 46
Table A.146 FU5 Send sequence number (Receipt F to P) 46
Table A.147 FU5 Receive sequence number (Sending P to F) 46
Table A.148 FU5 Receive sequence number (Receipt F to P) 47
Table A.149 FU6a frame structure (Sending P to F) 47
Table A.150 FU6a frame structure (Receipt F to P) 47
Table A.151 FU6a Length indicator field (Sending P to F) 47
Table A.152 FU6a Length indicator field (Receipt F to P) 47
Table A.153 FU6a Send sequence number (Sending P to F) 47
Table A.154 FU6a Send sequence number (Receipt F to P) 48
Table A.155 FU6b frame structure (Sending P to F) 48

Table A.156 FU6b frame structure (Receipt F to P) 48
Table A.157 FU6b Receive sequence number (Sending P to F) 48
Table A.158 FU6b Receive sequence number (Receipt F to P) 48
Table A.159 FU7 64 kbit/s frame structure (Sending P to F) 49
Table A.160 FU7 64 kbit/s frame structure (Receipt F to P) 49
Table A.161 FU7 64 kbit/s control field (Sending P to F) 49
Table A.162 FU7 64 kbit/s control field (Receipt F to P) 50
Table A.163 FU7 72 kbit/s frame structure (Sending P to F) 50
Table A.164 FU7 72 kbit/s frame structure (Receipt F to P) 50
Table A.165 FU7 72 kbit/s control field (Sending P to F) 50
Table A.166 FU7 72 kbit/s control field (Receipt F to P) 51
Table A.167 General error handling 51
Table A.168 Class A error handling and recovery 51
Table A.169 Class B error handling and recovery 51

Blank page

Foreword

This European Telecommunication Standard (ETS) has been produced by the Radio Equipment and Systems (RES), Technical Committee of the European Telecommunications Standards Institute (ETSI).

The DECT Common interface Protocol Implementation Conformance Statement (PICS) proforma standard comprises seven parts as follows:

Part 1: "Network (NWK) layer - Portable radio Termination (PT)";

Part 2: "Data Link Control (DLC) layer - Portable radio Termination (PT)";

Part 3: "Medium Access Control (MAC) layer - Portable radio Termination (PT)";

Part 4: "Network (NWK) layer - Fixed radio Termination (FT)";

Part 5: "Data Link Control (DLC) layer - Fixed radio Termination (FT)";

Part 6: "Medium Access Control (MAC) layer - Fixed radio Termination (FT)";

Part 7: "Physical layer".

Annex A contains the PICS proforma for the PT network layer.

Transposition dates	
Date of adoption of this ETS:	16 August 1996
Date of latest announcement of this ETS (doa):	30 November 1996
Date of latest publication of new National Standard or endorsement of this ETS (dop/e):	31 May 1997
Date of withdrawal of any conflicting National Standard (dow):	31 May 1997

Blank page

1 Scope

This European Telecommunication Standard (ETS) provides the Protocol Implementation Conformance Statement (PICS) proforma for the Digital Enhanced Cordless Telecommunications Data Link Control layer at the Portable Termination as defined in ETS 300 175 Part 4 [4] in compliance with the relevant requirements and in accordance with the relevant guidance given in ISO/IEC 9646-7 [14].

The supplier of an implementation which is claimed to conform to ETS 300 175-4 [4] is required to complete a copy of the PICS proforma provided in the annex A of this standard.

2 Normative references

This ETS incorporates, by dated or undated reference, provisions from other publications. These normative references are cited at the appropriate places in the text and the publications are listed hereafter. For dated references, subsequent amendments to or revisions of any of these publications apply to this ETS only when incorporated in it by amendment or revision. For undated references the latest edition of the publication referred to applies.

[1] ETS 300 175-1: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 1: Overview".

[2] ETS 300 175-2: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 2: Physical Layer".

[3] ETS 300 175-3: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 3: Medium Access Control (MAC) layer".

[4] ETS 300 175-4: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 4: Data Link Control (DLC) layer".

[5] ETS 300 175-5: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 5: Network (NWK) layer".

[6] ETS 300 175-6: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 6: Identities and addressing".

[7] ETS 300 175-7: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 7: Security features".

[8] ETS 300 175-8: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 8: Speech coding and transmission".

[9] ETS 300 175-9: "Radio Equipment and Systems (RES); Digital European Cordless Telecommunications (DECT); Common Interface (CI); Part 9: Public Access Profile (PAP)".

[10] ETS 300 406 (1995): "Methods for Testing and Specification (MTS); Protocol and profile conformance testing specifications; Standardization methodology".

[11] ISO/IEC 9646-1 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 1: General concepts".

[12] ISO/IEC 9646-7 (1995): "Information technology - Open Systems Interconnection - Conformance testing methodology and framework - Part 7: Implementation Conformance Statements".

3 Definitions, symbols and abbreviations

3.1 Definitions

For the purposes of this ETS, the following terms and definitions apply:

- terms defined in ETS 300 175-1 [1]
- terms defined in ISO/IEC 9646-1 [11] and in ISO/IEC 9646-7 [12].

In particular, the following terms defined in ISO/IEC 9646-1 [11] apply:

Implementation Conformance Statement (ICS): A statement made by the supplier of an implementation or system claimed to conform to a given specification, stating which capabilities have been implemented. The ICS can take several forms: protocol ICS, profile ICS, profile specific ICS, information object ICS, etc.

ICS proforma: A document, in the form of a questionnaire, which when completed for an implementation or system becomes an ICS.

Protocol ICS (PICS): A PICS for an implementation or system claimed to conform to a given protocol specification.

3.2 Abbreviations

For the purposes of this ETS, the abbreviations defined in ISO/IEC 9646-1 [11], the data link control layer abbreviations defined in ETS 300 175-4 [4], and the following abbreviations apply.

ICS	Implementation Conformance Statement
IUT	Implementation Under Test
PICS	Protocol Implementation Conformance Statement
SCS	System Conformance Statement
SUT	System Under Test

4 Conformance requirement to this PICS proforma specification

If it claims to conform to this ETS, the actual PICS proforma to be filled in by a supplier shall be technically equivalent to the text of the PICS proforma given in annex A, and shall preserve the numbering/naming and ordering of the proforma items.

A PICS which conforms to this ETS shall be a conforming PICS proforma completed in accordance with the guidances for completion given in clause A.1.

Annex A (normative): PICS Proforma for DECT DLC PT

Notwithstanding the provisions of the copyright clause related to the text of the present ETS (see front page), ETSI grants users of this ETS to freely reproduce the PICS Proforma in this annex so that it can be used for its intended purposes and may further publish the completed PICS.

A.1 Introduction for completing the PICS proforma

A.1.1 Purposes and structure

The purpose of this PICS proforma is to provide a mechanism whereby a supplier of an implementation of the portable termination specific data link control layer requirements of ETS 300 175-4 [4]: DECT Data link control layer may provide information about the implementation in a standardized manner.

The PICS proforma is subdivided into subclauses for the following categories of information:

- instructions for completing the PICS proforma;
- identification of the implementation;
- identification of the ETS 300 175-4 [4]: DECT Data link control layer;
- PICS proforma tables;
    - global statement of conformance;
    - functional groups and procedures;
    - timers and protocol parameters;
    - messages;
    - information elements;
    - protocol error handling.

The PICS proforma contained in this annex is comprised of information in tabular form in accordance with the guidelines presented in ISO/IEC 9646-7 [12].

Item column

The item column contains a number which identifies the item in the table.

Item description column

The item description column describes in free text each respective item (e.g. parameters, timers, etc.). It implicitly means "is <item description> supported by the implementation?".

Status column

The following notations, defined in ISO/IEC 9646-7 [12], are used for the status column:

m or M	mandatory - the capability is required to be supported.
o or O	optional - the capability may be supported or not (e.g. the capability is not allowed because the underlying DECT layers (service provider) cannot handle it or the requirement belongs to an application i.e. does not belong to the data link control layer)
n/a or N/A	not applicable - in the given context, it is impossible to use the capability.
x or X	prohibited (excluded) - there is a requirement not to use this capability in the given context.
o.i or O.i	qualified optional - for mutually exclusive or selectable options from a set. "i" is an integer which identifies an unique group of related optional items and the logic of their selection which is defined immediately following the table.
ci or Ci	conditional - the requirement on the capability ("m", "o", "x" or "n/a") depends on the support of other optional or conditional items. "i" is an integer identifying an unique conditional status expression which is defined immediately following the table.
i or I	out-of-scope - this capability is outside the scope of the given specification, and hence irrelevant and not subject to conformance testing. This status is in particular applicable for data fields which are reserved for future use. The structure of such fields has to be supported, but the value is undefined and thus to be ignored.

Reference column

The reference column gives reference to ETS 300 175-4 [4]: Data link control layer, except where explicitly stated otherwise.

Support column

The support column shall be filled in by the supplier of the implementation. The following common notations, defined in ISO/IEC 9646-7 [12], are used for the support column:

Y or y	supported by the implementation
N or n	not supported by the implementation
N/A, n/a or -	no answer required (allowed only if the status is n/a, directly or after evaluation of a conditional status)

In each context, the kind of "non-support" which is implemented at the receipt may be additionally indicated such as:

- Err the item is treated as a protocol error;
- lg the item is received and ignored (i.e. processed syntactically, but not semantically);
- rj the item is received and rejected.

NOTE: As stated in ISO/IEC 9646-7 [12], support for a PDU requires the ability to parse all valid parameters of that PDU. Supporting a PDU while having no ability to parse a valid parameter is non-conformant. Support for a parameter on a PDU means that the semantics of that parameter are supported.

Values allowed column

The values allowed column contains the values or the ranges of values allowed. The range of value is defined as follows: [min value] .. [max value]. Alternative values are defined as follows:

[value1], [value 2], ..., [value n].

EXAMPLE: '00110000'B .. '01001011'B is the value range
from '00110000'B to '01001011'B

'00110000'B, '01001011'B the value can be '00110000'B or '01001011'B.

Values supported column

The values supported column shall be filled in by the supplier of the implementation. In this column, the values or the ranges of values supported by the implementation shall be indicated.

Prerequisite line

A prerequisite line takes the form: Prerequisite: <predicate>.

A prerequisite line before a clause or table title indicates that the whole clause or the whole table is not required to be completed if the predicate is FALSE.

A.1.2 Guidances for completing the PICS

The supplier of the implementation shall complete the PICS proforma in each of the spaces provided using the notation described in subclause A.1.1. Specific instruction is provided in the text which precedes certain table.

A.2 Identification of the implementation

A.2.1 Date of statement

Identification of the Implementation Under Test (IUT) and the system in which it resides (the System Under Test (SUT)) should be filled in so as to provide as much detail as possible regarding version numbers and configuration options.

Table A.1 Date of statement

Date of statement		
Day	**Month**	**Year**

A.2.2 Implementation Under Test (IUT) identification

The supplier of the implementation shall enter information necessary to uniquely identify the IUT in the table below.

Table A.2 IUT identification

IUT identification	
IUT name	
IUT version	

A.2.3 System Under Test (SUT) identification

The supplier of the implementation shall enter information necessary to uniquely identify the SUT in the table below.

Table A.3 SUT identification

IUT identification	
SUT name	International Portable Equipment Identity (IPEI):
Hardware configuration	

A.2.4 Product supplier

Table A.4 Product supplier

Product supplier	
Name	
Address	
Phone No.	
Fax No.	
E-mail address	
Additional information	

A.2.5 Client identification

The product supplier information and client information should both be filled in if they are different.

Table A.5 Client

Client	
Name	
Address	
Phone No.	
Fax No.	
E-mail address	
Additional information	

A.2.6 Contact person

A person who can answer queries regarding information supplied in the PICS should be named as the contact person.

Table A.6 Contact person

Contact person	
Name	
Address	
Phone No.	
Fax No.	
E-mail address	
Additional information	

A.3 Identification of the protocol

Table A.7 Identification of protocol

Identification of protocol	
Title of specification	Radio Equipment and Systems Digital Enhanced Cordless Telecommunications Common Interface Part 4: Data Link Control Layer
Reference no.	ETS 300 175-4
Date of Publication	

A.4 Global statement of conformance

An explicit answer shall be entered, in each of the support or supported column boxes provided, using the notation described in subclause A.1.2.

Table A.8 Global statement of conformance

Global statement of conformance	
Are all mandatory capabilities implemented?	

NOTE: Answering "No" to this question indicates non-conformance to the <reference specification type> specification. Non-supported mandatory capabilities are to be identified in the ICS, with an explanation of why the implementation is non-conforming, on pages attached to the ICS proforma.

A.5 Capabilities

A.5.1 Major capabilities

A.5.1.1 Services

Table A.9 Data link services

Item	Data link services	Ref.	Status	Support
1	C-plane services	5	o	
2	U-plane services	11	o	

Table A.10 C-plane services

Prerequisite: A.9/1				
Item	**C-plane services**	**Ref.**	**Status**	**Support**
1	Class U service	5.1	o.10	
2	Class A service	5.1	o.10	
3	Class B service	5.1	o.10	
4	Broadcast service	5.2, 9.4	o.10	

o.10: It is mandatory to support at least one of this options

Table A.11 U-plane services

Prerequisite: A.9/2				
Item	**U-plane services**	**Ref.**	**Status**	**Support**
1	LU1 - Transparent Unprotected service (TRUP)	11.2	o.11	
2	LU2 - Frame Relay service (FREL)	11.3	o.11	
3	LU3 - Frame Switching service (FSWI)	11.4	c1101	
4	LU4 - Forward error correction service (FEC)	11.5	c1101	
5	LU5 - Basic Rate Adaptation (BRAT) protected service	11.6	o.11	
6	LU5 - Basic Rate Adaptation (BRAT) unprotected service	11.6	o.11	
7	LU6 - Secondary Rate Adaptation service (SRAT)	11.7	c1102	
8	LU7 - 64kbit/s data bearer service	11.9	c1103	
9	LU16 - Escape for non-standard family (ESC)	11.8	o.11	

o.11: It is mandatory to support at least one of this options
c1101: The definitive specification of this service is for further study
c1102: IF A.11/6 THEN o ELSE x
c1103: IF 64kbit/s data service required THEN m ELSE n/a

Table A.12 Management services

Item	Management services	Ref.	Status	Support
1	MAC connection management	10.2	c1201	
2	DLC C-plane management	10.3	c1202	
3	DLC U-plane management	10.4	c1203	
4	Connection handover management	10.5	o	
5	Connection ciphering management	10.6	o	

c1201: IF A.9/1 OR A.9/2 THEN m ELSE n/a
c1202: IF A.9/1 THEN m ELSE n/a
c1203: IF A.9/2 THEN m ELSE n/a

A.5.1.2 Procedures

A.5.1.2.1 Generic signalling procedures

Table A.13 Generic signalling procedures

Prerequisite: A.10/2 OR A.10/3				
Item	**Generic signalling procedures**	**Ref.**	**Status**	**Supp.**
1	Segmentation of NWK information	5.1.1, 7.7	o	
2	C_S channel fragmentation and recombination	6.1.2, 6.1.3, 6.1.4, 6.1.4.2	o.13	
3	C_F channel fragmentation and recombination	6.1.2, 6.1.3, 6.1.4, 6.1.4.1	o.13	

o.13: It is mandatory to support at least one of this options

A.5.1.2.2 Class U procedures

Table A.14 Class U procedures

Prerequisite: A.10/1				
Item	**Class U procedures**	**Ref.**	**Status**	**Support**
1	Class U link establishment	9.3.2	m	
2	Class U information transfer	9.3.3	m	
3	Class U link release	9.3.4	m	

A.5.1.2.3 Class A procedures

Table A.15 Class A procedures

Prerequisite: A.10/2				
Item	**Class A procedures**	**Ref.**	**Status**	**Support**
1	Class A link establishment	9.2.3.1	m	
2	Class A acknowledged information transfer	9.2.3.2, 9.2.3.3, 9.2.3.4, 9.2.3.5, 9.2.3.6	m	
3	Class A link release	9.2.3.7	m	
4	Class A link re-establishment	9.2.3.8	o	
5	Class A connection handover	9.2.7.3, 9.2.7.3.1	o	

A.5.1.2.4 Class B procedures

Table A.16 Class B procedures

Prerequisite: A.10/3				
Item	**Class B procedures**	**Ref.**	**Status**	**Support**
1	Class B multiple frame establishment	9.2.4	m	
2	Class B information transfer	9.2.5	m	
3	Class B link release	9.2.6	m	
4	Class B link suspension and resumption	9.2.7	o	
5	Class B connection handover	9.2.7.3, 9.2.7.3.2	o	

A.5.1.2.5 Broadcast procedures

Table A.17 Broadcast procedures

Prerequisite: A.10/4				
Item	**Broadcast procedures**	**Ref.**	**Status**	**Support**
1	Normal operation	9.4.1	m	
2	Expedited operation	9.4.2	o	

A.5.1.2.6 LU1 procedures

Table A.18 LU1 procedures

Prerequisite: A.11/1				
Item	**LU1 procedures**	**Ref.**	**Status**	**Support**
1	U-plane Class 0/min delay	11.2	o.1801	
2	U-plane class 0	11.2	o.1801	
3	FU1 frame operation	12.2	m	

o.1801: It is mandatory to support at least one of these options

Table A.19 FU1 options

Prerequisite: A.18/3				
Item	**FU1 options**	**Ref.**	**Status**	**Support**
1	FU1 buffering procedures (FU1 frame operation)	12.2.2	m	
2	FU1 minimum delay (speech) operation	12.2.3	m	
3	FU1 connection handover	12.2.4	c1901	
4	FU1 transmission order	12.2.5	m	

c1901: IF A.15/5 OR A.16/5 THEN m ELSE n/a

A.5.1.2.7 LU2 procedures

Table A.20 LU2 procedures

Prerequisite: A.11/2				
Item	**LU2 procedures**	**Ref.**	**Status**	**Support**
1	Checksum operation	11.3.2	m	
2	Segmentation	11.3.3	m	
3	Data transmission	11.3.4	m	
4	FU4 buffering procedures	12.5.2	o.20	
5	FU5 buffering procedures	12.6.2	o.20	
6	FU6 buffering procedures	12.7.2	o.20	

o.20: It is mandatory to support at least one of this options

Table A.21 FU4 options

Prerequisite: A.20/4				
Item	**FU4 options**	**Ref.**	**Status**	**Support**
1	FU4 connection handover	12.5.3	o	
2	FU4 transmission order	12.5.4	m	

Table A.22 FU5 options

Prerequisite: A.20/5				
Item	**FU5 options**	**Ref.**	**Status**	**Support**
1	FU5 connection handover	12.6.3	o	
2	FU5 transmission order	12.6.4	m	

Table A.23 FU6 options

Prerequisite: A.20/6				
Item	**FU6 options**	**Ref.**	**Status**	**Support**
1	FU6 connection handover	12.7.3	o	
2	FU6 transmission order	12.7.4	m	

A.5.1.2.8 LU5 protected data procedures

Table A.24 LU5 protected data procedures

Prerequisite: A.11/5				
Item	**LU5 protected data procedures**	**Ref.**	**Status**	**Support**
1	Data buffering and initial rate adaptation	11.6.2.2	m	
2	Multi-channel set multiplexing	11.6.2.3	m	
3	Segmentation of Multiplexed Data Units	11.6.2.4	m	
4	Frame sequencing	11.6.2.5	m	
5	FU5 buffering procedures	12.6.2	m	
6	FU5 connection handover	12.6.3	o	
7	FU5 transmission order	12.6.4	m	

A.5.1.2.9 LU5 unprotected data procedures

Table A.25 LU5 unprotected data procedures

Prerequisite: A.11/6				
Item	**LU5 unprotected data procedures**	**Ref.**	**Status**	**Support**
1	Data buffering and initial rate adaptation	11.6.3.2	m	
2	Multi-channel set multiplexing	11.6.3.3	m	
3	Segmentation of Multiplexed Data Units	11.6.3.4	m	
4	FU1 buffering procedure	12.2.2	m	
5	FU1 minimum delay (speech) operation	12.2.3	o	
6	FU1 connection handover	12.2.4	o	
7	FU1 transmission order	12.2.5	m	

A.5.1.2.10 LU7 procedures

Table A.26 LU7 procedures

Prerequisite: A.11/8				
Item	**LU7 procedures**	**Ref.**	**Status**	**Support**
1	Establishment and synchronisation procedures	E.4.3.1	m	
2	Active phase procedures	E.4.3.2	m	
3	Release procedures	E.4.3.3	m	
4	Exceptional procedures	E.4.4	m	

Table A.27 LU7 establishment and synchronisation procedures

Prerequisite: A.26/1				
Item	**LU7 establishment and synchronisation procedures**	**Ref.**	**Status**	**Support**
1	Incoming call establishment	E.4.3.1.1	m	
2	Outgoing call establishment	E.4.3.1.2	m	

Table A.28 LU7 active phase procedures

Prerequisite: A.26/2				
Item	**LU7 active phase procedures**	**Ref.**	**Status**	**Support**
1	Transmitting frames	E.4.3.2.1	m	
2	Re-transmitting frames	E.4.3.2.2	m	
3	Receiving frames	E.4.3.2.3	m	
4	Sending acknowledgements	E.4.3.2.4	m	
5	Receiving acknowledgements	E.4.3.2.5	m	

Table A.29 LU7 exceptional procedures

Prerequisite: A.26/4				
Item	**LU7 exceptional procedures**	**Ref.**	**Status**	**Support**
1	Invalid frame condition	E.4.4.1	m	
2	Establishment	E.4.4.2	m	
3	Transmitting frames	E.4.4.3	m	
4	Receiving frames	E.4.4.4	m	
5	Sending acknowledgements	E.4.4.5	m	
6	N(R) sequence error	E.4.4.7	m	
7	N(O) sequence error	E.4.4.8	m	
8	N(S) sequence error	E.4.4.9	m	
9	Format error	E.4.4.10	m	
10	Abnormal release	E.4.4.11	m	

A.5.1.2.11 Management procedures

Table A.30 Management procedures

Prerequisite: A.12				
Item	**Management procedures**	**Ref.**	**Status**	**Support**
1	MAC connection management	10.2	c3001	
2	DLC C-plane management	10.3	c3002	
3	DLC U-plane management	10.4	c3003	
4	Connection handover management	10.5	c3004	
5	Connection ciphering management	10.6	c3005	

c3001: IF A.12/1 THEN m ELSE n/a
c3002: IF A.12/2 THEN m ELSE n/a
c3003: IF A.12/3 THEN m ELSE n/a
c3004: IF A.12/4 AND (A.15/5 OR A.16/5 OR A.19/3 OR A.21/1 OR A.22/1 OR A.23/1 OR A.24/6 OR A.25/6) THEN m ELSE x
c3005: IF A.12/5 THEN m ELSE n/a

Table A.31 MAC connection management procedures

Prerequisite: A.30/1				
Item	**MAC connection management procedures**	**Ref.**	**Status**	**Support**
1	MAC connection set-up	10.2.1	m	
2	MAC connection release	10.2.2	m	
3	MAC connection modification	10.2.3	o	
4	MAC connection identification	10.2.4	m	
5	Selection of logical channels (C_S or C_F)	10.2.5	o	

Table A.32 DLC C-plane management procedures

Prerequisite: A.30/2				
Item	**DLC C-plane management procedures**	**Ref.**	**Status**	**Support**
1	Provision of link signature	10.3.1	m	
2	Routing of connection oriented links	10.3.2	c3201	
3	Routing of connectionless links	10.3.3	o	

c3201: IF A.9/1 THEN m ELSE n/a

Table A.33 DLC U-plane management procedures

Prerequisite: A.30/3				
Item	**DLC U-plane management procedures**	**Ref.**	**Status**	**Support**
1	U-plane establishment	10.4.1	m	
2	U-plane release	10.4.2	m	
3	U-plane suspend and resume	10.4.3	o	

Table A.34 Connection ciphering management procedures

Prerequisite: A.30/5				
Item	**Connection ciphering management procedures**	**Ref.**	**Status**	**Support**
1	Providing a key to the MAC layer	10.6.1	m	
2	Starting the ciphering	10.6.2	m	
3	Stopping the ciphering	10.6.2	o	
4	Connection handover of ciphered connection	10.6.3	c3401	

c3401: IF A.30/4 THEN m ELSE n/a

A.5.2 Protocol parameters

A.5.2.1 C-plane timers

Table A.35 C-plane timers

Prerequisite: A.9/1						
Item	**C-plane timers**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	DL.00	A.1	c3504		2 s	
2	DL.01	A.1	c3503		2 s	
3	DL.02	A.1	c3504		2 s	
4	DL.03	A.1	c3503		2 s	
5	DL.04 (CF routed frames)	A.1	c3501		1 s	
6	DL.04 (CS routed frames)	A.1	c3502		2 s	
7	DL.05	A.1	c3505		10 s	
8	DL.06	A.1	c3505		4 s	
9	DL.07	A.1	c3506		2 s	

c3501: IF A.13/3 THEN m ELSE n/a
c3502: IF A.13/2 THEN m ELSE n/a
c3503: IF A.16/4 THEN m ELSE n/a
c3504: IF A.10/3 THEN m ELSE n/a
c3505: IF A.30/4 THEN m ELSE n/a
c3506: IF A.10/2 THEN m ELSE n/a

A.5.2.2 U-plane timers

Table A.36 U-plane timers

Prerequisite: A.9/2						
Item	**U-plane timers**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	DLU.01	A.1	c3601		2 s	

c3601: IF A.43/4 OR A.43/5 OR A.43/6 THEN m ELSE n/a

A.5.2.3 Class A parameters

Table A.37 Class A parameter values

Prerequisite: A.10/2				
Item	**Class A parameter**	**Ref.**	**Status**	**Support**
1	Fixed window size of 1	9.2.3.2, 7.5.2.2	m	
2	Modulus 2	9.2.3.2, 7.5.2.1	m	

A.5.2.4 Class B parameters

Table A.38 Class B parameter values

Prerequisite: A.10/3				
Item	**Class B parameter**	**Ref.**	**Status**	**Support**
1	Fixed window size of 3	7.5.2.2	m	
2	Modulus 8	9.2.4.2, 7.5.2.1	m	

A.5.2.5 LU1 parameters

Table A.39 LU1 Frame types

Prerequisite: A.11/1				
Item	**Frame types**	**Ref.**	**Status**	**Support**
1	FU1 frame structure	11.2, 12.2	m	

Table A.40 LU1 Connection types

Prerequisite: A.11/1				
Item	**Connection types**	**Ref.**	**Status**	**Support**
1	IN / min delay - Half slot (10 octets)	11.2, 12.2.1	o.40	
2	IN / normal delay - Half slot (10 octets)	11.2, 12.2.1	o.40	
3	IN / min delay - Full slot (40 octets)	11.2, 12.2.1	o.40	
4	IN / normal delay - Full slot (40 octets)	11.2, 12.2.1	o.40	
5	IN / min delay - Double slot (100 octets)	11.2, 12.2.1	o.40	
6	IN / normal delay - Double slot (100 octets)	11.2, 12.2.1	o.40	

o.40: It is mandatory to support at least one of this options

A.5.2.6 LU2 parameters

Table A.41 LU2 Frame types

Prerequisite: A.11/2				
Item	**Frame type**	**Ref.**	**Status**	**Support**
1	FU4 frame structure	11.3.3, 12.5.1	c4101	
2	FU5 frame structure	11.3.3, 12.6.1	c4102	
3	FU6 frame structure	11.3.3, 12.7.1	c4103	

c4101: IF A.43/2 OR A.43/5 OR A.43/8 THEN m ELSE n/a
c4102: IF A.43/1 OR A.43/4 OR A.43/7 THEN m ELSE n/a
c4103: IF A.43/3 OR A.43/6 OR A.43/9 THEN m ELSE n/a

Table A.42 LU2 Connection types

Prerequisite: A.11/2				
Item	**Connection types**	**Ref.**	**Status**	**Support**
1	IP / error-detect- Half slot (08 octets)	11.3, 12.5.1, 12.6.1, 12.7.1	o.42	
2	IP / error-correct- Half slot (08 octets)	11.3, 12.5.1, 12.6.1, 12.7.1	o.42	
3	IP / error-detect- Full slot (32 octets)	11.3, 12.5.1, 12.6.1, 12.7.1	o.42	
4	IP / error-correct- Full slot (32 octets)	11.3, 12.5.1, 12.6.1, 12.7.1	o.42	
5	IP / error-detect- Double slot (80 octets)	11.3, 12.5.1, 12.6.1, 12.7.1	o.42	
6	IP / error-correct- Double slot (80 octets)	11.3, 12.5.1, 12.6.1, 12.7.1	o.42	

o.42: It is mandatory to support at least one of this options

Table A.43 LU2 Transmission classes

Prerequisite: A.11/2				
Item	**Transmission classes**	**Ref.**	**Status**	**Support**
1	class 0 / bi- or unidirectional	11.3.3	o.43	
2	class 0 / bidirectional	11.3.3	o.43	
3	class 0 / unidirectional	11.3.3	o.43	
4	class 1 / bi- or unidirectional	11.3.3	o.43	
5	class 1 / bidirectional	11.3.3	o.43	
6	class 1 / unidirectional	11.3.3	o.43	
7	class 2 / bi- or unidirectional	11.3.3	o.43	
8	class 2 / bidirectional	11.3.3	o.43	
9	class 2 / unidirectional	11.3.3	o.43	

o.43: It is mandatory to support at least one of this options

A.5.2.7 LU5 parameters

Table A.44 LU5 Frame types

Prerequisite: A.11/5 OR A.11/6				
Item	**Frame type**	**Ref.**	**Status**	**Support**
1	FU1 frame structure	11.6.3.1, 12.2	c4401	
2	FU5 frame structure	11.6.2.1, 12.6	c4402	

c4401: IF A.11/6 THEN m ELSE n/a
c4402: IF A.11/5 THEN m ELSE n/a

Table A.45 LU5 Connection types

Prerequisite: A.11/5 OR A.11/6				
Item	**Connection types**	**Ref.**	**Status**	**Support**
1	IP / error-detect- Half slot (08 octets)	11.3, 12.6.1	o.45	
2	IP / error-correct- Half slot (08 octets)	11.3, 12.6.1	o.45	
3	IP / error-detect- Full slot (32 octets)	11.3, 12.6.1	o.45	
4	IP / error-correct- Full slot (32 octets)	11.3, 12.6.1	o.45	
5	IP / error-detect- Double slot (80 octets)	11.3, 12.6.1	o.45	
6	IP / error-correct- Double slot (80 octets)	11.3, 12.6.1	o.45	

o.45: It is mandatory to support at least one of this options

Table A.46 LU5 Transmission classes

Prerequisite: A.11/5 OR A.11/6				
Item	**Transmission classes**	**Ref.**	**Status**	**Support**
1	class 0	11.6.2	c4601	
2	class 3	11.6.2	c4602	

c4601: IF A.44/1 THEN m ELSE n/a
c4602: IF A.44/2 THEN m ELSE n/a

A.5.2.8 LU7 parameters

Table A.47 LU7 Frame types

Prerequisite: A.11/8				
Item	**Frame types**	**Ref.**	**Status**	**Support**
1	FU7 frame structure	E.4.2	m	

Table A.48 LU7 Connection types

Prerequisite: A.11/8				
Item	**Connection types**	**Ref.**	**Status**	**Support**
1	IN / normal delay - Double slot (100 octets)	E.3	m	

Table A.49 LU7 Transmission classes

Prerequisite: A.11/8				
Item	**Transmission classes**	**Ref.**	**Status**	**Support**
1	class 0		m	

A.5.3 Protocol PDUs

A.5.3.1 C-plane PDUs

A.5.3.1.1 C-plane frame structure

Table A.50 Frame structures (Sending P to F)

Item	**Frame Structures**	**Ref.**	**Status**	**Support**
1	Frame structure of format type FA.	6.1	c5001	
2	Broadcast service frame structure	6.2	n/a	

c5001: IF A.9/1 THEN m ELSE n/a

Table A.51 Frame structures (Receipt F to P)

Item	**Frame Structures**	**Ref.**	**Status**	**Support**
1	Frame structure of format type FA.	6.1	c5101	
2	Broadcast service frame structure	6.2	c5102	

c5101: IF A.9/1 THEN m ELSE n/a
c5102: IF A.10/4 THEN m ELSE n/a

Table A.52 Frame format type FA (Sending P to F)

Prerequisite: A.50/1				
Item	**Frame elements**	**Ref.**	**Status**	**Support**
1	Address field	6.1	m	
2	Control field	6.1	m	
3	Length indicator field	6.1	m	
4	Information field	6.1	c5201	
5	Fill field	6.1	m	
6	Checksum field	6.1	m	

c5201: IF A.55/1 OR A.57/1 OR A.59/1 THEN m ELSE x

Table A.53 Frame format type FA (Receipt F to P)

Prerequisite: A.51/1				
Item	**Frame elements**	**Ref.**	**Status**	**Support**
1	Address field	6.1	m	
2	Control field	6.1	m	
3	Length indicator field	6.1	m	
4	Information field	6.1	c5301	
5	Fill field	6.1	m	
6	Checksum field	6.1	m	

c5301: IF A.56/1 OR A.58/1 OR A.60/1 THEN m ELSE x

Table A.54 Broadcast service frame structure (Receipt F to P)

Prerequisite: A.51/2				
Item	**Frame elements**	**Ref.**	**Status**	**Support**
1	Short frame format (3 octets)	6.2.1	o.54	
2	Long frame format (5 octets)	6.2.1	o.54	

o.54: It is mandatory to support at least one of this options

A.5.3.1.2 C-plane messages

A.5.3.1.2.1 Message support

Table A.55 Class A messages support (Sending P to F)

Prerequisite: A.10/2				
Item	**Class A messages**	**Ref.**	**Status**	**Support**
1	I-command	7.11, 9.1	m	
2	RR-command/response	7.11, 9.1	m	

Table A.56 Class A messages support (Receipt F to P)

Prerequisite: A.10/2				
Item	**Class A messages**	**Ref.**	**Status**	**Support**
1	I-command	7.11, 9.1	m	
2	RR-command/response	7.11, 9.1	m	

Table A.57 Class B messages support (Sending P to F)

Prerequisite: A.10/3				
Item	**Class B messages**	**Ref.**	**Status**	**Support**
1	I-command	7.11, 9.1	m	
2	RR-command/response	7.11, 9.1	m	
3	RNR-command/response	7.11, 9.1	m	
4	REJ-command/response	7.11, 9.1	m	
5	SABM-command	7.11, 9.1	m	
6	DM-response	7.11, 9.1	m	
7	DISC-command	7.11, 9.1	m	
8	UA-response	7.11, 9.1	m	

Table A.58 Class B messages support (Receipt F to P)

Prerequisite: A.10/3				
Item	**Class B messages**	**Ref.**	**Status**	**Support**
1	I-command	7.11, 9.1	m	
2	RR-command/response	7.11, 9.1	m	
3	RNR-command/response	7.11, 9.1	m	
4	REJ-command/response	7.11, 9.1	m	
5	SABM-command	7.11, 9.1	m	
6	DM-response	7.11, 9.1	m	
7	DISC-command	7.11, 9.1	m	
8	UA-response	7.11, 9.1	m	

Table A.59 Class U messages support (Sending P to F)

Prerequisite: A.10/1				
Item	**Class U messages**	**Ref.**	**Status**	**Support**
1	UI-command	7.11, 9.1	m	

Table A.60 Class U messages support (Receipt F to P)

Prerequisite: A.10/1				
Item	**Class U messages**	**Ref.**	**Status**	**Support**
1	UI-command	7.11, 9.1	m	

A.5.3.1.2.2 Class A I-command

Table A.61 Class A I-command (Numbered Information) (Sending P to F)

Prerequisite: A.55/1				
Item	**I-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Information field	6.1	m	
5	Fill field	7.8	m	
6	Checksum field	7.9	m	

Table A.62 Class A I-command (Numbered Information) (Receipt F to P)

Prerequisite: A.55/1				
Item	**I-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Information field	6.1	m	
5	Fill field	7.8	m	
6	Checksum field	7.9	m	

Table A.63 Class A I-command Control field (Sending P to F)

Prerequisite: A.61/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'0'B	
2	N(S)	7.4, 7.5.2.4	m		'000'B .. '001'B	
3	P	7.4, 7.5.1, 9.2.1.1	m		'0'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '001'B	

Table A.64 Class A I-command Control field (Receipt F to P)

Prerequisite: A.62/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'0'B	
2	N(S)	7.4, 7.5.2.4	m		'000'B .. '001'B	
3	P	7.4, 7.5.1, 9.2.1.1	m		'0'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '001'B	

Table A.65 Class A I-command Address field (Sending P to F)

Prerequisite: A.61/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.1	m		'001'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.66 Class A I-command Address field (Receipt F to P)

Prerequisite: A.62/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.1	m		'001'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.3 Class A RR command/response

Table A.67 Class A RR-command/response (Receive ready) (Sending P to F)

Prerequisite: A.55/2				
Item	**RR-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.68 Class A RR-command/response (Receive ready) (Receipt F to P)

Prerequisite: A.56/2				
Item	**RR-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.69 Class A RR Control field (Sending P to F)

Prerequisite: A.67/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'00'B	
3	P/F	7.4, 7.5.1, 9.2.1.1	m		'0'B	
4	N(R)	7.4, 7.5.2.4	m		'000'B .. '001'B	

Table A.70 Class A RR Control field (Receipt F to P)

Prerequisite: A.68/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'00'B	
3	P/F	7.4, 7.5.1, 9.2.1.1	m		'0'B	
4	N(R)	7.4, 7.5.2.4	m		'000'B .. '001'B	

Table A.71 Class A RR Address field (Sending P to F)

Prerequisite: A.67/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.1	m		'001'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.72 Class A RR Address field (Receipt F to P)

Prerequisite: A.68/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.1	m		'001'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.4 Class B I-command

Table A.73 Class B I-command (Numbered Information) (Sending P to F)

Prerequisite: A.57/1				
Item	**I-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Information field	6.1	m	
5	Fill field	7.8	m	
6	Checksum field	7.9	m	

Table A.74 Class B I-command (Numbered Information) (Receipt F to P)

Prerequisite: A.58/1				
Item	**I-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Information field	6.1	m	
5	Fill field	7.8	m	
6	Checksum field	7.9	m	

Table A.75 Class B I-command Control field (Sending P to F)

Prerequisite: A.73/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'0'B	
2	N(S)	7.4, 7.5.2.4	m		'000'B .. '111'B	
3	P	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.76 Class B I-command Control field (Receipt F to P)

Prerequisite: A.74/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'0'B	
2	N(S)	7.4, 7.5.2.4	m		'000'B .. '111'B	
3	P	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.77 Class B I-command Address field (Sending P to F)

Prerequisite: A.73/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '110'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.78 Class B I-command Address field (Receipt F to P)

Prerequisite: A.74/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.5 Class B RR command/response

Table A.79 Class B RR-command/response (Receive ready) (Sending P to F)

Prerequisite: A.57/2				
Item	**RR-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.80 Class B RR-command/response (Receive ready) (Receipt F to P)

Prerequisite: A.58/2				
Item	**RR-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.81 Class B RR Control field (Sending P to F)

Prerequisite: A.79/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'00'B	
3	P/F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.82 Class B RR Control field (Receipt F to P)

Prerequisite: A.80/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'00'B	
3	P/F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.83 Class B RR Address field (Sending P to F)

Prerequisite: A.79/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B, '1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.84 Class B RR Address field (Receipt F to P)

Prerequisite: A.80/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B, '1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.6 Class B RNR command/response

Table A.85 Class B RNR command/response (Receive Not Ready) (Sending P to F)

Prerequisite: A.57/3				
Item	**RNR-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.86 Class B RNR command/response (Receive Not Ready) (Receipt F to P)

Prerequisite: A.58/3				
Item	**RNR-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.87 Class B RNR Control field (Sending P to F)

Prerequisite: A.85/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'01'B	
3	P/F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.88 Class B RNR Control field (Receipt F to P)

Prerequisite: A.86/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'01'B	
3	P/F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.89 Class B RNR Address field (Sending P to F)

Prerequisite: A.85/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B, '1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.90 Class B RNR Address field (Receipt F to P)

Prerequisite: A.86/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B, '1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.7 Class B REJ command/response

Table A.91 Class B REJ command/response (Reject) (Sending P to F)

Prerequisite: A.57/4				
Item	**REJ-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Information field	6.1	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.92 Class B REJ command/response (Reject) (Receipt F to P)

Prerequisite: A.58/4				
Item	**REJ-command/response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Information field	6.1	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.93 Class B REJ Control field (Sending P to F)

Prerequisite: A.91/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'10'B	
3	P/F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.94 Class B REJ Control field (Receipt F to P)

Prerequisite: A.92/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'01'B	
2	S bits	7.4, 7.11	m		'10'B	
3	P/F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	N(R)	7.4, 7.5.2.6	m		'000'B .. '111'B	

Table A.95 Class B REJ Address field (Sending P to F)

Prerequisite: A.91/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B, '1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.96 Class B REJ Address field (Receipt F to P)

Prerequisite: A.92/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B, '1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.8 Class B SABM command

Table A.97 Class B SABM command (Set Asynchronous Balanced Mode) (Sending P to F)

Prerequisite: A.57/5				
Item	**SABM-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.98 Class B SABM command (Set Asynchronous Balanced Mode) (Receipt F to P)

Prerequisite: A.58/5				
Item	**SABM-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.99 Class B SABM Control field (Sending P to F)

Prerequisite: A.97/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'11'B	
3	P	7.4, 7.5.1, 9.2.1.2	m		'1'B	
4	U bits part 2	7.4, 7.11	m		'001'B	

Table A.100 Class B SABM Control field (Receipt F to P)

Prerequisite: A.98/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'11'B	
3	P	7.4, 7.5.1, 9.2.1.2	m		'1'B	
4	U bits part 2	7.4, 7.11	m		'001'B	

Table A.101 Class B SABM Address field (Sending P to F)

Prerequisite: A.97/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '110'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.102 Class B SABM Address field (Receipt F to P)

Prerequisite: A.98/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '110'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.9 Class B DM response

Table A.103 Class B DM-response (Disconnect Mode) (Sending P to F)

Prerequisite: A.57/6				
Item	**DM-response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.104 Class B DM-response (Disconnect Mode) (Receipt F to P)

Prerequisite: A.58/6				
Item	**DM-response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.105 Class B DM Control field (Sending P to F)

Prerequisite: A.103/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'11'B	
3	F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	U bits part 2	7.4, 7.11	m		'000'B	

Table A.106 Class B DM Control field (Receipt F to P)

Prerequisite: A.104/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'11'B	
3	F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	U bits part 2	7.4, 7.11	m		'000'B	

Table A.107 Class B DM Address field (Sending P to F)

Prerequisite: A.103/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.108 Class B DM Address field (Receipt F to P)

Prerequisite: A.104/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.10 Class B DISC command

Table A.109 Class B DISC command (Disconnect) (Sending P to F)

Prerequisite: A.57/7				
Item	**DISC-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.110 Class B DISC command (Disconnect) (Receipt F to P)

Prerequisite: A.58/7				
Item	**DISC-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.111 Class B DISC Control field (Sending P to F)

Prerequisite: A.109/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'00'B	
3	P	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	U bits part 2	7.4, 7.11	m		'010'B	

Table A.112 Class B DISC Control field (Receipt F to P)

Prerequisite: A.110/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'00'B	
3	P	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	U bits part 2	7.4, 7.11	m		'010'B	

Table A.113 Class B DISC Address field (Sending P to F)

Prerequisite: A.109/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.114 Class B DISC Address field (Receipt F to P)

Prerequisite: A.110/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.11 Class B UA response

Table A.115 Class B UA-response (Unnumbered ACK) (Sending P to F)

Prerequisite: A.57/8				
Item	**UA-response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.116 Class B UA-response (Unnumbered ACK) (Receipt F to P)

Prerequisite: A.58/8				
Item	**UA-response - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Fill field	7.8	m	
5	Checksum field	7.9	m	

Table A.117 Class B UA Control field (Sending P to F)

Prerequisite: A.115/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'00'B	
3	F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	U bits part 2	7.4, 7.11	m		'011'B	

Table A.118 Class B UA Control field (Receipt F to P)

Prerequisite: A.116/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'00'B	
3	F	7.4, 7.5.1, 9.2.1.2	m		'0'B, '1'B	
4	U bits part 2	7.4, 7.11	m		'011'B	

Table A.119 Class B UA Address field (Sending P to F)

Prerequisite: A.115/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

Table A.120 Class B UA Address field (Receipt F to P)

Prerequisite: A.116/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B	
4	LLN	7.2, 7.3.5, 9.2.2.2	m		'010'B .. '111'B	
5	NLF	7.2, 7.3.4	m		'0'B, '1'B	

A.5.3.1.2.12 Class U UI command

Table A.121 Class U UI command (Unnumbered Information) (Sending P to F)

Prerequisite: A.59/1				
Item	**UI-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Information field	6.1	m	
5	Fill field	7.8	m	
6	Checksum field	7.9	m	

Table A.122 Class U UI command (Unnumbered Information) (Receipt F to P)

Prerequisite: A.60/1				
Item	**UI-command - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	7.2	m	
2	Control field	7.4	m	
3	Length indicator field	7.6	m	
4	Information field	6.1	m	
5	Fill field	7.8	m	
6	Checksum field	7.9	m	

Table A.123 Class U UI Control field (Sending P to F)

Prerequisite: A.121/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'00'B	
3	P	7.4, 7.5.1, 9.3.3.1	m		'0'B	
4	U bits part 2	7.4, 7.11	m		'000'B	

Table A.124 Class U UI Control field (Receipt F to P)

Prerequisite: A.122/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	7.4	m		'11'B	
2	U bits part 1	7.4, 7.11	m		'00'B	
3	P	7.4, 7.5.1, 9.3.3.1	m		'0'B	
4	U bits part 2	7.4, 7.11	m		'000'B	

Table A.125 Class U UI Address field (Sending P to F)

Prerequisite: A.121/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'0'B	
3	SAPI	7.2, 7.3.3	m		'00'B, '11'B	
4	LLN	7.2, 7.3.5	m		'000'B	
5	NLF	7.2, 7.3.4, 9.3.3.1	m		'0'B	

Table A.126 Class U UI Address field (Receipt F to P)

Prerequisite: A.122/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	RES	7.2, 7.3.1	m		'1'B	
2	C/R	7.2, 7.3.2	m		'1'B	
3	SAPI	7.2, 7.3.3	m		'00'B, '11'B	
4	LLN	7.2, 7.3.5	m		'000'B	
5	NLF	7.2, 7.3.4, 9.3.3.1	m		'0'B	

A.5.3.2 U-plane PDUs

Table A.127 U-plane frames (Sending P to F)

Prerequisite: A.9/2				
Item	**U-plane frames**	**Ref.**	**Status**	**Support**
1	FU1 frame structure	12.2.1	c12701	
2	FU2 frame structure	12.3.1	c12702	
3	FU3 frame structure	12.4.1	c12703	
4	FU4 frame structure	12.5.1	c12704	
5	FU5 frame structure	12.6.1	c12705	
6	FU6 frame structure	12.7.1	c12706	
7	FU7 frame structure	E.4.2	c12707	

c12701: IF A.39/1 OR A.44/1 THEN m else n/a
c12702: The use of this frame is for future application
c12703: The use of this frame is for future application
c12704: IF A.41/1 THEN m else n/a
c12705: IF A.41/2 OR A.44/2 THEN m else n/a
c12706: IF A.41/3 THEN m else n/a
c12707: IF A.47/1 THEN m else n/a

Table A.128 U-plane frames (Receipt F to P)

Prerequisite: A.9/2				
Item	**U-plane frames**	**Ref.**	**Status**	**Support**
1	FU1 frame structure	12.2.1	c12801	
2	FU2 frame structure	12.3.1	c12802	
3	FU3 frame structure	12.4.1	c12803	
4	FU4 frame structure	12.5.1	c12804	
5	FU5 frame structure	12.6.1	c12805	
6	FU6 frame structure	12.7.1	c12806	
7	FU7 frame structure	E.4.2	c12807	

c12801: IF A.39/1 OR A.44/1 THEN m else n/a
c12802: The use of this frame is for future application
c12803: The use of this frame is for future application
c12804: IF A.41/1 THEN m else n/a
c12805: IF A.41/2 OR A.44/2 THEN m else n/a
c12806: IF A.41/3 THEN m else n/a
c12807: IF A.47/1 THEN m else n/a

A.5.3.2.1 FU1 frame structure

Table A.129 FU1 frame structure (Sending P to F)

Prerequisite: A.127/1				
Item	**FU1 frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Higher layer information	12.2.1	m	

Table A.130 FU1 frame structure (Receipt F to P)

Prerequisite: A.128/1				
Item	**FU1 frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Higher layer information	12.2.1	m	

A.5.3.2.2 FU4 frame structure

Table A.131 FU4 frame structure (Sending P to F)

Prerequisite: A.127/4				
Item	**FU4a frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Length indicator field	12.5.1, 13.3.2	m	
2	Send sequence number	12.5.1, 13.4.1	m	
3	Receive sequence number	12.5.1, 13.4.3	m	
4	Information field	12.5.1	m	
5	Fill field	13.5	m	

Table A.132 FU4 frame structure (Receipt F to P)

Prerequisite: A.128/4				
Item	**FU4a frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Length indicator field	12.5.1, 13.3.2	m	
2	Send sequence number	12.5.1, 13.4.1	m	
3	Receive sequence number	12.5.1, 13.4.3	m	
4	Information field	12.5.1	m	
5	Fill field	13.5	m	

Table A.133 FU4 Length indicator field (Sending P to F)

Prerequisite: A.131/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	M (more data bit)	13.3.2	m		'0'B, '1'B	
2	Length of information field	13.3.2	m		7 bits value	

Table A.134 FU4 Length indicator field (Receipt F to P)

Prerequisite: A.132/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	M (more data bit)	13.3.2	m		'0'B, '1'B	
2	Length of information field	13.3.2	m		7 bits value	

Table A.135 FU4 Send sequence number (Sending P to F)

Prerequisite: A.131/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ESi	13.4.1, 13.4.2, 14.2, 14.3	m		7 bits value	
2	I/R bit	13.4.1, 13.4.2	m		'0'B, '1'B	

Table A.136 FU4 Send sequence number (Receipt F to P)

Prerequisite: A.132/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ESi	13.4.1, 13.4.2, 14.2, 14.3	m		7 bits value	
2	I/R bit	13.4.1, 13.4.2	m		'0'B, '1'B	

Table A.137 FU4 Receive sequence number (Sending P to F)

Prerequisite: A.131/3						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ERi	13.4.3, 13.4.4, 14.2, 14.3	m		7 bits value	
2	A/N bit	13.4.3, 13.4.4	m		'0'B, '1'B	

Table A.138 FU4 Receive sequence number (Receipt F to P)

Prerequisite: A.132/3						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ERi	13.4.3, 13.4.4, 14.2, 14.3	m		7 bits value	
2	A/N bit	13.4.3, 13.4.4	m		'0'B, '1'B	

A.5.3.2.3 FU5 frame structure

Table A.139 FU5 frame structure (Sending P to F)

Prerequisite: A.127/5				
Item	**FU5 frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	12.6.1, 13.2.1	m	
2	Length indicator field	12.6.1, 13.3.2	m	
3	Send sequence number	12.6.1, 13.4.1	m	
4	Receive sequence number	12.6.1, 13.4.3	m	
5	Information field	12.6.1	m	
6	Fill field	13.5	m	

Table A.140 FU5 frame structure (Receipt F to P)

Prerequisite: A.128/5				
Item	**FU5 frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Address field	12.6.1, 13.2.1	m	
2	Length indicator field	12.6.1, 13.3.2	m	
3	Send sequence number	12.6.1, 13.4.1	m	
4	Receive sequence number	12.6.1, 13.4.3	m	
5	Information field	12.6.1	m	
6	Fill field	13.5	m	

Table A.141 FU5 Address field (Sending P to F)

Prerequisite: A.139/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	13.2	m		'1'B	
2	UCN (U-plane Channel Number)	13.2	m		'000'B .. '110'B	
3	ULN (U-plane Link Number)	13.2	m		'000'B .. '110'B	
4	G (flaG)	13.2	m		'0'B, '1''B	

Table A.142 FU5 Address field (Receipt F to P)

Prerequisite: A.140/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	Spare field	13.2	m		'1'B	
2	UCN (U-plane Channel Number)	13.2	m		'000'B .. '110'B	
3	ULN (U-plane Link Number)	13.2	m		'000'B .. '110'B	
4	G (flaG)	13.2	m		'0'B, '1"B	

Table A.143 FU5 Length indicator field (Sending P to F)

Prerequisite: A.139/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	M (more data bit)	13.3.2	m		'0'B, '1'B	
2	Length of information field	13.3.2	m		7 bits value	

Table A.144 FU5 Length indicator field (Receipt F to P)

Prerequisite: A.140/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	M (more data bit)	13.3.2	m		'0'B, '1'B	
2	Length of information field	13.3.2	m		7 bits value	

Table A.145 FU5 Send sequence number (Sending P to F)

Prerequisite: A.139/3						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ESi	13.4.1, 13.4.2, 14.2, 14.3	m		7 bits value	
2	I/R bit	13.4.1, 13.4.2	m		'0'B, '1'B	

Table A.146 FU5 Send sequence number (Receipt F to P)

Prerequisite: A.140/3						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ESi	13.4.1, 13.4.2, 14.2, 14.3	m		7 bits value	
2	I/R bit	13.4.1, 13.4.2	m		'0'B, '1'B	

Table A.147 FU5 Receive sequence number (Sending P to F)

Prerequisite: A.139/4						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ERi	13.4.3, 13.4.4, 14.2, 14.3	m		7 bits value	
2	A/N bit	13.4.3, 13.4.4	m		'0'B, '1'B	

Table A.148 FU5 Receive sequence number (Receipt F to P)

Prerequisite: A.140/4						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ERi	13.4.3, 13.4.4, 14.2, 14.3	m		7 bits value	
2	A/N bit	13.4.3, 13.4.4	m		'0'B, '1'B	

A.5.3.2.4 FU6a frame structure

Table A.149 FU6a frame structure (Sending P to F)

Prerequisite: A.127/6				
Item	**FU6a frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Length indicator field	12.7.1, 13.3.2	m	
2	Send sequence number	12.7.1, 13.4.1	m	
3	Information field	12.7.1	m	
4	Fill field	13.5	m	

Table A.150 FU6a frame structure (Receipt F to P)

Prerequisite: A.128/6				
Item	**FU6a frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Length indicator field	12.7.1, 13.3.2	m	
2	Send sequence number	12.7.1, 13.4.1	m	
3	Information field	12.7.1	m	
4	Fill field	13.5	m	

Table A.151 FU6a Length indicator field (Sending P to F)

Prerequisite: A.149/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	M (more data bit)	13.3.2	m		'0'B, '1'B	
2	Length of information field	13.3.2	m		7 bits value	

Table A.152 FU6a Length indicator field (Receipt F to P)

Prerequisite: A.150/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	M (more data bit)	13.3.2	m		'0'B, '1'B	
2	Length of information field	13.3.2	m		7 bits value	

Table A.153 FU6a Send sequence number (Sending P to F)

Prerequisite: A.149/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ESi	13.4.1, 13.4.2, 14.2, 14.3	m		7 bits value	
2	I/R bit	13.4.1, 13.4.2	m		'0'B, '1'B	

Table A.154 FU6a Send sequence number (Receipt F to P)

Prerequisite: A.150/2						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ESi	13.4.1, 13.4.2, 14.2, 14.3	m		7 bits value	
2	I/R bit	13.4.1, 13.4.2	m		'0'B, '1'B	

A.5.3.2.5 FU6b frame structure

Table A.155 FU6b frame structure (Sending P to F)

Prerequisite: A.127/6				
Item	**FU6b frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	#1 Receive sequence number	12.7.1, 13.4.3	m	
2	#2 Receive sequence number	12.7.1, 13.4.3	m	
3	#3 Receive sequence number	12.7.1, 13.4.3	m	
4	#4 Receive sequence number	12.7.1, 13.4.3	m	
5	#5 Receive sequence number	12.7.1, 13.4.3	m	
6	#6 Receive sequence number	12.7.1, 13.4.3	m	
7	#7 Receive sequence number	12.7.1, 13.4.3	m	

Table A.156 FU6b frame structure (Receipt F to P)

Prerequisite: A.128/6				
Item	**FU6b frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	#1 Receive sequence number	12.7.1, 13.4.3	m	
2	#2 Receive sequence number	12.7.1, 13.4.3	m	
3	#3 Receive sequence number	12.7.1, 13.4.3	m	
4	#4 Receive sequence number	12.7.1, 13.4.3	m	
5	#5 Receive sequence number	12.7.1, 13.4.3	m	
6	#6 Receive sequence number	12.7.1, 13.4.3	m	
7	#7 Receive sequence number	12.7.1, 13.4.3	m	

Table A.157 FU6b Receive sequence number (Sending P to F)

Prerequisite: A.155/1 TO A.155/7						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ERi	13.4.3, 13.4.4, 14.2, 14.3	m		7 bits value	
2	A/N bit	13.4.3, 13.4.4	m		'0'B, '1'B	

Table A.158 FU6b Receive sequence number (Receipt F to P)

Prerequisite: A.156/1 TO A.156/7						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	ERi	13.4.3, 13.4.4, 14.2, 14.3	m		7 bits value	
2	A/N bit	13.4.3, 13.4.4	m		'0'B, '1'B	

A.5.3.2.6 FU7 frame structure

Table A.159 FU7 64 kbit/s frame structure (Sending P to F)

Prerequisite: A.127/7				
Item	**FU7 64 kbit/s frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Control field (12 bytes)	E.4.2.1, E.4.2.1.10	m	
2	Information field (80 bytes)	E.4.2.2	m	
3	ARQ Checksum (2 bytes)	E.4.2.3	m	
4	RS parity symbol field (6 bytes)	E.4.2	m	

Table A.160 FU7 64 kbit/s frame structure (Receipt F to P)

Prerequisite: A.128/7				
Item	**FU7 64 kbit/s frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Control field (12 bytes)	E.4.2.1, E.4.2.1.10	m	
2	Information field (80 bytes)	E.4.2.2	m	
3	ARQ Checksum (2 bytes)	E.4.2.3	m	
4	RS parity symbol field (6 bytes)	E.4.2	m	

Table A.161 FU7 64 kbit/s control field (Sending P to F)

Prerequisite: A.159/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	N(O)	E.4.2.1.4	m		6 bits value	
2	Format-1	E.4.2.1.1	m		'00'B	
3	N(S)	E.4.2.1.7	m		3 bits value	
4	N(R)	E.4.2.1.9	m		3 bits value	
5	Format-2	E.4.2.1.1	m		'00'B, '01'B	
6	Octet 3	E.4.2.1, E.4.2.1.10	m		'00000000'B	
7	Octet 4	E.4.2.1, E.4.2.1.10	m		'00000000'B	
8	Octet 5	E.4.2.1, E.4.2.1.10	m		'00000000'B	
9	Octet 6	E.4.2.1, E.4.2.1.10	m		'00000000'B	
10	Octet 7	E.4.2.1, E.4.2.1.10	m		'00000000'B	
11	Octet 8	E.4.2.1, E.4.2.1.10	m		'00000000'B	
12	Octet 9	E.4.2.1, E.4.2.1.10	m		'00000000'B	
13	Octet 10	E.4.2.1, E.4.2.1.10	m		'00000000'B	
14	Octet 11	E.4.2.1, E.4.2.1.10	m		'00000000'B	
15	Octet 12	E.4.2.1, E.4.2.1.10	m		'00000000'B	

Table A.162 FU7 64 kbit/s control field (Receipt F to P)

Prerequisite: A.160/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	N(O)	E.4.2.1.4	m		6 bits value	
2	Format-1	E.4.2.1.1	m		'00'B	
3	N(S)	E.4.2.1.7	m		3 bits value	
4	N(R)	E.4.2.1.9	m		3 bits value	
5	Format-2	E.4.2.1.1	m		'00'B, '01'B	
6	Octet 3	E.4.2.1, E.4.2.1.10	m		'00000000'B	
7	Octet 4	E.4.2.1, E.4.2.1.10	m		'00000000'B	
8	Octet 5	E.4.2.1, E.4.2.1.10	m		'00000000'B	
9	Octet 6	E.4.2.1, E.4.2.1.10	m		'00000000'B	
10	Octet 7	E.4.2.1, E.4.2.1.10	m		'00000000'B	
11	Octet 8	E.4.2.1, E.4.2.1.10	m		'00000000'B	
12	Octet 9	E.4.2.1, E.4.2.1.10	m		'00000000'B	
13	Octet 10	E.4.2.1, E.4.2.1.10	m		'00000000'B	
14	Octet 11	E.4.2.1, E.4.2.1.10	m		'00000000'B	
15	Octet 12	E.4.2.1, E.4.2.1.10	m		'00000000'B	

Table A.163 FU7 72 kbit/s frame structure (Sending P to F)

Prerequisite: A.127/7				
Item	**FU7 72 kbit/s frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Control field (2 bytes)	E.4.2.1	m	
2	Information field (90 bytes)	E.4.2.2	m	
3	ARQ Checksum (2 bytes)	E.4.2.3	m	
4	RS parity symbol field (6 bytes)	E.4.2	m	

Table A.164 FU7 72 kbit/s frame structure (Receipt F to P)

Prerequisite: A.128/7				
Item	**FU7 72 kbit/s frame structure - Name of field**	**Ref.**	**Status**	**Supp.**
1	Control field (2 bytes)	E.4.2.1	m	
2	Information field (90 bytes)	E.4.2.2	m	
3	ARQ Checksum (2 bytes)	E.4.2.3	m	
4	RS parity symbol field (6 bytes)	E.4.2	m	

Table A.165 FU7 72 kbit/s control field (Sending P to F)

Prerequisite: A.163/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	N(O)	E.4.2.1.4	m		6 bits value	
2	Format-1	E.4.2.1.1	m		'01'B	
3	N(S)	E.4.2.1.7	m		3 bits value	
4	N(R)	E.4.2.1.9	m		3 bits value	
5	Format-2	E.4.2.1.1	m		'00'B, '01'B	

Table A.166 FU7 72 kbit/s control field (Receipt F to P)

Prerequisite: A.164/1						
Item	**Name of sub-field**	**Ref.**	**Status**	**Supp.**	**Value Allowed**	**Value Supported**
1	N(O)	E.4.2.1.4	m		6 bits value	
2	Format-1	E.4.2.1.1	m		'01'B	
3	N(S)	E.4.2.1.7	m		3 bits value	
4	N(R)	E.4.2.1.9	m		3 bits value	
5	Format-2	E.4.2.1.1	m		'00'B, '01'B	

A.5.4 Protocol error handling

A.5.4.1 General error handling

Table A.167 General error handling

Prerequisite: A.10/1 OR A.10/2 OR A.10/3				
Item	**General error handling**	**Ref.**	**Status**	**Support**
1	Unknown frames are discarded	9.2.9.1, 7.11	m	
2	Invalid frames are discarded	9.2.9.1, 6.1.5	m	

A.5.4.2 Class A error handling and recovery

Table A.168 Class A error handling and recovery

Prerequisite: A.10/2				
Item	**Class A error handling and recoverys**	**Ref.**	**Status**	**Support**
1	Waiting for acknowledgement, timer DL.04 expiry	9.2.3.6	m	

A.5.4.3 Class B error handling and recovery

Table A.169 Class B error handling and recovery

Prerequisite: A.10/3				
Item	**Class B error handling and recovery**	**Ref.**	**Status**	**Support**
1	N(S) sequence error	9.2.9.2.1	m	
2	N(R) sequence error	9.2.9.2.2	m	
3	Timer recovery condition	9.2.9.2.3	m	

History

Document history			
June 1995	Public Enquiry	PE 85:	1995-06-05 to 1995-09-29
May 1996	Vote	V 102:	1996-05-06 to 1996-08-09
August 1996	First Edition		

ISBN 2-7437-0873-5 - Edition complète
ISBN 2-7437-0877-8 - Partie 2
Dépôt légal : Août 1996